

ELEC 441 Assignment 2

James Marx

80562549

February 21, 2025

P1

a) Continuous-time system:

$$\dot{x}(t) = \begin{bmatrix} -1 & 0 & 0 \\ 0 & -1 & 1 \\ 0 & -2 & -1 \end{bmatrix} x(t)$$

i) Eigenvalue Criteria:

We begin by computing the eigenvalues of A

$$\det(A - \lambda I) = 0$$

$$\det \begin{bmatrix} -1 - \lambda & 0 & 0 \\ 0 & -1 - \lambda & 1 \\ 0 & -2 & -1 - \lambda \end{bmatrix} = 0$$

$$\begin{aligned} &= (-1 - \lambda) ((-1 - \lambda)^2 - (-2)) - 0 + 0 = 0 \\ &= (-1 - \lambda)(\lambda^2 + 2\lambda + 3) = 0 \end{aligned}$$

$$\lambda_1 = -1, \quad \lambda_2 = -1 + j\sqrt{2}, \quad \lambda_3 = -1 - j\sqrt{2}$$

This system is asymptotically stable as $\text{Re}\{\lambda_i\} < 0, \forall i$

ii) Lyapunov Theorem:

For the CT system, we solve for P in the following equation

$$A^T P + P A = -Q$$

Taking Q to be the identity matrix

$$\begin{bmatrix} -1 & 0 & 0 \\ 0 & -1 & -2 \\ 0 & 1 & -1 \end{bmatrix} \begin{bmatrix} p_1 & p_2 & p_3 \\ p_2 & p_4 & p_5 \\ p_3 & p_5 & p_6 \end{bmatrix} + \begin{bmatrix} p_1 & p_2 & p_3 \\ p_2 & p_4 & p_5 \\ p_3 & p_5 & p_6 \end{bmatrix} \begin{bmatrix} -1 & 0 & 0 \\ 0 & -1 & 1 \\ 0 & -2 & -1 \end{bmatrix} = \begin{bmatrix} -1 & 0 & 0 \\ 0 & -1 & 0 \\ 0 & 0 & -1 \end{bmatrix}$$

$$\begin{bmatrix} -2p_1 & -2p_2 - 2p_3 & p_2 - 2p_3 \\ -2p_2 & -2p_4 - 4p_5 & p_4 - 2p_5 - 2p_6 \\ p_2 - 2p_3 & p_4 - 2p_5 & 2p_5 - 2p_6 \end{bmatrix} = \begin{bmatrix} -1 & 0 & 0 \\ 0 & -1 & 0 \\ 0 & 0 & -1 \end{bmatrix}$$

$$p_1 = \boxed{\frac{1}{2}}$$

$$\begin{aligned} -2p_4 - 4p_5 &= -1 \\ -2p_4 &= -1 + 4p_5 \\ p_4 &= \frac{1}{2} - 2p_5 \end{aligned}$$

$$\begin{aligned}
2p_5 - 2p_6 &= -1 \\
-2p_6 &= -1 - 2p_5 \\
p_6 &= \frac{1}{2} + p_5
\end{aligned}$$

$$\begin{aligned}
p_4 - 2p_5 - 2p_6 &= 0 \\
\frac{1}{2} - 2p_5 - 2p_5 - 2\left(\frac{1}{2} + p_5\right) &= 0 \\
\frac{1}{2} - 4p_5 - 1 - 2p_5 &= 0 \\
\frac{1}{2} - 6p_5 - 1 &= 0 \\
-\frac{1}{2} - 6p_5 &= 0
\end{aligned}$$

$$p_5 = \boxed{-\frac{1}{12}}$$

$$p_4 = \boxed{\frac{2}{3}}$$

$$p_6 = \boxed{\frac{5}{12}}$$

$$p_2 = p_3 = \boxed{0}$$

$$P = \begin{bmatrix} \frac{1}{2} & 0 & 0 \\ 0 & \frac{2}{3} & -\frac{1}{12} \\ 0 & -\frac{1}{2} & \frac{5}{12} \end{bmatrix}$$

All diagonal entries are > 0 so P may be positive definite

Check principle minors

$$A_1 = \frac{1}{2} > 0$$

$$A_2 = \det \begin{bmatrix} \frac{1}{2} & 0 \\ 0 & \frac{2}{3} \end{bmatrix} = \frac{1}{2} \times \frac{2}{3} > 0$$

$$\begin{aligned}
A_3 &= \det \begin{bmatrix} \frac{1}{2} & 0 & 0 \\ 0 & \frac{2}{3} & -\frac{1}{12} \\ 0 & -\frac{1}{2} & \frac{5}{12} \end{bmatrix} = \frac{1}{2} \det \begin{bmatrix} \frac{2}{3} & -\frac{1}{12} \\ -\frac{1}{2} & \frac{5}{12} \end{bmatrix} + 0 + 0 \\
&= \frac{1}{2} \left(\frac{2}{3} \times \frac{5}{12} - \frac{1}{12} \times \frac{1}{12} \right) > 0
\end{aligned}$$

All principle minors are greater than 0 so P is positive definite.

The system is asymptotically stable since $P > 0$

b) Discrete-time system:

$$x[k+1] = \begin{bmatrix} 0 & -1 \\ \frac{1}{2} & 0 \end{bmatrix} x[k]$$

i) Eivenvalue Criteria:

We begin by computing the eigenvalues of A

$$\det(A - \lambda I) = 0$$

$$\det \begin{bmatrix} -\lambda & -1 \\ \frac{1}{2} & -\lambda \end{bmatrix} = \lambda^2 + \frac{1}{2} = 0$$

$$\lambda_1 = j\frac{\sqrt{2}}{2}, \quad \lambda_2 = \frac{\sqrt{2}}{j2}$$

$$|\lambda_1| = |\lambda_2| = \frac{\sqrt{2}}{2} < 1$$

This system is asymptotically stable as $|\lambda_i| < 1, \forall i$

ii) Lyapunov Theorem:

For the DT system, we solve for P in the following equation

$$A^T P A - P = -Q$$

Taking Q to be the identity matrix

$$\begin{bmatrix} 0 & \frac{1}{2} \\ -1 & 0 \end{bmatrix} \begin{bmatrix} p_1 & p_2 \\ p_2 & p_3 \end{bmatrix} \begin{bmatrix} 0 & -1 \\ \frac{1}{2} & 0 \end{bmatrix} - \begin{bmatrix} p_1 & p_2 \\ p_2 & p_3 \end{bmatrix} = \begin{bmatrix} -1 & 0 \\ 0 & -1 \end{bmatrix}$$

$$\begin{bmatrix} \frac{1}{4}p_3 - p_1 & -\frac{1}{2}p_3 - p_2 \\ -\frac{1}{2}p_2 - p_1 + 2 & p_1 - p_3 \end{bmatrix} = \begin{bmatrix} -1 & 0 \\ 0 & -1 \end{bmatrix}$$

$$p_1 - p_3 = -1$$

$$p_1 = p_3 - 1$$

$$\frac{1}{4}p_3 - p_1 = -1$$

$$\frac{1}{4}p_3 - p_3 + 1 = -1$$

$$-\frac{3}{4}p_3 = -2$$

$$p_3 = \boxed{\frac{8}{3}}$$

$$p_1 = \boxed{\frac{5}{3}}$$

$$p_2 = \boxed{0}$$

$$P = \begin{bmatrix} \frac{5}{3} & 0 \\ 0 & \frac{8}{3} \end{bmatrix}$$

P is diagonal with positive entries and is therefore positive definite.

The system is asymptotically stable since $P > 0$

P2

a) $M_1 = M_2 = k_1 = k_2 = 1$

$$A = \begin{bmatrix} 0 & 1 & 0 & 0 \\ -2 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & -1 & 0 \end{bmatrix}, \quad B = \begin{bmatrix} 0 \\ 1 \\ 0 \\ 0 \end{bmatrix}$$

$$C = \begin{bmatrix} -1 & 0 & 1 & 0 \\ -2 & 0 & 1 & 0 \\ 1 & 0 & -1 & 0 \end{bmatrix}, \quad D = \begin{bmatrix} 0 \\ 1 \\ 0 \end{bmatrix}$$

i) Controllability

$$\mathcal{C} = [B \quad AB \quad \dots \quad A^{n-1}B] \in \mathbb{R}^{n \times nm}$$

$$A^2 = \begin{bmatrix} 0 & 1 & 0 & 0 \\ -2 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & -1 & 0 \end{bmatrix} \begin{bmatrix} 0 & 1 & 0 & 0 \\ -2 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & -1 & 0 \end{bmatrix} = \begin{bmatrix} -2 & 0 & 1 & 0 \\ 0 & -2 & 0 & 1 \\ 1 & 0 & -1 & 0 \\ 0 & 1 & 0 & -1 \end{bmatrix}$$

$$A^3 = \begin{bmatrix} -2 & 0 & 1 & 0 \\ 0 & -2 & 0 & 1 \\ 1 & 0 & -1 & 0 \\ 0 & 1 & 0 & -1 \end{bmatrix} \begin{bmatrix} 0 & 1 & 0 & 0 \\ -2 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & -1 & 0 \end{bmatrix} = \begin{bmatrix} 0 & -2 & 0 & 1 \\ 5 & 0 & -3 & 0 \\ 0 & 1 & 0 & -1 \\ 3 & 0 & 2 & 0 \end{bmatrix}$$

We can determine from inspection, that pre-multiplying B with A^n will result in the second column of A^n

$$\mathcal{C} = \begin{bmatrix} 0 & 1 & 0 & -2 \\ 1 & 0 & -2 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix}$$

We can easily determine the rank of \mathcal{C} by re-arranging the rows

$$\begin{bmatrix} 0 & 1 & 0 & -2 \\ 1 & 0 & -2 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \sim \begin{bmatrix} 1 & 0 & -2 & 0 \\ 0 & 1 & 0 & -2 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{C}) = 4$$

Since the Controllability matrix has full rank, this system is controllable

ii) Observability

$$\mathcal{O} = \begin{bmatrix} C \\ CA \\ \vdots \\ CA^{n-1} \end{bmatrix}$$

$$CA = \begin{bmatrix} -1 & 0 & 1 & 0 \\ -2 & 0 & 1 & 0 \\ 1 & 0 & -1 & 0 \end{bmatrix} \begin{bmatrix} 0 & 1 & 0 & 0 \\ -2 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & -1 & 0 \end{bmatrix} = \begin{bmatrix} 0 & -1 & 0 & 1 \\ 0 & -2 & 0 & 1 \\ 0 & 1 & 0 & -1 \end{bmatrix}$$

$$CA^2 = \begin{bmatrix} -1 & 0 & 1 & 0 \\ -2 & 0 & 1 & 0 \\ 1 & 0 & -1 & 0 \end{bmatrix} \begin{bmatrix} -2 & 0 & 1 & 0 \\ 0 & -2 & 0 & 1 \\ 1 & 0 & -1 & 0 \\ 0 & 1 & 0 & -1 \end{bmatrix} = \begin{bmatrix} 3 & 0 & -2 & 0 \\ 5 & 0 & -3 & 0 \\ -3 & 0 & 2 & 0 \end{bmatrix}$$

$$CA^3 = \begin{bmatrix} -1 & 0 & 1 & 0 \\ -2 & 0 & 1 & 0 \\ 1 & 0 & -1 & 0 \end{bmatrix} \begin{bmatrix} 0 & -2 & 0 & 1 \\ 5 & 0 & -3 & 0 \\ 0 & 1 & 0 & -1 \\ 3 & 0 & 2 & 0 \end{bmatrix} = \begin{bmatrix} 0 & 3 & 0 & -2 \\ 0 & 5 & 0 & -3 \\ 0 & -3 & 0 & 2 \end{bmatrix}$$

$$\mathcal{O} = \begin{bmatrix} -1 & 0 & 1 & 0 \\ -2 & 0 & 1 & 0 \\ 1 & 0 & -1 & 0 \\ 0 & -1 & 0 & 1 \\ 0 & -2 & 0 & 1 \\ 0 & 1 & 0 & -1 \\ 3 & 0 & -2 & 0 \\ 5 & 0 & -3 & 0 \\ -3 & 0 & 2 & 0 \\ 0 & 3 & 0 & -2 \\ 0 & 5 & 0 & -3 \\ 0 & -3 & 0 & 2 \end{bmatrix}$$

We can conclude the rank of \mathcal{O} is 4 if we can find a subset of the rows with rank 4

$$\begin{aligned} \begin{bmatrix} 5 & 0 & -3 & 0 \\ -3 & 0 & 2 & 0 \\ 0 & 3 & 0 & -2 \\ 0 & 5 & 0 & -3 \end{bmatrix} &\sim \begin{bmatrix} 1 & 0 & -\frac{3}{5} & 0 \\ 1 & 0 & -\frac{3}{5} & 0 \\ 0 & 1 & 0 & -\frac{2}{5} \\ 0 & 1 & 0 & -\frac{3}{5} \end{bmatrix} \sim \begin{bmatrix} 1 & 0 & -\frac{3}{5} & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & -\frac{2}{5} \\ 0 & 1 & 0 & -\frac{3}{5} \end{bmatrix} \\ &\sim \begin{bmatrix} 1 & 0 & -\frac{3}{5} & 0 \\ 0 & 1 & 0 & -\frac{2}{5} \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & -\frac{3}{5} \end{bmatrix} \sim \begin{bmatrix} 1 & 0 & -\frac{3}{5} & 0 \\ 0 & 1 & 0 & -\frac{2}{5} \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix} = \text{rank}(\mathcal{O}) = 4 \end{aligned}$$

Since \mathcal{O} has a rank of 4, the system is observable

b) $R = C = 1$

$$A = \begin{bmatrix} -3 & 1 & 0 \\ 1 & -2 & 1 \\ 0 & 1 & -3 \end{bmatrix}, \quad B = \begin{bmatrix} 2 & 0 \\ 0 & 0 \\ 0 & 2 \end{bmatrix}, \quad C = \begin{bmatrix} 0 & 0 & 1 \end{bmatrix}$$

i) Controllability

$$\mathcal{C} = [B \quad AB \quad \dots \quad A^{n-1}B] \in \mathbb{R}^{n \times nm}$$

$$A^2 = \begin{bmatrix} -3 & 1 & 0 \\ 1 & -2 & 1 \\ 0 & 1 & -3 \end{bmatrix} \begin{bmatrix} -3 & 1 & 0 \\ 1 & -2 & 1 \\ 0 & 1 & -3 \end{bmatrix} = \begin{bmatrix} 10 & -5 & 1 \\ -5 & 6 & -4 \\ 1 & -4 & 5 \end{bmatrix}$$

Pre-multiplying B with A^n will result in a matrix with twice the first column of A^n and twice the third column of A^n

$$AB = \begin{bmatrix} -6 & 0 \\ 2 & 2 \\ 0 & -6 \end{bmatrix}$$

$$A^2B = \begin{bmatrix} 20 & 2 \\ -10 & -8 \\ 2 & 10 \end{bmatrix}$$

$$\mathcal{C} = \begin{bmatrix} 2 & 0 & -6 & 0 & 20 & 2 \\ 0 & 0 & 2 & 2 & -10 & -8 \\ 0 & 2 & 0 & -6 & 2 & 10 \end{bmatrix}$$

\mathcal{C} will have rank 3 if we can find 3 linearly independent columns

$$\begin{bmatrix} 2 & 0 & -6 \\ 0 & 0 & 2 \\ 0 & 2 & 0 \end{bmatrix} \sim \begin{bmatrix} 1 & 0 & -3 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{C}) = 3$$

Since the Controllability matrix has rank 3, this system is controllable

ii) Observability

$$\mathcal{O} = \begin{bmatrix} C \\ CA \\ \vdots \\ CA^{n-1} \end{bmatrix}$$

Pre-multiplying A^n with C will result in the third row of A^n .

$$\mathcal{O} = \begin{bmatrix} 0 & 0 & 1 \\ 0 & 1 & -3 \\ 1 & -4 & 5 \end{bmatrix} = \text{rank}(\mathcal{O}) = 3$$

Since \mathcal{O} has a rank of 3, the system is observable

c)

$$A = \begin{bmatrix} 0 & 1 & 0 & 0 \\ \frac{g(M+m)}{lm} & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ -\frac{mg}{M} & 0 & 0 & 0 \end{bmatrix}, \quad B = \begin{bmatrix} 0 \\ -\frac{1}{lM} \\ 0 \\ \frac{1}{M} \end{bmatrix}, \quad C = [0 \quad 0 \quad 1 \quad 0]$$

i) Controllability

$$A^2 = \begin{bmatrix} 0 & 1 & 0 & 0 \\ \frac{g(M+m)}{lm} & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ -\frac{mg}{M} & 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} 0 & 1 & 0 & 0 \\ \frac{g(M+m)}{lm} & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ -\frac{mg}{M} & 0 & 0 & 0 \end{bmatrix} = \begin{bmatrix} \frac{g(M+m)}{lM} & 0 & 0 & 0 \\ 0 & \frac{g(M+m)}{lM} & 0 & 0 \\ -\frac{mg}{M} & 0 & 0 & 0 \\ 0 & -\frac{mg}{M} & 0 & 0 \end{bmatrix}$$

$$A^3 = \begin{bmatrix} 0 & 1 & 0 & 0 \\ \frac{g(M+m)}{lm} & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ -\frac{mg}{M} & 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} \frac{g(M+m)}{lM} & 0 & 0 & 0 \\ 0 & \frac{g(M+m)}{lM} & 0 & 0 \\ -\frac{mg}{M} & 0 & 0 & 0 \\ 0 & -\frac{mg}{M} & 0 & 0 \end{bmatrix} = \begin{bmatrix} 0 & \frac{g(M+m)}{lM} & 0 & 0 \\ \left(\frac{g(M+m)}{lM}\right)^2 & 0 & 0 & 0 \\ 0 & -\frac{mg}{M} & 0 & 0 \\ -\frac{mg^2(M+m)}{lM^2} & 0 & 0 & 0 \end{bmatrix}$$

$$AB = \begin{bmatrix} -\frac{1}{lM} \\ 0 \\ \frac{1}{M} \\ 0 \end{bmatrix}$$

$$A^2B = \begin{bmatrix} 0 \\ -\frac{g(M+m)}{(lM)^2} \\ 0 \\ \frac{mg}{lM^2} \end{bmatrix}$$

$$A^3B = \begin{bmatrix} -\frac{g(M+m)}{(lM)^2} \\ 0 \\ \frac{mg}{lM^2} \\ 0 \end{bmatrix}$$

$$\mathcal{C} = \begin{bmatrix} 0 & -\frac{1}{lM} & 0 & \frac{g(M+m)}{(lM)^2} \\ -\frac{1}{lM} & 0 & -\frac{g(M+m)}{(lM)^2} & 0 \\ 0 & 0 & 0 & \frac{mg}{lM^2} \\ \frac{1}{M} & 0 & \frac{mg}{lM^2} & 0 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{C}) = 4$$

Since \mathcal{C} has a rank of 4, the system is controllable

ii) Observability

Pre-multiplying A^n with C will result in the third row of A^n

$$\mathcal{O} = \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ -\frac{mg}{M} & 0 & 0 & 0 \\ 0 & -\frac{mg}{M} & 0 & 0 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{O}) = 4$$

Since \mathcal{O} has a rank of 4, the system is observable

P3

a)

$$\begin{cases} \dot{x}(t) = \begin{bmatrix} 2 & -1 \\ 1 & 0 \end{bmatrix} x(t) + \begin{bmatrix} 1 \\ 0 \end{bmatrix} u(t), \\ y(t) = \begin{bmatrix} 1 & -1 \end{bmatrix} x(t) \end{cases}$$

We first find the controllability matrix, which will simply be B concatenated with the first column of A

$$\mathcal{C} = \begin{bmatrix} 1 & 2 \\ 0 & 1 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{C}) = 2$$

This system is fully controllable.

The observability matrix will be \mathcal{O} and the second row of A subtracted from the first

$$\mathcal{O} = \begin{bmatrix} 1 & -1 \\ 1 & -1 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{O}) = 1$$

This system is not fully observable.

Since \mathcal{C} has full rank, the Image space can be expressed as the span of the 2-D basis vectors

$$\text{Im}(\mathcal{C}) = \text{span} \left\{ \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \begin{bmatrix} 0 \\ 1 \end{bmatrix} \right\}$$

We will next find the Kernel space of \mathcal{O} which can easily be seen to be the line where $x_1 = x_2$

$$\text{Ker}(\mathcal{O}) = \text{span} \left\{ \begin{bmatrix} 1 \\ 1 \end{bmatrix} \right\}$$

We can now begin finding the bases of the subspaces needed to construct T^{-1}

$$T^{-1} = [T_{co} \quad T_{c\bar{o}} \quad T_{\bar{c}o} \quad T_{\bar{c}\bar{o}}]$$

$T_{c\bar{o}}$ will be a basis for the intersection of $\text{Im}(\mathcal{C})$ and $\text{Ker}(\mathcal{O})$

$$T_{c\bar{o}} = \begin{bmatrix} 1 \\ 1 \end{bmatrix}$$

$T_{\bar{c}o}$ will be the intersection of the orthogonal compliment of $\text{Im}(\mathcal{C})$ and the orthogonal compliment of $\text{Ker}(\mathcal{O})$, which is the zero subspace

$$T_{\bar{c}o} = \mathbf{0}$$

$T_{\bar{c}\bar{o}}$ will be the intersection of the orthogonal compliment of $\text{Im}(\mathcal{C})$ and $\text{Ker}(\mathcal{O})$, which again is the zero subspace

$$T_{\bar{c}\bar{o}} = \mathbf{0}$$

T_{co} will be the intersection of $\text{Im}(\mathcal{C})$ and the orthogonal compliment of $\text{Ker}(\mathcal{O})$

$$T_{co} = \begin{bmatrix} 1 \\ -1 \end{bmatrix}$$

$$T^{-1} = \begin{bmatrix} 1 & 1 \\ -1 & 1 \end{bmatrix} \Rightarrow T = \frac{1}{2} \begin{bmatrix} 1 & -1 \\ 1 & 1 \end{bmatrix}$$

We can now perform the coordinate transformation

$$\begin{aligned}
\bar{A} &= TAT^{-1} \\
&= \frac{1}{2} \begin{bmatrix} 1 & -1 \\ 1 & 1 \end{bmatrix} \begin{bmatrix} 2 & -1 \\ 1 & 0 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ -1 & 1 \end{bmatrix} \\
&= \frac{1}{2} \begin{bmatrix} 1 & -1 \\ 3 & -1 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ -1 & 1 \end{bmatrix} \\
&= \begin{bmatrix} 1 & 0 \\ 2 & 1 \end{bmatrix}
\end{aligned}$$

$$\begin{aligned}
\bar{B} &= TB \\
&= \frac{1}{2} \begin{bmatrix} 1 \\ 1 \end{bmatrix}
\end{aligned}$$

$$\begin{aligned}
\bar{C} &= CT^{-1} \\
&= \begin{bmatrix} 2 & 0 \end{bmatrix}
\end{aligned}$$

The new system after the coordinate transformation is

$$\begin{cases} \dot{z}(t) = \begin{bmatrix} 1 & 0 \\ 2 & 1 \end{bmatrix} z(t) + \frac{1}{2} \begin{bmatrix} 1 \\ 1 \end{bmatrix} u(t), \\ y(t) = \begin{bmatrix} 2 & 0 \end{bmatrix} z(t) \end{cases}$$

The new state vector z is

$$\begin{aligned}
z &= Tx \\
&= \frac{1}{2} \begin{bmatrix} 1 & -1 \\ 1 & 1 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix} \\
&= \frac{1}{2} \begin{bmatrix} x_1 - x_2 \\ x_1 + x_2 \end{bmatrix}
\end{aligned}$$

The state which is controllable and observable is $\frac{1}{2}(x_1 - x_2)$

The state which is controllable and not observable is $\frac{1}{2}(x_1 + x_2)$

No states are not controllable and observable/not observable.

b)

$$\begin{cases} \dot{x}(t) = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 1 \\ 1 & 0 & -1 \end{bmatrix} x(t) + \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} u(t), \\ y(t) = \begin{bmatrix} 0 & 0 & 1 \end{bmatrix} x(t) \end{cases}$$

We first find the controllability matrix, which will be B concatenated with the third columns of A^n

$$A^2 = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 1 \\ 1 & 0 & -1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 1 \\ 1 & 0 & -1 \end{bmatrix} = \begin{bmatrix} 1 & 1 & 0 \\ 1 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}$$

$$\mathcal{C} = \begin{bmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 1 & -1 & 1 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{C}) = 2$$

This system is partially controllable

The observability will be \mathcal{C} and the third rows of A^n

$$\mathcal{O} = \begin{bmatrix} 0 & 0 & 1 \\ 1 & 0 & -1 \\ 0 & 0 & 1 \end{bmatrix} \Rightarrow \text{rank}(\mathcal{O}) = 2$$

This system is partially observable

To find the Image space of \mathcal{C} we row reduce and pick two linearly independent columns

$$\begin{bmatrix} 1 & -1 & 1 \\ 0 & 1 & 0 \\ 0 & 0 & 0 \end{bmatrix} \sim \begin{bmatrix} 1 & 0 & 1 \\ 0 & 1 & 0 \\ 0 & 0 & 0 \end{bmatrix}$$

$$\text{Im}(\mathcal{C}) = \text{span} \left\{ \begin{bmatrix} 1 \\ 0 \\ 0 \end{bmatrix}, \begin{bmatrix} 0 \\ 1 \\ 0 \end{bmatrix} \right\}$$

Now for $\text{Ker}(\mathcal{O})$

$$\begin{bmatrix} 0 & 0 & 1 \\ 1 & 0 & -1 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix} = \mathbf{0}$$

$$\begin{aligned} x_3 &= 0 \\ x_1 - x_3 &= 0 \\ x_2 &= \text{free} \end{aligned}$$

$$\text{Ker}(\mathcal{O}) = \text{span} \left\{ \begin{bmatrix} 0 \\ 1 \\ 0 \end{bmatrix} \right\}$$

We can now begin finding the bases of the subspaces needed to construct T^{-1}

$$T^{-1} = [T_{co} \quad T_{c\bar{o}} \quad T_{\bar{c}o} \quad T_{\bar{c}\bar{o}}]$$

T_{co} will be a basis for the intersection of $\text{Im}(\mathcal{C})$ and the orthogonal compliment of $\text{Ker}(\mathcal{O})$

$$T_{co} = \begin{bmatrix} 1 \\ 0 \\ 0 \end{bmatrix}$$

$T_{c\bar{o}}$ will be the intersection of $\text{Im}(\mathcal{C})$ and $\text{Ker}(\mathcal{O})$

$$T_{c\bar{o}} = \begin{bmatrix} 0 \\ 1 \\ 0 \end{bmatrix}$$

$T_{\bar{c}o}$ will be the intersection of the orthogonal compliment of $\text{Im}(\mathcal{C})$ and the orthogonal compliment of $\text{Ker}(\mathcal{O})$

$$T_{\bar{c}o} = \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix}$$

$T_{\bar{c}\bar{o}}$ will be the intersection of the orthogonal compliment of $\text{Im}(\mathcal{C})$ and $\text{Ker}(\mathcal{O})$

$$T_{\bar{c}\bar{o}} = \mathbf{0}$$

$$T^{-1} = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix} \Rightarrow T = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}$$

After the transform, all matrices are the same as the transform is the identity

The state which is controllable and observable is x_1

The state which is controllable and not observable is x_2

The state which is not controllable and observable is x_3

MATLAB Result

```
Command Window
3 a) T inverse
    1.0000    1.0000
   -1.0000    1.0000

transformed state vector entries
   zco   zc_o   z_co   z_c_o
     1     1     0     0

3 b) T inverse
    1.0000         0         0
         0    1.0000         0
         0         0    1.0000

transformed state vector entries
   zco   zc_o   z_co   z_c_o
     1     1     1     0
```

Figure 1: MATLAB Output

MATLAB Code

a2.m

```
clc; clear;
```

```
%%% Problem 3 %%%
```

```
% a)
```

```
A = [2,-1;1,0];
```

```
B = [1;0];
```

```
C = [1,-1];
```

```
kd_a = kalman(A,B,C);
```

```
disp("3 a) T inverse")
```

```
disp(kd_a.T_inv)
```

```
disp("transformed state vector entries")
```

```
disp("    zco   zc_o   z_co   z_c_o")
```

```
disp(kd_a.z_dim)
```

```
% b)
```

```
A = [1,0,0;0,1,1;1,0,-1];
```

```
B = [0;0;1];
```

```
C = [0,0,1];
```

```
kd_b = kalman(A,B,C);
```

```
disp("3 b) T inverse")
```

```
disp(kd_b.T_inv)
```

```
disp("transformed state vector entries")
```

```
disp("    zco   zc_o   z_co   z_c_o")
```

```
disp(kd_b.z_dim)
```

kalman.m

```
% <strong>kalman</strong> - Kalman Decomposition
```

```
% Author: James Marx
```

```
% Edited: 2025.02.20
```

```
%
```

```
% This function returns the Kalman Decomposition of a state space model.
```

```
%
```

```
% Additional computations are made in an attempt to closer match an  
% answer which would be computed by hand - such as keeping basis vectors  
% positive and not defaulting to normalized vectors
```

```
%
```

```
% Syntax
```

```
% kd = <strong>kalman</strong>(A,B,C)
```

```
%
```

```
% Input Arguments
```

```
% <strong>A</strong> - State matrix
```

```
% <strong>B</strong> - Input matrix
```

```
% <strong>C</strong> - Output matrix
```

```
%
```

```
% Output Arguments
```

```
% <strong>kd.A</strong> - Coordinate transformed state matrix
```

```

% kd.B - Coordinate transformed input matrix
% kd.C - Coordinate transformed output matrix
% kd.T_inv - Coordinate transform matrix
% kd.z_dim - Array for dimension of transformed state variables
% [zco    zc_o    z_co    z_c_o]
% zco    - controllable and observable
% zc_o    - controllable and not observable
% z_co    - not controllable and observable
% z_c_o - not controllable and not observable
function KD = kalman(A,B,C)
    Cb = ctrb(A,B);
    Ob = obsv(A,C);

    % find basis for Image Space of Cb
    [R, pivot_cols] = rref(Cb);
    basis_Im = R(:,pivot_cols);
    basis_Im_comp = null(basis_Im');

    % find basis for Kernel Space of Ob
    basis_Ker = null(Ob);
    basis_Ker = normalizeOne(basis_Ker);
    basis_Ker_comp = normalizeOne(null(basis_Ker'));

    % find bases for coordinate transform matrix subspaces
    Tc_o = intersection_basis(basis_Im, basis_Ker);
    T_co = intersection_basis(basis_Im_comp, basis_Ker_comp);
    T_c_o = intersection_basis(basis_Im_comp, basis_Ker);
    Tco = intersection_basis(basis_Im, basis_Ker_comp);

    T_inv = [Tco, Tc_o, T_co, T_c_o];

    KD.A = T_inv\A*T_inv;
    KD.B = T_inv\B;
    KD.C = C*T_inv;
    KD.T_inv = T_inv;
    KD.z_dim = [size(Tco,2), size(Tc_o,2), size(T_co,2), size(T_c_o,2)];
end

% Computes a basis for the intersection of two subspaces
function B = intersection_basis(A, B)
    N = null([A, -B]);
    if (~isempty(N))
        N = normalizeOne(N);
        B = A * N(1:size(A,2), :);
        % Ensure the basis vectors are positive (if possible)
        positiveBasis = B;
        for i = 1:size(positiveBasis, 2)
            % If the first non-zero element is negative, flip the sign of the vector
            if any(positiveBasis(:, i) < 0)
                positiveBasis(:, i) = -positiveBasis(:, i);
            end
        end
        B = positiveBasis;
    else

```

```

        B = [];
    end
end

% normalize smallest value to 1 - keeping signs
function normA = normalizeOne(A)
    nonZeroElements = A(A ~= 0); % Extract non-zero elements
    smallestNonZero = min(nonZeroElements); % Find the smallest non-zero element
    normA = A / abs(smallestNonZero);
end

```