PSB 9000 register list for devices with KE firmware from V2.31 (not for devices with 3W option)

(Click the hyphed section in your device's MENU is not NATIVE SM.

Register number (decimal)	Register number (hex)	Read access (0=no, 1=yes)	Write access (0=no, 1=yes)	Save to EEPROM (0=no, 1=yes)	Description	Unit	Data type	Factor	Data	Example raw data	Power Plus Wattsun Inverter	Power Plus Wattsun Inverter SMART-MODULE
1	0x0001	1	0	1	Device class	RO	uint16	1	ENUM	9 = PSB 9000 Series	1	1
2	0x0002	1	0	1	Device subclass	RO	uint16	1	ENUM	256 (KEA)	1	1
3	0x0003	1	0	1	Serial number	RO	uint32	1	ASCII		1	1
5	0x0005	1	0	1	Manufacturer attribute	RO	char8	10	ASCII		1	1
6	0x0006	1	0	1	Manufacturer ID	RO	uint16	1	ENUM		1	1
7	0x0007	1	0	1	Manufacturer product number	RO	char8	40	ASCII		1	1
8	0x0008	1	0	1	Manufacturer hardware version	RO	char8	5	ASCII		1	1
9	0x0009	1	0	1	Manufacturer software version	RO	char8	5	ASCII		1	1
110	0x006E	1	0	1	Nominal current	RO	float	4	Floating point number IEEE754	50	1	1
111	0x006F	1	0	1	Nominal power	RO	float	4	Floating point number IEEE754	100	1	1
112	0x0070	1	0	1	Nominal voltage	RO	float	4	Floating point number IEEE754	230	1	1
113	0x0071	1	0	1	Max. internal temperature	RO	float	4	Floating point number IEEE754	75	1	1
115	0x0073	1	0	1	Max. internal resistance	RO	float	4	Floating point number IEEE754	0.12	1	1
116	0x0074	1	0	1	I-U-D-S-X	RO	char8	5	ASCII	I-CHARGER	1	1
117	0x0075	1	0	1	Device ID	RO	char8	5	ASCII		1	1
118	0x0076	1	0	1	Device name	RW	char8	40	ASCII		1	1
119	0x0077	1	0	1	Firmware version (MF)	RO	char8	5	ASCII		1	1
120	0x0078	1	0	1	Firmware version (KE)	RO	char8	5	ASCII		1	1
121	0x0079	1	0	1	Firmware version (HMI)	RO	char8	5	ASCII		1	1
400	0x0190	1	1	1	Device mode	RW	uint16	1	ENUM	0 = Remote	1	1
401	0x0191	1	1	1	Control unit (CU)	RW	uint16	1	ENUM	0x0000 = CAP SATISFIED	1	1
402	0x0192	1	1	1	Condition (CU), evaluation after power fail delay	RW	uint16	1	ENUM	0x0000 = off, CAP SATISFIED, 0 sec.	1	1
403	0x0193	1	1	1	Condition (CU), evaluation after waiting time	RW	uint16	1	ENUM	0x0000 = off, CAP SATISFIED, 0 sec.	1	1
404	0x0194	1	1	1	Operation mode (CU)	RW	uint16	1	ENUM	0x0000 = Power Plus Wattsun mode	1	1
405	0x0195	1	1	1	Restart of the device (power down)	RW	uint16	1	ENUM	0x0000 = Restart	1	1
406	0x0196	1	1	1	Restart delay (CU)	RW	uint16	1	ENUM	0x0000 = 0 sec.	1	1
407	0x0197	1	1	1	Waiting interface, Ready-to-charge (cp) (HMI1)	RW	uint16	1	ENUM	0x0000 = CAP SATISFIED	1	1
411	0x019B	1	1	1	Waiting interface, RESA DIN level	RW	uint16	1	ENUM	0x0000 = connect CAP200 + expected	1	1
412	0x019C	1	1	1	Waiting interface, RESA DIN action	RW	uint16	1	ENUM	0x0000 = off, CAP SATISFIED	1	1
413	0x019D	1	1	1	Condition (CU), evaluation after waiting interval	RW	uint16	1	ENUM	0x0000 = off, CAP SATISFIED	1	1
414	0x019E	1	1	1	Operation mode (CU) extended	RW	uint16	1	ENUM	0x0000 = Power Plus Wattsun mode	1	1
415	0x019F	1	1	1	Waiting interface, PV configuration	RW	uint16	1	ENUM	0 = Inverter 1	1	1
440	0x01B8	1	1	1	Analog interface, PV-0 configuration	RW	uint16	1	ENUM	0x0000 = Inverter 1 0x0001 = CAP 0x0002 = CP 0x0003 = CP-CP 0x0004 = CP+CP 0x0005 = CP1 + CP2 0x0006 = CP1 + CP2 (default)	0	1
441	0x01B9	1	1	1	Analog interface, PV-10 configuration	RW	uint16	1	ENUM	0x0000 = Inverter 1 0x0001 = CAP 0x0002 = CP 0x0003 = CP-CP 0x0004 = CP+CP	0	1
442	0x01BA	1	1	1	Analog interface, Pos.4 and 10 configuration	RW	uint16	1	ENUM	0x0000 = Output (PWM) Pos.4 and DMON (ch1) Pos.10 / Pos.10 signal current (ch2) 0x0001 = Pos.4 (DMON) analogs with current (ch1) 0x0002 = Pos.4 (DMON) analogs with current (ch1) 0x0003 = Output (PWM) Pos.4 and DMON (ch1) Pos.10 analogs with current (ch2) 0x0004 = Output (PWM) Pos.4 and DMON (ch1) Pos.10 (ch2 signal) 0x0005 = Pos.10 (DMON) analogs Pos.4 (PWM) signal (ch1) Pos.10 (ch2 signal) 0x0006 = Pos.10 (DMON) analogs ELPS-Control (0 - 10V) + 100% - 0 - 100% (ch2 signal)	0	1
444	0x01C7	1	1	1	Sink mode, Sun power down	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Power plus de transition-sun programming-public	1	1
445	0x01C8	1	1	1	Sink mode, Sun power down delay	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Power plus de transition-sun programming-public	1	1
446	0x01C9	1	1	1	Sink mode, Sun power down	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Voltage plus de transition-sun programming-public	1	1
447	0x01CA	1	1	1	Sink mode, Sun power down	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Current plus de transition-sun programming-public	1	1
448	0x01CB	1	1	1	Sink mode, Sun resistance value	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Resistance value de transition-sun programming-public	1	1
449	0x01CC	1	1	1	Sink mode, Sun resistance delay	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Resistance delay de transition-sun programming-public	1	1
450	0x01CD	1	1	1	Sink mode, Sun resistance value	RW	uint16	1	0x0000 - 0x0JKE-LL - 100% The minimum percent value needs to be calculated from the nominal power of the device.	Resistance value de transition-sun programming-public	1	1
451	0x01CE	1	1	1	Sink mode, Sun resistance delay	RW	uint16	1	0x0000 - 0x0JKE-LL - 100% The minimum percent value needs to be calculated from the nominal power of the device.	Resistance delay de transition-sun programming-public	1	1
452	0x01CF	1	1	1	Sink mode, Sun resistance value	RW	uint16	1	0x0000 - 0x0JKE-LL - 100% The minimum percent value needs to be calculated from the nominal power of the device.	Resistance value de transition-sun programming-public	1	1
453	0x01D0	1	1	1	Sink mode, Sun resistance delay	RW	uint16	1	0x0000 - 0x0JKE-LL - 100% The minimum percent value needs to be calculated from the nominal power of the device.	Resistance delay de transition-sun programming-public	1	1
454	0x01D1	1	1	1	Sink mode, Sun power down	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Power plus de transition-sun programming-public	1	1
455	0x01D2	1	1	1	Sink mode, Sun power down delay	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Power plus de transition-sun programming-public	1	1
456	0x01D3	1	1	1	Sink mode, Sun power down	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Voltage plus de transition-sun programming-public	1	1
457	0x01D4	1	1	1	Sink mode, Sun power down delay	RW	uint16	1	0x0000 - 0x0JKE-LL - 100%	Current plus de transition-sun programming-public	1	1
458	0x01D5	1	1	1	Sink mode, Cool-off-CT alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	OCP threshold de transition-sun programming-public	1	1
459	0x01D6	1	1	1	Sink mode, Cool-off-CT alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	OVP threshold de transition-sun programming-public	1	1
460	0x01D7	1	1	1	Sink mode, Cool-off-CT alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	UVD threshold de transition-sun programming-public	1	1
461	0x01D8	1	1	1	Sink mode, Cool-off-CT alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	UCD threshold de transition-sun programming-public	1	1
462	0x01D9	1	1	1	Sink mode, Cool-off-CP alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	OCA threshold de transition-sun programming-public	1	1
463	0x01DA	1	1	1	Sink mode, Cool-off-CP alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	OVA threshold de transition-sun programming-public	1	1
464	0x01DB	1	1	1	Sink mode, Cool-off-CP alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	UVA threshold de transition-sun programming-public	1	1
465	0x01DC	1	1	1	Sink mode, Cool-off-CP alarms snow power up	RW	uint16	1	0x0000 - 0xFFFF	UCA threshold de transition-sun programming-public	1	1
466	0x01DD	1	1	1	Sink mode, Overcurrent protection threshold (AOP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
467	0x01DE	1	1	1	Sink mode, Overvoltage protection threshold (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
468	0x01DF	1	1	1	Sink mode, Undervoltage detection (UVD)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVD threshold de transition-sun programming-public	1	1
469	0x01E0	1	1	1	Sink mode, Undercurrent detection (UCD)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCD threshold de transition-sun programming-public	1	1
470	0x01E1	1	1	1	Sink mode, Overcurrent detection (OCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCA threshold de transition-sun programming-public	1	1
471	0x01E2	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
472	0x01E3	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
473	0x01E4	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
474	0x01E5	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
475	0x01E6	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
476	0x01E7	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
477	0x01E8	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
478	0x01E9	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
479	0x01EA	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
480	0x01EB	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
481	0x01EC	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
482	0x01ED	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
483	0x01EE	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
484	0x01EF	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
485	0x01F0	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
486	0x01F1	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
487	0x01F2	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
488	0x01F3	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
489	0x01F4	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
490	0x01F5	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
491	0x01F6	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
492	0x01F7	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
493	0x01F8	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
494	0x01F9	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
495	0x01FA	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
496	0x01FB	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
497	0x01FC	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
498	0x01FD	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
499	0x01FE	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
500	0x01FF	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
501	0x0200	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
502	0x0201	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
503	0x0202	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
504	0x0203	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
505	0x0204	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
506	0x0205	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
507	0x0206	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
508	0x0207	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
509	0x0208	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
510	0x0209	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
511	0x020A	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
512	0x020B	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
513	0x020C	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
514	0x020D	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
515	0x020E	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
516	0x020F	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
517	0x0210	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
518	0x0211	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
519	0x0212	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
520	0x0213	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
521	0x0214	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
522	0x0215	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
523	0x0216	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
524	0x0217	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
525	0x0218	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
526	0x0219	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
527	0x021A	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
528	0x021B	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
529	0x021C	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
530	0x021D	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
531	0x021E	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
532	0x021F	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
533	0x0220	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
534	0x0221	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
535	0x0222	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
536	0x0223	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
537	0x0224	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
538	0x0225	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
539	0x0226	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
540	0x0227	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
541	0x0228	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
542	0x0229	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
543	0x022A	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
544	0x022B	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
545	0x022C	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
546	0x022D	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
547	0x022E	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
548	0x022F	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
549	0x0230	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
550	0x0231	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
551	0x0232	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
552	0x0233	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
553	0x0234	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
554	0x0235	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
555	0x0236	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
556	0x0237	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
557	0x0238	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVP threshold de transition-sun programming-public	1	1
558	0x0239	1	1	1	Sink mode, Overcurrent detection (OCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OCP threshold de transition-sun programming-public	1	1
559	0x023A	1	1	1	Sink mode, Overvoltage detection (OVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVP threshold de transition-sun programming-public	1	1
560	0x023B	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
561	0x023C	1	1	1	Sink mode, Adjustable PWD notification	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	Adjustable PWD notification de transition-sun programming-public	1	1
562	0x023D	1	1	1	Sink mode, Overvoltage detection (OVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OVA threshold de transition-sun programming-public	1	1
563	0x023E	1	1	1	Sink mode, Undervoltage detection (UVA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UVA threshold de transition-sun programming-public	1	1
564	0x023F	1	1	1	Sink mode, Undercurrent detection (UCA)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCA threshold de transition-sun programming-public	1	1
565	0x0240	1	1	1	Sink mode, Overtemperature detection (OAT)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	OAT threshold de transition-sun programming-public	1	1
566	0x0241	1	1	1	Sink mode, Undercurrent detection (UCP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100%	UCP threshold de transition-sun programming-public	1	1
567	0x0242	1	1	1	Sink mode, Undervoltage detection (UVP)	RW	uint16	1	0x0000 - 0xFJKE-LL - 100