ngspice-46 — Full Change Report

Every modification and its reason (original → current)

Ngspice + OpenVAF Enhancements project

July 2026

Contents

ngspice-46 — Full Change Report 3
1. The OSDI ABI, version 0.4 → 0.7 . . . 3
2. The OSDI runtime — `src/osdi/` . . . 4
3. Analyses — `src/spicelib/analysis/` . . . 5
4. Frontend — `src/frontend/` . . . 7
5. Parser and device registry — `src/spicelib/` . . . 8
6. Maths — `src/maths/` . . . 8
7. Build system . . . 10
8. Per-enhancement index . . . 10

ngspice-46 — Full Change Report

Every modification applied to ngspice-46 in this project, with its reason. The baseline is the pristine ngspice-46 source tree (as vendored in the project's `original/` snapshot, which already contains OpenVAF-Reloaded's stock OSDI support); the current state is the tree committed in this repository under `ngspice-46/`. Each entry links the enhancement write-up in `enhancements_doc/` that carries the full engineering detail and the verifying example suite. The companion document openvaf_changes_full-report.md covers the compiler side.

> Maintenance note: this report is updated whenever an enhancement touches ngspice sources. If you are reading it alongside a newer tree, the per-enhancement index at the end tells you the last change it covers.

Scope summary. One new source file and 41 modified ones carry all the functional changes (~2,000 substantive diff lines). A further ~100 `Makefile.in` files and `config.h.in` differ only because the autotools were regenerated with a current libtool (E-77); they contain no hand-written changes and are not listed individually. Everything below is behavior, interface, or diagnostics.

---

1. The OSDI ABI, version 0.4 → 0.7

`src/osdi/osdi.h` is the authoritative C contract between ngspice and the `.osdi` objects `openvaf-r` produces. The project extended it four times — twice additively (new exported symbols old loaders simply never look up), twice with genuine version bumps (layout changes):

Change	Kind	Enhancement	Why
`OSDI_ABSDELAY_COUNTS` / `OSDI_ABSDELAY_INFOS` exports	Additive symbols	E-1	`absdelay()` needs simulator-side waveform history and synthetic delay-equation rows; the descriptors tell ngspice which nodes/offsets each delay slot uses
`OSDI_LAST_CROSSING_COUNTS` / `OSDI_LAST_CROSSING_INFOS` exports	Additive symbols	E-6	`last_crossing()` needs waveform history and crossing interpolation — same additive pattern as absdelay
`OsdiNode.nodeset` field	ABI 0.5 (node stride change)	E-45	Verilog-A net initializers (`electrical a = 5.0;`) become solver initial-guess nodesets; every node record carries the hint
`num_ac_stim_src` / `ac_stim_sources` / `load_ac_stim` descriptor tail	ABI 0.6 (descriptor grows)	E-51	full `ac_stim()` support: a Verilog-A module can *be* the AC stimulus, so the descriptor must enumerate its AC right-hand-side sources
`load_noise` destination stride 1 → 2 (signed `(flat, react)` power pairs)	ABI 0.7	E-54	correct noise physics: operating-point-dependent factors and `ddt()`-shaped (jω) noise need a complex amplitude per source, `re + jω·im`, so coherent same-named sources (LRM 4.6.4) sum with correct sign and frequency shape

Two additive flag conventions ride on the existing `eval()` interface (not version bumps):

- `EVAL_FLAG_IS_FINAL_STEP` (bit $1 \ll 21$) in the eval *input* flags — `@(final_step)` firing (E-53);
- eval *return* flags for `$finish`/`$stop` requests and `$discontinuity`-driven step rejection (E-55).

Pairing consequence: this ngspice requires OSDI $\geq$ 0.7 and rejects older objects with a clear version message; `.osdi` files from older compilers must be recompiled (E-54).

---

2. The OSDI runtime — `src/osdi/`

`osdiaccept.c` — new file (E-55, E-1, E-6)

The accepted-timepoint hook (`DEVaccept`) OSDI previously lacked. It advances the `absdelay/last_crossing` waveform histories only at *accepted* points (so rejected timesteps don't corrupt the delay lines) and reads the per-attempt latched `$finish`/`$stop` request flags at the one boundary where honoring them is safe. Why: acting on `$stop` mid-Newton-iteration was treated as a step failure and ground the timestep into a rejection loop; `$finish` was ignored outright.

`osdidefs.h` (104 diff lines)

- `OsdiExtraInstData` grows the per-instance fields behind every runtime feature: `dt`/`temp` offsets with given-flags (instance temperature), `eval_flags`, absdelay waveform-history rows and pre-allocated KLU/SPARSE matrix-pointer sets for the delay-equation rows (re-pointed on every DC↔AC transition, mirroring the regular Jacobian handling), and the last_crossing history (E-1, E-6, E-55).
- `ALIGN` macro renamed `OSDI_ALIGN`: the macOS SDK's `<sys/param.h>` defines an unrelated `ALIGN`, producing a redefinition warning in every OSDI translation unit (E-77).

`osdiitf.h` / **`osdiext.h`**

The registry-entry structure gains the absdelay/last_crossing descriptor pointers, and `OSDIpendingRequests()` is exported so the analyses can ask "did any device request `$finish`/`$stop` at this accepted point?" (E-1, E-6, E-55).

`osdiregistry.c` (68 diff lines)

- Loads the absdelay/last_crossing descriptor arrays from each `.osdi` and threads them into the registry entries (E-1, E-6).
- Requires OSDI $\geq$ 0.7 (E-54).

`osdiinit.c` (8 diff lines)

- Registers the `DEVaccept` hook (E-55).
- Publishes the synthetic instance-temperature parameter under both spellings, `dt` and the conventional `dtemp` every built-in device uses; `n1 a b mod dtemp=10` used to fail with *"unknown parameter"* while the underlying plumbing was exact (E-80).

`osdiload.c` (441 diff lines — the largest OSDI change)

- Stamps the absdelay synthetic rows (`y_synth`, `z`) for DC, AC and transient, driving the delay from the recorded history (E-1).
- Evaluates `last_crossing` from the recorded waveform with linear interpolation between the bracketing timepoints (E-6).
- Passes the final-step flag through to `eval()` (E-53).
- Latches eval-return flags per timepoint attempt (`point_eval_flags`, OR-ed across Newton iterations, reset per attempt) so `$finish`/`$stop` under solution-dependent conditions survive to the accepted-point boundary (E-55).

- Folds the stride-2 signed noise-power pairs (`fac·|fac|` semantics) when transferring `load_noise` results (E-54, E-42).

`osdisetup.c` (178 diff lines)

- Creates the synthetic delay-equation unknowns and matrix entries for absdelay (E-1).
- Applies the OSDI nodesets (`OsdiNode.nodeset`) as solver initial guesses (E-45).
- A `$fatal`/`$finish` raised during setup (models rejecting their configuration by design — HiSIM's `$port_connected` guards) used to surface as ngspice's baffling *"impossible error — can't occur"*; it now reads *"a Verilog-A device rejected its configuration during setup"* (E-56).
- An internal OSDI node that appears in no Jacobian entry — a net structurally decoupled from the matrix, e.g. an explicit `ground gnd` reference whose branch contribution `V(p,gnd) <+ …` drops the `gnd` column — used to be allocated its own solver row. That all-zero row/column is benign under Sparse (it decouples to `V=0`) but makes the KLU matrix structurally singular, so KLU returned a wrong DC answer (`groundcontrib`: `v(p)=0` not `1.5`; `hierbranch`: branch currents `0`). Such nodes are now tied to ground (node 0) at setup, matching how OpenVAF already treats them and fixing both solvers (E-116).

`osdiacld.c` (89 diff lines)

- AC loading gains the `ac_stim` right-hand-side injection: the partitioned AC-stimulus source array is loaded through `load_ac_stim` and added to the AC RHS with exact magnitude and phase, `$mfactor` applied linearly (deterministic signals scale with multiplicity) (E-51, E-26).
- Complex (jω-shaped) noise coupling entries participate in the AC matrix (E-54).

`osdinoise.c` (93 diff lines)

- Per-instance grouping of same-named noise sources: coherent summation of complex amplitudes `(a + jω·b)·T` before squaring, per LRM 4.6.4 — same-named sources correlate (including exact anti-phase cancellation), differently-named ones stay independent (E-42).
- Reads the stride-2 signed pairs of ABI 0.7 (E-54).

`osditrunc.c` (34 diff lines)

- Honors `$discontinuity(n)`'s next-step clamp: a negative `bound_step` sentinel from the model limits the step after the event (E-24).
- Honors the step-rejection return flag: when an event fired inside the step, `OSDItrunc` requests `delta/8` (with a `20·CKTdelmin` termination floor) so the integrator bisects onto the discontinuity instead of extrapolating across it (E-55).

`osdi/Makefile.am`

Adds `osdiaccept.c` to the build (E-55).

---

3. Analyses — `src/spicelib/analysis/`

`dctran.c` (46 diff lines)

- Advances OSDI delay/crossing histories via the accept path and skips history corruption on rejected steps (E-1, E-6).
- Issues the dedicated `@(final_step)` evaluation at the converged end of a successful transient (E-53).

- Honors accepted-point `$finish` (ends the analysis cleanly, firing `final_step` at the requesting point), `$stop` (pauses resumably), and aborts with a clear error on `$fatal`'s `E_PANIC` instead of retrying it as nonconvergence (E-55).

`dcop.c` (9) and **`acan.c`** (10)

- Fire `@(final_step)` at their successful end (an operating point fires both step events — a single point is first *and* last) (E-53).
- An AC job's operating-point phase carries the analysis name bit (only the name — adding the reactive `CALC_*` bits would wrongly enable integration at an op), so `analysis("ac")` holds through the whole AC run per LRM 4.6.1 and `@(initial_step("ac"))` fires in AC (E-53).

`dctrcurv.c` (150) + **`include/ngspice/trcvdefs.h`** (13)

- Generic **`.dc @inst[param]`** sweeps (a new sweep code): the DC sweep previously hardcoded Vsource/Isource/Resistor/temperature, so sweeping any other device parameter was a fatal error. The generic sweep resolves `@inst[param]` through the device's own parameter tables, refreshes per point via `DEVtemperature` (for OSDI exactly the `alter` path), nests with other sweep variables, and restores the original value afterwards (E-62).
- Fires `final_step` at the last sweep point; honors a `$finish` raised mid-sweep (E-53, E-55).

`noisean.c` (37)

- A singular AC matrix during noise analysis crashed ngspice with a SIGABRT: the code ignored `NIacIter`'s return and the adjoint solve asserted on the unfactored matrix. It now aborts cleanly ("AC solution failed at … Hz") (E-56).
- Honors deferred `$finish`/`$stop` raised at the noise operating point and fires `final_step` on success (E-55, E-53).

`span.c` (31) + **`cktspdum.c`** (14)

- 1-port S-parameter analyses enabled: the "we need at least two ports" error was over-strict (a 1-port is a plain reflection measurement; the matrix machinery is N-general) — and it was hiding the `cadjoint` crash fixed in `dense.c` (E-64).
- **`Rbase`** published into the sp plot from port 1's `z0`, making the Touchstone writers work with no manual `let Rbase = 50` incantation (E-64).
- Stock NaN fixed in **`donoise`** noise-parameter extraction: the uncorrelated noise conductance `Gu` is analytically zero for fully-correlated single-source topologies, and floating-point rounding could land `sqrt(Ycor² + Gu/Rn)`'s argument at $-10^{-18} \to$ NaN for the noise figure. Clamped to the physical range ≥ 0 — found by parity testing against an OSDI resistor that produced the exact textbook NF where the built-in returned NaN (E-63).

`cktdisto.c` (16)

- `.disto` silently reported zero distortion for OSDI devices — the distortion kernel needs higher-order Taylor coefficients the OSDI ABI cannot provide (first derivatives only), and such devices were skipped without a word. A prominent warning now names each affected OSDI device type (E-62).

---

4. Frontend — `src/frontend/`

`plotting/pyplot.c` (new) + **`com_pyplot.c`** (new) + **`plotit.c`**, **`commands.c`** (E-94)

A new interactive command, **`pyplot`**, plots simulated vectors with matplotlib — a Python counterpart to `gnuplot`. `ft_pyplot()` (`plotting/pyplot.c`) mirrors `ft_gnuplot()`: it writes a `<file>.data` table and a `<file>.py` matplotlib script and `system()`s `python3` (synchronously for a PNG, backgrounded for an interactive window). A new `"pyplot"` device arm in `plotit()` routes to it, so it accepts the same plot expressions as `plot`/`gnuplot`; the `com_pyplot()` wrapper mirrors `com_gnuplot()`, and `pyplot` is registered in both command tables. Two `set` variables tune it: `pyplot_terminal=png` renders headless (Agg) to a PNG, and `pyplot_python` picks the interpreter (default `python3`). Purely additive (E-94). The output file base name is optional (E-95): `com_pyplot()` treats the first word as a file name only when it is not a plot expression (no `(`, and not a vector by `vec_get()`), otherwise it defaults to `pyplot` — so `pyplot v(out)` plots directly (the command's minimum argument count was lowered from 2 to 1). `ft_pyplot()` also grew stacked subplots (`set pyplot_subplots=N` → `plt.subplots(nrows, 1, sharex=True)`, `N` traces per panel; `vs` stays the x-axis, so it is not a panel separator) and matplotlib style sheets (`set pyplot_style=<name>`, `dark` → `dark_background`, guarded) (E-98). The headless `pyplot_terminal` was extended from PNG-only to the vector export formats `svg` and `pdf` (`set pyplot_terminal=svg/pdf` → `fig.savefig(<file>.<fmt>)`, matplotlib picking the writer from the extension), and a figure size control was added (`set pyplot_figsize="W,H"` → `plt.subplots(..., figsize=(W, H))`; quote the value so ngspice keeps the comma) (E-99).

`postcoms.c` (414 diff lines) + **`postcoms.h`** + **`commands.c`** (16)

The Touchstone I/O subsystem (E-64, E-72):

- **`wrsnp`** (with `wrs2p` dispatching to the same handler): Touchstone v1 for any port count — the classic 2-port `S11 S21 S12 S22` column order preserved byte-identically, N $\geq$ 3 in the spec's row-major layout with at most four complex pairs per line;
- writer options `wrsnp <file> [ri|ma|db] [s|y|z] [hz|khz|mhz|ghz]`, any combination in any order: MA/DB formats, Y/Z parameters (normalized to Rbase, `Y·R` / `Z/R`, per the v1 spec), frequency units — the option line reflects every choice;
- **`rdsnp`**: reads any Touchstone v1 file into a new plot with a Hz `frequency` scale and complex vectors matching the `.sp` plot's conventions (MA/DB converted back, Y/Z de-normalized, the 2-port column order handled, `Rbase` published so imports round-trip) — measured data diffs against simulation in one `let` expression.

Why: E-63 showed the S-parameter *analysis* was exact but its results could not leave ngspice in the industry-standard format (`wrs2p` demanded a never-created `Rbase` vector), and nothing could bring VNA data in.

`outitf.c` (16)

- Integer operating-point variables recorded per point: `getSpecial` masked with `IF_REAL` only, so an integer opvar saved with `.save @n1[flag]` produced garbage in transient vectors (E-32).
- The plot-memory guard's message printed `%Id` — a Windows-only printf length modifier that is undefined behavior elsewhere and rendered the message as the numberless `"memory required (Id Bytes)"`. Now `%zu`: real byte counts on every platform (E-77).

`resource.c` (27)

`ft_ckspace()` — the *"approaching max data size"* warning (RSS > 95% of RSS + free RAM) — now honors **`set no_mem_check`** (the same opt-out the fatal output-size estimate in `outitf.c` respects; one variable governs both memory guards) and warns once per excursion above the threshold, re-arming below 90%, instead of repeating on every check through a long analysis (E-81).

`display.c` (1)

`#undef NODEV` before the local macro definition — the macOS SDK's `<sys/param.h>` defines an unrelated `NODEV` (E-77).

---

5. Parser and device registry — `src/spicelib/`

`parser/inpgtok.c` (10)

A **`.model`** card override silently dropped its first parameter when the type name and the opening parenthesis had no space between them (`modname devtype(p1=v1 …)`): `INPgetNetTok`'s scan did not treat `(` as a token boundary, so the type token swallowed the paren and the first parameter name. Found while verifying event-function counters whose model-card overrides mysteriously kept defaults (E-8).

`parser/inpgmod.c` (5)

`find_model_parameter()` dereferenced `*(device->numModelParms)`, which is NULL for built-ins that take no model cards (VCVS, CCCS, …) — any *referenced* `.model m vcvs()` card segfaulted, with no OSDI involved at all (an ordinary MOS instance sufficed). This was the true root of the long-documented "module named like a built-in crashes" gotcha. One NULL guard; both shapes now produce clean, located errors (E-76).

`devices/dev.c` (51)

- Duplicate device-type registration warned and skipped: `osdi_add_device()` appended every descriptor unconditionally, and the model-card lookup scans front-to-back — so a module name duplicated across two loaded libraries silently resolved to the *first* registration (loading an updated model library gave the stale device with no hint), and a module named like a built-in corrupted model creation. Registration now checks the table case-insensitively and skips duplicates loudly (E-76).
- **`pre_osdi`** path dedup: loading an already-loaded file notes it and skips — with the remedy stated: *"restart ngspice to load a recompiled file"* (E-76, E-81).

`osdi/osdiparam.c` (E-93)

Setting a fixed (**`localparam`**) OSDI parameter from the netlist used to be swallowed silently: openvaf exports every `localparam` as a parameter, its "given" flag is forced false, and the written value is overwritten by the parameter-init default — so `.model … N=8` on a frozen structural width parameter changed nothing, with no feedback. `OSDIparam`/`OSDImParam` now test the new `PARA_FLAG_FIXED` descriptor flag (set by openvaf, a free bit of the parameter `flags` field) and emit *"parameter 'N' is a fixed (localparam) value and cannot be set from the netlist; ignored"* instead of silently dropping it (E-93).

---

6. Maths — `src/maths/`

`dense/dense.c` (11 substantive lines; the file also carries a whitespace/line-ending normalization from editing)

`cadjoint()` had no 1×1 base case: its cofactor loop allocated 0×0 and then negative-sized minors, killing ngspice with `malloc: can't allocate -8 bytes` — the crash that had been hiding behind the "at least two ports" guard in `span.c`. The adjugate of `[a]` is `[1]` (the empty minor's determinant is 1 by convention), making `cinverse` of a 1×1 equal `1/a`; a 100 Ω load on a 50 Ω port now writes a proper `.s1p` with S11 = 1/3 exactly (E-64).

`sparse/spfactor.c` (6)

The Markowitz-product overflow guards compare a `double` against `LARGEST_LONG_INTEGER` (= `LONG_MAX`), which is not exactly representable as a double; the conversion is now explicit — identical semantics, intentional and warning-free (E-77).

`KLU/klu_multiply.c` (16)

`SMPmultiply`'s KLU path passed `NULL` internal↔external ordering maps to `KLU_matrix_vector_multiply`, which dereferenced them unconditionally (`&NULL[n] = 0x14` for `n = 5`) and segfaulted — so `.option linesearch` crashed under `.option klu`. The line search is the only caller of `SMPmultiply` under KLU, so this path had never been exercised. A NULL map now means the identity ordering (`ext = i + 1`, since the KLU CSR is 0-based and the RHS/Solution vectors are 1-based), making the KLU matrix-vector product — and hence the E-111 line-search residual merit — correct under KLU, with a merit sequence numerically identical to Sparse 1.3 (E-112).

`KLU/klusmp.c` (SMPcaSolve)

`SMPcaSolve` is the complex adjoint (transposed) solve used by noise and S-parameters. Its Sparse branch calls `spSolveTransposed`, but the KLU branch called the *non-transposed* `klu_z_solve` — silently wrong for any asymmetric matrix (every circuit with a transistor or controlled source), which is why `.noise` was disabled under KLU. It now calls `klu_z_tsolve` (transposed), so KLU noise matches Sparse exactly (including OSDI device models). This is the core of E-113, which also removes the KLU refusal guards in `noisean.c` / `pzan.c` (single-ended pole-zero runs under KLU; balanced-output pole-zero keeps a targeted guard).

`spicelib/analysis/cktsens.c`

Sensitivity builds an auxiliary perturbation matrix `delta_Y` (holding $\partial Y/\partial p$) via `SMPnewMatrix`, which allocates a plain Sparse 1.3 matrix (`delta_Y->CKTkluMODE = 0`, no `SMPkluMatrix`). It is only *multiplied* against the solution (`SMPmultiply` → `spMultiply`), never factored, and `DEVbindCSC` always binds into `ckt->CKTmatrix`, not `delta_Y` — so it is correctly Sparse in every case. But two KLU-only setup blocks were gated on the main matrix's `CKTkluMODE`, so under `.option klu` they ran and dereferenced the NULL `delta_Y->SMPkluMatrix` — a segfault on every DC/AC `.sens` deck. The blocks now gate on `delta_Y->CKTkluMODE` (its own flag, `0`), keeping `delta_Y` Sparse under KLU exactly as it already is under the default solver, while the main `Y` matrix stays KLU. DC and AC sensitivity now match Sparse exactly (E-114).

`spicelib/analysis/distoan.c`

Distortion is a complex analysis (Volterra series solved at the harmonic / intermodulation frequencies via `NIdIter` → `SMPcSolve`), but `distoan.c` had no KLU code at all: under `.option klu` the KLU matrix stayed in *real* mode, the complex solves ran against an unconverted matrix, and every harmonic came back zero — a silent wrong answer. The fix mirrors `acan.c`: before the solve loop it converts the matrix to complex (`DEVbindCSCComplex` per device + `KLUmatrixIsComplex`), and on exit converts back to real (`DEVbindCSCComplexToReal`) so a later real analysis in the same session is unaffected. KLU distortion now matches Sparse bit-for-bit (single-tone, two-tone intermodulation, and OSDI models) (E-115).

---

7. Build system

`xspice/icm/makedefs.in` (4)

The XSPICE codemodel (`.cm`) link rule hardcoded the pre-macOS-10.3 idiom `-bundle -flat_namespace -undefined suppress`, deprecated loudly by the modern linker on all 14 codemodel links (CI macOS builds included). Now `-bundle -undefined dynamic_lookup` — the modern spelling for plugins whose host symbols resolve at load time (E-77).

Autotools regeneration (the ~100 **`Makefile.in`** files + **`config.h.in`**)

Regenerated by `./autogen.sh` with libtool 2.5.4 during the zero-warning work — a build tree whose `configure` predates libtool 2.4.7 selects the deprecated darwin `-undefined suppress` flag whenever `MACOSX_DEPLOYMENT_TARGET` is unset. No hand-written content (E-77).

---

8. Per-enhancement index

Every enhancement that touched ngspice, oldest first:

Enhancement	ngspice files	One line
E-1	osdi.h, osdidefs.h, osdiitf.h, osdiregistry.c, osdiload.c, osdisetup.c, dctran.c (+accept path)	`absdelay()`: synthetic delay rows + waveform history
E-6	osdi.h, osdidefs.h, osdiitf.h, osdiregistry.c, osdiload.c	`last_crossing()`: history + interpolated crossings
E-8	parser/inpgtok.c	`.model` card first-parameter drop fix
E-24	osditrunc.c	`$discontinuity` next-step clamp
E-25	osdi callbacks (get_simparams)	expose `analysis_name` + `simulator` simparams
E-32	outitf.c	integer opvars recorded per point
E-42	osdinoise.c	coherent same-named noise grouping (LRM 4.6.4)
E-45	osdi.h (ABI 0.5), osdisetup.c	Verilog-A nodesets applied to the solver
E-51	osdi.h (ABI 0.6), osdiacld.c	full `ac_stim` AC-RHS injection
E-53	dctran.c, dcop.c, dctrcurv.c, acan.c, noisean.c, osdiload.c	`@(final_step)` + analysis-name phase bits
E-54	osdi.h (ABI 0.7), osdinoise.c, osdiload.c, osdiacld.c, osdiregistry.c	node-free complex noise factors, stride-2 pairs
E-55	osdiaccept.c (new), osdiload.c, osditrunc.c, osdiinit.c, dctran.c, dctrcurv.c, osdiitf.h, Makefile.am	`$finish`/`$stop`/`$fatal` honored; `$discontinuity` step rejection
E-56	noisean.c, osdisetup.c	noise SIGABRT fix; setup-rejection diagnostics
E-62	dctrcurv.c, trcvdefs.h, cktdisto.c	generic `.dc @inst[param]` sweeps; `.disto` warning
E-63	span.c	`donoise` NaN clamp (stock defect, found by parity)
E-64	span.c, cktspdum.c, dense.c, postcoms.c/.h, commands.c	Touchstone export, auto-`Rbase`, 1-port `.sp`, `cadjoint` 1×1
E-72	postcoms.c/.h, commands.c	Touchstone round 2: MA/DB/Y/Z/units + `rdsnp` reader
E-76	dev.c, inpgmod.c	duplicate-registration warning, load dedup, stock `.model` segfault fix

Enhancement	ngspice files	One line
E-77	osdidefs.h, display.c, outitf.c, spfactor.c, makedefs.in (+autotools regen)	zero-warning build, 33 → 0
E-80	osdiinit.c	`dtemp` instance-parameter alias
E-81	resource.c, dev.c	memory-warning opt-out + once-per-excursion; reload-note hint
E-93	osdi.h, osdiparam.c	warn (not silently ignore) when a netlist sets a `PARA_FLAG_FIXED` (`localparam`) OSDI parameter
E-94	plotting/pyplot.c (new), com_pyplot.c (new), plotit.c, commands.c	new `pyplot` command — plot vectors with matplotlib (a Python `gnuplot`)
E-95	com_pyplot.c, commands.c	make the `pyplot` output file name optional (defaults to `pyplot`)
E-98	plotting/pyplot.c	`pyplot` stacked subplots (`pyplot_subplots=N`) + matplotlib style sheets (`pyplot_style`)
E-99	plotting/pyplot.c	`pyplot` vector export formats (`pyplot_terminal=svg/pdf`) + figure size (`pyplot_figsize`)
E-110	optdefs.h, tskdefs.h, cktsopt.c, cktntask.c	`.option errpreset=conservative|moderate|liberal` — one knob for a coordinated tolerance/robustness set; explicit options override regardless of order (`moderate` = historical defaults)
E-111	optdefs.h, tskdefs.h, cktdefs.h, cktsopt.c, cktdojob.c, cktntask.c, cktdest.c, niiter.c	`.option linesearch` — globalized (damped) Newton via Armijo backtracking on a new KCL-residual merit $\|F\| = \|G \cdot x - b\|$; result-neutral, off by default
E-112	maths/KLU/klu_multiply.c	KLU support for `.option linesearch` — `SMPmultiply`'s KLU path passed NULL ordering maps that `klu_matrix_vector_multiply` dereferenced (SIGSEGV); NULL now means identity ordering. Line search verified merit-identical KLU vs Sparse
E-113	maths/KLU/klusmp.c, spicelib/analysis/noisean.c, pzan.c	KLU support for noise + single-ended pole-zero — `SMPcaSolve`'s adjoint KLU branch used the non-transposed solve (silently wrong noise on asymmetric matrices); now `klu_z_tsolve`. Guards removed; balanced-output pz keeps a targeted guard
E-114	spicelib/analysis/cktsens.c	KLU support for sensitivity — the auxiliary perturbation matrix `delta_Y` is Sparse, but two KLU setup blocks gated on the *main* matrix's flag dereferenced its NULL `SMPkluMatrix` (segfault on every DC/AC `.sens`); now gated on `delta_Y`'s own flag. DC/AC `.sens` match Sparse exactly
E-115	spicelib/analysis/distoan.c	KLU support for distortion — `.disto` is a complex analysis but `distoan.c` had no KLU code, so under KLU the matrix stayed real and every harmonic came back zero (silent wrong answer); now converts real↔complex around the solve loop like `acan.c`. Matches Sparse bit-for-bit

Enhancement	ngspice files	One line
E-116	osdi/osdisetup.c	KLU wrong-DC fix — an OSDI internal node with no Jacobian entry (a decoupled `ground` reference) was given an all-zero solver row that made the KLU matrix structurally singular; now tied to ground. Fixes the `groundcontrib` and `hierbranch` KLU_XFAILs
E-117	configure.ac (`+configure`), spicelib/analysis/dcpss.c	Periodic steady state (PSS) productionized — built by default (was experimental `--enable-pss`, so `.pss` was unimplemented in shipped builds); ~230 lines of shooting-loop trace routed through `set ngdebug` (232 → 31 lines by default); fail-fast KLU guard (PSS hangs under KLU) directing `.pss` to `.option sparse`
E-118	spicelib/analysis/dcpss.c	PSS runs under KLU — the shooting loop hung under KLU (`klu_refactor`'s reused pivots inflated the truncation error into a ~20M-step timestep explosion); forcing a full re-factor (`NISHOULDREORDER`) each PSS step makes KLU converge to the same result as Sparse. E-117's Sparse-only guard removed
E-119	pssdefs.h, spicelib/analysis/dcpss.c	Retain the PSS periodic operating point — PSS sampled the node voltages per period for its DFT then freed them, and never captured device states; now the voltages and `CKTstate0` states are captured per sample and retained on the `PSSan` job (with frequency + dims) as the substrate for the periodic small-signal suite (PAC/pnoise/PXF). Self-checks that the retained samples reproduce the fundamental
E-120	spicelib/analysis/dcpss.c	Periodic small-signal Jacobian harmonics — walk the retained operating point, re-linearize each sample (`CKTload` MODEINITSMSIG) and stamp `G+jC` (`CKTacLoad` ω=1), read the osc-node diagonal → `g(t)`, `c(t)`, DFT to harmonics. The blocks the PAC conversion matrix is built from. (Fixed a complex-mode-not-set bug where `C(t)` accumulated across samples.) Verified: RC gives `G=1/R1`, `C=C1`, no harmonics
E-121	spicelib/analysis/dcpss.c	PAC conversion-matrix engine — extend E-120 from the osc diagonal to every matrix nonzero, complex-DFT to harmonics `G_k`, `C_k`, assemble the `(2M+1)N` harmonic conversion matrix `H_{nm}=G_{n−m}+jω_m·C_{n−m}`, inject a unit current at the osc node in sideband 0 and solve by dense complex LU (`pss_csolve`), report the sideband conversion gains. The numerical heart of PAC/pnoise/PXF. Verified: linear RC gives sideband-0 = AC driving-point ‘

Enhancement	ngspice files	One line
E-122	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	`.pac` command (periodic AC) — the user-facing analysis on the E-121 engine. `.pac Fguess StabTime OscNode Points Harmonics SC_iter Steady_coeff <dec|oct|lin> Npts Fstart Fstop` runs PSS then sweeps the input frequency, solving the conversion matrix at each point and emitting the 0-th-sideband node responses as a complex `PAC Analysis` plot (`print/plot/wrdata`). Reuses the PSS analysis via a `PSSdoPAC` flag; engine factored into `pac_extract_harmonics` (once) + `pac_solve_at` (per freq). Verified: swept sideband-0 `|b(f)|` == analytic AC driving-point `|Z(f)|` to 1.6e−7 across 10 kHz–1 MHz
E-123	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	finish `.pac` — (1) source-referenced stimulus: capture the netlist `AC`-source RHS from `CKTacLoad` as the sideband-0 stimulus `B_0` (a periodic-AC transfer/conversion gain), unit-current-at-osc-node fallback; (2) multi-sideband output: optional trailing `maxsideband Ksb` emits every conversion sideband `f_in+k·f0` (`k=−Ksb..Ksb`) as its own vector — sideband 0 keeps the node name, others `<node>_usb<k>`/`<node>_lsb<k>` via `IFnewUid`. Verified: RC with `V1 AC 1` gives sideband-0 = low-pass transfer `1/√(1+(2πfRC)²)` (0.998→0.157) with `b_usb1`/`b_lsb1` ~0 (no conversion)
E-124	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	`.pnoise` command (periodic noise) — fold each device's noise through the conversion matrix. `pac_solve_adjoint` solves `Hᵀ Ψ = e_{out,0}`; `pnoise_sweep` loads the sideband-k adjoint into `CKTrhs`/`CKTirhs` and calls the existing device noise routines (`NevalSrc`, OSDI `load_noise`) once per sideband, accumulating `Σ_k S·|ΔΨ_k|²` — reuses every device noise model via a minimal local `NOISEAN` context. `.pnoise <pss> OutNode InSrc <dec|oct|lin> Np Fstart Fstop`; emits `onoise_spectrum`/`inoise_spectrum`. Verified: linear RC reduces exactly to `.noise` (`4kTR/(1+(2πfRC)²)`, matches the `.noise` reference to every digit)

Enhancement	ngspice files	One line
E-125	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	`.pxf` command (periodic transfer function) — the adjoint of PAC, completing the PSS→PAC→Pnoise→PXF suite. `pxf_sweep` solves `H^T Ψ = e_{out,0}` per frequency and dots each sideband block with the AC-source pattern `B0` → `xf_k=Σ_j Ψ_k(j)·B0(j)`, the input→output transfer at each sideband. `.pxf <pss> OutNode <dec|oct|lin> Np Fstart Fstop [maxsb]`; emits `xf` + `xf_usb<k>`/`xf_lsb<k>`. Verified: by the identity `(H⁻¹B)_out=(H⁻ᵀe_out)ᵀB` the sideband-0 transfer is bit-identical to the PAC response (0.998→0.157 low-pass), conversion sidebands ~2e−16
E-126	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	cyclostationary noise — `.pnoise ... cyclo` evaluates each device's noise PSD `S(t)` at every PSS sample's bias (`CKTload` per sample) and folds it through the time-domain adjoint transfer `A_s(j)=Σ_k Ψ_k(j)e^{j2πks/P}`, averaging: `onoise(f)=(1/P)Σ_s S(t_s)·|ΔA_s|²`. Reuses the device noise routines. Verified: (1) reduces exactly to `.noise` on the linear RC (bias-independent thermal → Parseval); (2) a flicker resistor carrying the RC current gives `onoise·f = R1²·KF·⟨I²⟩ = 4.88e−10` (uses the period-average `⟨I²⟩`, matched to 5 digits)
E-127	include/ngspice/{optdefs,tskdefs,cktdefs}.h, spicelib/analysis/{cktsopt,cktntask,cktdojob,cktopt,cktdest}.c, maths/ni/niiter.c	pseudo-transient continuation — `.option pseudotran` solves `f(x)=0` in a backward-Euler pseudo-transient `f(x)+Gps·(x−x_prev)=0` and marches `dτ` small→large (`Gps`→`0`). `Gps` diagonal via the gmin path; the `Gps·x_prev` RHS coupling (added in `NIiter`) makes each step a stable-trajectory move, not a static gmin step. New `pseudo_transient` in the `CKTop` cascade, off by default. Verified under KLU+Sparse: result-neutral on normal circuits; on a stiff no-limiting exp, reaches the correct DC `0.837922 V` where plain Newton lands on a spurious `70.5 V` (21/21)

Enhancement	ngspice files	One line
E-128	include/ngspice/{optdefs,tskdefs,cktdefs}.h, spicelib/analysis/{cktsopt,cktntask,cktdojob}.c, spicelib/analysis/dctran.c	LTE-based dynamic integration-order control — `.option dynorder` selects the Gear order per step from the local-truncation-error limit instead of the stock 1↔2 toggle, so orders 3–6 (already coded in `NIcomCof` but never used) are actually exercised. The selector compares the raw LTE-limited step (uncapped `CKTtrunc`) at the current order and its ±1 neighbours and moves with hysteresis (1.2×), a settling hold after each change (let the BDF divided differences rebuild), and an order-dependent step-growth cap (2× at order $\leq 3 \rightarrow$ 1.3× at 6). Off by default; bounded by `maxord`; inert at the default `maxord=2`. Stiff-transient guards (post-breakpoint order hold + leaky-bucket rejection-rate order drop) keep it from collapsing the step on a violent slew. Verified under KLU+Sparse: RC decay 3–5× fewer steps at matched accuracy with monotone error; smooth RLC ringdown 8.9× fewer steps AND more accurate (0.13 % vs 0.34 %); nonlinear rectifier matches stock to 5 sig figs; the transistor-level µA741 ±5 V slew completes under dynorder and matches fixed Gear-2
E-129	frontend/outitf.c	sweep progress bar — the throttled `Reference value` status line (redrawn in place every 0.25 s during a sweep) now carries a live progress bar + percentage, e.g. `Reference value : 5.91926e-04 [================== ] 74%`. `outp_progress_frac()` computes the 0–1 fraction per analysis: transient from `(CKTtime−TSTART)/(TSTOP−TSTART)`, AC/noise from the frequency's linear/log position in the band, DC from the accepted-point count over the nested step-count product; analyses with no span (op, …) keep the plain line. Fixed-width (no stale chars), stdout status-line only (never in the rawfile/`wrdata`), same `!ft_norefprint && !cp_background` gating. Verified 22/22: printed % matches the analytic sweep fraction to 0.5 % across tran/AC/DC/noise; op shows no bar

Enhancement	ngspice files	One line
E-130	frontend/com_optimize.{c,h}, commands.c, options.c, include/ngspice/fteext.h, spicelib/analysis/cktdojob.c, frontend/outitf.c	built-in Nelder-Mead optimizer — `optimize -param <name> <init> <lo> <hi> [-param ...] -analysis <cmd> -minimize <expr> [-maxiter N] [-tol T] [-verbose]` varies device/`alter` parameters, re-runs an analysis, and minimizes a scalar objective expression via a derivative-free downhill simplex in normalized [0,1] space (scale-invariant across orders-of-magnitude params). Sub-commands dispatched synchronously through `cp_coms` (not the deferring re-entrant `cp_evloop`); the hundreds of inner analyses are silenced via a new `ft_optimizing` flag gating the banner/row-count/E-129 progress bar at source (`-verbose` to show). Verified 9/9 against analytic optima: DC divider R1→2333.3 Ω, AC low-pass R1→2756.6 Ω, 2-D compound objective R1=3k/R2=2k exactly
E-131	frontend/com_checkpoint.{c,h}, commands.c, com_commands.h, Makefile.am, spicelib/analysis/dctran.c, include/ngspice/cktdefs.h	transient checkpoint / restart — new `savestate <file>` / `loadstate <file>` commands serialize the full transient integration state (solution vector `CKTrhsOld`, device state history `CKTstates[]`, time/step/order/mode, pending breakpoints) to a binary file and resume it, including in a fresh process — so a long run survives a crash, splits across sessions, or moves between machines (stock ngspice could only `resume` in memory). `DCtran()` gains a `CKTcheckpoint`-gated branch that opens a fresh output plot (no live plot to `666`-relink across a reload), initializes the XSPICE breakpoint markers, and fixes up the breakpoint list before jumping into the stepping loop; the rhs length is keyed off `SMPmatSize+1` (not `CKTmaxEqNum`). A stored signature rejects a mismatched circuit; Sparse-solver only (KLU rejected with a clear message). Verified 19/19: resumed waveform bit-identical to an uninterrupted run for RC-step/pulse/diode built-ins and ~2e-7 for a compiled OSDI diode, across a separate process

Enhancement	ngspice files	One line
E-132	spicelib/analysis/dcpss.c, spicelib/parser/inp2dot.c, spicelib/analysis/psssetp.c, include/ngspice/pssdefs.h	periodic S-parameters (`.psp`) — small-signal scattering parameters around a PSS operating point, including conversion between the input frequency and its sidebands `f_in+k·f0` (mixers / switched circuits, where a static-DC `.sp` cannot see the conversion). Sits on the PSS→conversion-matrix suite (E-117–126): after PSS, `psp_sweep` excites each RF port (`portnum`/`z0`, the `.sp` framework) by driving its branch source (V=1, like `.sp`'s `VSRCspupdate`) through the shared `(2M+1)N` conversion matrix, reads per-sideband port waves in the same Kurosawa power-wave convention, and forms `S^(k)=B^(k)·A^−1` (dense-complex `cinverse`/`cmultiply`). `pac_solve_at`'s matrix assembly factored into a reusable `pac_build_matrix`; `PSSdoPSP` flag + `psp` PSS param + `dot_psp` card. Because `S=B·A^−1` is excitation-basis-invariant, sideband 0 reduces exactly to `.sp` for a time-invariant network. Runs under both linear solvers (the conversion matrix is a standalone dense LU; PSS runs under both since E-118). Verified 8/8: sideband-0 matches `.sp` to ~1e-16 for 1/2/3-port resistive + reactive networks (magnitude and phase) incl. OSDI Verilog-A devices (G + reactive `ddt` stamps), conversion sidebands correctly ~0
E-133	frontend/com_qpss.{c,h}, commands.c, com_commands.h, Makefile.am	quasi-periodic (two-tone) steady state (`qpss`) — `qpss <expr> <f1> <f2> [periods] [maxorder]` computes the two-tone steady-state spectrum: every mixing product `k1·f1+k2·f2` including third-order intermodulation (IM3 at 2f1-f2 / 2f2-f1) that single-tone AC/PSS cannot show. For commensurate tones (common beat `fb=gcd(f1,f2)`) it runs an ordinary transient over a few beat periods to reach steady state, then evaluates the Fourier coefficient directly at each exact intermod frequency (a direct DFT, exact — no FFT-bin rounding) and labels it by the 2-D index `(k1,k2)`. Deliberately not a slow beat-frequency shooting PSS; a front-end command driving a transient, so solver-independent and works with built-in and OSDI devices. Verified 11/11: analytic fundamentals/IM3/3f of a cubic, no even-order products, the 3:1 IP3 slope law (fund ×2, IM3 ×8 per 2× drive), beat-frequency derivation, and an OSDI cubic matching the built-in

Enhancement	ngspice files	One line
E-134	spicelib/analysis/dcpss.c, frontend/com_hb.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h	Harmonic Balance (`hb <f0> <K>`) — solves the periodic steady state in the frequency domain by Newton (each node a truncated Fourier series), instead of integrating in time; the real analysis behind ngspice's unimplemented `WITH_HB` stub. Residual `F_k = I_R,k(V) + [dq/dt]_k − Is_k = 0` with the E-121 `(2K+1)N` conversion matrix as the exact Jacobian. Per iteration: inverse-DFT V→v(t_s); drive DC+AC device loads at those voltages for the resistive current `I_R = G*v − b` (companion `b` saved before acLoad, so it's the ACTUAL current not the tangent `G*v`), and `G(t)/C(t)`; DFT; dense complex Newton (`pss_csolve`). Nonlinear reactive with NO charge extraction: `dq/dt = C(v)*v'`, so the reactive current is the conversion matrix's `jwC` term applied to V. Solver-independent (KLU + Sparse): the dense complex Newton is HB's own; the sparse solver only *reads* `G(t)/C(t)` off the device matrix, so `hb_extract` carries the same `#ifdef KLU` complex-CSC binding (`DEVbindCSCComplex`) as the PAC extraction, and `com_hb` copies the task's KLU mode before building so a bare `hb` honours `.option klu` — verified bit-identical under both. Built-in + OSDI. Verified 8/8 vs transient/`fourier`, quadratic convergence: nonlinear R (analytic 3rd harmonic), R+C, a real diode rectifier (junction limiting), OSDI varactor `Q(v)` 2nd harmonic, KLU==Sparse parity

Enhancement	ngspice files	One line
E-135	spicelib/analysis/dcpss.c, examples/hb_examples/verify_hb.py	HB source-stepping continuation — makes E-134 Harmonic Balance robust on strongly-driven circuits where a cold full-strength Newton diverges (`|F|`→`1e69`). `HBanalyze`'s Newton loop is wrapped in an adaptive homotopy: every independent source scaled by `λ: 0`→`1`, each level warm-started from the last converged `V`. The residual becomes `F = I_R + I_C − λ·Is`; on level success `V` is checkpointed and `dλ` grows (×1.7), on failure (Newton exhausted, residual non-finite, or singular Jacobian) `V` is restored and `dλ` halves; `dλ<1e−5` → reported as no reachable steady state. First level is full strength (`dλ=1`) so easy circuits converge at `λ=1` immediately, bit-identical to the plain solve. Automatic (no new syntax); `set hb_verbose` shows the λ ramp, summary reports iterations + continuation steps. Verified 9/9: a strongly-driven diode rectifier (5 V into 20 Ω, sharp `IS=1e−14`) diverges cold but converges in 3 continuation steps, matching transient `fourier` to <0.1% for DC/f0/2f0; the 8 existing HB checks stay bit-identical
E-136	spicelib/analysis/dcpss.c, frontend/com_qpss.c, frontend/commands.c, include/ngspice/cktdefs.h, examples/qpss_examples/verify_qpss_hb.py	two-tone Harmonic Balance (`qpss <expr> <f1> <f2> hb [K1] [K2]`) — the TRUE, incommensurate-capable quasi-periodic steady state, a frequency-domain HB engine alongside the E-133 transient `qpss` (which is unchanged, commensurate-only). Each node is a 2-D Fourier series `v(t)=ΣΣ V_{k1,k2} e^{j(k1ω1+k2ω2)t}`; `QPSShb` samples devices on a 2-D phase grid `(θ1,θ2)` — time never appears, so incommensurate tones (no beat period) just work — and 2-D DFTs to the conversion matrix `H_{(n),(m)}=G_{n−m}+jω_m·C_{n−m}` (`qp_build_matrix`), Newton-solved by `pss_csolve` with the E-135 source stepping. Sources captured by an oversampled least-squares APFT (`Γ^H Γ) Is = Γ^H b` (a square Vandermonde is catastrophically ill-conditioned past a few harmonics). Reactive needs NO charge extraction (`dq/dt=C(v)v'`); the converged operating point is retained (`qpss_hb_saved`) for `qpac` (E-137). Solver-independent (KLU + Sparse) — same `#ifdef KLU` complex-CSC binding as PAC/HB. Built-in + OSDI. Verified 7/7: analytic cubic `|IM3(2,−1)|/|3rd(3,0)|=3`, even products ~0, 3:1 IP3 slope, incommensurate ?2 tones (E-133 cannot), HB==transient (commensurate), KLU==Sparse; E-133 `verify_qpss.py` stays 11/11

Enhancement	ngspice files	One line
E-137	spicelib/analysis/dcpss.c, frontend/com_qpac.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h, examples/qpss_examples/verify_qpac.py	two-tone small-signal QPAC (`qpac <f_in>`) — completes the quasi-periodic gap: the two-tone analogue of PAC. Run after `qpss … hb`, `QPACanalyze` injects a small signal at `f_in` around the retained QPSS operating point (`qpss_hb_saved`) and reports the response at every sideband `f_in+k1·f1+k2·f2`, mixing it through the SAME 2-D conversion matrix `H_{(n),(m)}=G_{n−m}+jω_m·C_{n−m}` (`qp_build_matrix` at `f_in`) that the QPSS Newton used as its Jacobian. Stimulus placed in the `(0,0)` sideband — a netlist `AC`-source RHS `B0` (captured bias-independent at the op-point) or a unit-current fallback — one dense `pss_csolve`. Adds no device evaluation → solver-independent (KLU + Sparse) by construction. Verified 7/7: reduce-to-AC (pump→0 ⍰ direct `(0,0)` = plain `.ac` response = R, sidebands vanish), `v²`-pump conversion ratio `|(1,1)|/|(2,0)|=2`, equal-tone symmetry, clean no-op-point error, KLU==Sparse; E-136 (7/7) + E-133 (11/11) unaffected
E-138	spicelib/analysis/dcpss.c, frontend/com_qpnoise.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h, examples/qpss_examples/verify_qpnoise.py	two-tone small-signal QPnoise (`qpnoise <output_node> <f_in>`) — quasi-periodic noise, the two-tone analogue of pnoise (E-124), on the retained `qpss … hb` operating point. Reports output + input-referred noise density at `f_in`, folding every device's noise over all sidebands `f_in+k1·f1+k2·f2` (mixer/PA noise conversion invisible to a static `.noise`). `QPnoiseAnalyze` biases the devices at the QPSS operating point, then `qp_solve_adjoint` transposes the 2-D conversion matrix (`qp_build_matrix`) and solves `Hᵀ Ψ = e_{out,(0,0)}` — one adjoint gives the transimpedance from every (node, sideband) to the output; each device's `DEVnoise` computes `S·|Ψ|²` (reading the transfer from `CKTrhs`/`CKTirhs`) and the sum over all Nh harmonics is the folded onoise; input-referred via the QPAC gain. Reads only retained data → solver-independent (KLU + Sparse) by construction. With no pump the conversion matrix is block-diagonal so only `(0,0)` survives ⍰ reduces to `.noise`. Verified 6/6: reduce-to-noise (pump→0 ⍰ onoise == plain `.noise` == `4kTR` exactly), conversion active under pump, `inoise=onoise/gain²`, clean no-op-point error, KLU==Sparse; E-133 (11/11) + E-136 (7/7) + E-137 (7/7) unaffected

Enhancement	ngspice files	One line
E-139	spicelib/analysis/dcpss.c, frontend/com_qpnoise.c, frontend/commands.c, include/ngspice/cktdefs.h, examples/qpss_examples/verify_qpnoise.py	cyclostationary QPnoise (`qpnoise <output_node> <f_in> cyclo`) — upgrades E-138 to a time-varying device PSD. Under a two-tone pump a device's bias swings over the period (a diode's shot noise `2qI_D(t)` spikes when it conducts), so `QPnoiseAnalyze` gains a `cyclo` branch using the identity `onoise = (1/P)·Σ_s S(t_s)·|A_s|²`, where `A_s(j) = Σ_{(k1,k2)} Ψ_{(k1,k2)}(j)·e^{j2π(k1 s1/P1+k2 s2/P2)}` is the inverse 2-D DFT of the adjoint transfers (the time-domain transimpedance at phase sample s). Each sample re-biases the devices at the retained op-point (`qp_synth`, `P1`/`P2` now stored in `qp_harm`) with per-sample junction settling (the E-134 `MODEINITFLOAT` walk — else a limited diode reports a stale bias and the "cyclostationary" result collapses onto the stationary one), evaluates `S(t_s)`, folds through `A_s`, and averages. By Parseval reduces to the stationary sum (and `.noise`) when `S` is constant. Verified 10/10 (6 E-138 + 4 cyclo): cyclo reduce-to-noise, Parseval (bias-independent thermal PSD ⇒ cyclo==stationary even under pump), a hard-pumped diode where cyclo differs from stationary by ~8× (switching-mixer cyclostationary enhancement, visible only with the settling), cyclo KLU==Sparse; E-133/136/137 unaffected

Enhancement	ngspice files	One line
E-140	spicelib/analysis/dcpss.c, frontend/com_hbosc.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h, examples/phasenoise_examples/verify_phasenoise.py	oscillator phase noise (`hbosc <oscnode> <K> [fguess] [tstab]` + `phasenoise <fstart> <fstop> [pts]`) — closes the periodic/phase-noise gap with the phase-noise pkg. `HBOSCanalyze` is an autonomous harmonic balance: an oscillator has no source, so `F(V)=I_R+[dq/dt]=0` is solved for the harmonics AND the unknown oscillation frequency `ω0`. The conversion matrix `dF/dV=H` is singular (right null space = phase mode `u_k=jkV_k`, since the oscillator's phase is free), so Newton runs on the bordered system `[H, ∂F/∂ω0; u∗ᵀ, 0]` (nonsingular by bordering, `∂F/∂ω0=I_C/ω0`, gauge row `u∗`), transient-seeded (`hbosc` runs a short transient from the deck's `.ic`, reads amplitude + zero-crossing frequency), converging quadratically (LC osc: 4 iters to `|F|=3e−12`; inductors fit the `G+jωC` matrix via branch-current MNA). `PhaseNoiseAnalyze` builds the adjoint of `H` at OFFSET `df` with the unit at the carrier sideband (m=1) and folds device noise (`DEVnoise`); as `df`→`0` the limit-cycle matrix goes singular through the phase mode so the transimpedance diverges as `1/df` → folded noise `1/df²`, normalized to carrier power `2|V1|²` → `L(df)` in dBc/Hz. Verified 8/8 on an LC oscillator: autonomous HB converges to `f0`+describing-function amplitude, `L(df)` has the −20 dB/dec skirt near carrier flattening into the noise floor at a physical level (≈−147 dBc/Hz @1kHz), thermal scaling **`L`**∝**`T`** (2×T → +3 dB exactly, pinning the absolute), clean no-op-point error, KLU==Sparse; pnoise (9/9) + qpnoise (10/10) unaffected

Enhancement	ngspice files	One line
E-141	spicelib/analysis/dcpss.c, frontend/com_qpxf.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h, examples/qpss_examples/verify_qpxf.py	two-tone small-signal QPXF (`qpxf <output_node> <f_in>`) — the quasi-periodic transfer function, the ADJOINT of QPAC (E-137), completing the two-tone small-signal suite (QPSS→QPAC→QPnoise→QPXF ≡ PSS→PAC→pnoise→PXF). `QPXFanalyze` runs one adjoint solve `Hᵀ Ψ = e_{out,(0,0)}` (`qp_solve_adjoint`, reused from QPnoise E-138) and dots each sideband block of Ψ with the netlist AC-source pattern `B0` (the QPAC stimulus, captured at the op-point) → the transfer `H_{(k1,k2)} = Σ_j Ψ_{(k1,k2),j}·B0_j` from an input at every sideband `f_in+k1·f1+k2·f2` to the output, all from ONE adjoint. By the reciprocity identity `(H⁻¹B)_out=(H⁻ᵀe_out)ᵀB` the sideband-`(0,0)` transfer is bit-identical to the QPAC response (the PXF↔PAC cross-check, E-125). Reads only retained data → solver-independent (KLU + Sparse). Verified 6/6: reciprocity (QPXF(0,0)==QPAC(0,0) bit-identical), conversion-sideband reciprocity, reduce-to-XF (pump→0 ⍰ `(0,0)`=plain transfer=R, sidebands vanish), clean no-op-point error, KLU==Sparse; QPSS 11/11 + QPSS-HB 7/7 + QPAC 7/7 + QPnoise 10/10 unaffected

Enhancement	ngspice files	One line
E-142	spicelib/analysis/dcpss.c, frontend/com_qpac.{c,h}, com_qpnoise.c, com_qpxf.c, commands.c, include/ngspice/cktdefs.h, examples/qpss_examples/verify_qpss_sweep.py	input-frequency sweep for the two-tone small-signal analyses. `qpac`/`qpnoise`/`qpxf` gain a `<dec|oct|lin> N fstart fstop` sweep of `f_in` that emits a plottable ngspice plot (conversion gain / noise figure / image-rejection curves vs frequency), matching how `.ac`/`.pnoise`/`.pxf` sweep. `QPACsweep`/`QPnoiseSweep`/`QPXFsweep` step `f_in` and reuse the exact single-frequency solve per point: `qpac` records per-node `|(0,0) response|`, `qpnoise` records `onoise_spectrum`/`inoise_spectrum`, `qpxf` records `xf` (in-band `(0,0)`) + `xf_conv` (total conversion √Σ`|H_{sb≠0}|²`). The analysis fills plain arrays; the front-end builds the plot with a `frequency` scale via the nutmeg vector API (`plot_alloc`/`dvec_alloc`/`vec_new`) — the correct layer for a front-end command (the analysis OUTp framework dereferences a live analysis job's `JOBtype`, which a front-end command lacks → was crashing). Shared helpers `qp_steptype`/`qp_sweep_maxpts`/`qp_emit_plot`. Verified 5/5: swept value at 0.3G == single-frequency `qpac`/`qpxf`/`qpnoise` (machine precision), reactive roll-off vs `f_in`, correct point count; single-frequency QPAC 7/7 + QPnoise 10/10 + QPXF 6/6 unaffected

Enhancement	ngspice files	One line
E-143	frontend/com_optimize.c, frontend/commands.c, examples/optimize_examples/verify_optimize.py, examples/optimize_examples/optimize_lsq_demo.cir	gradient least-squares curve fitting for **`optimize`**. The built-in optimizer (E-130, derivative-free Nelder-Mead on a scalar `-minimize`) gains a least-squares mode: one or more weighted `-target <expr> <value> [<weight>]` measurements, optionally spread over several `-analysis` stages (each `-analysis` opens a stage; following `-target`s attach to it, so a single fit can combine e.g. a DC operating point AND an AC response), are fitted with Levenberg-Marquardt — a forward/backward finite-difference Jacobian `J`, normal equations `A=JᵀJ`, `g=Jᵀr`, damped solve `(A+λ·diag(A))δ=−g` via a small partial-pivot Gauss solver, standard λ up/down loop. Exploiting the sum-of-squares structure it converges in far fewer analysis runs than the simplex (27 vs 67 evals on a two-target RC fit). `-method nm|lm` overrides the auto choice (LS→lm, scalar→nm); the scalar `-minimize`/Nelder-Mead path is unchanged; `-minimize` and `-target` are mutually exclusive. Parameters are still applied in place with `alter` (no re-source) and the search runs in normalized [0,1] space. All changes in `com_optimize.c` (+ one help string); no new files, no ABI change. Verified 23/23 (E-130 checks [1]–[5] + E-143 [6]–[10]): 1-param/3-target/3-stage RC magnitude fit, 2-param DC+AC multi-analysis fit (R1=3k,R2=2k), LM-fewer-evals-than-NM, OSDI/Verilog-A diode extraction (recover both `is`→1e-14 and `n`→1.2 from two measured I-V points by weighted least squares), and input validation (lm-without-target, minimize+target, multi-analysis+scalar all rejected)

Enhancement	ngspice files	One line
E-144	frontend/com_optimize.c, frontend/inp.c, frontend/commands.c, examples/optimize_examples/verify_optimize.py, examples/optimize_examples/optimize_dparam_expander	**optimize** tunes symbolic **.param** values via a new knob kind −dparam. −param remains an alter target (device/instance, changed in place); −dparam names a netlist .param symbol (e.g. .param w=1u, R1={500∗k}) which — being expanded at parse time — is changed with alterparam <name>=<value> + a reset that re-sources the deck (re-evaluating .param expressions and re-stamping device values). Per parameter a kind (OPT_ALTER / OPT_DECKPARAM) is tracked; when any −dparam is present opt_eval applies ALL deck params first, re-sources ONCE, THEN applies the in-place alter params (reset rebuilds from the deck and would otherwise wipe an earlier alter — this ordering is what lets the two kinds mix; verified on a joint .param+device fit). No −dparam ? the E-130/-143 fast path is untouched (no reset, no perf hit). The two re-source banners (Reset re−loads circuit … and Circuit: … in inp.c) are gated by the existing ft_optimizing flag so hundreds of inner re-sources are silent (only the final leave-at-optimum run shows); ft_optimizing re-asserted after each reset. Also fixed 5 pre-existing −Wsign−conversion warnings in inp.c's ∗ng_script_with_params handler (argc/size unsigned). Closes the last E-143 follow-up. No new files, no ABI change. Verified 31/31 (E-130/-143 [1]–[10] + E-144 [11]–[15]): scalar .param fit (rtop→2333.3), mixed −dparam+−param joint fit (rtop=3k,R2=2k), .param in expression (k→6), least-squares −dparam (LM), quiet re-source (≤1 banner); AC + OSDI-device-value .param verified manually

Enhancement	ngspice files	One line
E-145	frontend/com_optimize.c, frontend/commands.c, examples/optimize_examples/verify_optimize.py, examples/optimize_examples/optresm.va, examples/optimize_examples/optimize_mparam_demo.cir	**optimize** tunes **.model**-card parameters via a third knob kind –mparam. –param remains an alter instance target and –dparam a symbolic .param (re-source); –mparam <@model[param]> names a .model-card parameter (e.g. @dmod[is], @rmod[r]) — which is NOT alter-reachable and NOT –dcr sweepable (only sources/resistors/instance params are) — and is changed in place with altermod <name>=<value>, no re-source (as cheap per eval as –param, unlike –dparam). A new kind value OPT_MODELPARAM; in opt_eval the deck params are re-sourced first (E-144), then the in-place knobs: alter for instances, altermod for models. @model[param] is passed straight to altermod (which accepts that accessor form), mirroring how –param @m1[w] emits alter @m1[w]=…. Circuits with only –param/–mparam keep the E-130/-143 fast path (no reset). All three knob kinds mix in one run. Change confined to com_optimize.c (+1 help line); no new source files, no inp.c change, no ABI change. Verified 39/39 (E-130/-143/-144 [1]–[15] + E-145 [16]–[20]): OSDI model-param fit (@rmod[r] →3k), built-in diode model-param fit (@dmod[is] →1.22e-14), determined model+instance joint fit (r=3k,R2=2k), –mparam does 0 re-sources (in-place fast path), and all three kinds (–dparam+–mparam+–param) coexist and converge

(E-25's simparam exposure lives in the OSDI callback table populated at load time; its diff rides inside the osdiload.c/callbacks changes.)

Build-warning cleanup (post-E-127): a full rebuild under the repo's –Wconversion flags surfaced latent warnings. configure.ac had –s (a strip flag) in the compile CFLAGS, so clang warned "argument unused during compilation: '-s'" on every source file (~1526 warnings) — removed (binaries are stripped separately by the fold and CI). –Wconversion also flagged a real latent bug in maths/ni/nipzmeth.c (b = 0.0 was an assignment where b == 0.0 was intended) — fixed — and benign double→bool conversions in maths/cmaths/cmath4.c — made explicit. Full-build warnings dropped 1903 → 394; the remainder are –Wconversion warnings in third-party SuiteSparse (KLU) and CMC device models (HiSIM), which are left to their upstream sources.

Every entry above is guarded by a verify script under examples/ and was regression-checked against the full example arsenal, the compiler's integration suite, and the VA_TEST industry-model corpus at the time it landed.