

ngspice-46 — Full Change Report

Every modification and its reason (original → current)

Ngspice + OpenVAF Enhancements project

July 2026

Contents

ngspice-46 — Full Change Report	3
1. The OSDI ABI, version 0.4 → 0.7	3
2. The OSDI runtime — <code>src/osdi/</code>	4
3. Analyses — <code>src/spicelib/analysis/</code>	5
4. Frontend — <code>src/frontend/</code>	7
5. Parser and device registry — <code>src/spicelib/</code>	8
6. Maths — <code>src/math/</code>	8
7. Build system	10
8. Per-enhancement index	10

ngspice-46 — Full Change Report

Every modification applied to ngspice-46 in this project, with its reason. The baseline is the pristine ngspice-46 source tree (as vendored in the project's `original/` snapshot, which already contains OpenVAF-Reloaded's stock OSDI support); the current state is the tree committed in this repository under `ngspice-46/`. Each entry links the enhancement write-up in [enhancements_doc/](#) that carries the full engineering detail and the verifying example suite. The companion document [openvaf_changes_full-report.md](#) covers the compiler side.

Maintenance note: this report is updated whenever an enhancement touches ngspice sources. If you are reading it alongside a newer tree, the per-enhancement index at the end tells you the last change it covers.

Scope summary. One new source file and 41 modified ones carry all the functional changes (~2,000 substantive diff lines). A further ~100 `Makefile.in` files and `config.h.in` differ only because the auto-tools were regenerated with a current libtool ([E-77](#)); they contain no hand-written changes and are not listed individually. Everything below is behavior, interface, or diagnostics.

1. The OSDI ABI, version 0.4 → 0.7

`src/osdi/osdi.h` is the authoritative C contract between ngspice and the `.osdi` objects `openvaf-r` produces. The project extended it four times — twice additively (new exported symbols old loaders simply never look up), twice with genuine version bumps (layout changes):

Change	Kind	Enhancement	Why
<code>OSDI_ABSDELAY_COUNT</code> / <code>OSDI_ABSDELAY_INFO</code> exports	additive sym- bols	E-1	<code>absdelay()</code> needs simulator-side waveform history and synthetic delay-equation rows; the descriptors tell ngspice which nodes/offsets each delay slot uses
<code>OSDI_LAST_CROSSING_COUNT</code> / <code>OSDI_LAST_CROSSING_INFO</code> exports	additive sym- bols	E-6	<code>last_crossing()</code> needs waveform history and crossing interpolation — same additive pattern as <code>absdelay</code>
<code>OsdiNode.nodeset</code> field	ABI 0.5 (node stride change)	E-45	Verilog-A net initializers (<code>electrical a = 5.0;</code>) become solver initial-guess nodesets; every node record carries the hint
<code>num_ac_stim_src</code> / <code>ac_stim_sources</code> / <code>load_ac_stim</code> descriptor tail	ABI 0.6 (de- scriptor grows)	E-51	full <code>ac_stim()</code> support: a Verilog-A module can be the AC stimulus, so the descriptor must enumerate its AC right-hand-side sources
<code>load_noise</code> destination stride 1 → 2 (signed (<code>flat</code> , <code>react</code>) power pairs)	ABI 0.7	E-54	correct noise physics: operating-point-dependent factors and <code>ddt()</code> -shaped ($j\omega$) noise need a complex amplitude per source, $re + j\omega \cdot im$, so coherent same-named sources (LRM 4.6.4) sum with correct sign and frequency shape

Two additive flag conventions ride on the existing `eval()` interface (not version bumps):

- `EVAL_FLAG_IS_FINAL_STEP` (bit 1 ≪ 21) in the `eval input` flags — `@(final_step)` firing ([E-53](#));
- `eval return` flags for `$finish/$stop` requests and `$discontinuity`-driven step rejection ([E-55](#)).

Pairing consequence: this ngspice requires $\text{OSDI} \geq 0.7$ and rejects older objects with a clear version message; `.osdi` files from older compilers must be recompiled (E-54).

2. The OSDI runtime — `src/osdi/`

osdiaccept.c — new file (E-55, E-1, E-6)

The accepted-timepoint hook (`DEVaccept`) OSDI previously lacked. It advances the `absdelay/last_crossing` waveform histories only at *accepted* points (so rejected timesteps don't corrupt the delay lines) and reads the per-attempt latched `$finish/$stop` request flags at the one boundary where honoring them is safe. Why: acting on `$stop` mid-Newton-iteration was treated as a step failure and ground the timestep into a rejection loop; `$finish` was ignored outright.

osdidefs.h (104 diff lines)

- `OsdiExtraInstData` grows the per-instance fields behind every runtime feature: `dt/temp` offsets with given-flags (instance temperature), `eval_flags`, `absdelay` waveform-history rows and pre-allocated KLU/SPARSE matrix-pointer sets for the delay-equation rows (re-pointed on every DC↔AC transition, mirroring the regular Jacobian handling), and the `last_crossing` history (E-1, E-6, E-55).
- `ALIGN` macro renamed `OSDI_ALIGN`: the macOS SDK's `<sys/param.h>` defines an unrelated `ALIGN`, producing a redefinition warning in every OSDI translation unit (E-77).

osdiitf.h / osdiext.h

The registry-entry structure gains the `absdelay/last_crossing` descriptor pointers, and `OSDIpendingRequests()` is exported so the analyses can ask "did any device request `$finish/$stop` at this accepted point?" (E-1, E-6, E-55).

osdiregistry.c (68 diff lines)

- Loads the `absdelay/last_crossing` descriptor arrays from each `.osdi` and threads them into the registry entries (E-1, E-6).
- Requires $\text{OSDI} \geq 0.7$ (E-54).

osdiinit.c (8 diff lines)

- Registers the `DEVaccept` hook (E-55).
- Publishes the synthetic instance-temperature parameter under both spellings, `dt` and the conventional `dtemp` every built-in device uses; `n1 a b mod dtemp=10` used to fail with "unknown parameter" while the underlying plumbing was exact (E-80).

osdiload.c (441 diff lines — the largest OSDI change)

- Stamps the `absdelay` synthetic rows (`y_synth`, `z`) for DC, AC and transient, driving the delay from the recorded history (E-1).
- Evaluates `last_crossing` from the recorded waveform with linear interpolation between the bracketing timepoints (E-6).
- Passes the final-step flag through to `eval()` (E-53).
- Latches `eval`-return flags per timepoint attempt (`point_eval_flags`, OR-ed across Newton iterations, reset per attempt) so `$finish/$stop` under solution-dependent conditions survive to the accepted-point boundary (E-55).

- Folds the stride-2 signed noise-power pairs ($\text{fac} \cdot |\text{fac}|$ semantics) when transferring `load_noise` results (E-54, E-42).

osdisetup.c (178 diff lines)

- Creates the synthetic delay-equation unknowns and matrix entries for `absdelay` (E-1).
- Applies the OSDI nodesets (`OsdiNode.nodeset`) as solver initial guesses (E-45).
- A `$fatal/$finish` raised during setup (models rejecting their configuration by design — HiSIM's `$port_connected` guards) used to surface as ngspice's baffling *"impossible error — can't occur"*; it now reads *"a Verilog-A device rejected its configuration during setup"* (E-56).
- An internal OSDI node that appears in no Jacobian entry — a net structurally decoupled from the matrix, e.g. an explicit ground `gnd` reference whose branch contribution `V(p,gnd) <+ ...` drops the `gnd` column — used to be allocated its own solver row. That all-zero row/column is benign under Sparse (it decouples to $V=0$) but makes the KLU matrix structurally singular, so KLU returned a wrong DC answer (groundcontrib: $v(p)=0$ not 1.5; hierbranch: branch currents 0). Such nodes are now tied to ground (node 0) at setup, matching how OpenVAF already treats them and fixing both solvers (E-116).

osdiacld.c (89 diff lines)

- AC loading gains the `ac_stim` right-hand-side injection: the partitioned AC-stimulus source array is loaded through `load_ac_stim` and added to the AC RHS with exact magnitude and phase, `$mfactor` applied linearly (deterministic signals scale with multiplicity) (E-51, E-26).
- Complex ($j\omega$ -shaped) noise coupling entries participate in the AC matrix (E-54).

osdinoise.c (93 diff lines)

- Per-instance grouping of same-named noise sources: coherent summation of complex amplitudes $(a + j\omega \cdot b) \cdot T$ before squaring, per LRM 4.6.4 — same-named sources correlate (including exact anti-phase cancellation), differently-named ones stay independent (E-42).
- Reads the stride-2 signed pairs of ABI 0.7 (E-54).

osditrunc.c (34 diff lines)

- Honors `$discontinuity(n)`'s next-step clamp: a negative `bound_step` sentinel from the model limits the step after the event (E-24).
- Honors the step-rejection return flag: when an event fired inside the step, `OSDitrunc` requests `delta/8` (with a $20 \cdot \text{CKTdelmin}$ termination floor) so the integrator bisects onto the discontinuity instead of extrapolating across it (E-55).

osdi/Makefile.am

Adds `osdiaccept.c` to the build (E-55).

3. Analyses — **src/spicelib/analysis/**

dctran.c (46 diff lines)

- Advances OSDI delay/crossing histories via the accept path and skips history corruption on rejected steps (E-1, E-6).
- Issues the dedicated `@(final_step)` evaluation at the converged end of a successful transient (E-53).

- Honors accepted-point `$finish` (ends the analysis cleanly, firing `final_step` at the requesting point), `$stop` (pauses resumably), and aborts with a clear error on `$fatal`'s `E_PANIC` instead of retrying it as nonconvergence ([E-55](#)).

dcop.c (9) and **acan.c** (10)

- Fire `@(final_step)` at their successful end (an operating point fires both step events — a single point is first *and* last) ([E-53](#)).
- An AC job's operating-point phase carries the analysis name bit (only the name — adding the reactive `CALC_*` bits would wrongly enable integration at an op), so `analysis("ac")` holds through the whole AC run per LRM 4.6.1 and `@(initial_step("ac"))` fires in AC ([E-53](#)).

dctrcurv.c (150) + **include/ngspice/trcvdefs.h** (13)

- Generic `.dc @inst[param]` sweeps (a new sweep code): the DC sweep previously hardcoded `Vsource/Isource/Resistor/temperature`, so sweeping any other device parameter was a fatal error. The generic sweep resolves `@inst[param]` through the device's own parameter tables, refreshes per point via `DEVtemperature` (for OSDI exactly the `alter` path), nests with other sweep variables, and restores the original value afterwards ([E-62](#)).
- Fires `final_step` at the last sweep point; honors a `$finish` raised mid-sweep ([E-53](#), [E-55](#)).

noisean.c (37)

- A singular AC matrix during noise analysis crashed ngspice with a SIGABRT: the code ignored `NIacIter`'s return and the adjoint solve asserted on the unfactored matrix. It now aborts cleanly ("AC solution failed at ... Hz") ([E-56](#)).
- Honors deferred `$finish/$stop` raised at the noise operating point and fires `final_step` on success ([E-55](#), [E-53](#)).

span.c (31) + **cktspdum.c** (14)

- 1-port S-parameter analyses enabled: the "we need at least two ports" error was over-strict (a 1-port is a plain reflection measurement; the matrix machinery is N-general) — and it was hiding the `cadjoint` crash fixed in `dense.c` ([E-64](#)).
- **Rbase** published into the `sp` plot from port 1's `z0`, making the Touchstone writers work with no manual `let Rbase = 50` incantation ([E-64](#)).
- Stock NaN fixed in **donoise** noise-parameter extraction: the uncorrelated noise conductance `Gu` is analytically zero for fully-correlated single-source topologies, and floating-point rounding could land `sqrt(Ycor2 + Gu/Rn)`'s argument at $-10^{-18} \rightarrow \text{NaN}$ for the noise figure. Clamped to the physical range ≥ 0 — found by parity testing against an OSDI resistor that produced the exact textbook NF where the built-in returned NaN ([E-63](#)).

cktdisto.c (16)

- `.disto` silently reported zero distortion for OSDI devices — the distortion kernel needs higher-order Taylor coefficients the OSDI ABI cannot provide (first derivatives only), and such devices were skipped without a word. A prominent warning now names each affected OSDI device type ([E-62](#)).

4. Frontend — `src/frontend/`

plotting/pyplot.c (new) + **com_pyplot.c** (new) + **plotit.c, commands.c** (E-94)

A new interactive command, **pyplot**, plots simulated vectors with matplotlib — a Python counterpart to gnuplot. `ft_pyplot()` (`plotting/pyplot.c`) mirrors `ft_gnuplot()`: it writes a `<file>.data` table and a `<file>.py` matplotlib script and `system()`s `python3` (synchronously for a PNG, backgrounded for an interactive window). A new "pyplot" device arm in `plotit()` routes to it, so it accepts the same plot expressions as `plot/gnuplot`; the `com_pyplot()` wrapper mirrors `com_gnuplot()`, and `pyplot` is registered in both command tables. Two set variables tune it: `pyplot_terminal=png` renders headless (Agg) to a PNG, and `pyplot_python` picks the interpreter (default `python3`). Purely additive (E-94). The output file base name is optional (E-95): `com_pyplot()` treats the first word as a file name only when it is not a plot expression (no `(`, and not a vector by `vec_get()`), otherwise it defaults to `pyplot` — so `pyplot v(out)` plots directly (the command's minimum argument count was lowered from 2 to 1). `ft_pyplot()` also grew stacked subplots (set `pyplot_subplots=N` → `plt.subplots(nrows, 1, sharex=True)`, `N` traces per panel; `vs` stays the x-axis, so it is not a panel separator) and matplotlib style sheets (set `pyplot_style=<name>`, `dark` → `dark_background`, guarded) (E-98). The headless `pyplot_terminal` was extended from PNG-only to the vector export formats `svg` and `pdf` (set `pyplot_terminal=svg/pdf` → `fig.savefig(<file>.<fmt>)`, matplotlib picking the writer from the extension), and a figure size control was added (set `pyplot_figsize="W,H"` → `plt.subplots(..., figsize=(W, H))`; quote the value so ngspice keeps the comma) (E-99).

postcoms.c (414 diff lines) + **postcoms.h** + **commands.c** (16)

The Touchstone I/O subsystem (E-64, E-72):

- **wrsnp** (with `wrs2p` dispatching to the same handler): Touchstone v1 for any port count — the classic 2-port `S11 S21 S12 S22` column order preserved byte-identically, $N \geq 3$ in the spec's row-major layout with at most four complex pairs per line;
- writer options `wrsnp <file> [ri|ma|db] [s|y|z] [hz|khz|mhz|ghz]`, any combination in any order: MA/DB formats, Y/Z parameters (normalized to `Rbase`, $Y \cdot R / Z / R$, per the v1 spec), frequency units — the option line reflects every choice;
- **rdnsnp**: reads any Touchstone v1 file into a new plot with a Hz frequency scale and complex vectors matching the `.sp` plot's conventions (MA/DB converted back, Y/Z de-normalized, the 2-port column order handled, `Rbase` published so imports round-trip) — measured data diffs against simulation in one `let` expression.

Why: E-63 showed the S-parameter *analysis* was exact but its results could not leave ngspice in the industry-standard format (`wrs2p` demanded a never-created `Rbase` vector), and nothing could bring VNA data in.

outitf.c (16)

- Integer operating-point variables recorded per point: `getSpecial` masked with `IF_REAL` only, so an integer opvar saved with `.save @n1[flag]` produced garbage in transient vectors (E-32).
- The plot-memory guard's message printed `%Id` — a Windows-only printf length modifier that is undefined behavior elsewhere and rendered the message as the numberless "memory required (Id Bytes)". Now `%zu`: real byte counts on every platform (E-77).

resource.c (27)

`ft_ckptspace()` — the "approaching max data size" warning (`RSS > 95%` of `RSS` + free RAM) — now honors `set no_mem_check` (the same opt-out the fatal output-size estimate in `outitf.c` respects; one variable governs both memory guards) and warns once per excursion above the threshold, re-arming below 90%, instead of repeating on every check through a long analysis (E-81).

display.c (1)

#undef NODEV before the local macro definition — the macOS SDK's <sys/param.h> defines an unrelated NODEV ([E-77](#)).

5. Parser and device registry — **src/spicelib/**

parser/ingtok.c (10)

A **.model** card override silently dropped its first parameter when the type name and the opening parenthesis had no space between them (`modname devtype(p1=v1 ...)`): INPgetNetTok's scan did not treat (as a token boundary, so the type token swallowed the paren and the first parameter name. Found while verifying event-function counters whose model-card overrides mysteriously kept defaults ([E-8](#)).

parser/ingmod.c (5)

`find_model_parameter()` dereferenced `*(device->numModelParms)`, which is NULL for built-ins that take no model cards (VCVS, CCCS, ...) — any *referenced* `.model m vcvs()` card segfaulted, with no OSDI involved at all (an ordinary MOS instance sufficed). This was the true root of the long-documented "module named like a built-in crashes" gotcha. One NULL guard; both shapes now produce clean, located errors ([E-76](#)).

devices/dev.c (51)

- Duplicate device-type registration warned and skipped: `osdi_add_device()` appended every descriptor unconditionally, and the model-card lookup scans front-to-back — so a module name duplicated across two loaded libraries silently resolved to the *first* registration (loading an updated model library gave the stale device with no hint), and a module named like a built-in corrupted model creation. Registration now checks the table case-insensitively and skips duplicates loudly ([E-76](#)).
- **pre_osdi** path dedup: loading an already-loaded file notes it and skips — with the remedy stated: *"restart ngspice to load a recompiled file"* ([E-76](#), [E-81](#)).

osdi/osdiparam.c (E-93)

Setting a fixed (**localparam**) OSDI parameter from the netlist used to be swallowed silently: `openvaf` exports every `localparam` as a parameter, its "given" flag is forced false, and the written value is overwritten by the parameter-init default — so `.model ... N=8` on a frozen structural width parameter changed nothing, with no feedback. `OSDIparam/OSDIiParam` now test the new `PARAM_FLAG_FIXED` descriptor flag (set by `openvaf`, a free bit of the parameter `flags` field) and emit *"parameter 'N' is a fixed (localparam) value and cannot be set from the netlist; ignored"* instead of silently dropping it ([E-93](#)).

6. Maths — **src/maths/**

dense/dense.c (11 substantive lines; the file also carries a whitespace/line-ending normalization from editing)

cadjoint() had no 1×1 base case: its cofactor loop allocated 0×0 and then negative-sized minors, killing ngspice with `malloc: can't allocate -8 bytes` — the crash that had been hiding behind the "at least two ports" guard in `span.c`. The adjugate of `[a]` is `[1]` (the empty minor's determinant is 1 by convention), making `cinverse` of a 1×1 equal `1/a`; a 100 Ω load on a 50 Ω port now writes a proper `.s1p` with `S11 = 1/3` exactly ([E-64](#)).

sparse/spfactor.c (6)

The Markowitz-product overflow guards compare a double against `LARGEST_LONG_INTEGER` (= `LONG_MAX`), which is not exactly representable as a double; the conversion is now explicit — identical semantics, intentional and warning-free ([E-77](#)).

KLU/klu_multiply.c (16)

`SMPmultiply`'s KLU path passed `NULL` internal↔external ordering maps to `KLU_matrix_vector_multiply`, which dereferenced them unconditionally (`&NULL[n] = 0x14` for `n = 5`) and segfaulted — so `.option linesearch` crashed under `.option klu`. The line search is the only caller of `SMPmultiply` under KLU, so this path had never been exercised. A `NULL` map now means the identity ordering (`ext = i + 1`, since the KLU CSR is 0-based and the RHS/Solution vectors are 1-based), making the KLU matrix-vector product — and hence the [E-111](#) line-search residual merit — correct under KLU, with a merit sequence numerically identical to Sparse 1.3 ([E-112](#)).

KLU/klusmp.c (SMPcaSolve)

`SMPcaSolve` is the complex adjoint (transposed) solve used by noise and S-parameters. Its Sparse branch calls `spSolveTransposed`, but the KLU branch called the *non-transposed* `klu_z_solve` — silently wrong for any asymmetric matrix (every circuit with a transistor or controlled source), which is why `.noise` was disabled under KLU. It now calls `klu_z_tsolve` (transposed), so KLU noise matches Sparse exactly (including OSDI device models). This is the core of [E-113](#), which also removes the KLU refusal guards in `noisean.c` / `pzan.c` (single-ended pole-zero runs under KLU; balanced-output pole-zero keeps a targeted guard).

spicelib/analysis/cktsens.c

Sensitivity builds an auxiliary perturbation matrix `delta_Y` (holding $\partial Y / \partial p$) via `SMPnewMatrix`, which allocates a plain Sparse 1.3 matrix (`delta_Y->CKTkluMODE = 0`, no `SMPkluMatrix`). It is only *multiplied* against the solution (`SMPmultiply` → `spMultiply`), never factored, and `DEVbindCSC` always binds into `ckt->CKTmatrix`, not `delta_Y` — so it is correctly Sparse in every case. But two KLU-only setup blocks were gated on the main matrix's `CKTkluMODE`, so under `.option klu` they ran and dereferenced the `NULL` `delta_Y->SMPkluMatrix` — a segfault on every DC/AC `.sens` deck. The blocks now gate on `delta_Y->CKTkluMODE` (its own flag, `0`), keeping `delta_Y` Sparse under KLU exactly as it already is under the default solver, while the main `Y` matrix stays KLU. DC and AC sensitivity now match Sparse exactly ([E-114](#)).

spicelib/analysis/distoan.c

Distortion is a complex analysis (Volterra series solved at the harmonic / intermodulation frequencies via `NIIdIter` → `SMPcSolve`), but `distoan.c` had no KLU code at all: under `.option klu` the KLU matrix stayed in *real* mode, the complex solves ran against an unconverted matrix, and every harmonic came back zero — a silent wrong answer. The fix mirrors `acan.c`: before the solve loop it converts the matrix to complex (`DEVbindCSCComplex` per device + `KLUmatrixIsComplex`), and on exit converts back to real (`DEVbindCSCComplexToReal`) so a later real analysis in the same session is unaffected. KLU distortion now matches Sparse bit-for-bit (single-tone, two-tone intermodulation, and OSDI models) ([E-115](#)).

7. Build system

xspice/icm/makedefs.in (4)

The XSPICE codemodel (.cm) link rule hardcoded the pre-macOS-10.3 idiom `-bundle -flat_namespace -undefined suppress`, deprecated loudly by the modern linker on all 14 codemodel links (CI macOS builds included). Now `-bundle -undefined dynamic_lookup` — the modern spelling for plugins whose host symbols resolve at load time (E-77).

Autotools regeneration (the ~100 **Makefile.in** files + **config.h.in**)

Regenerated by `./autogen.sh` with libtool 2.5.4 during the zero-warning work — a build tree whose configure predates libtool 2.4.7 selects the deprecated darwin `-undefined suppress` flag whenever `MACOSX_DEPLOYMENT_TARGET` is unset. No hand-written content (E-77).

8. Per-enhancement index

Every enhancement that touched ngspice, oldest first:

Enhancement	ngspice files	One line
E-1	osdi.h, osdidefs.h, osdiitf.h, osdiregistry.c, osdiload.c, osdisetup.c, dctrans.c (+accept path)	absdelay(): synthetic delay rows + waveform history
E-6	osdi.h, osdidefs.h, osdiitf.h, osdiregistry.c, osdiload.c	last_crossing(): history + interpolated crossings
E-8	parser/inpgtok.c	.model card first-parameter drop fix
E-24	osditrunc.c	\$discontinuity next-step clamp
E-25	osdi callbacks (get_simparams)	expose analysis_name + simulator simparams
E-32	outitf.c	integer opvars recorded per point
E-42	osdinoise.c	coherent same-named noise grouping (LRM 4.6.4)
E-45	osdi.h (ABI 0.5), osdisetup.c	Verilog-A nodesets applied to the solver
E-51	osdi.h (ABI 0.6), osdiacld.c	full ac_stim AC-RHS injection
E-53	dctrans.c, dcopy.c, dctrans.c, acan.c, noisean.c, osdiload.c	@(final_step) + analysis-name phase bits
E-54	osdi.h (ABI 0.7), osdinoise.c, osdiload.c, osdiacld.c, osdiregistry.c	node-free complex noise factors, stride-2 pairs
E-55	osdiaccept.c (new), osdiload.c, osditrunc.c, osdiinit.c, dctrans.c, dctrans.c, osdiitf.h, Makefile.am	\$finish/\$stop/\$fatal honored; \$discontinuity step rejection
E-56	noisean.c, osdisetup.c	noise SIGABRT fix; setup-rejection diagnostics
E-62	dctrans.c, trcvdefs.h, cktdisto.c	generic .dc @inst[param] sweeps; .disto warning
E-63	span.c	donoise NaN clamp (stock defect, found by parity)
E-64	span.c, cktsdpdum.c, dense.c, postcoms.c/.h, commands.c	Touchstone export, auto-Rbase, 1-port .sp, cadjoint 1x1
E-72	postcoms.c/.h, commands.c	Touchstone round 2: MA/DB/Y/Z/units + rdsnp reader
E-76	dev.c, inpgmod.c	duplicate-registration warning, load dedup, stock .model segfault fix
E-77	osdidefs.h, display.c, outitf.c, spfactor.c, makedefs.in (+autotools regen)	zero-warning build, 33 → 0
E-80	osdiinit.c	dtemp instance-parameter alias

Enhancement	spice files	One line
E-81	resource.c, dev.c	memory-warning opt-out + once-per-excursion; reload-note hint
E-93	osdi.h, osdiparam.c	warn (not silently ignore) when a netlist sets a PARA_FLAG_FIXED (localparam) OSDI parameter
E-94	plotting/pyplot.c (new), com_pyplot.c (new), plotit.c, commands.c	new pyplot command — plot vectors with matplotlib (a Python gnuplot)
E-95	com_pyplot.c, commands.c	make the pyplot output file name optional (defaults to pyplot)
E-98	plotting/pyplot.c	pyplot stacked subplots (pyplot_subplots=N) + matplotlib style sheets (pyplot_style)
E-99	plotting/pyplot.c	pyplot vector export formats (pyplot_terminal=svg/pdf) + figure size (pyplot_figsize)
E-110	optdefs.h, tsdefs.h, cktsopt.c, cktntask.c	.option errpreset=conservative moderate liberal — one knob for a coordinated tolerance/robustness set; explicit options override regardless of order (moderate = historical defaults)
E-111	optdefs.h, tsdefs.h, cktdefs.h, cktsopt.c, cktdojob.c, cktntask.c, cktdest.c, niiter.c	.option linesearch — globalized (damped) Newton via Armijo backtracking on a new KCL-residual merit $F = G \cdot x - b$; result-neutral, off by default
E-112	maths/KLU/klu_multiply.c	KLU support for .option linesearch — SMPmultiply's KLU path passed NULL ordering maps that klu_matrix_vector_multiply dereferenced (SIGSEGV); NULL now means identity ordering. Line search verified merit-identical KLU vs Sparse
E-113	maths/KLU/klusmp.c, spicelib/analysis/noisean.c, pzan.c	KLU support for noise + single-ended pole-zero — SMPcaSolve's adjoint KLU branch used the non-transposed solve (silently wrong noise on asymmetric matrices); now klu_z_tsolve. Guards removed; balanced-output pz keeps a targeted guard
E-114	spicelib/analysis/cktsens.c	KLU support for sensitivity — the auxiliary perturbation matrix delta_Y is Sparse, but two KLU setup blocks gated on the <i>main</i> matrix's flag dereferenced its NULL SMPkluMatrix (segfault on every DC/AC .sens); now gated on delta_Y's own flag. DC/AC .sens match Sparse exactly
E-115	spicelib/analysis/distoan.c	KLU support for distortion — .disto is a complex analysis but distoan.c had no KLU code, so under KLU the matrix stayed real and every harmonic came back zero (silent wrong answer); now converts real $\leftrightarrow$ complex around the solve loop like acan.c. Matches Sparse bit-for-bit
E-116	osdi/osdisetup.c	KLU wrong-DC fix — an OSDI internal node with no Jacobian entry (a decoupled ground reference) was given an all-zero solver row that made the KLU matrix structurally singular; now tied to ground. Fixes the groundcontrib and hierbranch KLU_XFAILs

Enhancement	spice files	One line
E-117	configure.ac (+configure), spicelib/analysis/dcpss.c	Periodic steady state (PSS) productionized — built by default (was experimental —enable-pss, so .pss was unimplemented in shipped builds); ~230 lines of shooting-loop trace routed through set ngdebug (232 → 31 lines by default); fail-fast KLU guard (PSS hangs under KLU) directing .pss to .option sparse
E-118	spicelib/analysis/dcpss.c	PSS runs under KLU — the shooting loop hung under KLU (klu_refactor's reused pivots inflated the truncation error into a ~20M-step timestep explosion); forcing a full re-factor (NISHOULDREORDER) each PSS step makes KLU converge to the same result as Sparse. E-117's Sparse-only guard removed
E-119	pssdefs.h, spicelib/analysis/dcpss.c	Retain the PSS periodic operating point — PSS sampled the node voltages per period for its DFT then freed them, and never captured device states; now the voltages and CKTstate0 states are captured per sample and retained on the PSSan job (with frequency + dims) as the substrate for the periodic small-signal suite (PAC/pnoise/PXF). Self-checks that the retained samples reproduce the fundamental Periodic small-signal Jacobian harmonics — walk the retained operating point, re-linearize each sample (CKTload MODEINITSMSIG) and stamp $G+jC$ (CKTacLoad $\omega=1$), read the osc-node diagonal $\rightarrow g(t), c(t)$, DFT to harmonics. The blocks the PAC conversion matrix is built from. (Fixed a complex-mode-not-set bug where $C(t)$ accumulated across samples.) Verified: RC gives $G=1/R1$, $C=C1$, no harmonics
E-120	spicelib/analysis/dcpss.c	Periodic small-signal Jacobian harmonics — walk the retained operating point, re-linearize each sample (CKTload MODEINITSMSIG) and stamp $G+jC$ (CKTacLoad $\omega=1$), read the osc-node diagonal $\rightarrow g(t), c(t)$, DFT to harmonics. The blocks the PAC conversion matrix is built from. (Fixed a complex-mode-not-set bug where $C(t)$ accumulated across samples.) Verified: RC gives $G=1/R1$, $C=C1$, no harmonics
E-121	spicelib/analysis/dcpss.c	PAC conversion-matrix engine — extend E-120 from the osc diagonal to every matrix nonzero, complex-DFT to harmonics G_k, C_k , assemble the $(2M+1)N$ harmonic conversion matrix $H_{\{nm\}}=G_{\{n-m\}}+j\omega_m \cdot C_{\{n-m\}}$, inject a unit current at the osc node in sideband 0 and solve by dense complex LU (pss_solve), report the sideband conversion gains. The numerical heart of PAC/pnoise/PXF. Verified: linear RC gives sideband-0 = AC driving-point ‘

Enhancement	ngspice files	One line
E-122	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	.pac command (periodic AC) — the user-facing analysis on the E-121 engine. .pac Fguess StabTime OscNode Points Harmonics SC_iter Steady_coeff <dec oct lin> Npts Fstart Fstop runs PSS then sweeps the input frequency, solving the conversion matrix at each point and emitting the 0-th-sideband node responses as a complex PAC Analysis plot (print/plot/wrdata). Reuses the PSS analysis via a PSSdoPAC flag; engine factored into pac_extract_harmonics (once) + pac_solve_at (per freq). Verified: swept sideband-0 $ b(f) == \text{analytic AC driving-point } Z(f) $ to $1.6e-7$ across 10 kHz–1 MHz
E-123	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	finish .pac — (1) source-referenced stimulus: capture the netlist AC-source RHS from CKTacLoad as the sideband-0 stimulus B_0 (a periodic-AC transfer/conversion gain), unit-current-at-osc-node fallback; (2) multi-sideband output: optional trailing maxsideband Ksb emits every conversion sideband $f_{in+k \cdot f_0}$ ($k=-Ksb..Ksb$) as its own vector — sideband 0 keeps the node name, others <node>_usb<k>/<node>_lsb<k> via IFnewUid. Verified: RC with V1 AC 1 gives sideband-0 = low-pass transfer $1/\sqrt{1+(2\pi fRC)^2}$ ($0.998 \rightarrow 0.157$) with b_usb1/b_lsb1 ~0 (no conversion)
E-124	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	.pnoise command (periodic noise) — fold each device's noise through the conversion matrix. pac_solve_adjoint solves $H^T \Psi = e_{\{out,0\}}$; pnoise_sweep loads the sideband-k adjoint into CKTrhs/CKTirhs and calls the existing device noise routines (NevalSrc, OSDI load_noise) once per sideband, accumulating $\Sigma_k S \cdot \Delta \Psi_k ^2$ — reuses every device noise model via a minimal local NOISEAN context. .pnoise <pss> OutNode InSrc <dec oct lin> Np Fstart Fstop; emits onoise_spectrum/inoise_spectrum. Verified: linear RC reduces exactly to .noise $(4kTR/(1+(2\pi fRC)^2))$, matches the .noise reference to every digit)

Enhancement	ngspice files	One line
E-125	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	.pxf command (periodic transfer function) — the adjoint of PAC, completing the PSS→PAC→Pnoise→PXF suite. pxf_sweep solves $H^T \Psi = e_{\{out,0\}}$ per frequency and dots each sideband block with the AC-source pattern $B0 \rightarrow xf_k = \sum_j \Psi_k(j) \cdot B0(j)$, the input→output transfer at each sideband. .pxf <pss> OutNode <dec oct lin> Np Fstart Fstop [maxsb]; emits $xf + xf_{usb<k>}/xf_{lsb<k>}$. Verified: by the identity $(H^{-1}B)_{out} = (H^{-T}e_{out})^T B$ the sideband-0 transfer is bit-identical to the PAC response (0.998→0.157 low-pass), conversion sidebands ~2e-16
E-126	include/ngspice/pssdefs.h, spicelib/analysis/psssetp.c, spicelib/parser/inp2dot.c, spicelib/analysis/dcpss.c	cyclostationary noise — .pnoise ... cyclo evaluates each device's noise PSD $S(t)$ at every PSS sample's bias (CKTload per sample) and folds it through the time-domain adjoint transfer $A_s(j) = \sum_k \Psi_k(j) e^{j2\pi k s/P}$, averaging: $onoise(f) = (1/P) \sum_s S(t_s) \cdot \Delta A_s ^2$. Reuses the device noise routines. Verified: (1) reduces exactly to .noise on the linear RC (bias-independent thermal → Parseval); (2) a flicker resistor carrying the RC current gives $onoise \cdot f = R1^2 \cdot KF \cdot \langle I^2 \rangle = 4.88e-10$ (uses the period-average $\langle I^2 \rangle$, matched to 5 digits)
E-127	include/ngspice/{optdefs,tskdefs,cktdefs}, spicelib/analysis/{cktsopt,cktntask,cktdo}, maths/ni/niiter.c	pseudo-transient continuation — .option ptcont in the CKTop cascade, a backward-Euler pseudo-transient $f(x) + Gps \cdot (x - x_{prev}) = 0$ and marches Δt small→large ($Gps \rightarrow 0$). Gps diagonal via the gmin path; the $Gps \cdot x_{prev}$ RHS coupling (added in NIiter) makes each step a stable-trajectory move, not a static gmin step. New pseudo_transient in the CKTop cascade, off by default. Verified under KLU+Sparse: result-neutral on normal circuits; on a stiff no-limiting exp, reaches the correct DC 0.837922 V where plain Newton lands on a spurious 70.5 V (21/21)

Enhancement	ngspice files	One line
E-128	include/ngspice/{optdefs,tskdefs,cktdefs} spicelib/analysis/{cktsopt,cktnntask,cktdojob} spicelib/analysis/dctran.c	LTE-based dynamic integration-order control — dynorder selects the Gear order per step from the local-truncation-error limit instead of the stock 1↔2 toggle, so orders 3–6 (already coded in NIcomCof but never used) are actually exercised. The selector compares the raw LTE-limited step (uncapped CKTtrunc) at the current order and its ±1 neighbours and moves with hysteresis (1.2×), a settling hold after each change (let the BDF divided differences rebuild), and an order-dependent step-growth cap (2× at order ≤3 → 1.3× at 6). Off by default; bounded by maxord; inert at the default maxord=2. Stiff-transient guards (post-breakpoint order hold + leaky-bucket rejection-rate order drop) keep it from collapsing the step on a violent slew. Verified under KLU+Sparse: RC decay 3–5× fewer steps at matched accuracy with monotone error; smooth RLC ringdown 8.9× fewer steps AND more accurate (0.13 % vs 0.34 %); nonlinear rectifier matches stock to 5 sig figs; the transistor-level μA741 ±5 V slew completes under dynorder and matches fixed Gear-2
E-129	frontend/outitf.c	sweep progress bar — the throttled Reference value status line (redrawn in place every 0.25 s during a sweep) now carries a live progress bar + percentage, e.g. Reference value : 5.91926e-04 [=====] 74%. outp_progress_frac() computes the 0–1 fraction per analysis: transient from (CKTtime-TSTART)/(TSTOP-TSTART), AC/noise from the frequency's linear/log position in the band, DC from the accepted-point count over the nested step-count product; analyses with no span (op, ...) — keep the plain line. Fixed-width (no stale chars), stdout status-line only (never in the rawfile/wrdata), same !ft_norefprint && !cp_background gating. Verified 22/22: printed % matches the analytic sweep fraction to 0.5 % across tran/AC/DC/noise; op shows no bar

Enhancement	ngspice files	One line
E-130	frontend/com_optimize.{c,h}, commands.c, options.c, include/ngspice/ftext.h, spicelib/analysis/cktdojob.c, frontend/outitf.c	built-in Nelder-Mead optimizer — optimize -param <name> <init> <lo> <hi> [-param ...] -analysis <cmd> -minimize <expr> [-maxiter N] [-tol T] [-verbose] varies device/alter parameters, re-runs an analysis, and minimizes a scalar objective expression via a derivative-free downhill simplex in normalized [0,1] space (scale-invariant across orders-of-magnitude params). Sub-commands dispatched synchronously through cp_coms (not the deferring re-entrant cp_evloop); the hundreds of inner analyses are silenced via a new ft_optimizing flag gating the banner/row-count/E-129 progress bar at source (-verbose to show). Verified 9/9 against analytic optima: DC divider R1→2333.3 Ω, AC low-pass R1→2756.6 Ω, 2-D compound objective R1=3k/R2=2k exactly
E-131	frontend/com_checkpoint.{c,h}, commands.c, com_commands.h, Makefile.am, spicelib/analysis/dctran.c, include/ngspice/cktdefs.h	transient checkpoint / restart — new savestate <file> / loadstate <file> commands serialize the full transient integration state (solution vector CKTrhs0ld, device state history CKTstates[] , time/step/order/mode, pending breakpoints) to a binary file and resume it, including in a fresh process — so a long run survives a crash, splits across sessions, or moves between machines (stock ngspice could only resume in memory). DcTran() gains a CKTcheckpoint-gated branch that opens a fresh output plot (no live plot to 666-relink across a reload), initializes the XSPICE breakpoint markers, and fixes up the breakpoint list before jumping into the stepping loop; the rhs length is keyed off SMPmatSize+1 (not CKTmaxEqNum). A stored signature rejects a mismatched circuit; Sparse-solver only (KLU rejected with a clear message). Verified 19/19: resumed waveform bit-identical to an uninterrupted run for RC-step/pulse/diode built-ins and ~2e-7 for a compiled OSDI diode, across a separate process

Enhancement	ngspice files	One line
E-132	spicelib/analysis/dcpss.c, spicelib/parser/inp2dot.c, spicelib/analysis/psssetp.c, include/ngspice/pssdefs.h	periodic S-parameters (.psp) — small-signal scattering parameters around a PSS operating point, including conversion between the input frequency and its sidebands $f_{in}+k \cdot f_0$ (mixers / switched circuits, where a static-DC .sp cannot see the conversion). Sits on the PSS→conversion-matrix suite (E-117–126): after PSS, psp_sweep excites each RF port (portnum/z0, the .sp framework) by driving its branch source (V=1, like .sp's VSRCspupdate) through the shared (2M+1)N conversion matrix, reads per-sideband port waves in the same Kurosawa power-wave convention, and forms $S^{(k)}=B^{(k)} \cdot A^{-1}$ (dense-complex cinverse/cmultiply). pac_solve_at's matrix assembly factored into a reusable pac_build_matrix; PSSdoPSP flag + psp PSS param + dot_psp card. Because $S=B \cdot A^{-1}$ is excitation-basis-invariant, sideband 0 reduces exactly to .sp for a time-invariant network. Runs under both linear solvers (the conversion matrix is a standalone dense LU; PSS runs under both since E-118). Verified 8/8: sideband-0 matches .sp to ~1e-16 for 1/2/3-port resistive + reactive networks (magnitude and phase) incl. OSDI Verilog-A devices (G + reactive ddt stamps), conversion sidebands correctly ~0
E-133	frontend/com_qpss.{c,h}, commands.c, com_commands.h, Makefile.am	quasi-periodic (two-tone) steady state (qpss) — qpss <expr> <f1> <f2> [periods] [maxorder] computes the two-tone steady-state spectrum: every mixing product $k_1 \cdot f_1 + k_2 \cdot f_2$ including third-order intermodulation (IM3 at $2f_1 - f_2$ / $2f_2 - f_1$) that single-tone AC/PSS cannot show. For commensurate tones (common beat $f_b = \gcd(f_1, f_2)$) it runs an ordinary transient over a few beat periods to reach steady state, then evaluates the Fourier coefficient directly at each exact intermod frequency (a direct DFT, exact — no FFT-bin rounding) and labels it by the 2-D index (k1, k2). Deliberately not a slow beat-frequency shooting PSS; a front-end command driving a transient, so solver-independent and works with built-in and OSDI devices. Verified 11/11: analytic fundamentals/IM3/3f of a cubic, no even-order products, the 3:1 IP3 slope law (fund ×2, IM3 ×8 per 2× drive), beat-frequency derivation, and an OSDI cubic matching the built-in

Enhancement	ngspice files	One line
E-134	spicelib/analysis/dcpss.c, frontend/com_hb.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h	Harmonic Balance (hb <f0> <K>) — solves the periodic steady state in the frequency domain by Newton (each node a truncated Fourier series), instead of integrating in time; the real analysis behind ngspice's unimplemented WITH_HB stub. Residual $F_k = I_{R,k}(V) + [dq/dt]_k - I_{s,k} = 0$ with the E-121 $(2K+1)N$ conversion matrix as the exact Jacobian. Per iteration: inverse-DFT $V \rightarrow v(t_s)$; drive DC+AC device loads at those voltages for the resistive current $I_R = G*v - b$ (companion b saved before acLoad, so it's the ACTUAL current not the tangent $G*v$), and $G(t)/C(t)$; DFT; dense complex Newton (pss_csolve). Nonlinear reactive with NO charge extraction: $dq/dt = C(v)*v'$, so the reactive current is the conversion matrix's jwC term applied to V . Solver-independent (KLU + Sparse): the dense complex Newton is HB's own; the sparse solver only <i>reads</i> $G(t)/C(t)$ off the device matrix, so hb_extract carries the same <code>#ifdef KLU</code> complex-CSC binding (<code>DEVbindCSCComplex</code>) as the PAC extraction, and com_hb copies the task's KLU mode before building so a bare hb honours <code>.option klu</code> — verified bit-identical under both. Built-in + OSDI. Verified 8/8 vs transient/fourier, quadratic convergence: nonlinear R (analytic 3rd harmonic), R+C, a real diode rectifier (junction limiting), OSDI varactor Q(v) 2nd harmonic, KLU==Sparse parity HB source-stepping continuation — makes E-134
E-135	spicelib/analysis/dcpss.c, examples/hb_examples/verify_hb.py	Harmonic Balance robust on strongly-driven circuits where a cold full-strength Newton diverges ($ F \rightarrow 1e69$). HBanalyze's Newton loop is wrapped in an adaptive homotopy: every independent source scaled by λ : $0 \rightarrow 1$, each level warm-started from the last converged V . The residual becomes $F = I_R + I_C - \lambda \cdot I_s$; on level success V is checkpointed and $d\lambda$ grows ($\times 1.7$), on failure (Newton exhausted, residual non-finite, or singular Jacobian) V is restored and $d\lambda$ halves; $d\lambda < 1e-5 \rightarrow$ reported as no reachable steady state. First level is full strength ($d\lambda=1$) so easy circuits converge at $\lambda=1$ immediately, bit-identical to the plain solve. Automatic (no new syntax); set <code>hb_verbose</code> shows the λ ramp, summary reports iterations + continuation steps. Verified 9/9: a strongly-driven diode rectifier (5 V into 20 Ω , sharp $I_S=1e-14$) diverges cold but converges in 3 continuation steps, matching transient fourier to $<0.1\%$ for DC/f0/2f0; the 8 existing HB checks stay bit-identical

Enhancement	ngspice files	One line
E-136	spicelib/analysis/dcpss.c, frontend/com_qpss.c, frontend/commands.c, include/ngspice/cktdefs.h, exam- ples/qpss_examples/verify_qpss_hb.py	two-tone Harmonic Balance (qpss <expr> <f1> <f2> hb [K1] [K2]) — the TRUE, incommensurate-capable quasi-periodic steady state, a frequency-domain HB engine alongside the E-133 transient qpss (which is unchanged, commensurate-only). Each node is a 2-D Fourier series $v(t) = \sum \sum V_{\{k1,k2\}} e^{j(k1\omega_1+k2\omega_2)t}$; QPSShb samples devices on a 2-D phase grid (θ_1, θ_2) — time never appears, so incommensurate tones (no beat period) just work — and 2-D DFTs to the conversion matrix $H_{\{(n),(m)\}} = G_{\{n-m\}} + j\omega_m \cdot C_{\{n-m\}}$ (qp_build_matrix), Newton-solved by pss_csolve with the E-135 source stepping. Sources captured by an oversampled least-squares APFT ($\Gamma^H \Gamma$) $I_s =$ $\Gamma^H b$ (a square Vandermonde is catastrophically ill-conditioned past a few harmonics). Reactive needs NO charge extraction ($dq/dt = C(v)v'$); the converged operating point is retained (qpss_hb_saved) for qpac (E-137). Solver-independent (KLU + Sparse) — same #ifdef KLU complex-CSC binding as PAC/HB. Built-in + OSDI. Verified 7/7: analytic cubic $ IM3(2, -1) / 3rd(3, 0) = 3$, even products ~0, 3:1 IP3 slope, incommensurate 2 tones (E-133 cannot), HB==transient (commensurate), KLU==Sparse; E-133 verify_qpss.py stays 11/11
E-137	spicelib/analysis/dcpss.c, frontend/com_qpac.{c,h}, commands.c, com_commands.h, Makefile.am, include/ngspice/cktdefs.h, exam- ples/qpss_examples/verify_qpac.py	two-tone small-signal QPAC (qpac <f_in>) — completes the quasi-periodic gap: the two-tone analogue of PAC. Run after qpss ... hb, QPACanalyze injects a small signal at f_in around the retained QPSS operating point (qpss_hb_saved) and reports the response at every sideband $f_{in} + k1 \cdot f1 + k2 \cdot f2$, mixing it through the SAME 2-D conversion matrix $H_{\{(n),(m)\}} = G_{\{n-m\}} + j\omega_m \cdot C_{\{n-m\}}$ (qp_build_matrix at f_in) that the QPSS Newton used as its Jacobian. Stimulus placed in the ($0, 0$) sideband — a netlist AC-source RHS B0 (captured bias-independent at the op-point) or a unit-current fallback — one dense pss_csolve. Adds no device evaluation → solver-independent (KLU + Sparse) by construction. Verified 7/7: reduce-to-AC (pump→0 $\Rightarrow$ direct ($0, 0$) = plain .ac response = R, sidebands vanish), v^2 -pump conversion ratio $ (1, 1) / (2, 0) = 2$, equal-tone symmetry, clean no-op-point error, KLU==Sparse; E-136 (7/7) + E-133 (11/11) unaffected

(E-25's simparam exposure lives in the OSDI callback table populated at load time; its diff rides inside the

osdload.c/callbacks changes.)

Build-warning cleanup (post-E-127): a full rebuild under the repo's `-Wconversion` flags surfaced latent warnings. `configure.ac` had `-s` (a strip flag) in the compile `CFLAGS`, so clang warned "argument unused during compilation: '-s'" on every source file (~1526 warnings) — removed (binaries are stripped separately by the fold and CI). `-Wconversion` also flagged a real latent bug in `maths/ni/nipzmeth.c` (`b = 0.0` was an assignment where `b == 0.0` was intended) — fixed — and benign `double→bool` conversions in `maths/cmaths/cmath4.c` — made explicit. Full-build warnings dropped 1903 → 394; the remainder are `-Wconversion` warnings in third-party SuiteSparse (KLU) and CMC device models (HiSIM), which are left to their upstream sources.

Every entry above is guarded by a verify script under [examples/](#) and was regression-checked against the full example arsenal, the compiler's integration suite, and the VA_TEST industry-model corpus at the time it landed.