Here's the table again with each field's byte offset in the 512-byte IDENTIFY buffer. Word n starts at offset 2n. In your captures the BIOS buffer began at 0x101D_3120, so add that base to get a memory address: word 49, for example, was at 0x101D_3182.

Word	Offset	Field	Notes
0	0x000	General configuration	`848Ah` is the CompactFlash signature; many cards report `044Ah` instead (your good and bad cards). Bit 15 = 0 means ATA; bit 7 = removable; bit 6 = fixed.
1	0x002	Default cylinders	CHS geometry
2	0x004	Specific configuration	ATA-5 and later; usually 0 on CF
3	0x006	Default heads	
4-5	0x008-0x00B	Obsolete	unformatted bytes per track and per sector
6	0x00C	Default sectors per track	
7-8	0x00E-0x011	Sectors on the card	CF only; word 7 is the high word
9	0x012	Retired	
10-19	0x014-0x027	Serial number	20 ASCII characters, space-padded
20-22	0x028-0x02D	Retired	buffer type, buffer size, ECC bytes; often filled in on CF
23-26	0x02E-0x035	Firmware revision	8 ASCII characters
27-46	0x036-0x05D	Model number	40 ASCII characters
47	0x05E	READ/WRITE MULTIPLE limit	bits 7-0 = maximum sectors per block; bits 15-8 = `80h`
48	0x060	Reserved	ATA-1: 32-bit I/O; CF: 0
49	0x062	Capabilities	bit 11 = IORDY supported, bit 10 = IORDY can be disabled, bit 9 = LBA, bit 8 = DMA
50	0x064	Capabilities 2	bit 14 = 1 when valid
51	0x066	PIO mode	bits 15-8 = PIO mode 0-2

Word	Offset	Field	Notes
52	0x068	Single-word DMA mode	obsolete
53	0x06A	Which fields are valid	bit 0: words 54-58, bit 1: words 64-70, bit 2: word 88
54-56	0x06C-0x071	Current cylinders, heads, sectors per track	
57-58	0x072-0x075	Current CHS capacity in sectors	
59	0x076	Current multiple setting	bit 8 = valid; bits 7-0 = sectors per block now set
60-61	0x078-0x07B	LBA capacity in sectors	28-bit
62	0x07C	Single-word DMA	obsolete
63	0x07E	Multiword DMA	bits 2-0 = modes supported, bits 10-8 = mode selected
64	0x080	Advanced PIO modes	bit 0 = PIO 3, bit 1 = PIO 4
65-66	0x082-0x085	Multiword DMA cycle time	minimum and recommended, in ns
67	0x086	Minimum PIO cycle without IORDY	ns
68	0x088	Minimum PIO cycle with IORDY	ns
69-79	0x08A-0x09F	Reserved	queue depth in word 75 (0x096)
80	0x0A0	Major version	bit n set = supports ATA-n
81	0x0A2	Minor version	
82	0x0A4	Command sets supported	bit 0 = SMART, 1 = security, 3 = power management, 5 = write cache, 6 = look-ahead, 12 = WRITE BUFFER, 13 = READ BUFFER, 14 = NOP
83	0x0A6	Command sets supported, continued	bit 2 = CFA feature set, 3 = advanced power management, 10 = 48-bit LBA, 12 = FLUSH CACHE, 13 = FLUSH CACHE EXT; bits 15-14 = `01` when valid

Word	Offset	Field	Notes
84	0x0A8	Command sets supported, more	bits 15-14 = `01` when valid
85-87	0x0AA-0x0AF	Command sets enabled	same bits as words 82-84; word 85 bit 5 = write cache on
88	0x0B0	Ultra DMA	bits 6-0 = modes supported, bits 14-8 = mode selected
89-90	0x0B2-0x0B5	Security erase times	
91-94	0x0B6-0x0BD	Power, password, reset and acoustic values	91 = power level, 92 = master password revision, 93 = hardware reset result, 94 = acoustic level
100-103	0x0C8-0x0CF	48-bit LBA capacity	
128	0x100	Security status	
129-159	0x102-0x13F	Vendor specific	
160	0x140	CFA power mode 1	bit 15 = word valid; bits 11-0 = maximum current in mA
161-175	0x142-0x15F	Reserved for the CompactFlash Association	words 163-164 (0x146-0x149) report CF-only faster modes, which Roscoe can't use
176-205	0x160-0x19B	Media serial number	ATA-7
255	0x1FE	Integrity word	low byte `A5h` if present; then all 512 bytes add up to 0 (mod 256)

These offsets match a buffer stored exactly as read from the Data register. Your BIOS stores IDENTIFY byte-swapped, as it does sector data, so in its buffer each word's two bytes are reversed (`848Ah` sits at 0x000 as `8A 84`). The offsets themselves don't change.