

Open Mower

Hardware v2

Inhaltsverzeichnis

Setting up the new Hardware..... 1

 What to buy.....1

 Prepare SD-Card..... 1

 Put the Boards together.....1

 Make it work..... 1

Prepare your existing Hardware for Open Mower..... 1

 Worx Landroid SO500i (WR105SI)..... 1

1. Setting up the new Hardware

1.1 What to buy

1. Universal Board, 3x ESC, xCore Board
2. Raspberry Pi Compute Module 4 Lite, BCM2711, ARM Cortex-A72, 4GB-RAM
<https://de.farnell.com/raspberry-pi/cm4004000/rpi-compute-module-4-lite-4gb/dp/3678901>

1.2 Prepare SD-Card

1. Download image (<https://github.com/ClemensElflein/OpenMowerOS/actions/runs/17615522586>)
2. Flash image to SD-Card with imager with user- and wifi-settings (ReadMe
<https://github.com/ClemensElflein/OpenMowerOS/blob/v2-rework/README.md>)

1.3 Put the Boards together

1. Put RPi CM4 on xCode Module (image)
2. Add Distanceholder between RPi, xCode Module and Universal Board (smaller distance is between RPi and xCode module, image)
3. Insert SD-Card (into xCode Module or RPi?, image)
4. Insert xCode Module into Universal Board (image)
5. Add USB-Wifi Dongle for Network Access
5. Add screws to Distanceholder (optional, only do this if everything works, image)

1.4 Make it work

1. Power up the mower (Where? Values?)
2. Setup docker environment for your mower at "http://openmower:5001" (see readme)
3. Setup openmower at "http://openmower:8080"

2. Prepare your existing Hardware for Open Mower

2.1 Worx Landroid SO500i (WR105SI)



1. Open the Lid (Orange Cover, no screws)



2. Remove Blade Disc (3 screws, Type 1)




3. Remove Blade Cover (3 screws, Type 2)

4. Remove Top (8 screws, Type 3)



1. Unplug Cables (7. Power Supply (Battery and external), 8. Top Button and LED)
5. Remove Electronics (3 screws, Type 2)



1. Unplug remaining Cables

1. Motor Left
2. Motor Right
3. Motor Blade
4. Boundary, Lift and ???
5. Power Switch, Rain Sensor, USB Port
6. Acoustic Signal

