SPECIFICATIONS

MCU	Arduino Nano
DISPLAY	0.96" Dual-Color OLED
AUDIO	3.5mm jack, clip-on lavalier
POWER	9V USB-C Rechargeable Lithium
BATTERY GAUGE	% on every screen, ~16 hr runtime
POWER BTN	Latching, Blue-Lit, Guarded
MEMORY	60 Shots / last string saved
RESOLUTION	0.01 s display, 0.10 s min split
START DELAY	Random, 3–8 s
ENCLOSURE	PLA+ 3D Printed
FIRMWARE	Open Source v1.7.5
SOURCE	github.com/jfkure/shot-timer-mk1
LICENSE	GPL-3.0 · CERN-OHL-S · CC BY-SA
PRICE	$75.00 USD

ORDER: **order@huckleberryinnovations.com**
HUCKLEBERRY INNOVATIONS — LEXINGTON, SC

SHOT TIMER MK1

HUCKLEBERRY INNOVATIONS
OPERATOR QUICK-START

HI



START SCREEN · v1.7.5

LEXINGTON, SC
J.F. KURE
v1.7.5

SHOT TIMER MK1 — OPERATOR REFERENCE

00 // POWER

A	**POWER**	Glows blue — timer ON, battery % top right
B	**POWER**	Depress — timer OFF, no battery drain

* Recessed guard prevents accidental presses

01 // RUN A STRING


1	TAP START	LED on — random 3–8 s wait
2	BUZZER · GO!	LED blinks — shoot, shots timed
3	PRESS STOP	LED off — string saved, results up

Keep START a quick tap; holding 2 s opens test mode. Up to 60 shots. A pause over 65.5 s shows as 65.53+.


02 // REVIEW RESULTS

1ST SHOT › AVERAGE › SPLITS › TOTALS › BATTERY

Tap STOP to step through pages; times in seconds. At power-on, tap STOP for your **last string**.



1ST SHOT · draw time



SPLITS · 3 per page

03 // BATTERY

Charge until the battery light turns **green**, then mark it full:

1	TAP STOP	Go to the BATTERY page
2	HOLD START 3s	MARK FULL? appears
3	TAP STOP	FULL — gauge set to 100%

LOW	15% left (~2 hr) — beep every 60 s
CHARGE	5% left (~45 min) — double beep every 30 s

Rechargeable 9V lithium only. No beeps while shooting.

04 // SETUP

A	HOLD STOP 2s	Sensitivity: START +10, STOP saves
B	HOLD START 2s	Test mode: live mic level, STOP exits
C	HOLD BOTH 3s	Factory reset (threshold back to 150)

TIP Threshold 150 suits most ranges. Extra shots counted? Raise it. Shots missed? Lower it.

WHITE LED

●	**SOLID**	Waiting for the beep · test & setup screens
~	**BLINK**	Clock running, listening for shots
○	**OFF**	String stopped · reviewing results

● START ○ STOP ⦿ POWER (lit when on)