



JTECH ENGINEERING

PANEL MAKER - AUTOMATION - GENERAL TRADING

PT.JIDOUKA TEKNOLOGI INDONESIA

JABODETABEK :

Perum Graha Persada Jl. Persada 7 No 26 ,Cibitung
Kab. Bekasi Jawa Barat 1724

Phone : 087870386649

NPWP : 042.673.277.2-427.000

EMAIL : marketing@jtech-engineer.com

WEB : www.jtech-engineer.com

TEST REPORT

Customer	PT. XD SAKTI INDONESIA	No Doc	JTI-2602-005 /2024SK023 TEST REPORT
Project Name	PENGADAAN TRAFO DAYA 150/22KV UNTUK GITET SOREK	Job Order	PO.25.0337.ITEM
Panel Name	CONTROL CABINET 150/22kv 60MVA TRANSFORMER	Date	FEBRUARI 2026

1. VISUAL CHECKLIST

NO	DESKRIPSI	CHECK
1	Periksa tata letak komponen yang terpasang sesuai dengan desain gambar	✓
2	Periksa dimensi komponen dan grounding masing – masing komponen harus terkoneksi pada busbar	✓
3	Periksa dan pastikan merek dan model sesuai dengan list komponen pada desain gambar	✓
4	Periksa dan pastikan kekencangan koneksi setiap wiring harus kencang dan dilakukan marking pada komponen yang telah dicek	✓
5	Periksa marking komponen,label komponen dal label phasa harus sesuai dengan desain gambar	✓

2. INDIVIDUAL CHECKLIST

NO	QTY	MARK	EQUIPMENT	MANUFACTURER	TYPE	TECHNICAL DATA	FITTING	LABEL	FUCTION TEST
1	1	QF1	CIRCUIT BREAKER FOR MAIN SUPPLY	SCHNEIDER (MG)	iC-60H + Aux Contact	400V AC 3Ø 50Hz 63A	✓	✓	✓
2	1	ST1	PHASE CONTROL RELAY	SCHNEIDER	RM17TE00	183..528 V AC, 1 C/O, Sett Min = 300 Max=45	✓	✓	✓
3	1	ST2	VOLTAGE DROP RELAY	SCHNEIDER	RM22UB34	80V ADC, 2C/O 8A	✓	✓	✓

4	1	QF2	CIRCUIT BREAKER FOR DC MAIN SUPPLY	SCHNEIDER	iC-60H + Aux Contact	110V DC 50 Hz 40A	✓	✓	✓
5	1	QF3	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	230V AC 2Ø 50Hz 10A	✓	✓	✓
6	3	QF4, QF6, QF7	CIRCUIT BREAKER	SCHNEIDER	C60HDC + Aux Contact	110V DC 2Ø 10A	✓	✓	✓
7	1	QF8	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	230V AC 2Ø 50Hz 2A	✓	✓	✓
8	1	QF9	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	230V AC 2Ø 50Hz 6A	✓	✓	✓
9	1	QF12	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	230V AC 2Ø 50Hz 4A	✓	✓	✓
10	2	QF13, QF140	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	230V AC 2Ø 50Hz 16A	✓	✓	✓
11	1	QF5	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	400V AC 3Ø 50Hz 20A	✓	✓	✓
12	3	1QF ~ 3QF	CIRCUIT BREAKER	SCHNEIDER	iC-60N + Aux Contact	230V AC 3Ø 50Hz 6A	✓	✓	✓
13	3	1KM ~ 3KM	CONTACTOR 3 POLE	SCHNEIDER	LC1-D09 FD	3P, AC-3 9A, Coil: 110 V DC	✓	✓	✓
14	3	1RJ ~ 3RJ	THERMAL RELAY	SCHNEIDER	LRD-07	ADJ. 1,60- 2,50 A, SETTING 2,1A	✓	✓	✓
15	1	CZ	STOP KONTAK	HAGER / EQUAL	SCHUKO	1PH 10/16A	✓	✓	✓

16	1	EH	HEATER	SUNGHO	CONHEAT	230V AC, 50 HZ, 100W	✓	✓	✓
17	1	WS	THERMOSTAT FOR HEATER	SCHNEIDER	NSYCCOTH	0~60'C 1NO/NC	✓	✓	✓
18	1	CK1	LIMIT SWITCH	OMRON	Z - Series	-	✓	✓	✓
19	1	EL	PANEL ILLUMINATION	LOCAL	LED	4 WATT, 230 VAC	✓	✓	✓
20	1	PS1	POWER SUPPLY	MEAN WELL	NDR-120-24	220 VAC TO 24 VDC 10A	✓	✓	✓
21	6	KX11~KX1 3, KX21~KX2 3	MINIATURE RELAY	SCHNEIDER	RXM4	110 VDC, 4CO	✓	✓	✓
22	1	KT	WEEKLY TIME RELAY	FORT/EQUAL	-	230V AC	✓	✓	✓
23	1	S01	SELECTOR SWITCH	K & N	CA10-A221-600	POSITION, LOCAL - REMOTE, 2 POLE	✓	✓	✓
24	2	S02, S03	SELECTOR SWITCH	K & N	CA10-A211-600	POSITION, AUTO - OFF - MANUAL, 2 POLE	✓	✓	✓
25	2	S10, S11	MULTI STEP SELECTOR SWITCH	K & N	CA10-A230-600	POSITION, 1 - 2 - 3, 1 POLE	✓	✓	✓
26	40	X2.2, X4	TERMINAL BLOCK	PHOENIX / EQUAL	UK6N	Screw TYPE	✓	✓	✓
27	10	X3	TERMINAL BLOCK	PHOENIX / EQUAL	URTK/S	Screw Type	✓	✓	✓

28	260	X1, X2.1, X2.3 ~ X2.7	TERMINAL BLOCK	PHOENIX / EQUAL	UK5-MTK-P/P	PIN-KNIFE TYPE	✓	✓	✓
29	15	X5	TERMINAL BLOCK	PHOENIX / EQUAL	UIK-35	Screw Type	✓	✓	✓
30	2	DTC-48	DUCTING CABLE	PUMA	PERFORATED	48x100 mm	✓	✓	✓
31	4	DTC-70	DUCTING CABLE	PUMA	PERFORATED	70x100 mm	✓	✓	✓
32	4	DTC-100	DUCTING CABLE	PUMA	PERFORATED	100x100 mm	✓	✓	✓
33	1	PB	PUSH BUTTON	SCHNEIDER	XB5AL73415	-	✓	✓	✓
34	4	KA1~KA4	CONTACTOR RELAY	SCHNEIDER	CA3KN31 FD	3NO 1NC, Coil 110V DC	✓	✓	✓
35	1	NYAF	INTERNAL CABLE	LOCAL/IMPORT	-	Ø1.5, Ø2.5, Ø4	✓	✓	✓
36	1	LIYCY	INTERNAL CABLE	LOCAL/IMPORT	-	0.5	✓	✓	✓
37	2	M10, M11	AMPERE METER	HELES/EQUAL	CR-45	0-5 A, Cls 2,5	✓	✓	✓

	Company	Name	Signature
Check By	PT. JIDOUKA TEKNOLOGI INDONESIA	Syurya Abiddin	

