

mlxphyburn – Burning Tool for Externally Managed PHY

Mlxphyburn tool allows the user to burn firmware of an externally managed PHY. The tool burns and verifies a pre-compiled binary PHY firmware image on the PHY’s flash. It is supported only on Linux.

Tool Requirements

- ConnectX-3/ConnectX-3 Pro with an externally managed PHY
- A device that has access to the PHY flash module
- MLNX_OFED driver (if installed) must be down
- Access to the device through the PCI interface (pciconf/pci_cr)
- Firmware version that supports access to an externally managed PHY
 - Version 2_33_5000 and above

mlxphyburn Synopsis

```
1 # mlxphyburn [-d <device>] [-i Phy_fw_image] b[urn]|q[uery]
```

where:



-d --dev <device>	Device which has access to the PHY.
-i --img <PHY_fw_image>	PHY firmware image.
-v --version	Display version info.
-h --help	Display help message.
b[urn]	Burn given PHY image on the device's PHY.
q[uery]	Query PHY FW on device.

If no device is specified, mlxphyburn will attempt to burn the PHY firmware image on all mst devices on the machine.

Examples of mlxphyburn Usage

Burn Example

```
1 # mlxphyburn -d /dev/mst/mt4099_pciconf0 -i Firmware_1.37.10_N32722.cld burn
2 -I- attempting to burn PHY Fw on device: /dev/mst/mt4099_pciconf0
3 -I- Burning...(Process might take a few minutes)
4 -I- Device burned and verified.
```

Query Example

```
1 # mlxphyburn -d /dev/mst/mt4099_pciconf0 q
2 -I- Querying device: /dev/mst/mt4099_pciconf0
3 Flash Type : Atmel AT25DF041A
4 FW version : 1.37
5 Image ID : 1.37.10 InterfaceMasters N32722 Apr 14, 2014 12:21:00
6 Image ROM ID : 0
```

Last updated: February 16, 2022

🔮 Use with AI ▾

