

3. **Bitwise Intersection:** The valid indicator bitmask vector $\mathbf{M}$ is computed via bitwise AND:

$$\mathbf{M} = \text{_mm256_and_si256}(\mathbf{M}_{\text{lower}}, \mathbf{M}_{\text{upper}}) \quad (8)$$

4. **Bitmask Extraction:** The 8-lane SIMD result is packed into an 8-bit scalar bitmask $m \in \{0, \dots, 255\}$ using sign-bit extraction:

$$m = \text{_mm256_movemask_ps}(\text{_mm256_castsi256_ps}(\mathbf{M})) \quad (9)$$

5. **Branchless Selection via Hardware Trailing-Zero Count:** Candidates in FDV are ordered deepest-first. Because sibling intervals are mutually exclusive (Section 4.3 in Jiang & Gong (2026)), the deepest valid token corresponds strictly to the lowest set bit in m . The exact lane index idx is pinpointed in a single clock cycle using the hardware bit-scan instruction `tzcnt`:

$$\text{idx} = \text{tzcnt}(m), \quad \theta(sc) = \mathbf{t}[\text{idx}] \quad (10)$$

This vector pipeline resolves candidate validation in $O(1)$ constant time with zero control flow branches, rendering execution latency completely immune to branch mispredictions.

Unrolled Scalar Gather vs. Native Vector Gather. In Stage 1, non-contiguous history timestamps are retrieved into vector registers. While hardware vector gather instructions (`\_mm256\_i32gather\_epi32`) exist, microarchitectural benchmarking across Intel (Ice Lake, Sapphire Rapids) and AMD (Zen 3, Zen 4) processors reveals that native gather instructions incur high instruction latencies (12–20 clock cycles) due to internal microcode serialization and L1 memory port contention. In contrast, an unrolled scalar load loop into a 32-byte cache-aligned temporary buffer followed by a single contiguous vector load (`\_mm256\_load\_si256`) executes in only 5–7 cycles for $N = 8$ lanes, completely avoiding microcode sequencing stalls (see detailed microarchitectural breakdown in Appendix B).

3.4 ATOMIC FAST-PATH BYPASS AND HYBRID CST FALLBACK

Atomic Fast-Path Bypass. When processing raw text streams, character transitions frequently land on single-byte atomic tokens that possess no multi-byte suffix extensions in V . To eliminate unnecessary history array overheads in these cases, VD-STrans overlays a 256-bit transition bitmask on the root state of the Aho–Corasick automaton.

If the incoming byte transition c matches a root state with no suffix extensions, the atomic bypass flag triggers immediately. In this fast-path regime, VD-STrans directly emits single-byte token c and skips history state array indexing, timestamp extraction, and SIMD vector operations entirely.

Hybrid CST Fallback. For rare deep Suffix-Successor Trees where $|\text{SufSucTree}(\tau)| > 8$ (representing $< 0.8\%$ of vocabulary entries), flat SIMD register capacity is exceeded. VD-STrans maintains theoretical robustness by seamlessly falling back to Centroid Search Tree (CST) decomposition (Jiang & Gong (2026)). This hybrid control flow preserves the optimal $O(\log^2 t)$ worst-case per-byte time complexity, ensuring asymptotic stability on pathological or adversarial inputs.

4 EXPERIMENTS

In this section, we present an empirical evaluation of VD-STrans against baseline implementations across diverse LLM vocabularies, text datasets, and execution regimes. We then provide detailed ablation studies dissecting every structural component.

4.1 EXPERIMENTAL SETUP

Hardware Environment. All benchmarks were executed on a bare-metal server powered by an Intel Xeon Platinum 8362 CPU @ 2.80GHz (32 physical cores, 128 GB RAM) running Linux. To eliminate measurement noise, CPU execution was pinned to a single NUMA node, with Hyper-Threading (SMT), Turbo Boost, and Address Space Layout Randomization (ASLR) disabled. Benchmarks utilized 30 parallel workers running isolated single-threaded processes with the `mimalloc` allocator.