

Template paper for the Robotics: Science and Systems Conference

Author Names Omitted for Anonymous Review. Paper-ID [add your ID here]

Abstract—The abstract goes here.

I. INTRODUCTION

This documents provides a detail explanation of the state-space algorithm that is implemented in this project. The algorithm is developed based on existing state-space algorithm [7][8] and is very similar to the approach used by PLECS [1] and DSpace [4].

II. RECOGNIZE CIRCUIT TOPOLOGY

Although the paper published by PLECS [1] points out how to retrieve state-space matrix from a network topology matrix, but the authors did not give any detail on a systematic method for obtaining those state-space matrix. In Dspace's paper[4], the authors point to a highly influential paper[5] on how to retrieve state-space matrix based on circuit network Topology. In Massarini and Reggiani's paper, the authors points to the book co-author by L.O.Chua and P.M.Lin[2] for methods on retriving state-space matrix base on circuit network Topology.

After a detail comparison, the author found many of the ideas by Kuh and Rohrer [5] exist in the book [2]. Thus, the author decide to further develop the algorithm base on the work by Massarini and Reggiani[7], [8].

The paper by Massarini and Reggiani[8] start develop based on the (1) which obtained in [2]. For a detail overview of the equation, please refer to chapter 4 and chapter 6 of [2].

$$\begin{bmatrix} Day_{11} & 0 & 1 & 0 & D_{ab} & 0 \\ 0 & -(D_{zb})^T & 0 & 1 & 0 & -(D_{ab})^T \\ \hat{F}_{iy} & \hat{F}_{vz} & \hat{F}_{ia} & \hat{F}_{vb} & \hat{F}_{ib} & \hat{F}_{va} \end{bmatrix} \times \begin{bmatrix} i_y \\ V_z \\ i_a \\ v_b \\ i_b \\ v_a \end{bmatrix} = 0 \quad (1)$$

III. EXTENSION OF THE WORK

At the end of section 2in [8], the author mentioned both M and Q is not full rank when there exist dependency between state variables. However, the author did not give any specific details in handling those situation while maintaining the number of state variables consistent through out the simulation.

Assume given matrix E, M, A, B of a LTI(linear time-invariant) state-space system with the form

$$M \times \dot{x} = A \times x + B \times u \quad (2)$$

where E is the Capacitance/Inductance of the coreesponding element. If M is full rank, it implies the result of

$$ME = M_f$$

is invertible, which simplifies the state-space equation in (2) to

$$\dot{x} = M_f^{-1}(A \times x + B \times u), M_f = ME \quad (3)$$

Consider the following state-space form for an hypothetically RLC circuit. Clearly, M_f is always invertible regardless the value of L and C.

$$\begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \begin{bmatrix} L & 0 \\ 0 & C \end{bmatrix} \dot{x} = \begin{bmatrix} -0.001 & 10 \\ 1 & 2 \end{bmatrix} x + \begin{bmatrix} 2 \\ 3 \end{bmatrix} u$$

However, the equation in (3) no longer holds when M is no longer full rank. In this case, several possible solution is possible.

In [12], it recognized such system as a "Singular Perturbed Systems." In [12], the authors proposed filling M matrix with small ε value . However, the process of determine this ε is often a iterative, trial-error process.

On the other hand, in [11], [10], and [6] views such singular system as descriptor state space system. In both [11] and [10], it proposed to use either shuffle algorithm, Weierstrass-Kronecker Decomposition or Drazin Inverse method to transform the descriptor state space system into standard state-space form. However, the transformation involves redefine the state variable as

$$\begin{bmatrix} z \\ w \end{bmatrix} = V \times x_i$$

where V is a matrix and x_i is the independent state in the system. In other words, the new states is linear combination of independent states of the original system. While this method works well for large system containing parallel capacitors or series inductor, it is not the perfect solution for state-space simulation. Because for every switch/diode change, it transformed into a new topology with own set of M, A, B matrix, which also changes the definition of state variable. Given the new topology's initial state value depends on the old topology state value, it would be an issue if the old topololgy's z defined by different x_i from the new topology's z.

In this project, I end using a similar simplification that is similiar to shuffle algorithm. In (4), x_1 represents the independent state variable and x_2 represents the dependent state variable.

$$\begin{bmatrix} M_{f11} & M_{f12} \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \hat{x}_1 \\ \hat{x}_2 \end{bmatrix} = \begin{bmatrix} A_{11} & A_{12} \\ A_{21} & A_{22} \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix} + \begin{bmatrix} B1 \\ B2 \end{bmatrix} u \quad (4)$$

Given A22 is invertable, which is the case when there does not exist CE-loop/I-J cutset [2] in the circuit,

$$x_2 = -A_{22}^{-1} A_{21} x_1 - A_{22}^{-1} B_2 u \quad (5)$$

and

$$M_{f11}\hat{x}_1 + M_{f12}\hat{x}_2 = A_{11}x_1 + A_{12}x_2 + B_1u \quad (6)$$

which simplifies to

$$[M_{f11} - M_{f12}A_{22}^{-1}A_{21}]\hat{x}_1 = (A_{11} - A_{12}A_{22}^{-1}A_{21})x_1 + (B_1 - A_{12}A_{22}^{-1}B_2)u \quad (7)$$

//TODO: add explain why is full rank and invertible
Then, (7) simplifies to

$$\hat{x}_1 = [M_{f11} - M_{f12}A_{22}^{-1}A_{21}]^{-1}[(A_{11} - A_{12}A_{22}^{-1}A_{21})x_1 + (B_1 - A_{12}A_{22}^{-1}B_2)u] \quad (8)$$

In addition, by taking derivative on both side of (5), it turn to be

$$\hat{x}_2 = -A_{22}^{-1}A_{21}\hat{x}_1 - A_{22}^{-1}B_2\hat{u} \quad (9)$$

Given the simulation has a relative small iteration step, $\hat{u}$ is effectively almost 0, which simplify the (9) to

$$\hat{x}_2 = -A_{22}^{-1}A_{21}\hat{x}_1 \quad (10)$$

Furthermore, from [8], the author define the output matrix of the system as

$$Qy = C_1\hat{x} + Cx + Du \quad (11)$$

which simplify to

$$Qy = C_1E^{-1}[Ax + Bu] + Cx + Du \quad (12)$$

base on (2) given M became back to identity matrix where Q is an identity matrix when there does not exist CE-loop/I-J cutset. But when there is dependent in output variables causing Q not being a full rank matrix, we can still simplify the equation to standard form by finding the minimum norm of the Q matrix

A. Subsection Heading Here

Subsection text here. we can see in (1)

1) Subsubsection Heading Here: Subsubsection text here.

IV. RSS CITATIONS

Please make sure to include `natbib.sty` and to use the `plainnat.bst` bibliography style. `natbib` provides additional citation commands, most usefully `\citet`. For example, rather than the awkward construction

`\cite{kalmal1960new}` demonstrated...

rendered as “[3] demonstrated...,” or the inconvenient

Kalman `\cite{kalmal1960new}` demonstrated...

rendered as “Kalman [3] demonstrated...”, one can write

`\citet{kalmal1960new}` demonstrated...

which renders as “Kalman [3] demonstrated...” and is both easy to write and much easier to read.

A. RSS Hyperlinks

This year, we would like to use the ability of PDF viewers to interpret hyperlinks, specifically to allow each reference in the bibliography to be a link to an online version of the reference. As an example, if you were to cite “Passive Dynamic Walking” [9], the entry in the bibtex would read:

```
@article{McGeer01041990,
  author = {McGeer, Tad},
  title = {\href{http://ijr.sagepub.com/content/9/2/62.a}
  volume = {9},
  number = {2},
  pages = {62-82},
  year = {1990},
  doi = {10.1177/027836499000900206},
  URL = {http://ijr.sagepub.com/content/9/2/62.abstract},
  eprint = {http://ijr.sagepub.com/content/9/2/62.full.p},
  journal = {The International Journal of Robotics Resea
}
```

and the entry in the compiled PDF would look like:

[1] Tad McGeer. Passive Dynamic Walking. *The International Journal of Robotics Research*, 9(2):62–82, 1990.

where the title of the article is a link that takes you to the article on IJRR’s website.

Linking cited articles will not always be possible, especially for older articles. There are also often several versions of papers online: authors are free to decide what to use as the link destination yet we strongly encourage to link to archival or publisher sites (such as IEEE Xplore or Sage Journals). We encourage all authors to use this feature to the extent possible.

V. CONCLUSION

The conclusion goes here.

ACKNOWLEDGMENTS

REFERENCES

- [1] J.H. Allmeling and W.P. Hammer. Plecs-piece-wise linear electrical circuit simulation for simulink. In *Proceedings of the IEEE 1999 International Conference on Power Electronics and Drive Systems. PEDS'99 (Cat. No.99TH8475)*, volume 1, pages 355–360 vol.1, 1999. doi: 10.1109/PEDS.1999.794588.
- [2] L. O. Chua and P. M. Lin. *Computer-aided analysis of electronic circuits*. Prentice-Hall, Inc, 1975.
- [3] R.E. Kalman. A new approach to linear filtering and prediction problems. *Journal of Basic Engineering*, 82(1):35–45, 1960.
- [4] Axel Kiffe, Thorben Hoffstadt, and Frank Puschmann. Modeling approach for real-time capable oversampling models applied to a fast switching llc resonant converter. In *2021 23rd European Conference on Power Electronics and Applications (EPE'21 ECCE Europe)*, pages P.1–P.11, 2021. doi: 10.23919/EPE21ECCEurope50061.2021.9570187.
- [5] E.S. Kuh and R.A. Rohrer. The state-variable approach to network analysis. *Proceedings of the IEEE*, 53(7): 672–686, 1965. doi: 10.1109/PROC.1965.3991.

- [6] Yitong Li, Timothy C. Green, and Yunjie Gu. Descriptor state space modeling of power systems. *IEEE Transactions on Power Systems*, 39(4):5495–5508, 2024. doi: 10.1109/TPWRS.2023.3343817.
- [7] A. Massarini and U. Reggiani. Computer-aided time-domain large-signal analysis of networks with switches. In *Proceedings of IEEE International Symposium on Industrial Electronics*, volume 2, pages 567–572 vol.2, 1996. doi: 10.1109/ISIE.1996.551005.
- [8] A. Massarini and U. Reggiani. An efficient algorithm for the formulation of state equations and output equations for networks with ideal switches. In *ISCAS 2001. The 2001 IEEE International Symposium on Circuits and Systems (Cat. No.01CH37196)*, volume 3, pages 521–524 vol. 2, 2001. doi: 10.1109/ISCAS.2001.921362.
- [9] Tad McGeer. Passive Dynamic Walking. *The International Journal of Robotics Research*, 9(2):62–82, 1990. doi: 10.1177/027836499000900206. URL <http://ijr.sagepub.com/content/9/2/62.abstract>.
- [10] Karl Heinz Kienitz Roberto Kawakami Harrop Galvão and Sillas Hadjiloucas. Conversion of descriptor representations to state-space form: an extension of the shuffle algorithm. *International Journal of Control*, 91(10):2199–2213, 2018. doi: 10.1080/00207179.2017.1336671.
- [11] Łukasz Sajewski. Descriptor fractional continuous-time linear system and its solution – comparison of three different methods. In Roman Szewczyk, Cezary Zieliński, and Małgorzata Kaliczyńska, editors, *Automation 2017*, pages 45–57, Cham, 2017. Springer International Publishing. ISBN 978-3-319-54042-9.
- [12] G. Verghese, B. Levy, and T. Kailath. A generalized state-space for singular systems. *IEEE Transactions on Automatic Control*, 26(4):811–831, 1981. doi: 10.1109/TAC.1981.1102763.