

$\sqrt{Eurocomp}$ LGP-21 Subroutine Handbook
English translation

Equinox Deschanel

June 2026

“Our need will be the real creator.”

— Plato, *The Republic*

“The enemy of art is the absence of limitations.”

— Orson Welles

Contents

1	Preface	4
1.1	Document organization	4
1.2	Repeated/redundant information	5
1.3	Archeological notes	5
1.4	Acknowledgements and disclaimers	5
2	Introduction to the LGP-21	7
2.1	Number representation	7
2.2	LGP-21 coding conventions	9
2.2.1	Address notation	9
2.2.2	Calling sequences	9
3	Trigonometric functions	13
	SINE-COSINE 1 — B1-10.0	13
	SINE-COSINE 2 — B1-10.1	15
	ARCTANGENT 1 — B1-11.0	17
	ARCTANGENT OF A VECTOR 1 — B1-11.1	19
	ARCSIN/ARCCOS 1 — B1-12.0	21
4	Logarithmic Functions	23
	EXPONENTIAL FUNCTION 1 — B3-10.0	23
	LOG 1 — B3-11.0	25
5	Root Extraction	28
	SQUARE ROOT 1 — B4-10.0	28
	n -TH ROOT — B4-11.0	30
6	Matrix Operations	32
	MATRIX PROGRAMS 1 — D1-10.0	32
	MATRIX INVERSION 1 — D1-11.0	33
	MATRIX-VECTOR MULTIPLICATION 1 — D1-12.0	37
	MATRIX MULTIPLICATION 1 — D1-13.0	40
	MATRIX ADDITION AND SUBTRACTION 1 — D1-14.0	43
	MATRIX TRANSPOSITION 1 — D1-15.0	46
	COMPLEX OPERATIONS INTERPRETIVE SYSTEM — H1-10.0	48
7	Floating-Point Interpretive Systems	52
	FLOATING POINT INTERPRETER 1 — H1-11.0	52
	FIXED-POINT TO FLOATING-POINT CONVERSION (AND VICE VERSA) — L3-12.0	59
	Floating-Point Interpreter System 1 — Memory Layout	61
	FLOATING POINT INTERPRETER 2 — H1-11.1	67
8	Format Conversion	88
	DECIMAL-HEXADECIMAL TAPE CONVERSION — H4-10.0	88

9 Program Input	91
PROGRAM LOADER 1 — J1-10.0	91
PROGRAM LOADER 2 — J1-10.1	102
10 Data Input	113
DATA INPUT 1 — J2-10.0	113
DATA INPUT 2 — J2-10.1	117
DATA INPUT 3 — J2-10.2	124
DATA INPUT 4 — J2-10.3	127
DATA INPUT 5 — J2-10.4	132
11 Data Output	136
DATA OUTPUT 1 — J3-10.0	136
DATA OUTPUT 2 — J3-10.1	140
DATA OUTPUT 3 — J3-10.2	145
DATA OUTPUT 4 — J3-10.3	149
DATA OUTPUT 5 — J3-10.4	152
DATA OUTPUT 6 — J3-10.5	155
12 Hexadecimal Output	158
HEXADECIMAL OUTPUT 2 — J4-10.1	158
HEXADECIMAL OUTPUT 3 — J4-10.2	161
HEXADECIMAL OUTPUT 4 — J4-10.3	165
13 Alphanumeric Output	168
ALPHANUMERIC OUTPUT 1 — J4-11.0	168
ALPHANUMERIC OUTPUT 2 — J4-11.1	172
14 Hexadecimal Input	175
HEXADECIMAL INPUT 3 — J5-10.0	175
15 Specialized Input/Output	179
DIRECTION OR ANGLE INPUT AND OUTPUT 1 — J9-11.0 . . .	179
16 Tracing	183
TRACE 1 — K1-10.0	183
17 Memory Dumps	186
MEMORY PRINT 1 — K2-10.0	186
MEMORY DUMP 2 — K2-10.1	189
18 Sorting	191
SORTING 1 — L1-10.0	191
SORTING 2 — L1-10.1	194
SORTING 3 — L1-10.2	198
SORTING 4 — L1-10.3	201

19 Conversion to Binary	206
BINARY CONVERSION OF WHOLE NUMBERS 1 — L3-10.0 . . .	206
20 Backup Utilities	209
MEMORY COPY 1 — L4-10.0	209
TAPE DUPLICATOR 1 — L4-11.0	210
21 Binary Searching	213
TABLE SEARCH 1 (BINARY SEARCH) — L7-10.0	213
22 Programming Utilities	216
LOOP COUNTER 1 — L8-10.0	216
23 Bibliography	221

1 Preface

1.1 Document organization

First, the code described in this document spans a wide range of functions. Some of it really is subroutines, some of it what we'd call functions (subroutines that return a specific value or result), and some is what we'd call a program, utility, or monitor. The original document simply calls everything a subroutine, and what the document calls a "calling sequence" is how the code is executed. This means that some "calling sequences" really are a set of machine instructions that perform a subroutine call, while others are a series of operations that the machine operator must perform to load and start the program.

Because the actual function of the code is highly variable, I've chosen to refer to the individual programs as appropriate, whether a function, subroutine, utility, etc. "Calling sequence" is altered as appropriate for the kind of program in question; in particular, where the code is a stand-alone program rather than a callable subroutine, the heading appears as "Operating Instructions" instead.

The document is organized in broad sections, broken into mathematical functions, a pair of floating-point calculators, input and output support code, utilities, and a grab-bag of miscellaneous other algorithms and utilities: sorts, searches, data maintenance/backup, and programming tools. (The tool that automates self-modifying code loops is particularly engaging!)

Code names

The programs do not have names! This is probably because the name was pretty arbitrary as far as the machine was concerned – you can't load a program by name, etc.; it's all simply reference material for humans. As such the names are assigned to organize the programs, from broad functional groups down to exactly which program is which.

The first character of the name establishes which broad area a program falls into: B is mathematical, D is matrixes, J is input/output, and so on. The second character refines this: B1 is trig functions; B3 is exponential/log functions; B4 is roots. There is no rule as to how the refinement is assigned other than personal taste.

The numeric part of the name refines the classification further. B1 is trig; B1-10 is sine and cosine, B1-11 is arctangent, B1-12 is arcsin/arccos. Within that numeric classification, we have a point number that differentiates implementations. So B1-10.0 (we number the point classifications from 0) is mathematics (B), trigonometry (1), sine/cosine (-10), first implementation (.0). As a sample, B1-10.0 is the *first* sine and cosine implementation (point number .0), which accepts degrees; B1-10.1 is the *second* sine and cosine implementation (point number .1), which accepts radians.

These break up reasonably well into sections and subsections, so I've done that to make it easier to navigate the table of contents. I have not reordered any of the programs to ensure that any cross-referencing between the German

and English versions of the document was easy to do.

1.2 Repeated/redundant information

Because this is a reference manual meant for use by people who were casually programmers and principally something else entirely, this manual fairly consistently repeats things like the standard B/R/U instruction sequence used to call a function as noted in Section 2.2.2. I have tried to condense this where possible; some of it still remains. We'll get it on the next edit.

Some subroutines use unusual parameterization (such as patching the values of words in the subroutine itself to save parameters there!), or are actually programs to be loaded and run and not subroutines at all. I have retained all of the setup information and/or programming information as it was originally written in these cases.

1.3 Archeological notes

Reading the original German document, it becomes extremely clear that a number of different hands wrote the code and documentation of it. A deep textual analysis would be rewarding to get a better handle on this; unfortunately, the act of translation obscures this significantly, but a few pointers still remain – there are a few program examples that were provided as LGP-21 *coding sheets* – the literal “we need to punch this on the tape and feed it to PIR” data – and I've preserved these to remind us that there is some interesting research there for a digital archaeologist.

1.4 Acknowledgements and disclaimers

Thanks in particular to David Lovett of Usagi Electric for resurrecting a real, physical LGP-21 and starting me down this road; Rhys Weatherly for the lgp21-tools, and Paul Kimpel for the wonderful LGP-21 web emulator that has given me such a lot of pleasure learning the machine.

Thanks also to the many people whose names I don't know¹, who have tirelessly made sure that important historical documents like the original German version of this manual and the programs that go with it have been preserved. This document is my small contribution to this historical preservation effort, and I am immensely grateful to those giants upon whose shoulders I stand.

This work *is* a translation, and I cannot guarantee I have been completely accurate, whether from misunderstanding or transcription error. I've done my best to be sure my interpretation of what's documented here is correct, but I have not run or tested all of the programs referenced, and I can't make any guarantees as to their fitness and accuracy, nor can I be sure that the document I've translated here is in fact 100 percent accurate itself! I have made corrections where errors were obvious, but I may have missed things.

¹Send me patches via GitHub so I can credit you, please!

To that end, this document will be up on GitHub; please feel free to submit PRs for corrections and errata there if you find anything that needs a fix. I intend to CC license this document such that it can be freely built upon and distributed, but that credit for the basic work is retained.

2 Introduction to the LGP-21

2.1 Number representation

Introduction to fractional fixed-point architecture

The LGP-21's fractional fixed-point number representation is very different from more modern computing platforms, though it is not unique; many early computers used it, including the IBM 701[3], the ILLAC I[4], the Elliot 405[5], the RPC-4000[10], and the LGP-21's predecessor, the LGP-30[6]. This is known as the IAC architecture, and was first proposed by John von Neumann for EDSAC[1].

Fixed-point fractional representation treats all numbers as fractions lying strictly between -1 and $+1$. As von Neumann pointed out[2], the multiplication of 2 n -bit integers results in a value that may require $2n$ bits to represent it, which could easily overflow a register, but the multiplication of two *fractions* less than 1 always results in a number no larger than, and usually smaller than, both multiplicands (e.g., $0.5 \times 0.5 = 0.25$). The answer still requires $2n$ bits to represent, but the extra bits end up in the *least* significant digits, preventing overflow from occurring, and making a good compromise between accurate representation and complexity.

This design uses a combined register pair to contain the $2n$ bits; on the LGP-21, the accumulator receives the most significant half, and a hidden multiplication register not available to the programmer gets the least significant half. The LGP-21 simply throws the multiplier register part away. These are the least significant digits, so the (unscaled) error introduced is 2^{-31} or less.

This advantage in multiplication is offset by a problem it creates with division: fractional multiplication *shrinks* numbers², but fractional division (potentially) *expands* them.

In a fractional fixed-point architecture, dividing two numbers requires that the absolute magnitude of the divisor has to be *strictly greater than* the absolute magnitude of the dividend.

$$|\text{Divisor}| > |\text{Dividend}|$$

Getting this wrong means that the theoretical quotient is ≥ 1.0 , and such a value overflows because the architecture maintains the *hardware* binary point just after the sign bit³.

Von Neumann wrote that “[t]he programmer must see to it [emphasis mine - ED] that the left-shift [scale factor] is sufficiently large to ensure this inequality.”[2] The cognitive load of remembering where the *implied* binary point is (via the scaling factor) vs. the *physical* binary point (implemented by the hardware) is placed solely on the programmer.

²The numerators of numbers representable in fractional fixed-point are strictly smaller than their denominators, so the product of the numerators must always be smaller than the product of the denominators, resulting in a value that is smaller

³The LGP-21 also does not have the concept of an exception; the best it can do is set the overflow indicator. This makes division particularly sensitive to scaling factors.

Modern embedded systems actually still use similar notation (referred to as *Q-notation* or *fixed-point scaling*) to define this manual placement of the implicit binary point within a computer word, and in fact, the original German version of this document refers to the scaling factor as q at various points.

LGP-21 Fractional Fixed-point Implementation

The LGP-21 treats all 31-bit words strictly as fractions ranging from -1 to $+1$, with the physical binary point fixed immediately to the right of the (left-most) sign bit. To work with integers or mixed numbers, the programmer must mentally shift this binary point to the right by n bits.

This original version of this manual is inconsistent as to how this is notated (most likely because of multiple authors). As noted, the scaling factor is referred to as q , but there are multiple alternate notations for it. Some contributors use $q = n$. Others prefer a shorthand $@n$ notation. Still others simply refer to “a q of 9” (e.g.).

For example, a value at $q = 3$ allocates 3 bits for the integer portion of a number (allowing values up to 7.999999 to be represented) and the remaining 27 bits for the fraction. As noted above, the programmer is *entirely responsible* for tracking this scale factor across operations, and must manually shift, multiply, or divide intermediate values as needed to maintain the desired scale factor.

I have retained the melange of different notations for now, but I plan to standardize the usage as $q = n$ for scale factors.

Regardless of how it is notated, the scaling factor represents the *programmer's* division of the 31 bits of the LGP-21's word into a *logical* integer portion and fractional portion. The hardware binary point remains fixed, but the programmer's binary point can shift. In general, the subroutines that had specific q requirements state them, and note when the q of a result will not match that of original value.

Scale Factors During Arithmetic Operations

Addition and subtraction require that the q factors of both operands be identical before the operation is executed. The LGP-21 treats every 31-bit word as a fixed-point fraction with the hardware binary point just to the right of the sign bit. If you add two numbers with different q factors without shifting them so their q factors match, the machine will simply perform the operation requested on the two numbers, yielding an invalid result.

For example, if you attempt to add 1.0 scaled at $q = 1$ to 1.0 scaled at $q = 4$ without normalizing them first:

$$\begin{array}{rcl}
 1.0 \text{ at } q = 1 & \rightarrow & 0 \ 100000\dots \quad (\text{Hardware sees } 2^{29}) \\
 + \quad 1.0 \text{ at } q = 4 & \rightarrow & 0 \ 000100\dots \quad (\text{Hardware sees } 2^{26}) \\
 \hline
 \text{Result} & \rightarrow & 0 \ 100100\dots \quad (\text{Hardware sees } 2^{29} + 2^{26})
 \end{array}$$

Obviously, the answer is not 2.0, as it should be. The machine will not throw an error, trigger an overflow, or warn you; it will simply calculate perfectly

represented garbage because the *logical* binary point in the two numbers is in *two different places*.

Multiplication and division also change the scale factor. Multiplication *adds* q values, division *subtracts* them: a $q = 4$ value times a $q = 5$ value gives a $q = 9$ result. The bit width of the word doesn't change, so the further the result's q drifts from where you want it, the more least significant figures have been lost.

Division has the extra restriction noted earlier: the divisor's magnitude must exceed the dividend's. Equivalently, if subtracting q_{divisor} from q_{dividend} gives a negative result, the operation overflows and the high-order bits are gone for good. Dividing a $q = 1$ value by a $q = 9$ value formally yields $q = -8$ — i.e. the top 8, *most* significant bits of the answer were thrown away.

It is vital to remember that the LGP-21 hardware itself does not know about scale factors and does not check them or track them, and that this is absolutely, 100% *your job*.

2.2 LGP-21 coding conventions

2.2.1 Address notation

Subroutine addresses in the original text are written as L or, for offsets into program code, $L+n$.

Addresses in the main program are written as α or $\alpha + n$.

The LGP-21 is too primitive to have anything like a linkage editor, so it's the programmer/operator's responsibility to use the LGP-21's Program Input Routine⁴ to load subroutine code and automatically relocate it as it's loaded.

The usage of L for the base address of code is to remind the reader that they will need to relocate these library functions by hand and use the new base addresses in their code to make subroutine calls work properly. $\alpha \pm n$ notation is a reminder that these instructions can live pretty much anywhere that they're not intruding on other loaded code.

2.2.2 Calling sequences

Because the LGP-21 libraries were written by multiple programmers, and there was no oversight body to enforce a One True Way of doing things, there is a Cambrian explosion of alternatives. Very capable programmers not only coded their algorithms, but cleverly spaced their storage so that the data was under the disk's read head when an instruction wanted to access memory.⁵

Fortunately, none of those programming tricks are used here⁶, but the “let a million flowers bloom” philosophy does show itself in the multiple ways there are to call subroutines.

⁴or Rhys Weatherly's `lgp21-tools` assembler, which can include and relocate subroutines.

⁵See the story of Mel[11], who originally wrote for the LGP-30; his code was famous for using instructions as data, and exploiting the weird corners of the instruction set to do things like have loops with no exit which nevertheless eventually exit.

⁶As far as I know. Heaven knows what's actually lurking in the library code itself.

Accumulator-only parameters

One calling convention streamlines the call as much as possible by loading the parameter into the accumulator, setting the return address in a U instruction in the subroutine at an agreed-upon offset, and then jumping to the subroutine:

Location	Instruction	Address	Description
$\alpha - 1$	B	N	Bring N into the accumulator.
α	R	$L+n$	Store the return address in the subroutine.
$\alpha + 1$	U	L	Unconditional branch to the subroutine entry.

In this example a B loads the argument into the accumulator, but any instruction that gets the appropriate value into the accumulator is just as valid. The R saves the return address ($\alpha+2$) in the subroutine, and the main program's U to the start of the subroutine calls it. Execution of the main program resumes just after the U to L at $\alpha + 2$.

Here we see the effect of the LGP-21's limited instruction set: there's no such thing as an indirect jump or a stack. Calling a subroutine means that code in that subroutine *must* be modified for a jump back to the caller to work: specifically, a U (unconditional jump) instruction in the subroutine must be altered to set the return address. A second call to the subroutine before it returns will absolutely clobber any previous return address; there's nowhere to put it. Programmers must ensure that they carefully manage the hierarchy of subroutine calls to prevent a second call to a subroutine, directly or indirectly, before it returns.

Inlined parameters

A second calling convention, with longer, in-memory parameter lists, looks like this:

Location	Instruction	Address	Description
$\alpha - 1$	E	0000	Exit from the Interpretive System.
α	R	L	Modify subroutine instruction with key word address.
$\alpha + 1$	U	L	Unconditional branch to subroutine entry.
$\alpha + 2$	...	...	A fixed number of parameter words
$\alpha + n$	—	—	Return to main program.

This call looks exceedingly strange if you're used to the previous calling convention. If we were doing exactly the same operation as before (altering a U instruction to set the return, then jumping to the subroutine), we'd just jump right back, so that can't be right, and it isn't.

This convention uses the R instruction to load the address of the *parameters* and store it into a B instruction at the start of the subroutine instead. Jumping

to the subroutine loads the address of the parameters ($\alpha + 2$) into the accumulator, allowing the subroutine to add an offset to this address to set it to $\alpha + n$, which can then be stored locally in a U instruction to do the actual return to the caller, and to have a pointer to the parameters as well!

Deep Wizardry: Floating-Point Parameters

A third, even more astounding calling sequence passes a two-word floating-point⁷ number to a subroutine as an argument.

Location	Instruction	Address	Description
$\alpha - 1$	B	N	Bring word 1 of floating-point number N .
α	R	L+offset	Store the return address ($\alpha + 2$) inside the subroutine.
$\alpha + 1$	U	L	Unconditional branch to the subroutine entry.

Now wait a minute, I hear you say. A floating-point number is *two* words long. That cannot possibly fit in the single-word hardware accumulator—what kind of trickery is this?

You’re right. The full floating-point number doesn’t get loaded; only its first word does. But the B instruction itself at location $\alpha - 1$ now contains the exact piece of metadata the subroutine needs: *the starting memory address N of the floating-point block*⁸.

This explains why the manual repeatedly states that “loading this value into the accumulator by any means” is acceptable for some subroutines, but does *not* say that for this one⁹. The B here is essential to the program working. It relies on the code in the subroutine that’s modified by the R instruction to *find and read its caller*:

1. The subroutine picks up the return address ($\alpha + 2$) deposited by the R instruction into location **L+offset**.
2. It subtracts 3 from that value to locate location $\alpha - 1$ (the B instruction).
3. It modifies the next instruction, a B, to set its address to $\alpha - 1$.
4. The modified B instruction loads the literal 32-bit instruction word stored at $\alpha - 1$...that contains the address of the floating-point number.
5. It strips away the B opcode bits using a bitmask, leaving behind only the raw address N.

⁷While the LGP-21 lacks floating-point *hardware*, it relies entirely on a software-driven floating-point math *interpreter*. See Section 7.

⁸My reaction was “You are *kidding* me” with a significant expletive titre.

⁹Gun, meet foot.

6. Now the subroutine has the address of the first of the two words making up the floating-point number, and can proceed.

The value loaded into the accumulator at step $\alpha - 1$ is *entirely ignored*. The B instruction's sole purpose in this calling sequence is to serve as an *executable static data pointer*, which the subroutine finds and dissects to find word 2 (N+1) of the floating-point parameter.

3 Trigonometric functions

SINE-COSINE 1 — B1-10.0

PURPOSE

B1-10.0 calculates the sine or cosine of an angle value in degrees. If the angle supplied is greater than 360° , the value is reduced to an angle between 0° and 360° before the function value is calculated. A 9th-degree polynomial is used for approximation.

B1-10.0 uses the standard LGP-21 calling sequence. The angle argument must be supplied in the accumulator $q = 9$. The function value, including its sign, will be in the accumulator $q = 1$ when the subroutine returns.

STORAGE REQUIREMENTS

Memory	1 track (64 words)
Temporary storage	Sectors 2, 4, 5, 6, 7, 45 of track 63

INPUT

The input variable for B1-10.0 is an angle in degrees, θ , for which the function value is to be calculated. θ must be in the accumulator $q = 9$ when the jump to the subroutine occurs. The angle is reduced to an angle between 0° and 360° by the subroutine before evaluation.

CALLING SEQUENCE

Different calling sequences are provided for sine and cosine. Only one value (either sine or cosine) can be calculated per subroutine call.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	θ	Load θ at $q = 9$ into the accumulator.
α	R	L+49	Store return address at end of subroutine.
$\alpha + 1$	U	L	Call the sine routine.

Sine This is a standard function call, with the argument passed in the accumulator and the result returned in it.

Cosine The calling sequence for cosine is exactly the same as for sine, except the subroutine is entered at the origin address of the B1-10.0 subroutine plus 4 words.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	θ	Load θ at $q = 9$ into the accumulator.
α	R	L+49	Store return address at end of subroutine.
$\alpha + 1$	U	L+4	Call the cosine routine.

OUTPUT

When the subroutine returns, the properly-signed function value is in the accumulator $q = 1$.

OPERATION

- **Accuracy:** The value is accurate to within 5×10^{-7} .
- **Time required:** approximately 775 ms.
- **Program input:** the tape contains the program in two versions:
 - Relocatable, hexadecimal. Valid for J1-10.0 (section 9).
 - Relocatable, decimal, in coding sheet format.
- **Required I/O devices:** none.
- **Overflow:** ignored on entry and not reset on exit.

SINE-COSINE 2 — B1-10.1

PURPOSE

B1-10.1 calculates the sine or cosine of an angle θ supplied in radians. The absolute value of the argument must not exceed 7.9999999. Before calculating the function, the subroutine reduces the angle θ to an angle β whose absolute value in radians is ≤ 1.75 . A 14th-degree Taylor series is used to calculate the function.

B1-10.1 uses a standard LGP-21 calling sequence. The angle argument must be in the accumulator when the subroutine is called. The function value is in the accumulator $q = 1$ when the function returns.

STORAGE REQUIREMENTS

Memory	1 track (64 words)
Temporary storage	Sectors 8 and 49 of track 63

INPUT

The input variable for B1-10.1 is an angle θ , whose function value is to be calculated. θ must be in the accumulator $q = 3$ and have a value ≤ 7.9999999 when the call to the subroutine occurs. The subroutine reduces the angle to an equivalent angle β with an absolute value ≤ 1.75 .

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	θ	Load θ at $q = 3$ into the accumulator.
α	R	L+16	Store return address at end of subroutine.
$\alpha + 1$	U	L	Call the sine routine.

Sine This is a standard LGP-21 function call; the argument is loaded into the accumulator before the call, and the result is returned in the accumulator.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	θ	Load θ at $q = 3$ into the accumulator.
α	R	L+16	Store return address at end of subroutine.
$\alpha + 1$	U	L+45	Call the cosine routine.

Cosine The calling sequence is exactly the same as for the sine, except that we jump to the cosine entry point to the subroutine, 45 words past the start of the subroutine.

OUTPUT

On return, the function value with the appropriate sign is in the accumulator $q = 1$.

OPERATION

- **Accuracy:** The error in radian measure is less than 8×10^{-9} .
- **Time required:** approx. 1200 ms.
- **Program format:** the tape contains the program in two ways:
 - Relocatable, hexadecimal, valid for J1-10.0 (section 9).
 - Relocatable, decimal, in coding sheet format.
- **Required input/output devices:** None.
- **Overflow:** Ignored and not reset.

ARCTANGENT 1 — B1-11.0

PURPOSE

B1-11.0 calculates the arctangent of any number less than 512. The returned value is signed and expressed in degrees. A 15th-degree polynomial is used to approximate the function.

B1-11.0 is a standard LGP-21 subroutine. The argument must be in the accumulator; the arctangent value is in the accumulator on return to the main program. [Translator note: see section below on result scaling.]

This is a standard LGP-21 function call: the argument is loaded into the accumulator before the call, and the result is returned in the accumulator.

STORAGE REQUIREMENTS

Memory	1 track (64 words)
Temporary storage	Sectors 4, 5, 6, 7, 8, 9, 10, 13, 50, and 51 of track 63

INPUT

The input variable for B1-11.0 is the value N at $q = 9$ whose arctangent is to be computed. This value must be loaded into the accumulator before the subroutine is called.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 9$ into the accumulator.
α	R	L+51	Store return address at end of subroutine.
$\alpha + 1$	U	L	Call the arctangent routine.

This is a standard function call. Load the argument into the accumulator before the call; the value is returned in the accumulator.

OUTPUT

Upon returning to the main program, the signed principal value of the arctangent in degrees is in the accumulator $q = 9$. The absolute value will be between 0° and 89.90° .

OPERATION

- **Accuracy:** The absolute error is no greater than 5×10^{-7} degrees.
- **Time required:** 950 ms.
- **Program format** - the tape contains the program in two ways:
 - Arbitrarily relocatable hexadecimal, suitable for J1-10.0 (section 9).
 - arbitrarily relocatable decimal, in coding sheet format.
- **Required input/output devices:** None.
- **Overflow:** Neither considered at input nor reset at output.

REMARKS

A slight modification to the subroutine call can be made to allow larger input values whose arctangents are closer to 90° (absolute) by changing the contents of memory locations $\alpha + 56$ and $\alpha + 59$ to rescaled values of 1 and 2.

Memory location	Contents (old)	Contents (new)
L+56	1 at $q = 9$	1 at q
L+59	2 at $q = 9$	2 at q

The argument passed in the accumulator must be rescaled as well to the same q scaling value when jumping to the subroutine.

Translator's Notes

Arctangent calculations near 90 degrees At the default $q = 9$, the input fits in roughly $\pm 2^9 \approx \pm 512$. As an angle approaches 90° , its tangent grows without bound, so an input above 512 has no valid representation and a calculation involving such a value will overflow.

To extend the range, repatch the constants at $\alpha + 56$ and $\alpha + 59$ to a larger q . The input must use the same q as the constants; the routine does *not* check this, and a mismatch produces silent garbage. Note also that the word width is fixed at 31 bits, so every bit you give to the integer side is taken from the fractional side — pushing q higher costs precision on smaller results.

ARCTANGENT OF A VECTOR 1 — B1-11.1

PURPOSE

B1-11.1 calculates θ such that, given x and y , the following holds:

$$y = \sqrt{x^2 + y^2} \sin \theta \quad (1)$$

$$x = \sqrt{x^2 + y^2} \cos \theta \quad (2)$$

The x and y values may be positive or negative; the function operates correctly in all quadrants of the cartesian plane. The values x and y must be given at the same q . The result is the angle expressed as a fraction of a half-turn (so 1.0 corresponds to 180° or π radians); multiply by 180 to convert to degrees, or by π to convert to radians.

B1-11.1 uses a standard LGP-21 subroutine call, but the y value must be stored in the subroutine's designated parameter storage, and x must be in the accumulator prior to the call. Upon returning to the main program, the result will be in the accumulator $q = 1$.

STORAGE REQUIREMENTS

Memory	2 tracks, 17 sectors (145 words)
Temporary storage	None

INPUT

The input variables for the program are the values x and y , which must have the same q . y must be stored in the subroutine, and x must be in the accumulator when the subroutine is called.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 3$	B	Y	Load Y at q into the accumulator.
$\alpha + 2$	C	L+34	Save into subroutine parameter storage.
$\alpha + 1$	B	X	Load X at q into the accumulator.
α	R	L+10	Set return address.
$\alpha + 1$	U	L	Call the arctangent routine.

Store y in the designated parameter storage, L+34 (any operation that puts it there is fine). Load x into the accumulator (again, any operation accomplishing this is fine). Remember that x and y must be scaled to the same q value.

OUTPUT

On return from the subroutine, the accumulator $q = 1$ will contain the result. To convert to degrees, multiply this value by 180; to convert to radians, multiply the value by π .

OPERATION

- **Accuracy:** No error exceeds 4×10^{-8} in the half-turn result.
- **Time required:** approx. 1160 ms.
- **Program format** - the tape contains the program in two versions:
 - Relocatable hexadecimal, valid for J1-10.0 (section 9).
 - Relocatable decimal, in coding sheet format.
- No input/output devices are required.
- **Overflow:** Ignored at subroutine call, and not reset at exit.

ARCSIN/ARCCOS 1 — B1-12.0

PURPOSE

B1-12.0 calculates either the arcsine or the arccosine of a given number from $-1 \leq N \leq 1$. The signed return value is expressed in degrees. A 7th-degree polynomial is used for approximation.

B1-12.0 is a standard LGP-21 subroutine. When jumping to the subroutine, the argument must be in the accumulator, and the return address must be stored in the subroutine. Upon returning to the main program, the desired function value is in the accumulator $q = 9$.

STORAGE REQUIREMENTS

Memory	2 tracks, 32 sectors (160 words)
Temporary storage	Sectors 12, 16, 18, 19, 20, 21, 23, 24, 28 of Track 63

INPUT

The value N at $q = 1$, with $-1 \leq N \leq 1$, must be in the accumulator when the function is called.

CALLING SEQUENCE

Arcsin

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 1$ into the accumulator.
α	R	L+21	Set return address.
$\alpha + 1$	U	L	Call the arcsin routine.

Load N into the accumulator, set the return address at L+21, and jump to L to compute the arcsin. Mainline execution continues after the jump.

Arccos

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 1$ into the accumulator.
α	R	L+21	Set return address.
$\alpha + 1$	U	L+211	Call the arccos routine.

Load N into the accumulator, set the return address at L+21, and jump to L+211 to compute the arccos. Mainline execution continues after the jump.

OUTPUT

Output is returned in the accumulator $q = 9$ in radians; the value of the function is $-\pi/2$ to $\pi/2$ for arcsin, and 0 to π for arccos.

REMARKS

Since calculating the arcsine or arccosine requires calculating a square root, a program for this has been included in this subroutine. It can be used independently with the following calling sequence:

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	value	Load value into the accumulator at an <i>even</i> q (see translator notes).
α	R	L+150	Set return address.
$\alpha + 1$	U	L+100	Call the square root routine.

The square root is returned in the accumulator. Note that the q value of the result is *half* of the argument's q value.

Translator's Note

There's a lot hiding inside that throwaway "the q value of the result is half of the argument's q value". You may also be wondering why the q value of the argument *must* be even, especially since we're doing all this math at $q = 1$ and $q = 9$.

This all goes back, again, to the fractional fixed-point math of the LGP-21. In modern floating-point math, the hardware (or software) manages all the exponents for you, but on the LGP-21, something interesting happens when we take the square root of a scaled number.

If you have a value X scaled to factor q , its internal integer representation in the machine is actually $X = x \cdot 2^q$. When you take the square root of that internal machine representation, look at what happens to the exponent:

$$\sqrt{X} = \sqrt{x \cdot 2^q} = \sqrt{x} \cdot 2^{q/2} \quad (3)$$

If your scale factor q is an odd number (like the standard at $q = 1$ or the at $q = 9$ used elsewhere in these library functions), then $q/2$ is a fraction (4.5)! You cannot shift a binary word by 4.5 bits, meaning that you can't make the result of the square root operation commensurate to any q .

Forcing the programmer to provide an input with an even q (like at $q = 2$, at $q = 8$, or at $q = 18$) means that the resulting scale factor after the square root function finishes will be an integer (at $q = 1$, at $q = 4$, or at $q = 9$, respectively) and that the result will be valid.

4 Logarithmic Functions

EXPONENTIAL FUNCTION 1 — B3-10.0

PURPOSE

B3-10.0 calculates the exponential function K^x , where $K = 2, e$, or 10 and $x : -1 \leq x \leq 1$. B3-10.0 expects x in the accumulator, and returns K in the accumulator.

STORAGE REQUIREMENTS

Memory	63 sectors (63 words)
Temporary storage	None

INPUT

The input value x must be scaled to $-1 \leq x \leq 1$ and have a q at $q = 1$.

CALLING SEQUENCE

Each of the exponential functions has a separate entry point into the subroutine:

2^x

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 1$ into the accumulator.
α	R	L+9	Set return address.
$\alpha + 1$	U	L	Call the 2^x routine.

e^x

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 1$ into the accumulator.
α	R	L+9	Set return address.
$\alpha + 1$	U	L+2	Call the e^x routine.

10^x

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 1$ into the accumulator.
α	R	L+9	Set return address.
$\alpha + 1$	U	L+3	Call the 10^x routine.

Each of the entry points is a standard LGP-21 subroutine call; mainline execution resumes directly following the unconditional jump to the subroutine.

OUTPUT

On return, the function value is in the accumulator at $q = 4$.

REMARKS

- **Accuracy:** No error is greater than 5×10^{-8} .
- **Time required:** approx. 775 ms.
- **Program format** - the tape contains the program in two versions:
 - Relocatable hexadecimal, valid for J1-10.0 (section 9)
 - Relocatable decimal, in coding sheet format.
- **Required input/output devices:** None.
- **Overflow:** The program neither checks overflow upon input nor resets it.

Translator's Notes

While the input to these functions is strictly restricted to $q = 1$, the routine returns the final calculated value in the accumulator scaled to at $q = 4$. This choice of scale factor represents a best-case compromise with the LGP-21's fixed-point architecture.

Because the maximum possible input value to any of these functions is 1.0, the maximum possible outputs are predetermined:

$$2^1 = 2.0$$

$$e^1 = 2.718281828\dots$$

$$10^1 = 10.0$$

Recalling that the representation of the largest possible value for any of these functions as an integer is 10, or 1010_2 — four bits in binary — this means we need to have four bits in front of the binary point, but not more, to represent the maximum value of 10.0: a q of $q = 4$.

If we instead chose to return the data at a standard library scale like at $q = 9$, this would throw away bits on the right side of the binary point to provide space to on the left-hand side of the binary point to represent values much larger that we would ever need. If, on the other hand, we chose to use $q = 1$, this would limit the return value's maximum to 1.99, causing an overflow on 2^1 and most positive e^x and 10^x calculations.

By standardizing the output to at $q = 4$, B3-10.0 allows the maximum possible value (10.0) for any of these functions to be returned while preserving an optimal 26 bits of precision for the fractional portion of the result for smaller numbers.

LOG 1 — B3-11.0

PURPOSE

B3-11.0 calculates the logarithm of a positive number to the base 2, e , or 10. A 7th-degree polynomial is utilized as the approximation method.

B3-11.0 uses an altered multi-argument LGP-21 function call sequence. The function argument must reside in the accumulator, but the two words immediately following the jump to the subroutine must contain the q of the argument and the desired base of the logarithm. The return value is in the accumulator on return.

STORAGE REQUIREMENTS

Program Space: 1 track, 58 words

Temporary Storage: None

INPUT

The required input consists of:

1. N : The positive number whose logarithm is to be calculated.
2. Q : The q factor of N .
3. K : The desired base of the logarithm.

N must be a positive number greater than zero ($N > 0$) and must reside in the accumulator with a positive q factor when branching to the subroutine.

The q factor must lie within the range $0 \leq q \leq 31$. In the calling sequence, Q is stored in the sector portion of a Z instruction that immediately follows the branch instruction.

K , the desired base of the logarithm, is also stored in the sector portion of a Z instruction.

- For $\log_2 N$, $K = 00$
- For $\log_e N$, $K = 01$
- For $\log_{10} N$, K can take any value other than 00 or 01.

The Z instruction containing K is the final entry in the calling sequence.

CALLING SEQUENCE

As usual, any instruction sequence leaving N in the accumulator prior to the call is fine as long as it leaves N there with a positive q . The instruction at location α patches the address of the Z instruction containing Q ($\alpha + 2$) into the subroutine, giving it the address of Q and K .¹⁰

¹⁰Translator's note: the subroutine figures out the return address by taking the address supplied by the R instruction and adding 2 to skip over the two parameter words. It then updates a U instruction in *itself* to jump back to the proper return address

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	N	Load N at $q = 1$ into the accumulator.
α	R	L+24	Set return address.
$\alpha + 1$	U	L	Call the log routine. The following parameter constants are effectively scaled at $q = 29$.
$\alpha + 2$	Z	00Q	The q value of N .
$\alpha + 3$	Z	00K	Desired base K .

Execution resumes following the second parameter constant upon return from the subroutine.

OUTPUT

Upon the return branch to the main program, the calculated logarithm to the desired base resides in the accumulator at $q = 6$.

OPERATING DETAILS

1. Accuracy:

Any potential error is less than 3×10^{-8} .

2. Execution time:

Approximately 1350 ms.

3. Program input:

The program tape contains the routine in two formats:

- Relocatable hexadecimal, valid for J1-10.0 (section 9)
- Relocatable decimal, in coding sheet format.

4. Required input/output devices:

None.

5. Overflow:

Overflow is neither checked upon entry to the subroutine nor reset upon exit.

6. Error Stops:

Memory Location	Meaning and Remedy
$\alpha + 8$	Argument N is zero or negative. The accumulator contains the value $N - (1 \text{ at } q = 30)$. To continue, deposit a corrected value, and jump manually via the console to resume execution.

Translator's Notes

The behavior on an invalid argument ($N \leq 0$) is a little odd. Halting at L+8 leaves execution close to the error, fine; but why also leave $N - (1 \text{ at } q = 30)$ in the accumulator instead of just N ?

“1 at $q = 30$ ” means a single 1 bit in position 30 of the word, i.e. the value 2^{-30} — one bit short of the LSB. Subtracting it from N is essentially $N - \epsilon$: the result looks almost identical to N if you read it as a number, but the low end of the word will differ.

The LGP-21's console isn't a wall of indicator lights; it's a small oscilloscope tube that paints the accumulator, the address register, and the current instruction as rows of dashes — a 0 bit is drawn low, a 1 bit drawn high. The machine is slow enough that on a stop, the row sits there steady and you can read off the bits.

So the actual point of L+8 probably isn't that the difference makes the value easier to recognize visually — it's that subtracting that one bit is a cheap way to *prove*, at the stop, that the routine got as far as detecting the error and ran the trap. If the operator sees a value with a flipped low end, the error path ran; if they see the original N untouched, something else stopped the machine. The accumulator doubles as a one-bit status flag without spending a location on one.

5 Root Extraction

SQUARE ROOT 1 — B4-10.0

PURPOSE

B4-10.0 calculates the square root of a positive number. The number must reside in the accumulator at an even q factor. The program utilizes Newton's method to solve the equation:

$$0 = x^2 - N \quad (4)$$

by means of successive approximations:

$$x_{i+1} = x_i + \frac{1}{2} \left(\frac{N}{x_i} - x_i \right) \quad (5)$$

The program operates as a subroutine and is invoked via a calling sequence in the main program. Upon branching to the subroutine, the argument must reside in the accumulator, and the return address must be stored within the subroutine. Upon return to the main program, the calculated square root is held in the accumulator.

STORAGE REQUIREMENTS

Program Space: 51 words

Temporary Storage: None

INPUT

The input variable for "Square Root 1" is N , the positive number whose square root is to be calculated.

N must reside in the accumulator with an even q factor when branching to the subroutine.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	L	Bring N into the accumulator at an even q .
α	R	L+50	Store the return address in the subroutine.
$\alpha + 1$	U	L	Unconditional branch to the subroutine entry.

This function uses a standard LGP-21 function call. The only notable factor is that N must have an even q .¹¹

¹¹See Section 3 for why.

OUTPUT

Upon the return branch to the main program, the square root of the argument N resides in the accumulator at $q_N/2$. For example, if N is at $q = 24$, then $\sqrt{N}$ will be at $q = 12$.

OPERATING DETAILS

1. **Accuracy:**

No error is greater than 2^{-30} .

2. **Execution Time:**

Approximately 775 ms.

3. **Program input:**

The program tape contains the routine in two formats:

- Relocatable hexadecimal, valid for J1-10.0 (section 9)
- Relocatable decimal, in coding sheet format.

4. **Required Input/Output Units:**

None.

5. **Overflow:**

Overflow is ignored and is not reset upon return.

6. **Error Stops:**

Memory Location	Meaning and Remedy
L+24	N is negative. After pressing the START button, the accumulator is cleared, and control returns directly to the main program.

***n*-TH ROOT — B4-11.0**

PURPOSE

B4-11.0 calculates the n -th root of any non-negative value. The exponent n must be an integer such that $2 \leq n \leq 20$. The results are calculated using an iterative method according to the formula:

$$y_{i+1} = y_i + \frac{1}{n} \left(\frac{A}{y_i^{n-1}} - y_i \right) \quad (6)$$

where y_i represents the i -th approximation of the root.

B4-11.0 uses a calling sequence similar to 4, except it has only one secondary parameter. The number A whose root is to be taken is loaded into the accumulator with an appropriate scale factor (see below), and the degree of the root n is stored in a Z instruction following the R that calls the subroutine. On return to the main program, the desired root resides in the accumulator at q/n .

STORAGE REQUIREMENTS

Program Space: 1 track (64 words)

Temporary Storage: Sectors 01, 02, 04, 05, 44, 53, 54, and 60 of track 63.

INPUT

The input variables for B4-11.0 are A , the non-negative value whose root is to be calculated, and n , the integer specifying the degree of the root ($2 \leq n \leq 20$).

Upon branching to the subroutine, A must reside in the accumulator scaled to a q factor that is exactly divisible by n .¹²

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	A	Bring A into accumulator at a q divisible by n .
α	R	L+16	Store the parameter address in the subroutine.
$\alpha + 1$	U	L	Unconditional branch to the subroutine entry.
$\alpha + 2$	Z	08nn	Parameter n encoded as a decimal sector address.

¹²This is similar to the requirement that a number whose square root is being taken is divisible by two; however, n only needs to divide A 's q factor exactly to be acceptable. As an example, if we had A at $q = 12$, then the square, cube, fourth, and sixth roots of A could all be taken, as all are even divisors of 12.

The instruction at location $\alpha - 1$ brings the value A into the accumulator at a q factor that is divisible by n . (Any instruction sequence that achieves this result is permissible.)

The instruction at location α stores the address $(\alpha + 2)$ containing the parameter instruction for n within the subroutine, and execution resumes at $\alpha + 3$.¹³

OUTPUT

Upon the return branch to the main program, the n -th root of the argument resides in the accumulator scaled to a q factor of q_A/n . For example, if $n = 3$ and $q_A = 12$, the result $\sqrt[3]{A}$ will have $q = 4$.

OPERATING DETAILS

1. Accuracy:

The result is guaranteed accurate to eight decimal places.

2. Execution time:

Between 2 and 60 seconds. Execution times are significantly longer when calculating high-degree roots of small values.

3. Required input/output devices:

None.

4. Overflow:

Overflow is ignored upon entry and is not reset upon exit.

5. Error stops:

Memory Location	Meaning and Remedy
L+61	The requested root is an imaginary value (i.e., an even-degree root of a negative number). Pressing the START button clears the accumulator and returns execution directly to the main program.

¹³The subroutine takes the parameter address supplied via the R instruction, recalculates the return address, and adjusts its own code to properly return.

6 Matrix Operations

MATRIX PROGRAMS 1 — D1-10.0

D1-10.0 is a collection of five routines, all of which utilize the Floating-Point Interpretive System 1 (H1-11.0). This suite consists of the following programs:

Program	SC Number	Title
D1-11.0	2044	Matrix Inversion 1
D1-12.0	2045	Matrix-Vector Multiplication 1
D1-13.0	2046	Matrix Multiplication 1
D1-14.0	2047	Matrix Addition/Subtraction 1
D1-15.0	2048	Matrix Transposition 1

TRANSLATOR NOTE

Floating-Point Interpreter 1 (H1-11.0, Section 7) provides a software floating-point implementation for the LGP-21, and is used extensively in the matrix routines.

MATRIX INVERSION 1 — D1-11.0

PURPOSE

D1-11.0 inverts a square matrix in place, using the Floating-Point Interpretive System 1 (H1-11.0) for its arithmetic. The matrix must be square, non-singular, of rank greater than 1, and stored in floating-point format; it can be as large as available memory allows.

Matrix Inversion 1 is called as a subroutine. Before the call you must exit the Interpretive System (with an E instruction) and patch the interpreter's starting address into the subroutine; the calling sequence then supplies the matrix's rank and starting address. On return, the inverse has replaced the original matrix in memory.

STORAGE REQUIREMENTS

Program Storage: 2 tracks (128 words)

Temporary Storage: None

INPUT

The input is the N^2 elements of an $N \times N$ matrix in floating-point format, stored row-major (so the first element of row 2 immediately follows the last element of row 1). The matrix must be non-singular.

The subroutine needs an extra column of scratch space, so reserve a contiguous block of $N^2 + N$ locations starting at base address M even though only N^2 holds the matrix itself.¹⁴

Before calling the subroutine, the starting address of the Interpretive System (see Section 6) must be stored at **L+163**, where L is the base address of the matrix-inversion code. The operator can do this by hand right after loading the tape, or the main program can do it as part of its setup.

CALLING SEQUENCE

The calling sequence must provide the following parameters:

1. N : The rank (dimension) of the matrix, scaled at $q = 1$, with $N > 1$.
2. M : The starting memory address of the matrix, specified in decimal track/sector notation.

Both parameters N and M are packed into a single parameter word. If N is greater than 15, the packed configuration requires hexadecimal entry format.

The E at $\alpha - 1$ is only needed if the preceding main-program instruction was an interpretive pseudo-instruction; otherwise it can be omitted. The rest of the

¹⁴The matrix inversion is implemented using a Gauss-Jordan elimination algorithm that requires a one-column working vector to track pivoting operations and column swaps as it performs the inversion in-place.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	E	0000	Exit from the Interpretive System.
α	R	L+14	Modify subroutine instruction with key word address.
$\alpha + 1$	U	L	Unconditional branch to subroutine entry.
$\alpha + 2$	...	...	Packed parameter word: N at $q = 15$ and M at $q = 29$. ¹⁵
$\alpha + 3$	—	—	Return to main program.

sequence is the standard R/U call described in Section 2.2.2, with the packed parameter word at $\alpha + 2$ holding N at $q = 15$ and M at $q = 29$.

OUTPUT

The inverse B replaces the original matrix in memory: N^2 row-major elements starting at M , same layout as the input.

OPERATING DETAILS

1. Program Input:

The subroutine tape is provided in two distribution formats:

- a) arbitrarily relocatable, hexadecimal format, compatible with J1-10.0; and
- b) arbitrarily relocatable, decimal coding sheet format.

2. Required Input/Output Units:

None.

3. Overflow:

Overflow does not disrupt the entry phase and is not reset upon subroutine exit.

4. Error Stops:

Memory Location	Meaning and Remedy
L+759	The matrix is singular. Mathematical inversion is impossible. Execution stops; do not attempt to bypass or resume.

REMARK

The subroutine exits the Interpretive System on its own before returning, so control comes back to the main program in native (fixed-point) mode.

TRANSLATOR'S NOTES

Gauss-Jordan elimination is probably the most sophisticated algorithm usable for this purpose on the LGP-21, but it has some pitfalls. Because it performs a larger total number of arithmetic operations than, say, Gaussian elimination with back-substitution, it is even more vulnerable to subtractive cancellation and catastrophic loss of significance.

Subtractive cancellation occurs when you subtract two nearly identical numbers. The leading bits, which match, cancel each other out and leave zeros.

For instance, consider two numbers that match out to 25 bits:

$$\begin{array}{r} 1.0110110110110110110110110 \quad 101 \quad \times 2^e \\ 1.0110110110110110110110110 \quad 011 \quad \times 2^e \\ \hline 0.0000000000000000000000000 \quad 010 \quad \times 2^e \end{array}$$

After the subtraction, the only remaining non-zero significant bits are the last two. The floating-point interpreter will normalize this result by shifting it left, which shifts in zeroes from the right side of the word. Because the original numbers only had 30 bits of precision, those newly-added lower bits are *garbage*! You now have a value where the error is as large as the signal itself.

In a classic Gauss-Jordan implementation, you aren't just clearing elements below the pivot; you are simultaneously clearing elements *above* the pivot to force the left side of the matrix to be a pure identity matrix. This requires roughly $\frac{n^3}{2}$ multiplications and subtractions compared to the $\frac{n^3}{3}$ required by Gaussian elimination. Every extra row operation is another opportunity for subtractive cancellation to add errors to your data.

If a pivot element becomes very small (usually due to an earlier subtractive cancellation), dividing the rest of the row by that tiny pivot scales up any existing truncation errors dramatically. When that row is subsequently subtracted from all the other rows, that amplified noise propagates through the entire matrix.

Matrix Inversion 1 (Section 6) uses a couple of techniques to help prevent this:

- **Partial Pivoting:** The routine scans down the current column to find the element with the largest absolute magnitude and swaps that row to the pivot position. This ensures that you are always dividing by the largest possible number, keeping the multipliers less than or equal to 1.0, which drastically decreases error amplification.
- **The L+759 Hard Stop:** If the largest available pivot is zero (or dangerously close to it under the interpreter's precision bounds), the routine

realizes that it has hit a singular or ill-conditioned matrix where subtractive cancellation has wiped out all meaningful data. Rather than returning a useless result, it hits the brakes and halts.

MATRIX-VECTOR MULTIPLICATION 1 — D1-12.0

PURPOSE

D1-12.0 multiplies a matrix by a column vector using the Floating-Point Interpretive System 1 (Section 7), storing the product vector at a specified address. The matrix has i rows and j columns (each less than 64; the matrix doesn't have to be square); the column vector has j elements. All data is in floating-point format, and the total of matrix, vector, and product elements must fit in available memory.

Matrix-Vector Multiplication 1 is called as a subroutine. The Interpretive System must already be loaded; exit it (with an E instruction) before the call. The calling sequence supplies the interpreter's starting address, the matrix's dimensions and starting address, and the starting addresses of the input vector and the output product vector. On return, the product vector occupies the specified locations.

STORAGE REQUIREMENTS

Program Storage: 1 track, 32 sectors (96 words)

Temporary Storage: None

INPUT

The inputs are:

1. an $i \times j$ matrix in row-major order (i and $j < 64$, not necessarily equal),
2. a column vector of j elements in consecutive locations.

Both must be in Floating-Point Interpretive System 1 format. The matrix, input vector, and output vector together must fit in available memory.

CALLING SEQUENCE

The calling sequence supplies, in order: the Interpretive System's starting address F , the matrix's starting address M , the matrix's dimensions (row count i as the track part, column count j as the sector part of a single address), the column vector's starting address V , and the destination address P for the product vector. All addresses are in decimal track/sector notation. A sample calling sequence (with L the subroutine's base address) is shown below.

The E at $\alpha - 1$ is only needed if the preceding main-program instruction was an interpretive pseudo-instruction. The rest is the standard inlined-parameter call described in Section 2.2.2; locations $\alpha + 2$ through $\alpha + 6$ are the parameter list, and $\alpha + 7$ is where execution resumes after the call.

OUTPUT

The product vector is written to consecutive locations starting at P .

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	XE	0000	Exit from the Interpretive System.
α	R	L_0	Store the Interpretive System entry address in subroutine.
$\alpha + 1$	U	L_0	Unconditional branch to subroutine entry.
$\alpha + 2$	Z	F_0	Starting address of the Interpretive System.
$\alpha + 3$	Z	M	Starting address of the matrix.
$\alpha + 4$	Z	ii jj	Matrix dimensions: rows (ii) and columns (jj).
$\alpha + 5$	Z	V	Starting address of the column vector.
$\alpha + 6$	Z	P	Starting address of the destination product vector.
$\alpha + 7$	—	—	Return to main program.

OPERATING DETAILS

1. Program Input:

The subroutine tape is distributed in two formats:

- a) arbitrarily relocatable, hexadecimal format, compatible with J1-10.0;
and
- b) arbitrarily relocatable, decimal coding sheet format.

2. Required Input/Output Units:

None.

3. Overflow:

Overflow is ignored during the execution initialization phase and is not reset upon subroutine exit.

NOTES

The subroutine exits the Interpretive System on its own before returning, so control comes back to the main program in native (fixed-point) mode.

TRANSLATOR'S NOTE

This is the first function to use the extended calling sequence that looks like this, documented at Section 2.2.2.

Speculating slightly, because I have not seen/dumped the code in question, this is my best guess on how it works.

- The **R** instruction in the main program stores the return address ($\alpha + 2$) into L_0 . Note that the current address $+ 2$ is the start of the parameter list to be passed to the subroutine.
- The **U** instruction at $\alpha + 1$ jumps to L_0 .
- A **B** instruction at L_0 loads $\alpha + 2$, the parameter list's address into the accumulator.
- The subroutine adds 5 to the accumulator to get the actual return address (the word following the parameter list).
- The subroutine then stores the return address into a **U** instruction that it will use for the return to the main program.

This lets the **B** instruction at L_0 do double duty: it both stashes the parameter-list address (which the subroutine treats as a stand-in for the return address) and loads that address into the accumulator so the subroutine can compute the real return point.

MATRIX MULTIPLICATION 1 — D1-13.0

PURPOSE

D1-13.0 computes the matrix product $C = AB$ using the Floating-Point Interpretive System 1 (H1-11.0), where A is $n \times m$, B is $m \times p$, and C is $n \times p$. All inputs are in floating-point format. The matrix dimensions must each be less than 64.¹⁶ The total of all elements of A , B , and C must fit in available memory.

Matrix Multiplication 1 is called as a subroutine. Exit the Interpretive System (with an E instruction) before the call. The calling sequence supplies the interpreter's starting address, the dimensions and starting addresses of A and B , and the starting address of C . On return, the product matrix occupies the destination locations.

STORAGE REQUIREMENTS

Program Storage: 2 tracks, 50 sectors (178 words)

Temporary Storage: None

INPUT

The inputs are matrix A ($n \times m$) and matrix B ($m \times p$), both in row-major order, both in Floating-Point Interpretive System 1 format (Section 7). The two matrices plus the destination C require $(n \times m) + (m \times p) + (n \times p)$ contiguous locations of memory in total.

CALLING SEQUENCE

The calling sequence supplies, in order: the Interpretive System's starting address F , the starting address of matrix A , the dimensions of A (rows n as the track part, columns m as the sector part), the starting address of matrix B , the dimensions of B (rows m as the track part, columns p as the sector part), and the starting address of the destination matrix C . All addresses are in decimal track/sector notation. A template calling sequence (with L_0 the subroutine's base address) is shown below.

The E at $\alpha - 1$ is only needed if the preceding main-program instruction was an interpretive pseudo-instruction.

OUTPUT

C is written in row-major order to consecutive locations starting at C , $n \times p$ elements total.

¹⁶**Translator's note:** The limit of 64 is an architectural artifact of the LGP-21's memory, which is physically structured as 64 tracks of 64 sectors each. Capping dimensions at 64 allows index calculation loops to stay bound within simple track-selection logic without risking multi-track pointer overflow.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	E	0000	Exit from the Interpretive System.
α	R	L_0	Store parameter keyword tracking address in subroutine. ¹⁷
$\alpha + 1$	U	L_0	Unconditional branch to subroutine entry.
$\alpha + 2$	Z	F_0	Starting address of the Interpretive System.
$\alpha + 3$	Z	A	Starting address of matrix A .
$\alpha + 4$	Z	nnmm	Dimensions of matrix A : rows (nn) and columns (mm).
$\alpha + 5$	Z	B	Starting address of matrix B .
$\alpha + 6$	Z	mmpp	Dimensions of matrix B : rows (mm) and columns (pp).
$\alpha + 7$	Z	C	Starting address of destination product matrix C .
$\alpha + 8$	—	—	Return to main program (execution resumes here).

OPERATING DETAILS

1. Program Input:

The subroutine tape is distributed in two formats:

- a) arbitrarily relocatable, hexadecimal format, compatible with J1-10.0;
and
- b) arbitrarily relocatable, decimal coding sheet format.

2. Required Input/Output Units:

None.

3. Overflow:

Overflow is ignored during the entry configuration phase and is not reset upon subroutine exit.

4. Error Stops:

Memory Location	Meaning and Remedy
L+241	Inner matrix dimensions mismatch: the number of columns in matrix A (m) does not equal the number of rows in matrix B (m). Mathematical multiplication is undefined. Do not attempt to resume execution; the input data dimensions must be corrected.

NOTES

The subroutine exits the Interpretive System on its own before returning, so control comes back to the main program in native (fixed-point) mode.

MATRIX ADDITION AND SUBTRACTION 1 — D1-14.0

PURPOSE

D1-14.0 adds or subtracts two $i \times j$ matrices A and B using the Floating-Point Interpretive System 1 (H1-11.0), storing the result in a third memory area. The matrices don't need to be square; i and j must each be less than 64. The two inputs and the destination must all fit in available memory.

Matrix Addition and Subtraction 1 is called as a subroutine. Exit the Interpretive System (with an E instruction) before the call. The calling sequence supplies the interpreter's starting address, the matrix dimensions and starting addresses, the desired operation (add or subtract), and the destination address. On return, the result occupies the destination.

STORAGE REQUIREMENTS

Program Space: 1 track (64 words)

Temporary Storage: None

INPUT

The inputs are matrices A and B , both $i \times j$ and in identical layouts — both row-major or both column-major.¹⁸ Both must be in Floating-Point Interpretive System 1 format, with i and j each less than 64. The matrices and the destination together require $3(ij)$ locations of memory in total.

CALLING SEQUENCE

The calling sequence supplies, in order: the Interpretive System's starting address F_0 , the starting address of matrix A , the matrix dimensions (rows i as the track part, columns j as the sector part), the operation word — an A or S opcode with B 's starting address as its operand¹⁹ — and the destination address C . All addresses are in decimal track/sector notation. A template calling sequence (with L_0 the subroutine's base address) is shown below.

The E at $\alpha - 1$ is only needed if the preceding main-program instruction was an interpretive pseudo-instruction.

¹⁸This is significantly more flexible than the Matrix Multiplication routine (D1-13.0). Because addition and subtraction are purely element-by-element operations, the subroutine doesn't actually care about row vs. column orientation, as long as both inputs share the exact same structure. The execution loop simply scans linearly across both matrices.

¹⁹Another memory-saving optimization: instead of wasting an entire word on an operation flag or setting up a parsing branch, the subroutine reads this parameter word at $\alpha + 5$ and injects it directly into its internal math loop as an executable instruction; the address of the second matrix B is *also* packed into this instruction; the instruction (A for Add, S for Subtract) is executed dynamically against the current matrix address via self-modifying code.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	E	0000	Exit from the Interpretive System.
α	R	L_0	Store parameter tracking address in the subroutine.
$\alpha + 1$	U	L_0	Unconditional branch to subroutine entry.
$\alpha + 2$	Z	F_0	Starting address of the Interpretive System.
$\alpha + 3$	Z	A	Starting address of matrix A .
$\alpha + 4$	Z	ii jj	Dimensions of the matrices: rows (ii) and columns (jj).
$\alpha + 5$	A/S	B	Operation (A or S) and starting address of matrix B .
$\alpha + 6$	Z	C	Starting address of destination area for the resulting matrix.
$\alpha + 7$	—	—	Return to main program (execution resumes here).

OUTPUT

The result is written in floating-point format to consecutive locations starting at C , ij elements total.

OPERATING DETAILS

1. Program Input:

The subroutine tape is distributed in two formats:

- a) arbitrarily relocatable, hexadecimal format, compatible with J1-10.0; and
- b) arbitrarily relocatable, decimal coding sheet format.

2. Required Input/Output Units:

None.

3. Overflow:

Overflow is ignored during the entry initialization phase and is not reset upon subroutine exit.

REMARKS

The subroutine exits the Interpretive System on its own before returning, so control comes back to the main program in native (fixed-point) mode.

The destination can be matrix A , matrix B , or a separate region. If you use a separate region, its memory range must not overlap with A or B .

MATRIX TRANSPOSITION 1 — D1-15.0

PURPOSE

D1-15.0 transposes a square matrix in memory, writing the result to a destination address (which may be the same as the source). The matrix's rank must be less than 32. Both fixed-point and floating-point formats are supported. The matrix and (if separate) the destination together must fit in available memory.

Matrix Transposition 1 is called as a subroutine. Exit the Interpretive System (with an E instruction) before the call. The calling sequence supplies the matrix's rank and starting address and the destination address. On return, the transposed matrix occupies the destination.

STORAGE REQUIREMENTS

Program Space: 1 track, 58 sectors (122 words)

Temporary Storage: None

INPUT

The input is the elements of a square matrix in consecutive locations, either row-major or column-major. The data can be in raw fixed-point fractional format or in Floating-Point Interpretive System 1 format (H1-11.0). The rank N must satisfy $2 < N \leq 31$. The matrix takes N^2 locations; if the destination is separate, total memory required is $2N^2$.

CALLING SEQUENCE

The calling sequence supplies, in order: the matrix's rank N (at $q = 15$) and starting address M — packed into a single parameter word at $\alpha + 2$, requiring hexadecimal entry if $N > 15$ — and the destination address T . All addresses are in decimal track/sector notation. T may equal M (in-place transposition); otherwise, the destination region must not overlap the source. A template calling sequence (with L the subroutine's base address) is shown below.

The E at $\alpha - 1$ is only needed if the preceding main-program instruction was an interpretive pseudo-instruction.

OUTPUT

The transposed matrix is written to consecutive locations starting at T , in the same row/column orientation as the input (so a row-major input produces a row-major output of the transpose, and likewise for column-major).

OPERATING DETAILS

1. Program Input:

The subroutine tape is distributed in two formats:

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	E	0000	Exit from the Interpretive System.
α	R	L	Store the parameter key-word tracking address in the subroutine.
$\alpha + 1$	U	L	Unconditional branch to subroutine entry.
$\alpha + 2$	...	...	Packed parameter word: N at $q = 15$ and M at $q = 29$.
$\alpha + 3$	Z	T	Starting address for the transposed matrix.
$\alpha + 4$	—	—	Return to main program (execution resumes here).

a) arbitrarily relocatable, hexadecimal format, compatible with J1-10.0;
and

b) arbitrarily relocatable, decimal coding sheet format.

2. Required Input/Output Units:

None.

3. Overflow:

Overflow is ignored during the execution initialization phase and is not reset upon subroutine exit.

REMARK

Unlike the other routines in the matrix suite, this subroutine *does not* invoke or use the Floating-Point Interpretive System internally.²⁰

²⁰Because matrix transposition is a purely structural index manipulation (swapping element positions (i, j) with (j, i)), the subroutine does not perform any actual arithmetic on the matrix values themselves, so it's completely unnecessary to incur the massive overhead of the floating-point interpreter H1-11.0. We're just moving data, so it doesn't matter if it's native fixed-point integers or multi-word floating-point interpreter variables.

COMPLEX OPERATIONS INTERPRETIVE SYSTEM — H1-10.0

PURPOSE

H1-10.0 is a fixed-point interpreter that lets you write code with complex numbers ($a + bi$) as if they were ordinary reals. It also provides left and right bit-shifting, address-register arithmetic, and a loop-end comparison — all without leaving the interpreter loop.

STORAGE REQUIREMENTS

Program Space: 3 tracks (192 words)

Temporary Storage: None

INPUT

A complex number occupies two consecutive locations at the same q factor: the real part at **ttss** and the imaginary part at **ttss+1**.

Because complex values are two words wide, the interpreter keeps its working registers in memory rather than in the hardware accumulator: a pseudo-accumulator at **L+33**, an address register at **L+219**, and a saved copy of the hardware accumulator at **L+59** (where **L** is the interpreter's base address).

The interpreter has 15 instructions, listed below. For arithmetic instructions, the address field **ttss** points at the real component and the interpreter operates on both halves automatically. For other instructions, **ttss** is a single-word address. Only the instructions listed below are valid inside an interpretive sequence.

1. Arithmetic Instructions

Bttss (Bring): Load **ttss/ttss+1** into the pseudo-accumulator.

Attss (Add): Add **ttss/ttss+1** to the pseudo-accumulator.

Sttss (Subtract): Subtract **ttss/ttss+1** from the pseudo-accumulator.

Mttss (Multiply): Multiply the pseudo-accumulator by **ttss/ttss+1**.²¹

Dttss (Divide): Divide the pseudo-accumulator by **ttss/ttss+1**.

Httss (Hold): Store the pseudo-accumulator into **ttss/ttss+1** (the pseudo-accumulator is unchanged).

Cttss (Clear): Store the pseudo-accumulator into **ttss/ttss+1**, then zero the pseudo-accumulator.

²¹**Translator's note:** A complex multiplication $(a + bi)(c + di)$ requires computing $(ac - bd) + (ad + bc)i$. Performing this in a single interpretive step saves a massive amount of main-program setup and temporary storage management.

2. Auxiliary Instructions

XR00nn (Shift Right): Shift both halves of the pseudo-accumulator right by nn bits ($0 \leq nn \leq 10$).

XP00nn (Shift Left): Shift both halves of the pseudo-accumulator left by nn bits ($0 \leq nn \leq 10$).

Uttss (Unconditional Jump): Jump to the pseudo-instruction at **ttss**. Can't be used to exit the interpreter — **ttss** must point at another interpreter instruction.

XE0000 (Exit): Leave the interpreter. The next word is executed as a native hardware instruction.

3. Address Modification Instructions

Ettss (Set Address Register): Load the address field of the word at **ttss** into the address register.

Ittss (Increment Address): Add the value **ttss** to the address register.

Yttss (Inject Address): Write the address register's value into the address field of the word at **ttss**.

Zttss (Test and Skip): If **ttss** equals the address register, skip the next pseudo-instruction; otherwise continue with the next instruction.

CALLING SEQUENCE

The calling sequence enters the interpreter using the standard **R/U** pair; **L** is the interpreter's base address. The **R** at α stashes the address of the first pseudo-instruction ($\alpha + 2$) inside the interpreter so it knows where to start fetching, and the **U** at $\alpha + 1$ branches into the interpreter. An **XE** somewhere in the pseudo-instruction sequence exits back to native execution.

OPERATING DETAILS

1. Execution Time Maximum execution time per instruction, in drum rotations and milliseconds.²²

²²Notice how left-shifting (the **P** instruction) is significantly slower than right-shifting (**R**). On a magnetic disk memory system like the LGP-21, bit-shifting requires track-recirculation delays and masking. Left shifts require repeated additions or multiplication loops to slide data up toward the sign bit, adding extra revolutions, whereas right shifts could take advantage of standard hardware truncation.

Memory Location	Instruction	Address	Meaning
α	R	L	Store parameter tracking address inside the interpreter.
$\alpha + 1$	U	L	Unconditional branch to interpreter entry.
$\alpha + 2$	...	...	First complex pseudo-instruction to be interpreted.
$\vdots$	$\vdots$	$\vdots$	Sequence of complex operations.
$\alpha + n$	XE	0000	Exit from the Interpretive System.
$\alpha + n + 1$	...	...	First native hardware instruction (execution resumes here).

Instruction	Rotations	Time (ms)	Instruction	Rotations	Time (ms)
B	11	561	P	17	1167
A	14	714	U	8	408
S	14	714	XE (Exit)	6	306
M	22	1122	E (Set Addr)	9	459
D	41	2091	I	6	306
H	14	714	Y	8	408
C	14	714	Z (= 0)	11	561
R (Shift R)	14	714	Z ($\neq$ 0)	13	663

- 2. Program Input:** The subroutine tape is distributed in two formats:
- a) arbitrarily relocatable, hexadecimal format, compatible with J1-10.0; and
 - b) arbitrarily relocatable, decimal coding sheet format.

3. Required Input/Output Units: None.

4. Error Stops:

Location	Meaning	Remedy
L+122	Negative Instruction encountered (Illegal format).	Fatal error.
L+135	Invalid N- Type instruction variation.	Fatal error.
L+154	Invalid T- Type instruction variation.	Fatal error.

5. Overflow: Overflow status is ignored during interpretive entry execution loops and is not explicitly reset upon subroutine exit.

REMARKS

The first instruction at $\alpha + 2$ must not be an **XE0000** — the interpreter would exit immediately before doing anything useful.

TRANSLATOR NOTES

The address-arithmetic pseudoinstructions (**E**, **I**, **Y**, **Z**) make this more than just a complex-math library — they let a program walk through multi-element arrays of complex numbers without ever leaving the interpreter loop.

7 Floating-Point Interpretive Systems

FLOATING POINT INTERPRETER 1 — H1-11.0

PURPOSE

Floating-Point Interpretive System 1 is a 33-instruction interpreter that lets you write floating-point code on the LGP-21 without managing scale factors by hand. Inputs and outputs are 7-digit decimal mantissas with a separate power-of-10 exponent; the interpreter handles the binary mantissa/exponent split internally.

Each number is packed into one machine word in memory. While the interpreter is operating on a number it unpacks it into two words — one for the mantissa, one for the exponent — so the hardware can do ordinary signed arithmetic on each half. The exact bit layout is given under “Internal Number Format” below.

The interpreter is bundled with transcendental subroutines (data input/output, sin/cos, arctan, log, exp, sqrt) that are called as interpreter instructions, not as B/R/U calls — once you’re inside the interpreter loop, those operations are part of the instruction set. The interpreter engine itself and the companion fixed-point/floating-point conversion routine (I3-12.0) are entered with a normal machine calling sequence.

INTERNAL NUMBER FORMAT

Each floating-point number is packed into a single word. The word holds two independent signed numbers: a mantissa M and an exponent E , representing the value

$$Z = M \cdot 2^E$$

The mantissa is a sign bit followed by 24 bits of magnitude, treated as a fraction at $q = 0$. Mantissas are always stored normalized, so the leading magnitude bit has the place value 2^{-1} . The exponent is a sign bit followed by 5 bits of magnitude, treated as an integer at $q = 30$. Negative values in either field are stored in two’s complement of the magnitude bits, with the two fields complemented independently — so a negative mantissa and a positive exponent can sit in the same word without interfering.

That accounts for 31 of the LGP-21’s 32 bits per word; the remaining bit is unused.

Translator’s note: transcription errors in the worked examples The three worked examples below are transcribed from the original manual, but the bit patterns don’t round-trip to the stated decimal values under the field layout described above. The +3.75 pattern has 011111 at the top of the word, which gives a 24-bit mantissa magnitude of 0.96875 rather than 0.9375. The +0.46875 pattern has the same problem. The −3.75 pattern’s mantissa bits don’t reconstruct 0.9375 under either one’s or two’s complement.

3.75:

01111100000000000000000000000100

[illegible]

- 3.75:**

`1000100000000000000000000000000000000000000000000000000`

- 0.46875:**

01111100000000000000000001111110

- When a value is loaded into the floating-point accumulator or the multiplication register, it expands to two words — one for the mantissa, one for the exponent — with the mantissa shifted right by one bit (the “implicit shift” mentioned in the translator’s note above; it puts the leading magnitude bit at 2^{-2} instead of 2^{-1}). The mantissa and exponent are still paired as one logical value.

The interpreter provides four registers: a floating-point accumulator, a multiplication register, an address register, and an instruction counter. The accumulator and multiplication register each occupy two words (mantissa + exponent); the address and instruction-counter registers occupy one word each.

53

1. Floating-Point Accumulator. Holds intermediate calculation results. Mantissa at $q = 0$ (shifted right by one bit as described above), exponent at $q = 30$, each with its own sign. Modified by arithmetic operations, function evaluations, and the Clear, Swap, and Set Sign instructions.

2. Multiplication Register (M -register). Holds the multiplicand for the Multiply and Cumulative Multiplication instructions. Same internal layout as the accumulator. Modified only by the Set and Swap instructions.

3. Address Register. A single word holding a track/sector value at $q = 29$. Used by the Store Address instruction to patch the operand field of an instruction in memory, and by the Test for Zero branch. Modified only by Set Address and Increment Address.

4. Instruction Counter. Holds the address of the currently-executing interpreter instruction, and points at the next instruction to fetch. Initialized by the main program's calling sequence on entry, and incremented by one per instruction. Jump instructions overwrite it with a new target; the Return instruction stores its current value plus 2 into the operand field of its target location.

FLOATING-POINT INSTRUCTIONS

The interpreter has 33 pseudo-instructions. Each is a single word with an opcode and an operand address. In the descriptions below, **ttss** is an operand address in decimal track/sector format; instructions with operand 0000 have a special meaning (typically a register-only operation or a function call). All instructions run to completion without leaving the interpreter.

1. Arithmetic Instructions

B ttss (Bring): Load **ttss** into the accumulator.

A ttss (Add): Add **ttss** to the accumulator.

S ttss (Subtract): Subtract **ttss** from the accumulator.

D ttss (Divide): Divide the accumulator by **ttss**.

P ttss (Set M-Register): Load **ttss** into the M -register.

M ttss (Multiply): Multiply the M -register by **ttss**; the product replaces the accumulator. M -register is unchanged.

N ttss (Cumulative Multiplication): Multiply the M -register by **ttss** and add the product to the accumulator. M -register is unchanged.

D 000y (Shift Right): Divide the accumulator by 2^y ($0 \leq y \leq 9$).

M 000y (Shift Left): Multiply the accumulator by 2^y ($0 \leq y \leq 9$).

H ttss (Hold): Store the accumulator into **ttss**. Accumulator is unchanged.

C ttss (Clear): Store the accumulator into **ttss**, then zero the accumulator.

2. Jump / Branch Instructions

U ttss (Unconditional Jump): Jump to **ttss**. Can't exit the interpreter — **ttss** must point at another interpreter instruction.

T ttss (Test for Minus): Jump to **ttss** if the accumulator is negative; otherwise fall through. Same restriction.

800T ttss (Conditional Jump): Jump to **ttss** if the accumulator is negative *or* if Program Selector Switch 7 (PST) is ON. Same restriction.

3. Address Modification Instructions

E ttss (Set Address): Load the address field of the word at **ttss** into the address register.

I ttss (Increment Address): Add **ttss** to the address register. Subtraction works by supplying the two's complement.

Y ttss (Store Address): Write the address register into the address field of the word at **ttss** (other fields of **ttss** and the address register itself are unchanged).

Z ttss (Test for Zero): If **ttss** equals the address register, skip the next instruction; otherwise fall through.

R ttss (Return): Write (instruction counter + 2) into the address field of the word at **ttss**.

4. Auxiliary Instructions

The operand address field for all auxiliary commands must be exactly zero (0000).

U 0000 (Swap): Swap the *M*-register and the accumulator.

B 0000 (Set Plus Sign): Make the accumulator positive ($|x|$). No-op if already non-negative.

T 0000 (Set Minus Sign): Make the accumulator negative ($-|x|$). No-op if already negative.

Y 0000 (Invert Sign): Negate the accumulator.

Z 0000 (Stop): Halt execution. Pressing *Start* resumes at the next instruction. Skipped if Break Point Switch 16 (PS-16) is ON.

E 0000 (Exit): Leave the interpreter. The next word is executed as a native machine instruction.

5. Input / Output Instructions

The operand address field for all I/O commands must be exactly zero (0000).

I 0000 (Input): Read a block of decimal numbers from tape, convert to floating-point, and store them in sequential locations. The destination address is taken from the tape's leader.

P 0000 (Output): Print the accumulator on the output device in floating-point notation. Accumulator is unchanged.

6. Transcendental Function Evaluation Instructions

The operand address field for all function evaluations must be exactly zero (0000).

R 0000 (Square Root): Replace the accumulator with $\sqrt{x}$.

S 0000 (Sine): Replace the accumulator with $\sin x$ (x in radians).

C 0000 (Cosine): Replace the accumulator with $\cos x$ (x in radians).

A 0000 (Arctangent): Replace the accumulator with the principal value of $\arctan x$ (result in radians).

N 0000 (Natural Logarithm): Replace the accumulator with $\ln x$.

H 0000 (Exponential Function): Replace the accumulator with e^x .

Data Input and Output 1

Data Input

Data Input and Output 1 reads decimal numbers from tape, converts them to floating-point, and stores them in the locations you specify. It's invoked from inside the interpreter loop with an I 0000 pseudo-instruction, and returns control to the instruction following the I 0000 once all data has been read.

The input tape is structured as follows.

- a) **Input Keyword (Control Word).** Each group of data starts with a control word: a signed two-digit decimal place count P ($-03 \leq P \leq +16$) and the destination's starting address **ttss** in decimal track/sector notation. A positive P shifts the decimal point left when the value is converted; a negative P shifts it right.
- b) **Numeric Data Elements.** Each value is a signed decimal integer of up to 7 digits. Positive values may omit the plus sign and leading zeros; negative values must include all leading zeros between the minus sign and the first significant digit. A value of zero is just a single stop code (').

Example: with the control word +032400', the value **16.192** is punched as 16192'.²³

- c) **End-of-Block Marker.** A minus-zero word (-0000000') marks the end of a group; it's not stored in memory, just consumed. The interpreter then expects another control word and starts a new group.

A minus-zero word followed by a second stop code (-0000000'') marks the end of the entire input. The subroutine prints a carriage return and returns to the interpreted program (the instruction following the I 0000 that called it).

The following example illustrates the physical layout of a typical structured data block:

Input control word			S t o	Decimal numbers with sign		S t o	
±	P	Location	p	±		p	CR
+	07	2004	,		1090000	,	☐
					120000	,	☒
					340000	,	☐
					560000	,	☒
					780000	,	☐
					900000	,	☒
+			,	—	0000000	,	☐
+	03	2010	,	—	4320001	,	☒
				—	0000021	,	☐
				—	3470	,	☒
				—		,	☐
					10	,	☒
				—	0000000	,	☐
						,	☒

Table 1: LGP-21 Floating Point Tape Input Example

The first six decimal numbers are read in and stored as follows:

²³**Translator's Note:** Because $P = +03$, the interpreter shifts the implied decimal point 3 places to the left upon ingestion, reconstructing $16192 \times 10^{-3} = 16.192$.

Memory Location	Contents
2004	109
2005	0.012
2006	0.034
2007	0.056
2008	0.078
2009	0.09

The second record group consisting of five data words would be stored as follows:

Memory Location	Contents
2010	−4320.001
2011	−0.021
2012	3.47
2013	0
2014	0.01

The minus-zero word ends each group; the double-stop code at the end ends the whole read. Mantissas are stored at $q = 0$ with 24 bits of precision, packed into the same word as their exponent (at $q = 30$).

2. Data Output

Data Input and Output 1 prints the accumulator as a signed 7-digit decimal mantissa followed by a signed 2-digit decimal exponent, then issues a tab and returns to the interpreted program (the instruction following the P 0000 that called it).

Output Format

.XXXXXXX± EE±

where .XXXXXXX± is the decimal mantissa with its trailing sign, and EE± is the power-of-10 exponent with its trailing sign.

Output Examples Sample printouts and their conventional decimal values:

Machine Printout	Conventional Representation
.5060000− 04	−5060.000
.0937500− 02−	−0.000937500
.1000000− 06−	−0.0000001000000
.1000000− 10	$−0.1 \times 10^{-10}$

SINE-COSINE 3 — B1-10.2

Returns $\sin x$ (via S0000) or $\cos x$ (via C0000) of the accumulator (in radians) in the accumulator.

ARCTANGENT 2 — B1-11.2

Returns $\arctan x$ of the accumulator in the accumulator (in radians).

LOGARITHM 2 — B3-11.1

Returns $\ln x$ (natural logarithm) of the accumulator in the accumulator.

EXPONENTIAL FUNCTION 2 — B3-10.1

Returns e^x of the accumulator in the accumulator.

SQUARE ROOT 2 — B4-10.1

Returns $\sqrt{x}$ of the (positive) accumulator in the accumulator.

CALLING SEQUENCE

Floating-Point Interpreter System 1 is invoked from the main program with the standard R/U calling sequence. The interpreter instructions follow immediately after the U, and an XE 0000 returns to native execution. L is the interpreter's base address.

Memory Location	Instruction	Address	Meaning
α	R	L_0	Store starting address of floating-point instructions.
$\alpha + 1$	U	L_0	Entry into the interpreter system.
$\alpha + 2$	$\langle \dots \rangle$		Floating-point instructions.
$\alpha + n$ $\alpha + n + 1$	$\langle \dots \rangle$ XE	0000	Exit from the interpreter system. Return to fixed-point instructions.

FIXED-POINT TO FLOATING-POINT CONVERSION (AND VICE VERSA) — L3-12.0

L3-12.0 converts a number between fixed-point and the floating-point format used by Floating-Point Interpreter System 1, in either direction. It's a stan-

alone fixed-point subroutine, not part of the interpreter itself, intended for moving data in or out of the interpreter's world.

Exit the interpreter before calling. Place the number in the hardware accumulator and pass the scale factor q in the calling sequence. The result comes back in the accumulator — floating-point if you converted forward, fixed-point at the given q if you converted back. One number per call.

Range limits: converting forward, the fixed-point number must not need an exponent greater than 31; converting back, the floating-point value must fit at the requested q .

Conversion to floating-point

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Load fixed-point number into accumulator.
α	R	$L + 25$	Store address of q .
$\alpha + 1$	U	L	Entry into the subroutine.
$\alpha + 2$	Z	$089q$	Specify q of the number.
$\alpha + 3$	etc.		Return to main program.

Conversion to fixed-point

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Load floating-point number into accumulator.
α	R	$L + 148$	Store address of q .
$\alpha + 1$	U	$L + 122$	Entry into the subroutine.
$\alpha + 2$	Z	$08qq$	Specify target q for the number.
$\alpha + 3$	etc.		Return to main program.

PROGRAM STOPS

L is the starting address of the subroutine.

REQUIRED INPUT/OUTPUT UNITS

None. The subroutine runs entirely from the accumulator and the calling sequence.

Memory Location	Meaning and Remedy
$L + 152$	The number is too large for the specified q during backward conversion. Pressing “Start” clears the accumulator and returns control to the main program.
$L + 262$	The number requires an exponent greater than 31 during forward conversion. Pressing “Start” clears the accumulator and returns control to the main program.

Floating-Point Interpreter System 1 — Memory Layout

The remainder of this section describes the floating-point system as a whole rather than L3-12.0 specifically: how it’s laid out in memory, how it’s loaded, and how it operates at runtime.

Memory Allocation

Only Square Root 2 is bundled into the interpreter core. The other subroutines are separate and can be loaded individually as needed. The table below gives each subroutine’s load address and size, with L the starting address of the interpreter core.

Subroutine	Initial Filler Keyword	Modifier Keyword	Memory Required
Interpreter System	L	L	10 Tracks
Data Input & Output 1	L+1000	L+1000	7 Tracks
Sine-Cosine 3	L+1700	L+1700	2 Tracks, 32 Sectors
Arctangent 2	L+1932	L+1932	1 Track, 32 Sectors
Logarithm 2	L+2100	L+2100	1 Track
Exponential Function 2	L+2200	L+2200	2 Tracks
Fixed/Floating Conversion & Vice Versa 1	<i>Anywhere</i>	<i>Anywhere</i>	3 Tracks

Track 63 is used as scratchpad memory by everything except L3-12.0, so no part of the system should be loaded into Track 63.

OPERATION

1. Program Input The system ships on two tapes: a relocatable hexadecimal tape compatible with Program Input 1 (J1-10.0), and a relocatable decimal coding-sheet tape. Both contain the interpreter core followed by the subroutines

in the order shown under Memory Allocation. Program Input 1 is assumed to start at address 0000.

On the hex tape, with PS-32 ON the computer reads continuously up to the Fixed-Point/Floating-Point Conversion routine. With PS-32 OFF it stops after each subroutine. There's no built-in stop between the interpreter core and Data Input and Output 1.

The decimal tape has built-in stops after the core and after each subroutine, regardless of PS-32.

The fixed/floating conversion routine must be loaded with a new modifier and a fresh device-selection keyword — never the same modifier as any other part of the system.

On any stop, press **Start**: with PS-32 OFF you return to Program Input 1 for the next entry; with PS-32 ON the computer halts on the next input command inside Program Input 1.

2. Required Input/Output Units The Flexowriter must be selected for both input and output operations.

Switch	Setting	Function
PS-16	ON	Suppresses the programmatic halt at a Z 0000 instruction.
	OFF	Permits a programmatic halt at a Z 0000 instruction.
PS-32	ON	Forces 800T (Conditional Jump) to branch unconditionally.
	OFF	800T behaves as a normal Test-for-Minus branch.

3. Program Selector Switches

4. Program Stops *L* represents the absolute starting address of the interpreter system.

REMARKS

The initial location of the interpreter system should ideally align with Sector 00 of a track so that the reference addresses targeting Track 63 are optimally mapped.

Remember that when the interpreter is running all instructions are pseudo-instructions! The interpreter is substituting itself for the standard fetch-execute cycle that the CPU would do. Another way of saying it is that the interpreter is an emulator for a CPU that has a floating-point instruction set, and we have an agreed-upon protocol to enter and exit emulation.

Pseudo-instructions whose operand addresses are between 0000 and 0009 have special meanings: rather than referring to those memory locations, they

Location	Meaning	Remedy
$L + 557$	Exponent too large for an H or C, or negative square-root argument. The offending instruction's address is in the accumulator.	Press <i>Start</i> to skip the instruction.
$L + 759$	Division by zero.	Don't proceed; correct the data.
$L + 1152$	Input value's exponent is too large.	Press <i>Start</i> to advance; zero is stored in place of the rejected value.
$L + 2005$	Natural log of a non-positive number.	Press <i>Start</i> to continue with a result of zero.
$L + 2056$	Natural log exponent too large.	Don't proceed; correct the data.

invoke interpreter functions (transcendentals, register operations, etc.). The interpreter has 16 such address-driven operations. The shift instructions D 000y and M 000y use y (1–9) as a shift count, not as a memory address, which means standard D ttss or M ttss instructions inside the interpreter cannot reference locations 0000–0009.

EXAMPLE

This example evaluates a fourth-degree polynomial $y = A_4x^4 + A_3x^3 + A_2x^2 + A_1x + A_0$ using Horner's method:

$$y = (((((A_4)x + A_3)x + A_2)x + A_1)x + A_0$$

Rather than unrolling the additions and multiplications, the program uses the interpreter's address-modification instructions (E, I, Y, Z) to step through the coefficients in a loop, patching the add-instruction's operand on each iteration to point at the next coefficient.

The interpreter core is loaded at 0300. The program loads at 4200; X-prefixed instructions are not relocated, others get 4200 added to their operand by the loader. Lines 00 and 01 are native code that enter the interpreter; from line 02 on, everything is an interpreter pseudo-instruction (until XE at 12 exits back to native, where 13 halts the machine in fixed-point mode).

The “Address contents” column annotates what the operand field will hold once any preceding patch instructions have run — it's reference annotation for someone hand-tracing the code, not part of the instruction encoding.

Loader directive	Loc	Op	Address contents	Comment
;0004200'				Block count: track 02, sector 00
/0004200'				Origin / relocation base 4200
	00	XR0300		Enter interpreter
	01	XU0300		
	02	XI0000		Read X and coefficients from tape
	03	E0017	4307	Load addr-reg from operand of 17
	04	Y0006	4307	Patch 06's operand to 4307
	05	B0013		Clear accumulator
	06	XA4307	a_n	Add next coefficient
	07	XI0001		Addr-reg $+= 1$
	08	Y0006	$a(4306 + n)$	Patch 06's operand to next coefficient
	09	XZ4312		Done if addr-reg = 4312
	10	U0014		Not done --- jump to multiply step
	11	XP0000		Print result
	12	XE0000		Exit interpreter
	13	XZ0000		Native stop
	14	XU0000		Swap accumulator and M-register
	15	XM4306		Multiply M-register by X
	16	U0006		Back to add next coefficient
	17	XZ4307		Data: initial coefficient address

Lines 14--16 are the loop continuation: when the address test at 09 fails, the program jumps to 14, swaps the accumulator and M-register, multiplies M by X (giving (partial sum)· x in the accumulator), and jumps back to 06 to add the next coefficient.

The input tape (in the format described under Data Input above) supplies X and the five coefficients:

```
+074306'+1090000'  X
      + 120000'     $A_0$ 
      + 340000'     $A_1$ 
      + 560000'     $A_2$ 
      + 780000'     $A_3$ 
      + 900000'     $A_4$ 
      -0000000'    end of group
      '            end of input
```

Translator's note: self-modifying code as the norm Even with the interpreter's address register, address-modifiable arithmetic on the LGP-21 still requires self-modifying instructions. Line 06's A operand starts as 4307 (loaded from line 17's data slot via the E at 03 and the Y at 04), and each pass through the loop overwrites that operand to the next coefficient's address. This is normal LGP-21 idiom; instructions are data, and you patch them constantly.

INSTRUCTION SUMMARY

Operational Notation Definitions

() Contents of location or register
→ Displaces / moves to / becomes
Acc Floating-Point Software Accumulator
A Reg. Address Register
M Reg. Multiplier Register
C Reg. Counter Register

Op	Operand (ttss)	Result / Action
B	ttss	(ttss) → Acc
A	ttss	(Acc) + (ttss) → Acc
S	ttss	(Acc) - (ttss) → Acc
D	ttss	(Acc) / (ttss) → Acc
P	ttss	(ttss) → M Reg.
M	ttss	(M Reg.) × (ttss) → Acc
N	ttss	(M Reg.) × (ttss) + (Acc) → Acc
H	ttss	(Acc) → ttss
C	ttss	(Acc) → ttss; then 0 → Acc
U	ttss	Unconditional Jump: Next instruction is at ttss
T	ttss	Conditional Jump: Jump to ttss if (Acc) < 0
800T	ttss	Conditional Jump: Jump to ttss if (Acc) < 0 or if PST is ON
E	ttss	(Address Part of ttss) → A Reg.
I	ttss	(A Reg.) + ttss → A Reg.
Y	ttss	(A Reg.) → Address Part of ttss
Z	ttss	Skip next instruction if (A Reg.) = ttss; else fall through
R	ttss	Return: (Instr. Counter + 2) → Address Part of ttss

Extended Interpreter Instruction Set

Behavior when the operand is 0000 When the operand field of an interpreter instruction is 0000, the instruction invokes one of the interpreter's built-in operations rather than referencing memory location zero. The shift instructions D 000y and M 000y are also special-cased here (see FLOATING-POINT INSTRUCTIONS above).

Op	Action	
D	$(\text{Acc})^2 \rightarrow \text{Acc}$	[Square the Accumulator]
M	$(\text{Acc}) \times 2 \rightarrow \text{Acc}$	[Double the Accumulator]
U	Swap values: $(\text{Acc}) \longleftrightarrow (\text{M Reg.})$	
B	Make (Acc) positive	[Absolute Value: $ \text{Acc} $]
T	Make (Acc) negative	[Force Negative Sign]
Y	Invert Sign: Change sign bit of (Acc)	
Z	Conditional Program Stop (Halts execution if console switch PS-16 is OFF)	
E	Exit Interpreter Mode (Return control to native machine hardware)	
I	Read floating-point numbers from paper tape input	
P	Print/Punch floating-point numbers to output device	
R	$\sqrt{(\text{Acc})} \rightarrow \text{Acc}$	[Square Root]
S	$\text{Sine}(\text{Acc}) \rightarrow \text{Acc}$	
C	$\text{Cosine}(\text{Acc}) \rightarrow \text{Acc}$	
A	$\text{Arctangent}(\text{Acc}) \rightarrow \text{Acc}$	
N	$\ln(\text{Acc}) \rightarrow \text{Acc}$	[Natural Logarithm]
H	$e^{(\text{Acc})} \rightarrow \text{Acc}$	[Exponential Function]

FLOATING POINT INTERPRETER 2 — H1-11.1

INTRODUCTION

Floating-Point Interpretive System 2 is a 33-instruction floating-point interpreter (like H1-11.0) but with much wider range and higher precision, at the cost of using two memory words per number instead of one. Inputs are 9-digit signed decimal mantissas with a 2-digit decimal exponent (± 99); outputs are 7-digit decimal mantissas with the same exponent range.

The interpreter ships on a single tape (relocatable hex, compatible with Program Input 1, J1-10.0) bundling Data Input, Data Output, and the usual transcendental functions. Only the subroutines you actually need must be loaded, but the cross-reference addresses between subroutines must be preserved when you do.

If your data swings across many orders of magnitude, this interpreter saves a lot of the scaling bookkeeping you'd have to do by hand in fixed-point.

Principles The interpreter presents the LGP-21 to the programmer as if it had a native floating-point instruction set. To do this it provides:

1. **Software registers:** a floating-point accumulator, a multiplier register, an address register, and an instruction counter.
2. **A richer instruction set:** arithmetic and transcendentals (including a multiply-accumulate), sign manipulation, address-register operations, and built-in I/O.
3. **Wide numerical range:** inputs are signed 9-digit mantissas with a base-10 exponent in ± 99 ; outputs are signed 7-digit mantissas with the same exponent range.
4. **Built-in I/O:** dedicated read and print pseudo-instructions for floating-point data.

The complete system takes 28 tracks of memory: the interpreter core plus Data Input (7 tracks), Data Output (4 tracks), and floating-point functions (6 tracks). That leaves 36 tracks (2,304 words) for the main program and data.

INTERNAL REGISTERS

The interpreter provides four registers: a floating-point accumulator, a multiplier register, an address register, and an instruction counter. The accumulator and multiplier register are each two words wide (matching the in-memory two-word floating-point format); the address register and instruction counter are each one word.

All four registers are zero on initial load. Instructions referenced in the descriptions below are detailed in the Pseudo-Instructions section.

1. **Floating-Point Accumulator.** Holds intermediate calculation results and output values. Mantissa at $q = 0$, 30 bits of precision, normalized so the leading bit is at 2^{-1} ; exponent at $q = 29$; each with its own sign bit. Modified by arithmetic, transcendental functions, and the Clear, Swap, and Set Sign instructions.
2. **Multiplier Register.** Holds the multiplicand for Multiply and Cumulative Multiplication. Same internal layout as the accumulator. Modified only by Set and Swap.
3. **Address Register.** A single word holding a track/sector address at $q = 29$. Used by Store Address to patch the operand field of an instruction, and by the zero-test branch. Modified only by Set Address and Increment Address.
4. **Counter Register.** The interpreter's program counter. Holds the address of the current pseudo-instruction and points at the next. Initialized by the main program's calling sequence on entry, and incremented by one per instruction. A Return instruction stores (counter + 2) into the operand field of its target. Jumps and conditional branches overwrite it.

INTERNAL NUMBER FORMAT

Each floating-point number occupies two consecutive locations:

- **First location:** the mantissa M at $q = 0$ --- a sign bit plus 30 magnitude bits, always stored normalized (so the leading magnitude bit has the place value 2^{-1}).
- **Second location:** the exponent E at $q = 29$ --- a sign bit plus magnitude bits, a small integer.

The represented value is $Z = M \cdot 2^E$.

Example 1: Representation of +3.75 In floating-point memory, the decimal value 3.75 is internally normalized as $0.9375 \cdot 2^2$. Its exact binary equivalent on the magnetic drum is structured as follows:

First Location (Mantissa at $q = 0$):

Second Location (Exponent at $q = 29$):

Bit 0	Bits 1--30	Bit 31
0	111100000000000000000000000000	0
↑	↑	↑
Sign (+)	Normalized Mantissa (0.9375)	Unused

Bit 0	Bits 1--29	Bits 30--31
0	000000000000000000000000000000	10
↑	↑	↑
Sign (+)	Padding Zone	Binary Exponent (2)

Example 2: Representation of a Negative Number (-3.75) A negative mantissa has its sign bit set and its magnitude bits stored in two's complement. The exponent is unaffected by the sign of the mantissa, so it's identical to the $+3.75$ case (not shown again here).

First Location (Mantissa at $q = 0$):

Bit 0	Bits 1--30	Bit 31
1	000100000000000000000000000000	0
↑	↑	↑
Sign (−)	Two's Complement Mantissa	Unused

Sequential Allocation in Drum Memory Multiple floating-point numbers stored consecutively occupy memory in pairs, alternating mantissa and exponent:

Operational Boundaries (Note):

1. **Input range:** decimal exponent $-99 \leq E_{10} \leq +99$.
2. **Output range:** decimal exponent $-99 \leq E_{10} \leq +99$ (matching input).
3. **Internal range:** the binary exponent must stay in $-333 \leq E_2 \leq +333$ during arithmetic and stores. The interpreter does not trap on overflow/underflow as long as this is satisfied.

PSEUDO-INSTRUCTIONS

The interpreter's 33 pseudo-instructions are listed below. ``Accumulator'' refers to the two-word software floating-point accumulator. In the Arithmetic and Branch tables, XXXX is an operand address; in the Auxiliary, I/O, and Function tables it is always 0000.

Arithmetic Instructions *Note: XXXX represents the absolute starting memory address of the target floating-point number's mantissa.*

Memory Location	Location Contents
4304	Mantissa of Variable 1
4305	Binary Exponent of Variable 1
4306	Mantissa of Variable 2
4307	Binary Exponent of Variable 2

Opcode	Name	Action
BXXXX	Bring	(XXXX) $\rightarrow$ Accumulator
AXXXX	Add	(Accumulator) + (XXXX) $\rightarrow$ Accumulator
SXXXX	Subtract	(Accumulator) - (XXXX) $\rightarrow$ Accumulator
DXXXX	Divide	(Accumulator) / (XXXX) $\rightarrow$ Accumulator
PXXXX	Place	(XXXX) $\rightarrow$ M Register
MXXXX	Multiply	(M Register) $\times$ (XXXX) $\rightarrow$ Accumulator
NXXXX	Multiply Cumulatively	[(M Register) $\times$ (XXXX)] + (Accumulator) $\rightarrow$ Accumulator
XD000y	Divide by 2^y	(Accumulator) / $2^y \rightarrow$ Accumulator ($0 \leq y \leq 9$)
XM000y	Multiply by 2^y	(Accumulator) $\times 2^y \rightarrow$ Accumulator ($0 \leq y \leq 9$)
HXXXX	Hold	(Accumulator) $\rightarrow$ XXXX
CXXXX	Clear	(Accumulator) $\rightarrow$ XXXX; then 0 $\rightarrow$ Accumulator

For the power-of-two scaling commands (XD000y and XM000y), the accumulator strictly maintains its internal normalized floating-point structure throughout the bit-shifting sequence.

Logical or Branch Instructions *Note: XXXX represents the target instruction address on the magnetic drum.*

Auxiliary Instructions *Note: The address field (XXXX) for all auxiliary operations must be explicitly configured as 0000.*

Input/Output Instructions *Note: The address field for all input/output commands must be set to 0000.*

Inside an I0000, input continues from the tape until a stop code returns control to the next interpreter instruction.

Function Instructions *Note: The address field for all transcendental operations must be set to 0000. The input argument must already sit in the Accumulator.*

The core interpreter loop contains the arithmetic, branch, address-register, auxiliary, and square-root instructions. Data Input, Data Output, and

Opcode	Name	Action
UXXXX	Unconditional Jump	Jump to XXXX. Cannot be used to exit the interpreter.
TXXXX	Test Minus	Jumps to XXXX if (Accumulator) < 0; else executes next sequential line.
800TXXXX	Conditional Jump	Jumps to XXXX if (Accumulator) < 0 OR if console switch PST is ON.
EXXXX	Set Address	(Address Part of XXXX) → Address Register
IXXXX	Increment Address	(Address Register) + XXXX → Address Register ²⁴
YXXXX	Store Address	(Address Part of Address Register) → Address Part of location XXXX
ZXXXX	Zero Test	(Address Register) - XXXX. If result = 0, skip next instruction; else execute next line.
RXXXX	Return	Links subroutines: (PC + 2) → Address Part of target location XXXX.

Opcode	Name	Action
U0000	Swap Registers	(M Register) ↔ (Accumulator)
B0000	Set Plus Sign	Forces (Accumulator) positive [Absolute Value: Accumulator]
T0000	Set Minus Sign	Forces (Accumulator) negative [Inverse Absolute Value: - Accumulator]
Y0000	Change Sign	(Accumulator) × -1 → Accumulator [Toggle sign bit]
Z0000	Operational Stop	Halts execution if console switch PS-16 is ON. Resumes on manual START.
E0000	Exit Interpreter	Safe exit from Virtual Machine; returns to native hardware control at next location.

the other transcendental functions (sin/cos/atan/log/exp) are separate modules; load only the ones you need.

INPUT

The I0000 pseudo-instruction reads a data tape with the following structure:

1. A starting address.
2. Signed decimal integers paired with their exponents.
3. A group-termination code after each block.
4. A final stop code at the end of the tape.

Opcode	Name	Action
I0000	Data Input	Diverts to tape-reader module. Parses, normalizes, and stores decimal variables.
P0000	Data Output	Prints/Punches the current Accumulator value. Accumulator data remains unaltered.

Opcode	Name	Action
R0000	Square Root	$\sqrt{\text{Accumulator}} \rightarrow \text{Accumulator}$. Negative inputs trigger an immediate error halt.
S0000	Sine	$\sin(\text{Accumulator}) \rightarrow \text{Accumulator}$. Input argument must be formatted in radians.
Q0000	Cosine	$\cos(\text{Accumulator}) \rightarrow \text{Accumulator}$. Input argument must be formatted in radians.
A0000	Arctangent	$\arctan(\text{Accumulator}) \rightarrow \text{Accumulator}$. Resulting output is scaled in radians.
N0000	Natural Logarithm	$\ln(\text{Accumulator}) \rightarrow \text{Accumulator}$.
H0000	Exponential	$e^X \rightarrow \text{Accumulator}$, where X represents the initial value held in the Accumulator.

The Starting Address Each data group starts with an absolute destination address in decimal track/sector notation, terminated by a stop code. For example, 4200' stores the group's values starting at location 4200.

The Data Structure Each value is two consecutive punched values on the tape: a 7-digit signed first word and a 2-digit second word concatenated with a 2-digit signed exponent, each terminated by a stop code:

$$\begin{aligned} \text{Word 1: } & \pm d_1 d_2 d_3 d_4 d_5 d_6 d_7' \\ \text{Word 2: } & d_8 d_9 \pm e_1 e_2' \end{aligned}$$

The nine digits $d_1 \dots d_9$ form a signed 9-digit decimal integer; $\pm e_1 e_2$ is its base-10 exponent ($-99 \leq E_{10} \leq +99$). The value is $\text{integer} \times 10^{E_{10}}$. Negative numbers have a leading minus on the first digit of word 1; positive numbers may have a leading space but must not have an explicit + sign. The subroutine converts each value to binary floating-point and stores it in a two-word block.

Input Encoding Examples

- **Example 1:** $0.0900000521374209 = 521374209 \times 10^{-16}$, punched as:

5213742'
09-16'

- **Example 2:** $5522829640000000 = 552282964 \times 10^{+07}$, punched as:

5522829'
64+07'

Termination Stopcodes Two stop codes mark the boundaries:

1. **Group end.** A stop code where a number is expected ends the current group. The interpreter then reads the next group's starting address from the tape.
2. **Input end.** Two consecutive stop codes where a number is expected end the whole input. The interpreter issues a carriage return, stops the tape reader, and returns to the interpreted program (the instruction following the I0000 that called it).

Input example Table 2 shows a sample tape layout. Each group starts with a destination address, then alternates 7-digit mantissa words and 2-digit-plus-exponent words. A stop code where a number is expected ends the group; two such stop codes in a row end the whole input.

INPUT CONTROL WORD (Starting Address)		S T O P	SIGNED DECIMAL NUMBERS				S T O P
			Part 1		Part 2		
			$d_1 d_2 \dots d_7$		$d_8 d_9 \ e_1 e_2$		
		P					P
1	5500	' [†]	-	3300000	'	00 -	04 ' [Group 1]
2				3141592 [‡]	'	65 -	08 '
3			-	0000592	'	34 -	11 '
4					' [¶]		
5	2134	'		0	'		' [Group 2]
6				30	'	50 -	'
7				750	'	00 +	'
8			-	0100000	'	00 +	'
9					' [§]		'

Table 2: Sample Data Input Format

[†] The stopcode (') immediately following the initial address ends the address and starts number entry for the input group.

[‡] A single stopcode with no numeric input terminates the input group.

¶ Positive quantities are encoded with *no* prefix; negative values should have an explicit minus sign (-). Do not punch a plus sign (+) for positive values.

§ This single stopcode ends the second data group.

|| This stopcode following the group terminator stopcode tells the interpreter to exit input mode and resume execution.

Group 1 is read into consecutive locations starting at 5500²⁵:

5500 -33000.0

5501 (*Exponent for -33000.0*)

5502 3.14159265

5503 (*Exponent for 3.14159265*)

5504 -0.00000059234

5505 (*Exponent for -0.00000059234*)

All exponents are stored at $q = 29$. After Group 1's terminating stop code, the interpreter reads the next group's destination address (2134²⁶) and stores Group 2 there:

2134 → Zero (0.0)

2135 → Zero (0.0)

2136 → 30.50

2137 → (*Exponent for 30.50*)

2138 → 750000.0

2139 → (*Exponent for 750000.0*)

2140 → -10000000000000.0

2141 → (*Exponent for -10000000000000.0*)

Group 2 ends with a single stop code, and the second stop code immediately after it ends the whole input.

Special case. A literal zero must be punched as 0' (with the explicit digit), not as a bare stop code²⁷. The bare stop code is reserved for group/input termination, so the parser needs the explicit digit to recognize a real zero.

OUTPUT

The output format works to make the numbers a consistent size on the page, and to have a consistent format. Each number has:

- a leading character for the sign. This will be a space for positive numbers, and - for negative ones,

²⁵Translator's note: I've preserved the original manual's representation here; suffice it to say that the values indicated are handwaving the actual values in memory.

²⁶Note that these addresses don't need to be ordered. The input routine will happily build two-word floating-point numbers wherever you indicate.

²⁷This is different from other input routines, particularly the Program Input 1 (Section 9) loader.

- the mantissa of the floating-point number, in leading-decimal format,
- a separator space,
- the sign of the exponent (this is either + or −, and *always* appears),
- the two-digit exponent itself, and
- a tab character.

The space/− convention means that positive and negative numbers will align properly to the left down a column.

The tab character enables the user to easily create well-formatted output on the Flexowriter by setting the hardware tab stops.

Control returns to the interpreted program after each number; the subroutine prints one number per call. The printed format looks like this:

```
Positive  .xxxxxxx ±ee[Tab]
Negative -.xxxxxxx ±ee[Tab]
```

This is the standard scientific-notation form:

$$\pm .xxxxxxx \cdot 10^{\pm ee}$$

Output Examples

Printed Output	Mathematical Value	Notes
-.5060000+04	-5060.0	Negative mantissa, positive exponent
.9375000-02	0.009375	Leading space for positive mantissa
-.1000000-06	-0.0000001	Extreme fractional negative
.1000000+30	1.0×10^{30}	Large positive value

Output Limits and Constraints The formatting routine enforces the following bounds:

- **Decimal exponent range:** $-99 \leq ee \leq +99$.
- **Decimal mantissa bounds:** $0.1000000 \leq |\text{mantissa}| \leq 0.9999999$, or exactly zero.
- **Internal binary exponent range:** $-333 \leq \text{exponent} \leq +333$.

If the internal binary exponent drops below −333, the routine prints a zero. If it exceeds +333, the interpreter triggers a range-error stop and halts.

FUNCTION SUBROUTINES

SINE-COSINE This subroutine calculates the sine or cosine of a given value expressed in radians, using a 9th degree polynomial to approximate the value. To use, load the angle into the floating-point accumulator then execute the appropriate pseudo-instruction (S0000 for sine or C0000 for cosine). The result is placed in the floating-point accumulator. The following table shows the method for calculating the function values depending on the exponent of the argument.

Exponent (binary)	Sine X	Cosine X	Notes
+26 to +127	Range error	Range error	
-8 to +25	Polynomial evaluation	Polynomial evaluation	
-20 to -9	Sine X = X	Polynomial evaluation	$\sin X \approx X$ for small angles
-127 to -21	Sine X = 0	Cosine X = 1.0	Exceeds precision

ARCTANGENT This subroutine calculates the angle that corresponds to a given tangent argument. Load the tangent value into the floating-point accumulator and execute the A0000 pseudo-instruction. The result is returned in radians in the floating-point accumulator.

LOGARITHM AND EXPONENTIAL FUNCTION Load the independent variable X into the floating-point accumulator and execute the appropriate pseudo-instruction (N0000 for $\log_e$ and H0000 for e^x); the resulting value is returned in the floating-point accumulator.

SQUARE ROOT This subroutine, which is included in the interpreter system, calculates the square root of the number in the floating-point accumulator and returns it there.

OPERATION

Input is floating-point numbers loaded from tape or in memory, or from numbers in the pseudo-registers from previous operations.

Running the interpreter Entry to the interpreter is via a subroutine call using an R/U sequence. Similar to the Floating-point Interpreter I, the R instruction sets the address portion of a B instruction at L_0 , which in this case acts as an executable pointer back to the pseudo-instructions

inline after the U. The interpreter extracts the address of the code to be interpreted from this B instruction. It does *not* set a return address, but instead uses the E0000 instruction to detect the end of the interpreted pseudo-instructions, and branches back to the (fixed-point) instruction following the end of the floating-point code.

Memory Location	Instruction	Address	Meaning
α	R	L_0	Store starting address of floating-point instructions.
$\alpha + 1$	U	L_0	Entry into the interpreter system.
$\alpha + 2$	$\langle \dots \rangle$		Floating-point instructions.
$\alpha + 3$	$\langle \dots \rangle$		
$\alpha + n$	E	0000	Exit from the interpreter system.
$\alpha + n + 1$	$\langle \dots \rangle$		Resume fixed-point instructions.

Memory Requirements If the starting address of H1-11.1 is defined as L_0 , then the routines on this tape must be loaded as follows (using the corresponding input and modifier key words).

Program	Input key word	Modifier key word	Memory required
Interpreter system	L_0		11 tracks
Data input	$L_0 + 1100$	L_0	6 tracks
Data output	$L_0 + 1700$	L_0	4 tracks
Sine - Cosine	$L_0 + 2100$	L_0	2 tracks
Arctangent	$L_0 + 2300$	L_0	83 sectors
Logarithm	$L_0 + 2419$	L_0	45 sectors
Exponential function	$L_0 + 2500$	L_0	2 tracks

Scratch Storage --- The program uses locations 6300 to 6363 as working storage.

Program Stops

Memory Location	Meaning	Remedy / Action
$L_0 + 0947$	Negative argument for square root	Press START. The pseudo-instruction exits with the original argument in the accumulator.
$L_0 + 0312$	Exponent 333 for Hold or Clear	Press START. Hold or Clear pseudo-instructions are bypassed.
$L_0 + 0710$	Division by zero or non-floated number	Execution cannot continue.
$L_0 + 1808$	Exponent > 99 during data input	Press START. The Flexowriter tabs to the next stop without printing, and the code exits to the core interpreter.
$L_0 + 2100$	Argument for $\sin/\cos \geq 2^{26}$	Press START. The S0000 or C0000 operation is skipped.
$L_0 + 2426$	Argument for $\log_e X \leq 0$	Press START. The pseudo-instruction returns zero and control returns to the main program.
$L_0 + 2629$	Argument for $e^X \geq 128$	Press START. The pseudo-instruction is skipped.

Program Control Switches The PS-16 switch on the console can be used as a ``breakpoint'' facility to halt execution at selected points.

Console Switch	Setting	Action
PS-16	ON	Execution stops at Z0000 instructions.
	OFF	Execution continues past Z0000 instructions.

Precision and Accuracy

- **Sine-Cosine:** Maximum error is 5×10^{-8} .
- **Data Output:** The maximum error is limited to:
 - 1 unit in the last decimal place of the mantissa if $\text{EXP}_{10} \leq 30$.

- 5 units in the last decimal place of the mantissa if $\text{EXP}_{10} \leq 99$.

Translator's note: To print a floating-point number, the data output routine has to convert a binary exponent (2^x) into a decimal exponent (10^y). Mathematically, this requires multiplying or dividing the mantissa by powers of 10 (or powers of $\log_{10}(2)$) until the binary scaling is cleared out.

1. For ≤ 30 : For these exponents, the conversion can be done using exact or very tightly bounded multiplication factors that fit cleanly within a single or double-word of 31-bit precision. The rounding error is kept to a minimum of 1 unit in the last place.
2. For > 30 : For very large numbers (up to 10^{99}), the output routine has to repeatedly multiply by large powers of 10. Because of the LGP-21's 31-bit word size, the intermediate multiplication constants themselves have to be rounded to fit. As the algorithm repeatedly loops and multiplies to scale down large exponents, the rounding errors in these constants also multiply.

By the time the conversion routine finishes working through a number like 10^{95} , the accumulated rounding error corrupts the bottom bits of the mantissa, producing an output that could be off by up to 5 units in the 7th decimal digit.

REMARKS

1. A program can exit H1-11.1 interpreter mode and return to it without the contents of the pseudo-registers being lost.
2. The starting address of the system should be at sector 00 of a track. Otherwise, many of the addresses that refer to track 63 are not optimal.
3. It's good practice to load the entirety of H1-11.1, and to then punch out the individual sub-libraries by means of J4-10.2 or J4-10.3. This enables you to load only the parts that you require using J1-10.0 or by means of J5-10.0. This allows you to verify checksums on load.
4. Instructions with zero addresses do not actually refer to location 0000, but are used to indicate special pseudo-instructions. The interpreter has 14 pseudo-instructions with zero addresses, plus the two special shift instructions D000y and M000y. These instructions set their address part to values from 0001 to 0009, meaning that the division and normal multiplication instructions must not use these addresses in interpreter mode.

INSTRUCTION	RESULT, IF ADDRESS XXXX $\neq$ 0
Z	(Address reg.) - (XXXX) = 0? yes $\rightarrow$ skip next instruction; no $\rightarrow$ do not skip
B	(XXXX) $\rightarrow$ (Accumulator)
Y	(Address reg.) $\rightarrow$ address part of (XXXX)
R	Address of R plus 2 $\rightarrow$ address part of (XXXX)
I	(Address reg.) + (XXXX) $\rightarrow$ (Accumulator)
D	(Accumulator) / (XXXX) $\rightarrow$ (Accumulator)
N	(M Reg.) $\times$ (XXXX) + (Accumulator) $\rightarrow$ (Accumulator)
M	(M Reg.) $\times$ (XXXX) $\rightarrow$ (Accumulator)
P	(XXXX) $\rightarrow$ (M Reg.)
E	Address part of (XXXX) $\rightarrow$ address part of the (Accumulator)
U	Take next instruction from XXXX
T	Jump if (Accumulator) is negative
-T	Jump if (Accumulator) is negative or if PST is turned on
H	(Accumulator) $\rightarrow$ (XXXX)
C	(Accumulator) $\rightarrow$ (XXXX); 0 $\rightarrow$ (Accumulator)
A	(Accumulator) + (XXXX) $\rightarrow$ (Accumulator)
S	(Accumulator) - (XXXX) $\rightarrow$ (Accumulator)
INSTRUCTION	RESULT, IF ADDRESS = 0 *
Z	Stop (PS-16); continue calculating after START is pressed
B	Make (Accumulator) positive
Y	Form complement of the (Accumulator)
R	$\sqrt{\text{(Accumulator)}} \rightarrow \text{(Accumulator)}$
I	Input of floating-point data
D	(Accumulator) / $2^y \rightarrow$ (Accumulator) [address is not 0000, but 0001 to 0009]
N	$\text{Log}_e \text{(Accumulator)} \rightarrow \text{(Accumulator)}$
M	(Accumulator) $\times 2^y \rightarrow$ (Accumulator) [address is not 0000, but 0001 to 0009]
P	Print (Accumulator)
E	Exit interpreter mode
U	Swap (Accumulator) and (M Reg.)
T	Make (Accumulator) negative
-T	Jump if (Accumulator) is negative or if PST switch is on
H	$e^{\text{(Accumulator)}} \rightarrow \text{(Accumulator)}$
C	Cosine (Accumulator) $\rightarrow$ (Accumulator)
A	Arctangent (Accumulator) $\rightarrow$ (Accumulator)
S	Sine (Accumulator) $\rightarrow$ (Accumulator)

Coding sheet for Horner's Method example [Translator's note: This coding example and its data are simply oddly bunged on to the end of the chapter; best guess is that someone wanted a coding example of how to use the interpreter, and someone threw together a quick demo.]

Input keyword	S T O P	Loc.	Opcode & Addr.	S T O P	Address Contents	Comments
;0004200	'					Word counter to Track 04, Sector 00.
/0004200	'					Origin to Track 04, Sector 00.
		00	xR 1400	'		Set interpreted section pointer in interpreter
		01	xU 1400	'		Begin interpreting floating-point code
		02	xI 0000	'		Read coefficients from Flexowriter (see below)
		03	E 0018	'	4306	Set starting address
		04	Y 0006	'	4306	
		05	B 0013	'	Zero	
		06	A []	'	a_n	This address will be overwritten
		07	xL 0002	'	$a(4306 + 2n)$	Increment address
		08	Y 0006	'	$a(4306 + 2n)$	register by 2
		09	xZ 4316	'		Check for completion
		10	U 0015	'		Not finished
		11	xP 0000	'		Print result before exit
		12	xE 0000	'		Exit interpreter
		13	xZ 0000	'		Stop machine (fixed-point opcode)
		14	U 0000	'		Swap accumulator into instruction counter
		15	xU 0000	'		Swap Accu. / M. Reg.
		16	xM 4304	'		Multipl. by x
		17	U 0006	'		Return for next term
		18	xZ 4306 ₈₂	'		Initial coefficient
000XXXX		19		'		

Data input sheet for Horner's Method This is sample data in the format that Horner's Method demo program expects.

	INPUT CONTROL WORD (Starting Address)	S T O P	SIGNED DECIMAL NUMBERS				S T O P
			Part 1 $d_1 d_2 \dots d_7$	'	Part 2 $d_8 d_9$	$e_1 e_2$	
1	4304	'	1090000	'	00 +	09	'
2			0120000	'	00 -	09	'
3			0340000	'	00 -	09	'
3			0560000	'	00 -	09	'
3			0780000	'	00 -	09	'
3			0900000	'	00 -	09	'
9		'					'

Translator's Notes

Why do we have *two* floating point packages? Modern programmers would look at this documentation and immediately start trying to figure out how to get rid of one of these two packages. Why would anyone want, or need, two separate floating point packages?

The following is speculation, based off the architectures of the two interpreters and years of experience with human nature, so take it with a grain of salt. If we ever have a real LGP-21 programmer around to ask, who actually *used* both, we can nail it down for sure. But having said that, it appears that there two different floating-point interpreters because there were two different audiences who needed floating point.

The first set of users would be people who are familiar with the LGP-21 and the fixed-point fractional architecture; who are comfortable thinking about numbers in terms of q and who have relatively lightweight requirements for floating-point operations. They will be writing code mostly in LGP-21 native mode, and occasionally dropping into floating point for a few calculations. Basic I/O of floating point works fine for them. Interpreter 1 is their choice.

The second set of users are primarily engineers, mathematicians, scientists...anyone whose native way of thinking about math is ``things you do with real numbers''. They want an instruction set that natively Does The Thing, using floating point numbers. Power-of-10 scaling makes perfect sense to them, but bit-twiddling and screwing around with representation is a distraction from the work they need to get done. Their attitude is effectively: *``I just want to work with actual numbers. These fixed-point fractions are too weird.''*

There are tradeoffs; we can see some of them from the descriptions of the two interpreters:

- Interpreter 2 has a pad word following each mantissa-exponent pair, interpreter 1 doesn't. Is this because the all-float interpreter

2 runs *slower* than the limited interpreter 1? Or is it a brilliant speed hack that makes it run *faster*?

- Code written for interpreter 1 is *probably* faster, up to a point, but after the ratio of fixed-point to floating-point operations tilts far enough toward floating-point, the overhead to move in and out of floating-point mode and the overhead to move *data* in and out will eventually make the interpreter 1 program larger than the same program written for interpreter 2, which doesn't have the mode-switch overhead, and eventually *may* make it slower.
- An Interpreter 2 program may be slower than an Interpreter 1 program, but it is likely to be *smaller* because the mode-switch overhead is no longer needed.

We won't know for sure until we find a programmer who used both, or two programmers who have had a 50-plus year argument about which is better.

Why interpreters? A modern programmer's second thought is ``why are the LGP-21's floating point implementations *interpreters*?'' Couldn't we just write some nice libraries and call it a day?

On a more modern machine with a stack or other good support for subroutine calls, sure. (We'll pretend it doesn't have native floating point.) Let's say we're doing `fmul(fadd(a,b),fadd(c+d))`. We'd put `a` on the stack, call the conversion routine, push `b` on the stack, convert it, call the float-add function, put `c` on, convert, put `d` on, convert, call float-add, call float-multiply, done!

On the LGP-21, there are *so many* more operations. We have no stack, so everything has to go in temporary storage. We can't hold a two-word (mantissa and exponent) number in the regular accumulator, so we'll have to do something like this²⁸:

Operation	Estimated instructions	Description
<code>fread(a)</code>	3	read value for <code>a</code>
<code>fread(b)</code>	3	read value for <code>b</code>
<code>fread(c)</code>	3	read value for <code>c</code>
<code>fread(d)</code>	3	read value for <code>d</code>
<code>fadd(a, b, t1)</code>	3	<code>a + b</code> to <code>t3</code>
<code>fadd(c, d, t2)</code>	3	<code>c + d</code> to <code>t4</code>
<code>fmul(t1, t2, t1)</code>	3	Final result in <code>t1</code>
<code>print(t1)</code>	3	Print it

²⁸This is only the instructions needed to set up to *do* the operations; we're skipping the actual functions and the wiring necessary to do things like set up return addresses, find arguments, etc. Those are assumed to be library overhead and not something the caller codes...but that overhead exists too.

Assuming that we can use a B/R/U calling sequence for each of these operations, that's 24 instructions to evaluate the expression; 4 words to store the values of a, b, c, and d that we read; and 6 for temp storage t1, t2, and t3; a total of 34 words. If we use an interpreter that ``natively'' understands floating point, we can do this:

Memory Location	Instruction	Address	Meaning
α	R	L_0	Start of interpreter.
$\alpha + 1$	U	L_0	Entry into the interpreter system.
$\alpha + 2$	I	0000	Read a, b, c, d as float.
$\alpha + 3$	B	a	Load a.
$\alpha + 4$	A	b	Add b.
$\alpha + 5$	H	t1	Store result in t1.
$\alpha + 6$	B	c	Load c.
$\alpha + 7$	A	d	Add d.
$\alpha + 8$	H	t2	Store result in t2.
$\alpha + 9$	B	t1	Load t1.
$\alpha + 10$	A	t2	Multiply t2.
$\alpha + 11$	P	0000	Print result.
$\alpha + 12$	E	0000	Exit from the interpreter.
$\alpha + n + 1$	...		Resume fixed-point.

To execute the exact same set of operations, the interpreter version only takes 12 (pseudo) instructions plus 10 words to store 5 floating-point numbers, 22 total, and is much simpler to understand. Fitting your program into much less storage is a serious consideration on a machine with only 4K words, especially since you'll be giving up memory to your libraries or your interpreter. (Interestingly, it should be noted that for Interpreter 2, the floating-point library functions are *smaller* than the corresponding fixed-point fractional ones.)

Coding example for Interpreter 2 This is a far better example of using all of the facilities of Interpreter 2 than the very simple comparison program above.

The Interpreter 2 Horner's Method example shows how a program would have been coded on an LGP-21 coding sheet, and then fed to one of the program loaders in 9 to make it resident in memory.

The program as designed is set up to allow the user to run the program, enter a set of exactly 5 coefficients (we're not up to handling dynamic loops here), and have them multiplied out:

$$f(x) = a_4x^4 + a_3x^3 + a_2x^2 + a_1x + a_0$$

Reading an LGP-21 coding sheet We've elected to keep the coding sheet for this particular example instead of writing out assembler code because it's useful to see how an LGP-21 program was coded by hand. Note that the locations start at 00 and go up; these line numbers act as ``virtual'' memory addresses, and can be referred to by other instructions by number, very much like a BASIC program. Instead of a GOTO 200, you have a U 0015 to branch to the instruction on line 15.

The instructions with a leading x are *non-relocated*; their addresses are not modified when the program is loaded. For example, lines 0 and 1 set up Interpreter 2 by saving the address of the instruction 2 on from line 0 into the interpreter itself, at the fixed address 1400. Additionally, the interpreter's special I and P instructions, to read and write data, have to have an address field of exactly 0000 to work properly, so those instructions are also marked as non-relocatable.

These two items together are key to understanding how the program works. A more modern²⁹ assembler would have had labels for the line-number branches that the coding sheet uses, but would still emit assembled code that looks more like the coding sheet than anything else.

How the Horner's Method coding sheet and data input sheet would have been used To actually execute this on the LGP-21, an operator would have gone through the following sequence:

1. Power on the LGP-21 and ensure the Loader Utility Program is resident in memory. Load it if not.
2. Sit down at the Flexowriter and type out the coding sheet to produce a physical paper tape punched with the instruction bits and carriage-return stop codes ('').
3. Take the finished source tape, walk over to the LGP-21 console, and feed it into the paper tape reader.
4. Set the console switches to execute the resident loader, and sets the input device to the paper tape reader, then tells the loader to load the tape.
5. The loader starts the tape and reads the initial tape headers (;0004200 and /0004200), targets Track 04 Sector 00, and begins shifting the relative instruction addresses to match their new home on the drum.
6. Once the program tape finishes loading, the operator removes it and inserts a Data Tape containing the actual floating-point numbers for x and the polynomial coefficients

²⁹Or at least as modern as you're going to get for a computer built in 1963

7. The operator clears the manual controls and presses START on the physical control panel.
8. The computer starts executing the program, which starts Interpreter 2, pauses at Line 02 (xI 0000), reads in the data values from the data tape, and immediately begins crunching the numbers through the self-modifying loop.
9. The interpreter finishes the math, commands the Flexowriter to type out the final evaluation result on paper (xP 0000), drops out of interpretive mode, and triggers a hard system stop via Line 13 (xZ 0000).
10. If the operator wants to clear the current run and evaluate a completely fresh data tape using the same polynomial structure, they simply hit START again. The machine executes Line 14 (U 0000), which immediately vectors execution right back to the beginning of the program loop (relative line 0) to read the next input tape of x and the coefficients.

8 Format Conversion

DECIMAL-HEXADECIMAL TAPE CONVERSION — H4-10.0

PURPOSE

H4-10.0 converts arbitrarily relocatable, decimal-coded program tapes that are permissible for Program Input 1 (J1-10.0) into arbitrarily relocatable hexadecimal tapes, usable by 9. A conversion log is created with a listing of all instructions to be converted and whether or not they are relocatable, and a memory map of where the program is currently loaded.

Any corrections required in the program can be made by means of Program Input 1 9 before output. The resulting arbitrarily relocatable hexadecimal tape can be verified via checksum after output.

STORAGE REQUIREMENTS

Program Space: 11 tracks and 35 sectors (739 words)

Temporary Storage: None

The program is loaded into memory immediately following Program Input 1.

INPUT

H4-10.0 dynamically patches Program Input 1 upon execution, hooking its input routines to intercept the incoming program stream and construct the tracking tables. Once the target program has been completely read, H4-10.0 restores Program Input 1's original code to return it to normal operation. It must be resident before the program to be converted is loaded.

The decimal program to be converted should be stored at least 15 tracks above the starting address of Program Input 1, and loaded so that it could be executed, with the correct fill keyword (;) and modifier (/). All Program Input 1 input keywords work normally. Program Input 1 as modified by H4-10.0 creates a bitmap table to track relocatable versus absolute instructions.

A second allocation bitmap tracks which memory regions contain valid data, ensuring only actually-populated sectors are eventually punched to tape. PIR's direct absolute memory write command (+) bypasses this tracking mechanism and clobbers live location contents directly; it does not update the instruction-patching or allocation bitmaps. Once the new program is loaded, execution can be intercepted via console switch PS-4 to hand control back to Program Input 1 for further memory patching prior to output.

When the operator resumes program execution at L_0+0601 to punch the output, the computer selects the Flexowriter for input and requests the selection keyword for the output unit. The Flexowriter's punch is selected by default; press START to continue with this device, or enter a zero and press START to select the high-speed punch.

After the output unit is selected, the computer selects the Flexowriter again for input to read the output modifier. This is a number in decimal track/sector notation which will be subtracted from the modifiable addresses. This modifier must be four digits or smaller.

As an example, we'll assume that the program to be converted is loaded at 4000. If it is to be punched with relocatable address adjusted to be relative to 1000, one would enter an output modifier of 3000.³⁰

OPERATION

The program has the following five entry points:

$L_0 + 0600$	for reading the program to be converted
$L_0 + 0601$	for punching the converted program
$L_0 + 0602$	for restoring Program Input 1 if the tape fails verification
$L_0 + 0603$	for verifying the output
$L_0 + 0604$	for restoring Program Input 1 after successful verification

L_0 is the starting address of Program Input 1 (*not* this program!).

OUTPUT

Pressing START after entering the output modifier punches the converted program in arbitrarily relocatable hexadecimal form. Tables printed on the console indicate which portions of memory were punched and which instructions were marked as modifiable.

The converted words are punched in groups of 64 or fewer. Each group is preceded by a PIR keyword for hexadecimal fill (M), and each group is followed by a checksum. (Details of the format can be found at 9). After punching is complete, Program Input 1 is restarted.

After output, both the content and checksums of the output tape can be verified. To do this, place the just-punched tape into the reader and jump to $L_0 + 0603$, where L_0 is the starting address of Program Input 1. The computer selects the typewriter for input of a modifier, which must be the same as the one used when the program was punched. The computer selects the typewriter again to allow the input unit to be selected (if necessary). Press START to read and verify the tape.

³⁰To relocate code to a higher memory address, the operator would input the tens-complement of the desired upward shift, forcing the subtraction routine to wrap around the address space allocation boundaries. This requires a lot of care.

The program is *not* reloaded into memory during verification; the contents of memory are used to verify that the tape matches. If a fill block on the tape fails validation, the console types out a character: "w" indicates a memory word does not match; "e" indicates that a checksum is incorrect. These error indications apply to the specific hexadecimal fill block currently being verified; the tape reader will immediately halt, allowing the operator to inspect the block and locate the error.

9 Program Input

The programs in this section are designed to make it easier to load programs into the LGP-21 than tediously typing them on the Flexowriter and depositing them word-by-word into memory. They can read blocks of data from tape, store it, and checksum the data read to ensure that it has been read correctly. They also perform the functions of a crude dynamic loader, making it possible to code relative to location 0000 and then load the code at an arbitrary address, relocating all relative addresses in the process. For 1963, this is a fairly sophisticated little pair of utilities.

J1-10.0, commonly known as PIR, can be modified by H4-10.08 to automatically relocate tapes and repunch them as checksummed hexadecimal.

PROGRAM LOADER 1 — J1-10.0

PURPOSE

Program Input 1, J1-10.0 is a memory loader program. It facilitates the reading of hexadecimal tapes—whether arbitrarily relocated or not—and calculates a checksum during the reading process. It can also read and check arbitrarily relocated decimal programs.

J1-10.0 performs the following functions:

1. Reading, encoding, and storing instruction words to predefined memory locations.
2. Reading and storing hexadecimal or alphanumeric words to predefined memory locations without encoding.
3. Setting an address modifier in a program to a specific value.
4. Reading decimal addresses incremented by the modifier value.
5. Setting the ``Start Fill'' counter to a specific address value.
6. Reading specific instructions and executing them immediately.
7. Reading decimal addresses, followed by a jump either to this memory location or to the memory location specified by the address plus modifier.
8. Reading a decimal address; the contents of this memory location appear in the accumulator.
9. Reading, encoding, and storing arbitrarily relocatable decimal tapes.
10. Reading and storing hexadecimal tapes.
11. Selecting a specific input unit.

Hexadecimal tapes are usually generated by a hexadecimal dump program, such as the J4-10.0 program.

STORAGE REQUIREMENTS

Hexadecimal input only	2 tracks
Combined input	3 tracks, 29 sectors
Temporary storage	None

- **MNNKHHHH** This keyword reads NN hexadecimal words in ascending order into consecutive memory locations, starting at memory location HHHH plus the modifier. The K is a store instruction. The input keyword contains a flag bit (bit 31); each of the NN words that are to be modified must also contain a flag bit.

The address modifier (see below) is added to the operand address portion of each flagged word before it is stored.

A checksum is calculated from all NN words as they are being stored plus the input keyword (all values are checksummed without the address modifier). If the calculated checksum does not match the checksum on the tape following these words, an error stop occurs. If the checksums match, the computer requests a new input keyword.

Example: Let the modifier be 1200 (decimal) and the input keyword be M40K1201' (hexadecimal). The next 64 (40 hex) hexadecimal words are read and modified (if they have a flag bit) and are stored consecutively, beginning in memory location 3000.

- **VNNCHHHH** -

The hexadecimal fill keyword for non-relocatable [absolute] tapes reads in NN hexadecimal words starting with memory location HHHH. C is a store instruction. The input keyword does not contain a flag bit. The most recently-entered address modifier value is added to the operand address portion of all hexadecimal fill words that have a flag bit as they are stored.

A checksum is calculated from all NN words as they are being stored plus the input keyword (all values are checksummed without the address modifier). If the calculated checksum does not match the checksum on the tape following these words, an error stop occurs. If the checksums match, the computer requests a new input keyword.

- **VNNCTTSS**

Example: The input keyword V40C1100' causes the following 64 (40 hex) hexadecimal words to be stored, beginning in memory location 1700.

When reading hexadecimal tapes with V or M keywords, the Program Input Routine verifies each stored word; specifically, after a

word is stored, the value in memory is compared with the read-in value. If the two values do not match, an error stop occurs.

- /000TTSS

The Modifier Input Keyword sets the address modifier to the address TTSS contained within the input keyword.

When entering hexadecimal tapes, this Address Modifier is added to all keywords and words that contain a flag bit.

When entering decimal instruction words, the modifier is added to the operand addresses of all instructions except those preceded by an ``X'`.

The modifier remains unchanged until it is replaced by a new Modifier Input Keyword.

Example: The input keyword /0001200' causes 1200 to be added to all flagged operand addresses and keywords.

- .000TTSS'

The Absolute Stop and Jump Input Keyword causes the computer to stop. If the Start button is subsequently pressed, a jump occurs to location TTSS. If the PS-32 switch is set to ON, execution continues at the target address.

Example: The input keyword .0001663' would cause the computer to jump to 1663 and halt execution (if PS-32 is off).

- .100TTSS'

The Relative Stop and Jump Input Keyword causes the computer to stop. If the Start button is subsequently pressed, a jump occurs to location TTSS plus the modifier. If the PS-32 switch is set to ON, the stop is suppressed.

Example: If the modifier has been set to 1200, then the input keyword .1001663' would cause a jump to 2863.

- S000TTyy'

The Selection Keyword selects the specific input unit designated by the decimal track address TT. (yy can be any arbitrary sector address; it is ignored, but must be supplied). A list specifying the corresponding input units for specific track addresses can be found in the LGP-21 Programming Manual.

After entering the Selection Keyword, the computer stops. After pressing the Start button, the computer continues reading via the selected input unit.

Restarting J1-10.0 by jumping to the start of the program will automatically reselect the primary Flexowriter for input. Reading

will then continue via the Flexowriter until a new Selection Keyword selects a different unit.

Example: If 32 refers to a second Flexowriter, then the keyword S0003200' selects this second typewriter for further input.

DECIMAL INPUT

- 000TTSS'

The Decimal Fill keyword causes the input program to store decimal words in ascending order into consecutive locations, beginning with memory location TTSS.

Any valid address followed by a stop code may be used. Every decimal input should be preceded by a Decimal Fill keyword. The ``start fill'' address is stored in the start-fill counter. This memory location of the subroutine contains the address for the decimal input. The counter is incremented by 1 each time after a word (not a keyword) is read and stored. The read-in words are stored consecutively until a new decimal fill keyword is read or the input is terminated.

Example: The fill keyword ;0000400' would store read-in words beginning with memory location 0400.

- ,00000NN'

The keyword for entering hexadecimal words causes NN hexadecimal words to be stored, specifically beginning in the location whose address is held in the start-fill counter. NN must be specified in decimal and can take a value from 1 to 63. The stored words are not incremented by the address modifier. Leading zeros may be omitted for the hexadecimal words that are to be read in.

Each hexadecimal word and keyword must be followed by a stop code. If a zero is to be entered, it is not necessary to write a 0. A stop code alone is sufficient to indicate a zero. Each hexadecimal word must not consist of more than 8 characters.

Example: The input keyword ,0000003' followed by the three hexadecimal words -2'JK73'' would cause the values 00000002, 0000JK73, and 00000000 to be stored into the next three consecutive locations.

- A00000NN'

The keyword for entering alphanumeric words causes NN alphanumeric words to be stored, beginning in the location whose address is held in the start-fill counter. The alphanumeric words are shifted two places to the left and stored without binary conversion. NN must be specified in decimal and can take a value from 1 to 63.

Each word can contain up to five characters in 6-bit representation (if more than five characters per word are entered, only the last five are retained). The last stored word receives a group-end indicator, i.e., 1 at $q = 30$. All characters except tape feed (blank tape), delete code, and stop code can be entered; for example, lowercase letters can be stored.

Example: The input keyword A0000004' followed by the four words TOTAL' UNIT'S PRO'DUCED' would cause the information TOTAL UNITS PRODUCED to be stored into four consecutive memory locations without conversion into binary.

- +00LTSS'

The Instruction Input Keyword is treated by the subroutine exactly like an instruction.

The arbitrary instruction LTTSS contained within the keyword—where L is any positive machine instruction and TTSS represents any valid address—is executed immediately after either the input of a subsequent hexadecimal word or the input of a stop code (if no subsequent word is required). The address portion of the input keyword is not altered by the Address Modifier.

Each hexadecimal keyword and input word must be followed by a stop code. Left-side leading zeros within a word may be omitted. The computer returns to an input command without the execution of the instruction causing a branch. Jump instructions should be avoided.

Note: The instruction contained within the input keyword does not alter the fill counter.

Example: The input keyword +00h1637' followed by the hexadecimal word 73W08' would cause the value 00073W08 to be stored in location 1637.

- -000TTSS'

The Sequential Display Input Keyword causes the contents of location TTSS to appear in the accumulator when the computer stops. A start signal causes a return to an input command for a new keyword, provided that the PST switch is off. If the PST switch is on, the contents of $TTSS+i$ (where $i = 1, 2, \dots$) will appear in the accumulator.

With each start signal, i is incremented by 1. It is also possible to obtain the address of the displayed word by switching to single-step operation and starting the machine. (The B instruction that fetched the information just displayed will appear in the accumulator.) TTSS may be any arbitrary valid address.

Example: The input keyword -0003263' would directly display the contents of location 3263 in the accumulator.

Every entered word whose leftmost four bits correspond either to an ``8'' (negative instruction) or a zero (positive instruction) is treated as an instruction. The operand address is altered by the Address Modifier, unless the instruction is preceded by an ``X''. The subroutine allows the inclusion of index tags (used by some interpretive systems) immediately preceding the instructions. The inclusion of an ``X'' or an index tag does not alter the instruction in memory. If the leftmost four bits of a word correspond to any of the numbers 9 through 13, an error stop occurs (see the list of error stops).

Example: Let the Address Modifier be 0600. Different types of instruction words would be stored as follows:

Input	Storage
B 1234	B 1834
XB 1234	B 1234
800T 1234	800T 1834
80XT 1234	800T 1234
8B 1234	8B 1834
X8B 1234	8B 1234

The subroutine consists of two parts: hexadecimal input and decimal input. The hexadecimal input section can be used independently of the decimal input; however, the decimal input is dependent on the hexadecimal section, which must always be stored in memory.

CALLING SEQUENCE

The program is called manually by jumping to the starting address (regardless of which section is being used).

OPERATING INSTRUCTIONS

Program Input The tape contains the program in relocatable hexadecimal form with its own bootstrap loader. Operation is performed as follows:

- Place the program tape into the typewriter's reader mechanism and release all levers.
- Set the mode selector switch to Manual Input on the console.
- Press Start Read on the Flexowriter.
- Press Fill Clear on the console.
- Press Start Read.
- If the program is to be relocated, enter the starting address in hexadecimal form via the typewriter (typically the starting address is 0000); otherwise, omit this step.

- g) Set the mode selector switch to Single Step.
- h) Press Execute on the console.
- i) Repeat steps b) through h) until ``normal'' is completely printed out by the computer.
- j) Set the mode selector switch to NORMAL.
- k) Press START on the console.
- l) The program automatically continues reading in.

Note: If the PS-32 switch is turned *off*, the computer stops after reading in the hexadecimal input section. If the PS-32 switch is turned *on* or if START is pressed, the decimal input section or a hexadecimal object program tape will be read in.

PS-32 should be turned *off* before the decimal input section is completely read in; otherwise, the reader mechanism will continue to operate without tape after the read-in process is complete.

The bootstrap always occupies locations 0000 and 0002...0008 (absolute), while the remainder resides in the area designated for the hexadecimal input section.

INSTRUCTIONS FOR RELOADING

The bootstrap remains intact in memory if the program has not been relocated. To re-load the program without the bootstrap, proceed as follows:

- a) Place the program tape into the reader, specifically aligning it at the blank tape section between the bootstrap and the program.
- b) Set the mode selector switch to Manual Input on the console.
- c) Enter C0000 via the typewriter.
- d) Press Fill Clear on the console.
- e) Enter the modifier in hexadecimal form (all 8 characters), or enter 8 zeros if the program is not to be relocated.
- f) Set the mode selector switch to Single Step on the console.
- g) Press Execute on the console.
- h) Set the mode selector switch to Manual Input on the console.
- i) Enter U0008.
- j) Press Fill Clear on the console.

- k) Set the mode selector switch to Single Step on the console.
- l) Press Execute.
- m) Set the mode selector switch to NORMAL on the console.
- n) Press Start. The program will be read in automatically.

The C0000 and U0008 Instructions In the LGP-21 instruction set, C is the Clear and Transfer instruction (storing the accumulator contents in memory), and U is the Unconditional Jump instruction. Entering U0008 manually forces the to skip the initial bootstrap block and jump straight to the start of the primary loader routine at location 0008.

REQUIRED INPUT/OUTPUT UNITS

Input units other than the standard typewriter must be specified by a selection code. Output units are not required.

THE EFFECT OF THE PROGRAM JUMP SWITCHES

- PS-32 (Program Switch 32)
 - OFF:
 - * The computer stops before executing a jump when a Stop and Jump Input Keyword is used.
 - * The computer stops after reading in the hexadecimal input section of the subroutine.
 - ON
 - * No stop occurs when a Stop and Jump Input Keyword is used.
 - * No stop occurs after reading in the hexadecimal or decimal section of the subroutine.
- PST (Program Switch-Typewriter)
 - OFF: Only the contents of a single, specific location will appear in the accumulator.
 - ON: Consecutive locations can be loaded into the accumulator by repeatedly pressing the Start button.

MESSAGES

E (Input Error) Cause:

- Hexadecimal Tape Input: This character indicates a checksum error.
- Decimal Tape Input: This character indicates an invalid input code.

Remedy:

- a) Move the tape back to the last M or V input keyword.
- b) Press START (the input unit does not need to be re-selected).

Remedy for an Invalid Input Code (the last word read contains the error):

- a) Press Manual Input on the typewriter.
- b) Set the mode selector switch to Manual Input.
- c) Enter a jump to the starting address of the subroutine in hexadecimal form (i.e., U0000 or the respective starting address). If the subroutine begins in memory location 0000, steps c), e), and h) may be omitted.
- d) Press Clear and Input (Fill Clear) (TR).
- e) Set the mode selector switch to Single Operation (Single Step) (TR).
- f) Press Execute (TR).
- g) Set the mode selector switch to Normal (TR).
- h) Press Start (TR). The typewriter lamp lights up.
- i) Input the correct input code.
- j) If the typewriter is the active input unit, release the Manual Input lever, and the tape will continue reading.
- k) If another input unit is used, enter its selection code, press the Computer Start lever, then press Start (TR), and the tape will continue reading.

W (Write/Verify Error) This printout indicates that a verification error occurred during the reading of a hexadecimal tape (i.e., the word actually stored in memory did not match the word read from the tape).

This error is remedied in the same manner as a checksum error.

Tape verification By modifying two instructions in the subroutine, it can be used to verify hexadecimal tapes. For example, after a hexadecimal tape has been punched, alter the two instructions in the subroutine and then read the hexadecimal tape in.

The subroutine will read the tape (without storing it) and compare it word-for-word with memory. The checksums are also verified. If the comparison is unsuccessful, the program halts with the error stop ``W'' or ``E''. The tape is correct if it reads through without difficulty.

The instructions to be modified are:

Memory Location	Old Contents	New Contents
L+24	H []	U 0025
L+31	Y 0024	U 0032

ADDRESS NOTATION LEGEND

Ø Machine instruction code, represented as a letter.
 TT Track portion of the address, in decimal (00--63).
 SS Sector portion of the address, in decimal (00--63).
 NN Number of words to read, in decimal.
 HHHH Hexadecimal memory address.

INSTRUCTION KEYWORD QUICK REFERENCE

Keyword Format	Basic Meaning
ØTTSS	Instruction -- may be modified.
XØTTSS	Instruction -- may not be modified.
800ØTTSS	Negative instruction -- may be modified.
80XØTTSS	Negative instruction -- may not be modified.
IØTTSS	Instruction with index tag -- may be modified.
XIØTTSS	Instruction with index tag -- may not be modified.

DETAILED OPERATION SUMMARY

Keyword	Operation & Detailed Description
MNNKHHHH	<i>Fill with Relocatable Words</i> Read NN hexadecimal words into memory, starting at location HHHH + modifier. If bit 31 is 1, operand address is modified. Checksum calculated and compared with word NN+1.
VNNCHHHH	<i>Fill with Non-relocatable Words</i> Read NN hexadecimal words into memory, starting at location HHHH. If bit 31 is 1, operand address is modified. Checksum calculated and compared with word following the NN words previously read.
/000TTSS	<i>Set Modifier</i> Sets an address modifier to TTSS. Modifier is added to all hexadecimal fields that have bit 31 set, and to the addresses of decimal instructions not preceded by an X.

Keyword	Operation & Detailed Description
.000TTSS	<i>Stop and Jump Absolute</i> Sets program counter to TTSS and stops execution. If PS-32 is ON, execution continues.
.100TTSS	<i>Stop and Jump Relative</i> Sets program counter to TTSS + modifier and stops. If PS-32 is ON, execution continues.
S000TTxx	<i>Device Select</i> Selects (decimal) input device TT (xx is ignored) and stops. To continue, press START.
;000TTSS	Decimal Fill Reads decimal instructions into memory starting at address TTSS.
,00000NN	Hexadecimal Fill Reads NN hexadecimal words into the following NN consecutive locations.
A00000NN	Alphanumeric Fill Reads NN alphanumeric words into the following NN consecutive locations.
+00ØTTSS	Execute Immediate Executes the instruction ØTTSS contained within the keyword. If the instruction has no operand, enter a stop code. Otherwise enter the operand word in hexadecimal notation an a stop code.
-000TTSS	Sequential Dump The contents of location TTSS are shown in the console's accumulator display when the computer stops. After pressing START, the computer requests an command if PST is OFF. If PST is ON, pressing START causes the contents of TTSS+1 to appear in the accumulator, and so on. The address of the location currently shown in the accumulator display appears in the accumulator if you switch to ``Single Operation'' and press Start.

PROGRAM LOADER 2 — J1-10.1

PURPOSE

J1-10.1 is a general-purpose memory loader and monitor utility, hereafter referred to as GPMon. It accepts arbitrarily relocatable decimal programs, hexadecimal words, and alphanumeric words. It can also read non-relocatable hexadecimal programs, calculate checksums, and verify them against the checksums on the hexadecimal tape.

Additionally, this program can load memory contents directly into the accumulator, execute instructions directly without storing them in memory, and perform manual program jumps.

STORAGE REQUIREMENTS

Memory	3 tracks (192 words)
Temporary storage	None

COMMANDS

GPMon commands dictate how the utility processes incoming tape data; they are used to:

- a) set the format for subsequent data words,
- b) store specific words into memory, or
- c) execute instructions immediately in the accumulator.

These input commands, and the formats of the words that follow them, are discussed on the following pages. (Please note that if you are entering GPMon commands from the keyboard, you must type the command followed by a stop code (') to mark the end of the input, and then press START to execute it.)

- ;000TTSS': Start Fill

The Start Fill command sets the starting address TTSS for a series of words to be stored. This value is kept in the ``fill counter'` --- a word within the GPMon program --- and designates which location will receive the next word. The counter is incremented every time a word other than a keyword is successfully read and stored.

The words to be read in may be instructions, hexadecimal words, or alphanumeric words. Words are stored into consecutive locations until input ends or another fill keyword appears. The TTSS address must be in decimal track/sector notation, followed by a stop code. Any physical address in memory can be used. For example, the keyword ;0001600' causes fill to start at address 1600.

- `[prefix]0TTSS'` Instruction Input

The parsing subroutine identifies a word as an instruction by inspecting its leading bits. A valid instruction must contain zeros in bit positions 1 through 3; bit 0 acts as the sign bit with a 0 for standard instructions or a 1 for negative instructions. When this bit pattern is recognized, the word is interpreted as an instruction consisting of an alphabetical command mnemonic (here represented by 0) followed by a four-digit decimal operand address (*TTSS*)³¹.

If the accumulator is cleared prior to input, leading zeros (those preceding the instruction) may be omitted. The entire instruction is converted into its binary equivalent and stored in the location specified by the fill counter.

An optional prefix may be added to indicate that instructions are negative, non-relocatable, or both.

Prefix	Properties
(no prefix)	Positive, relocatable instruction
-	Negative, relocatable instruction
X	Positive, non-relocatable instruction
-X	Negative, non-relocatable instruction

Non-relocatable instructions will be stored exactly as given and their address field will not be adjusted by the address modifier.

- `/000TTSS'` Set Address Modifier

This command sets GPMon's internal address modifier to the decimal TTSS value specified. The modifier value is added to the operand address of all subsequent instruction words, unless the instruction is preceded by an X.

The modifier remains in effect until it is changed by another Set Address Modifier command. The modifier may be set to any real address in decimal track/sector notation, followed by a stop code.

Example: the keyword `/0001100'` sets the address modifier value to 1100. This value is added to the address field of all subsequent instructions that are not preceded by an ```X'`:

Instruction Read	Instruction Stored
B2611'	B3711
XB2611'	B2611
800Z0400'	800Z1500
80XZ0400'	800Z0400

³¹Refer to the *LGP-21 Reference Manual*[9] for the defined instruction mnemonics.

- .000TTSS' Stop and Jump

When this command is entered, the computer stops execution and sets the program counter to TTSS. If PS-32 is OFF, the computer halts. Pressing START resumes execution at TTSS. If PS-32 is ON, the computer jumps to location TTSS and continues execution immediately.

Example: the keyword .0002000' with PS-32 OFF causes the computer to halt; when the START button is pressed, a jump to 2000 occurs and execution continues from there.

- +[*prefix*]ØTTSS' Direct Execute

This keyword enables the programmer to have the computer execute an instruction directly. The instruction ØTTSS contained within the keyword (where Ø represents a valid opcode symbol and TTSS is any real address in decimal track/sector notation) is executed following the entry of a hexadecimal word and/or a stop code. The second hexadecimal word is loaded into the accumulator.

The address portion of the command entered is *not* modified by the address modifier; nor is any hexadecimal word entered as a secondary word. All keywords and additional hexadecimal words must be followed by a stop code. Leading zeros in the hexadecimal word may be omitted.

The Direct Execute command allows you to immediately execute a command without writing it to memory.

For example, if we wished to execute an H command to store the hexadecimal word 73W08 into location 1637, the command sequence +00H1637'73W08' causes the value 00073W08 to be stored in location 1637. As a second example, the command +00U1735'' (note the two stop codes to indicate ``no second word'') causes a jump to 1735.

The keyword for the direct command does not alter the fill counter; any subsequent fill continues from the last fill location.

- ,00000NN' Store Hexadecimal Words

This command causes the following NN words to be stored as hexadecimal words in consecutive locations according to the current state of the fill counter. NN must be less than 64. The words to be stored must be in hexadecimal format and are not modified.

For example, ;0002200',0000003',3W7'140Q''³² causes the memory to look like this after entry:

³²This example string features three consecutive inputs after setting the fill address to 2200: 3W7', 140Q', and a final empty input before the last stop code. Because leading zeros can be dropped and a solo stop code represents zero, the monitor correctly shifts and pads them into full 32-bit words, parsing '' correctly as zero, and clearing location 2202 to all zeroes.

Location	Contents
2200	000003W7
2201	0000140Q
2202	00000000

A hexadecimal word may contain a maximum of eight characters. Any combination of the characters 0,1,...,9 and F,G,J,K,Q,W may be used; 00000000 is the smallest value and WWWWWWWW is the largest value the computer can accept. If a word is zero, only a stop code is required. Leading zeros may be omitted; every word must be followed by a stop code.

- VNNCHHHH' Checksummed Hexadecimal Fill

This keyword causes the following NN hexadecimal words to be stored in consecutive locations, beginning with HHHH (a Start Fill command is not required to begin filling memory). The C is a clear instruction [sic]³³. This keyword uses hexadecimal notation and is normally generated by a hexadecimal output program, where it is found at the beginning of a block of 64 (or fewer) hexadecimal words.

During input, a checksum is computed from the keyword and the following NN hexadecimal words. Once all NN words are stored, the program checks the PST switch. If it is OFF, the computed checksum is compared with the tape checksum word following the final word. If they are equal, reading continues; if they are unequal, an error stop occurs. See under ``Error Stops.''' If PST is ON, the checksum comparison is skipped.

For example, the keyword V1WC2W00' causes the next $1W_{16} = 31_{10}$ hexadecimal words to be stored, beginning in location $2W00_{16} = 4700_{10}$.

- A00000NN' Alphanumeric Word Fill

This keyword permits the entry of alphanumeric information in a 6-bit format³⁴. Information read in this manner can be punched back out directly by print commands without any conversion, or handled by an alphanumeric print program.

Every word, with the exception of the last word of a block, must contain exactly 5 characters (the last word may contain fewer) and must be followed by a stop code. The quantity NN of words to be stored must be less than 64. The NN words are stored in

³³It is not at all obvious *what* we are clearing; may need to run this in the simulator, snapshot memory, and compare before/after dumps to see whether this actually clears a memory location, or if it is a hijacked C instruction

³⁴See table 3 in the *LGP-21 Reference Manual*[9]

consecutive locations (at $q = 29$), starting at the location indicated by the current state of the fill counter.

For example, the entry A0000005' DEPRE'SS ST'ART T'O CON'TINUE' causes the string ``DEPRESS START TO CONTINUE'' to be stored across five consecutive locations.

- -000TTSS' Examine

The Examine keyword loads words from memory into the accumulator. If the computer's console is equipped with an oscilloscope display, the programmer can view the contents of the accumulator without executing any instructions. Words are loaded sequentially, starting at TTSS. To examine the next word, press the START key.

To exit³⁵ the Examine command and return to normal operation:

1. Set the MODE switch to MANUAL INPUT.
2. Press FILL CLEAR.
3. Set the selector switch to NORMAL.
4. Press START.

For example, the keyword -0002003' loads the contents of location 2003 into the accumulator. After pressing START, the contents of 2004 appear, and so on. This process can be continued until the above sequence of operations interrupts the command.

- S000TTss' Input Device Select

This command causes an alternate input device to be selected (other than the default console Flexowriter). The program reverts to console input when GPMon starts (via a branch to 0000) and following error stops. The selection codes and their corresponding units are listed on p. 30 in the *LGP-21 Reference Manual*[9].

The selection codes must be specified in decimal track/sector notation TTSS, followed by a stop code (the sector portion value is irrelevant). For example, if another input device could be selected by the identification number 32, the selection keyword S0003200' causes this device to be selected for this routine's input.

Tapes to be read by the program should be capable of being typed out on the typewriter; that is, a carriage return should occur after every four to eight words³⁶.

³⁵Because this monitor instruction takes over the machine's primary execution cycle, stepping through and examining the contents of memory instead of executing instructions, it is necessary to force a manual reset of the input buffer via the console switches to restore standard program control.

³⁶Data tapes should contain a carriage return (CR) after every four to eight words simply because of the mechanical realities of working with a hardware Flexowriter as console. If a continuous stream of data was read off a tape without embedded carriage returns, the physical

If incorrect information is read, the program selects the console typewriter³⁷, prints err, and halts. See ``Error Stops'' (Section 9).

PROGRAM EXECUTION

The following steps are necessary to load the program from tape:

1. Press the MANUAL INPUT lever on the Flexowriter.
2. Set the selector switch on the system console to MANUAL INPUT³⁸.
3. Press FILL AND CLEAR³⁹ on the console.
4. Set the selector switch to NORMAL.
5. Press the START button.

OPERATING INSTRUCTIONS

Initial Load The program tape contains the software in two separate versions: a) a relocatable hexadecimal format with its own bootstrap routine, and b) a decimal format matching the standard coding sheet layout.

The input procedure is executed as follows:

- a) Insert the tape into the typewriter's tape reader. Ensure that all typewriter levers are released.
- b) Press the I/O button on the computer panel.
- c) Set the MODE switch to MAN INPUT.
- d) Press START READ on the typewriter.
- e) Press FILL CLEAR on the computer panel.
- f) Press START READ on the typewriter.
- g) Set the MODE switch to ONE OPER on the computer panel.

typing element would reach the end of its travel at the right margin and continue to push against the margin as more characters are printed. This both imposes mechanical strain and overprints the input as an unreadable mess of characters at the edge of the log sheet.

³⁷Automatically reverting control back to the primary console upon start/restart at 0000 or after an error stop is a fail-safe. If an external high-speed paper tape reader or secondary device feeds malformed data or fails mid-transfer, the system won't lock up; it immediately brings the main console back online so the operator can see the error state and intervene.

³⁸This dual mechanical lockout prevented the computer from attempting to read from the console until the operator has explicitly prepared both the peripheral device and the central processing unit to accept manual keypresses.

³⁹Pressing FILL AND CLEAR clears the machine's primary instruction and input registers, ensuring that when the mode switch is set to NORMAL and START is pressed, the processor begins execution from the starting address of the J1-10.1 routine without processing residual data or garbage instructions.

- h) Press EXECUTE on the computer panel.
- i) Repeat steps c) through h) twice; then proceed to step j).
- j) Set the mode selector switch to MAN INPUT on the computer panel.
- k) Press START READ on the typewriter.
- l) Press FILL CLEAR on the computer panel.
- m) Set the MODE switch to ONE OPER on the computer panel.
- n) Press EXECUTE on the computer panel.
- o) Set the MODE switch to NORMAL on the computer panel.
- p) Press START on the computer panel. The remainder of the tape is automatically read in, and the computer then comes to a halt.
- q) Press MAN INPUT on the typewriter.
- r) Press START on the computer panel.
- s) The typewriter's MANUAL INPUT indicator lamp lights up, signaling that the computer is ready for manual keyboard input.

Re-reading the Tape If the program fails to execute after step r), or if it becomes corrupted in memory after loading, the bootstrap routine may still be intact. In this case, the program can be reloaded without re-entering the bootstrap sequence by proceeding as follows:

- a) Place the tape into the reader, skipping past the bootstrap section so that the bootstrap is not reread using the tape feed/leader.
- b) Set the mode selector switch to ``Manual Input'' on the computer panel.
- c) Press START READ on the typewriter.
- d) Press FILL CLEAR on the computer panel.
- e) Set the MODE switch to ONE OPER on the computer panel.
- f) Press EXECUTE on the computer panel.
- g) Set the mode selector switch to NORMAL.
- h) Press START on the computer panel. The tape will be read in, and the computer will then come to a halt.

If the tape fails to read properly this time, the entire initial load bootstrap procedure must be repeated from the beginning.

REQUIRED INPUT/OUTPUT UNITS

If an input unit other than the typewriter's paper tape reader is to be selected, the selection command (S) must be used. The program selects the required output units automatically.

MEANING OF THE PROGRAM SWITCH KEYS

Switch	State	Result
PS-32	OFF	The computer halts before jumping when a Stop and Jump command is executed.
	ON	The computer executes the Stop and Jump without halting.
PST	OFF	Checksums are compared when reading hexadecimal tapes.
	ON	Checksums are <i>not</i> compared when reading hexadecimal tapes.

ERROR STOPS

Message	Meaning and Resolution
err	The computer has detected an error. After entering a hexadecimal fill keyword (V): a) Back up the tape to the last input keyword. b) Press START (on the computer). In the case of an incorrect or missing word: a) Press Manual Input (on the typewriter). b) Press START (on the computer). c) Enter the correct word. d) Release Manual Input (on the typewriter). e) Press START (on the computer). (Note: The last word read contains the error).

Note: Following an error stop, the subroutine automatically selects the typewriter for input.

REMARKS

This program cannot process data words (or constants) in decimal notation.

When a tape is read in, GPMon examines the sign and the three most significant bits of each input word⁴⁰ and jumps to the corresponding

⁴⁰In the LGP-21 machine word layout, this specific bit slice contains the bits that distinguish an executable instruction from a raw data pattern, enabling GPMon to use a fast software jump table.

command.

A program can be broken down into logically independent sections, some of which can be reused in other programs. Examples of this include all kinds of subroutines, standard input and output routines, and programs for mathematical sub-problems. To make these sections available for use by other programs, they will need to be assigned when loaded to separate memory areas such that no two subprograms share the same memory block. To this end, these program sections should be coded relative to address 0000. By using the Start Fill (;) and Address Modifier (/) commands, the programmer can place the program into any arbitrary block of unused memory without disrupting the relationship of the instructions to one another. (Instructions in these sections which are not to be changed by the Address Modifier must be preceded by an X.)

On the other hand, if it is unnecessary to do so, the modification of an entire instruction group can be avoided by simply setting the address modifier to zero. There are no ``reserved'' blocks of memory; the programmer may use the LGP-21's memory as they see fit.

SUMMARY

Keyword	Meaning & Detailed Description
ØTTSS	Relocatable instruction Instruction to be altered by the address modifier.
XØTTSS	Non-relocatable instruction Absolute instruction; not altered by the address modifier.
-ØTTSS	Relocatable negative instruction Instruction with negative sign bit or inverted logic flag; modifiable.
-XØTTSS	Non-relocatable negative instruction Instruction with negative sign bit or inverted logic flag; not modified.
;000TTSS	Start Fill Store the following words (modifier excluded) in consecutive locations starting at TTSS.
/000TTSS	Set Address Modifier Set the address modifier base to TTSS. Add this value to all subsequent modifiable commands.
.000TTSS	Stop and Jump Halt (unless PS-32 is pressed) then jump to location TTSS when the START button is pressed.

Keyword	Meaning & Detailed Description
+00ØTTSS	Direct Command Immediately execute a command; a second (hexadecimal) word may be supplied as a data word.
,00000NN	Store Hexadecimal Words The next NN hexadecimal words are to be stored consecutively in the locations defined by the fill counter ($1 \leq NN \leq 64$).
VNNCHHHH	Hexadecimal Fill with Checksum Store NN hexadecimal words starting at HHHH ($1 \leq NN \leq 40_{16}$). For each group of words, including the command, a checksum is calculated. If PST is OFF, this checksum is compared with the checksum word punched on the tape just following the NN words. If PST is ON, no checksum comparison takes place.
A00000NN	Store Alphanumeric Words The next NN words are to be stored in consecutive locations as alphanumeric words containing 5 six-bit characters each at $q = 29$ ($1 \leq NN \leq 63$).
-000TTSS	Examine Load the word at TTSS into the accumulator. Press START to load the word at TTSS+1 into the accumulator, and so on. Exit this mode by executing a manual jump to 0000 to restart GPMon.
S000TTxx	Input Unit Select Select the designated input unit TT for continuous input by GPMon. (The xx portion of the command may be anything and is ignored.)

Legend:

Ø	Any defined opcode
TT	Track address (decimal)
SS	Sector address (decimal)
NN	Number of words to read in (decimal)
HHHH	Address expressed in hexadecimal notation

Translator's Notes

Rather than just a loader, GPMon is more of a programmer's interactive monitor.

Notably, PIR uses the Flexowriter stop code (') to terminate a command. GPMon does not. This means GPMon relies heavily on interactive execution via the Flexowriter keyboard, requiring you to physically hit the START COMP lever or START button on the computer to continue execution.

10 Data Input

DATA INPUT 1 — J2-10.0

PURPOSE

J2-10.0 reads data into the computer for use by a main program. The data, provided in decimal notation, is read in, converted to binary, shifted to the desired fractional bit position (q), and stored in designated memory locations. During each program execution run, the required quantity of decimal numbers can be converted and stored. All parameters regarding the type of conversion must be input alongside the data.

Data Input 1 functions as a subroutine and is called via a calling sequence in the main program. Before a jump to the subroutine occurs, the calling sequence must store the return address within the subroutine.

If an alternative input device is to be used instead of the default console typewriter, a suitable selection keyword must be included in the calling sequence. Upon return to the main program, all decimal numbers will have been converted and stored in the specified locations.

STORAGE REQUIREMENTS

Memory	4 tracks (256 words)
Temporary storage	None

INPUT REQUIREMENTS

To process decimal numbers using J2-10.0, the following information must be entered in the specified order, with each entry followed by a stop code ('):

1. **Decimal Places (P):** The number of decimal places P for each subsequent data word, entered in decimal form ($0 \leq P \leq 11$).
2. **Scale Factor (Q):** The value representing the fixed-point scaling factor q at which the words should be stored. Q must consist of exactly three characters, including the sign ($-36 \leq Q \leq +46$).
3. **Starting Address:** The initial destination address of the memory allocation block, specified in decimal track/sector notation (TTSS).
4. **Decimal Data:** Decimal numbers consisting of a maximum of 7 digits, preceded by a sign. Negative numbers must explicitly include the minus sign and all leading zeros to the left. For positive numbers, both the sign and leading zeros may be omitted.
5. **Control Character j :** The letter ``j' instructs the parser to stop reading data and prepare to read a new set of P , Q , and destination address parameters.

6. Control Character w: The letter ``w' terminates the routine and executes a return to the main program.

REMARKS

If the decimal place count P , scale factor Q , or the target address sequence changes mid-tape, a j command must be injected, followed by the updated P and Q values, and the target address (any parameters that are identical must be repeated).

Example Input Stream:

```
4'+13'2318'627138'48390'j'
2'+20'3800'5134'664'-0000047'w'
```

This sequence performs the following operations:

- The decimal numbers 62.7138 and 4.8390 are converted at a scaling factor of $q = 13$ and stored in locations 2318 and 2319, respectively.
- The control character j ends the block.
- The numbers 51.34, 6.64, and -0.47 are then converted at a scaling factor of $q = 20$ and stored in locations 3800, 3801, and 3802.
- The control character w stops input and triggers the return to the main program.

By default, the subroutine selects the standard console typewriter for input. A modified calling sequence to select an alternative input unit is available. When using the alternative sequence, the corresponding selection code must be loaded into the accumulator at $q = 23$ when the jump to the subroutine is executed.

CALLING SEQUENCES

Calling Sequence 1 selects the standard console typewriter for input. For alternative input devices, use Calling Sequence 2.

Memory Location	Instruction	Address	Meaning
α	R	L+138	Set return address.
$\alpha + 1$	U	L	Enter subroutine.
$\alpha + 2$	...		Return point to main program.

Calling Sequence 1 (Standard Input) The instruction at location α stores the return address ($\alpha + 2$) within the subroutine structures.

The instruction at $\alpha+1$ executes a branch to the start of the subroutine (L). Location $\alpha+2$ contains the first main program instruction to be executed after the subroutine finishes.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[TTSS]	Load alternative device selection code.
α	R	L+138	Set return address.
$\alpha + 1$	U	L+247	Enter subroutine at device override entry point.
$\alpha + 2$	...		Return point to main program.
TTSS	Z	SS00	Input device selection code data word.

Calling Sequence 2 (Alternative Input Device) The instruction at $\alpha-1$ loads the selection code for the new input unit into the accumulator. The instruction at α stores the return address ($\alpha+2$) into the subroutine. The instruction at $\alpha+1$ executes a branch to entry point L+247 of the subroutine. Here, the internal input device selection parameters are modified, and the subroutine runs normally until control returns to location $\alpha+2$ via a branch instruction at L+138.

PROGRAM LOADING INSTRUCTIONS

The routine tape contains the program in two distinct formats:

- A relocatable hexadecimal format compatible with loader program J1-10.0.
- A relocatable decimal format utilizing the standard coding sheet layout.

EXECUTION TIME

The program processes and converts decimal data into binary at an average rate of 35 five-digit numbers per minute.

REQUIRED INPUT/OUTPUT UNITS

The standard console typewriter is selected for input by default. No hardware output device is required. The device assignment can be altered dynamically via Calling Sequence 2 (see above).

OVERFLOW

Any arithmetic overflow conditions occurring during data entry or base conversion are intentionally ignored. The system's overflow register flag is automatically reset to zero before control returns to the main program.

DATA INPUT 2 — J2-10.1

PURPOSE

J2-10.1 reads data into the computer for use by a main program. The decimal data is read, converted to binary, shifted to the desired fractional bit position (q), and, if more than one number is processed, stored in consecutive designated locations. If only a single number is read, it remains in the accumulator after being shifted to its corresponding q . Any number of decimal values can be converted and stored via a single program call. The main program must supply all configuration parameters regarding the conversion.

This program functions as a subroutine called by a sequence in the main program. Prior to branching to the subroutine, the calling sequence must store both the starting address of the ****Conversion Control List**** and the return address inside the subroutine structure. Upon return to the main program, all data will have been converted and either stored in memory or left in the accumulator.

STORAGE REQUIREMENTS

Memory	4 tracks, 48 sectors (304 words)
Temporary storage	None

INPUT REQUIREMENTS

The data to be processed must be entered as 7-digit decimal numbers preceded by a sign. For positive numbers, both the sign and leading zeros may be omitted. Before jumping to the subroutine, the main program must have stored a ****Conversion Control List**** in consecutive memory locations. The structure of this list is as follows:

1. Word 1 (N): The number of data words to process, specified using track/sector notation (i.e., modulo 64 format).
2. Word 2 (L): The initial destination address for the data, specified in decimal track/sector notation.
3. Word 3 (Q and P): A single combined configuration word:
 - (a) Q (Track Portion): The target fixed-point scale factor q entered as a decimal track address ($-47 \leq Q \leq +36$).
 - (b) P (Sector Portion): The number of decimal places entered as a decimal sector address ($0 \leq P \leq 11$).

CONTROL MATRIX FLAGS

The subroutine utilizes the sign bits and specific instruction bits of the control list to determine state persistence from previous execution runs: * **Negative N :** If N is embedded in a negative instruction format (sign bit = 1), the word count from the previous run is preserved. * **Negative L :** If L is inside a negative instruction format, the storage destination address from the previous run is reused. All standard instruction bits for the N and L command entries must otherwise be 0. * **Negative Q :** If the combined Q/P word is negative, the value of Q (q) is treated as a negative scale factor. * **Initialization Override:** If the very first bit of the instruction location containing Q and P is a 1, the program reuses the exact configuration state of the previous execution run.

Special Case Values: * **$N = 0$:** The routine reads an unlimited stream of data words continuously until the block-termination character ``w' is encountered on the tape. * **$N = 1$:** The single data word read is converted and left in the accumulator at the specified q ; it is *not* written to the destination address L . * **Negative List Address Instruction:** The accumulator must hold an instruction containing the starting address of the control list when entering the subroutine. If this setup instruction is negative, the subroutine uses the exact control values from the prior run. * **Control Pre-Load Optimization:** If the first bit of the instruction containing the control list address is set to a 1, the subroutine pre-loads and sets up the new control values **without reading any data tape**. This allows setup parameters to be configured just once for an entire sequence of subsequent operations.

Alternative Input Unit Selection: If the input hardware device is to be changed, an alternative calling sequence must be used (by default, the subroutine reverts to the console typewriter). A device change requires a **fourth word** added to the Conversion Control List. This extra word must contain the destination device identification selection code specified as a decimal track address. This assignment remains active until explicitly overwritten by a new selection word.

APPLICATION EXAMPLES

Note: Addresses enclosed in parentheses represent relative internal offsets inside the subroutine space.

Example 1: Standard Block Load This configuration instructs the subroutine to ingest 90 decimal words from the tape, convert them to binary, scale them to $q = 12$ with 5 decimal places, and store them

Memory Location	Instruction	Address	Meaning
0500	000Z	2430	Starting address of Control List
0610	000B	0500	Load list pointer into accumulator
0611	000R	(0442)	Set return address
0612	000U	(0445)	Jump to subroutine entry point
0613	...		Main program execution resumes
2430	000Z	0126	$N = 90$ words ($01_{track} \times 64 + 26_{sector} = 90_{10}$)
2431	000Z	4200	$L =$ Destination location 4200
2432	000Z	1205	$Q = q = 12$, $P = 5$ decimal places

sequentially beginning at location 4200. Control then returns to main program location 0613.

Memory Location	Instruction	Address	Meaning
0501	000Z	2433	Starting address of Control List
0729	000B	0501	Load list pointer
0730	000R	(0442)	Set return address
0731	000U	(0445)	Jump to subroutine
0732	...		Main program execution resumes
2433	000Z	0000	$N = 0$ (Read indefinitely until w)
2434	800Z	0000	Negative instruction flag: Reuse destination address L from previous run
2435	800Z	0109	Negative scale flag: $Q = q = -01$, $P = 9$ decimal places

Example 2: Indefinite Tape Stream with Reused Base Address This configuration processes an unknown length of data words until a stop code ``w'' marks the end of the block. The numbers are scaled to $q = -1$ with 9 decimal places and stored sequentially starting directly

from the last memory address boundary computed during the previous subroutine invocation.

Memory Location	Instruction	Address	Meaning
0502	000Z	2436	Starting address of Control List
1925	000B	0502	Load list pointer
1926	000R	(0442)	Set return address
1927	000U	(0445)	Jump to subroutine
1928	...		Main program execution resumes
2436	000Z	0001	$N = 1$ word (Leave in Accumulator)
2437	000Z	1340	$L = 1340$ (Dummy address required by parser, but ignored)
2438	000P	0000	First bit is 1: Reuse Q (q) and P states from previous run

Example 3: Single Word Accumulator Read The subroutine reads a single decimal value from the tape, converts it using the exact scale settings leftover from the last run, and leaves the value directly in the accumulator. No data is written to location 1340.

Memory Location	Instruction	Address	Meaning
0503	800Z	0000	Negative pointer instruction: Reuse prior configuration
3618	000B	0503	Load negative pointer execution command
3619	000R	(0442)	Set return address
3620	000U	(0445)	Jump to subroutine
3621	...		Main program execution resumes

Example 4: Total Control List Persistence Because the pointer token at 0503 has its sign bit set to negative, the subroutine bypasses parsing new parameters entirely and mirrors the execution profile of the preceding run.

Memory Location	Instruction	Address	Meaning
0504	000P	2439	Opcode is P (First bit is 1): Configuration initialization entry point
1231	000B	0504	Load control initialization command
1232	000R	(0442)	Set return address
1233	000U	(0413)	Jump to secondary initialization entry point
1234	...		Main program execution resumes
2439	800Z	0000	Negative instruction flag: Reuse N from previous run
2440	000Z	1500	Set new target address $L = 1500$
2441	000Z	2700	Set new scale settings: $Q = q = 27$, $P = 0$ decimal places
2442	000Z	0400	Hardware override: Select alternative input device code 04

Example 5: Non-Reading Control Parameter Ingestion Because the entry command at 0504 uses an initialization opcode format starting with a 1 bit pattern, and points to subroutine entry point (0413), the routine loads the new parameters, updates the hardware pointer to device 04, but **does not read any data from the tape reader**. Control returns immediately to location 1234.

CALLING SEQUENCES

Utilize Calling Sequence 1 if the input unit selection remains unchanged. Use Calling Sequence 2 to declare a new input device structure.

Calling Sequence 1 (Retain Input Unit)

Calling Sequence 2 (Modify Input Unit) The input hardware unit used by the system will dynamically match whichever device selection code is currently declared inside the Conversion Control List.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[List]	Load the pointer instruction containing the Control List address.
α	R	L+442	Set return address.
$\alpha + 1$	U	L+445	Jump to subroutine main entry point.
$\alpha + 2$	...		Return point to main program.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[List]	Load the pointer instruction containing the Control List address.
α	R	L+442	Set return address.
$\alpha + 1$	U	L+413	Jump to device-configuration entry point.
$\alpha + 2$	...		Return point to main program.

OPERATING INSTRUCTIONS

1. **Execution Time:** The program processes and converts decimal data into binary at an average rate of 40 five-digit numbers per minute.
2. **Program Loading Instructions:** The routine tape contains the software in two distinct formats:
 - a) A relocatable hexadecimal format compatible with loader program J1-10.0.
 - b) A relocatable decimal format utilizing the standard coding sheet layout.
3. **Required Input/Output Units:** The subroutine automatically selects the standard console typewriter for input, unless an alternative unit override has been explicitly established via Calling Sequence 2. No hardware output devices are required.
4. **Overflow:** Any arithmetic overflow conditions occurring during data entry or base conversion are explicitly ignored upon input. The CPU's internal overflow register flag is automatically cleared and reset to zero before the routine exits back to the main program.

TECHNICAL NOTE

To maintain maximum mathematical accuracy and prevent underflow or truncation errors during fixed-point binary conversion, the programmer should always specify the smallest practical scale factor value Q (q) necessary for the expected data range.

DATA INPUT 3 — J2-10.2

PURPOSE

J2-10.2 converts a single signed 7-digit decimal number into binary, or reads and converts it in a single operation.

This program functions as a subroutine called by a sequence in the main program. Prior to branching to the subroutine, the calling sequence must store the return address within the subroutine structures. Depending on the calling sequence chosen, the integer to be converted must already reside in the accumulator. Upon return to the main program, the converted binary number is left in the accumulator at $q = 30$.

STORAGE REQUIREMENTS

Memory	1 track, 9 sectors (73 words). (<i>Note: The program must be loaded to start at sector 00 of an arbitrary track.</i>)
Temporary storage	None

INPUT REQUIREMENTS

The input variable is a decimal number N , which is either read directly from tape by the subroutine or supplied internally by the main program:

- **Tape Input via Subroutine:** N may consist of up to seven decimal digits plus a sign. For positive numbers, the plus sign may be omitted. For negative numbers, the minus sign must explicitly precede the seven digits.
- **Internal Input via Accumulator:** If the number is supplied by the main program, it must already be loaded into the accumulator at either $q = 30$ or $q = 31$, depending on the calling sequence used.
- **Sign Bit Positions:** The sign of the pre-loaded number is determined dynamically by specific bit slices:
 - If N is at $q = 30$, the sign is indicated by **bit position 2**.
 - If N is at $q = 31$, the sign is indicated by **bit position 3**.

A 1 in the respective bit position designates a negative number, while a 0 designates a positive number.

CALLING SEQUENCES

Calling Sequence 1 must be used if N is to be read from tape by the subroutine. If N is supplied internally by the main program, choose Calling Sequence 2 (for N at $q = 31$) or Calling Sequence 3 (for N at $q = 30$).

Memory Location	Instruction	Address	Meaning
α	R	L+44	Set return address.
$\alpha + 1$	U	L	Enter subroutine at tape-read entry point.
$\alpha + 2$	...		Return point to main program; N read from tape.

Calling Sequence 1 (Tape Input) The instruction at location α stores the return address ($\alpha+2$) inside the subroutine. The instruction at $\alpha+1$ executes a branch to the initial starting address of the subroutine (L). Location $\alpha+2$ contains the first main program instruction executed after the subroutine runs.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	I		Read/Input N into the accumulator.
α	R	L+44	Set return address.
$\alpha + 1$	U	L+2	Enter subroutine at $q = 31$ handling entry point.
$\alpha + 2$	...		Return point to main program.

Calling Sequence 2 (Accumulator Input at $q = 31$) The instruction at $\alpha-1$ reads or brings N into the accumulator. The instruction at α stores the return address ($\alpha+2$). The instruction at $\alpha+1$ executes a branch to entry offset L+2. Note that a 1 (negative) or 0 (positive) in bit position 3 of the accumulator dictates the sign evaluation, and N is processed at $q = 31$.

Calling Sequence 3 (Accumulator Input at $q = 30$) The instruction at $\alpha-1$ loads N from memory into the accumulator. The instruction at α sets the return address ($\alpha+2$). The instruction at $\alpha+1$ executes a branch to entry offset L+58. Note that a 1 (negative) or 0 (positive) in bit position 2 of the accumulator dictates the sign evaluation, and N is processed at $q = 30$.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[Dest]	Bring N from memory into the accumulator.
α	R	L+44	Set return address.
$\alpha + 1$	U	L+58	Enter subroutine at $q = 30$ handling entry point.
$\alpha + 2$	...		Return point to main program.

OUTPUT

Upon return to the main program sequence, the converted binary representation of the decimal number N resides completely within the accumulator scaled exactly to $q = 30$.

OPERATING INSTRUCTIONS

1. **Execution Time:** The program requires approximately 1.1 seconds to read and binary-convert a single 5-digit decimal number.
2. **Program Loading Instructions:** The routine tape contains the software in two distinct formats:
 - a) A relocatable hexadecimal format compatible with loader program J1-10.0.
 - b) A relocatable decimal format utilizing the standard coding sheet layout.
3. **Required Input/Output Units:** When executing Calling Sequence 1, the subroutine automatically selects the standard console typewriter for input. For Calling Sequences 2 and 3, device selection is purely a function of the main program logic. No hardware output devices are required.
4. **Overflow:** Arithmetic overflow states are neither evaluated nor altered by this program.

DATA INPUT 4 — J2-10.3

PURPOSE

J2-10.3 reads data into the computer for use by a main program. It reads a predetermined number of decimal data words, converts them to binary, aligns them according to a specified decimal point (P), and stores them in consecutive locations at a designated scale factor. During a single program execution run, any quantity of decimal numbers can be converted and stored. All parameters regarding the conversion must be supplied by the main program.

The program functions as a subroutine called via a calling sequence in the main program. The calling sequence must supply the starting address of the Conversion Control List as well as the return address. Upon return to the main program, all data has been converted to binary and stored.

STORAGE REQUIREMENTS

Memory	3 tracks, 52 sectors (244 words)
Temporary storage	None

INPUT REQUIREMENTS

The decimal numbers to be converted can consist of an algebraic sign and up to seven digits. A negative number must explicitly consist of its minus sign and seven digits; for positive numbers, both the sign and leading zeros may be omitted.

The number of decimal values N to be read is limited only by the available memory space. The number of decimal places P must satisfy: $0 \leq P \leq 11$. The scale factor value must satisfy: $-36 \leq \text{scale factor} \leq +47$.

The Conversion Control List, which occupies consecutive locations, is structured as follows:

1. Word 1 (Q and P): A single combined configuration word:
 - (a) Q (Track Portion): The target fixed-point scale factor entered as a two-digit decimal track address.
 - (b) P (Sector Portion): The number of decimal places entered as a two-digit decimal sector address.
2. Word 2 (N): The number of words to be read, specified in track/sector notation (i.e., modulo 64 format).
3. Word 3 (Address): The initial destination address for the data, specified in decimal track/sector notation.

The scale factor is negative if the instruction containing Q is formatted as a negative instruction (sign bit = 1). All other instructions in the control list must be positive.

Additionally, an instruction containing the starting address of the Control List must be present. This instruction must reside in the accumulator when the jump to the subroutine is executed.

If the selection of the input unit is to be modified, a special calling sequence must be used (by default, the subroutine selects the standard console typewriter). This requires a **fourth word** in the Conversion Control List, which contains the desired device selection code as a decimal track address. This selection code remains effective until explicitly replaced by a different one.

CALLING SEQUENCES

If the standard console typewriter is to be used as the input device, Calling Sequence 1 must be used. Calling Sequence 2 is intended for variable device selection override.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[List]	Load starting address of Control List.
α	R	L+351	Set return address.
$\alpha + 1$	U	L+308	Enter subroutine at standard entry point.
$\alpha + 2$	...		Return point to main program.

Calling Sequence 1 (Standard Input) The instruction at $\alpha - 1$ loads the instruction containing the starting address of the Control List into the accumulator. The instruction at α stores the return address ($\alpha + 2$) within the subroutine structures. The instruction at $\alpha + 1$ causes a jump to location L+308 of the subroutine, where L is the base address of the subroutine. Location $\alpha + 2$ contains the first instruction of the main program to be executed after completing the subroutine.

Calling Sequence 2 (Variable Device Selection Override) Calling Sequence 2 is identical to Calling Sequence 1, except for the instruction at $\alpha + 1$. This instruction causes a jump to L+300, so that the desired device selection is performed based on the selection code provided in the fourth word of the Control List.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[List]	Load starting address of Control List.
α	R	L+351	Set return address.
$\alpha + 1$	U	L+300	Enter subroutine at device-selection entry point.
$\alpha + 2$	...		Return point to main program.

OPERATING INSTRUCTIONS

1. **Execution Time:** The program reads and binary-converts decimal data at an average rate of 40 five-digit numbers per minute.
2. **Program Loading Instructions:** The routine tape contains the software in two distinct formats:
 - a) A relocatable hexadecimal format compatible with loader program J1-10.0.
 - b) A relocatable decimal format utilizing the standard coding sheet layout.
3. **Required Input/Output Units:** The subroutine automatically selects the standard console typewriter for input, unless an alternative device selection override has been established via Calling Sequence 2. No hardware output devices are required.
4. **Overflow:** Any arithmetic overflow conditions occurring during data entry or base conversion are ignored upon input, but the overflow flag is automatically reset to zero prior to returning to the main program.

EXAMPLES

The following are examples of Conversion Control Lists:

Example 1: Standard Typewriter Block Ingestion This example instructs the subroutine to read 110 decimal numbers from the tape, convert them to binary, align them for $P = 4$ decimal places, and store them in consecutive locations starting at location 1500 at scale factor $q = 13$. Control then returns to location 0535 of the main program.

Example 2: Alternative Device Selection with Negative Scale Factor This example instructs the subroutine to read 19 decimal numbers, convert them to binary, align them for $P = 8$ decimal places, and store them

Memory Location	Instruction	Address	Meaning
0500	Z	2420	Starting address of Control List
0532	B	0500	Load list pointer into accumulator
0533	R	L+0351	Set return address
0534	U	L+0308	Jump to standard entry point
0535	...		Main program execution resumes
2420	Z	1304	$Q = q = 13$, $P = 4$ decimal places
2421	Z	0146	$N = 110$ words ($01_{\text{track}} \times 64 + 46_{\text{sector}} = 110_{10}$)
2422	Z	1500	Target starting address for data block
Memory Location	Instruction	Address	Meaning
0501	Z	2423	Starting address of Control List
0636	B	0501	Load list pointer
0637	R	L+0351	Set return address
0638	U	L+0300	Jump to device-selection override entry point
0639	...		Main program execution resumes
2423	800Z	0108	Negative instruction flag: $Q = @-01$, $P = 8$ decimal places
2424	Z	0019	$N = 19$ words ($00_{\text{track}} \times 64 + 19_{\text{sector}} = 19_{10}$)
2425	Z	1820	Target starting address for data block
2426	Z	0800	Device selection code data word (Device code 08)

in consecutive locations starting at location 1820 at scale factor @-01. Input is executed via the peripheral unit corresponding to code 08. Control then returns to location 0639 of the main program.

TECHNICAL NOTE

To maintain maximum mathematical accuracy, the smallest practical scale factor value should be used. The program does not halt if a number cannot be properly represented or stored at the intended scale factor target; instead, it continues execution using an invalid, meaningless value.

DATA INPUT 5 — J2-10.4

PURPOSE

J2-10.4 reads data into the computer for use by a main program. It reads an indefinite quantity of decimal data words, converts them to binary, aligns them according to a specified decimal point (P), and stores them in consecutive locations at a designated scale factor. During a single program execution run, any quantity of decimal numbers can be converted and stored. All parameters controlling the conversion must be supplied by the main program.

Data Input 5 functions as a subroutine called via a calling sequence in the main program. The calling sequence must supply the subroutine with the Conversion Control List as well as the return address. Upon return to the main program, all data has been converted and stored.

STORAGE REQUIREMENTS

Memory	3 tracks, 48 sectors (240 words)
Temporary storage	None

INPUT REQUIREMENTS

Data Input 5 can convert decimal numbers consisting of an algebraic sign and up to seven digits into binary. A negative number must explicitly consist of its minus sign and seven digits; for positive numbers, both the sign and leading zeros may be omitted.

The number of decimal places P must satisfy: $0 \leq P \leq 11$. The scale factor value Q must satisfy: $-36 \leq Q \leq +47$.

The Conversion Control List, which must be stored in consecutive locations before entering the subroutine, is structured as follows:

1. Word 1 (Q and P): A single combined configuration word:
 - (a) Q (Track Portion): The target fixed-point scale factor entered as two decimal digits in the track address field.
 - (b) P (Sector Portion): The number of decimal places entered as two decimal digits in the sector address field.
2. Word 2 (Address): The initial destination address for the data, specified in decimal track/sector notation.

The scale factor Q is negative if the instruction containing it is formatted as a negative instruction (sign bit = 1). All other instructions in the control list must be positive.

Additionally, an instruction containing the starting address of the Control List must be present. This instruction must reside in the accumulator when the jump to the subroutine is executed.

The ingestion of decimal numbers is terminated by the specific stop code keyword w'.

If the selection of the input unit is to be modified, a special calling sequence can be used (by default, the subroutine selects the standard console typewriter). This requires an additional ****third word**** in the Conversion Control List, which follows the other two. This instruction must contain the device selection code for the desired unit in its decimal track address field. This selection code remains effective until explicitly replaced by a different selection code.

CALLING SEQUENCES

Calling Sequence 1 should be used if the standard console typewriter is chosen as the input device; otherwise, use Calling Sequence 2 to select a specific alternative peripheral unit.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[List]	Load starting address of Control List.
α	R	L+347	Set return address.
$\alpha + 1$	U	L+308	Enter subroutine at standard entry point.
$\alpha + 2$	...		Return point to main program.

Calling Sequence 1 (Standard Input) The instruction at $\alpha - 1$ loads the instruction containing the starting address of the Control List into the accumulator. The instruction at α stores the return address ($\alpha + 2$) inside the subroutine structures. The instruction at $\alpha + 1$ causes a jump to location L+308 of the subroutine, where L is the base address of the subroutine. Location $\alpha + 2$ contains the first instruction of the main program to be executed after completing the subroutine.

Calling Sequence 2 (Variable Device Selection Override) Calling Sequence 2 differs from Calling Sequence 1 only by the instruction at $\alpha + 1$. This instruction causes a jump to L+300 of the subroutine, so that the corresponding peripheral unit is selected based on the selection code provided in the Control List.

OPERATING INSTRUCTIONS

1. **Execution Time:** The program reads and binary-converts data at an average rate of 40 five-digit numbers per minute.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[List]	Load starting address of Control List.
α	R	L+347	Set return address.
$\alpha + 1$	U	L+300	Enter subroutine at device-selection entry point.
$\alpha + 2$	...		Return point to main program.

2. **Program Loading Instructions:** The routine tape contains the software in two distinct formats:
 - a) A relocatable hexadecimal format compatible with loader program J1-10.0.
 - b) A relocatable decimal format utilizing the standard coding sheet layout.
3. **Required Input/Output Units:** The subroutine automatically selects the standard console typewriter for input. This assignment can be altered dynamically via alternative Calling Sequence 2 (see above). No hardware output devices are required.
4. **Overflow:** Any arithmetic overflow conditions occurring during data entry or base conversion are ignored upon input, but the overflow register flag is automatically reset to zero prior to returning to the main program.

EXAMPLES

The following examples illustrate the application of the Conversion Control List:

Example 1: Indefinite Stream via Standard Typewriter This example instructs the subroutine to read an indefinite quantity of data words from the tape, convert them to binary, align them for $P = 0$ decimal places, and store them in consecutive locations starting at location 1500 at scale factor $q = 01$. Control then returns to location 2003 of the main program.

Example 2: Indefinite Stream via Alternative Unit Override This example instructs the subroutine to read an indefinite number of data words via the peripheral device corresponding to selection code 04, convert them to binary, align them for $P = 9$ decimal places, and store

Memory Location	Instruction	Address	Meaning
1700	Z	2900	Starting address of Control List
2000	B	1700	Load list pointer into accumulator
2001	R	L+0347	Set return address
2002	U	L+0308	Jump to standard entry point
2003	...		Main program execution resumes
2900	Z	0100	$Q = q = 01, P = 0$ decimal places
2901	Z	1500	Target starting address for data block
Memory Location	Instruction	Address	Meaning
1701	Z	2902	Starting address of Control List
3000	B	1701	Load list pointer
3001	R	L+0347	Set return address
3002	U	L+0300	Jump to device-selection override entry point
3003	...		Main program execution resumes
2902	800Z	0209	Negative instruction flag: $Q = @-02, P = 9$ decimal places
2903	Z	1200	Target starting address for data block
2904	Z	0400	Device selection code data word (Device code 04)

them in consecutive locations starting at location 1200 at scale factor @ - 02. Control then returns to location 3003 of the main program.

TECHNICAL NOTE

To maintain maximum mathematical accuracy, the smallest practical scale factor value should be chosen. The program does not halt if a number cannot be properly represented or stored at the specified scale factor target; instead, it continues execution using an invalid, meaningless value.

11 Data Output

DATA OUTPUT 1 — J3-10.0

PURPOSE

J3-10.0 converts binary numbers stored in memory into decimal format, including an algebraic sign and decimal point. The scale factor of the binary number can range between $q = 0$ and $q = 30$. The maximum number of decimal places printed is mathematically bounded by:

$$\frac{30 - \text{scale factor}}{3}$$

A maximum of 10 digits can be output. Leading zeros are automatically suppressed.

The data output routine operates as a subroutine and is invoked via a calling sequence in the main program. Prior to jumping to the subroutine, the binary number to be printed must reside in the accumulator. The required scale factor of the binary number must be stored in the location immediately following the jump instruction. Upon return to the main program, the decimal equivalent of the binary number has already been printed. The main program can be structured to repeatedly invoke Data Output 1 to print an entire list of decimal values sequentially.

STORAGE REQUIREMENTS

Memory	4 tracks (256 words)
Temporary storage	None

INPUT REQUIREMENTS

The input variables required for Data Output 1 are:

1. The binary number N , whose decimal equivalent is to be computed.
2. The value Q , which represents the scale factor position of the binary number.

When jumping to the subroutine, N must reside in the accumulator, and Q must be stored in the location immediately following the branch instruction.

N may be any arbitrary binary number. Q must be a positive integer and can never be greater than 30. Q can be supplied either as the sector address portion of a Z instruction or as a raw hexadecimal constant at $q = 29$.

The number of fractional digits (F) printed after the decimal point is determined directly by the value of the scale factor q according

to the formula:

$$F = \left\lfloor \frac{30 - q}{3} \right\rfloor$$

(The evaluated value of F is rounded down to the nearest integer).

Binary Point (q)	Fractional Digits (F)	Integer Digits (I)
30	0*	10
28--29	0	9
25--27	1	8
22--24	2	7
19--21	3	6
16--18	4	5
13--15	5	4
10--12	6	3
7--9	7	2
4--6	8	1
1--3	9	0
0	10	0

**Note: For $q = 30$, either 9 or 10 digits are written depending on the actual magnitude of the number.*

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
α	R	L+4	Store the address of Q into the subroutine.
$\alpha + 1$	U	L	Jump to subroutine entry point.
$\alpha + 2$	Z	00qq	Scale factor Q written as a decimal sector address at $q = 29$.
$\alpha + 3$	...		Return point to main program.

In the calling sequence shown above, the instruction at memory location α copies the absolute tracking address ($\alpha+2$) of the Z instruction containing parameter Q directly into the operand address field of the modified instruction located inside subroutine location L+4 (where L represents the base execution address of the subroutine).

The instruction at $\alpha+1$ triggers a branch to entry location L. Memory location $\alpha+2$ holds the structural value of Q encoded at $q = 29$. Finally, location $\alpha+3$ contains the first instruction of the main program sequence to resume execution after the output parsing completes.

Important Setup Note: The binary number N must be loaded directly into the accumulator immediately prior to executing this calling sequence.

OUTPUT

Each time a branch executes from the main program to Data Output 1, the raw binary integer N held inside the accumulator is parsed, converted according to scale parameter Q , and printed as a formatted decimal string.

To guarantee the highest possible printing precision, the programmer should choose the absolute smallest practical scale factor value Q . When properly configured, the transformation error remains bounded within ± 1 unit of the least significant decimal digit.

The computer automatically selects the console typewriter hardware for the output operation. A maximum of 10 characters are printed per number, and all leading zeros are completely suppressed. Every completed value printed is automatically followed by a typewriter tab instruction.

OPERATION

1. **Execution Time:** Output processing runs at approximately 30 formatted numbers per minute via the Flexowriter peripheral system.
2. **Mathematical Accuracy:** The final precision of the printed text remains fundamentally bounded by the initial bit resolution defined by the scale factor Q .
3. **Program Loading Instructions:** The routine tape contains the software in two distinct formats:
 - a) A relocatable hexadecimal format compatible with loader program J1-10.0.
 - b) A relocatable decimal format utilizing the standard coding sheet layout.
4. **Required Input/Output Units:** No hardware input devices are used during execution. The subroutine automatically selects the standard console typewriter for output processing.
5. **Overflow:** Any arithmetic overflow conditions that occurred prior to entering the subroutine are explicitly ignored upon entry. The CPU's internal overflow register flag is automatically cleared and reset to zero before the routine exits back to the main program.
6. **Error Halts:**

Memory Location	Meaning and Corrective Action
L + 361	Q is either negative or greater than 30. After pressing the <i>Start</i> key, the subroutine exits immediately back to the main program without performing any data output.

REMARKS

If a peripheral output device other than the standard console typewriter is required, the programmer must manually modify the following output print instructions located within the subroutine body.

Location	Instruction	Location	Instruction
L + 035	XP []	L + 235	80XP []
L + 037	XP []	L + 238	80XP []
L + 054	XP []	L + 241	80XP []
L + 101	XP []	L + 244	80XP []
L + 119	XP []	L + 247	80XP []
L + 136	XP []	L + 250	80XP []
L + 209	XP []	L + 253	80XP []
L + 211	XP []	L + 256	80XP []
		L + 259	80XP []

By default, fractional values are not mathematically rounded during base conversion. However, rounding can be implemented by inserting a specific add instruction (A) at location L + 128. The algebraic effect of this added rounding value depends entirely on the target scale factor at which the number is to be printed.

Alternatively, rounding can be achieved without inserting an additional instruction by directly reducing the constant value stored at location L + 352. Here too, the operational impact depends on the specific scale factor of the number being printed. Integer-only output values are automatically rounded when the scale factor is configured to $q = 28$ or $q = 29$, and are calculated exactly when the scale factor is precisely $q = 30$.

DATA OUTPUT 2 — J3-10.1

PURPOSE

J3-10.1 prints the contents of consecutive locations in decimal notation. Each printed number comprises up to 8 digits plus an algebraic sign and a decimal point. The numbers to be printed must be stored as integers scaled to $q = 30$. For positive numbers, all leading zeros and the plus sign are suppressed and replaced by spaces.

The decimal point is only printed if fractional places are explicitly specified. Words sharing the same formatting parameters can be grouped together. Consecutive numbers form a block, and identical word formats form a group within that block. Any number of blocks, and any number of groups within those blocks, are permissible.

Data Output 2 operates as a subroutine invoked by a calling sequence in the main program. The calling sequence must supply:

1. The total number of words to be output within the block.
2. The number of consecutive words in each format group.
3. The total field width for each number.
4. The number of decimal places for each format group.

Upon return to the main program, the specified values have been printed.

STORAGE REQUIREMENTS

Memory	5 tracks, 48 sectors (368 words). (<i>Note: The program must be loaded to start at sector 00 of an arbitrary track.</i>)
Temporary storage	None

INPUT REQUIREMENTS

The input variables for Data Output 2 consist of two types of control words: Block Parameters (N) and Group Parameters (N_1). These parameters must be provided by the calling sequence in the following strict order:

- **Block Parameter (N):** This control word must be negative (sign bit = 1). It contains the total number of consecutive words to be output scaled to $q = 15$, and the memory address of the first data word scaled to $q = 29$.
- **Group Parameter (N_1):** This control word must be positive. It encodes the following formatting specifications:
 - (N_1): The number of consecutive words requiring identical P and D formatting. N_1 is located in the operation field of the instruction word.

- (W_1): The total field width of each printed number or group.
 W_1 is located in the track address field of the word.
- (D_1): The number of decimal places for each word in this group.
 D_1 is located in the sector address field of the word.

The numbers to be printed must be stored at $q = 30$ and must be strictly less than $\pm 1 \times 10^7$. The structural boundaries for N , N_1 , W_1 , and D_1 are defined as:

$$0 \leq D_1 \leq 8$$

$$128 \geq W_1 \geq (2 + D_1) \quad (\text{ensuring sufficient space for the decimal point and sign})$$

$$1 \leq (N_1 \text{ and } N) \leq 15$$

$$\sum N_1 = N_t \quad (\text{for each individual block})$$

For integer-only numbers (no decimal places), no space needs to be budgeted for a decimal point. If the required boundaries for W_1 and D_1 are violated, or if the specified total field width is too narrow to hold the magnitude of the number, the output will be corrupted. If the control values N_1 and N fall between 10 and 15, they can be specified using the hexadecimal characters F, G, J, K, Q, and W.

CALLING SEQUENCES

Two calling sequences are provided. Calling Sequence 1 automatically selects the console typewriter as the output unit. Calling Sequence 2 is used exclusively when an alternative output peripheral is required or when changing the active output device channel.

Calling Sequence 1 (Standard Typewriter Output Block) Where L is the base starting address of the subroutine. Memory location $x+n+1$ contains either the negative block parameter for the subsequent data block or the next executable instruction of the main program.

Calling Sequence 2 (Device Selection Initialization) The instruction at $x - 1$ loads the specific device selection control word into the accumulator (any instruction achieving this result can be used). This sequence merely primes the subroutine configuration; it executes no data printing operations directly.

OUTPUT

The program prints the decimal equivalent of each word according to the group formatting specifications. Leading zeros are suppressed. The sign is appended to the end of the printed number: a space for positive numbers and a minus sign for negative numbers. The decimal point is written only if fractional places ($D_1 > 0$) are requested. All planned

Memory Location	Instruction	Address	Meaning
α	R	L+22	Store address of first control word into subroutine.
$\alpha + 1$	U	L	Jump to subroutine entry point.
$\alpha + 2$	80X	ttss	Block Parameter N: Negative flag, count at $q = 15$, start address at $q = 29$.
$\alpha + 3$	[N1]	W1 D1	Group 1 Format: N_1 in Opcode, Field Width W_1 , Decimals D_1 .
$\alpha + 4$	[N2]	W2 D2	Group 2 Format: N_2 in Opcode, Field Width W_2 , Decimals D_2 .
$\dots$	$\dots$	$\dots$	$\dots$
$\alpha + n$	[Ni]	Wi Di	Group i Format specifications.
$\alpha + n + 1$	...		Begin next block block parameter, or resume main program.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[Code]	Load device selection control word into accumulator.
α	R	L+421	Set return address.
$\alpha + 1$	U	L+532	Jump to device selection entry point.
$\alpha + 2$	...		Return point to main program (no data printed yet).

spaces between numbers are trailing spaces. No tabulator or carriage return commands are issued automatically.

OPERATION

1. **Execution Time:** In a standard benchmark test utilizing the console typewriter, printing 100 data words with a field width of $W_1 = 9$ required 155 seconds. This total includes overhead for exits, carriage returns, and address modifications performed after every 10 words.

EXAMPLE

Suppose 10 numbers are stored across two memory regions: 3600 to 3605 and 3630 to 3633. The numbers are to be printed in rows according to the following layout template:

```

1         2         3         4         5         6         7
+XXX.XX  +XXX.XX  XX.XXX++  XX.XXX++  XXXX.XX++  XXXX.XX++  XXXX.XX++
8         9         10
XXXXX+   XXXXX+   XXXXX+...
```

Formatting Breakdown:

- Word 1: 2 integer digits, 3 decimal places → (*Note: Typo in original description mismatch; adjusted to align with the Group word values below*).
- Words 2--4: 2 integer digits, 3 decimal places, 2 trailing spaces.
- Words 5--6: 4 integer digits, 2 decimal places, 2 trailing spaces.
- Words 7--10: 5 integer digits, 0 decimal places, 3 trailing spaces.

The subroutine is loaded at base address 1600. The calling sequence begins at location 2243 and is structured as follows:

Location	Opcode	Address	Instruction Value	Comments
2243	R	1622		Set Control List link pointer.
2244	U	1600		Jump to standard execution entry.
2245	80X	06 3600	80x6 3600	Block 1: $N = 6$ words; starts at 3600.
2246	X	07 03	x1 0703	Group 1: $N_1 = 1$; $W_1 = 7 [(I = 2) + (D = 3) + 2_{\text{const}}]$.
2247	X	09 03	x3 0903	Group 2: $N_1 = 3$; $W_1 = 9 [(I = 2) + (D = 3) + (S = 2) + 2_{\text{const}}]$.
2248	X	10 02	x2 1002	Group 3: $N_1 = 2$; $W_1 = 10 [(I = 4) + (D = 2) + (S = 2) + 2_{\text{const}}]$.
2249	80X	04 3630	80x4 3630	Block 2: $N = 4$ words; starts at 3630.
2250	X	09 00	x4 0900	Group 1: $N_1 = 4$; $W_1 = 9 [(I = 5) + (S = 3) + 1_{\text{const}}]$.

The comments column illustrates the value for N and the derivation of the formatting values. Note that $\sum N_1$ within each block matches its total block count parameter N . Furthermore, when adding up the

integer digits (I), decimal places (D), and trailing spaces (S), a constant of 2 must be added to account for the decimal point and sign characters.

In location 2250, this formatting constant is only 1 because no decimal point is required for integer-only output.

DATA OUTPUT 3 — J3-10.2

PURPOSE

J3-10.2 prints the contents of consecutive locations in decimal notation. Each printed number can consist of up to 7 digits, an algebraic sign, a decimal point, and leading zeros. The numbers to be printed must be stored as integers scaled to $q = 30$. Leading zeros and the plus sign are suppressed and replaced by spaces. The decimal point is written only if fractional places are explicitly specified.

Values that are to be printed using identical formatting parameters can be combined into groups. Any number of blocks of consecutive locations, and any number of groups of identical word formats within those blocks, are permissible.

The program functions as a subroutine invoked by a calling sequence in the main program. The calling sequence must supply:

1. The total number of words to be output within the block.
2. The number of consecutive words in each format group.
3. The total field width for each number.
4. The number of decimal places for each value.

Upon return to the main program, the specified values have been printed.

STORAGE REQUIREMENTS

Memory	5 tracks, 13 sectors (333 words). (<i>Note: Reduces to 5 tracks and 7 sectors if the alternate device-selection entry point is bypassed.</i>)
Temporary storage	None

INPUT REQUIREMENTS

The input variables consist of two types of control words: Block Parameters (N_t) and Group Parameters (N_i). These control words must be provided by the calling sequence in the following strict order:

- **Block Parameter (N_t):** This control word must be negative (sign bit = 1). It contains the total number of consecutive words to be output scaled to $q = 15$, and the memory address of the first data word scaled to $q = 29$.
- **Group Parameter (N_i):** This control word must be positive. It encodes the following formatting specifications:

- (N_i) : The number of consecutive words requiring identical P and D formatting. N_i is located in the operation field of the instruction word.
- (W_i) : The total field width of each printed number in the group. W_i is located in the track address field of the word.
- (D_i) : The number of decimal places for each word in this group. D_i is located in the sector address field of the word.

The numbers to be printed must be stored at $q = 30$ and must be strictly less than $\pm 1 \times 10^7$. The structural boundaries for N_t , N_i , W_i , and D_i are defined as:

$$0 \leq D_i \leq 7$$

$$128 \geq W_i \geq (2 + D_i) \quad (\text{ensuring sufficient space for the decimal point and sign})$$

$$1 \leq (N_i \text{ and } N_t) \leq 15$$

$$\sum N_i = N_t \quad (\text{for each individual block})$$

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
α	R	L+22	Set the address of the first control word into the sub-routine.
$\alpha + 1$	U	L	Entry into the subroutine (L+7 is equivalent as an entry).
$\alpha + 2$	$80X(N_t)$	ttss	N at $q = 15$ and starting address of the data at $q = 29$.
$\alpha + 3$	$[N_1]$	$W_1 D_1$	Format specifications
$\alpha + 4$	$[N_2]$	$W_2 D_2$	Format specifications
$\dots$	$\dots$	$\dots$	
$\alpha + n$	N_i	$W_i D_i$	
$\alpha + n + 1$	$\dots$		Beginning of the next block or return to the main program (return instruction must be positive).

L is the starting address of the subroutine. Location $\alpha + n + 1$ contains either the N control word for the next block or the next instruction of the main program.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[]	Bring selection code
α	R	L+512	Set return address
$\alpha + 1$	U	L+220	Entry into the subroutine
$\alpha + 2$	...		Main program

The instruction in $\alpha-1$ brings the selection code for the output unit into the accumulator (any instruction that does this is permissible). L is the starting address of the subroutine. This calling sequence only prepares the subroutine; no output results from it.

OUTPUT

The program prints the decimal equivalent of each word according to the group formatting specifications. Leading zeros are suppressed. The sign is appended to the end of the printed number: a space for positive numbers and a minus sign for negative numbers. The decimal point is written only if fractional places ($D_1 > 0$) are requested. All planned spaces between numbers are trailing spaces. No tabulator or carriage return commands are issued automatically.

OPERATION

1. **Execution Time:** In a standard benchmark test utilizing the console typewriter, printing 100 data words with a field width of $W_1 = 9$ required 155 seconds. This total includes overhead for exits, carriage returns, and address modifications performed after every 10 words.

EXAMPLE

Suppose 10 numbers are stored across two memory regions: 3600 to 3605 and 3630 to 3633. The numbers are to be printed in rows according to the following layout template:

```

1      2      3      4      5      6      7
XXX.XX+XXX.XX+  XX.XXX+  XX.XXX+  XXXX.XX+  XXXX.XX+  XXXX.XX+...
8      9      10
XXXXX+  XXXXX+  XXXXX+...
```

Formatting Breakdown:

- Word 1: 2 integer digits, 3 decimal places → (*Note: Adjusted to map the Group parameters below*).
- Words 2--4: 2 integer digits, 3 decimal places, 2 trailing spaces.
- Words 5--6: 4 integer digits, 2 decimal places, 2 trailing spaces.

- Words 7--10: 5 integer digits, 0 decimal places, 3 trailing spaces.

The subroutine is loaded at base address 1600. The calling sequence begins at location 2243 and is structured as follows:

Location	Opcode	Address	Instruction Value	Technical Notes
2243	R	1622		Set Control List link pointer.
2244	U	1600		Jump to standard execution entry.
2245	80X	06 3600	80x6 3600	Block 1: $N = 6$ words; starts at 3600.
2246	X	07 03	x1 0703	Group 1: $N_1 = 1$; $W_1 = 7 [(I = 2) + (D = 3) + 2_{\text{const}}]$.
2247	X	09 03	x3 0903	Group 2: $N_1 = 3$; $W_1 = 9 [(I = 2) + (D = 3) + (S = 2) + 2_{\text{const}}]$.
2248	X	10 02	x2 1002	Group 3: $N_1 = 2$; $W_1 = 10 [(I = 4) + (D = 2) + (S = 2) + 2_{\text{const}}]$.
2249	80X	04 3630	80x4 3630	Block 2: $N = 4$ words; starts at 3630.
2250	X	09 00	x4 0900	Group 1: $N_1 = 4$; $W_1 = 9 [(I = 5) + (S = 3) + 1_{\text{const}}]$.

The notes column illustrates the value for N and the derivation of the formatting values. Note that $\sum N_1$ within each block matches its total block count parameter N . Furthermore, when adding up the integer digits (I), decimal places (D), and trailing spaces (S), a constant of 2 must be added to account for the decimal point and sign characters.

In location 2250, this formatting constant is only 1 because no decimal point is required for integer-only output.

TECHNICAL REMARK

This program works identically and satisfactorily with both the Mod 18 and Mod 9 print mechanism variants of the console typewriter.

DATA OUTPUT 4 — J3-10.3

PURPOSE

The program prints the contents of the accumulator. Up to nine decimal places plus an algebraic sign, a decimal point, and a tabulator command are output. Leading zeros are suppressed, and the output is printed correctly. The data to be output may be positioned at any one of 10 predetermined q scale factors.

The program operates as a subroutine invoked by a calling sequence in the main program. The calling sequence must supply:

1. The number of digits C that can stand before the decimal point.
2. The number of digits D to be printed after the decimal point (q is determined by C).

STORAGE REQUIREMENTS

Memory	3 tracks (192 words)
Temporary storage	None

INPUT REQUIREMENTS

The input consists of the data word to be printed and the control keyword for C and D .

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$x - 1$	B	[]	(Any instruction sequence that supplies data). Loads data word into the accumulator.
x	R	Lo+12	Set return link pointer.
$x + 1$	U	Lo	Entry into the subroutine.
$x + 2$	Z	ODOC	D encoded at $q = 23$ and C encoded at $q = 29$.
$x + 3$	...		Main program.

KEYWORD SPECIFICATIONS

D may be any integer between 0 and 9, provided that $C + D \leq 9$.

C may be any integer between 0 and 9, provided that $C + D \leq 9$. The scale factor q of the value to be printed is supplied by C , as shown in the following table:

C	q	C	q
0	0	5	17
1	4	6	20
2	7	7	24
3	10	8	27
4	14	9	30

OUTPUT

The value in the accumulator is printed with C digits before the decimal point (leading zeros are suppressed) and D digits after the decimal point (properly rounded up), followed by a minus sign or a space, and a tabulator jump.

OPERATION

1. **Execution Time:** Variable, depending on C and D . Output speed is approx. 6 characters/second.
2. **Accuracy:** If nine digits are printed, an error of 1 unit may be present in the ninth decimal place.
3. **Program Loading Instructions:** The tape contains the program in two versions:
 - a) Relocatable hexadecimal format compatible with Program Input 1.
 - b) Decimal format utilizing the coding sheet layout.
4. **Required Input/Output Units:** Output is sent via the Model 121 typewriter hardware. Input units are not required.

ERROR HALTS

Memory Location	Meaning and Corrective Action
Lo + 120	$C + D$ is greater than 9. After pressing <i>Start</i> , "fld" is printed and execution returns to the main program.
Lo + 120	The number to be output cannot be printed within C integer digits. After pressing <i>Start</i> , "big" is printed and execution returns to the main program.

EXAMPLE

A number with the formatting layout template XXXXX.XX+ is to be printed.
This example assumes that Data Output 4 is located at base address

Memory Location	Instruction	Address	Meaning
1345	B	[]	Target data word scaled to $q = 17$.
1346	R	2312	Link pointer mapped to $Lo + 12$.
1347	U	2300	Jump to entry point Lo.
1348	XZ	0205	Keyword control word ($D = 2, C = 5$).
1349	...		Main program resumes.

2300. The calling sequence begins at memory location 1345.

DATA OUTPUT 5 — J3-10.4

PURPOSE

J3-10.4 outputs a nine-digit decimal number plus an algebraic sign and a decimal point. For a negative number, a minus sign is printed; a space appears in place of a plus sign.

The program functions as a subroutine invoked by a calling sequence in the main program. The calling sequence must supply a keyword in location $x+2$ that specifies the number of digits in the integer portion of the value.

STORAGE REQUIREMENTS

Memory	120 sectors (120 words)
Temporary storage	None

INPUT REQUIREMENTS

The input consists of the number to be printed and the identification digit C , which specifies the number of digits in the integer portion.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$x-1$	B	L(N)	Load data word into the accumulator.
x	R	Lo+12	Set address of the keyword into the subroutine.
$x+1$	U	Lo	Entry into the subroutine.
$x+2$	Z	000C	Identification code C , which corresponds to q .
$x+3$	...		Main program.

Memory location $x-1$ does not strictly require a load (B) instruction. Any instruction that leaves the argument inside the accumulator is permissible. C is an identification digit bounded between 0 and 9.

OUTPUT

The output consists of: nine decimal digits, an algebraic sign (or a space if positive), and the decimal point. Leading zeros are replaced by spaces.

KEYWORD SPECIFICATIONS

C	q	Output Format
0	0	.XXXXXXXX
1	4	X.XXXXXX
2	7	XX.XXXXX
3	10	XXX.XXXXX
4	14	XXXX.XXXXX
5	17	XXXXX.XXXX
6	20	XXXXXX.XXX
7	24	XXXXXXX.XX
8	27	XXXXXXXX.X
9	30	XXXXXXXXX.

Note: Every binary number is scaled and converted as a fraction. The identification digit is used by the subroutine as a column placement counter. Every completed number print is followed by a tabulator command. Execution then returns to location $x+3$ of the main program.

OPERATION

1. **Execution Time:** 3.0 seconds per number.
2. **Accuracy:** The maximum error is bounded within 1 unit at the ninth decimal digit position.
3. **Program Loading Instructions:** The program is available in two versions:
 - a) Relocatable hexadecimal format, readable via Program Input 1.
 - b) Decimal format utilizing the standard coding sheet layout.
4. **Required Input/Output Units:** The program selects the paper tape typewriter channel for output. Hardware input units are not required.

PRINT INSTRUCTIONS TO BE PATCHED

Location	Instruction
Lo + 0048	XPC 0200
Lo + 0053	XPC 0200
Lo + 0111	XPC 0200
Lo + 0117	XPC 0200
Lo + 0132	80XPC 0200

ERROR HALTS

Memory Location	Meaning and Corrective Action
Lo + 46	The argument is $\geq 10^9$. The computer halts. After pressing <i>Start</i> , the routine exits without printing.

DATA OUTPUT 6 — J3-10.5

PURPOSE

J3-10.5 prints one or more groups of numbers in decimal notation, each of which can contain one or more individual values. The numbers within a group must be stored in consecutive locations scaled to the same scale factor q . Leading zeros are replaced by spaces; a space or a minus sign follows immediately behind the last decimal place.

STORAGE REQUIREMENTS

Memory	3 tracks, 32 sectors (224 words)
Temporary storage	Sectors 42 and 43 of Track 63 are utilized as scratchpads.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
x	R	Lo+3	Set return link pointer.
$x + 1$	U	Lo	Entry into subroutine.
$x + 2$	Z	Loc1	Destination address of the first data word in Group 1.
$x + 3$	Z	N1 q1	Total words N_1 and scale factor q_1 for Group 1.
$x + 4$	Z	Loc2	Destination address of the first data word in Group 2.
$x + 5$	Z	N2 q2	Total words N_2 and scale factor q_2 for Group 2.
...	...	...	...
$x + 2i$	Z	Loc i	Destination address of the first data word in Group i .
$x + 2i + 1$	Z	N i q i	Total words N_i and scale factor q_i for Group i .
$x + 2i + 2$	...		Exit marker (This instruction field must NOT be a Z opcode).

Where Loc $_i$ represents the starting memory address of the first data value in the i -th group; N represents the absolute quantity of data values in the i -th group; q is the binary scale factor of all data points

within the i -th group. The values N and q each occupy 2 decimal digits, corresponding directly to the track and sector layout fields respectively.

OUTPUT

Each output value consists of 8 to 10 decimal digits, a decimal point, a space or minus sign, and a tabulator command. Two distinct Z instructions are required to cleanly define each data group block. After printing the final data group, execution exits to the instruction immediately following the calling sequence array; this exit instruction must not use a Z opcode.

OUTPUT FORMAT LAYOUTS

Scale Factor Range (q)	Output Format Template
0	.XXXXXXXX+
0 – 4	X.XXXXXXX+
4 – 7	XX.XXXXXX+
7 – 10	XXX.XXXXX+
10 – 14	XXXX.XXXX+
14 – 17	XXXXX.XXX+
17 – 20	XXXXXX.XX+
20 – 24	XXXXXXX.X+
24 – 27	XXXXXXXX+
27 – 30	XXXXXXXXX.+
30 – 31	XXXXXXXXXX.+

EXAMPLE

Suppose 10 values are stored sequentially. The calling sequence starts at memory address x and points to locations 2100 and 2110:

Location	Opcode	Address	Instruction Value	Technical Notes
x	R	Lo+3		Set return link pointer.
$x + 1$	U	Lo		Jump to entry point Lo.
$x + 2$	Z	2100	xZ 2100	Loc ₁ = 2100
$x + 3$	Z	0407	xZ 0407	$N_1 = 4$ words; scale factor $q_1 = 7$.
$x + 4$	Z	2110	xZ 2110	Loc ₂ = 2110
$x + 5$	Z	1115	xZ 1115	$N_2 = 11$ words; scale factor $q_2 = 15$.
$x + 6$	B	[]	xB []	Main program exit (Non-Z instruction).

The calling sequence above executes the following parsing stages:

1. Prints the content of locations 2100, 2101, 2102, and 2103 using the template XX.XXXXXX+ for values whose absolute magnitude is strictly less than 100.00000, or using the template XXX.XXXXXX+ for values scaling above this boundary (see $q = 7$ range rules inside the format guide).
2. Prints the content of locations 2110 through 2120 using the layout template XXXXX.XXX+.
3. Branches out to position $x+6$, where the non-Z operational code safely terminates the subroutine parser sequence loop.

FEHLERSTOPS

Memory Location	Meaning and Corrective Action
Lo + 207	$N \leq 1$. After pressing <i>Start</i> , execution exits back to the main program loop without executing any prints.

TECHNICAL SPECS

1. **Accuracy:** Output calculations carry a potential maximum mathematical rounding error of 1 unit at the eighth printed decimal place position.
2. **Execution Time:** Processing throughput clocks at approximately 25 words/minute.
3. **Program Loading Instructions:** The tape contains the routines in two standard alternative distributions: relocatable hexadecimal format, and decimal formatting using the standard coding sheet structures. Both tapes are natively read using Program Input 1.

12 Hexadecimal Output

The programs in this section are mostly utilities for taking existing data and reformatting it for use with one of the program loaders.

- J4-10.1 is the equivalent of a ``delinker''. It takes a block of memory, subtracts a relocation constant from a set of memory blocks defined by its input, and punches that out to tape. This allows programs which had been loaded and relocated with PIR or GPMOD to be relocated back to zero-based addressing for loading again at a different address later.
- J4-10.2 is a straight dump-memory-to-tape backup program. Given a starting track, and an ending track, the program dumps the memory in 64-word blocks with a checksum.
- J4-10.3 is a slightly more refined dump program, taking a starting track and sector and an ending track and sector. The output has a carriage return inserted every 8 words; this makes the output a useful, readable hex dump as well as a way to dump that memory to tape.

[There is no Hexadecimal Output 1 (which would have been J4-10.0) program in this document.]

HEXADECIMAL OUTPUT 2 — J4-10.1

PURPOSE

J4-10.1 punches the contents of a specified memory region onto paper tape in a relocatable hexadecimal format. For every block of 64 words (or fewer), a hexadecimal loader control word (Füllschlüsselwort) and a checksum are punched along with the data. The contents are output in ascending order of memory addresses.

The program tape generated by this routine can be read back into the computer using Program Input 1 (J1-10.0).

STORAGE REQUIREMENTS

Memory	6 tracks (384 words)
Temporary storage	Storage table for the hexadecimal regions (see ``Input Requirements'').

INPUT REQUIREMENTS

J4-10.1 subtracts a specified modifier value from all instruction words (with the exception of instructions containing an I or P operation code). Therefore, all instructions (or hexadecimal words configured

to look like instructions) that must not be modified during relocation must be declared inside the hexadecimal regions table. The memory area allocated for this table, along with its specific entries, is supplied to the computer following the print prompts "tbl" and "hex".

Upon branching to the program's starting location, the computer prompts the operator with the following query-and-response routine:

Tbl Enter the boundaries for the hexadecimal region storage table using decimal track/sector notation. If no boundaries are input, the computer automatically defaults to Track 63. When specifying a custom area, the start and end addresses must be entered together as a single word (e.g., 0300 0463' allocates Tracks 03 and 04 for the table). The table accommodates up to $(N-1)$ entries, where N represents the absolute number of locations allocated to the table region. For instance, if two tracks are assigned, up to 63 entry lines can be stored.

Hex This prompt functions as a multi-line sequential input entry; the entire table of hexadecimal regions is managed as a single logical entity. Enter the boundaries-using decimal track/sector notation-for all memory zones that are to be punched using absolute addresses, regardless of how the words appear. The starting and ending address of each contiguous block of locations must be entered as a single word (e.g., 0300 0301', 0402 0432', 0533 0533', etc.).

Any word containing a P or I opcode is automatically output with an absolute address. Similarly, any word that contains a 1 bit set outside the standard sign, opcode, or address fields is automatically treated as absolute. These words do not need to be manually declared via the "Hex" prompt.

Pnch. Enter the boundaries of the memory region whose contents are to be output, using decimal track/sector notation. Provide the start and end address inside a single input word (e.g., 0300 0663').

Modi Enter the modifier value-in decimal track/sector notation-that must be subtracted from each instruction word so that it gets converted into a relative address format (e.g., 0300').

The locations selected for output must reside in a continuous, ascending sequence. Any arbitrary quantity of locations may be specified.

CALLING SEQUENCE

The program is executed by branching directly to its designated starting address.

OUTPUT CHARACTERISTICS

J4-10.1 punches the contents of the specified memory range onto tape in relocatable hexadecimal format. The data is structured into discrete blocks of 64 words each (the final block may contain fewer). Each block is preceded by a hexadecimal loader control word and followed by a calculated verification checksum. A carriage return is automatically punched after a maximum of 10 words. Blank feed spaces are punched between individual data blocks.

Output processing proceeds sequentially through ascending memory addresses. The actual contents of the source locations remain unaltered by the program. Once the requested data stream is completely punched, the computer executes a halt instruction. Pressing the *Start* key triggers a branch back to the beginning of the program loop.

OPERATING INSTRUCTIONS

1. **Program Loading Instructions:** The routine tape contains the software in two alternate distributions:
 - a) A relocatable hexadecimal format compatible with Program Input 1.
 - b) A relocatable decimal format using the standard coding sheet layout.
2. **Required Input/Output Units:** The standard console typewriter is automatically selected by the program logic to handle all parameter entry prompts and data tape punching operations.

HEXADECIMAL OUTPUT 3 — J4-10.2

PURPOSE

J4-10.2 punches the contents of a specified memory region onto paper tape in the format required by Program Input 3 (J5-10.0). The requested information is punched in hexadecimal notation in structural blocks of 64 words. Blank feed spaces are punched between individual data words within a block. Each block comprises an entire, unbroken track. Every block is accompanied by a hexadecimal loader control word (Eingabeschlüsselwort) and a verification checksum. Any arbitrary number of tracks can be punched in a single execution pass, provided they reside in ascending memory sequence order.

STORAGE REQUIREMENTS

Memory	4 tracks (256 words), or 4 tracks and 17 sectors (273 words), depending on the selected output unit configuration (see ``Program Loading Instructions'').
Temporary storage	None

INPUT REQUIREMENTS

Upon executing a branch to the program's starting address, the computer selects the console typewriter for input parameters and requests the following boundaries:

1. L1: The address of the first track to be punched, entered as a 2-digit track number.
2. L: The address of the last track to be punched, entered as a 2-digit track number.

When the computer halts to request these output boundaries, and before the operator enters the final track address (L), any number of negative words may be input to be punched directly onto the tape. These words are interpreted by Hexadecimal Input 3 as absolute execution jump instructions and must strictly conform to the specifications of that input program.

CALLING SEQUENCE

The program is invoked by branching directly to its designated starting address. Program distributions featuring an integrated bootstrap loader terminate with an automatic branch to the starting address; other distributions end with a halt-and-transfer sequence (see ``Program Loading Instructions').

OUTPUT CHARACTERISTICS

The program punches the contents of consecutive tracks onto paper tape in hexadecimal notation. Processing advances sequentially from the specified starting track address to the ending track address. Only complete tracks are output; partial track dumping is not supported.

The hexadecimal words are arranged on the tape in 64-word blocks. Each block covers a distinct track, and the words within a block follow a specific layout pattern separated by space characters. The physical sector tracking sequence within each output block is ordered exactly as follows:

56,	58,	60,	63,	01,	03,	05,	62,	00,	02,	04,	06,	08,	10,	12,	07,
09,	11,	13,	15,	17,	19,	14,	16,	18,	20,	22,	24,	26,	21,	23,	25,
27,	29,	31,	33,	28,	30,	32,	34,	36,	38,	40,	35,	37,	39,	41,	43,
45,	47,	42,	44,	46,	48,	50,	52,	54,	49,	51,	53,	55,	57,	59,	61.

Each block is preceded by a hexadecimal loader control word and followed by a calculated verification checksum. All negative jump control keywords are punched to tape immediately upon manual entry. Following the completion of the final track (L), the program automatically execution-branches back to the starting address so that new output boundaries may be entered.

OPERATING INSTRUCTIONS

1. **Execution Time:** Approximately 26 seconds are required per track when outputting via the Model 151 high-speed paper tape punch peripheral.
2. **Program Loading Instructions:** The program tape contains the software in four alternate distributions:
 - a) Relocatable hexadecimal format with a Track 00 bootstrap loader.
 - b) Relocatable hexadecimal format with a Track 63 bootstrap loader.
 - c) Relocatable hexadecimal format compatible with Program Input 1 (J1-10.0).
 - d) Relocatable decimal format using the standard coding sheet structures.

The exact entry procedure varies depending on the selected distribution and the active input peripheral:

Relocatable Hexadecimal Format with Bootstrap Relocatable hexadecimal programs paired with an independent bootstrap loader allow the operator to enter the routine via either the Model 121 console typewriter or the Model 141 high-speed tape reader, as a dedicated bootstrap block is provided for each device. They are structured sequentially on the tape in the following order:

- (a) Track 00 bootstrap for program input via the Model 141 tape reader.
- (b) Track 00 bootstrap for program input via the Model 121 console typewriter.
- (c) Program J4-10.2 software body.
- (d) Track 63 bootstrap for program input via the Model 141 tape reader.
- (e) Track 63 bootstrap for program input via the Model 121 console typewriter.
- (f) Program J4-10.2 software body.

The operator must select the specific bootstrap block that matches both the target destination track and the desired input hardware, then feed it according to the standard bootstrap entry procedure described in the *Program Input 1* documentation.

The first instruction word loaded by the bootstrap is the modifier, which defines the absolute starting address where the program is to be stored. The tape features the following predefined (and manually alterable) modifier flags:

- Track 00 bootstraps utilize a modifier value of 0000.
- Track 63 bootstraps utilize a modifier value of 6000.
- After the bootstrap block finishes reading, 4 program tracks are loaded automatically, and the computer executes a halt.

If the program is intended to run utilizing the Model 121 typewriter as the active output device, a manual jump to the program starting address must be executed at this stop point (see ``Manual Branching Procedure'').

If the operator instead intends to route output to the Model 151 high-speed tape punch, they should press the *START* switch instead of executing the manual jump when the machine halts. The computer will then ingest and store 14 additional instructions that overwrite the default print commands, reconfiguring the program to target the Model 151 high-speed punch channel. Following the ingestion of these 14 patching instructions, the computer halts. To execute a jump to the program's starting address, the operator only needs to press the *START* switch.

Relocatable Hexadecimal Format (Program Input 1 Variant)

This distribution is loaded using the standard loading routine detailed in the *Program Input 1* reference guide. The loader ingests the 4 tracks of the program body and then halts.

If the console typewriter is to be used as the output device, set the control lever to *Manual Input* (Eingabe von Hand) and press the *START* switch. The typewriter is now selected for entry. Manually enter a stop-and-transfer command pointing to the starting address of the program, set the control toggle to *START COMP*, and press the *START* switch.

If the operator wishes to preserve arbitrary peripheral device assignment options at runtime, execute the following sequence precisely when the initial loading phase halt occurs:

- (a) Set the control lever to *MANUAL INPUT* (Eingabe von Hand).
- (b) Press the *START* switch. (The console typewriter is selected for input parameters).
- (c) Type the standard Program Input 1 device assignment keyword matching the physical peripheral device through which the tape is being fed (e.g., S000 0000 for the Model 141 high-speed reader).
- (d) Set the control toggle to *START COMP*.
- (e) Release the *MANUAL INPUT* control lever.
- (f) Press the *START* switch.

The remainder of the tape profile (17 patching instructions) is ingested, and the computer executes a halt. (An automatic jump-and-transfer instruction pointing to the starting address of the dumper program is located at the tail end of this block. Pressing the *START* switch at this point begins program execution, defaulting the typewriter channel for input and output).

To override this and explicitly lock down a custom output unit channel, execute a manual execution branch to address $L + 0400$, where L represents the base starting address of the active input loader program. The routine selects the typewriter for input. Enter the device selection keyword for the desired output hardware peripheral as a standard 2-digit track address token. The routine dynamically overwrites the internal print commands to target the selected device channel and begins runtime operations immediately (i.e., requesting the start and end track parameters) without executing an intermediate halt.

3. Manual Branching Procedure (Das ``Springen von Hand'')

- a) Set the master mode selection dial to *MANUAL INPUT* (Eingabe von Hand).
- b) Type an unconditional execution transfer instruction (U) targeting the desired location address using hexadecimal notation (e.g., to target memory location 6000, type 000 U3J00).

- c) Press the *FILL/CLEAR* (Füllen/Löschen) button.
 - d) Set the master mode selection dial to *SINGLE STEP* (Einzeloperation).
 - e) Press the *EXECUTE* (Ausführen) button.
 - f) Return the master mode selection dial to *NORMAL*.
 - g) Press the *START* switch.
4. **Required Input/Output Units** The standard console typewriter hardware is automatically designated to handle all manual boundary input parameters. The destination output unit is assigned by the loader block processing sequence based entirely on the specific configuration selections executed by the operator at load time.

HEXADECIMAL OUTPUT 4 — J4-10.3

PURPOSE

J4-10.3 punches blocks of memory in hexadecimal format. The resulting paper tapes can be read back into the computer using Program Input 1 or 2 (J1-10.0 or J1-10.1). The active output peripheral unit can be designated by the user at runtime as desired.

STORAGE REQUIREMENTS

Memory	3 tracks (192 words)
Temporary storage	None

INPUT REQUIREMENTS

The input parameters consist of the decimal device selection code, the starting and ending addresses of the memory block to be punched, and an execution address for an absolute ``Halt and Jump'' control word (.000XXXX). All of these parameters must be entered using decimal track/sector notation.

OUTPUT CHARACTERISTICS

The output stream is structured into blocks of up to 64 words in hexadecimal format. Each block is preceded by a loader control word (VNNCHHHH; see reference documentation for Program Input 1 or 2), and each block is followed by a calculated verification checksum that incorporates both the control keyword and every individual data word contained within the punched block.

A carriage return command is automatically punched after every eight words. To optimize tape space, data words that are completely equal to zero have all eight hexadecimal zero characters entirely suppressed. Words containing three leading zeros (as seen in the vast majority

of standard instruction words) have those three leading zeros suppressed. All other data words are punched as a full sequence of eight hexadecimal characters.

OPERATING TIMES

Console Typewriter Tape Punch	Approx. 68 seconds / track
High-Speed Tape Punch	Approx. 34 seconds / track

OPERATING INSTRUCTIONS

1. **Program Loading Instructions:** The tape contains the program in two alternate distributions:
 - a) Relocatable hexadecimal format compatible with Program Input 1 (J1-10.0).
 - b) Relocatable decimal format using the standard coding sheet layout.
2. **Program Execution Steps:**
 - (a) Execute a branch to the starting address of the program.
 - (b) Type the decimal device selection code: 02 for the console typewriter tape punch or 06 for the high-speed paper tape punch peripheral.
 - (c) Type the starting address of the memory block to be punched using decimal track/sector notation.
 - (d) Type the ending address of the memory block to be punched using decimal track/sector notation. (*Note: The ending address must be greater than or equal to the starting address*).
 - (e) Type the target execution address that is to be encoded into the final ``Halt and Jump'' control word. This causes the block sequence terminator .000TTSS to be punched at the tail end of the operation. If no ``Halt and Jump'' control keyword is desired after the block, the operator can simply press the typewriter's *START COMP* (Rechnen Start) lever without entering prior characters. (If an absolute stop code of .0000000 is explicitly desired, at least one zero character must be typed before pressing the *START COMP* lever).
 - (f) Once the punching routine completes, the program loops back to step 3 and waits for a new starting address input.
3. **Required Input/Output Units:** The program automatically selects the console typewriter hardware to handle all manual entry parameters. The active output peripheral destination is determined dynamically by the decimal selection code entered at runtime (02 for the typewriter punch; 06 for the high-speed punch).

REMARKS

The program automatically clears the hardware overflow flag. The overflow status register is guaranteed to be reset following the completion of each punched block sequence.

13 Alphanumeric Output

ALPHANUMERIC OUTPUT 1 — J4-11.0

PURPOSE

J4-11.0 translates keywords and handles their output as alphabetic and/or numeric text. The alphanumeric text must be stored by the main program in a 4-bit character encoding format. It consists of a group of words composed of special codes corresponding to the characters and functions of the typewriter. The amount of data to be stored for J4-11.0 is limited only by the available memory space. The information must be stored in ascending sequence in consecutive locations.

J4-11.0 operates as a subroutine. It is called by a calling sequence in the main program. Before jumping to the subroutine, the starting address of the data block to be output must be stored within the subroutine. The memory locations following the jump instruction must contain the control keywords. Upon return to the main program, the output operation has already been executed.

STORAGE REQUIREMENTS

Memory	56 sectors (56 words)
Temporary storage	None

INPUT

The starting address of the keyword list must be stored before jumping to the subroutine. The data block must consist of consecutive words located immediately following the jump instruction of the calling sequence. Each word consists of four keyword symbols (encoded as pairs of characters), which correspond to alphabetic characters as well as the control functions of the typewriter.⁴¹

The last word of the block is designated by the special termination symbol 7Q. Since every word must contain four keyword symbols (representing eight total hexadecimal digits per word), two to six trailing zeros are required to fill out the final word. The number of words in a block is limited only by available memory space. In the main program, every block of 63 or fewer keywords must be preceded by a hexadecimal loader control word, as required by Program Input 1.

⁴¹This subroutine essentially encodes the Flexowriter's 6-bit characters as 8-bit ones, so that each character takes up two hex digits. Instead of having to bit-slice characters in one's head and attempt to pack them 5 to a word, this subroutine lets you pack them 4 to a word on hex-digit boundaries and not lose your marbles.

ALPHANUMERIC KEYWORD SYMBOL TABLE

42

Keycap	Symbol	Keycap	Symbol
)0	04	Bb	0F
L1	0J	Cc	6F
*2	14	Dd	2F
"3	1J	Ee	4F
△4	24	Ff	54
%5	2J	Gg	5J
\$6	34	Hh	62
π7	3J	Ii	22
Σ8	44	Jj	64
(9	4J	Kk	6J
Space	06	Ll	0J
-	0A	Mm	3F
=+	16	Nn	32
:;	1A	Oo	46
?/	26	Pp	42
].	2A	Qq	74
[,	36	Rr	1F
Tab	30	Ss	7F
Lower	08	Tt	5F
Upper	10	Uu	52
Color	18	Vv	3A
CR	20	Ww	7J
Backspace	28	Xx	4A
'	40	Yy	12
Terminator	7Q	Zz	02
Aa	72		

[Translator's note: Readers should note that the table includes ``A'' as a hex code, which in LGP-21 parlance is nonsense; the hex digits are F G J K Q W. I have no documentation that specifically explains why this is ``A'' here. Best guess is that this was touch-typed on an AZERTY keyboard by someone used to a QWERTY keyboard, which would swap A for Q.]

EXAMPLE

The following example illustrates how to compile a data group for ``Alphanumeric Output 1'':

⁴²This table is transcribed accurately from the original typed documentation; I have preserved the errors noted in the translator's note. If it turns out we can test this routine at a later date, we can verify if those values are Q's or not and correct this table.

Loader Word	Location	Opcode	Address	Description
	x	R	L	Set data pointer.
	$x + 1$	U	L	Branch to subroutine.
.0000004	$x + 2$	20	42 09 72	Alphanumeric raw hex data tokens.
	$x + 3$	32	32 22 32	Alphanumeric raw hex data tokens.
	$x + 4$	5J	06 42 72	Alphanumeric raw hex data tokens.
	$x + 5$	12	7F 7Q 00	Alphanumeric raw hex data tokens with end marker.
	$x + 6$	...		Main program resumes.

This example issues an automatic carriage return command, prints the text "PLANNING PAYS", and cleanly branches execution back to location $x+6$ of the main program logic sequence. The token 7Q inside the final memory word marks the structural end code statement; the remaining trailing zero characters are solely included to fill out the word boundary layout.

CALLING SEQUENCE

There are two distinct calling sequences available for invoking ``Alphanumeric Output 1''. Calling Sequence 1 is utilized exclusively when routing output to the standard console typewriter. Calling Sequence 2 is used when an alternative hardware output peripheral unit is required.

Memory Location	Instruction	Address	Meaning
x	R	L	Transfer starting address of data block into subroutine location L.
$x + 1$	U	L	Jump to subroutine standard execution entry point.
$x + 2$	...		First control keyword string token word.
...	...		Alphanumeric string control words.
$x + n$	...		Final control keyword string token word, containing 7Q.
$x + n + 1$	...		Main program execution resumes.

Calling Sequence 1 (Standard Typewriter Output) The instruction at location x stores the entry pointer of the data block into the subroutine body. The command at $x+1$ triggers the execution branch. Locations $x+2$ through $x+n$ contain the n string keyword words. Location $x+n+1$ holds the next instruction of the main program to be executed immediately following subroutine exit.

Memory Location	Instruction	Address	Meaning
$x - 1$	B	[Code]	Load custom device selection control word into accumulator.
x	R	L	Store starting address of keywords into subroutine body.
$x + 1$	U	L+50	Jump to alternative device-selection entry point.
$x + 2$	...		First control keyword string token word.
...	...		Alphanumeric string control words.
$x + n$	...		Final control keyword string token word, containing 7Q.
$x + n + 1$	...		Main program execution resumes.

Calling Sequence 2 (Custom Peripheral Routing) This configuration differs from the standard entry pattern by exactly two operational instructions. The command at $x - 1$ stages the peripheral selection mask inside the accumulator register. This selection code can be encapsulated within the track address operand field of a standard non-operative instruction word (e.g., xZ tt00, where tt represents the physical target peripheral selector code). The command at $x+1$ branches into the alternative subroutine device configuration entry sequence at offset address L+50.

OUTPUT

Upon execution return to the main program context, the alphanumeric string array text generation sequence has been completely processed and sent to the printer hardware buffer.

OPERATION

1. **Execution Speed:** Throughput clocks at approximately 660 characters per minute.
2. **Program Loading Instructions:** The routine tape distribution features the software in two alternate styles:
 - a) Relocatable hexadecimal format compatible with Program Input 1.
 - b) Relocatable decimal format mapped to the standard coding sheet structure.
3. **Required Input/Output Units:** Hardware data input units are not required. If an alternative hardware peripheral unit other than the primary console typewriter is designated for text routing, the absolute track operational address entries inside locations L+06, L+14, L+22, and L+30 of the subroutine body must be manually patched to match the system configuration constants (consult the *LGP-21 Programming Manual* peripheral channel assignment tables for absolute unit selector byte lists).
4. **Hardware Overflow Flag Status:** The register status is neither read nor impacted by this program's internal loop execution paths.

ALPHANUMERIC OUTPUT 2 — J4-11.1

PURPOSE

J4-11.1 outputs alphabetic and/or numeric information that has been stored without binarization (i.e., stored as raw character codes). The alphanumeric data must be stored as **five-character-long words in 6-bit format**. A data block for J4-11.1 must not exceed 63 locations. The data must be stored in consecutive locations.

The program operates as a subroutine called by a calling sequence from the main program. The starting address of the data block must be supplied to the subroutine before entry. Upon return to the main program, the specified information has already been printed.

STORAGE REQUIREMENTS

Program Space: 24 sectors

Temporary Storage: None

INPUT

Before jumping to the subroutine, the calling sequence must insert into the first location of the subroutine the address of the Z instruction

which contains the starting address of the alphanumeric data block to be printed. This makes it possible to store the data block at any arbitrary location in memory, instead of forcing it to immediately follow the calling sequence as is typical. This Z instruction must not be omitted.

The data table consists of consecutive words of exactly 5 characters or typewriter functions each (the final word may contain fewer). The number of words in a single block must not exceed 63. The data must be stored in ascending order in consecutive locations.

During input storage, the data must be preceded by the constant keyword of J1-10.0 so that it is not binarized. (The input keyword also automatically places an end-of-block marker ``into the final word').

Example

Command	Location	Instruction	Address	Description
	α	R	L	Store return address
	+1	U	L	Entry to subroutine
	+2	Z	AA	Pointer to data block
	+3	u.s.w.		Return to main program
A0000003 A	AA	PLANN		First data word
	+1	ING P		Second data word
	+2	AYS		Final data word

This example causes the printout of PLANNING PAYS and returns execution to +3 of the main program. The end-of-block marker is automatically stored by the program input keyword. The alphanumeric data can reside anywhere in memory.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
α	R	L	Insert the address of the Z instruction (+2) into L.
+1	U	L	Entry into the subroutine.
+2	Z	A	Starting address of the data block (A).
+3		<i>etc.</i>	Return to the main program.

The instruction at α stores the address (+2) of the instruction containing the data block's starting address into the subroutine. The instruction at +1 executes a jump to the starting address (L) of the

subroutine. Location $+2$ contains the Z instruction with A , the starting address of the data block. Location $\alpha+3$ contains the instruction of the main program that will be executed first after exiting the subroutine.

Please note: The Z instruction must always reside directly within the calling sequence, even if the data block immediately follows the calling sequence.

OUTPUT

Upon return to the main program, the desired data block has already been output to the terminal.

OPERATION

1. Time Required: Approximately 190 characters per minute.
2. Program Input: The tape contains the program in two versions:
 - a) Arbitrarily relocatable hexadecimal (valid for Program Input 1).
 - b) Arbitrarily relocatable decimal (in coding sheet format).
3. Required Input/Output Units: No input units are required. The standard typewriter is selected for output by default. If a different output unit is to be used, the track addresses in locations L+03, L+05, L+07, L+09, and L+11 of the subroutine must be replaced with the corresponding selection identifier (see the *LGP-21 Programming Manual*, where selection identifiers and their associated units are listed).
4. Overflow: Neither tested nor altered by the program.

REMARKS

The program should ideally begin at Sector 00 to ensure optimal drum execution timing.

14 Hexadecimal Input

HEXADECIMAL INPUT 3 — J5-10.0

PURPOSE

J5-10.0 reads and stores hexadecimal tapes that were produced by the program Hexadecimal Output 3 (J4-10.2). Only full tracks can be stored, up to the limit of storage space available. The program is optimized for high-speed reading.

STORAGE REQUIREMENTS

Memory used: 3 tracks (192 words)

Temporary storage: none

INPUT

After a jump to the starting address of the program, the computer selects the typewriter and requests the identification code for the input unit to be used by the program. Use (0000 for the high-speed reader or 0200 for the Flexowriter reader). Enter the corresponding word in hexadecimal notation and press START.

The program reads tapes in a special hexadecimal word format. The words must be arranged in groups of 64, with each group corresponding to one track. Each group must be preceded by a four-character hexadecimal input command of the form tt00, whereby tt represents the track number. Each group must also be followed by a checksum of all the words in the group.

The words must be in the specific order described below, with the words separated by a single space. This optimizes the read/write speed of the program at the expense of pre-shuffling the words from 00, 01, 02,..., 64 into the indicated order.

56, 58, 60, 63, 01, 03, 05, 62, 00, 02, 04, 06, 08, 10, 12,
07, 09, 11, 13, 15, 17, 19, 14, 16, 18, 20, 22, 24, 26, 21,
23, 25, 27, 29, 31, 33, 28, 30, 32, 34, 36, 38, 40, 35, 37,
39, 41, 43, 45, 47, 42, 44, 46, 48, 50, 52, 54, 49, 51, 53,
55, 57, 59, 61.

The subroutine is capable of accepting a Stop and Jump'' command of the form 8000ttss, whereby ttss is a track/sector address in hexadecimal notation. The key word must always *follow* a checksum to avoid it being stored as part of the input. If this command is read after a checksum, the computer stops, and when START is pressed, a jump occurs to the address specified in the command and execution continues.

J5-10.0 performs a check sum of the input as it is read. After each full track, this checksum is compared with the one on the tape following

the block. If the checksums match, reading continues. If not, the program prints a carriage return and e is printed, and stops (see error stops).

CALLING SEQUENCE

The program is run by executing by a jump to its starting address. If the program has only just been read in, pressing START runs it.

OUTPUT

The program to be read in is stored on the specified tracks in the correct sequence. No other output.

OPERATION

- Time requirement: approx. 13 sec. for the input of one track.
- Program input: The tape contains the program in four versions:
 - a) Arbitrarily relocatable hexadecimal with bootstrap on track 00.
 - b) Arbitrarily relocatable hexadecimal with bootstrap on track 63.
 - c) Arbitrarily relocatable hexadecimal permissible for Program Input 1 (J1-10.0).
 - d) Arbitrarily relocatable decimal in coding sheet format.

The input procedure varies depending on the version used:

Arbitrarily relocatable hexadecimal with bootstrap

Arbitrarily relocatable hexadecimal programs with their own bootstrap permit the operator to enter the program either via the paper tape typewriter or via the high-speed reader, since a special bootstrap is provided for each input unit. They appear on the tape in the following sequence:

1. Track-00-bootstrap for input of the program via the high-speed reader.
2. Track-00-bootstrap for input of the program via the paper tape typewriter.
3. Program J5-10.0.
4. Track-63-bootstrap for input of the program via the high-speed reader.

5. Track-63-bootstrap for input of the program via the paper tape typewriter.

6. Program J5-10.0.

One chooses a bootstrap corresponding to the desired track and input unit, and enters it according to the bootstrap procedure (described in Program Input 1).

The first instruction stored in the bootstrap is the address modifier, which sets the starting address of the program to be stored. The following modifiers are preset on the tape, and can be changed as desired:

- Track-00-bootstraps have the modifier 0000.
- Track-63-bootstraps have the modifier 6100.

Arbitrarily relocatable hexadecimal, permissible for Program Input 1

This version is read in according to the procedure described in Program Input 1.

Required input/output units:

The input unit is selected by a suitable selection code at the beginning of the operation of the subroutine (see Input). An output unit is not required.

Error stops:

Printout	Meaning and Remedy
e	The checksums do not match. Rewind the tape to the beginning of the last group and restart.

REMARKS

The program should be loaded in an even-numbered track, so that the reading-in occurs optimally.

ADDENDUM

The tape ``Hexadecimal Input 3'' in arbitrarily relocatable hexadecimal version with Track-00- or Track-63-bootstrap, can be patched so that it can be stored at the beginning of a program tape. After the following alterations, the program will automatically select the same input unit it was read on for its own input.

```
'c01gj'8'u02g4'j's01k0'10'c0068'30'u0034'64'u0068'w4'b00k.j'w8'  
u02g8'70'u0074'78'u007j'80'u0084'88'c0118'8j'b0100'  
1q0'a0000'1q4'a0000'1q8'a0000'1qj'a0000'1w0'a0000'1w4'a0000'  
1w8'a0000'200'80010000'204'18'2f4'kj'2f8'q4'2fj''c00w4''
```

The alteration adds four additional instructions in the first line and modifies the last word in the last line. The rest of the program, including bootstrap, remains unaltered.

15 Specialized Input/Output

DIRECTION OR ANGLE INPUT AND OUTPUT 1 — J9-11.0

PURPOSE

J9-11.0 reads or prints a positive or negative angle, or a direction, consisting of the specification of the quadrant and a positive angle. All angles must be smaller than 512° , and direction angles must not be greater than 90° ⁴³. The entered angle or peak circle [vertex circle] of the direction is binarized and placed into the accumulator.

The printing of an angle occurs in decimal notation in degrees and minutes, each followed by a dash, and in seconds, accurate up to one-tenth of a second. For a direction, the angle is printed in the same way, except that a character N (North) or S (South) precedes it and a character E (East) or W (West) follows it.

The program operates as a subroutine that is called by a calling sequence of the main program. Before the jump into the subroutine, the calling sequence must store the return address. In the case of the output function, the angle or the direction must stand in the accumulator before the entry into the subroutine occurs. Upon return to the main program, the angle or the direction is read and placed into the accumulator if the input function was called, or the angle or the direction is printed if the output function was called.

STORAGE REQUIREMENTS

Memory: 2 tracks, 61 sectors (189 words)

Temporary storage: sectors 2, 5, 15, 17, 48, 51, 52, 56, and 60 of track 63

INPUT

The input for the program consists of one of the two following possibilities:

1. A positive angle in decimal notation in degrees, minutes, and seconds.
2. A direction, consisting of the characters S or N, a positive angle in decimal notation in degrees, minutes, seconds, and the characters E or W.

Each value must be specified as one word; e.g.: 1422038' to specify an angle of $142^\circ 20' 38''$; S204010W to specify the direction SW $20^\circ 40' 10''$; or N000342E to specify the direction NE $0^\circ 3' 42''$.

⁴³The German text here says "600" rather than 90° , but the Input section below correctly gives 90° , so I've used that value here. Since directions specify a quadrant plus an angle within it, 90° is the right limit.

The angle specification can be at most seven digits; leading zeros on the left may be omitted. All angles must be smaller than 512° . Every direction specification must consist of eight characters; for vanishing quantities, the zeros must be written out completely; algebraic signs are not specified. The angle specifications for directions must not be greater than 90° .

CALLING SEQUENCE

In the subroutine, three calling sequences are provided: 1. for input, 2. for angle output, 3. for direction output. In every case, L_0 is the starting address of the subroutine.

1. Input:

Intended for reading in an angle or a direction.

Memory Location	Instruction	Address	Meaning
α	R	$L_0 + 47$	Store return address in the subroutine.
+1	U	L_0	Entry into the subroutine.
+2		<i>etc.</i>	Return to the main program.

2. Angle Output:

Intended for printing an angle. The angle must reside in the accumulator at $q = 9$ before the jump into the subroutine occurs.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	[angle]	Bring the angle into the accumulator.
α	R	$L_0 + 249$	Store return address in the subroutine.
+1	U	$L_0 + 100$	Entry into the subroutine.
+2		<i>etc.</i>	Return to the main program.

3. Direction Output:

Intended for printing a direction. The peak circle of the direction must reside in the accumulator at $q = 9$ when the jump into the subroutine occurs.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	C3	Bring peak circle into the accumulator.
α	R	$L_0 + 219$	Store return address in the subroutine.
$+1$	U	$L_0 + 200$	Entry into the subroutine.
$+2$		<i>etc.</i>	Return to the main program.

In the calling sequences 2 and 3, the instruction in $\alpha - 1$ does not need to be a B instruction. Any instruction sequence that brings the quantity to be outputted at $q = 9$ into the accumulator is permissible. In all calling sequences, the instruction in α stores the return address ($\alpha+2$) into the subroutine. The instruction in $\alpha+1$ effects a jump to the corresponding location of the subroutine. In $\alpha+2$ stands the instruction of the main program that is executed first after running through the subroutine.

OUTPUT

The program binarizes every entered angle or the peak circle of every direction specification and places them at $q = 9$ into the accumulator.

Each angle printout occurs in decimal form in degrees, minutes, seconds, and tenths of a second, whereby the degrees and minutes are followed by a separation dash; e.g., an angle of $80^\circ 37' 01''$ would be printed out as 80-37-01.0.

Upon output of a direction, the angle is written in the same manner, however one of the letters N or S precedes the angle specification, and one of the letters E or W follows it; i.e., a direction of NW $42^\circ 1' 28''$ would be printed as N 42-01-28.0W.

OPERATION

1. Accuracy: max. error: ± 1 second.
2. Time requirement: approx. 1.5 seconds to read or write a quantity.
3. Program input: The tape contains the program in two ways:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
 - b) arbitrarily relocatable, decimal, in coding sheet format.
4. **Required input/output units:** The subroutine selects the paper tape typewriter both for the input and for the output. The selection can be changed by changing the following memory contents:

Input (80XItt00)	Output (80XPtt00)	Output (XPtt00)
$L_0 + 1$	$L_0 + 105$	$L_0 + 116$
$L_0 + 113$	$L_0 + 121$	$L_0 + 126$
$L_0 + 123$	$L_0 + 133$	$L_0 + 136$
$L_0 + 131$	$L_0 + 142$	$L_0 + 210$
$L_0 + 140$	$L_0 + 216$	
	$L_0 + 218$	

5. **Overflow:**
Is not tested upon entry, but is however reset upon output.

REMARK

After each outputted value, a tabulator jump [tab command] is executed.
To suppress the printing of the period and the last decimal place, change $L_0 + 137$ from E0252 to U0247.

16 Tracing

TRACE 1 — K1-10.0

PURPOSE

K1-10.0 facilitates the debugging of a fixed-point program residing in memory by providing a detailed printout. Any or all addresses, instructions, and/or the results of their execution can be printed. Addresses are written in decimal track/sector notation; calculation results are written in hexadecimal form.

STORAGE REQUIREMENTS

Memory: 3 tracks, 51 sectors (243 words)

Temporary storage: none

INPUT

This subroutine establishes simulated counters, instruction registers, an accumulator, and a PST [Program Sense Switch] in memory.

When the program is executed, the computer selects the Flexowriter, prints a carriage return, and requests the address of the main program which is to be traced in decimal track/sector notation.

When this address has been entered, or when PST has been turned ON, the computer selects the typewriter, executes a carriage return, and requests an output formatting command. A list of command characters and their functions follows. The registers mentioned in these commands -- accumulator, counter register, and instruction register -- are the registers simulated by this program.

Command	Function
T	Turns on simulated PST. This "switch" has the same function while tracing the tested program as the real PST would during normal operation of the traced program.
C	Print the contents of the simulated counter register in decimal track/sector notation after the execution of each instruction of the traced program.
R	Print the contents of the instruction register in instruction format after execution of each instruction of the traced program. The instruction is preceded by a space character or a minus sign.
A	Print the contents of the accumulator in hexadecimal notation after the execution of each instruction of the traced program.

Note: Any combination of the above command characters can be entered and the corresponding commands remain in effect until the next input. Entering a new command disables all functions first and then re-enables the ones entered. These characters may be entered in any order.

Command	Function
X	Restart the program and enter a new address for tracing.
0	Continue tracing from the point where execution was stopped, without printout.
(none)	Pressing START without entering T, C, R, or A causes tracing to continue from the point where execution was stopped; the previous key words remain effective.

Note: The accumulator is never re-initialized by ``Trace 1''. The program under test must take care of this housekeeping itself.

CALLING SEQUENCE

Start execution via a jump to the starting address.

OUTPUT

The program prints the content of the simulated registers and/or the accumulator depending on the key word specification after each instruction of the program under test has been executed.

The instructions of the program under test are in fact executed exactly as they would be during normal program flow. Any output from the traced program is written on the same line as the content of the simulated registers. When the program traces without printing, any output that occurs is executed exactly where the P instruction of the traced program has it.

If the physical PST switch is turned ON during tracing, the computer print a carriage return and the contents of the simulated registers according to the currently-specified command characters. The computer then stops and requests the entry of a command. Continuously pressing **START** in this state causes the execution of the respective next instruction of the traced program, exactly as if the computer were in ONE OPER mode. This continues until PST is turned OFF.

Note that tracing without output can cause confusion if the traced program executes an I instruction. If the PST is ON, the computer prints a carriage return, the address of the last traced instruction, and requests a new command. In this state, pressing **START** allows execution to continue, but if the following instruction requests input again, the computer stops again -- but this time Any input will be routed

to the program under test. This state can be recognized by the fact that there was no address printout before the computer stopped.

OPERATION

1. Program input:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for J1-10.0,
and
- b) arbitrarily relocatable, decimal, in coding sheet format.

2. Required input/output units:

The subroutine selects the paper tape typewriter for input and output.

3. Program sense switches:

Switch	Position	Function K1-10.0
PST	OFF	No effect.
	ON	Jump to an input instruction of the program to enter new commands.

4. Error stops:

The subroutine executes all Z instructions of the program under test as stops. The only stop instructions in the trace program itself are before the initial output formatting command and before the entry of a new trace address.

REMARK

If the traced program requests input during checking, the least significant bit of the entered word is lost.

17 Memory Dumps

MEMORY PRINT 1 — K2-10.0

PURPOSE

K2-10.0 outputs the contents of a specified memory region. There are three possible types of output:

- a) in coding sheet format,
- b) arbitrarily relocatable decimal, permissible for J1-10.0,
- c) both: a and b.

The words can be output as instructions or as hexadecimal constants, depending on appearance or according to the specifications of the user. If hexadecimal words are punched, they are preceded by the input key word for hexadecimal constants. Output occurs location by location in ascending sequence.

STORAGE REQUIREMENTS

Memory: 9 tracks (576 words)

Temporary storage: none

INPUT

After a jump to the starting address of K2-10.0, the computer requests the following information:

Question	Answer
lins	Number of lines per page as a two-digit decimal number.
locs	Number of memory addresses to be printed on a page as two decimal digits.
wrds	The number of words to be printed in one line (only becomes effective if PS-4 is ON) as two decimal digits.
skip	The number of blank lines between two pages as a two-digit decimal number.

Note: The above answers must consist of two digits: zero must be entered as ``00''. The blank lines between pages are output when either the full number of memory addresses has been printed, or when the number of outputted lines plus ``skip'' equals ``lins''.

Note: In all address specifications, the second address must be higher than the first.

Question	Answer
md a	The boundaries of the memory region in which the modifier is to become effective (see below) in one word in decimal track/sector notation (i.e., TTSSTTSS).
modi	The value that is to be subtracted from the address part of the instructions in the modification region, in decimal track/sector notation.
hx a	The boundaries of the region that is to be output in the form of hexadecimal words, regardless of content, as one word per region in decimal track/sector notation (i.e., TTSSTTSS). The termination of input is designated by pressing START twice after the last address.
pnch	The boundaries of the output region as one word in decimal track/sector notation (i.e., TTSSTTSS).

If PS-32 is ON when the program starts, the computer skips the first four questions and uses the values from the previous run or the defaults: lins=51, locs=32, wrds=08, and skip=08.

The program *does not stop* after the answer to ``pnch''. The typewriter lever PUNCH ON should already be pressed when START is pressed.

CALLING SEQUENCE

The program is run by a jump to the starting address.

OUTPUT

The output occurs in one of two versions, depending on the setting of PS-4.

- aON) Each line begins with an address (absolute minus modifier) followed by a space character and one instruction per line. Input key words for hexadecimal words are printed out one to a line and are counted toward the number of lines per page.
- OFF) Each line begins with the address (absolute minus modifier) of the first word of that line, followed by a space character and as many words as specified for ``wrds''. Input key words for hexadecimal words are not counted toward the number of words per line.

For both formats, eight characters are output per word. Hexadecimal words contain leading zeros where applicable. Instruction words replace leading zeros with spaces.

All instructions outside the modification region are preceded by an ``X'' during output. P and I instructions are never modified and

are always provided with an X^{44} . Hexadecimal words are output in groups of at most 63 words; each group is preceded by a command for hexadecimal input (see J1-10.0 regarding the command).

Every word that contains a ``1' bit outside of the sign position of the operation part and the operand address field is output as a hexadecimal word. If a word looks like an instruction but is in reality a hexadecimal word, this must be specified during the entry of hx a. If instructions in the modification region are not designated as hexadecimal words, or if they are not P or I instructions, the modifier is subtracted from the operand addresses and they are not dumped with an X.

Memory is dumped in ascending location order. The program sense switches can be used as noted below to control the output type and format. Once the whole of the selected region has been output, the computer stops; pressing START restarts the program.

OPERATION

1. Program input:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
- b) arbitrarily relocatable, decimal, in coding sheet format.

2. Required input/output units:

The subroutine selects the paper tape typewriter for input and output.

3. Program sense switches:

REMARKS

Optimal operation is independent of the starting sector number.

If only a single memory dump is needed, Memory Print 2, K2-10.1 is preferable.

ADDENDUM

Suppression of the address printout:

During the generation of a decimal tape, an address is output at the beginning of each line. This tape can be read in via the typewriter using Program Input 1, but not via the high-speed reader.

K2-10.0 can be patched to suppress the output of the memory addresses; this produces a tape that can be entered via the high-speed reader.

L_0 is the starting address of K2-10.0.

⁴⁴Relocating unit constants is a bad idea.

Switch	Position	Function
PS-4	ON	Prints an address (minus modifier) and a predetermined number of words per line. Key words for hexadecimal input are not counted.
	OFF	Prints an address and its content per line. A key word for hexadecimal input is counted as one line.
PS-8	ON	Jump to the starting address of the subroutine and request new parameters when the next word is output.
	OFF	No effect.
PS-16	ON	Halt after the output of each word. Continuation after pressing "Start".
	OFF	No effect.
PS-32	ON	The computer uses the page format from the previous run, or if the program was only just read in, the page format native to the original program (i.e., the first four questions and answers are omitted).
	OFF	Computer requests page format specifications.

In Location	Replace	By
$B[L_0 + 0242]$	$L_0 + 0234$	$U[L_0 + 0241]$

MEMORY DUMP 2 — K2-10.1

PURPOSE

K2-10.1 dumps the contents of consecutive locations in ascending sequence. The words are printed in hexadecimal or in instruction format, depending on the content or the state of the PST.

STORAGE REQUIREMENTS

Memory used: 2 tracks (128 words)

Temporary storage: none

INPUT

After jumping to the starting address, the computer requests the following output parameters:

1. L_s Starting address of the region to be output in decimal track/sector notation.
2. L_e Ending address of the region to be output in decimal track/sector notation.

The ending address of a region must in each case be higher than the starting address. If L_e is numerically smaller than L_s , the computer prints L_e and a carriage return, and requests new parameters.

After the dump the specified memory region, the computer requests new output parameters.

CALLING SEQUENCE

The program is executed by a jump to its starting address.

OUTPUT

The program prints one address and eight words per line until the content of the last address has been printed out. Hexadecimal words are printed if there are ``1'' bits outside of the sign, operation part, and operand address part, or if the PST is ON. Instruction words are printed if the above conditions do not apply. Negative instructions are preceded by a minus sign. The contents of consecutive locations are output in ascending sequence.

OPERATION

1. Program input:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
- b) arbitrarily relocatable, decimal, in coding sheet format.

2. Required input/output units:

The subroutine selects the paper tape typewriter for input and output.

3. Program sense switches:

Switch	Position	Function
PST	ON	Print in hexadecimal word format.
	OFF	Print in the format defined by the memory content.

REMARKS

This program is intended as a simple tool for memory investigation. If an output useful for Program Input 1 is desired, one should use K2-10.0.

18 Sorting

SORTING 1 — L1-10.0

PURPOSE

L1-10.0 sorts a list of numbers within memory by magnitude (smallest value to largest value) according to a specified mask. The sorted numbers are stored in the same memory region as the unsorted ones, so no additional memory space is required. The mask determines which parts of the words are compared.

The program operates as a subroutine called by a calling sequence from the main program. Upon jumping to the subroutine, the starting address of the numbers to be sorted must reside in the accumulator, and the address of the mask must have been stored in the subroutine. The two locations following the jump instruction must contain the mask and the ending address of the list. Upon returning to the main program, the numbers stand sorted by magnitude (smallest to largest) in the original memory region of the list.

STORAGE REQUIREMENTS

Memory: 1 track, 32 sectors (96 words)

Temporary storage: sectors 54, 55, 62, and 63 of track 63

INPUT

Sequence of input variables:

1. L_1 Starting address of the numbers to be sorted in decimal track/sector notation.
2. Arbitrary mask controlling the sorting process, in hexadecimal notation.
3. L_2 Ending address of the numbers to be sorted in decimal track/sector notation.

The mask must not contain a ``1'' in the sign position, as the subroutine ignores the sign of the numbers being sorted. L_1 and L_2 are inclusive.

Upon jumping to the subroutine, L_1 at $q = 29$ must reside in the accumulator. The locations following the jump instruction must contain the mask and L_2 . The numbers to be sorted must reside in consecutive locations.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Bring L_1 at $q = 29$.
α	R	$L_0 + 3$	Store the address of the mask in the subroutine.
$+1$	U	L_0	Jump to the subroutine.
$+2$	,0000001'		Mask.
$+3$	Z	L_2	Specification of L_2 .
$+4$		<i>etc.</i>	Return to the main program.

CALLING SEQUENCE

The instruction at $\alpha - 1$ brings L_1 into the accumulator at $q = 29$. (Any instruction that achieves this may be used.) The instruction at α stores the address of the mask ($\alpha+2$) in the subroutine. The instruction at $\alpha+1$ effects a jump to L_0 , the starting address of the subroutine. Location $\alpha+2$ contains the hexadecimal mask. The instruction at $\alpha+3$ contains L_2 . Location $\alpha+4$ contains the instruction of the main program that is executed first after the subroutine runs.

OPERATION

1. Execution time:

Average values:

- 32 words -- 114 sec.
- 64 words -- 6 min.
- 128 words -- 27 min.

2. Program entry:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
- b) arbitrarily relocatable, decimal, in coding sheet format.

3. Required input/output units:

No input or output units are required.

4. Overflow:

Ignored upon entry and not reset upon exit.

EXAMPLE

Suppose numbers are stored in locations 1500 to 1731, which are to be sorted according to their content in bit positions 7 to 11 and 24

to 29. Let ``Sorting 1'' be stored at 700 to 832, and the main program occupies locations 900 to 1215. The calling sequence would look as follows:

Memory Location	Instruction	Address	Meaning
1011	B	1211	Bring L_1 at $q = 29$.
1012	R	0703	Set the address of the mask.
1013	U	0700	Jump to the subroutine.
1014	,0000001' 01W0 00WJ		Mask.
1015	Z	1731	L_2 .
1016		<i>etc.</i>	Return to main program.
1211	Z	1500	L_1 .

The instruction in 1011 brings 1500 at $q = 29$ into the accumulator; the instruction in 1012 stores the address of the mask to 0703; and the instruction in 1013 effects a jump to the starting address of ``Sorting 1''. Location 1014 contains the sorting mask. Note that only those bit positions that correspond to ``1'' bits in the mask are compared. The instruction in 1015 defines the ending address of the list. Location 1016 contains the main program instruction to which execution returns.

SORTING 2 — L1-10.1

PURPOSE

L1-10.1 sorts one-word or multi-word ``intervals'' [records] within a contiguous memory region by magnitude (smallest value to largest value) according to a designated ``sorting key word'' located within each respective record. Each record can be 1 to 64 words long. An additional memory region is required to temporarily buffer record contents during the sorting process. Sorting occurs relative to an arbitrary mask.

``Sorting 2'' operates as a subroutine called by a calling sequence from the main program. Upon jumping to the subroutine, a key word specifying the number of records to process and the starting address of the first record must reside in the accumulator. Additionally, the calling sequence must supply the ``sorting key word'' position and the mask. Upon returning to the main program, the records stand sorted in the original memory region.

STORAGE REQUIREMENTS

Memory: 4 tracks (256 words)

Temporary storage: 2 tracks ($L_0 + 0400$ to $L_0 + 0563$, where L_0 is the starting address of the subroutine).

INPUT

The input consists of three hexadecimal key words supplied by the calling sequence and the record contents to be sorted. The key words are:

1. R , the number of records at $q = 15$; and L_1 , the starting address of the first record at $q = 29$.
2. N , the number of words in each record at $q = 15$; and K , the position of the sorting key word within a record at $q = 29$. (For example, $K = 3$ at $q = 29$ specifies that the third word of the record is the sorting key).
3. A mask indicating the bit positions to be compared during sorting.

The number of records sortable in a single run is limited only by available memory space. For N (the number of words per record), the following applies: $1 \leq N \leq 64$. The mask should not contain a ``1'' in the sign position, as the subroutine ignores the sign of the words during sorting.

The records to be sorted must reside in consecutive locations.

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Bring the word containing R and L_1 .
α	R	$L_0 + 20$	Store the address of the control data.
+1	U	L_0	Entry to subroutine.
+2	,0000002' N K		N at $q = 15$; K at $q = 29$.
+3	Mask		Mask.
+4		<i>etc.</i>	Return to main program.

CALLING SEQUENCE

The instruction at $\alpha - 1$ brings R at $q = 15$ and L_1 at $q = 29$ into the accumulator. (Any instruction that accomplishes this is permissible.) The instruction at α stores the address ($\alpha + 2$) of the instruction containing N and K into the subroutine. The instruction at $\alpha + 1$ effects a jump to L_0 , the starting address of the subroutine. Location $\alpha + 2$ contains N at $q = 15$ and K at $q = 29$. Location $\alpha + 3$ contains the mask. After $\alpha + 4$, execution returns from the subroutine.

OPERATION

1. Execution time:
An average of 3 seconds per word for small examples.
2. Program entry:
The tape contains the program in two versions:
 - a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
 - b) arbitrarily relocatable, decimal, in coding sheet format.
3. Required input/output units:
No input or output units are required.
4. Overflow:
Ignored upon entry and not reset upon exit.

EXAMPLES

Let the subroutine begin at 300; the main program occupies tracks 10 to 15.

Example 1

Sort 37 words, stored in 4900 to 4936, treated as 37 single-word records, considering only bits 15 to 30.

Memory Location	Instruction	Address	Meaning
1010	B	1559	Bring R and L_1 .
1011	R	0320	Store the N-K word address.
1012	U	0300	Jump to "Sorting 2".
1013	,0000002' 0001	0004	$N = 1$ at $q = 15$; $K = 1$ at $q = 29$.
1014	0001 wwwQ		Mask for bits 15 to 30.
1015		<i>etc.</i>	Return to main program.
1559	,0000001' 0025	3100	$r = 37$ at $q = 15$; $L_1 = 4900$.

Note that during sorting, the subroutine only compares word components that match ``1' bits in the mask.

Example 2

Sort 32 words, stored in 3200 to 3231, treated as eight 4-word records. They are to be sorted by magnitude according to the value of the second word of each record (smallest value to largest value; sorting the full records based on the magnitude of their respective second words). The comparison should only occur at bit positions 4 to 11 and 16 to 20.

Memory Location	Instruction	Address	Meaning
1401	B	1563	Bring R and L_1 .
1402	R	0320	Store the N-K word address.
1403	U	0300	Jump to "Sorting 2".
1404	,0000002' 0004	0008	$N = 4$ at $q = 15$; $K = 2$ at $q = 29$.
1405	0ww0 W800		Mask for bits 4–11 and 16–20.
1406		<i>etc.</i>	Return to main program.
1563	,0000001' 0008	2000	$R = 8$ at $q = 15$; $L_1 = 3200$.

Sample printouts follow, showing what both calling sequences achieve.

SAMPLE PRINTOUT

Example 1

Location	Unsorted
4900	0wj00004'
4901	g0000010'
4902	00jj0018'
4903	0kqw0026'
4904	00qj001j'
4905	7wqj002f'
4906	0fg00008'
4907	0w000030'
4908	0k00000f'
4909	0q00003j'
4910	0g000032'
4911	0w00000j'
4912	0q00003w'
4913	0f00001f'
4914	qj00003j'
4915	00000014'
4916	w000012j'
4917	0w000006'
4918	0q00000b'
4919	qk000020'
4920	3j000064'
4921	fg000190'
4922	kf000002'

Location	Unsorted
4923	0k000012'
4924	00000036'
4925	0k000022'
4926	0j000016'
4927	0q000038'
4928	0w000258'
4929	0f00003w'
4930	0j000024'
4931	0000001w'
4932	0g00003f'
4933	0f0000j8'
4934	0g000034'
4935	0k000028'
4936	0w0001w2'

Location	Sorted
4900	kf000002'
4901	0wj00004'
4902	0w000006'
4903	0fg00008'
4904	0k00000f'
4905	0w00000j'
4906	0q00000b'
4907	g0000010'
4908	0k000012'
4909	00000014'
4910	0j000016'
4911	00jj0018'
4912	0f00001f'
4913	00qj001j'
4914	0000001g'
4915	qk000020'
4916	0k000022'
4917	0j000024'
4918	0k000028'
4919	7wqj002f'
4920	0w000030'
4921	0g000032'
4922	0q000034'

Location	Sorted
4923	00000036'
4924	0q000038'
4925	0g00003f'
4926	0q00003j'
4927	qj00003j'
4928	0g00003q'
4929	0f00003q'
4930	3j000064'
4931	0f0000j8'
4932	w000012j'
4933	fg000190'
4934	0w0001w2'
4935	0w000258'
4936	0kqw0026'

Example 2

Location	Unsorted	Location	Sorted
3200	080403j0'	3200	0f0803j0'
3201	02q05000'	3201	0080f800'
3202	00001000'	3202	000f0800'
3203	00g00005'	3203	01606800'
3204	0404003g'	3204	01050330'
3205	03g0q800'	3205	01607000'
3206	00048000'	3206	0fg09800'
3207	02q0w800'	3207	00j080j0'
3208	030j03g0'	3208	040403g0'
3209	02q0w800'	3209	0160q000'
3210	03g00000'	3210	00j0q000'
3211	0010j0w0'	3211	000gq000'
3212	040403g0'	3212	080403j0'
3213	0160q000'	3213	02g05000'
3214	00j0q000'	3214	00001000'
3215	000gq000'	3215	00g00004'
3216	040403j0'	3216	030j03g0'
3217	03g0f800'	3217	02q0w800'
3218	0ww0w800'	3218	03g00000'
3219	0q801000'	3219	0010j0w0'
3220	090w03jo'	3220	040403j0'
3221	03g0f800'	3221	03g0f800'
3222	016j8000'	3222	0ww0w800'
3223	03g0f800'	3223	0q801000'
3224	010303jo'	3224	090w03jo'
3225	01607000'	3225	03g0f800'
3226	0fg09800'	3226	016j8000'
3227	005080jo'	3227	03g0f800'
3228	0f0803j0'	3228	0404003f'
3229	0080f800'	3229	03g0q800'
3230	000f0800'	3230	00048000'
3231	01606800'	3231	02q0w800'

SORTING 3 — L1-10.2

PURPOSE

L1-10.2 sorts a list of numbers within memory by magnitude (smallest value to largest value) according to a specified mask. Although the sorted numbers are written back to their original memory region, additional buffer locations are required. The mask determines which parts of the

words are compared.

The program operates as a subroutine called by a calling sequence from the main program. Upon jumping to the subroutine, the number of words in the list must reside in the accumulator. The locations following the jump instruction must contain the starting address of the list and the mask. Upon returning to the main program, the numbers stand sorted by magnitude (smallest to largest) in the original memory region of the list.

STORAGE REQUIREMENTS

Memory: 3 tracks (192 words)

Temporary storage: none

INPUT

The input variables for ``Sorting 3'' are listed below in the sequence of their appearance in the calling sequence:

1. N , the number of values to be sorted in decimal track/sector notation.
2. S_0 , the starting address of the words in decimal track/sector notation.
3. The arbitrary mask directing the sorting process, in hexadecimal notation.

The numbers to be sorted must be positive and reside in consecutive locations.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Bring N at $q = 29$.
α	R	$L_0 + 63$	Store the address of the first list word in the subroutine.
+1	U	L_0	Jump to the subroutine.
+2	Z	S_0	Starting address of the list.
+3	,0000001' Mask		Mask.
+4			<i>etc.</i> Return to main program.

The instruction at $\alpha - 1$ brings N into the accumulator. (Any instruction that achieves this is permissible.) The instruction at α stores the

address $(\alpha+2)$ of the first list word in the subroutine. The instruction at $\alpha+1$ effects a jump to L_0 , the starting address of the subroutine. Location $\alpha+2$ contains the address S_0 of the first list word, and location $\alpha+3$ contains the hexadecimal word representing the mask. After $\alpha+4$, control returns from the subroutine.

OPERATION

1. Execution time:

Average values:

- 32 words -- 1.95 min.
- 64 words -- 5.50 min.
- 128 words -- 12.87 min.

2. Program entry:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
- b) arbitrarily relocatable, decimal, in coding sheet format.

3. Required input/output units:

No input or output units are required.

4. Overflow:

Ignored upon entry and not reset upon exit.

EXAMPLE

The contents of locations 1514 to 1645 are to be sorted by magnitude, considering only bit positions 3 to 9 and 18 to 23. Let ``Sorting 3'' occupy 0500 to 0763, and the main program occupies 3600 to 4228.

Memory Location	Instruction	Address	Meaning
3715	B	4221	Bring N (96 words).
3716	R	0563	Set the list address.
3717	U	0500	Entry to subroutine.
3718	Z	1514	Starting address of the list.
3719	,0000001'	1WJ0 3W00	Mask.
3720		<i>etc.</i>	
4221	Z	0132	$N = 1$ track, 32 sectors.

Please note that during sorting, only those bit positions that correspond to ``1'' bits in the mask are compared.

SORTING 4 — L1-10.3

PURPOSE

L1-10.3 sorts single-word or multi-word ``intervals'' [records]. In a list of single-word records, every word is treated as a comparison word [key]. In a list of multi-word records, any arbitrary word at the same position across all records can be designated as the comparison key word.

The sorting process can be executed using any of the three following methods:

- Method I:** Sorts the comparison key words by magnitude (smallest value to largest value) and generates a contiguous list of the addresses where these key words are located; i.e., the first location of the new list contains the address of the key word with the smallest numerical value from the original list.
- Method II:** Sorts the comparison key words by magnitude (smallest value to largest value) and creates a contiguous list containing only the sorted key words themselves.
- Method III:** Sorts the comparison key words by magnitude (smallest value to largest value) and generates a new list containing the fully sorted records. With this method, the new sorted list has the exact same length as the original list.

Note: If two comparison key words are identical in magnitude, the first one encountered is treated as though it has the smaller value.

The program is invoked via a calling sequence from the main program. Upon jumping to ``Sorting 4'', the starting address of the parameter list must reside in the accumulator. Upon returning to the main program, the list stands sorted and stored in accordance with the specifications in the parameter list.

STORAGE REQUIREMENTS

Memory used: 3 tracks (192 words)

Temporary storage: none

PROGRAM VARIABLES

The seven program parameters must be specified in the following exact sequence:

1. bbbb, the starting address of the unsorted list.
2. aaaa, the starting address of the memory region where the sorted list is to be stored.

3. nnnn, the number of records [intervals] in the list, in decimal track/sector notation.
4. www, the number of words per record [interval], in decimal track/sector notation.
5. kkkk, specifies which word within each record is to be used as the comparison key word.
6. t, the selection code for the sorting method: 1 for Method I, 2 for Method II, or 3 for Method III.
7. mmmm mmmm, the mask, in hexadecimal notation.

Note: The mask must not contain a ``1' in the sign position, as the program ignores the sign of the key words.

CALLING SEQUENCE

The starting address of the parameter list is designated as β . This address β must reside in the accumulator when the jump to the subroutine occurs.

Memory Location	Instruction	Address	Meaning
α	B	L	Bring the starting address of the parameter list (β) into the accumulator.
+1	R	$L_0 + 1$	Store the return address.
+2	U	L_0	Entry to the subroutine.
+3		<i>etc.</i>	Return point in the main program.

The parameter block list for the subroutine is defined as follows:

OPERATION

1. Execution time:

Examples:

- 64 single-word entries: 27 min. 15 sec.
- 32 two-word entries: 7 min. 25 sec.

2. Program entry:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
- b) arbitrarily relocatable, decimal, in coding sheet format.

Memory Location	Instruction	Address	Meaning
β	XZ	bbbb	Starting address of the unsorted list.
+1	XZ	aaaa	Starting address of the sorted destination region.
+2	XZ	nnnn	Number of records [intervals] per list.
+3	XZ	www	Number of words per record [interval].
+4	XZ	kkkk	Position index of the comparison key word within all records.
+5	XZ	000t	Selection code for the sorting method ($t = 1, 2$, or 3).
+6	mmmmmmmm		Comparison mask.

3. Required input/output units:

No input or output units are required.

4. Overflow:

Ignored upon entry and not reset upon exit.

EXAMPLE

The example demonstrates the three available sorting methods. Sample calling sequence for ``Sorting 4'' stored starting at 4100:

Memory Location	Instruction	Address	Meaning
3013	B	3129	Bring parameter word address.
3014	R	4100	Set subroutine linkage.
3015	U	4201	Jump to subroutine.
3016		<i>etc.</i>	Return point.
3129	XZ	3236	Address of parameter block.
3236	XZ	1000	L_1 (Starting address of unsorted list).
3237	XZ	2020	L_3 (Starting address for sorted destination list).
3238	XZ	0005	R (Number of records/intervals to sort).
3239	XZ	0003	N (Number of words per record/interval).
3240	XZ	0002	K (Position of the sorting key word within a record).
3241	XZ	000 <i>t</i>	Method selection code ($t = 1, 2$, or 3).
3242	000000WQ		Sorting mask.

The calling sequence above defines a list of five 3-word records [intervals], stored starting at memory location 1000. The list is to be sorted based on the contents of the second word ($K = 2$) of each record, using the hexadecimal mask 000000WQ. The resulting sorted list is to be stored starting at memory location 2020.

Original List Address Mapping	Data Value	Method I Location	Method I Value	Method II Value	Method III Value
1000 $\rightarrow$ 2020	7658	1010	614	3846	136
1001 $\rightarrow$ 2021	136	1004	428	614	428
1002 $\rightarrow$ 2022	3429	1001	136	4948	346
1003 $\rightarrow$ 2023	1876	1013	346	1876	170
1004 $\rightarrow$ 2024	428	1007	170	428	4470
1005 $\rightarrow$ 2025	4470			4470	7658
1006 $\rightarrow$ 2026	18208			7658	136
1007 $\rightarrow$ 2027	170			136	3429
1008 $\rightarrow$ 2028	7720			3429	5650
1009 $\rightarrow$ 2029	3846			5650	346
1010 $\rightarrow$ 2030	614			346	6312
1011 $\rightarrow$ 2031	4948			6312	18208
1012 $\rightarrow$ 2032	5650			18208	170
1013 $\rightarrow$ 2033	346				7720
1014 $\rightarrow$ 2034	6312				

19 Conversion to Binary

BINARY CONVERSION OF WHOLE NUMBERS 1 — L3-10.0

PURPOSE

L3-10.0 converts a positive 8-digit decimal number into its binary equivalent. Leading zeros must be explicitly included.

The program operates as a subroutine invoked by a calling sequence from the main program. Upon jumping to the subroutine, the return address must be stored, and the argument must reside in the accumulator. Upon returning to the main program, the binarized number is held in the accumulator.

STORAGE REQUIREMENTS

Memory used: 58 sectors, 58 words (starting at sector 00)

Temporary storage: none

INPUT

The input variable -- a positive 8-digit decimal number scaled at $q = 31$ -- must reside in the accumulator when the jump to the subroutine occurs. Leading zeros must be explicitly specified.

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Load the input argument @ 31.
α	R	$L_0 + 42$	Store the return address in the subroutine.
$+1$	U	L_0	Jump to the subroutine starting address.
$+2$		<i>etc.</i>	Return point in the main program.

The instruction at $\alpha - 1$ brings the argument scaled at $q = 31$ into the accumulator. (Any instruction that achieves this may be used.) The instruction at α stores the return address ($\alpha + 2$) into the subroutine. The instruction at $\alpha + 1$ effects a jump to L_0 , the starting address of the subroutine. Control returns to location $\alpha + 2$ of the main program.

EXAMPLE

Suppose the 8-digit decimal value to be converted is 00024576, stored in memory location 2500. Let the subroutine ``Binarization 1'' be loaded at location 0800, and the main program calling sequence occupies locations 1200 to 1203.

Memory Location	Instruction	Address	Meaning
1200	B	2500	Bring decimal number 00024576 @ 31 into the accumulator.
1201	R	0842	Set return address linkage inside the subroutine.
1202	U	0800	Jump to the subroutine entry point.
1203		<i>etc.</i>	Execution resumes here with the binary result held in the accumulator @ 30.

The instruction at 1200 loads the data word containing the decimal integer representation. The instruction at 1201 sets the return path to location 1203 inside the subroutine's exit tracking line (at 0800+42). Location 1202 triggers the jump to the routine. Upon return to location 1203, the accumulator contains the true binary value equivalent to 0x6000 (decimal 24576) correctly shifted to $q = 30$.

OUTPUT

Upon returning to the main program, the binarized number scaled at $q = 30$ stands in the accumulator.

OPERATION

1. Execution time:
Average of 530 milliseconds.
2. Program entry:
The tape contains the program in two versions:
 - a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
 - b) arbitrarily relocatable, decimal, in coding sheet format.
3. Required input/output units:
No input or output units are required.

4. **Overflow:**

Ignored upon entry and not reset upon exit.

20 Backup Utilities

MEMORY COPY 1 — L4-10.0

PURPOSE

L4-10.0 copies the contents of a designated memory region to another designated memory region. The copied data words are not altered in any way. The block of words can be moved arbitrarily anywhere within memory.

The program is invoked by a calling sequence that must supply: 1. the starting address of the data block, 2. the new destination starting address, and 3. the number of words to be copied. Upon returning to the main program, the data block has been copied.

STORAGE REQUIREMENTS

Memory: 56 sectors (56 words)

Temporary storage: none

INPUT

The input variables are specified in the following exact sequence:

1. M_1 , the starting address of the data block to be copied, in decimal track/sector notation.
2. M_2 , the starting address of the destination region where the words are to be copied, in decimal track/sector notation.
3. N , the number of words to be copied, in decimal track/sector notation.

These control parameters must reside in the three locations immediately following the jump instruction of the calling sequence.

The data block must occupy consecutive locations and may be copied in any direction; i.e., M_2 may be greater than or less than M_1 . Overlapping regions are handled safely.

CALLING SEQUENCE

The instruction at α stores the address of the parameter block ($\alpha+2$) into the subroutine tracking logic. The instruction at $\alpha+1$ effects a jump to L_0 , the starting address of the subroutine. Location $\alpha+2$ contains the starting address of the original data block; location $\alpha+3$ contains the starting address of the new target area; and location $\alpha+4$ contains the total count of words making up the block.

Memory Location	Instruction	Address	Meaning
α	R	L_0	Store the parameter block address in the subroutine.
$\alpha + 1$	U	L_0	Jump to the subroutine.
$\alpha + 2$	Z	M_1	Source starting address of the data block.
$\alpha + 3$	Z	M_2	Destination starting address for the data block.
$\alpha + 4$	Z	N	Number of words to be copied.
$\alpha + 5$		<i>etc.</i>	Return point in the main program.

OPERATION

1. **Execution time:**
Approximately 18 seconds per track.
2. **Program entry:**
The tape contains the program in two versions:
 - a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
 - b) arbitrarily relocatable, decimal, in coding sheet format.
3. **Required input/output units:**
No input or output units are required.
4. **Overflow:**
Ignored upon entry and not reset upon exit.

EXAMPLE

Suppose a memory block of 200 words (decimal), beginning at location 0700, is to be copied to a target area starting at location 4200, and that ``Memory Copy 1'' is loaded starting at location 0300. The calling sequence in the main program begins at location 0500:

TAPE DUPLICATOR 1 — L4-11.0

PURPOSE

L4-11.0 duplicates any tape encoded for the LGP-21. The original tape is read via the high-speed reader and punched out via the high-speed

Memory Location	Instruction	Address	Meaning
0500	R	0300	Set parameter block entry link inside the subroutine.
0501	U	0300	Jump to the subroutine.
0502	Z	0700	M_1 (Source starting address).
0503	Z	4200	M_2 (Destination starting address).
0504	Z	0308	N (200 words represented as 3 tracks, 8 sectors ($3 \times 64 = 192$) + 8).
0505		<i>etc.</i>	Execution resumes here with the data copied.

punch. The resulting tape is a faithful duplicate of the original tape, with the sole exception that all delete codes [rubouts] are omitted⁴⁵.

STORAGE REQUIREMENTS

Memory used: 1 track (64 words)

Temporary storage: none

INPUT

``Tape Duplicator 1'' processes any tape that has been encoded for the LGP-21. The tape must be read via the high-speed reader and punched via the high-speed punch.

CALLING SEQUENCE

Program execution is initiated by jumping to L_0+1 , where L_0 is the starting address of the program. A jump instruction to L_0+1 is explicitly provided at the end of the program tape itself.

OUTPUT

Upon jumping to the starting address, the program begins reading the tape to be duplicated and punching it out via the high-speed punch. The output tape is an exact copy of the read tape, except that delete/rub-out codes are omitted. Reading and punching continue until the entire tape has been duplicated.

⁴⁵This provides a handy way to take a messy tape with a lot of corrections and duplicate it as a clean copy.

OPERATION

1. Program entry:

The tape contains the program in two versions:

- a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
- b) arbitrarily relocatable, decimal, in coding sheet format.

2. Required input/output units:

The high-speed reader is required for input, and the high-speed punch is required for output. Both units are automatically selected by Tape Duplicator 1.

3. Program control switches [Break Point Switches]:

None.

4. Error stops:

None.

21 Binary Searching

TABLE SEARCH 1 (BINARY SEARCH) — L7-10.0

PURPOSE

L7-10.0 searches a table of values for the address of the entry that matches a given comparison word [search key]. The table must be stored in ascending order and contain at least two numbers. All data must be in fixed-point format. The program uses the binary search method.

This means the comparison word is first compared with the word in the middle of the table. If they are equal, the search terminates. If the comparison word is larger, it is compared with the word located midway between the middle and the end of the table. If the comparison word was smaller than the middle one, it is compared with the word located midway between the beginning and the middle of the table. The search continues in this manner until a match is found.

The subroutine is invoked via a calling sequence from the main program. Upon jumping to the subroutine, the comparison word must reside in the accumulator, and the calling sequence must supply the starting address of the table and the number of words it contains. Upon returning to the main program, the memory address where the match was found is held in the accumulator.

STORAGE REQUIREMENTS

Memory used: 3 tracks (192 words)

Temporary storage: sectors 01, 27, and 44 of track 63

INPUT

The input variable is a comparison word, C . This comparison word can be any arbitrary word in memory and must reside in the accumulator when the jump to the subroutine occurs. All data must be in fixed-point format. The table must consist of at least two words. The words must be stored in consecutive locations and in ascending numerical order.

The locations immediately following the jump instruction of the calling sequence must contain:

1. NNNN, the number of words in the table in decimal track/sector notation (i.e., modulo 64).
2. T, the starting address of the table in decimal track/sector notation.

CALLING SEQUENCE

The instruction at $\alpha-1$ brings C into the accumulator. (Any instruction that achieves this may be used.) The instruction at α stores the address

Memory Location	Instruction	Address	Meaning
$\alpha - 1$	B	$\langle \dots \rangle$	Bring C into the accumulator.
α	R	$L_0 + 31$	Store the address of NNNN into the subroutine.
$\alpha + 1$	U	L_0	Entry to the subroutine.
$\alpha + 2$	XZ	NNNN	Size of the table (modulo 64).
$\alpha + 3$	XZ	T	Starting address of the table.
$\alpha + 4$		<i>etc.</i>	Return point in the main program.

($\alpha+2$) into the subroutine. The instruction at $\alpha+1$ effects a jump to L_0 , the starting address of the subroutine. Location $\alpha+2$ contains NNNN modulo 64; for example, XZ 0132 represents 96 table words (1 track and 32 sectors). The instruction at $\alpha+3$ contains the table address T . Control returns from the subroutine at $\alpha+4$.

OUTPUT

Upon returning to the main program, the address of the word that matches the comparison word stands in the accumulator scaled at $q = 29$.

OPERATION

1. **Execution time:**
The operating time depends on the length of the table and the position of the searched word.
2. **Program entry:**
The tape contains the program in two versions:
 - a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
 - b) arbitrarily relocatable, decimal, in coding sheet format.
3. **Required input/output units:**
No input or output units are required.
4. **Overflow:**
Ignored upon entry and not reset upon exit.
5. **Program stops:**

Memory Location	Meaning	Remedy
$L_0 + 0130$	No word in the table matches C , or C lies outside the sequence bounds.	Do not continue. The input data must be corrected.
$L_0 + 0218$	Either C was modified or the contents of locations $L_0 + 247$ to $L_0 + 259$ were altered when the subroutine was modified to proceed with the same C and identical table values (see under “Remarks”).	Do not continue.

REMARKS

If C and the table are to be used repeatedly without any modifications, the following program modifications can be made after the first search to accelerate subsequent searches (where L_0 is the starting address of the subroutine):

1. Change the content of $L_0 + 0033$ from N 0019 to U 0054.
2. Change the content of $L_0 + 0056$ from E 0214 to U 0149.

The contents of locations $L_0 + 0007$ and $L_0 + 0247$ to $L_0 + 0259$ must be preserved for subsequent searches.

22 Programming Utilities

LOOP COUNTER 1 — L8-10.0

PURPOSE

L8-10.0 simulates an index register for the LGP-21. It does this by incrementing the operand addresses of marked instructions, executing a designated sequence of instructions a predetermined number of times, and restoring the modified operand addresses back to their original values. The designated addresses are incremented by 1 before each pass through the loop, and all instructions within the designated loop are executed during every iteration.

The routine is invoked via a subroutine call from the main program. The calling sequence must supply:

1. The starting address of the instruction sequence, and
2. the total number of loop iterations.

Upon returning to the main program, the specified number of passes will have been completed, and all addresses in the instructions that were incremented are safely restored to their initial values.

STORAGE REQUIREMENTS

Memory used: 1 track (64 words)

Temporary storage: none

INPUT

The block of instructions to be repeatedly executed must be located in the main program immediately *preceding* the calling sequence. All instructions are permitted.

The operand addresses of all *negative* instructions within the block are incremented by 1 before each loop iteration; that is, any instruction prepended with an operational code modifier of 800. For example, the modified instruction 800A2000 would be transformed to 800A2001 *before* the first execution pass. The addresses of normal positive instructions remain unaltered.

The calling sequence must supply the following parameters in this exact sequence upon entering the subroutine:

1. *S*, the *starting address* of the target instruction block, formatted as the operand inside an I instruction in decimal track/sector notation.
2. *X*, the *total number* of loop iterations, formatted as the operand inside an N instruction in decimal track/sector notation (i.e., modulo 64).

CALLING SEQUENCE

Memory Location	Instruction	Address	Meaning
α	R	L_0	Store the starting address of the instruction block into the subroutine.
$\alpha + 1$	U	L_0	Jump to the subroutine entry point.
$\alpha + 2$	I	S	Starting address of the loop instruction block.
$\alpha + 3$	N	XXXX	Number of loop iterations (X).
$\alpha + 4$		<i>etc.</i>	Return point in the main program.

The instruction at α stores the parameter pointer address ($\alpha+2$) into the tracking logic of the subroutine. The instruction at $\alpha+1$ effects an immediate jump to L_0 , the starting address of the subroutine. Location $\alpha + 2$ contains the address S , and location $\alpha + 3$ contains the loop execution limit value X . Control returns from the subroutine at location $\alpha + 4$.

OPERATION

1. **Execution time:**
Variable per loop. The execution overhead depends strictly on the structural size of the block, the number of modified instructions, and the total number of iterations.
2. **Program entry:**
The tape contains the program in two versions:
 - a) arbitrarily relocatable, hexadecimal, permissible for Program Input 1, and
 - b) arbitrarily relocatable, decimal, in coding sheet format.
3. **Overflow:**
Not checked or processed by this routine.

REMARKS

The operand address of *every* single negative instruction embedded within the designated loop block will be incremented before each loop.

If an early exit out of the loop block is triggered before the specified loop iteration count is exhausted, the contents of subroutine location $L_0 + 2$ must be patched as follows:

Old Contents: (...)
New Contents: U (L_0 + 3)

It is entirely permissible to jump out of an active loop structure mid-execution (for example, executing a subroutine branch), provided that the target subroutine contains absolutely no modifiable (negative) instructions^46.

EXAMPLE

Compute ten values for L according to the mathematical formula:

L = (2x + y) * z / w

Given Data Arrangements:

- Ten values for x stored in locations 3100--3109 scaled at q = 10.
• Ten values for y stored in locations 3200--3209 scaled at q = 20.
• Ten values for z stored in locations 3300--3309 scaled at q = 15.
• Ten values for w stored in locations 3400--3109 scaled at q = 10.

Target Destination Area:

- Ten calculated values of L to be written to locations 3500--3509 scaled at q = 23.

Available Scaling Constants:

- Value 2 at q = 15 located in location 3000.
• Value 1 at q = 5 located in location 3001.
• Value 1 at q = 3 located in location 3002.

Assume ``Loop Counter 1'' is loaded on track 40 (starting at location 4000).

^46This is because the loop utility would patch those instructions as the loop runs, but would have no way to track that it modified instructions outside the designated loop block, and would not fix the address fields it updated in the subroutine.

PROGRAM CODING SHEET

Input Key Word	Loc.	Opcode	S T	Address / Contents	Comments
;0002000' /0000000'					Block count to Track 02, Sector 00. Origin execution mapping to 0000.
	2000	B		3000	Bring constant 2 @ 15.
	2001	M	8	3100	Multiply by x @ 10 (Negative instruction, shifts index).
	2002	D		3001	Shift product to match scale of y ($q = 20$).
	2003	A	8	3200	Add y @ 20 (Negative instruction, shifts index).
	2004	D		3001	Shift sum to match scale of z ($q = 15$).
	2005	M	8	3300	Multiply by z @ 15 (Negative instruction, shifts index).
	2006	D	8	3400	Divide by w @ 10 (Negative instruction, shifts index).
	2007	M		3002	Shift calculated quotient to target scale ($q = 23$).
	2008	H	8	3500	Store result to L @ 23 (Negative instruction, shifts index).
	2009	R		4000	Initialize Loop Counter execution tracking.
	2010	U		4000	Jump to Loop Counter 1 subroutine.
	2011	I		2000	Pass first instruction address of the loop block (S).
	2012	N		0010	Pass iteration count (10 decimal iterations).
	2013	Z		0000	Halt machine execution upon loop completion.

COMPUTER-CONTROLLED PRINT LOOP

An output subroutine is frequently programmed as a computer-controlled print loop. Because it would normally be necessary to store and update the loop counter between individual print commands during a standard print cycle, printing could occur at most once per drum revolution. This architectural limitation restricts output velocity to approximately 20 characters per second.

While this programming approach poses no speed bottleneck when routing output to the standard Flexowriter typewriter, utilizing the high-speed paper tape punch requires a much faster print loop to avoid stalling the peripheral. The optimization method illustrated below permits punching at a rate of approximately 40 characters per second by packing exactly two print operations into a single drum revolution.

EXAMPLE

Assume the total number of characters to be printed is stored as a count register scaled at $q = 30$. The following program continuously prints a single character (for example, a Carriage Return) for the exact duration specified by the counter.

PROGRAM CODING SHEET

Loc.	Opcode	S T	Address / Contents	Comments
0000	C		0050	Store formally.
0001	S		Count	Subtract character count limit.
0002	U		0059	Zero-test branch for the remaining count.
0003	E		0049	First interleaved execution pass (43ww wwWQ).
0004	XP		0200	Output character via Print instruction.
0005	A		0055	Add index offset (GJ00 0002).
0006	T		0056	Transfer tracking to address 0056.
0007	U		0060	Exit loop.
0049	43WW WWQ			Operational control word.
0050	<i>Formal storage slot</i>			Reserved for internal assembly linkage.
0051	GJ00 0002			Index step constant.
0052	<i>Unused</i>			Unallocated sector.
0053	43ww WWQ			Alternate phase operational control word.
0054	<i>Unused</i>			Unallocated sector.
0055	GJ00 0002			Index step constant.
0056	E		0049	Second interleaved execution pass.
0057	XP		0200	Output character via Print instruction.
0058	A		0051	Add index offset (GJ00 0002).
0059	T		0003	Loop branch back to address 0003.
0060	U		Exit	Exit program execution.

23 Bibliography

References

- [1] J. von Neumann, ``First Draft of a Report on the EDVAC,`` Moore School of Electrical Engineering, University of Pennsylvania, Philadelphia, PA, Tech. Rep., Jun. 1945.
- [2] A. W. Burks, H. H. Goldstine, and J. von Neumann, ``Preliminary discussion of the logical design of an electronic computing instrument,`` Institute for Advanced Study, Princeton, NJ, Tech. Rep., Jun. 1946.
- [3] International Business Machines Corporation, *Principles of Operation, Electronic Data Processing Machines Type 701*, New York, NY, 1953.
- [4] Digital Computer Laboratory, *Electronic Digital Computer: Internal Organization, Programming, and Coding (ILLIAC I)*, University of Illinois, Urbana, IL, 1954.
- [5] Elliott Brothers (London) Ltd., *The Elliott 405 Electronic Data Processing System: Reference Manual*, London, UK, 1956.
- [6] Royal McBee Computer Corporation, *LGP-30 Programming Manual*, Port Chester, NY, 1957.
- [7] General Precision Electronic Computer Company, *LGP-21 Maintenance and Training Manual*, Burbank, CA, 1963
- [8] Eurocomp GmbH, *LGP-21 Unterprogramm-Handbuch*, Minden, Westphalia, 1963
- [9] General Precision Electronic Computer Company, *LGP-21 Computer System Reference Manual*, Burbank, CA, 1963
- [10] General Precision Electronic Computer Company, *RPC-4000 Programmers Reference Manual*, Burbank, CA, 1960.
- [11] E. Nigh, ``The Story of Mel,`` first posted to Usenet newsgroup net.followup, May 1983. [Online; accessed June 2026]. Available:
<https://users.cs.utah.edu/~elb/folklore/mel.html>