

Envelope Mode

Modulation channel modulator assignment

Model Name	MOD Channel 1 (Shape)	MOD Channel 2 (ShiftShape)	MOD Channel 3 (Param1)	A.S.
Virtual Analog	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	Log
VA Sync	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	Log
Tides	Wavefold T	Asymmetry M	Waveform H	Log
Warps	Wavefold T	Asymmetry M	Waveform H	Log
FM	Modulation Index T	Frequency Ratio H	Feedback 1OP/2OP M	Log
Grain	Formant Frequency T	Width and Shape M	Frequency Ratio H	Log
ZBraits	CF Freq T	Saw>Sqr>Tri M	PK>LP>BP>HP H	Log
Additive	Harmonic Index T	Bump Shape M	Number of Bumps H	Log
SWARM	Pitch Randomization H	Grain Duration/Overlap M	Grain Density T	Lin
Particle	Pitch Randomization H	Filter Type All/BandPass M	Particle Density T	Lin
Noise	Filter Resonance M	LP>BP>HP H	Clock Frequency T	Lin
NoiseDBP	Filter Resonance M	2nd BP Center frequency	Clock Frequency T	Lin
String	Inharmonicity H	Brightness/density T	Decay M	KeyT
Modal	Inharmonicity H	Brightness/density T	Decay M	KeyT
Bass Drum	Brightness T	Sharpness/Overdrive H	Decay M	Lin
Snare	Mode Balance T	Harmonic/Noisy H	Decay M	Lin
HiHat	HP Filter Cutoff T	Metallic/Noisy H	Decay M	Lin

LFO mode

Modulation channel modulator assignment

Model Name	MOD Channel 1 (Shape)	MOD Channel 2 (ShiftShape)	MOD Channel 3 (Param1)	A.M.
Virtual Analog	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	LFO2
VA Sync	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	LFO2
Tides	Wavefold T	Asymmetry M	Waveform H	LFO2
Warps	Wavefold T	Asymmetry M	Waveform H	LFO2
FM	Modulation Index T	Frequency Ratio H	Feedback 1OP/2OP M	LFO2
Grain	Formant Frequency T	Width and Shape M	Frequency Ratio H	LFO2
ZBraits	CF Freq T	Saw>Sqr>Tri M	PK>LP>BP>HP H	LFO2
Additive	Harmonic Index T	Bump Shape M	Number of Bumps H	LFO2
SWARM	Pitch Randomization H	Grain Duration/Overlap M	Grain Density T	LFO2
Particle	Pitch Randomization H	Filter Type All/BandPass M	Particle Density T	LFO2
Noise	Filter Resonance M	LP>BP>HP H	Clock Frequency T	LFO2
NoiseDBP	Filter Resonance M	2nd BP Center frequency	Clock Frequency T	LFO2
String	Inharmonicity H	Brightness/density T	Decay M	KeyT
Modal	Inharmonicity H	Brightness/density T	Decay M	KeyT
Bass Drum	Brightness T	Sharpness/Overdrive H	Decay M	LFO2
Snare	Mode Balance T	Harmonic/Noisy H	Decay M	LFO2
HiHat	HP Filter Cutoff T	Metallic/Noisy H	Decay M	LFO2

Spectral Models	KT+EG*EV (use EG INT)	KT+LFO*EV	KT*EV
Unpitched Models	LFO * EV	LFO * EV	LFO * EV

Modulation Key Envelope Mode control ranges

EG*EV	Param5	Param6	
EG*EV+LFO	Attack	Decay	
Env*EV	[+] Rate	[+] Rate	AD Envelope
Envelope	[+] Rate	[-] Rate	AR Envelope
Env+LFO	[-] Rate	[+] Rate	ADSR 40% Sustain
Key Track	[-] Rate	[-] Rate	ADSR 70% Sustain
KT+LFO			
KT*EV			

Device	I/O type	Max	Min	Key
Logue	Key Tracking	+1	0	KT
Logue	Shape LFO	+1	0	LFO
Logue	EG Velocity	+1	0	EV
Logue	EG Envelope	+1	0	EG
Logue	EG INT	+1	-1	EGI
Built-in Mod	LFO2	+1	0	LFO2
Built-in Mod	Envelope	+1	0	Env
Built-in Mod	Intensity 1-3	+1	-1	
Model	Bias 1-3	+1	-1	
Model	Input 1-3	+1	0	

Modulations are simple addition and multiplication

Modulation Key LFO Mode control ranges

KT+EV*LFO	Param5	Param6	
LFO2[x]LFO	Attack	Decay	
LFO2*EV	0	[+] Rate	LFO2+LFO
Key Track	0	[-] Rate	LFO2*LFO
LFO2	[+] Rate	0	LFO2trem+LFO
LFO2[x]LFO+	[-] Rate	0	LFO2trem*LFO
EG*EV*EGI			
KT+EG*EV			
KT*EV			
KT+LFO*EV			
LFO*EV			

KT Mode control ranges (ALL)

Param5	Param6	
Brightness	Decay	
	[+] Rate	+EG Velocity Decay
	[-] Rate	- EG Velocity Decay
[+] Rate		- EG Velocity Brightness
[-] Rate		+EG Velocity Brightness

Quick Mode

Param5	Param6	
Attack	Decay	
0	0	See Channel Assignments
0	0	LFO*EV