

Envelope Mode

Modulation channel modulator assignment

Model Name	MOD Channel 1 (Shape)	MOD Channel 2 (ShiftShape)	MOD Channel 3 (Param1)	A.S.
Virtual Analog	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	Log
VA Sync	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	Log
Tides	Wavefold T	Asymmetry M	Waveform H	Log
Warps	Wavefold T	Asymmetry M	Waveform H	Log
FM	Modulation Index T	Frequency Ratio H	Feedback 1OP/2OP M	Log
Grain	Formant Frequency T	Width and Shape M	Frequency Ratio H	Log
ZBraid	CF Freq T	Saw>Sqr>Tri M	PK>LP>BP>HP H	Log
Additive	Harmonic Index T	Bump Shape M	Number of Bumps H	Log
SWARM	Pitch Randomization H	Grain Duration/Overlap M	Grain Density T	Lin
Particle	Pitch Randomization H	Filter Type All/BandPass M	Particle Density T	Lin
Noise	Filter Resonance M	LP>BP>HP H	Clock Frequency T	Lin
NoiseDBP	Filter Resonance M	2nd BP Center frequency	Clock Frequency T	Lin
String	Inharmonicity H	Brightness/density T	Decay M	KeyT
Modal	Inharmonicity H	Brightness/density T	Decay M	KeyT
Bass Drum	Brightness T	Sharpness/Overdrive H	Decay M	Lin
Snare	Mode Balance T	Harmonic/Noisy H	Decay M	Lin
HiHat	HP Filter Cutoff T	Metallic/Noisy H	Decay M	Lin

LFO mode

Modulation channel modulator assignment

Model Name	MOD Channel 1 (Shape)	MOD Channel 2 (ShiftShape)	MOD Channel 3 (Param1)	A.M.
Virtual Analog	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	LFO2
VA Sync	Tri>Saw>PW M	Detune -Pitch/+Pitch H	Pulse Width T	LFO2
Tides	Wavefold T	Asymmetry M	Waveform H	LFO2
Warps	Wavefold T	Asymmetry M	Waveform H	LFO2
FM	Modulation Index T	Frequency Ratio H	Feedback 1OP/2OP M	LFO2
Grain	Formant Frequency T	Width and Shape M	Frequency Ratio H	LFO2
ZBraid	CF Freq T	Saw>Sqr>Tri M	PK>LP>BP>HP H	LFO2
Additive	Harmonic Index T	Bump Shape M	Number of Bumps H	LFO2
SWARM	Pitch Randomization H	Grain Duration/Overlap M	Grain Density T	LFO2
Particle	Pitch Randomization H	Filter Type All/BandPass M	Particle Density T	LFO2
Noise	Filter Resonance M	LP>BP>HP H	Clock Frequency T	LFO2
NoiseDBP	Filter Resonance M	2nd BP Center frequency	Clock Frequency T	LFO2
String	Inharmonicity H	Brightness/density T	Decay M	KeyT
Modal	Inharmonicity H	Brightness/density T	Decay M	KeyT
Bass Drum	Brightness T	Sharpness/Overdrive H	Decay M	LFO2
Snare	Mode Balance T	Harmonic/Noisy H	Decay M	LFO2
HiHat	HP Filter Cutoff T	Metallic/Noisy H	Decay M	LFO2

Spectral Models	KT+EG*EV (use EG INT)	KT+LFO*EV	KT*EV
Unpitched Models	LFO * EV	LFO * EV	LFO * EV

Modulation Key Envelope Mode control ranges

Env*EV
EG*EV
EG*EV+LFO
Envelope
Env+LFO
KT+LFO
Key Track
KT*EV

Param5	Param6
Attack	Decay
[+] Rate	[+] Rate
[+] Rate	[-] Rate
[-] Rate	[+] Rate
[-] Rate	[-] Rate

AD Envelope
AR Envelope
ADSR 40% Sustain
ADSR 70% Sustain

Device	I/O type	Max	Min	Key
Logue	Shape LFO	+1	0	LFO
Logue	Key Tracking	+1	0	KT
Logue	EG Velocity	+1	0	EV
Logue	EG Envelope	+1	0	EG
Logue	EG INT	+1	-1	EG_INT
Model	Intensity 1-3	+1	-1	
Model	Bias 1-3	+1	-1	
Model	Input 1-3	+1	-1	
Model	LFO2	+1	0	LFO2
Model	Envelope	+1	0	Env

Modulations are simple addition and multiplication

Modulation Key LFO Mode control ranges

LFO2*EV
LFO2
LFO2[x]LFO
KT+EV*LFO
Key Track
KT*EV
LFO*EV
KT+EG*EV
KT+LFO*EV

Param5	Param6
Attack	Decay
0	[+] Rate
0	[-] Rate
[+] Rate	0
[-] Rate	0

LFO2+LFO
LFO2*LFO
LFO2trem+LFO
LFO2trem*LFO

KT Mode control ranges (ALL)

Param5	Param6
Brightness	Decay
	[+] Rate
	[-] Rate
[+] Rate	
[-] Rate	

+EG Velocity Decay
- EG Velocity Decay
- EG Velocity Brightness
+EG Velocity Brightness

3 x LFO / 3 x KT Mode(s)

Param5	Param6
Attack	Decay
0	0
0	0

See Channel Assignments
LFO*EV