

Bill of Material		
Number	Reference	Designation
<b>Chrono</b>		
1		RaspberryPi 3B+
1	MB-MC32GA	<a href="#">SD Card 32GB</a>
1		Arduino nano
1		<a href="#">Waveshare display 3.5 LCD @</a>
1		<a href="#">BLUEWAY High power wifi dongle</a>
1		PCB custom
1	1883715	<a href="#">Pcb Female connector 2*20</a>
1	1580891	<a href="#">PCB Male connector 2*40</a>
6		Resistor 10K 1/4W
1		Resistor 5K6 1/4W
2		Resistor 1K 1/4W
2		Resistor 0K33 1/4W
2		BC547B
2		<a href="#">Buzzer 5V</a>
1		Mpx 6 pins female
1		XT 60 female
2	2109227	<a href="#">Jack 6.35</a>
1	738619	<a href="#">Jack 3.5 female</a>
1	491751	<a href="#">cable jack male</a>
1	701281	<a href="#">push button</a>
1		Switch Bec 3A - 5/6V - Hobbywing
1		heat-shrinkable sleeve
1		set of screws
1	3Dprinter	case side
1	3Dprinter	case top
1	3Dprinter	case
1	3Dprinter	display support 1
1	3Dprinter	display support 2
1	3Dprinter	light cover
1	3Dprinter	adaptor for photo stand
1	3Dprinter	multiplex plug holder
<b>Wire for button</b>		
4	1569183	<a href="#">Jack 6.35 male</a>
2		2 Wires 50m
<b>Wired button</b>		
2	2109227	<a href="#">Jack 6.35</a>
2	701281	<a href="#">push button</a>
1		set of screws
2	3Dprinter	btn base case - part1
2	3Dprinter	btn base case - part2

Battery case		
1		Cell 3S 3000mA 18650
1		XT 60 Male
1		set of screws
1	3Dprinter	BatteryCase part1
1	3Dprinter	BatteryCase part2
1	3Dprinter	BatteryCase part3 Flex
1	3Dprinter	Hex_cell
1		heat-shrinkable sleeve
Buzzer Case		
2	1566911	<a href="#">buzzer 110db 12V</a>
2		BC547B
1		P16NF06
2		Resistor 10K 1/4w
2		Resistor 1K 1/4w
1		Resistor 4K 1/4w
1		Cable 3 wires *1m
1		heat-shrinkable sleeve
1		set of screws
1	3Dprinter	Side buzzer case
1	3Dprinter	bottom buzzer case

Display 3.5" Pinout		
PIN NO.	SYMBOL	Designation
1, 17	3.3V	Power positive (3.3V power input)
2, 4	5V	Power positive (5V power input)
3, 5, 7, 8, 10, 12, 13, 15, 16	NC	NC
6, 9, 14, 20, 25	GND	Ground
11	TP_IRQ	Touch Panel interrupt, low level while the Touch Panel detects touching
18	LCD_RS	Instruction/Data Register selection
19	LCD_SI / TP_SI	SPI data input of LCD/Touch Panel
21	TP_SO	SPI data output of Touch Panel
22	RST	Reset
23	LCD_SCK / TP_SCK	SPI clock of LCD/Touch Panel
24	LCD_CS	LCD chip selection, low active
26	TP_CS	Touch Panel chip selection, low active
Raspberry Pi External		
29	GPIO05	Base A button
31	GPIO06	Base B button
32	GPIO12	Next Button
33	GPIO13	free
35	GPIO19	buzzer output
37	GPIO26	free
38	GPIO20	free
40	GPIO21	Buzzer next output
	+5V	
	GND	
Raspberry pi vers chrono		
8	GPIO14	TX
10	GPIO15	RX
	GND	
Chrono Arduino vers ext		
	+5V	+VIN 6-20VDC
	GND	GND
32	D2/INT0	Base A button
1	D3/INT1	Base B button
13	A0/PCO	Buzzer output
24	ADC1	Cell pack voltage 3S Max
31	TXD	TX
30	RXD	RX

## Raspberry Pi B+ J8 Header

Pin#	NAME	NAME	Pin#
01	3.3v DC Power	DC Power 5v	02
03	GPIO02 (SDA1 , I2C)	DC Power 5v	04
05	GPIO03 (SCL1 , I2C)	Ground	06
07	GPIO04 (GPIO_GCLK)	(TXD0) GPIO14	08
09	Ground	(RXD0) GPIO15	10
11	GPIO17 (GPIO_GEN0)	(GPIO_GEN1) GPIO18	12
13	GPIO27 (GPIO_GEN2)	Ground	14
15	GPIO22 (GPIO_GEN3)	(GPIO_GEN4) GPIO23	16
17	3.3v DC Power	(GPIO_GEN5) GPIO24	18
19	GPIO10 (SPI_MOSI)	Ground	20
21	GPIO09 (SPI_MISO)	(GPIO_GEN6) GPIO25	22
23	GPIO11 (SPI_CLK)	(SPI_CE0_N) GPIO08	24
25	Ground	(SPI_CE1_N) GPIO07	26
27	ID_SD (I2C ID EEPROM)	(I2C ID EEPROM) ID_SC	28
29	GPIO05	Ground	30
31	GPIO06	GPIO12	32
33	GPIO13	Ground	34
35	GPIO19	GPIO16	36
37	GPIO26	GPIO20	38
39	Ground	GPIO21	40

Rev. 1.1  
16/07/2014

<http://www.element14.com>

