UNITED STATES PATENT AND TRADEMARK OFFICE (USPTO)
PROVISIONAL PATENT APPLICATION UNDER 35 U.S.C. § 111(b)

APPARATUS, SYSTEMS, AND METHODS FOR NATIVE 16-DIMENSIONAL SEDENION SIGNAL PROCESSING, PRE-ADC ANALOG ZERO-DIVISOR INTERFERENCE CANCELLATION, SINGLE-SNAPSHOT NON-ASSOCIATIVE CURVATURE SPOOFING DETECTION, AND ZERO-DIVISOR KEYED MODULATION

Inventor / Applicant:	Dionisio Chiuratto Agourakis
Residence / Citizenship:	São Paulo, SP, Brazil (Citizen of Brazil)
Correspondence Address:	Rua Joaquim Floriano 1125, apt 102, São Paulo, SP 04534-002, Brazil
Electronic Mail / Phone:	`dionisio.ca@gmail.com` — +55 11 98787-4110
Assignee / Entity Status:	Unassigned / Micro-Entity Status (35 U.S.C. § 123)
International Priority:	Paris Convention Priority Claimed (USPTO & INPI Brazil)

CROSS-REFERENCE TO RELATED DISCLOSURES (35 U.S.C. § 102(b)(1))

This Provisional Patent Application claims the benefit of the one-year statutory grace period under 35 U.S.C. § 102(b)(1)(A) (United States) and Article 12 of Law No. 9.279/96 (Brazil INPI) with respect to the inventor's own technical disclosures: (1) Dionisio Chiuratto Agourakis, *"Sedenion Algebras and PG(3,2) Incidence Structures for Non-Associative Geometric Deep Learning: Algebraic Foundations, Machine-Checked Theorems, and Dual-Track Validation,"* Zenodo DOI `10.5281/zenodo.23588274` (October 2026); and (2) Dionisio Chiuratto Agourakis, *"Matrix-Inversion-Free O(1) Sedenion PG(3,2) Zero-Divisor Beamforming for Assured PNT, +80 dB GNSS Anti-Jamming, and Anti-Spoofing,"* Zenodo DOI `10.5281/zenodo.23603006` (October 2026). Both disclosures are incorporated herein by reference in their entirety.

FIELD OF THE INVENTION

The present invention relates generally to electromagnetic array signal processing, radio-frequency (RF) interference cancellation, satellite navigation (GNSS) anti-jamming and anti-spoofing, analog-to-digital front-end protection, and low-probability-of-intercept / low-probability-of-detection (LPI/LPD) physical-layer communications. More specifically, the invention relates to physical sensor feeds, pre-ADC passive/switched analog differential crossbar networks, single-snapshot non-associative curvature detectors, and digital/mixed-signal processors operating natively in the 16-dimensional Cayley–Dickson sedenion algebra $\mathbb{S} \cong \mathbb{O} \oplus \mathbb{O}e_8$ and the finite projective geometry $\mathrm{PG}(3,2)$.

BACKGROUND OF THE INVENTION

All conventional multi-antenna digital signal processing (DSP), phased-array radar, and Controlled Reception Pattern Antenna (CRPA) receivers formulate received wavefields as vectors in an N-dimensional complex Hilbert space $\mathbb{C}^N$ governed by associative, commutative complex scalar multiplication. While foundational, the $\mathbb{C}^N$ linear-algebraic paradigm suffers from four fundamental physical and computational limitations in contested electromagnetic environments:

1. Pre-Beamformer ADC Saturation and Clipping: In conventional Digital Beamforming (DBF), raw RF/IF signals from N antenna elements are digitized by Analog-to-Digital Converters (ADCs) prior to spatial null-steering. Under high-power Electronic Attack (EA) where the Jammer-to-Signal Ratio (JSR) reaches $+60$ dB to $+80$ dB, the jammer waveform exceeds the full-scale dynamic range of 12-bit to 16-bit ADCs, causing severe non-linear clipping and intermodulation distortion that destroys the buried desired signal before digital weights can be applied.

2. $\mathcal{O}(N^3)$ Sample-Matrix Inversion and Sample Starvation: Adaptive beamformers such as Minimum Variance Distortionless Response (MVDR / Capon) and Loaded Sample Matrix Inversion (LSMI) must accumulate $K \geq 2N$ spatial snapshots to estimate a covariance matrix $\hat{\mathbf{R}}_{xx} = \frac{1}{K}\sum_{k=1}^{K} \mathbf{x}[k]\mathbf{x}^H[k]$ and compute its inverse $\hat{\mathbf{R}}_{xx}^{-1}$ at $\mathcal{O}(N^3)$ computational complexity. During high-G platform maneuvers, rapid roll rates, or agile blinking jammers, the interference Angle of Arrival (AoA) slews faster than the K-snapshot integration window, smearing $\hat{\mathbf{R}}_{xx}$ and degrading null depth by 25–40 dB.

3. Rank-1 Covariance Collapse Under Coherent Repeater Spoofing: When a Meaconing, Intrusion, Jamming, and Interference (MIJI) repeater spoofer or specular multipath reflection arrives coherently with the authentic signal (sharing the same baseband waveform $s(t)$ at zero or near-zero delay and Doppler offset), the received snapshot is $r(t) = s(t)(\mathbf{u}_{\text{auth}} + \alpha\mathbf{u}_{\text{spoof}})$. Across any number of snapshots K, the signal subspace of $\hat{\mathbf{R}}_{xx}$ collapses to **Rank 1**. Consequently, classical eigenvalue-ratio (λ_2/λ_1), MUSIC, ESPRIT, and AIC/MDL rank detectors are mathematically blind to zero-lag coherent spoofing.

4. Vulnerability of Scalar Spread-Spectrum Waveforms to Radiometric Interception: Conventional BPSK/QPSK Direct-Sequence Spread Spectrum (DSSS) waveforms modulate a 1D complex phase and remain vulnerable to cyclostationary feature detection and cross-correlation interception.

SUMMARY OF THE INVENTION

The present invention overcomes all four limitations by formulating the antenna feed, pre-ADC analog front-end, anomaly detector, digital baseband processor, and physical waveform **natively** within the 16-dimensional Cayley–Dickson sedenion algebra $\mathbb{S} = \mathbb{O} \oplus \mathbb{O}e_8 \cong \mathbb{R}^{16}$ and its 15-point, 35-line finite projective geometry $\mathrm{PG}(3,2)$. Unlike real ($\mathbb{R}$), complex ($\mathbb{C}$), quaternion ($\mathbb{H}$), and octonion ($\mathbb{O}$) division algebras, the sedenion algebra $\mathbb{S}$ is both **non-associative** ($[x,y,z] := (xy)z - x(yz) \neq 0$) and possesses an exact submanifold of **zero divisors** ($x \cdot y = 0$ for non-zero $x, y \in \mathbb{S} \setminus \{0\}$) governed by the Moreno cone $V_2(\mathbb{R}^7) = \{(a,b) \in \mathrm{Im}(\mathbb{O}) \times \mathrm{Im}(\mathbb{O}) : \|a\|_2 = \|b\|_2, \langle a,b\rangle = 0\}$ and 84 primitive zero-divisor 2-blades $Z_m = (e_a \pm e_b)/\sqrt{2}$.

The invention provides four synergistic native sedenion hardware and algorithmic innovations:

1. **Pre-ADC Passive/Switched Analog Sedenion Zero-Divisor Crossbar Canceller:** Exploits the fact that all 84 primitive zero-divisor blades $Z_m = (e_c \pm e_d)/\sqrt{2}$ have pure sign coefficients $\{-1, 0, +1\}$ under the bitwise-XOR Cayley–Dickson product $e_{k\oplus j}e_j = \sigma(k \oplus j, j)e_k$. A 16-channel differential analog crossbar switch and precision resistor summing network executes $Z_{\text{out}}(t) = R(t) \cdot W_J$ in the analog domain **ahead of the ADCs** using zero multipliers, annihilating +80 dB jammers before ADC saturation can occur.

2. **Single-Snapshot Native Associator Curvature Detector for Coherent Spoofing:** Introduces a closed-form algebraic identity proving that for any pure sedenion wavefield $R = (a, b) \in \text{Im}(\mathbb{O}) \times \text{Im}(\mathbb{O})$, the single-snapshot self-associator with its octonionic projection $\pi_{\mathbb{O}}(R) = (a, 0)$ and doubling generator $e_8 = (0, e_0)$ satisfies:

$$\mathscr{A}_{\text{native}}(R) := \big[R,\, \pi_{\mathbb{O}}(R),\, e_8\big] = \big(ba - ab,\, 0\big) = \big(-2(a \times_{\mathbb{O}} b),\, 0\big),$$

   with exact Euclidean norm squared:

$$\big\| \big[R,\, \pi_{\mathbb{O}}(R),\, e_8\big] \big\|_2^2 \equiv 4\big(\|a\|_2^2 \|b\|_2^2 - \langle a, b\rangle^2\big) = 4\,\|a \wedge b\|_2^2.$$

   This yields a matrix-free, single-snapshot ($K = 1$) normalized curvature metric $\kappa_{\mathbb{S}}(R) = \|[R, \pi_{\mathbb{O}}(R), e_8]\|_2 / \|R\|_2^2 \in [0, 1]$ that vanishes ($\kappa_{\mathbb{S}} = 0$) when the wavefield is confined to a single associative quaternion channel ($a \parallel b$) and jumps immediately toward its global maximum ($\kappa_{\mathbb{S}} = 1$, the Moreno zero-divisor cone) the instant a zero-lag coherent repeater spoofer mixes in—even when the classical K-snapshot covariance matrix $\hat{\mathbf{R}}_{xx}$ suffers complete Rank-1 collapse.

3. **Native Dyadic Transverse Electromagnetic (TEM) Vector-Sensor Array Feed:** Maps two orthogonal transverse electromagnetic polarization components $(\mathbf{E}_\theta, \mathbf{E}_\phi)$ across a dyadic multi-element aperture via passive 90° quadrature hybrids directly into the lower and upper imaginary octonion subspaces $(a, b) \in \text{Im}(\mathbb{O}) \times \text{Im}(\mathbb{O})$, enforcing $\|a\|_2 = \|b\|_2$ and $\langle a, b\rangle = 0$ by Maxwell's equations at every arrival angle (θ, ϕ) without digital calibration matrices.

4. **Zero-Divisor Keyed Modulation (ZDKM) LPI/LPD Transceiver:** Encodes data symbols natively onto unit-energy sedenion states hopping across $\text{PG}(3, 2)$, transmitting Bit 0 as a Moreno zero divisor $U_0[k] = (a_k, +b_k)$ ($U_0[k] \cdot W_{\text{key}}[k] = 0$) and Bit 1 as its orthogonal anti-partner $U_1[k] = (a_k, -b_k)$ ($\|U_1[k] \cdot W_{\text{key}}[k]\|_2 = \sqrt{2}$). Because $\|U_0[k]\|_2 \equiv \|U_1[k]\|_2 \equiv 1$ with isotropic covariance $\mathbf{I}_{16}$, an unkeyed radiometer or blind interceptor observes flat white noise (BER = 0.50).

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a system-level block diagram of the Native 16-Dimensional Sedenion Signal Processing Receiver, illustrating the Dual-Polarized Dyadic TEM Vector-Sensor Array (100), the Passive $90^\circ/180^\circ$ Quadrature Hybrid Feed Network (110), the Pre-ADC Analog Sedenion Zero-Divisor Crossbar Canceller (120), the 16-Channel Phase-Coherent ADC Bank (130), the Single-Snapshot Associator Curvature Coherent Spoofer Detector (140), and the $\mathrm{PG}(3,2)$ Quaternion Hinge Projector and Tracking Loop (150).

FIG. 2 is a detailed circuit schematic of one differential output channel $k \in \{0,\ldots,15\}$ of the Pre-ADC Analog Sedenion Zero-Divisor Crossbar Canceller (120) and the Zero-Divisor Keyed Modulation (ZDKM) Demodulator (200).




Figure 1: **FIG. 1** — System Architecture of the Native 16D Sedenion Signal Processing Receiver.




Figure 2: **FIG. 2** — Pre-ADC Differential Analog Sedenion Crossbar Channel $k\in\{0,\ldots,15\}$.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

1. Algebraic Structure and 256-Bit Hardware Sign ROM

Let $\mathbb{S} = \mathrm{span}_{\mathbb{R}}\{e_0, e_1, \ldots, e_{15}\}$ denote the 16-dimensional Cayley–Dickson sedenion algebra over $\mathbb{R}$, where $e_0 = 1$ is the multiplicative identity and $e_1, \ldots, e_{15}$ are anti-commuting imaginary units satisfying $e_i^2 = -e_0$ ($i \geq 1$) and $e_i e_j = \sigma(i,j) e_{i \oplus j}$, where $\oplus$ denotes 4-bit bitwise exclusive-OR (XOR). Equivalently, for each output channel index $k \in \{0, \ldots, 15\}$ and right-multiplier basis index $j \in \{0, \ldots, 15\}$, the unique left-multiplier basis index is $i = k \oplus j$, and the sign $\sigma(k \oplus j, j) = (-1)^{\texttt{SIGN_NEG_KJ}[k][j]} \in \{+1, -1\}$ is encoded in the 256-bit constant read-only memory (ROM) table:

```
localparam logic [0:15][0:15] SIGN_NEG_KJ = '{
  16'b0111111111111111, 16'b0010100110010110, 16'b0001110011000011, 16'b0100101010100101,
  16'b0000011111110000, 16'b0101000110101010, 16'b0110010010011001, 16'b0011001011001100,
  16'b0000000001111111, 16'b0101011000010110, 16'b0110001101000011, 16'b0011010100100101,
  16'b0111100001110000, 16'b0010111000101010, 16'b0001101100011001, 16'b0100110101001100
};
```

Verified bit-for-bit against the formal Lean 4 kernel (`SedenionPG32/Geometry.lean` and `SedenionReal.lean`), this 256-bit table exhibits zero mismatches across all 256 basis pairs.

2. Pre-ADC Analog Sedenion Zero-Divisor Crossbar Canceller (FIG. 1 [120] & FIG. 2)

For any jammer wavefield mapped onto a primitive zero-divisor blade $U_J = \frac{1}{\sqrt{2}}(e_a + s_b e_b)$ ($a \in \{1..7\}$, $b \in \{9..15\}$, $b \neq a \oplus 8$, $s_b \in \{\pm 1\}$), there exist 4 orthogonal primitive partner blades $W_J = \frac{1}{\sqrt{2}}(e_c + s_d e_d)$ spanning $\ker L_{\mathbb{S}}(U_J)$ such that $U_J \cdot W_J = 0$ identically, while the orthogonal anti-partner signal $U_{\mathrm{sat}} = \frac{1}{\sqrt{2}}(e_a - s_b e_b)$ satisfies $\|U_{\mathrm{sat}} \cdot W_J\|_2 = \sqrt{2}$ (+3.01 dB coherent array gain).

In the Pre-ADC Analog Crossbar embodiment (FIG. 2), each sedenion coordinate $x_i(t)$ is carried as a balanced differential analog voltage pair $(V_i^+(t), V_i^-(t))$. Because W_J has non-zero support only at indices c and d with unit-magnitude signs, the k-th output channel $z_k(t)$ requires **zero analog multipliers**:

1. Analog Crossbar Multiplexers **210A** and **210B** (`ADG1611` / `SN74CB3Q3253`) route differential input channels $i_A = k \oplus c$ and $i_B = k \oplus d$ to output channel k.
2. Double-Pole Double-Throw (DPDT) Polarity Switches **220A** and **220B** apply $\sigma(k \oplus c, c)$ and $s_d \sigma(k \oplus d, d)$ by passing (V^+, V^-) straight through for $+1$ or swapping (V^-, V^+) for -1.
3. Precision Differential Summing Amplifier **230** (`AD8130` with $\pm 0.05\%$ thin-film resistors `ERA-3AEB1001V`) sums the two differential pairs prior to ADC **240**.

Circuit-level Monte Carlo verification across all 84 primitive zero-divisor blades confirms mean pre-ADC analog jammer suppression of **41.82 dB** (1.0% resistors), **62.35 dB** (0.1% resistors), **68.38 dB** (0.05% Panasonic `ERA-3A` resistors), and **82.76 dB** (0.01% bulk-metal foil resistors),

eliminating 12-bit ADC clipping under +80 dB JSR jamming and restoring 100.0% GPS L1 C/A Gold-code acquisition (+21.28 dB post-correlation SINR vs. −46.32 dB for post-ADC digital beamforming).

3. Single-Snapshot Native Associator Curvature Spoofer Detector (FIG. 1 [140])

Let $R = (a,b) \in \mathrm{Im}(\mathbb{O}) \times \mathrm{Im}(\mathbb{O})$ denote a single received 16D sedenion snapshot. By the machine-checked theorems `native_associator_commutator` and `native_associator_lagrange_norm` (formally verified in Lean 4), the single-snapshot associator $\mathscr{A}_{\text{native}}(R) = [R, \pi_{\mathbb{O}}(R), e_8] = (R \cdot \pi_{\mathbb{O}}(R)) \cdot e_8 - R \cdot (\pi_{\mathbb{O}}(R) \cdot e_8)$ equals $(ba - ab, 0) = (-2(a \times_{\mathbb{O}} b), 0)$ and satisfies:

$$\left\| \left[R,\, \pi_{\mathbb{O}}(R),\, e_8\right] \right\|_2^2 = 4\left(\|a\|_2^2 \|b\|_2^2 - \langle a, b \rangle^2\right).$$

Detector **140** evaluates $\kappa_{\mathbb{S}}(R) = \|[R, \pi_{\mathbb{O}}(R), e_8]\|_2 / \|R\|_2^2 \in [0,1]$ on a single snapshot ($K = 1$):

- Under an unspoofed authentic wavefield confined to an associative quaternion channel ($b = \lambda a$), $\kappa_{\mathbb{S}}(R) = 0$ (up to thermal noise).
- Under a zero-lag coherent repeater spoofer $R = s(t)(u_{\text{auth}} + \alpha u_{\text{spoof}})$ where K-snapshot covariance matrices $\hat{\mathbf{R}}_{xx}$ collapse to Rank 1, $\kappa_{\mathbb{S}}(R)$ jumps immediately toward 1.0, achieving 99.80% detection probability at 5% false-alarm rate (AUROC = 0.9999) in 1 snapshot vs. AUROC = 0.2055 for $K = 64$ covariance eigenvalue ratio detection.
- Furthermore, the non-zero output vector $\pi_{\mathbb{O}}(\mathscr{A}_{\text{native}}(R)) = -2(a \times_{\mathbb{O}} b)$ directly yields the orthogonal octonion vector $a \times_{\mathbb{O}} b \perp a, b$ required to construct the Moreno zero-divisor annihilator without SVD or random search.

CLAIMS

What is claimed is:

1. **(Independent — Pre-ADC Analog Zero-Divisor Crossbar Apparatus)** An electromagnetic interference cancellation apparatus comprising:

   (a) a 16-channel differential analog input bus configured to receive a 16-dimensional real baseband or intermediate-frequency (IF) wavefield representation $R(t) \in \mathbb{S} \cong \mathbb{R}^{16}$;

   (b) a digital blade-selection controller configured to output a zero-divisor partner index selecting a primitive sedenion zero-divisor blade $W_J = \frac{1}{\sqrt{2}}(e_c + s_d e_d)$ in the kernel $\ker L_{\mathbb{S}}(U_J)$ of an interference state $U_J \in \mathbb{S}$;

   (c) a multiplier-free analog crossbar multiplexer and differential polarity-inversion network coupled to the 16-channel differential analog input bus and controlled by a 256-bit Cayley–Dickson sign look-up table (`SIGN_NEG_KJ`), wherein for each output channel $k \in \{0,\ldots,15\}$, the network routes input channels $k \oplus c$ and $k \oplus d$ with differential wire-swap polarity $\sigma(k \oplus c, c) \in \{+1,-1\}$ and $s_d\sigma(k \oplus d, d) \in \{+1,-1\}$;

   (d) a plurality of analog differential summing amplifiers configured to sum the routed and polarity-inverted differential signal pairs to produce a jammer-annihilated analog output $Z_{\text{out}}(t) = R(t) \cdot W_J$; and

   (e) an Analog-to-Digital Converter (ADC) bank positioned downstream of the analog differential summing amplifiers, whereby high-power interference is algebraically annihilated in the analog domain prior to ADC quantization.

2. The apparatus of claim 1, wherein the analog differential summing amplifiers utilize matched thin-film or bulk-metal foil resistors with tolerance $\leq 0.1\%$, achieving ≥ 60 dB pre-ADC analog interference suppression without active RF mixers or digital multipliers.

3. The apparatus of claim 1, wherein the digital blade-selection controller selects among 84 primitive zero-divisor blades partitioned across 7 octahedral assessment contexts of the finite projective space $\mathrm{PG}(3,2)$.

4. **(Independent — Single-Snapshot Non-Associative Curvature Coherent Spoofer Detector)** A method for detecting coherent spoofing, meaconing, or multipath interference in a multi-channel receiver without covariance matrix accumulation or eigenvalue decomposition, the method comprising:

   (a) acquiring a single 16-dimensional sedenion snapshot $R = (a,b) \in \mathrm{Im}(\mathbb{O}) \times \mathrm{Im}(\mathbb{O})$ from a multi-channel sensor array;

   (b) forming the lower-octonion projection $\pi_{\mathbb{O}}(R) = (a,0)$ and selecting the Cayley–Dickson doubling generator $e_8 = (0,e_0)$;

   (c) computing in hardware or software the single-snapshot sedenion associator $\mathscr{A}_{\text{native}}(R) = (R \cdot \pi_{\mathbb{O}}(R)) \cdot e_8 - R \cdot (\pi_{\mathbb{O}}(R) \cdot e_8) = (ba - ab, 0)$;

   (d) computing the normalized non-associative curvature metric $\kappa_{\mathbb{S}}(R) = \|\mathscr{A}_{\text{native}}(R)\|_2 / \|R\|_2^2 \in [0,1]$; and

(e) declaring the presence of a coherent spoofer or multi-mode interferer when $\kappa_{\mathbb{S}}(R)$ exceeds a predetermined threshold above zero, even when the authentic signal and coherent interferer share an identical time-domain waveform resulting in a Rank-1 sample covariance matrix.

5. The method of claim 4, further comprising extracting the octonionic cross-product vector $a \times_{\mathbb{O}} b = -\frac{1}{2}\pi_{\mathbb{O}}(\mathscr{A}_{\text{native}}(R))$ directly from the associator output to construct a Moreno zero-divisor partner weight $W = (c,(ac)b)$ that annihilates the detected interferer in a single snapshot.

6. **(Independent — Native Dyadic TEM Vector-Sensor Array)** A native sedenion electromagnetic sensor array comprising:

   (a) a plurality of dual-polarized antenna elements arranged in a dyadic geometry configured to sense two mutually orthogonal transverse electromagnetic field components $(\mathbf{E}_\theta, \mathbf{E}_\phi)$; and

   (b) a passive 90° quadrature and 180° differential hybrid feed network coupling the $\mathbf{E}_\theta$ ports into the lower 7 imaginary octonion coordinates $a = (e_1,\ldots,e_7) \in \text{Im}(\mathbb{O})$ and the $\mathbf{E}_\phi$ ports into the upper 7 imaginary sedenion coordinates $b = (e_9,\ldots,e_{15}) \in \text{Im}(\mathbb{O})e_8$, such that any incident transverse electromagnetic plane wave natively satisfies $\|a\|_2 = \|b\|_2$ and $\langle a,b\rangle = 0$ on the Moreno zero-divisor cone $V_2(\mathbb{R}^7)$ across all continuous arrival angles (θ,ϕ) without digital array-manifold calibration matrices.

7. The sensor array of claim 6, wherein an authentic satellite or communication signal of opposite polarization handedness maps to the orthogonal anti-partner manifold $(a,-b) \in V_2(\mathbb{R}^7)$, experiencing $+3.01$ dB coherent array gain ($\|(a,-b)\cdot(c,(ac)b)\|_2 = \sqrt{2}\|a\|_2\|c\|_2$) simultaneously with exact zero-divisor jammer annihilation ($\|(a,b)\cdot(c,(ac)b)\|_2 = 0$).

8. **(Independent — Zero-Divisor Keyed Modulation [ZDKM] Transceiver)** A low-probability-of-intercept / low-probability-of-detection (LPI/LPD) communication and navigation system comprising:

   (a) a transmitter configured to hop across a cryptographically keyed sequence of Moreno zero-divisor states $(a_k,b_k) \in V_2(\mathbb{R}^7) \subset \mathbb{S}$, encoding a first binary state (`0`) as the unit zero-divisor sedenion $U_0[k] = (a_k,+b_k)/\sqrt{2}$ and a second binary state (`1`) as the unit orthogonal anti-partner sedenion $U_1[k] = (a_k,-b_k)/\sqrt{2}$; and

   (b) an authorized receiver synchronized to the cryptographic key sequence and configured to generate the corresponding Moreno nullspace partner weight $W_{\text{key}}[k] = (c_k,(a_kc_k)b_k)/\sqrt{2}$ and compute the bilinear sedenion product $Y[k] = R_{\text{rx}}[k]\cdot W_{\text{key}}[k]$, wherein $\|U_0[k]\cdot W_{\text{key}}[k]\|_2 = 0$ and $\|U_1[k]\cdot W_{\text{key}}[k]\|_2 = \sqrt{2}$, while both transmitted states maintain identical unit Euclidean norm $\|U_0[k]\|_2 = \|U_1[k]\|_2 = 1$ and isotropic spatial-polarimetric covariance $\mathbf{I}_{16}$ to an unkeyed eavesdropper.

9. The system of claim 8, further comprising a $\text{PG}(3,2)$ Quaternion Hinge projector configured to project the post-multiplication output $Y[k]$ onto one of the 35 four-dimensional associative quaternion subalgebras $\mathbb{H}_\ell = \text{span}\{e_0,e_i,e_j,e_{i\oplus j}\} \subset \mathbb{S}$ where the sedenion associator vanishes identically ($[x,y,z] = 0$), preserving carrier-phase continuity without cycle slips.

10. A digital integrated circuit or Field-Programmable Gate Array (FPGA) bitstream implementing the 16-dimensional sedenion zero-divisor beamformer and $\text{PG}(3,2)$ quaternion hinge pro-

jector of claims 1, 4, 6, or 8 in signed 16-bit fixed-point (`Q1.14`) arithmetic using a single-cycle XOR-sign butterfly and zero matrix inversions.

ABSTRACT OF THE DISCLOSURE

An apparatus, system, and method for native 16-dimensional Cayley–Dickson sedenion ($\mathbb{S} \cong \mathbb{O} \oplus \mathbb{O}e_8$) signal processing and finite projective $\mathrm{PG}(3,2)$ beamforming. A dual-polarized dyadic sensor feed maps transverse electromagnetic field components $(\mathbf{E}_\theta, \mathbf{E}_\phi)$ directly onto the Moreno zero-divisor cone $V_2(\mathbb{R}^7)$ ($\|a\| = \|b\|$, $\langle a,b\rangle = 0$) without calibration matrices. Ahead of the ADCs, a multiplier-free analog differential crossbar switch controlled by a 256-bit Cayley–Dickson sign ROM executes primitive zero-divisor blade multiplication $Z(t) = R(t) \cdot W_J$ via ± 1 differential wire-swapping and precision resistor summing, annihilating $+80$ dB jammers prior to ADC saturation. A single-snapshot non-associative curvature detector computes $\mathscr{A}_{\text{native}}(R) = [R, \pi_{\mathbb{O}}(R), e_8] = (-2(a \times_{\mathbb{O}} b), 0)$ with norm $4(\|a\|^2\|b\|^2 - \langle a,b\rangle^2)$ to detect zero-lag coherent repeater spoofers under Rank-1 covariance collapse, while a $\mathrm{PG}(3,2)$ quaternion hinge projector preserves associative carrier phase.