Hand BASIC preview atlas

RF test structures for the supplied copper / polyimide / mold-resin stack

500 MHz to 67 GHz

This report collects source-derived previews of all ten Hand BASIC programs in the parent folder: eight RF programs and two mathematical utilities. It records the requested physical stack, preserves the cardinal MPI probe arrangement, and identifies the model changes needed before electrical dimensions or performance can be assigned to this stack.

Physical configuration supplied by the user

Frequency range	0.500 to 67.000 GHz
Top copper thickness	2.2 μm
Insulation	FUJIFILM LTC-25000 polyimide, 6 μm cured thickness
Substrate	EME-G730 mold resin, 700 μm thick
RF grounds	Top-side GSG grounds only; no continuous ground plane
Installed probes	MPI TITAN, rated to 67 GHz, 150 μm adjacent-tip pitch

The existing grounded models do not predict the supplied stack. The BASIC programs synthesize microstrip and, in the ring launch, grounded CPW using a homogeneous dielectric and a continuous return plane. That plane is absent here. All printed impedances, widths, electrical lengths, mode frequencies and response curves inherited from those models are hypothetical reference results.


What this delivery establishes

The atlas supplies native-source artwork, port assignments, drawing-command records and reproducible generation files. It includes 14 RF drawing views and two utility text views. Schematics show program concepts and are not scaled mask layouts. The mobile Hand BASIC app was not executed. Published material information located for LTC-25000 and EME-G730 did not establish complex permittivity over this frequency range. No actual-stack impedance, loss, crosstalk, leakage isolation or ring resonance is asserted in this report.

Drawing revision 3 November 2026. PDF typeset with pdfLaTeX. Legacy numerical equations remain unchanged.

Stack and RF return path

The insulation thickness is not the full electromagnetic substrate height



Isolated landing grounds do not define the return path between probe planes.

Continuous top-side conductors and their connections require a multilayer CPW / EM design.

No 50-ohm width, gap, or mold-resin permittivity is inferred from the legacy grounded-model artwork.

Requested band: 0.5–67 GHz | Ground connectivity and material RF data remain design inputs.

The physical structure is a two-dielectric, top-conductor configuration. Coplanar-waveguide fields occupy air, polyimide and mold resin. A 6 μm polyimide coating cannot be substituted for the complete CPW substrate or for a 6 μm distance to an absent ground plane. A prober chuck or support underneath the mold may also affect the boundary conditions and belongs in the final model.

Connected ground conductors are required

The revised BASIC drawings connect ground rails to the probe grounds and follow straight lines, bends and stub junctions. The ring has two outer half-ring returns connected to the launch banks, without an isolated inner ground island. These are schematic connectivity corrections, not synthesized CPW dimensions. Define physical widths and slots and model the bends, junctions and any required ground bonds or bridges without shorting the signal.

Material properties remain open inputs


LTC-25000	Grade identified in public process work [2]; verified 0.5–67 GHz Dk/Df not located.
EME-G730	Exact suffix and RF data remain unspecified. Manufacturer G730 Ver. GR information concerns process/mechanical properties [3].
Reference calculations	Constant er=3.3 and loss tangent=0.01 are illustrative polyimide assumptions only. No mold Dk or Df was assigned.

The manufacturer's Dk/Df shown for G314 at 1 MHz are for a different grade and frequency. They are not used for EME-G730. Qucs distinguishes the CPW topology from microstrip and includes finite-substrate and conductor-thickness effects [4,5]; a stack-aware CPW or full-wave model is required here.

RDLLOSS / differential line loss

Two ports: P1 west, P2 east; north/south parked.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



Actual native drawing commands; the printed delta length is a hypothetical grounded-model result.

Measurement concept

Three separate coupons use common launches and short, middle and long line lengths. The intended measurement is the change in attenuation with length.


Changes needed for the supplied stack

The sketch now connects top-side ground rails along each line. Replace microstrip width and attenuation synthesis with ungrounded multilayer CPW and size the rails, slots and identical transitions. Include copper thickness, roughness, both dielectric losses, mismatch and calibration. **Specific model limit.** The source loss approximation also assumes a thick conductor. At 500 MHz its hypothetical skin depth is about 2.952 μm, exceeding the 2.2 μm copper thickness. Its three-skin-depth condition is reached only above about 8.102 GHz.

RDXTALK / four-port crosstalk

P1 west, P2 north, P3 south, P4 east. Aggressor W-to-N; victim S-to-E.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



Four cardinal GSG landings with connected outer grounds and no signal crossover. The coupled pair retains an unshielded central gap.

Measurement concept

Preserve the two parallel coupled conductors and cardinal access fanouts. P1 drives the aggressor; P2 is through, P3 is near-end and P4 is far-end coupling.

Changes needed for the supplied stack


Define the top-ground layout before solving the coupled CPW modes. Ground rails, slots, corners and finite ground regions all affect coupling. Use a four-port multilayer EM model and calibrate all four probe planes. **Specific model limit.** The current coupled microstrip calculation uses zero-thickness DUT conductors and omits access bends and probe parasitics. Its 1 mm adjacent landing-centre rule is adjustable and does not establish mechanical clearance of the installed probe bodies.

Port meaning: S21 is W-to-N aggressor through, S31 is W-to-S near-end coupling, and S41 is W-to-E far-end coupling. Full four-port calibration is required.

RFLEAK / via-connected layer transition

Two top-side ports: P1 west, P2 east; north/south parked.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



Top view: connected G-S-G routing and via locations. Signal side view: upper-left L1 drops to lower-right L2, then returns to L1 at the east pads. Not to scale.

Measurement concept

The west trace is on upper layer L1. A central signal via joins it to the right-hand trace on lower layer L2. Separate G-S-G vias at the east end return all three conductors to the top-side probe pads. Ground rails follow the traces and have their own layer transitions.


Changes needed for the supplied stack

Confirm the second patterned metal layer and define its thickness and dielectric separation. Size the signal and ground vias, rails and slots using a multilayer EM model. This connected structure is not an isolated broadside leakage capacitor. **Specific model limit.** The retained numerical routines calculate coupling between isolated plates, not this via-connected path. Their capacitance, isolation and via-fence rules must not be interpreted as the response of the new drawing.

STUBTEST / open and short shunt stubs

Two ports: P1 west, P2 east; north/south parked.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



Open-stub source artwork. The numerical width and length are legacy grounded-reference labels.

Measurement concept

A shunt branch is added to a through line. Both the open-ended and short-ended native schematic variants are included in the gallery.

Changes needed for the supplied stack


Design the through line, branch, tee junction and their ground rails as CPW on the actual two-dielectric stack. An RF short needs a defined connection to the top grounds. Include fringing at an open end and parasitics at a short. **Specific model limit.** The native 70 ohm stub synthesis and 20 GHz notch example use the grounded microstrip reference. They cannot establish a physical CPW length or notch frequency for this stack.

The gallery also contains `stubtest-short.png`, rendered from the source short-stub branch. Both variants retain two external ports.

TRLSET / multiline calibration standards

Two ports: P1 west, P2 east; one standard measured at a time.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



Native schematic of separate standards; row spacing and drawn lengths are illustrative and not a mask layout.

Measurement concept

The standards retain a common cross section and launches, with a thru and several extra line lengths. The same reflect reference is used across measurements.


Changes needed for the supplied stack

Use the same connected CPW grounds, slots and stack as the DUTs. Choose line lengths from the actual dispersive propagation constant, then check pairwise phase and calibration conditioning across 0.5 to 67 GHz. **Specific model limit.** The legacy source uses a homogeneous microstrip effective permittivity. Its two-port west/east standards do not supply the complete four-head calibration needed for the cardinal RDXTALK device.

VIAMATCH / one-port stud and via match

One external port: P1 west. The RL/RX load is internal; east/north/south parked.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



The right-hand block is the internal load, not a second external probe landing.

Measurement concept

The original calculation combines surrogate stud/via impedances and an ideal matching network feeding a specified internal load. Its RF output is input reflection or return loss.


Changes needed for the supplied stack

Specify the actual vertical metal path and its top-side return conductors. Replace the source closed cylindrical return with the fabricated geometry and a multilayer port model. Check finite-Q components and self-resonance. **Specific model limit.** An ungrounded mold substrate does not provide the assumed cylindrical return. The ideal match and its numerical return-loss floor cannot be treated as realizable device performance. This program has no external east through port or S21 prediction.

ZCOUPON / impedance and width variation

Two ports: P1 west, P2 east; separate width-variation coupons.

Source artwork only. Native numerical labels below belong to the legacy grounded reference and do not establish electrical behavior on the supplied ungrounded stack.



Native low/nominal/high-width artwork. Three rows are separate devices, not simultaneous probe positions.

Measurement concept

The source varies conductor width around a nominal value while retaining a common line length. This is a useful measurement concept for process sensitivity.

Changes needed for the supplied stack

For CPW, specify both signal width and ground slot width, finite ground width and top-ground continuity. Define whether the slot is held fixed or changes with the width DOE. Re-synthesize the nominal geometry on the actual stack. **Specific model limit.** The printed nominal width of about 12.431 μm was synthesized for a hypothetical grounded 6 μm dielectric. It is not a validated 50 ohm CPW width on EME-G730.

Ring dimensions and source assumptions

RESONATOR2 / legacy grounded-model evaluation / no physical-stack electrical prediction

```
HOST PREVIEW | legacy source artwork; numerical labels are hypothetical reference only
Actual stack: Cu 2.2 um / LTC-25000 6 um / EME-G730 700 um / 0.5-67 GHz
Legacy GROUNDED model; actual stack has NO backplane
Requested Cu 2.2 um also exceeds interactive MT/H <= 0.1 guard; native labels below are NOT physical-stack predictions.
RING DESIGNER V1.1 / FIRST-PASS RF DESIGN
01 / RING DIMENSIONS
```

MATERIAL / EXCITATION	RING / PROBE GEOMETRY
LTC-25000 (REFERENCE ONLY)	R scale 6.0635 mm
Er = 3.3 h = 6 um	Max copper radius 6.0697 mm
Band 0.5 to 67 GHz	Centreline length 38.0981 mm
Fundamental 5 GHz	Coupling gap 2 um
50-ohm trace 12.4466 um	Minimum bend R 6.0635 mm
Effective Er 2.4768	GSG pitch 150 um
Metal thickness 2.2 um	Modes in band 13
Lobes 0 depth 0	Checks flagged 2


```
MPI TITAN GSG150 / 67 GHz
R: centreline radius (circle), radial scale (lobes).
Starting geometry; inspect checks before fabrication.

TAP: NEXT PAGE M: MENU
```

The source reports a hypothetical 50 ohm trace of 12.4466 μm and a ring radius of 6.0635 mm for an illustrative 5 GHz fundamental. Neither dimension is a synthesized CPW design for the actual mold stack.

Circular ring and west/east access

RESONATOR2 / legacy grounded-model evaluation / no physical-stack electrical prediction



Connected outer half-ring ground rails follow the signal and join both launch banks. No floating inner ground island is drawn. Rail and slot dimensions and feed-to-ring coupling still require an ungrounded multilayer model; the legacy numerical model assumes an absent backplane.

GSG launch detail

RESONATOR2 / legacy grounded-model evaluation / no physical-stack electrical prediction

HOST PREVIEW | legacy source artwork; numerical labels are hypothetical reference only

Actual stack: Cu 2.2 um / LTC-25000 6 um / EME-G730 700 um / 0.5-67 GHz


Legacy GROUNDED model; actual stack has NO backplane

Requested Cu 2.2 um also exceeds interactive MT/H <= 0.1 guard; native labels below are NOT physical-stack predictions.

RING DESIGNER V1.1 / FIRST-PASS RF DESIGN

03 / GSG LAUNCH DETAIL

Contact centres: y = -pitch, 0, +pitch



Pitch 150 um

Pad width 100 um

Pad length 100 um

Pad local Z 11.1815 ohm

Neck width 16.5001 um

Neck slot 91.75 um

Neck Z 50 ohm

Contact X +/- 7.6217 mm

West detail; east mirrored. Crosses: tip centres.

W/E active; N/S parked. Local Z: long GCPW section.

TAP: NEXT PAGE M: MENU

The 150 μm contact pitch is retained. The source launch uses a grounded-CPW approximation of zero metal thickness; its neck and pad impedance labels do not describe this ungrounded stack. The 2.2 μm metal thickness must be included in a replacement launch model.


Nominal resonance-mode page

RESONATOR2 / legacy grounded-model evaluation / no physical-stack electrical prediction

```
HOST PREVIEW | legacy source artwork; numerical labels are hypothetical reference only
Actual stack: Cu 2.2 um / LTC-25000 6 um / EME-G730 700 um / 0.5-67 GHz
Legacy GROUNDED model; actual stack has NO backplane
Requested Cu 2.2 um also exceeds interactive MT/H <= 0.1 guard; native labels below are NOT physical-stack predictions.
RING DESIGNER V1.1 / FIRST-PASS RF DESIGN
04 / NOMINAL RESONANCE MODES
Mode frequency = order x F1; constant effective Er.

n= 1  5 GHz                                   n= 5  25 GHz
n= 2  10 GHz                                  n= 6  30 GHz
n= 3  15 GHz                                  n= 7  35 GHz
n= 4  20 GHz                                  n= 8  40 GHz

13 estimated modes; first eight listed above.
```



```
0.5 GHz                                                    67 GHz
Mode positions only; not an S21 response.
TAP: NEXT PAGE M: MENU
```

A 5 GHz illustrative fundamental produces 13 nominal reference modes at 5,10,...,65 GHz. These are unloaded length-model positions, not measured resonances, not actual-stack predictions, and not an S21 passband.

Native model checks

RESONATOR2 / legacy grounded-model evaluation / no physical-stack electrical prediction

```
HOST PREVIEW | legacy source artwork; numerical labels are hypothetical reference only
Actual stack: Cu 2.2 um / LTC-25000 6 um / EME-G730 700 um / 0.5-67 GHz
Legacy GROUNDED model; actual stack has NO backplane
Requested Cu 2.2 um also exceeds interactive MT/H <= 0.1 guard; native labels below are NOT physical-stack predictions.
RING DESIGNER V1.1 / FIRST-PASS RF DESIGN
05 / ASSUMPTIONS AND CHECKS
```

CONSTRUCTION / MODEL	CHECKS FOR THIS DESIGN
Model assumes backside ground.	GCPW METAL NOT THIN VERSUS W/S
Sketch: top-side return rails.	MICROSTRIP METAL NOT THIN VS W
No inner floating ground island.	
W/E active; N/S heads parked.	
Bulk isotropic Er; air above.	
No dielectric stack or coating.	
No loss, Q, or S21 prediction.	
EM-tune tapers and ring gaps.	


```
Cosine lobes differ from the paper's circular arcs.

TAP: NEXT PAGE M: MENU
```

At 6 μm insulation, the source input guard permits at most 0.6 μm copper; requested copper is 2.2 μm. These host previews evaluate the unchanged equations directly outside that interactive guard. The source also flags both microstrip and GCPW thin-metal conditions.

Six-lobe source variant

RESONATOR2 / legacy grounded-model evaluation / no physical-stack electrical prediction



The extra variant uses six cosine lobes at 10 percent depth. It illustrates the source shape parameterization, not a validated alternative for the physical stack. It retains two west/east ports and parked north/south heads.

Mathematical utilities

Source text previews complete the ten-program Hand BASIC inventory

MATMUL.BAS / SOURCE TEXT PREVIEW

```
MATRIX LIBRARY
1: INPUT A
2: INPUT B
3: SHOW A
4: SHOW B
5: A + B
6: A - B
7: A * B
8: TRANSPOSE A
9: IDENTITY
10: DETERMINANT
11: K * A
12: SWAP ROWS IN A
13: SWAP COLS IN A
14: INVERSE A
15: GAUSS-JORDAN
16: SOLVE AX=B
17: MATRIX POWER
18: COPY A TO C
19: RREF
20: TRACE
21: RANK
22: LU DECOMP
23: EIGENVALUES 2X2
24: EIGENVALUES 3X3
25: EXIT
CHOICE?
```

RF frequency, insulation and probe settings do not apply.

varprec.bas / SOURCE TEXT PREVIEW

```
VARIABLE-PRECISION INTEGER CALCULATOR
ENTER NONNEGATIVE DECIMAL INTEGERS (UP TO 88 DIGITS)
FIRST INTEGER?
```

RF frequency, insulation and probe settings do not apply.

These two programs have no RF frequency, dielectric, copper or probe inputs. The previews extract the actual initial PRINT text and first INPUT prompt; menu actions and arithmetic are not executed by the preview generator.


Archived reference calculations

Debugging the existing equations; excluded from actual-stack design claims

This archive does not solve the physical stack. Microstrip widths and line responses assume a hypothetical continuous plane under the polyimide. Leakage capacitance and via matching use separate idealized plate and closed-return surrogates. The ungrounded multilayer structure is not solved. Agreement with source equations establishes reproducibility only.

The archive uses er=3.3, loss tangent=0.01, copper resistivity=17.2 nOhm m and RMS roughness=0.3 μm. The last two values are retained source defaults; none is a measurement on this fabrication. Source equations were translated independently and checked against the source-driven interpreter at 70 values.

Program	Example hypothetical result and interpretation
RDLLOSS	67 GHz loss: 1.2765 dB/mm. Used only to reproduce the source loss-length calculation.
RDXTALK	Base-gap S31=-17.608 dB, S41=-15.472 dB at 67 GHz; coupled microstrip reference only.
RFLEAK	0.038958 pF from the parallel-plate formula with assumed er and 6 μm gap.
STUBTEST	Open-stub reference length 2.46236 mm for the source 20 GHz example.
TRLSET	One long line exceeds 40 mm; remaining eligible pairs cover the 201 sampled reference points. This does not establish physical CPW calibration coverage.
VIAMATCH	Ideal matching values 0.18212 nH and 0.15927 pF at 20 GHz depend on the surrogate return and load.
ZCOUPON	Nominal reference width 12.43114 μm is 50 ohms by the microstrip synthesis. It is not a CPW width.



Below three skin depths, the source flags the conductor approximation; loss tangent is assumed.

The gallery stores all seven response plots under a separate, initially collapsed reference section. Raw results, assumptions, source-line provenance and cross-check results are in `rf-results.json` and `rf-results.csv`. No actual-stack S-parameter file is generated.

Files, verification and next design steps

Reproduce the previews and PDF without changing the BASIC listings

Delivered files

`handbasic-previews/index.html`	Preview gallery, with RF artwork, utility text and reference-plot sections.
`handbasic-preview-profile.json`	User stack and probes; explicit reference assumptions and model applicability.
`handbasic-previews/*.svg / *.png`	Editable vector artwork and viewing images.
`*-commands.json / *manifest.json`	Source commands, source/profile hashes, calculation entry points and limits.
`reports/build.ps1`	Regenerate previews, data, gallery and report with pdfLaTeX.
`reports/handbasic-ltc25000-eme-g730.tex`	Editable report source.

Run `powershell -File reports/build.ps1` from the project folder. Node.js, ImageMagick and pdfLaTeX are required. The build checks that all RF manifests use the same profile and unchanged BASIC sources; mathematical text previews are literal extraction. Mobile app behavior, probe-body fit, fabricated dimensions and physical RF performance are not validated by this build.

Scope of the program inventory

All ten parent-folder BASIC programs are represented. The C64-only `RING67.PRG` is a separate synthetic ideal two-port model, not an additional Hand BASIC program; it is not a solver for this physical stack and is not presented as one.

Before assigning fabrication dimensions or RF predictions

Obtain the complex permittivity of both exact cured material grades over 0.5–67 GHz, together with copper conductivity/roughness and the support/chuck boundary. Define connected top-ground regions, CPW slots, optional bridges, the RFLEAK second metal layer and VIAMATCH return geometry. Then solve the finite-thickness multilayer CPW structures and launches, synthesize the nominal 50 ohm geometry, and check calibration on matching standards. Preserve the existing cardinal port counts and assignments during that redesign.

Sources

[1] MPI Corporation, Probe Selection Guide, T67, p.6: 67 GHz family and available GSG pitches. Rating is a probe specification, not a guarantee for the DUT or the complete measurement system.

[2] EV Group / FUJIFILM, SWTest 2024 digital-lithography process study. Identifies LTC 25000 in process trials; it is not broadband dielectric characterization.

[3] Sumitomo Bakelite, SUMIKON EME semiconductor encapsulants. G730 Ver. GR and G314 are separate entries. Exact user grade suffix is unconfirmed.

[4] Qucs technical documentation, Coplanar waveguides. Topology, finite-substrate and conductor-thickness considerations.

[5] Qucs technical documentation, Single microstrip line. Source model family and thickness corrections.