



Initializing the FlashArray

Generated on: 28 May 2026

Contents

Initializing the FlashArray 3

Initializing the FlashArray

Note: When using the ZTP tool to provision RC4 arrays that use ETH4/5 as their management ports, the config.json file that is used must be modified to specify ct0.eth4, ct1.eth4, and vir4 as the interfaces that are being given IPs. This is instead of the original eth0 and vir0 ports that are typically used.

If this is not done, an error with status code 400 will show 'invalid key vir0 in array configuration'. An example is shown [here](#).

Following is the information required to initialize the FlashArray. Please note that except for the fields marked as "optional", the rest of the information must be provided in order to initialize the FlashArray:

Information Required to Initialize the FlashArray			
FlashArray Name			
vir0	IP Address	Netmask	Gateway
ct0.eth0	IP Address	Netmask	Gateway
ct1.eth0	IP Address	Netmask	Gateway
DNS Domain (optional)	Name Servers		
NTP Servers			
Time Zone			

Information Required to Initialize the FlashArray			
SMTP Relay Host (optional)	Sender Domain	Alert Email Addresses (optional)	
Agreement to Accept the EULA	Full Name	Job Title	Name of Organization

The above information has to be put into the JSON format, as shown in the example below, and sent to the FlashArray in a PATCH request over the REST API. Do not use the format shown in the GET command above, as it contains additional fields for which the FlashArray does not accept user input, such as the array serial number.

Copy the text in the example below to create the JSON configuration. Replace the sample information with the information specific to your environment. Then use the following PATCH Request to send this configuration to the FlashArray via the REST API endpoint at ct1.eth0.

PATCH Request URL = <http://10.211.212:8081/array-initial-config>

Where: 10.211.212 is the IP address of ct1.eth0 on the FlashArray

Following is an example of the information that should be sent in the body of the PATCH Request to initialize the FlashArray (for more information on JSON, check out <http://www.json.org/>):

```
{
  "array_name": "tmeffa10",
  "ct0.eth0":
  {
    "address": "10.21.1.183",
    "netmask": "255.255.255.0",
    "gateway": "10.21.1.1"
  },
  "ct1.eth0":
  {
    "address": "10.21.1.184",
    "netmask": "255.255.255.0",
    "gateway": "10.21.1.1"
  },
  "vir0":
```

```

{
  "address": "10.21.1.182",
  "netmask": "255.255.255.0",
  "gateway": "10.21.1.1"
},
"dns":
{
  "domain": "dev.purestorage.com",
  "nameservers":
  [
    "10.14.240.240"
  ]
},
"ntp_servers":
[
  "time1.purestorage.com"
],
"timezone": "America/Los_Angeles",
"smtp":
{
  "relay_host": "blackhole-smtp2.dev.purestorage.com",
  "sender_domain": "purestorage.com"
},
"alert_emails":
[
  "amin@purestorage.com"
],
"eula_acceptance":
{
  "accepted": true,
  "accepted_by":
  {
    "organization": "Pure Storage",
    "full_name": "Syed Amin",
    "job_title": "TME"
  }
}
}

```

Please note in the EULA (End User License Agreement) section at the end of the JSON file. By entering the following information into the JSON file, you, as the customer, are agreeing to the terms and conditions in the EULA:

```

"eula_acceptance":
{
    "accepted": true,
    "accepted_by":
    {
        "organization": "ABC Corporation",
        "full_name": "John Smith",
        "job_title": "System Administrator"
    }
}

```

If the PATCH Request is successful, and there are no error messages, the FlashArray will send a response similar to the following:

```

{
    "status": "initializing",
    "array_id": "",
    "ct0.eth0":
    {
        "netmask": "255.255.255.0",
        "address": "10.21.1.183",
        "gateway": "10.21.1.1",
        "mac_address": "24:a9:37:00:34:33"
    },
    "smtp":
    {
        "relay_host": "blackhole-smtp2.dev.purestorage.com",
        "sender_domain": "purestorage.com"
    },
    "vir0":
    {
        "netmask": "255.255.255.0",
        "address": "10.21.1.182",
        "gateway": "10.21.1.1",
        "mac_address": ""
    }
}

```

```

    },
    "alert_emails":
    [
        "amin@purestorage.com"
    ],
    "ct1.eth0":
    {
        "netmask": "255.255.255.0",
        "gateway": "10.21.1.1",
        "address": "10.21.1.184"
    },
    "ntp_servers":
    [
        "time1.purestorage.com"
    ],
    "version": "5.2.4",
    "eula_acceptance":
    {
        "accepted_by":
        {
            "organization": "Pure Storage",
            "full_name": "Syed Amin",
            "job_title": "TME"
        },
        "accepted": true
    },
    "progress": 0.01,
    "dns":
    {
        "nameservers":
        [
            "10.14.240.240"
        ],
        "domain": "dev.purestorage.com"
    },
    "timezone": "America/Los_Angeles",
    "serial_number": "PCHFL17320104",
    "os": "Purity//FA",
    "array_name": "tmeffa10"
}

```

Once the FlashArray has been initialized successfully, use the static IP addresses that were assigned to the array during initialization in order to communicate with the FlashArray. The DHCP assigned IP

addresses will no longer be valid. Also, the "array-initial-config" request will no longer be valid. Therefore, authentication is required to communicate with the FlashArray via the REST API endpoint.

Configuration Examples

Typical JSON config example:

```
{
  "array_name": "slc-314-fa01",
  "ct0.eth0":
  {
    "address": "10.235.118.73",
    "netmask": "255.255.252.0",
    "gateway": "10.235.116.1"
  },
  "ct1.eth0":
  {
    "address": "10.235.118.74",
    "netmask": "255.255.252.0",
    "gateway": "10.235.116.1"
  },
  "vir0":
  {
    "address": "10.235.118.72",
    "netmask": "255.255.252.0",
    "gateway": "10.235.116.1"
  },
}
```

Modified config example with ETH4/VIR4

```
{
  "array_name": "slc-314-fa01",
  "ct0.eth4":
  {
    "address": "10.235.118.73",
    "netmask": "255.255.252.0",
    "gateway": "10.235.116.1"
  },
  "ct1.eth4":
  {
    "address": "10.235.118.74",
    "netmask": "255.255.252.0",
    "gateway": "10.235.116.1"
  },
}
```

```
},  
"vir4":  
{  
  "address": "10.235.118.72",  
  "netmask": "255.255.252.0",  
  "gateway": "10.235.116.1"  
},  
{
```

© 2015-2026 Pure Storage® ("Pure"), Portworx® and associated its trademarks can be found here as and its virtual patent marking program can be found here. Third party names may be trademarks of their respective owners. The Pure Storage products and programs described in this documentation are distributed under a license agreement restricting the use, copying, distribution, and decompilation/reverse engineering of the products. No part of this documentation may be reproduced in any form by any means without prior written authorization from Pure Storage, Inc. and its licensors, if any. Pure Storage may make improvements and/or changes in the Pure Storage products and/or the programs described in this documentation at any time without notice. This documentation is provided "as is" and all express or implied conditions, representations and warranties, including any implied warranty of merchantability, fitness for a particular purpose, or non-infringement, are disclaimed, except to the extent that such disclaimers are held to be legally invalid. Pure shall not be liable for incidental or consequential damages in connection with the furnishing, performance, or use of this documentation. The information contained in this documentation is subject to change without notice.
