VECTOR

MICROSAR OS

Technical Reference

Version 3.01.00

Authors	Anton Schmukel, Ivan Begert, Stefano Simoncelli, Torsten Schmidt, Da He, David Feuerstein, Michael Kock, Martin Schultheiß, Andreas Jehl, Fabian Wild, Senol Cendere, Benjamin Seifert, Bilal Parvez, Rainer Künnemeyer, Alexander Egorenkov, Daniel Quick, Lukas Rohrwild, Susann Rothweiler, Alexander Lerach, Muhammad Suliman, Sascha Mauser
Status	Released

Document Information

History

Author	Date	Version	Remarks
Torsten Schmidt	2016-04-27	1.0.0	First release version
Torsten Schmidt	2016-05-18	1.0.1	References to hardware manuals added. Revision work
Torsten Schmidt	2016-06-03	1.0.2	Fix of ESCAN00089598
Torsten Schmidt	2016-06-20	1.1.0	List of OS internal objects added. Additional startup concept chapter added. Chapter “Memory mapping concept” reworked. Description of “generate callout stubs” feature added.
Torsten Schmidt	2016-07-05	1.1.1	Chapter “Memory Mapping Concept” extended. IOC notification callback concept changed. HSI of RH850 family added. HSI of Power PC family added.
Torsten Schmidt	2016-07-19	1.1.2	Chapter “Memory Mapping Concept” changed. Hints for shorter compile times added. Nesting behavior of OS hooks described.
Ivan Begert	2016-08-11	1.1.3	HSI of ARM family added.
Torsten Schmidt	2016-08-12	1.1.4	Chapter “Memory Mapping Concept” extended. Chapter “Clear Pending Interrupt” extended. Chapter “RH850 Special Characteristics” extended.
Ivan Begert	2016-08-18	1.1.5	HSI of ARM Zynq UltraScale added.
Torsten Schmidt	2016-08-30	1.1.6	HSI of RH850 extended.
Torsten Schmidt	2016-08-31	1.1.7	ORTI Debugging added. Timing Hook Macros reworked. Chapter “Memory Mapping Concept” changed. Chapter “Category 1 Interrupts” extended.
Stefano Simoncelli Torsten Schmidt	2016-09-15	1.1.8	Chapter “Interrupt Source API” extended. HSI chapter for ARM extended
Torsten Schmidt	2016-09-22	1.2.0	VTT OS and Dual Target Concept added. Chapter ORTI Debugging extended.
Anton Schmukel Da He	2016-10-14	1.3.0	Ristrictions concerning API usage before StartOS() documented. Clarification concerning forcible termination and schedule tables added. Deviations in IOC added. Notes on mixed criticality systems added. Chapter “RH850 Special Characteristics” extended.

Torsten Schmidt	2016-10-19	1.3.1	Chapter “Configuration of X-Signals” added. Chapter “Power PC Special Characteristics” extended. Correction of startup examples. Chapter “User include files” added. RH850 HSI extended. PPC HSI extended. Hardware Overview extended by RH850.
David Feuerstein	2016-11-03	1.4.0	PPC HSI extended. Chapter ORTI Debugging extended.
Michael Kock	2016-11-25	1.5.0	Updated chapter Timing Hooks
Martin Schultheiß	2016-12-08	1.6.0	PPC HSI extended. Updated characteristics of VTT OS.
David Feuerstein Andreas Jehl Ivan Begert Stefano Simoncelli	2016-12-22	1.7.0	Updated precautions in PreStartTask. Support new Power PC Derivative: PC580003 Support IAR compiler for ARM ARM Cortex-A HSI added
David Feuerstein Torsten Schmidt	2017-01-23	1.8.0	Chapter “Memory Mapping Concept” changed. Chapter “Resulting sections” extended. Chapter “X-Signals” extended. Chapter “API Description” extended.
Torsten Schmidt Stefano Simoncelli David Feuerstein	2017-02-06	2.0.0	Chapter “Memory Mapping Concept” corrected. Chapter “MICROSAR OS Deviations from AUTOSAR OS Specification” extended. Chapter “IOC” extended. Feature “Fast Trusted Functions” added. Chapter “Non-Trusted Functions (NTF)” changed. ARM Cortex-M Hardware overview updated. Feature “Barriers” added.
Martin Schultheiß Benjamin Seifert Da He Torsten Schmidt Stefano Simoncelli Anton Schmukel	2017-03-22	2.1.0	Updated Hardware Overview for Power PC derivative groups (RM revisions). Chapter “MICROSAR OS Deviations from AUTOSAR OS Specification” corrected. Added API OSError_GetScheduleTableStatus_ScheduleStatus Chapter “ARM Special characteristic” extended. Chapter “Cortex-R derivatives” extended. Chapter “Idle Task” extended. TI Compiler added as supported compiler for ARM. Platform POSIX added Added HSI for ARM Cortext-M
Fabian Wild Stefano Simoncelli	2017-03-31	2.2.0	Added AUTOSAR specification deviations. Changed address parameter type in peripheral API functions.

Da He Martin Schultheiß	2017-04-11	2.3.0	Added HSI for TI AR16xx Added information for Hardware Init Core
Senol Cendere Torsten Schmidt Martin Schultheiß Da He	2017-05-10	2.4.0	Added HSI for R-Car H3. Extended chapter “Memory Mapping Concept”. Added chapter “Linking of Spinlocks”. Updated HSI for S32K derivatives. Added chapter for exception context manipulation
Fabian Wild Martin Schultheiß	2017-06-19	2.5.0	Removed ORTI tracing from Os_Init and Os_InitMemory Support new Power PC Derivative: SPC574Sxx
Torsten Schmidt	2017-06-06	2.6.0	Added descriptions for category 0 ISRs.
Ivan Begert Senol Cendere	2017-07-05	2.6.1	Chapter “ARM Special characteristic” extended. RH850 HSI extended. Updated Table 1-9 Supported RH850 Compilers. Updated Chapter 4.5.2 RH850
Torsten Schmidt	2017-07-17	2.7.0	Chapter “Software Stack Check” extended. Chapter “VTT OS Specifics” extended. Chapter “Initialization of Interrupt Sources” extended. Chapter “Notes on Category 1 ISRs” extended. Chapter “Notes on Category 0 ISRs” extended. Chapter “Pre-Process Linker Command Files” added. API description of “Os_Init” extended.
Senol Cendere Da He Andreas Jehl	2017-08-15	2.8.0	Documented support for more RH850 derivatives and compiler versions. Updated documentations regarding location of OS identifiers. Support ARM CC (5.x) compiler for ARM Cortex-M Documented support of TC39x derivative with Tasking v6.0r1p2 compiler
Martin Schultheiß	2017-08-17	2.9.0	Updated Derivative Support for PPC and RH850
Senol Cendere Torsten Schmidt Rainer Künnemeyer	2017-10-25	2.10.0	New vector timing hooks OS_VTHACTIVATION_LIMIT and OS_VTH_WAITEVENT_NOWAIT, usage of vector timing hooks now also in safety systems. Chapter “Task Stack Sharing” Extended Added comments on RTE interrupt API
Da He Benjamin Seifert	2017-11-13	2.11.0	Support GCC Linaro compiler for ARM Cortex-A/R and Cortex-M Added HighTec compiler support for PowerPC and TriCore Added MPC56xx derivatives to chapter “Hardware Overview” and “Hardware Software Interfaces” Fixed Timing Hooks API descriptions

Stefano Simoncelli Torsten Schmidt Benjamin Seifert	2017-12-14	2.12.0	Support for TDA2x family derivatives Support for TriCore Aurix TC38x Added caution to chapter “Aurix Special Characteristics” Fixed descriptions in "Os generated objects"
Bilal Parvez Senol Cendere Stefano Simoncelli	2018-01-11	2.13.0	Chapter “VTT OS Specifics” corrected Added RH850 F1KH hardware manual reference Chapter “Floating Point Context Extension” Updated HSI Chapter
Martin Schultheiß Simoncelli Stefano	2018-02-02	2.14.0	Adapted HSI – MSR Bits used by OS Added Chapter “User defined processor state.” Support for TMSLS57021x_31x derivatives
Torsten Schmidt	2018-03-09	2.14.1	Adapted a note in chapter “Floating Point Context Extension”
Senol Cendere	2018-03-14	2.15.0	Adapted Chapter 4.3.3 “Section Symbols” Added Chapter 2.4.8 “Unhandled Syscalls” Added Chapter 4.2.1.8 “Configuration of Interrupt Sources”
Rainer Künnemeyer Benjamin Seifert Fabian Wild	2018-04-03	2.16.0	Added chapter 4.10 “Preprocessing of assembler language files” Added supported compiler version for ARM Added deviation regarding spinlock deadlock detection
Benjamin Seifert	2018-04-17	2.17.0	Added support for TMS570LC43x derivatives Updated chapter "4.2.4.4 ARM Special Characteristics"
Bilal Parvez Benjamin Seifert	2018-05-14	2.18.0	Added description for Interrupt Mapping support Updated the usage section of the Exception Context Manipulation chapter Added caution for GetTaskID to chapter "2.3.4 Software Stack Check"
Bilal Parvez Benjamin Seifert	2018-06-28	2.19.0	Support for CYT2Bx derivatives Extended Chapter "4.11.2 ARM Family” Added Chapter "4.12 Stack Summary" Small fix in Chapter "2.17.5 Protection Violation Handling"
Rainer Künnemeyer Bilal Parvez	2018-07-16	2.20.0	Improved chapter “5.2.12 Timing Hooks” in order to describe calls to timing hooks in case of forcible termination Added support for IMX8x derivatives

Stefano Simoncelli Martin Schultheiß	2018-08-03	2.21.00	Added support for S32x derivatives Improved chapter “1.4.3 Hardware Overview - ARM” Improved chapter “3.15.2 Floating Point Context Extension - Usage” Updated description for Pre- and PostTaskHook behaviour in case of violations.
Stefano Simoncelli	2018-10-17	2.22.00	Added support for TMPV770x derivatives.
Alexander Egorenkov, Rainer Künnemeyer	2018-11-27	2.24.00	Imroved structure of chapter “3.17 Memory Protection” to avoid duplicates. Improved the structure of chapter “5.2 Hardware Software Interface” and made it more uniform. Add description for “Init Stack”. New function to enable all interrupt sources.
Daniel Quick, Stefano Simoncelli, Alexander Egorenkov	2019-03-29	2.25.00	Added a warning to the specific characteristics of the TriCore Aurix Family. Added a limitation to the API service Os_InitialEnableInterruptSources. Corrected the entry KernelErrors in chapter “ErrorHandling”.. Added support for CYT4Bx, Xavier, Cortex-M0. Extended Chapter 2.4.3 “ARM Hardware Overview”. Extended Chapter 5.2.4 “ARM HSI”. Extended Chapter 5.5.4.1 – “X-Signal ISR Interrupt Sources”. Added new return values for Event-API-.
Alexander Egorenkov, Lukas Rohrwild	2019-04-18	2.26.00	STORY-11978, SystemApplication information, adaption of HIS overview. Updated Derivative Support for RH850. Extended Chapter 5.2.4 “ARM HSI”.
Rainer Künnemeyer	2019-05-15	2.27.00	STORY-12408: Refinement of XSignal mechanism description in chapters 3.15.3, 4.9 and 5.5. STORY-12722: Improved description of Vector timing hook OS_VTH_SCHEDULE
Stefano Simoncelli, Lukas Rohrwild	2019-06-28	2.28.00	Added support for ExynosAuto9 derivatives. Added support for CYT4Bx (Cortex-M0) derivatives. Added FRT support for iMx8 derivatives. Support Windriver DiabData compiler for RH850.

Stefano Simoncelli Susann Rothweiler, Torsten Schmidt Daniel Quick Martin Schultheiß	2019-07-09	2.29.00	Removed RTT Timer references. Fix of ESCAN00103432 Added support of Windriver Diab compiler for TriCore Aurix Added support of GHS compiler for TriCore Aurix Added support of Aurix TC33x, TC35x, TC36x, TC37x Provide Os_BarrierSynchronize as ASIL-D feature. Added new linker labels (*_LIMIT).
Alexander, Egorenkov, Daniel Quick	2019-08-21	2.30.00	Added description of the new API function Os_GetCoreStartState
Lukas Rohrwild, Bilal Parvez, Martin Schultheiß	2019-09-19	2.31.00	Added description for Interrupt Mapping support (RH850). Extend chapter 5.2.2 “RH850 HSI”. Added support for PPC S32R29x derivatives. Extended chapter 5.2.4 “ARM Family HSI”. Documented support of Arm Family with Tasking v6.2r2p2 Arm compiler. Added additional information for HRT solution and S32K derivative group.
Bilal Parvez, Lukas Rohrwild, Martin Schultheiß	2019-10-16	2.32.00	Extended chapter 5.2.4 “ARM HSI”. Updated Derivative Support for RH850. Extend chapter 5.2.2 “RH850 HSI”. Extended description for section access rights.
Martin Schultheiß, Lukas Rohrwild, Ahmed El Amri	2019-11-04	2.33.00	Update for S32K derivatives HSI description. PPC HSI extended. Updated compiler and derivative support for PPC. Add HSI for TI Jacinto7 TDA4x.
Martin Schultheiß, Rainer Künnemeyer	2019-11-22	2.34.00	Updated description for Timing Hook usage. Fix of ESCAN00105025 by documentation of interrupt state in Shutdown- and ProtectionHook.
Alexander Lerach, Rainer Künnemeyer, Muhammad Suliman, Bilal Parvez	2019-12-20	2.35.00	Added documentation of time slice scheduling. Added FRT support for ExynosAuto9 derivatives. Fix of ESCAN00104931.
Lukas Rohrwild Torsten Schmidt Susann Rothweiler	2020-01-28	2.36.00	Updated Derivative Support for RH850. Updated derivative support for TI Jacinto. Fixed ESCAN00105308: Wrong OS API return value (ReleaseResource).

Sascha Mauser, Alexander Lerach, Muhammad Suliman, Andreas Jehl	2020-03-09	2.37.00	Updated Derivative Support ARM Added HSI for S32K2TV/S32K3xx Added additional information to the RTE Interrupt API. Updated support for S32x derivatives. Updated derivative support and HSI for PowerPC HSM.
Alexander Lerach, Susann Rothweiler	2020-03-30	3.00.00	Added IOC call context documentation. Correction of user API return values. Splitted TechnicalReference in Core and HAL part.
Martin Schultheiß	2020-04-21	3.01.00	Added deviation for Pre- and PostTaskHook.

Reference Documents

No.	Source	Title	Version
[1]	AUTOSAR	Specification of Operating System Document ID 034: AUTOSAR_SWS_OS	4.2.1
[2]	OSEK/VDX	OSEK/VDX Operating System Specification This document is available in PDF-format on the Internet at the OSEK/VDX homepage (http://www.osek-vdx.org)	2.2.3
[3]	OSEK/VDX	OSEK RunTime Interface (ORTI) Part A: Language Specification. This document is available in PDF-format on the Internet at the OSEK/VDX homepage (http://www.osek-vdx.org)	2.2
[4]	OSEK/VDX	OSEK Run Time Interface (ORTI) Part B: OSEK Objects and Attributes This document is available in PDF-format on the Internet at the OSEK/VDX homepage (http://www.osek-vdx.org)	2.2
[5]	Lauterbach	ORTI Representation of SMP Systems (ORTI 2.3)	4
[6]	Vector	vVIRTUALtarget Technical Reference	See delivery information
[7]	Vector	Startup with Vector and vVIRTUALtarget	See delivery information
[8]	Vector	MICROSAR VStdLib Technical Reference TechnicalReference_VstdLib_GenericAsr.pdf	See delivery information
[9]	Vector	MICROSAR OS HAL Technical Reference	See delivery information



Caution
We have configured the programs in accordance with your specifications in the questionnaire. Whereas the programs do support other configurations than the one specified in your questionnaire, Vector´s release of the programs delivered to your company is expressly restricted to the configuration you have specified in the questionnaire.

Contents

1 Component History 26

2 Introduction 27
2.1 Architecture Overview 27
2.2 Abstract 28
2.3 Characteristics 28
2.4 VTT OS 29
2.4.1 Characteristics of VTT OS 29

3 Functional Description 30
3.1 General 30
3.2 MICROSAR OS Deviations from AUTOSAR OS Specification 30
3.2.1 Generic Deviation for API Functions 30
3.2.2 Trusted Function API Deviations 30
3.2.3 Service Protection Deviation 31
3.2.4 Code Protection 31
3.2.5 SyncScheduleTable API Deviation 31
3.2.6 CheckTask/ISRMemoryAccess API Deviation 31
3.2.7 Interrupt API Deviation 32
3.2.8 Cross Core Getter APIs 32
3.2.9 IOC 32
3.2.10 Return value upon stack violation 33
3.2.11 Handling of OS internal errors 33
3.2.12 Forcible Termination of Applications 34
3.2.13 OS Configuration 34
3.2.14 Spinlocks 35
3.2.15 Errors within the PreTaskHook() and PostTaskHook() 35
3.3 Stack Concept 36
3.3.1 Task Stack Sharing 37
3.3.1.1 Description 37
3.3.1.2 Activation 38
3.3.1.3 Usage 38
3.3.2 ISR Stack Sharing 38
3.3.2.1 Description 38
3.3.2.2 Activation 38
3.3.2.3 Usage 39
3.3.3 Stack Check Strategy 39
3.3.4 Software Stack Check 39
3.3.4.1 Description 39

3.3.4.2 Activation 40
3.3.4.3 Usage 40
3.3.5 Stack Supervision by MPU 41
3.3.5.1 Description 41
3.3.5.2 Activation 41
3.3.5.3 Usage 41
3.3.6 Stack Usage Measurement 42
3.3.6.1 Description 42
3.3.6.2 Activation 42
3.3.6.3 Usage 42
3.4 Interrupt Concept 43
3.4.1 Interrupt Handling API 43
3.4.2 Interrupt Levels 43
3.4.3 Interrupt Vector Table 44
3.4.4 Nesting of Category 2 Interrupts 44
3.4.4.1 Description 44
3.4.4.2 Activation 44
3.4.5 Category 1 Interrupts 44
3.4.5.1 Implementation of Category 1 ISRs 44
3.4.5.2 Nesting of Category 1 ISRs 44
3.4.5.3 Category 1 ISRs before StartOS 45
3.4.5.4 Notes on Category 1 ISRs 45
3.4.6 Initialization of Interrupt Sources 46
3.4.7 Unhandled Interrupts 47
3.4.8 Unhandled Syscalls 47
3.5 Exception Concept 48
3.5.1 Exception Vector Table 48
3.5.2 Unhandled Exceptions 48
3.6 Timer Concept 49
3.6.1 Description 49
3.6.2 Activation 49
3.6.3 Usage 49
3.6.4 Dependencies 49
3.7 Periodical Interrupt Timer (PIT) 50
3.7.1 Description 50
3.7.2 Activation 50
3.8 High Resolution Timer (HRT) 51
3.8.1 Description 51
3.8.2 Activation 51
3.9 PIT versus HRT 51
3.10 Startup Concept 52

3.11 Single Core Startup 53
3.11.1 Single Core Derivatives 53
3.11.2 Multi Core Derivatives 53
3.11.2.1 Examples for SC1 / SC2 Systems 53
3.11.2.2 Examples for SC3 / SC4 Systems 54
3.12 Multi Core Startup 56
3.12.1 Example for SC1 / SC2 Systems 56
3.12.2 Examples for SC3 / SC4 systems 57
3.12.2.1 Only with AUTOSAR Cores 57
3.12.2.2 Mixed Core System 57
3.13 Error Handling 59
3.14 Error Reporting 59
3.14.1 Extension of Service IDs 59
3.14.2 Extension of Error Codes 60
3.14.3 Detailed Error Codes 60
3.15 Multi Core Concepts 62
3.15.1 Scheduling and Dispatching 62
3.15.2 Multi Core Data Concepts 62
3.15.3 X-Signals 62
3.15.4 Master / Slave Core 62
3.15.5 Hardware Init Core 62
3.15.6 Startup of a Multi Core System 62
3.15.7 Spinlocks 62
3.15.7.1 Linking of Spinlocks 63
3.15.8 Cache 63
3.15.9 Shutdown 63
3.15.9.1 Shutdown of one Core 63
3.15.9.2 Shutdown of all Cores 63
3.15.9.3 Shutdown during Protection Violation 63
3.16 Debugging Concepts 64
3.16.1 Description 64
3.16.2 Activation 64
3.16.3 ORTI Debugging 64
3.17 Memory Protection 66
3.17.1 Usage of the MPUs 66
3.17.2 Configuration Aspects 66
3.17.2.1 Static MPU Regions 67
3.17.2.2 Dynamic MPU Regions 67
3.17.2.3 Freedom from Interference 68
3.17.3 Stack Monitoring 68
3.17.4 Protection Violation Handling 68

3.17.5 Optimized / Fast MPU Handling ... 69
3.17.6 Recommended Configuration ... 69
3.18 Memory Access Checks ... 70
3.18.1 Description ... 70
3.18.2 Activation ... 70
3.18.3 Usage ... 70
3.18.4 Dependencies ... 70
3.19 Timing Protection Concept ... 71
3.19.1 Description ... 71
3.19.2 Activation ... 72
3.19.3 Usage ... 72
3.20 IOC ... 73
3.20.1 Description ... 73
3.20.2 Unqeued (Last Is Best) Communication ... 73
3.20.2.1 1:1 Communication Variant ... 73
3.20.2.2 N:1 Communication Variant ... 73
3.20.2.3 N:M Communication Variant ... 74
3.20.3 Queued Communication ... 74
3.20.4 Notification ... 74
3.20.5 Particularities ... 74
3.20.5.1 N:1 Queued Communication ... 74
3.20.5.2 IOC Spinlocks ... 75
3.20.5.3 Notification ... 75
3.20.5.4 Complex Data Types ... 76
3.21 Trusted OS Applications ... 77
3.21.1 Trusted OS Applications with Memory Protection ... 77
3.21.1.1 Description ... 77
3.21.1.2 Activation ... 77
3.21.1.3 Dependencies ... 77
3.21.2 Trusted OS Applications in User Mode ... 77
3.21.2.1 Description ... 77
3.21.2.2 Activation ... 77
3.21.2.3 Dependencies ... 77
3.21.3 Trusted Functions ... 78
3.22 OS Hooks ... 79
3.22.1 Runtime Context ... 79
3.22.2 Nesting behavior ... 79
3.22.3 Hints ... 79

4 Vector Specific OS Features ... 81
4.1 Optimized Spinlocks ... 81

4.1.1 Description ... 81
4.1.2 Activation ... 81
4.1.3 Usage ... 81
4.2 Barriers ... 82
4.2.1 Description ... 82
4.2.2 Activation ... 82
4.2.3 Usage ... 82
4.3 Peripheral Access API ... 84
4.3.1 Description ... 84
4.3.2 Activation ... 84
4.3.3 Usage ... 84
4.3.4 Dependencies ... 84
4.3.5 Alternatives ... 84
4.3.6 Common Use Cases ... 84
4.4 Trusted Function Call Stubs ... 85
4.4.1 Description ... 85
4.4.2 Activation ... 85
4.4.3 Usage ... 85
4.4.4 Dependencies ... 85
4.5 Non-Trusted Functions (NTF) ... 86
4.5.1 Description ... 86
4.5.2 Activation ... 86
4.5.3 Usage ... 86
4.5.4 Dependencies ... 86
4.6 Fast Trusted Functions ... 87
4.6.1 Description ... 87
4.6.2 Activation ... 87
4.6.3 Usage ... 87
4.6.4 Dependencies ... 87
4.7 Interrupt Source API ... 88
4.7.1 Description ... 88
4.8 Pre-Start Task ... 89
4.8.1 Description ... 89
4.8.2 Activation ... 89
4.8.3 Usage ... 89
4.8.4 Dependencies ... 90
4.9 X-Signals ... 91
4.9.1 Description ... 91
4.9.1.1 Notes on Synchronous X-Signals ... 93
4.9.1.2 Notes on Mixed Criticality Systems ... 93
4.9.2 Activation ... 94

4.10 Timing Hooks 95
4.10.1 Description 95
4.10.2 Activation 96
4.10.3 Usage 96
4.11 Kernel Panic 97
4.12 Generate callout stubs 98
4.12.1 Description 98
4.12.2 Activation 98
4.12.3 Usage 98
4.13 Exception Context Manipulation 99
4.13.1 Description 99
4.13.2 Usage 99
4.14 Category 0 Interrupts 100
4.14.1 Description 100
4.14.2 Usage 100
4.14.2.1 Implement Category 0 ISRs 100
4.14.2.2 Nesting of Category 0 ISRs 100
4.14.2.3 Category 0 ISRs before StartOS 100
4.14.2.4 Locations where category 0 ISRs are locked 101
4.14.3 Notes on Category 0 ISRs 101
4.15 Floating Point Context Extension 104
4.15.1 Description 104
4.15.2 Usage 104
4.16 User defined processor state 104
4.17 Interrupt Mapping 105
4.17.1 Description 105
4.17.2 Usage 105
4.18 Time Slice Scheduling 105
4.18.1 Description 105
4.18.2 Activation 105
4.18.3 Usage 105
4.18.3.1 Usage with OS resources 106

5 Integration 107
5.1 Compiler Optimization Assumptions 107
5.1.1 Compile Time 107
5.2 Hardware Software Interfaces (HSI) 107
5.3 Memory Mapping Concept 108
5.3.1 Provided MemMap Section Specifiers 108
5.3.1.1 Usage of MemMap Macros 111
5.3.1.2 Resulting sections 111

5.3.1.3 Access Rights to Variable Sections 117
5.3.1.4 Access Rights to Shared Data Sections 119
5.3.2 Link Sections 120
5.3.2.1 Pre-Process Linker Command Files 120
5.3.2.2 Simple Linker Defines 121
5.3.2.3 Hierachical Linker Defines 121
5.3.2.4 Selecting OS constants 121
5.3.2.5 Selecting OS variables 122
5.3.2.6 Selecting special OS Variables 123
5.3.2.7 Selecting User Constant Sections 124
5.3.2.8 Selecting User Variable Sections 125
5.3.3 Section Symbols 127
5.3.3.1 Aggregation of Data Sections 127
5.4 Static Code Analysis 128
5.5 Configuration of X-Signals 129
5.5.1 VTT OS 129
5.6 OS generated objects 129
5.6.1 System Application 130
5.6.2 Idle Task 130
5.6.3 Timer ISR 131
5.6.4 System Timer Counter 131
5.6.5 Timing Protection Counter 131
5.6.6 Timing protection ISR 131
5.6.7 Resource Scheduler 131
5.6.8 X-Signal ISR 132
5.6.9 IOC Spinlocks 132
5.7 VTT OS Specifics 133
5.7.1 Configuration 133
5.7.2 CANoe Interface 133
5.7.2.1 Idle Task behavior with VTT OS 133
5.8 User include files 134
5.9 Preprocessing of assembler language files 135
5.10 Stack Summary 136

6 API Description 137
6.1 Specified OS services 137
6.1.1 StartCore 137
6.1.2 StartNonAutosarCore 138
6.1.3 GetCoreID 139
6.1.4 GetNumberOfActivatedCores 140
6.1.5 GetActiveApplicationMode 141

6.1.6 StartOS 142
6.1.7 ShutdownOS 143
6.1.8 ShutdownAllCores 144
6.1.9 ControlIdle 145
6.1.10 GetSpinlock 146
6.1.11 ReleaseSpinlock 147
6.1.12 TryToGetSpinlock 148
6.1.13 DisableAllInterrupts 149
6.1.14 EnableAllInterrupts 150
6.1.15 SuspendAllInterrupts 151
6.1.16 ResumeAllInterrupts 152
6.1.17 SuspendOSInterrupts 153
6.1.18 ResumeOSInterrupts 154
6.1.19 ActivateTask 155
6.1.20 TerminateTask 156
6.1.21 ChainTask 157
6.1.22 Schedule 158
6.1.23 GetTaskID 159
6.1.24 GetTaskState 160
6.1.25 GetISRID 161
6.1.26 SetEvent 162
6.1.27 ClearEvent 163
6.1.28 GetEvent 164
6.1.29 WaitEvent 165
6.1.30 IncrementCounter 166
6.1.31 GetCounterValue 167
6.1.32 GetElapsedValue 168
6.1.33 GetAlarmBase 169
6.1.34 GetAlarm 170
6.1.35 SetRelAlarm 171
6.1.36 SetAbsAlarm 172
6.1.37 CancelAlarm 173
6.1.38 GetResource 174
6.1.39 ReleaseResource 175
6.1.40 StartScheduleTableRel 176
6.1.41 StartScheduleTableAbs 177
6.1.42 StopScheduleTable 178
6.1.43 NextScheduleTable 179
6.1.44 GetScheduleTableStatus 180
6.1.45 StartScheduleTableSynchron 181
6.1.46 SyncScheduleTable 182

6.1.47 SetScheduleTableAsync 183
6.1.48 GetApplicationID 184
6.1.49 GetCurrentApplicationID 185
6.1.50 GetApplicationState 186
6.1.51 CheckObjectAccess 187
6.1.52 CheckObjectOwnership 188
6.1.53 AllowAccess 189
6.1.54 TerminateApplication 190
6.1.55 CallTrustedFunction 191
6.1.56 Check Task Memory Access 192
6.1.57 Check ISR Memory Access 193
6.1.58 OSErrorGetServiceId 194
6.1.59 OSError_Os_DisableInterruptSource_ISRID 195
6.1.60 OSError_Os_EnableInterruptSource_ISRID 195
6.1.61 OSError_Os_EnableInterruptSource_ClearPending 196
6.1.62 OSError_Os_ClearPendingInterrupt_ISRID 196
6.1.63 OSError_Os_IsInterruptSourceEnabled_ISRID 197
6.1.64 OSError_Os_IsInterruptSourceEnabled_IsEnabled 197
6.1.65 OSError_Os_IsInterruptPending_ISRID 198
6.1.66 OSError_Os_IsInterruptPending_IsPending 198
6.1.67 OSError_CallTrustedFunction_FunctionIndex 199
6.1.68 OSError_CallTrustedFunction_FunctionParams 199
6.1.69 OSError_CallNonTrustedFunction_FunctionIndex 200
6.1.70 OSError_CallNonTrustedFunction_FunctionParams 200
6.1.71 OSError_StartScheduleTableRel_ScheduleTableID 201
6.1.72 OSError_StartScheduleTableRel_Offset 201
6.1.73 OSError_StartScheduleTableAbs_ScheduleTableID 202
6.1.74 OSError_StartScheduleTableAbs_Start 202
6.1.75 OSError_StopScheduleTable_ScheduleTableID 203
6.1.76 OSError_NextScheduleTable_ScheduleTableID_From 203
6.1.77 OSError_NextScheduleTable_ScheduleTableID_To 204
6.1.78 OSError_StartScheduleTableSynchron_ScheduleTableID 204
6.1.79 OSError_SyncScheduleTable_ScheduleTableID 205
6.1.80 OSError_SyncScheduleTable_Value 205
6.1.81 OSError_SetScheduleTableAsync_ScheduleTableID 206
6.1.82 OSError_GetScheduleTableStatus_ScheduleTableID 206
6.1.83 OSError_GetScheduleTableStatus_ScheduleStatus 207
6.1.84 OSError_IncrementCounter_CounterID 207
6.1.85 OSError_GetCounterValue_CounterID 208
6.1.86 OSError_GetCounterValue_Value 209
6.1.87 OSError_GetElapsedValue_CounterID 209

6.1.88 OSError_GetElapsedValue_Value 210
6.1.89 OSError_GetElapsedValue_ElapsedValue 210
6.1.90 OSError_TerminateApplication_Application 211
6.1.91 OSError_TerminateApplication_RestartOption 211
6.1.92 OSError_GetApplicationState_Application 212
6.1.93 OSError_GetApplicationState_Value 212
6.1.94 OSError_GetSpinlock_SpinlockId 213
6.1.95 OSError_ReleaseSpinlock_SpinlockId 213
6.1.96 OSError_TryToGetSpinlock_SpinlockId 214
6.1.97 OSError_TryToGetSpinlock_Success 214
6.1.98 OSError_ControlIdle_CoreID 215
6.1.99 OSError_Os_GetExceptionContext_Context 215
6.1.100 OSError_Os_SetExceptionContext_Context 216
6.1.101 OSError_ControlIdle_IdleMode 216
6.1.102 OSError_IocSend_IN 217
6.1.103 OSError_IocWrite_IN 217
6.1.104 OSError_IocSendGroup_IN 218
6.1.105 OSError_IocWriteGroup_IN 218
6.1.106 OSError_IocReceive_OUT 219
6.1.107 OSError_IocRead_OUT 219
6.1.108 OSError_IocReceiveGroup_OUT 220
6.1.109 OSError_IocReadGroup_OUT 220
6.1.110 OSError_StartOS_Mode 221
6.1.111 OSError_ActivateTask_TaskID 221
6.1.112 OSError_ChainTask_TaskID 222
6.1.113 OSError_GetTaskID_TaskID 222
6.1.114 OSError_GetTaskState_TaskID 223
6.1.115 OSError_GetTaskState_State 223
6.1.116 OSError_SetEvent_TaskID 224
6.1.117 OSError_SetEvent_Mask 224
6.1.118 OSError_ClearEvent_Mask 225
6.1.119 OSError_GetEvent_TaskID 225
6.1.120 OSError_GetEvent_Mask 226
6.1.121 OSError_WaitEvent_Mask 226
6.1.122 OSError_GetAlarmBase_AlarmID 227
6.1.123 OSError_GetAlarmBase_Info 227
6.1.124 OSError_GetAlarm_AlarmID 228
6.1.125 OSError_GetAlarm_Tick 228
6.1.126 OSError_SetRelAlarm_AlarmID 229
6.1.127 OSError_SetRelAlarm_increment 229
6.1.128 OSError_SetRelAlarm_cycle 230

6.1.129 OSError_SetAbsAlarm_AlarmID 230
6.1.130 OSError_SetAbsAlarm_start 231
6.1.131 OSError_SetAbsAlarm_cycle 231
6.1.132 OSError_CancelAlarm_AlarmID 232
6.1.133 OSError_GetResource_ResID 232
6.1.134 OSError_ReleaseResource_ResID 233
6.1.135 OSError_Os_GetUnhandledIrq_InterruptSource 233
6.1.136 OSError_Os_GetUnhandledExc_ExceptionSource 234
6.1.137 OSError_BarrierSynchronize_BarrierID 234
6.2 Additional OS services 235
6.2.1 Os_GetVersionInfo 235
6.2.2 Peripheral Access API 236
6.2.2.1 Read Functions 236
6.2.2.2 Write Functions 238
6.2.2.3 Bitmask Functions 240
6.2.3 Pre-Start Task 242
6.2.4 Non-Trusted Functions (NTF) 243
6.2.5 Fast Trusted Functions 244
6.2.6 Interrupt Source API 245
6.2.6.1 Disable Interrupt Source 245
6.2.6.2 Enable Interrupt Source 246
6.2.6.3 Clear Pending Interrupt 247
6.2.6.4 Check Interrupt Source Enabled 248
6.2.6.5 Check Interrupt Pending 249
6.2.6.6 Initial Enable Interrupt Sources 250
6.2.7 Detailed Error API 251
6.2.7.1 Get detailed Error 251
6.2.7.2 Unhandled Interrupt Requests 252
6.2.7.3 Unhandled Exception Requests 253
6.2.8 Stack Usage API 254
6.2.9 RTE Interrupt API 255
6.2.10 Time Conversion Macros 256
6.2.10.1 Convert from Time into Counter Ticks 256
6.2.10.2 Convert from Counter Ticks into Time 256
6.2.11 OS Initialization 257
6.2.12 Timing Hooks 258
6.2.12.1 Timing Hooks for Activation and Termination 258
6.2.12.1.1 Task Activation 258
6.2.12.1.2 Task Activation Exeeding Limit 259
6.2.12.1.3 Set Event 259
6.2.12.1.4 Wait Event Not Waiting 260

6.2.12.1.5 Timing Hook for Context Switch 261
6.2.12.1.6 Forcible Termination 262
6.2.12.2 Timing Hooks for Locking Purposes 262
6.2.12.2.1 Get Resource 262
6.2.12.2.2 Release Resource 263
6.2.12.2.3 Request Spinlock 264
6.2.12.2.4 Request Internal Spinlock 264
6.2.12.2.5 Get Spinlock 265
6.2.12.2.6 Get Internal Spinlock 265
6.2.12.2.7 Release Spinlock 266
6.2.12.2.8 Release Internal Spinlock 266
6.2.12.2.9 Disable Interrupts 267
6.2.12.2.10 Enable Interrupts 268
6.2.13 PanicHook 269
6.2.14 Barriers 270
6.2.15 Exception Context Manipulation 271
6.2.15.1 Os_GetExceptionContext 271
6.2.15.2 Os_SetExceptionContext 272
6.2.16 Os_GetCoreStartState 273

7 Configuration 275

8 Glossary 276

9 Contact 277

Illustrations

Figure 2-1 AUTOSAR Architecture Overview ... 27
Figure 3-1 Stack Safety Gap ... 42
Figure 3-2 Interrupt Lock Levels ... 43
Figure 3-3 API functions during startup ... 52
Figure 3-4 MICROSAR OS Detailed Error Code ... 61
Figure 3-5 N:1 Multiple Sender Queues ... 75
Figure 4-1 Barriers ... 83
Figure 4-2 X-Signal ... 91
Figure 4-3 Usage of manipulating exception context ... 99

Tables

Table 1-1 Component history ... 26
Table 2-1 MICROSAR OS Characteristics ... 28
Table 2-2 VTT OS characteristics ... 29
Table 3-1 MICROSAR OS Stack Types ... 37
Table 3-2 Stack Check Patterns ... 39
Table 3-3 PIT versus HRT ... 51
Table 3-4 Types of OS Errors ... 59
Table 3-5 Extension of Error Codes ... 60
Table 3-6 Linking of spinlocks ... 63
Table 3-7 Recommended Configuration MPU Access Rights ... 69
Table 4-1 Differences of OS and Optimized Spinlocks ... 81
Table 4-2 Comparison between Synchronous and Asynchronous X-Signal ... 92
Table 4-3 Priority of X-Signal receiver ISR ... 93
Table 5-1 Provided MemMap Section Specifiers ... 110
Table 5-2 MemMap Code Sections Descriptions ... 111
Table 5-3 MemMap Callout Code Sections Descriptions ... 111
Table 5-4 MemMap Const Sections Descriptions ... 112
Table 5-5 MemMap Variable Sections Descriptions ... 115
Table 5-6 MemMap Variable Stack Sections Descriptions ... 116
Table 5-7 Recommended Section Access Rights ... 118
Table 5-8 Recommended Shared Data Section Access Rights ... 119
Table 5-9 Recommended Shared Data Section Core Access Rights ... 119
Table 5-10 List of Generated Linker Command Files ... 120
Table 5-11 OS constants linker define group ... 121
Table 5-12 OS variables linker define group ... 122
Table 5-13 OS Barriers and Core status linker define group ... 123
Table 5-14 User constants linker define group ... 124
Table 5-15 User variables linker define group ... 125
Table 6-1 StartCore ... 137
Table 6-2 StartNonAutosarCore ... 138
Table 6-3 GetCoreID ... 139
Table 6-4 GetNumberOfActivatedCores ... 140
Table 6-5 GetActiveApplicationMode ... 141
Table 6-6 StartOS ... 142
Table 6-7 ShutdownOS ... 143
Table 6-8 ShutdownAllCores ... 144
Table 6-9 ControlIdle ... 145
Table 6-10 GetSpinlock ... 146
Table 6-11 ReleaseSpinlock ... 147

Table 6-12 TryToGetSpinlock 148
Table 6-13 DisableAllInterrupts 149
Table 6-14 EnableAllInterrupts 150
Table 6-15 SuspendAllInterrupts 151
Table 6-16 ResumeAllInterrupts 152
Table 6-17 SuspendOSInterrupts 153
Table 6-18 ResumeOSInterrupts 154
Table 6-19 ActivateTask 155
Table 6-20 TerminateTask 156
Table 6-21 ChainTask 157
Table 6-22 Schedule 158
Table 6-23 GetTaskID 159
Table 6-24 GetTaskState 160
Table 6-25 GetISRID 161
Table 6-26 SetEvent 162
Table 6-27 ClearEvent 163
Table 6-28 GetEvent 164
Table 6-29 WaitEvent 165
Table 6-30 IncrementCounter 166
Table 6-31 GetCounterValue 167
Table 6-32 GetElapsedValue 168
Table 6-33 GetAlarmBase 169
Table 6-34 GetAlarm 170
Table 6-35 SetRelAlarm 171
Table 6-36 SetAbsAlarm 172
Table 6-37 CancelAlarm 173
Table 6-38 GetResource 174
Table 6-39 ReleaseResource 175
Table 6-40 StartScheduleTableRel 176
Table 6-41 StartScheduleTableAbs 177
Table 6-42 StopScheduleTable 178
Table 6-43 NextScheduleTable 179
Table 6-44 GetScheduleTableStatus 180
Table 6-45 StartScheduleTableSynchron 181
Table 6-46 SyncScheduleTable 182
Table 6-47 SetScheduleTableAsync 183
Table 6-48 GetApplicationID 184
Table 6-49 GetCurrentApplicationID 185
Table 6-50 GetApplicationState 186
Table 6-51 CheckObjectAccess 187
Table 6-52 CheckObjectOwnership 188
Table 6-53 AllowAccess 189
Table 6-54 TerminateApplication 190
Table 6-55 CallTrustedFunction 191
Table 6-56 API Service CheckTaskMemoryAccess 192
Table 6-57 API Service CheckISRMemoryAccess 193
Table 6-58 OSErrorGetServiceId 194
Table 6-59 OSError_Os_DisableInterruptSource_ISRID 195
Table 6-60 OSError_Os_EnableInterruptSource_ISRID 195
Table 6-61 OSError_Os_EnableInterruptSource_ClearPending 196
Table 6-62 OSError_Os_ClearPendingInterrupt_ISRID 196
Table 6-63 OSError_Os_IsInterruptSourceEnabled_ISRID 197
Table 6-64 OSError_Os_IsInterruptSourceEnabled_IsEnabled 197
Table 6-65 OSError_Os_IsInterruptPending_ISRID 198

Table 6-66 OSError_Os_IsInterruptPending_IsPending 198
Table 6-67 OSError_CallTrustedFunction_FunctionIndex 199
Table 6-68 OSError_CallTrustedFunction_FunctionParams 199
Table 6-69 OSError_CallNonTrustedFunction_FunctionIndex 200
Table 6-70 OSError_CallNonTrustedFunction_FunctionParams 200
Table 6-71 OSError_StartScheduleTableRel_ScheduleTableID 201
Table 6-72 OSError_StartScheduleTableRel_Offset 201
Table 6-73 OSError_StartScheduleTableAbs_ScheduleTableID 202
Table 6-74 OSError_StartScheduleTableAbs_Start 202
Table 6-75 OSError_StopScheduleTable_ScheduleTableID 203
Table 6-76 OSError_NextScheduleTable_ScheduleTableID_From 203
Table 6-77 OSError_NextScheduleTable_ScheduleTableID_To 204
Table 6-78 OSError_StartScheduleTableSynchron_ScheduleTableID 204
Table 6-79 OSError_SyncScheduleTable_ScheduleTableID 205
Table 6-80 OSError_SyncScheduleTable_Value 205
Table 6-81 OSError_SetScheduleTableAsync_ScheduleTableID 206
Table 6-82 OSError_GetScheduleTableStatus_ScheduleTableID 206
Table 6-83 OSError_GetScheduleTableStatus_ScheduleStatus 207
Table 6-84 OSError_IncrementCounter_CounterID 207
Table 6-85 OSError_GetCounterValue_CounterID 208
Table 6-86 OSError_GetCounterValue_Value 209
Table 6-87 OSError_GetElapsedValue_CounterID 209
Table 6-88 OSError_GetElapsedValue_Value 210
Table 6-89 OSError_GetElapsedValue_ElapsedValue 210
Table 6-90 OSError_TerminateApplication_Application 211
Table 6-91 OSError_TerminateApplication_RestartOption 211
Table 6-92 OSError_GetApplicationState_Application 212
Table 6-93 OSError_GetApplicationState_Value 212
Table 6-94 OSError_GetSpinlock_SpinlockId 213
Table 6-95 OSError_ReleaseSpinlock_SpinlockId 213
Table 6-96 OSError_TryToGetSpinlock_SpinlockId 214
Table 6-97 OSError_TryToGetSpinlock_Success 214
Table 6-98 OSError_ControlIdle_CoreID 215
Table 6-99 OSError_Os_GetExceptionContext_Context 215
Table 6-100 OSError_Os_SetExceptionContext_Context 216
Table 6-101 OSError_ControlIdle_IdleMode 216
Table 6-102 OSError_IocSend_IN 217
Table 6-103 OSError_IocWrite_IN 217
Table 6-104 OSError_IocSendGroup_IN 218
Table 6-105 OSError_IocWriteGroup_IN 218
Table 6-106 OSError_IocReceive_OUT 219
Table 6-107 OSError_IocRead_OUT 219
Table 6-108 OSError_IocReceiveGroup_OUT 220
Table 6-109 OSError_IocReadGroup_OUT 220
Table 6-110 OSError_StartOS_Mode 221
Table 6-111 OSError_ActivateTask_TaskID 221
Table 6-112 OSError_ChainTask_TaskID 222
Table 6-113 OSError_GetTaskID_TaskID 222
Table 6-114 OSError_GetTaskState_TaskID 223
Table 6-115 OSError_GetTaskState_State 223
Table 6-116 OSError_SetEvent_TaskID 224
Table 6-117 OSError_SetEvent_Mask 224
Table 6-118 OSError_ClearEvent_Mask 225
Table 6-119 OSError_GetEvent_TaskID 225

Table 6-120 OSError_GetEvent_Mask 226
Table 6-121 OSError_WaitEvent_Mask 226
Table 6-122 OSError_GetAlarmBase_AlarmID 227
Table 6-123 OSError_GetAlarmBase_Info 227
Table 6-124 OSError_GetAlarm_AlarmID 228
Table 6-125 OSError_GetAlarm_Tick 228
Table 6-126 OSError_SetRelAlarm_AlarmID 229
Table 6-127 OSError_SetRelAlarm_increment 229
Table 6-128 OSError_SetRelAlarm_cycle 230
Table 6-129 OSError_SetAbsAlarm_AlarmID 230
Table 6-130 OSError_SetAbsAlarm_start 231
Table 6-131 OSError_SetAbsAlarm_cycle 231
Table 6-132 OSError_CancelAlarm_AlarmID 232
Table 6-133 OSError_GetResource_ResID 232
Table 6-134 OSError_ReleaseResource_ResID 233
Table 6-135 OSError_Os_GetUnhandledIrq_InterruptSource 233
Table 6-136 OSError_Os_GetUnhandledExc_ExceptionSource 234
Table 6-137 OSError_BarrierSynchronize_BarrierID 234
Table 6-138 Os_GetVersionInfo 235
Table 6-139 Read Peripheral API 236
Table 6-140 Write Peripheral APIs 238
Table 6-141 Bitmask Peripheral API 241
Table 6-142 API Service Os_EnterPreStartTask 242
Table 6-143 Call Non-Trusted Function API 243
Table 6-144 API Service Os_DisableInterruptSource 245
Table 6-145 API Service Os_EnableInterruptSource 246
Table 6-146 API Service Os_ClearPendingInterrupt 247
Table 6-147 API Service Os_IsInterruptSourceEnabled 248
Table 6-148 API Service Os_IsInterruptPending 249
Table 6-149 API Service Os_InitialEnableInterruptSources 250
Table 6-150 API Service Os_GetDetailedError 251
Table 6-151 API Service Os_GetUnhandledIrq 252
Table 6-152 API Service Os_GetUnhandledExc 253
Table 6-153 Overview: Stack Usage Functions 254
Table 6-154 Conversion Macros from Time to Counter Ticks 256
Table 6-155 Conversion Macros from Counter Ticks to Time 256
Table 6-156 API Service Os_Init 257
Table 6-157 API Service Os_InitMemory 257
Table 6-158 Barriers 270
Table 6-159 Os_GetExceptionContext 271
Table 6-160 Os_SetExceptionContext 272
Table 6-161 Os_GetCoreStartState 273
Table 6-162 Calling Context Overview 274

1 Component History

The component history gives an overview over the important milestones that are supported in the different versions of the component.

Component Version	New Features
2.00.00	Feature “Fast Trusted Functions” added.
2.06.00	Added support for exception context manipulation.
2.08.00	Added support for category 0 ISRs.
2.14.00	New vector timing hooks OS_VTHACTIVATION_LIMIT and OS_VTH_WAITEVENT_NOWAIT.
2.17.00	Hardware FPU context saving configurable.
2.18.00	Support for user configurable core status flags.
2.31.00	Added OS API Os_InitialEnableInterruptSources().
2.37.00	Feature “User configurable OS Barriers” added.
2.38.00	Added OS API Os_ GetCoreStartState().

Table 1-1 Component history

2 Introduction

This document describes the usage and functions of “MICROSAR OS”, an operating system which implements the AUTOSAR BSW module “OS” as specified in [1]. An overview of the supported hardware as well as platform specific details and restrictions can be found in [9].

This documentation assumes that the reader is familiar with both the OSEK OS[1] specification and the AUTOSAR OS specification.

2.1 Architecture Overview

The following figure shows the location of the OS module within the AUTOSAR architecture.




Figure 2-1 AUTOSAR Architecture Overview

[1] OSEK is a registered trademark of Continental Automotive GmbH (until 2007: Siemens AG)

2.2 Abstract

The MICROSAR OS operating system is a real time operating system, which was specified for the usage in electronic control.

As a requirement, there is no dynamic creation of new tasks at runtime; all tasks have to be defined before compilation (pre-compile configuration variant).

The OS has no dynamic memory management and there is no shell for the control of tasks by hand.

Typically the source and configuration files of the operating system and the application source files are compiled and linked together to one executable file, which is loaded into an emulator or is burned into an EPROM or Flash EEPROM.

2.3 Characteristics

MICROSAR OS has the following characteristics:

Supported Scalability Classes	SC1, SC2, SC3, SC4 (as described in [1])
Single Core ECUs	Supported
Multi Core ECUs	Supported
IOC	Supported

Table 2-1 MICROSAR OS Characteristics

MICROSAR OS supports various different processor families of different vendors in conjunction with multiple compilers.

The availability for a particular processor in conjunction with a specific compiler can be queried from Vector Informatik.

2.4 VTT OS

VTT OS stands for “vVIRTUALtarget Operating System”. It runs within Vectors CANoe development tool.

Vectors CANoe is capable of simulating an entire ECU network. Within such a simulated network the OS of each ECU can be simulated.

This is useful in early ECU development phases when no real hardware is available yet. Application development can be started at once.

The VTT OS behaves as regular AUTOSAR OS. All OS objects (e.g. tasks or ISRs) are simulated.

The VTT system is described in [6].

2.4.1 Characteristics of VTT OS

Supported Scalability Classes	SC1, SC2
Single Core ECUs	Supported
Multi Core ECUs	Up to 32 cores are supported
IOC	Supported
Number of Simulated Interrupt Sources	Up to 10000
Simulated Interrupt Levels	VTT OS allows interrupt levels from 1 .. 200 Whereas 1 is the lowest priority and 200 is the highest.
Memory Protection	Not supported[2]
Stack Protection	Not supported
Stack Usage Measurement	Not supported
Stack Sharing	Not supported

Table 2-2 VTT OS characteristics

[2] The memory protection can be configured. However the actual protection mechanism is not executed.

3 Functional Description

3.1 General

The MICROSAR OS basically implements the OS according to the AUTOSAR OS standard referred in [1].

It is possible that MICROSAR OS deviates from specified AUTOSAR OS behavior. All deviations from the standard are listed in the chapters hereafter.

On the other hand MICROSAR OS extends the AUTOSAR OS standard with numerous functions. These extensions in function are described in detail in chapter 3.21.1.

3.2 MICROSAR OS Deviations from AUTOSAR OS Specification

3.2.1 Generic Deviation for API Functions

Specified Behavior	There are some API functions which are only available within specific scalability classes (e.g. TerminateApplication() in SC3 and SC4 only).
Deviation Description	Within the MICROSAR OS all API functions are always available.
Deviation Reason	The static OS code gets more simplified for better maintainability (less pre-processor statements are necessary). Modern toolchains will remove unused function automatically.

3.2.2 Trusted Function API Deviations

Specified Behavior	The Operating System shall not schedule any other Tasks which belong to the same OS-Application as the non-trusted caller of the service. Also interrupts of Category 2 which belong to the same OS-Application shall be disabled during the execution of the service.
Deviation Description	In MICROSAR OS the re-scheduling of tasks in this particular case is not suppressed. The selective disabling of category 2 ISRs is also not done.
Deviation Reason	For a better runtime performance during trusted function calls the specified behavior is not implemented in MICROSAR OS. Data consistency problems can be solved in a more efficient way by using the OS interrupt API and/or OS resource API.

Specified Behavior	All specified OS APIs should be called with interrupts enabled. In case CallTrustedFunction() API is called with disabled interrupts it returns the status code E_OS_DISABLEDINT.
Deviation Description	In MICROSAR OS this limitation does not exist. It is allowed to call CallTrustedFunction() API with disabled interrupts. There is no error check. The return value E_OS_DISABLEDINT is not possible.
Deviation Reason	It offers the possibility to call CallTrustedFunction() API where interrupts may be disabled. This is more convenient and reasonable.

3.2.3 Service Protection Deviation

Specified Behavior	If an invalid address (address is not writable by this OS-Application) is passed as an out-parameter to an Operating System service, the Operating System module shall return the status code E_OS_ILLEGAL_ADDRESS.
Deviation Description	The validity of out-parameters is checked automatically by the MPU. Write accesses to such parameters are always done with the accessing rights of the caller of the OS service. If the address is invalid a MPU exception is raised. The return value E_OS_ILLEGAL_ADDRESS is not possible.
Deviation Reason	Hardware checks by the MPU are much more performant than software memory checks.

3.2.4 Code Protection

Specified Behavior	The Operating System module may provide an OS-Application the ability to protect its code sections against executing by non-trusted OS-Applications.
Deviation Description	The MICROSAR OS does not support code section protection.
Deviation Reason	Design decision.

3.2.5 SyncScheduleTable API Deviation

Specified Behavior	All specified OS APIs should be called with interrupts enabled. In case SyncScheduleTable() is called with disabled interrupts it returns the status code E_OS_DISABLEDINT.
Deviation Description	In MICROSAR OS this limitation does not exist. It is allowed to call SyncScheduleTable() with disabled interrupts. There is no error check. The return value E_OS_DISABLEDINT is not possible.
Deviation Reason	It offers the possibility to call SyncScheduleTable() where interrupts may be disabled. This is more convenient and reasonable.

3.2.6 CheckTask/ISRMemoryAccess API Deviation

Specified Behavior	All specified OS APIs should be called with interrupts enabled. In case one of these APIs is called with disabled interrupts it issues the error E_OS_DISABLEDINT.
Deviation Description	In MICROSAR OS this limitation does not exist. It is allowed to call these API functions with disabled interrupts. There is no error check. The return value E_OS_DISABLEDINT is not possible.
Deviation Reason	It offers the possibility to call these functions e.g. from hardware drivers where interrupts may be disabled. This is more convenient and reasonable.

Specified Behavior	The API functions CheckTask/ISRMemoryAccess() are only allowed within specific OS call contexts (Task/Cat2 ISR/ErrorHook/ProtectionHook) In case one of these APIs is called within the wrong OS call context it issues the error E_OS_CALLEVEL.
Deviation Description	In MICROSAR OS In MICROSAR OS this limitation does not exist. It is allowed to call these API functions from all OS contexts. The return value E_OS_CALLEVEL is not possible.
Deviation Reason	Practically it is more reasonable to allow these APIs in all OS runtime contexts.

3.2.7 Interrupt API Deviation

Specified Behavior	The API functions SuspendOSInterrupts() and ResumeOSInterrupts() are allowed within a category 1 ISR
Deviation Description	In MICROSAR OS it is not allowed to use SuspendOSInterrupts() and ResumeOSInterrupts() within a category 1 ISR.
Deviation Reason	The function SuspendOSInterrupts() lowers the current interrupt level when used in a category 1 ISR. This may lead to data inconsistencies if another category 1 ISR occurs. Therefore those functions are not allowed.

3.2.8 Cross Core Getter APIs

Specified Behavior	All getter APIs (e.g. GetTaskID()) may be called cross core within hooks and non nestable category 2 ISRs.
Deviation Description	MICROSAR OS does not allow usage of those functions within OS Hooks and non-nestable category 2 ISRs.
Deviation Reason	Deadlock avoidance due to disabled interrupts in case that there are two simultaneous concurrent usages of those APIs from multiple cores.

3.2.9 IOC

Specified Behavior	IocSend/IocWrite APIs have an IN parameter. The parameter will be passed by value for primitive data elements and by reference for all other types. The data type is configured in “OsIocDataTypeRef”.
Deviation Description	The configurator does not evaluate information in “OsIocDataTypeRef”. Instead it evaluates the parameter “OsIocDataType“. Primitive data types are passed by value. The configurator identifies all primitive AUTOSAR and OS data types (e.g. “uint8”, “sint32”, “TaskType”). All other data types are passed by reference.
Deviation Reason	Usage of “OsIocDataType” reduces dependencies and complexity of the OS configurator.

Specified Behavior	The configuration parameter “OsIocInitValue” is specified to be an initialization value.
Deviation Description	If the used data is of a complex type the configuration parameter “OsIocInitValue” holds the name of a constant, which contains the initialization value. For integral types it can hold a value or the name of a constant containing the value.
Deviation Reason	It enables the OS to initialize complex data types.

3.2.10 Return value upon stack violation

Specified Behavior	If a stack fault is detected by stack monitoring AND no ProtectionHook is configured, the Operating System module shall call the ShutdownOS() service with the status E_OS_STACKFAULT.
Deviation Description	Within a SC3 / SC4 system with MPU stack supervision: If a stack fault is detected by stack monitoring AND no ProtectionHook is configured, the Operating System module shall call the ShutdownOS() service with the status E_OS_PROTECTION_MEMORY.
Deviation Reason	With hardware stack supervision MICROSAR OS is not possible to distinguish between stack violation and other memory violation

Specified Behavior	If a stack fault is detected by stack monitoring AND a ProtectionHook is configured the Operating System module shall call the ProtectionHook() with the status E_OS_STACKFAULT.
Deviation Description	Within a SC3 / SC4 system with MPU stack supervision: If a stack fault is detected by stack monitoring AND a ProtectionHook is configured the Operating System module shall call the ProtectionHook() with the status E_OS_PROTECTION_MEMORY.
Deviation Reason	With hardware stack supervision MICROSAR OS is not possible to distinguish between stack violation and other memory violation

3.2.11 Handling of OS internal errors

Specified Behavior	In cases where the OS detects a fatal internal error all cores shall be shut down.
Deviation Description	In case that the OS detects an internal error the kernel panic mode is entered.
Deviation Reason	In case of OS internal errors normal operations (e.g. calling the protection hook) are possible no more, as the OS is in an inconsistent state.

3.2.12 Forcible Termination of Applications

Specified Behavior	AUTOSAR does not specify the handling of “next” schedule tables in case of forcible termination of applications.
Deviation Description	Use case: An application has a running schedule table which itself has a nexted schedule table of a foreign application. The foreign application is forcibly terminated. The OS removes the “next” request from the running schedule table.
Deviation Reason	Clarification of behavior. Impact on other applications should be minimal, therefore the current schedule table is not stopped. This is different to the behavior of StopScheduleTable().

Specified Behavior	AUTOSAR does not specify the handling of “next” schedule tables in case of forcible termination of applications.
Deviation Description	Use case: An application has a running schedule table which itself has a nexted schedule table of a foreign application. The first application is forcibly terminated. The OS stops the current schedule table of the terminated application. and removes the “next” request. As a result it does not switch to the “next” schedule table of the foreign application.
Deviation Reason	Clarification of behavior. Impact on other applications should be minimal. The described behavior is identical to the behavior of StopScheduleTable().

3.2.13 OS Configuration

Specified Behavior	The generator shall print out information about timers used internally by the OS during generation (e.g. on console, list file).
Deviation Description	In case of MICROSAR OS there is no such output. Instead the timer is visible to the user as any other timer during configuration.
Deviation Reason	In order to increase the transparency, OS internal objects are visible to the user during configuration time.

Specified Behavior	If ShutdownOS() is called and ShutdownHook() returns then the Operating System module shall disable all interrupts and enter an endless loop.
Deviation Description	If ShutdownOS() is called and ShutdownHook() returns then the Operating System module enters the kernel panic mode.
Deviation Reason	In case of unusual situations the MICROSAR OS enters the kernel panic mode. To keep the behaviour of the OS consistent, the kernel panic mode is also applied in case that the ShutdownHook() returns.

3.2.14 Spinlocks

Specified Behavior	The AUTOSAR Operating System shall generate an error if a TASK/ISR2 on a core, where the same or a different TASK/ISR already holds a spinlock, tries to seize another spinlock that has not been configured as a direct or indirect successor of the latest acquired spinlock (by means of the OsSpinlockSuccessor configuration parameter) or if no successor is configured.
Deviation Description	The nesting order check is only valid for a single task or ISR and if all nested spinlocks are members of the same lock order list.
Deviation Reason	By implementing this check, the user of MICROSAR OS would be enforced to ▶ either configure a single lock order list ▶ or the user would be enforced to ensure correct nesting of spinlock between tasks or ISRs of different diagnostic coverage.

3.2.15 Errors within the PreTaskHook() and PostTaskHook()

Specified Behavior	The AUTOSAR Operating System shall call the ErrorHook(), if a system service that is called within the PreTaskHook() or PostTaskHook() does not return with E_OK.
Deviation Description	In MICROSAR OS the ErrorHook() is never called within the PreTaskHook() and PostTaskHook(). The status value returned by the system service has to be evaluated by the user of MICROSAR OS to mke sure that the service has been executed.
Deviation Reason	PreTaskHook() and PostTaskHook() are implemented as callbacks during the context switch. There shall be no additional context switch to the ErrorHook() in case of an errorneous usage of the AUTOSAR APIs.

3.3 Stack Concept

MICROSAR OS implements a specific stack concept.

It defines different stacks which may be used by stack consumers (runtime contexts). Whereas not all stacks may be used by all consumers.

The following table gives an overview.

Stack Type	Multiplicity	Possible Stack Consumers
Init Stack	1 per core	> OS initialization, Os_PanicHook(), Category 0/1 ISRs
Kernel stack	1 per core	> OS memory exception handling > Os_PanicHook() > Category 0 ISRs
Protection stack	0..1 per core	> ProtectionHook() > OS API calls > Os_PanicHook() > Category 0 ISRs
Error stack	0..1 per core	> ErrorHooks (global and OS-application specific) > OS API calls > Category 0/1 ISRs > Os_PanicHook()
Shutdown stack	0..1 per core	> ShutdownHooks (global and OS-application specific) > OS API calls > Os_PanicHook() > Category 0 ISRs
Startup stack	0..1 per core	> StartupHooks (global and OS-application specific) > OS API calls > Category 0/1 ISRs > Os_PanicHook()
NTF stacks	0..n	> Non-trusted functions > OS API calls > OS ISR wrapper > Trusted functions > Alarm callback functions > Pre / PostTaskHook() > Category 0/1 ISRs > Os_PanicHook()
No nesting interrupt stack	0..1 per core	> No nesting category 2 ISRs > OS API calls > Trusted functions

		> Alarm callback functions > Category 0/1 ISRs > Os_PanicHook()
Interrupt level stacks	0..n	> Nesting category 2 ISRs > OS API calls > OS ISR wrapper > Trusted functions > Alarm callback functions > Category 0/1 ISRs > Os_PanicHook()
Task stacks	1..n	> Tasks > OS API calls > OS ISR wrapper > Trusted functions > Alarm callback functions > Pre / PostTaskHook() > Category 0/1 ISRs > Os_PanicHook()
IOC receiver pull callback stack	0..1 per core	> IOC receiver pull callback functions > Category 0 ISRs

Table 3-1 MICROSAR OS Stack Types



Note
The stack sizes of all stacks must be configured within the ECU configuration

3.3.1 Task Stack Sharing

3.3.1.1 Description

In order to save RAM it is possible that different basic tasks share the same task stack. Tasks which fulfill the following requirements share a stack:

- Basic tasks which have the same configured priority.
- Basic tasks which are non-preemptive and are configured to share stacks. Within such basic tasks the call of the OS service Schedule() is not allowed.
- Basic tasks which share an internal resource and are configured to share stacks. Within such basic tasks the call of the OS service Schedule() is not allowed.

3.3.1.2 Activation

The attribute “OsTaskStackSharing” of a basic task has to be set to TRUE. The OS decides then in dependancy of the preemption settings and assigned internal resources whether the stack of basic tasks may be shared or not.

The size of the shared task stack is the maximum of all stack sizes of tasks which share the stack.



Note

The OS activates stack sharing automatically for basic tasks with the same configured priority regardless of the value of OsTaskStackSharing.



Note

By setting “OsTaskStackSharing” to TRUE the OS API service Schedule() may not be called within the corresponding basic task.

The OS throws an error if Schedule() is called within a task with activated stack sharing.



Note

Stack sharing of tasks can only be achieved between tasks which are assigned to the same core!

3.3.1.3 Usage

Tasks which are cooperative to each other are sharing the same stack. No additional actions are necessary.

3.3.2 ISR Stack Sharing

3.3.2.1 Description

In order to save RAM it is possible that different category 2 ISRs share the same ISR stack.

> All category 2 ISRs which are not nestable can share one stack.

> All Category 2 ISRs which have the same priority can share one stack.

3.3.2.2 Activation

The attribute “OsIsrEnableNesting” must be set to FALSE for a category 2 ISR.

The size of the shared ISR stack is the maximum of all configured ISR stack sizes of non-nestable category 2 ISRs.

Note
Stack sharing of ISRs can only be achieved between ISRs which are assigned to the same core!

3.3.2.3 Usage

The feature is used automatically by the OS. All category 2 ISRs on the same core which are not nestable are sharing the same stack.

3.3.3 Stack Check Strategy

All OS stacks must be protected from overflowing.

MICROSAR OS offers different strategies to detect stack overflows or even to prevent stacks from overflowing.

In dependency of the configured scalability class there are the following strategies:

Scalability Class	Stack check strategy
SC1 / SC2	Software stack check (see 3.3.4)
SC3 / SC4	Stack supervision by memory protection unit (MPU) (see 3.3.5)

3.3.4 Software Stack Check

3.3.4.1 Description

The OS initializes the very last element of each stack to a specific stack check pattern. Whenever a stack switch is performed (e.g. a task switch) the OS checks whether this last element of the valid stack still holds the stack check pattern.

If the OS detects that the stack check pattern has been altered it assumes that the last valid stack did overflow.

	Stack Check Pattern
32-Bit Microcontrollers	0xAAAAAAAA

Table 3-2 Stack Check Patterns

Note
The software stack check is able to detect stack overflows. It is not capable to avoid them!



Caution
The software stack check is not able to detect all stack overflows. There may be scenarios where the memory of the adjacent stack is already overwritten, but the last element of the current stack still holds the stack check pattern.

In such cases the software stack check is not able to detect the overflow.



Caution
The software stack check is not able to detect the amount memory which has been destroyed.



Caution
In case of error reporting due to a stack fault (E_OS_STACK_FAULT), the API GetTaskID() might not return the ID of the causing task.

3.3.4.2 Activation

Within a SC1 or SC2 configuration the attribute “OsStackMonitoring” has to be set to TRUE to activate the software stack check feature.



Expert Knowledge
On platforms which disable the MPU in supervisor mode, the software stack check may be activated also for SC3 and SC4 configurations.

On other platforms the software stack check should be switched off in a SC3 or SC4 configuration.

3.3.4.3 Usage

Once the feature is activated the OS checks the stacks automatically upon each stack switch.

If the OS detects a stack overflow it goes into shutdown. If a ShutdownHook is configured it is invoked to inform the application about OS shutdown.



Note
Debugging hint: The stack check pattern is restored by the OS before the ShutdownHook() is called.

3.3.5 Stack Supervision by MPU

3.3.5.1 Description

During the whole runtime of the OS the current active stack is supervised by the MPU of the microcontroller. Therefore the OS reserves one MPU region which is reprogrammed by the OS with each stack switch.

Stack overflows cannot happen since the MPU avoids write accesses beyond the stack boundaries.

Whenever a memory violation is recognized (e.g. due to a stack violation) an exception is raised. Within the exception handling the OS calls the ProtectionHook().

The application decides in the ProtectionHook() how to deal with the memory protection violation. If the application invokes the shutdown of the OS, the ShutdownHook() is called as well (if configured).



Note
The stack supervision recognizes write accesses beyond stack boundaries and suppresses them.

3.3.5.2 Activation

The system must be configured as a SC3 or SC4 system.

3.3.5.3 Usage

In a SC3 / SC4 system the OS automatically initializes one MPU region for stack supervision.

To safely detect stack violations special care must be taken with configuring additional MPU regions and also with linking of sections:

- When configuring additional MPU regions included memory region must never overlap with any OS stack sections.
- By using an OS generated linker command file (see 0) it is assured that the OS stacks are linked consecutively into the RAM.
- A stack safety gap is needed which is linked adjacent to the stacks (in dependency of the stack growth direction; see Figure 3-1). No software parts must have write access to the stack safety gap.
- The size of the stack safety gap must be at least the granularity of the MPU.
- The linkage of the safety gap is mandatory. Otherwise a stack violation of the stack with the lowest address cannot be detected.




Figure 3-1 Stack Safety Gap

Caution
Don’t configure MPU regions which grant access to any OS stacks

Caution
Add a stack safety gap to the linkage scheme. The stack safety gap is a restricted memory region. No software parts must have write access to this region.

3.3.6 Stack Usage Measurement

3.3.6.1 Description

During runtime of the OS the maximum stack usage can be obtained by the application. The OS initializes all OS stacks with the stack check pattern (see Table 3-2).

There are API functions which are capable to return the maximum stack usage (since call of StartOS()) for each stack (see 6.2.8).

3.3.6.2 Activation

Set “OsStackUsageMeasurement” to TRUE

3.3.6.3 Usage

The stack usage APIs can be used anywhere in application.

Note
To save OS startup time, the feature can be deactivated in a productive environment.

3.4 Interrupt Concept

3.4.1 Interrupt Handling API

The AUTOSAR OS standard specifies several APIs to disable / enable Interrupts.

DisableAllInterrupts() EnableAllInterrupts()	The functions disable all category 1 and category 2 interrupts.
SuspendAllInterrupts() ResumeAllInterrupts()	
SuspendOSInterrupts() ResumeOSInterrupts()	The functions disable category 2 interrupts only.

3.4.2 Interrupt Levels

The OS defines several interrupt levels.




Figure 3-2 Interrupt Lock Levels

- Category 2 ISRs must have a lower priority than category 1 ISRs
- Category 1 ISRs must have a lower priority than the timing protection ISR (within an SC2 / SC4 system)
- The timing protection ISR must have a lower priority than category 0 ISRs (category 0 ISRs are described in detail in chapter 4.14)
- The TP Lock Level cannot be set by the user. Interrupts are disabled up to this level OS internally whenever timing protection is handled.
- Category 0 ISRs are disabled OS internally for very short times only e.g. when performing a stack switch (the locations where category 0 ISRs are locked can be found in chapter 3.14.2.4).

3.4.3 Interrupt Vector Table

The interrupt vector table is generated by MICROSAR OS with respect to the configuration, microcontroller family and used compiler.

In a multi core system multiple vector tables may be generated.

MICROSAR OS generates an interrupt vector for each possible interrupt source.

3.4.4 Nesting of Category 2 Interrupts

3.4.4.1 Description

To keep interrupt latency as low as possible it is possible that

- A higher priority category 2 ISR interrupts a lower priority category 2 ISR.
- A category 1 ISRs interrupts a category 2 ISR (category 1 ISR has always a higher priority)

3.4.4.2 Activation

When setting “OsIsrEnableNesting” to TRUE the category 2 ISR itself is interruptible by higher priority ISRs.

3.4.5 Category 1 Interrupts

3.4.5.1 Implementation of Category 1 ISRs

MICROSAR OS offers a macro for implementing a category 1 ISR. This is a similar mechanism like the macro for a category 2 ISR defined by the AUTOSAR standard.

MICROSAR OS abstracts the needed compiler keywords.



Implement a category 1 ISR

```
OS_ISR1(<MyCategory1ISR>)
{
}
```

3.4.5.2 Nesting of Category 1 ISRs

Since category 1 ISRs are directly called from interrupt vector table without any OS pro- and epilogue, automatic nesting of category 1 ISRs cannot be supported.

The configuration attribute “OsIsrEnableNesting” is ignored for category 1 ISRs.

Nevertheless the interrupts may be enabled during a category 1 ISR to allow interrupt nesting but OS API functions cannot be used for this purpose. The application has to use compiler intrinsic functions or inline assembler statements.



Example

```
OS ISR1(<MyCategory1ISR>)
{
   __asm(EI); /* enable nesting of this ISR */

   __asm(DI); /* disable nesting before leaving the function */
}
```

3.4.5.3 Category 1 ISRs before StartOS

There may be the need to activate and serve category 1 ISRs before the OS has been started.

The following sequence should be implemented:

1. Call Os_InitMemory()
2. Call Os_Init() (within the function the basic interrupt controller settings are initialized e.g. priorities of interrupt sources).
3. Enable the Interrupt sources of category 1 ISRs by directly manipulating the control registers in the interrupt controller.
4. Enable the interrupts by directly manipulating the global interrupt flag and / or current interrupt priority to allow the category 1 ISRs

3.4.5.4 Notes on Category 1 ISRs



Expert Knowledge

On platforms which have no automatic stack switch upon interrupt request there will be no stack switch at all if a category 1 ISR occurs. Thus the stack consumption of a category 1 ISR should be added to all stacks which are can be consumed by category 1 ISRs (see 3.2.15 for an overview).



Note

Although the interrupt priorities are initialized by MICROSAR OS there is no API to enable or acknowledge category 1 ISRs. The interrupt control registers have to be accessed directly.



Caution

The AUTOSAR OS standard does not allow OS API usage within category 1 ISRs (the only exception is the interrupt handling API).

If a not allowed OS API is called anyway, MICROSAR OS is not able to detect this and the called API may not work as expected.



Caution
Category 1 ISRs are always executed with trusted rights on supervisor level.



Caution
The macro “OS_ISR1” abstracts the appropriate compiler keyword for implementing the interrupt service routine. Thus the compiler generates code which safes and restore a subset of the general purpose registers.

In certain use cases e.g. usage of the FPU or nested interrupts it may require the application to save and restore more registers.

3.4.6 Initialization of Interrupt Sources

Through the OS configuration MICROSAR OS knows the assignment of interrupt sources and priorities to ISRs. In multi core system the core assignment of all ISRs is also known.

Based on these configuration information MICROSAR OS generates data structures for initializing the interrupt controller. It initializes the interrupt priority and its core assignment.



Note
Enabling of interrupt sources:

The OS enables the interrupt sources only for the OS generated timer ISRs.

Other user ISRs can be only be served if the corresponding interrupt sources are enabled by the application.

This should be done by using the interrupt source API (see 6.2.6 for details; function Os_EnableInterruptSource()).

3.4.7 Unhandled Interrupts

Interrupt sources which are not assigned to a user defined ISR are assigned to a default OS interrupt handler which collects those interrupt sources.

Thus interrupt requests from unassigned interrupt sources are handled by the OS. Within OS Hooks (e.g. ProtectionHook()) the application can obtain the source number of the unhandled interrupt request by an OS API (see 6.2.7.1 for details).

In case of an unhandled interrupt request which has occurred within OS code MICROSAR OS calls the PanicHook() because an inconsistent internal state is recognized and the OS does not know how to correctly continue execution.

In case of an unhandled interrupt request which has occurred within critical user sections, i.e. StartupHook, ErrorHook, PreTaskHook, PostTaskHook, Alarm callbacks, IOC receiver callbacks, Timing Hooks, ProtectionHook and ShutdownHook, MICROSAR OS calls the PanicHook() because an inconsistent internal state is recognized and the OS does not know how to correctly continue execution.

In all other cases of an unhandled interrupt request MICROSAR OS calls the ProtectionHook() with the parameter E_OS_SYS_PROTECTION_IRQ.

3.4.8 Unhandled Syscalls

Syscall sources which are not assigned to OS or user handlers are assigned to a default OS syscall handler which collects those exceptions.

Thus syscall requests from unassigned syscall sources are handled by the OS.

In case of an unhandled syscall request which has occurred within OS code MICROSAR OS calls the PanicHook() because an inconsistent internal state is recognized and the OS does not know how to correctly continue execution.

In case of an unhandled syscall request which has occurred within critical user sections, i.e. StartupHook, ErrorHook, PreTaskHook, PostTaskHook, Alarm callbacks, IOC receiver callbacks, Timing Hooks, ProtectionHook and ShutdownHook, MICROSAR OS calls the PanicHook() because an inconsistent internal state is recognized and the OS does not know how to correctly continue execution.

In all other cases of an unhandled syscall request MICROSAR OS calls the ProtectionHook() with the parameter E_OS_SYS_PROTECTION_SYSCALL.

3.5 Exception Concept

3.5.1 Exception Vector Table

The exception vector table is generated by MICROSAR OS with respect to the configuration, microcontroller family and used compiler.

In a multi core multiple vector tables may be generated.

MICROSAR OS generates an exception vector for each possible exception source.



Note
In a SC3 and SC4 system MICROSAR OS defines OS exception handlers for memory protection errors and for SYSCALL / TRAP instructions.

Exception sources which are used by the OS cannot be configured by the application.

3.5.2 Unhandled Exceptions

Exception sources which are not assigned to user defined exception handlers are assigned to a default OS exception handler which collects those exceptions.

Thus exception requests from unassigned exception sources are handled by the OS. Within OS Hooks the application can obtain the exception number of the unhandled exception request by an OS API (see 6.2.7.3 for details).

In case of an unhandled exception request which has occurred within OS code MICROSAR OS calls the PanicHook() because an inconsistent internal state is recognized and the OS does not know how to correctly continue execution.

In case of an unhandled exception request which has occurred within critical user sections, i.e. StartupHook, ErrorHook, PreTaskHook, PostTaskHook, Alarm callbacks, IOC receiver callbacks, Timing Hooks, ProtectionHook and ShutdownHook, MICROSAR OS calls the PanicHook() because an inconsistent internal state is recognized and the OS does not know how to correctly continue execution.

In all other cases of an unhandled exception request MICROSAR OS calls the ProtectionHook() with the parameter E_OS_PROTECTION_EXCEPTION.

3.6 Timer Concept

3.6.1 Description

MICROSAR OS can provide a time base generated from timer hardware located on the microcontroller. This time base can be used to drive alarms and schedule-tables.

3.6.2 Activation

The OS configuration may define an OsCounter Object of type “HARDWARE”. Then a driving hardware must be assigned to “OsDriver” attribute.

3.6.3 Usage

Once the hardware counter is defined it can be assigned to alarms (“OsAlarmCounterRef”) and schedule-tables (“OsScheduleTableCounterRef”).

Such alarms and schedule-tables are driven time based.

Additionally MICROSAR OS provides conversion macros (which are based on the hardware counter configuration) to convert from hardware ticks to time and vice versa (see for 6.2.10 details).

3.6.4 Dependencies

A hardware counter can be driven in two modes:

- Periodical interrupt timer mode (see 3.7)
- High resolution timer mode (see 3.8)

3.7 Periodical Interrupt Timer (PIT)

3.7.1 Description

The timer hardware is set up to generate timer interrupts requests in a strict periodical interval (e.g. 1ms). The interval does not change during OS runtime.

Within each timer ISR MICROSAR OS checks for alarm and schedule-table expirations and execute the configured OS action.

3.7.2 Activation

> Define an OsCounter of type “HARDWARE” and select the timer Hardware in “OsDriver”.

> Set the counter sub-attribute “OsDriverHighResolution” to FALSE.

> The attribute “OsSecondsPerTick” specifies the cycle time of interrupt generation.

> The attribute “OsCounterTicksPerBase” specifies the number of timer counter cycles which are necessary to reach “OsSecondsPerTick”.



Note
The OS will add an appropriate ISR automatically to the configuration.

3.8 High Resolution Timer (HRT)

3.8.1 Description

The timer hardware is set up to generate one timer interrupt request when an alarm or schedule-table action shall be executed.

Within each timer ISR MICROSAR OS performs that action, calculates the timer interval for the next action and reprograms the timer hardware with the new expiration time.

3.8.2 Activation

> Define an OsCounter of type “HARDWARE” and select the timer Hardware in “OsDriver”.

> Set the counter sub-attribute “OsDriverHighResolution” to TRUE.

> The attribute “OsSecondsPerTick” specifies the cycle time of the timer counter.

> The attribute “OsCounterTicksPerBase” must be set to “1”.

> The attribute “OsCounterMaxAllowedValue” must be set to 0x3FFFFFFF



Note
The OS will add an appropriate ISR automatically to the configuration.



Caution
To avoid corruption of the OS time base, the HRT ISR must not be delayed longer than a half hardware counter cycle.

For a 16 Bit hardware timer for instance, a half hardware counter cycle is the time needed to count from 0 to 0x7FFF.

3.9 PIT versus HRT

	PIT	HRT
Interrupt Requests are generated …	▶ Strictly periodical	▶ On demand
Precision of Alarms / Schedule-tables	▶ Only multiples of the attribute OsSecondsPerTick are possible for alarm / schedule-table times.	▶ Any times are possible. With precision of the cycle time of the used timer hardware.
Interrupt Load	▶ Generates a constant interrupt load which is equally distributed over runtime.	▶ Interrupt load is not equally distributed over runtime. ▶ Interrupt bursts may be possible.

Table 3-3 PIT versus HRT

3.10 Startup Concept

The following figure gives an overview of the different startup phases of the OS. It also shows which OS API functions are available in the different phases.




Figure 3-3 API functions during startup

3.11 Single Core Startup

This chapter shows some examples how MICROSAR OS is started as single core OS.

3.11.1 Single Core Derivatives



OS single core startup on a single core derivative

```
void main (void)
{
   Os_InitMemory();
   Os_Init();
   StartOS(OSDEFAULTAPPMODE);
}
```

3.11.2 Multi Core Derivatives

3.11.2.1 Examples for SC1 / SC2 Systems



OS single core startup on a multi core derivative

```
void main (void)
{
   StatusType rv;

   Os_InitMemory();
   Os_Init();

   switch(GetCoreID())
   {
      case OS_CORE_ID_MASTER:
         StartNonAutosarCore(OS_CORE_ID_1, &rv); /* call of StartNonAutosarCore is
                                                    optional the other core may also be
                                                    held in reset */
         StartOS(OSDEFAULTAPPMODE);
         break;
      case OS_CORE_ID_1:
         /* don't call StartOS; do something else */
         break;
      default:
         break;
   }
}
```

The example starts a single core OS on the master core of a multi core derivative.



OS single core startup on a multi core derivative

```
void main (void)
{
   StatusType rv;

   Os_InitMemory();
   Os_Init();

   switch(GetCoreID())
   {
      case OS_CORE_ID_MASTER:
         StartCore(OS_CORE_ID_1, &rv);
         /* don't call StartOS; do something else */
         break;
      case OS_CORE_ID_1:
         StartOS(OSDEFAULTAPPMODE);
         break;
      default:
         break;
   }
}
```

The example starts a single core OS on the slave core of a multi core derivative

3.11.2.2 Examples for SC3 / SC4 Systems



Caution

The function GetCoreID requires a trap into the OS to be functional. Since the OS does not initialize any trap tables on non-AUTOSAR cores GetCoreID cannot be used on such cores.

Therefore it is not possible to use the API function GetCoreID within the main function. A user function (e.g. UsrGetCoreID) is necessary which distinguishes the correct core ID.



OS single core startup on a multi core derivative

```
void main (void)
{
   StatusType rv;

   Os_InitMemory();
   Os_Init();

   switch(UsrGetCoreID())
   {
      case 0:
         StartNonAutosarCore(OS_CORE_ID_1, &rv); /* call of StartNonAutosarCore is
                                                    optional the other core may also be
                                                    held in reset */
         StartOS(OSDEFAULTAPPMODE);
         break;
      case 1:
         /* don't call StartOS; do something else */
         break;
      default:
         break;
   }
}
```

The example starts a single core OS on the master core of a multi core derivative.

3.12 Multi Core Startup

Within a multi core system each core has the following possibilities when entering the main function:

1. Mandatory: call to Os_InitMemory() and Os_Init().
2. Optional: calls to StartCore() to start additional cores under control of MICROSAR OS.
3. Optional: calls to StartNonAutosarCore() to start additional cores which are independent of MICROSAR OS.
4. Optional: call StartOS() to start MICROSAR OS on the core

   For a slave core this is only possible if the core once has been started with StartCore() API from another core.

   For the master core this is only possible if the core itself is configured to be an AUTOSAR core.

3.12.1 Example for SC1 / SC2 Systems



OS multi core startup

```
void main (void)
{
   StatusType rv;

   Os_InitMemory();
   Os_Init();

   switch(GetCoreID())
   {
      case OS_CORE_ID_MASTER:
         StartCore(OS_CORE_ID_1, &rv);
         StartCore(OS_CORE_ID_2, &rv);
         StartOS(OSDEFAULTAPPMODE);
         break;
      case  OS_CORE_ID_1:
         StartOS(DONOTCARE);
         break;
      case  OS_CORE_ID_2:
         StartCore(OS_CORE_ID_3, &rv);
         StartOS(DONOTCARE);
         break;
      case  OS_CORE_ID_3:
         StartOS(DONOTCARE);
         break;
      default:
         break;
   }
}
```

The example shows a possible startup sequence for a quad core system.

3.12.2 Examples for SC3 / SC4 systems

3.12.2.1 Only with AUTOSAR Cores



OS multi core startup

```
void main (void)
{
   StatusType rv;

   Os_InitMemory();
   Os_Init();

   switch(GetCoreID())
   {
      case OS_CORE_ID_MASTER:
         StartCore(OS_CORE_ID_1, &rv);
         StartCore(OS_CORE_ID_2, &rv);
         StartOS(OSDEFAULTAPPMODE);
         break;
      case  OS_CORE_ID_1:
         StartOS(DONOTCARE);
         break;
      case  OS_CORE_ID_2:
         StartCore(OS_CORE_ID_3, &rv);
         StartOS(DONOTCARE);
         break;
      case  OS_CORE_ID_3:
         StartOS(DONOTCARE);
         break;
      default:
         break;
   }
}
```

The example shows a possible startup sequence for a quad core system. All cores are configured to be AUTOSAR cores.

3.12.2.2 Mixed Core System



Caution

The function GetCoreID requires a trap into the OS to be functional. Since the OS does not initialize any trap tables on non-AUTOSAR cores GetCoreID cannot be used on such cores.

Therefore it is not possible to use the API function GetCoreID within the main function. A user function (e.g. UsrGetCoreID) is necessary which distinguishes the correct core ID.



OS multi core startup

```
void main (void)
{
   StatusType rv;

   Os_InitMemory();
   Os_Init();

   switch(UsrGetCoreID())
   {
      case 0:
         StartNonAutosarCore(OS_CORE_ID_1, &rv);
         StartCore(OS_CORE_ID_2, &rv);
         StartOS(OSDEFAULTAPPMODE);
         break;
      case 1:
         /* not an AUTOSAR core; do something else */
         break;
      case 2:
         StartCore(OS_CORE_ID_3, &rv);
         StartOS(DONOTCARE);
         break;
      case 3:
         StartOS(DONOTCARE);
         break;
      default:
         break;
   }
}
```

The example shows a possible startup sequence for a quad core system. Three cores are AUTOSAR cores and one core is a non-AUTOSAR core.

3.13 Error Handling

MICROSAR OS is able to detect and handle the following types of errors:

Application Errors …	▶ Are raised if the OS could not execute a requested OS API service correctly. Typically the OS API is used wrong (e.g. invalid object ID). ▶ Do not corrupt OS internal data. ▶ Will result in call of the global ErrorHook() for centralized error handling (if configured). ▶ Will result in call of an application specific ErrorHook (if configured). ▶ May not induce shutdown / terminate reactions. Instead the application may continue execution by simply returning from the ErrorHooks.
Protection Errors …	▶ Are raised if the application violates its configured boundaries (e.g. memory access violations, timing violations). ▶ Do not corrupt OS internal data. ▶ Are raised upon occurrence of unhandled exceptions and interrupts. ▶ Will result in call of the ProtectionHook() where a shutdown or terminate handling (with or without restart) is induced. ▶ If Shutdown is induced the ShutdownHook() is called (if configured). ▶ If no ProtectionHook() is configured shutdown is induced.
Kernel Errors …	▶ Are raised if the OS cannot longer assume the correctness of its internal data (e.g. memory access violation during ProtectionHook()) ▶ The OS will disable all interrupts and call the Os_PanicHook() to inform the application. ▶ Afterwards the OS enters an infinite loop.

Table 3-4 Types of OS Errors

3.14 Error Reporting

MICROSAR OS supports error reporting according to the AUTOSAR [1] and OSEK OS [2] standard.

This includes

> StatusType return values of OS APIs

> Parameter passing of error codes error to ErrorHook()

> Service ID information provided by the macro OSErrorGetServiceId()

> Parameter access macros (e.g. OSError_ActivateTask_TaskID())

3.14.1 Extension of Service IDs

MICROSAR OS introduces new service IDs for own services.



Reference

All service IDs are listed in the OS header file `Os_Types.h` and may be looked up in the enum data type `OSServiceIdType`.

3.14.2 Extension of Error Codes

MICROSAR OS introduces new 8 bit error codes which extend the error codes which are already defined by AUTOSAR OS and OSEK OS standard.

Type of Error	Related Error Code	Value
An internal OS buffer used for cross core communication is full.	E_OS_SYS_OVERFLOW	0xF5
A forcible termination of a kernel object has been requested e.g. terminate system applications.	E_OS_SYS_KILL_KERNEL_OBJ	0xF6
An OS-Application has been terminated with requested restart but no restart task has been configured.	E_OS_SYS_NO_RESTARTTASK	0xF7
The application tries to use an API cross core, but the target core has not been configured for cross core API	E_OS_SYS_CALL_NOT_ALLOWED	0xF8
The triggered cross core function is not available on the target core.	E_OS_SYS_FUNCTION_UNAVAILABLE	0xF9
A syscall instruction has been executed with an invalid syscall number.	E_OS_SYS_PROTECTION_SYSCALL	0xFA
An unhandled interrupt occurred.	E_OS_SYS_PROTECTION_IRQ	0xFB
The interrupt handling API is used wrong.	E_OS_SYS_API_ERROR	0xFC
Internal OS assertion (not issued to customer).	E_OS_SYS_ASSERTION	0xFD
A system timer ISR was delayed too long.	E_OS_SYS_OVERLOAD	0xFE

Table 3-5 Extension of Error Codes



Reference

All error codes and their values can be looked up in the header file `Os_Types.h`

3.14.3 Detailed Error Codes

MICROSAR OS provides detailed error code to extend the standard error handling of AUTOSAR to uniquely identify each possible OS error.

The detailed error code is assembled from AUTOSAR StatusType error code and unique error code.




Figure 3-4 MICROSAR OS Detailed Error Code

Within OS Hook routines the error code can be obtained by calling Os_GetDetailedError() (see 6.2.7.1 for details).

Note
Vector OS experts always asks about the detailed error codes when supporting customers in case of OS errors.

Reference
The detailed error codes are listed in the file `Os_Types.h` and may be looked up in the enum data type `Os_StatusType`.

Each detailed error code is preceded by a descriptive comment.

3.15 Multi Core Concepts

3.15.1 Scheduling and Dispatching

MICROSAR OS implements independent schedulers and dispatchers for each core.

3.15.2 Multi Core Data Concepts

The multi core data concept of MICROSAR OS tries to avoid concurrent writing accesses between cores.

Although cores may read all OS data of all cores, write accesses to OS data are only performed locally from the owning core.

This data concept allows optimized linking:

> The data of a particular core may be linked into fast accessible memory

> The data of a particular core may be linked into cached memory

Only the variables related to spinlocks have to be linked into global memory which must be accessible by all participating cores.

3.15.3 X-Signals

To realize cross core service APIs MICROSAR OS offers the X-Signal concept (see 4.9 for details). Mind that the X-Signal concept is used internally by the OS cross core API functions only. X-Signals do not provide a service to the application directly.

3.15.4 Master / Slave Core

In a real master / slave multi core architecture only one core is started upon reset. This is the master core. All other cores are held in a reset state and must be explicitly started by the master core. These are slave cores.

There are also multi core systems which starts all cores simultaneously. There is no hardware master / slave classification.

MICROSAR OS is capable to deal with both concepts. In a system with equal cores the OS emulates master / slave behavior according to the core configurations.

3.15.5 Hardware Init Core

To initialize the system peripherals used by the OS (e.g. System MPU, Interrupt Controller), MICROSAR OS uses a dedicated so called Hardware Init Core.

MICROSAR OS offers the possibility to configure one core as Hardware Init Core ("/MICROSAR/Os/OsOS/OsHardwareInitCore"). If the user does not configure a specific core, the Master Core is used as Hardware Init Core.

In safety-critical environments it is recommended to configure the core with the highest diagnostic coverage as Hardware Init Core.

3.15.6 Startup of a Multi Core System

The startup of a multi core system is described in detail in 3.12.

MICROSAR OS offers the possibility to configure a startup symbol for each core. Within a real master / slave system the OS needs this information for starting the slave cores.

3.15.7 Spinlocks

Synchronization of cores is done by

- OS Spinlocks (see [1]) or
- Optimized spinlocks (see 4.1)

3.15.7.1 Linking of Spinlocks

To achieve freedom from interference between cores with different diagnostic coverage capability, spinlocks are linked into different memory sections.

An MPU may be used to allow access from only specific cores or specific OS applications.

The used memory sections depend on the feature „OsForcibleTermination“

	OS spinlocks	Optimized spinlocks
OsForcibleTermination = TRUE	Spinlocks variables are linked into a core shared section	Spinlock variables are linked into a core shared section
OsForcibleTermination = FALSE		Spinlock variables are linked into an application shared section

Table 3-6 Linking of spinlocks

3.15.8 Cache

Due to cache coherency problems spinlock variables and other application variables which are shared among cores must not be cached.

3.15.9 Shutdown

3.15.9.1 Shutdown of one Core

If ShutdownOS() is called on one core, it induces shutdown actions.

- The core terminates all its applications
- Application specific ShutdownHooks are called
- The global ShutdownHook() is called
- Interrupts are disabled
- An endless loop is entered

3.15.9.2 Shutdown of all Cores

Upon call to ShutdownAllCores() synchronized shutdown of the system is invoked. An asynchronous X-Signal is used for this purpose.

Synchronized shutdown is described in [1].

3.15.9.3 Shutdown during Protection Violation

If the ProtectionHook() returns with “PRO_SHUTDOWN” a shutdown of all cores is invoked.

3.16 Debugging Concepts

3.16.1 Description

MICROSAR OS offers two software utilities to support OS debugging.

ORTI	MICROSAR OS generates an ORTI debug file (**O**SEK **R**un**T**ime **I**nterface). Many debuggers are capable of loading such ORTI files and provide comfortable debug means based upon the OS configuration. See chapter 3.16.3 for details
TimingHooks	MICROSAR OS provides macros which may be used for debugging purposes (also suitable for third party tools). See chapter 4.10 for details.

3.16.2 Activation

ORTI and TimingHooks may be switched on within the OsDebug container.



Note
There is an additional switch within the “OsDebug” container. It enables OS assertions. They are intended for OS internal test purposes. If activated the OS performs additional runtime checks on its own internal states.

3.16.3 ORTI Debugging

ORTI is the abbreviation of “OSEK Runtime Interface”.

When ORTI debugging is activated MICROSAR OS generates additional files with “`.ort`” extension. These files contain information about the whole OS configuration. They are intended to be read by a debugger.

The debugger uses the information from the ORTI files to display static and runtime information about OS objects e.g. task states.

ORTI versions supported by MICROSAR OS:

ORTI 2.2	As described in the OSEK standard [3] and [4]
ORTI 2.3	Unofficial “Standard” based upon ORTI 2.2. It does contain extensions for multi core OS and was proposed by “Lauterbach Development Tools” (described in [5]).

Both ORTI versions are capable to be used within single core and multi core systems.



Note for ORTI 2.2 multi core debugging

For each configured AUTOSAR core there is one separate ORTI file.

For multi core debugging, the debugger software must be capable to read several ORTI files.



Note for ORTI 2.3 multi core debugging

The debug information for all configured cores is aggregated in one file.



Note

Basically debuggers are capable to display the stack consumption for each stack (OsStackUsageMeasurement must be switched on).

Please note that uninitialized OS stacks may show 100% stack usage within ORTI debugging. Reliable information can only be given after the OS has initialized all stacks.



Caution

MESSAGE objects and CONTEXT information specified by ORTI 2.2 Standard are not supported in MICROSAR OS.



Caution

The following OS services are not traced by ORTI service tracing:

- GetSpinlock() (for optimized spinlocks)
- TryToGetSpinlock() (for optimized spinlocks)
- ReleaseSpinlock() (for optimized spinlocks)
- IOC API
- Os_GetVersionInfo()
- Os_Init()
- Os_InitMemory()

3.17 Memory Protection

MICROSAR OS uses memory protection facilities of a processor to achieve freedom from interference between OS applications and cores. For this purpose it may use the memory protection units (MPU) which are responsible for monitoring all memory accesses made by CPU and/or peripheral devices and triggering an exception upon detection of an illegal memory access.

3.17.1 Usage of the MPUs

The MPUs are used to achieve freedom from interference between applications / tasks / ISRs on the same core. The basic concept is that access rights of these runtime entities (read/write/execute) have to be granted explicitly to software parts.

This is done with the following steps:

Step	Toolchain phase
Set up an SC3 system	Configuration of OS
Configure memory regions	
Assign the memory regions to an MPU	
Assign the memory regions to OS applications / Tasks / ISRs (optional)	
Use the AUTOSAR MemMap mechanism to place code, constants and variables into appropriate sections (see 5.3.1.1)	Compilation
Use OS generated linker command files to locate the sections into memory (see 0)	Linkage



Note
Which MPUs are reserved for use by MICROSAR OS depend on the target hardware. Each MPU used by MICROSAR OS can be identified by the corresponding registers that are described in 5.2. MPUs reserved for MICROSAR OS may not be used for anything else.

3.17.2 Configuration Aspects

A memory region is typically configured by specifying

- A start and end address by number, or by linker labels (see 5.3.3 for OS generated section labels)
- Access rights to this region (a pre-defined set of access rights is referable)
- The validity of the region by ID (e.g. PID / ASID / Protection Set)
- To which MPU the region belongs
- The owner of the region

The owner of the memory region distinguishes the runtime behavior of the hardware MPU regions (whether the region is static or dynamic).



Note
The start and end addresses of configured memory region should always be a multiple of the granularity of the hardware MPU.



Note
The number of available hardware MPU regions is limited by hardware!

MICROSAR OS checks during code generation that the overall number of configured memory regions does not exceed the number of available hardware MPU regions.

3.17.2.1 Static MPU Regions

If no owner is specified, MICROSAR OS initializes a hardware MPU region to be static. It is never reprogrammed during runtime of the OS. It is valid for all software parts.



Note
The validity of a static MPU region may be restricted by using ID (e.g. PID / ASID / ProtectionSet).

3.17.2.2 Dynamic MPU Regions

If an owner is specified for a memory region MICROSAR OS initializes a hardware MPU region to be dynamically reprogrammed during OS runtime. Whenever the owner of the memory is active during runtime a specific hardware MPU region is programmed with the configured values of the memory region.

Memory regions which are assigned to an OS application are reprogrammed whenever the OS application is switched.

Memory regions which are assigned to tasks or ISRs are reprogrammed with each thread switch.

3.17.2.3 Freedom from Interference

MICROSAR OS is able to encapsulate OS application data, task private data and ISR private data. This does also depend on the owner of the memory region.

Memory Region Owner	Access Granted To	Access Denied For
OS application	Runtime objects of this OS application > Tasks > ISRs > IOC callbacks > Non-trusted functions > Application specific hooks	> Other non-trusted OS applications and their objects
Task	> The owning task	> Other non-trusted OS applications and their objects > Other runtime objects of the same OS application
ISR	> The owning ISR	

3.17.3 Stack Monitoring

MICROSAR OS uses one memory region of the MPU to supervise the current stack. This is the default handling in SC3 and SC4 systems. See 3.3.5 for details.



Caution
Memory regions must not be configured to allow write access into any stack regions. Otherwise the OS cannot ensure stack data integrity.

3.17.4 Protection Violation Handling

Upon any memory protection violation exception the OS first switches to the kernel stack and then informs the application.

In case of a memory protection violation exception which has occurred within OS code MICROSAR OS enters a Kernel Panic.

In case of a memory protection violation exception which has occurred within critical user sections, i.e. PreTaskHook, PostTaskHook, Alarm callbacks, Timing Hooks, ProtectionHook and ShutdownHook, MICROSAR OS calls the PanicHook().

In all other cases of a memory protection violation exception MICROSAR OS calls the ProtectionHook() with the parameter E_OS_PROTECTION_MEMORY.

3.17.5 Optimized / Fast MPU Handling

If the number of application / task / ISR specific memory regions is small, MICROSAR OS may have the possibility to initialize the MPU entirely with static MPU regions.

By utilizing memory protection identifiers different access rights may still be achieved between different applications.

MICROSAR OS switches access rights by simply switching the protection identifier. This will result in a very fast MPU handling.

> Configure only memory regions which are static (no owner is assigned).

> Use “OsMemoryRegionIdentifier” to assign a protection identifier to that region.

> Assign either OS applications or Tasks and ISRs to use a specific protection identifier (OsAppMemoryProtectionIdentifier, OsTaskMemoryProtectionIdentifier, OsIsrMemoryProtectionIdentifier)



Note
Depending on the used platform protection identifiers are also referred as PID (MPC), ASID (RH850) or protection sets (TriCore). But the basic technique is the same.

3.17.6 Recommended Configuration

MICROSAR OS offers a recommended MPU configuration which contains a basic setup.

It configures the MPU to achieve the access rights as follows

Access Rights	Trusted Software	Non-Trusted Software
Executable rights to whole memory	X	X
Read access to whole RAM / ROM	X	X
Write access to whole RAM (except stack regions)	X	-
Read / Write access to peripheral registers	X	-
Read / Write access to global shared memory	X	X
Write access to current active stack	X	X

Table 3-7 Recommended Configuration MPU Access Rights

3.18 Memory Access Checks

3.18.1 Description

AUTOSAR OS specifies functions for checking memory access rights of an ISR or task to a specific memory region.

- CheckTaskMemoryAccess
- CheckISRMemoryAccess

3.18.2 Activation

No explicit activation of these API service functions necessary. They are provided automatically by the OS.

3.18.3 Usage

The API service functions CheckTaskMemoryAccess() and CheckISRMemoryAccess() work on additional configuration data which has to be provided by the user.

Therefore additional regions (“OsAccessCheckRegion“) may be configured. Tasks and ISRs may be assigned to each access check region.



Note
All memory access checks are based upon the configured “OsAccessCheckRegion” objects. They are not based upon current MPU values during runtime!

OsAccessCheckRegions and OsMemoryRegions contain redundant information.

3.18.4 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

3.19 Timing Protection Concept

3.19.1 Description

To implement timing protection, MICROSAR OS needs a timer hardware which is able to generate an interrupt with high priority. This interrupt is never disabled by the OS interrupt handling API.

Two concepts may be implemented within MICROSAR OS:

- The timing protection interrupt request is non-maskable (NMI request)
- The timing protection interrupt request is maskable

The consequences of both concepts are shown in the comparison:

	Timing Protection IRQ is Maskable	Timing Protection IRQ is NMI
Level of timing protection IRQ	The level of the interrupt source is chosen to be higher than the highest category 1 ISR.	The exception source has no interrupt level.

Caution
Any category 1 ISR bypasses the OS. For this reason such an ISR may get terminated in case it is executed, while the budget of a monitored entity is exhausted.

Thus the AUTOSAR OS specification advises not to use category 1 ISRs within a system which uses timing protection.

Caution
In case of an inter-arrival time violation MICROSAR OS does currently not provide the information which task or ISR did violate its inter-arrival time. GetTaskID() and GetISRID() return the current task / ISR. The suppressed task / ISR ID is not returned by these APIs.

3.19.2 Activation

Timing protection features are activated by setting the scalability class to SC2 or SC4 (OsScalabilityClass).

Afterwards timing protection containers may be configured for tasks or ISRs (OsTaskTimingProtection / OsIsrTimingProtection). Observed times are configured within these containers.



Note
The OS will add an appropriate ISR automatically to the configuration.



Caution
To avoid corruption of the OS Timing Protection facility, the Timing Protection ISR must not be delayed longer than one hardware counter cycle. For a 16 Bit hardware timer for instance, one hardware counter cycle is the time needed to count from 0 to 0xFFFF.

3.19.3 Usage

Once the timing protection feature is active tasks and ISRs are observed automatically by the OS.

Observation of a particular OS object (task / ISR) only takes place if any execution budgets or locking times are configured for this object.

3.20 IOC

3.20.1 Description

The Inter OS-Application Communicator (IOC) is responsible for data exchange between OS applications. It handles two important tasks

> Data exchange across core boundaries

> Data exchange across memory protection boundaries

Parts of the IOC API services are generated.

MICROSAR OS always tries to generate IOC API services and data structures to minimize resource usage.

Especially the runtime of IOC API services is influenced by the configuration of IOC objects. For the customer it is important how configuration aspects minimize the IOC runtime.

For each IOC object MICROSAR OS decides during runtime whether

> Interrupt locks

> Spinlocks

Are used or not.

3.20.2 Unqeued (Last Is Best) Communication



Note
Whenever the data of a last is best IOC object can be written / read atomically (integral data type) no spinlocks are used at all.

3.20.2.1 1:1 Communication Variant

	Sender and Receiver are located on the same core	Sender and Receiver are located on the different cores
Interrupt Locks	Used	Not used
Spinlocks	Not Used	Used
System Call Traps	Not Used	Not Used

3.20.2.2 N:1 Communication Variant

	Sender and Receiver are located on the same core	Sender and Receiver are located on the different cores
Interrupt Locks	Used	Not used
Spinlocks	Not Used	Used
System Call Traps	Used	Used

3.20.2.3 N:M Communication Variant

	Sender and Receiver are located on the same core	Sender and Receiver are located on the different cores
Interrupt Locks	Used	Not used
Spinlocks	Not Used	Used
System Call Traps	Used	Used

3.20.3 Queued Communication

For 1:1 and N:1 Communication the following table is applied:

	Sender and Receiver are located on the same core	Sender and Receiver are located on the different cores
Interrupt Locks	Not Used	Not used
Spinlocks	Not Used	Not Used
System Call Traps	Not Used	Not Used

3.20.4 Notification

MICROSAR OS provides configurable receiver callback functions for notification purposes.



Note
In case an IOC object has a configured receiver callback function a system call trap is needed in any case.

3.20.5 Particularities

3.20.5.1 N:1 Queued Communication

N:1 queued communication is realized with multiple sender queues. The receiver application does an even multiplexing on all sender queues when calling the receive function (see figure).




Figure 3-5 N:1 Multiple Sender Queues

3.20.5.2 IOC Spinlocks

Note
During generation of OS data structures, if MICROSAR OS detects that a spinlock is needed for a particular IOC object, it automatically creates a spinlock object within the OS configuration.

3.20.5.3 Notification

Based on the core assignment of sender and receiver of an IOC object, two possible scenarios for callback handling are possible.

Sender and Receiver are located on the same core	> The callback notification function is called within the IOC send function
Sender and Receiver are located on different cores	> The sender triggers an X-Signal request on the receiving core > The callback notification function is called within the X-Signal ISR



Note

> All callback functions are using the cores IOC receiver pull callback stack.
> During execution of the IOC receiver pull callback function category 2 ISRs are disabled.
> Within IOC receiver pull callback functions only other IOC API functions and interrupt dis/enable API functions are allowed.

3.20.5.4 Complex Data Types



Note

If “OsIocDataType” of an IOC object is a complex data type, MICROSAR OS uses a memcpy function of the VStdLib Module for data transfer and initialization.

See VStdLib Technical Reference [8].

3.21 Trusted OS Applications

Trusted OS Applications are basically executed in supervisor mode. They can have read/write access to nearly the whole memory (except stack regions).

MICROSAR OS allows gradually restricting of access rights of trusted OS applications.

Trusted OS applications may be restricted by memory access or by processor mode.

3.21.1 Trusted OS Applications with Memory Protection

3.21.1.1 Description

Runtime objects (Tasks / ISRs / Trusted functions) of trusted OS applications with enabled memory protection have the following behavior

- They run in supervisor mode
- Memory access has to be granted explicitly (in the same way as for a non-trusted OS application)
- The MPU is re-programmed whenever software of the OS application is executed.

3.21.1.2 Activation

Set “OsTrustedApplicationWithProtection” to TRUE.

3.21.1.3 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

3.21.2 Trusted OS Applications in User Mode

3.21.2.1 Description

Such OS applications can have read/write access to nearly the whole memory (except stack regions), but they are running in user mode. This is also applied to all runtime objects (Tasks / ISRs / Trusted functions) assigned to this OS application.



Note

> API runtimes for OS applications which run in user mode are longer.

3.21.2.2 Activation

Set “OsApplicationIsPrivileged” to FALSE.

3.21.2.3 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

3.21.3 Trusted Functions



Note

> The interrupt state of the caller is preserved when entering the trusted function.

> The trusted function may manipulate the interrupt state by using OS services. The changed interrupt state is preserved upon return from the trusted function.



Caution

Nesting level of trusted functions is limited to 255.

The application has to ensure that this limitation is held. There is no error detection within the OS.

3.22 OS Hooks

3.22.1 Runtime Context

MICROSAR OS implements the runtime context and accessing rights of OS Hooks according to the following table

Hook Name	Processor Mode	Access Rights	Interrupt State
StartupHook	Supervisor	Trusted	Category 2 lock level
ErrorHook			
ShutdownHook			TP lock level
ProtectionHook			
StartupHook_<OS application name>	Depending on the configuration of the owning OS application		Category 2 lock level
ErrorHook_<OS application name>			
ShutdownHook_<OS application name>			TP lock level
Os_PanicHook	Supervisor	Trusted	TP lock level
PreTaskHook	Supervisor	Trusted	TP lock level
PostTaskHook	Supervisor	Trusted	TP lock level
AlarmCallbacks	Supervisor	Trusted	Category 1 lock level
IOC receiver pull callbacks	Depending on the configuration of the owning OS application		Category 2 lock level

3.22.2 Nesting behavior

It is possible that OS hooks may be nested by other OS hooks according to the following table

Nested by OS Hook	ErrorHook(s)	ProtectionHook	StartupHook(s)	ShutdownHook(s))	IOC Callbacks
ErrorHook(s)	Not possible	possible	Not possible	possible	possible
ProtectionHook	Not possible	Not possible	Not possible	possible	possible
StartupHook(s)	possible	possible	Not possible	possible	possible
ShutdownHook(s)	Not possible	Not possible	Not possible	Not possible	possible
IOC Callbacks	possible	possible	Not possible	possible	Not possible

3.22.3 Hints



Caution
Within OS Hooks the interrupts must not be enabled again!



Caution
Hooks must never be called by application code directly.



Note for SC2 or SC4
Hooks don’t have any own runtime budgets. OS Hooks consume the budget of the current task / ISR.



Caution: Protection violations during Pre- and PostTaskHook

- In case of a memory violation during execution of Pre-/PostTaskHook, the OS will always end up in PanicHook.
- In case of an unhandled exception or an unhandled interrupt during execution of Pre-/PostTaskHook, the OS will always end up in PanicHook.
- After termination of a task a timing violation in the according PostTaskHook could not be detected by the OS.

4 Vector Specific OS Features

This chapter describes functions which are available only in MICROSAR OS. They extend the standardized OS functions from the AUTOSAR and OSEK OS standard [1] [2].

4.1 Optimized Spinlocks

4.1.1 Description

For core synchronization in multi core systems, MICROSAR OS offers (beneath the AUTOSAR specified OS spinlocks) additional optimized spinlocks.

They are able to reduce the runtime of the Spinlock API. Configuration is also easier.

AUTOSAR specified OS spinlocks cannot cause any deadlocks between cores (see unique order of nesting OS spinlocks in AUTOSAR OS standard). Therefore some error checks on OS configuration data are necessary.

The error checks are not performed with optimized spinlocks.

	OS Spinlocks	Optimized Spinlocks
Deadlocks	No deadlocks possible	Deadlocks are possible
Runtime	Longer runtime due to more error checks	Smaller runtime due to less error checks
Configuration	OsSpinlockSuccessor must be configured if spinlocks must be nested	OsSpinlockSuccessor need not to be configured
Nesting	Can be nested by other OS spinlocks	Nesting of optimized spinlock should be avoided or at least be used with caution
Linking	OS and optimized spinlock variables are placed into different dedicated memory sections (see 5.3.1).	

Table 4-1 Differences of OS and Optimized Spinlocks

4.1.2 Activation

The spinlock attribute “OsSpinlockLockType” may be set to “OPTIMIZED”.

The “OsSpinlockSuccessor” attribute should not be configured for an optimized spinlock.

4.1.3 Usage

Once a spinlock object is configured to be an optimized spinlock the application may use the Spinlock API as usual. The Spinlock service functions are capable to deal with optimized and OS spinlocks.

4.2 Barriers

4.2.1 Description

MICROSAR OS offers a feature to synchronize tasks from different cores using a barrier object. The calling task of the synchronization API method blocks until all other tasks participating in the same barrier have also called the synchronization method.

4.2.2 Activation

Within OS configuration “Barrier” objects may be specified. A barrier consists of a list of tasks which participate in the barrier.



Note
Only one task per core may be assigned to a barrier object. The assigned task must also be the task that calls the API.

4.2.3 Usage

If one or more barriers are configured, participating tasks may call Os_BarrierSynchronize() with a BarrierID they are participating in. A task can participate in multiple barriers.

Multiple tasks of one core may not participate in the same barrier.

After a task calls Os_BarrierSynchronize() for a specific barrier, it blocks until all other participants of the same barrier have also called Os_BarrierSynchronize() with the same BarrierID.

If a participating core has not been started, the participating task of that core will not be considered as participant of the barrier.



Note
Os_BarrierSynchronize() does not disable the interrupts internally. Therefore, higher priority threads may preempt the calling task.

Threads with lower priority will not be executed until the synchronization is complete.

If the core should stop execution until the barrier synchronization is completed, the user has to disable the interrupts before calling the API.




Figure 4-1 Barriers

Caution
A deadlock may occur if one task has called Os_BarrierSynchronize() and one of the other participants does not call Os_BarrierSynchronize() for the same barrier. All participants must call the API method the same number of times to ensure deadlock free scheduling.

Caution
A deadlock occurs when the API method is called for a barrier of which one of the participants was killed.

4.3 Peripheral Access API

4.3.1 Description

MICROSAR OS offers peripheral access services for manipulating registers of peripheral units. The application may delegate such accesses to the OS in case that its own accessing rights are not sufficient to manipulate specific peripheral registers.

4.3.2 Activation

The API service functions themselves do not need any activation.

But within the OS configuration “OsPeripheralRegion” objects may be specified. They are needed for error and access checking by the OS.

An OsPeripheralRegion object consists of the start address, end address and a list of OS applications which have accessing rights to the peripheral region.



Note
Access to a peripheral region is granted if the following constraint is held

Start address of peripheral region <= Accessed address <= End address of peripheral region

4.3.3 Usage

Once peripheral regions are configured they may be passed to the API functions.



Reference
The API service functions themselves are described in chapter 6.2.2.

4.3.4 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

4.3.5 Alternatives

The access rights to peripheral registers may also be granted by configure an additional MPU region for the accessing OS application.

4.3.6 Common Use Cases

The peripheral access APIs may be used …

- … if the accessing OS application runs in user mode but the register to be manipulated can only be accessed in supervisor mode.
- … if the application does not want to spend a whole MPU region to grant access rights.

4.4 Trusted Function Call Stubs

4.4.1 Description

Since the OS service CallTrustedFunction() is very generic, there is the need to implement a stub-interface which does the packing and unpacking of the arguments for trusted functions.

MICROSAR OS is able to generate these stub functions.

4.4.2 Activation

The OS application attribute “OsAppUseTrustedFunctionStubs” must be set to TRUE. Data types must be defined in the header file which is referred by “OsAppCalloutStubsIncludeHeader”.

4.4.3 Usage

A particular trusted function is called with the following syntax:

```
<configured return type> Os_Call_<trusted function name>
(<configured parameters>);
```

Parameter packing, unpacking and return value handling is done by the stub function.

4.4.4 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

4.5 Non-Trusted Functions (NTF)

4.5.1 Description

Service functions which are provided by non-trusted OS applications are called non-trusted functions. They have the following characteristics:

- They run in user mode.
- They run with the MPU access rights of the owning OS application.
- They perform a stack switch to specific non-trusted function stacks.
- They run on an own secured stack.
- They can safely provide non-trusted code to other OS applications.
- Parameters are passed to the NTF with a reference to a data structure provided by the caller.
- Returning of values is only possible if the caller passes the non-trusted functions parameters as pointer to global accessible data.

4.5.2 Activation

They are defined within an OsApplication container (“OsApplicationNonTrustedFunction”). The attribute “OsTrusted” for this OS application must be set to FALSE.

4.5.3 Usage

Similar to the CallTrustedFunction() API of the AUTOSAR OS standard MICROSAR OS implements an additional service which is called Os_CallNonTrustedFunction() (see chapter 6.2.4 for Details).

Configured non-trusted functions are called with this API.



Note

- The interrupt state of the caller is preserved when entering the non-trusted function
- The non-trusted function may manipulate the interrupt state by using OS services. The changed interrupt state is preserved upon return from the non-trusted function.



Caution

Non-trusted functions currently cannot be terminated without termination of the caller.

4.5.4 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

4.6 Fast Trusted Functions

4.6.1 Description

MICROSAR OS offers the feature of runtime optimized trusted functions (fast trusted functions).

The speedup of the runtime is achieved by removing most of the OS error checks, the application switch and the MPU reprogramming.

Fast trusted functions have the following characteristics:

- They may be called with disabled interrupts.
- They run in supervisor mode.
- They run with the application ID of the caller.
- They run on the stack of the caller.
- They run with the MPU settings of the caller.
- Parameters are passed to the fast trusted function with a reference to a data structure provided by the caller.



Caution
Calls to other OS API services are not allowed within a fast trusted function!

4.6.2 Activation

They are defined within an OsApplication container (“OsApplicationFastTrustedFunction”). The attribute “OsTrusted” for this OS application must be set to TRUE.

4.6.3 Usage

Similar to the CallTrustedFunction() API of the AUTOSAR OS standard MICROSAR OS implements an additional service which is called Os_CallFastTrustedFunction() (see chapter 6.2.5 for Details).

Configured fast trusted functions are called with this API.

4.6.4 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

4.7 Interrupt Source API

4.7.1 Description

MICROSAR OS offers additional API services for category 2 ISRs and their respective interrupt sources.

The services include

- Enable of an interrupt source
- Disable of an interrupt source
- Clearing of the interrupt pending bit
- Checking if the interrupt source is enabled
- Checking of interrupt pending bit status
- Enabling of all interrupt sources

(See 6.2.6 for API details).

4.8 Pre-Start Task

4.8.1 Description

MICROSAR OS offers the possibility to provide a set of OS API functions for initialization purposes before StartOS() has been called.

Therefore a pre-start task may be configured which is capable to run before the OS has been started. Within this task stack protection is enabled and particular OS APIs can be used.

The table in 6.2.15 lists the OS API functions which may be used within the Pre-Start task.

4.8.2 Activation

> Define a basic task

> Within a core object this basic task has to be referred to be the pre-start task of this core (attribute “OsCorePreStartTask”). Only one pre-start task per core is possible.

> Start the OS as described below

4.8.3 Usage

1. Execute Startup Code
2. Call `Os_InitMemory()`
3. Call `Os_Init()`
4. Call `Os_EnterPreStartTask()` (see 6.2.3 for Details)
5. The OS schedules and dispatches to the task which has been referred as pre-start task.
6. The pre-start task has to be left by a call to `StartOS()`



Caution
The pre-start task may only be active once prior to StartOS() call.



Caution
Within the pre-start task the getter OS API services (e.g. GetActiveApplicationMode()) neither return a valid result nor a valid error code.



Caution
If MICROSAR OS encounters an error within the pre-start task, only the global hooks (ErrorHook(), ProtectionHook() and ShutdownHook()) are executed. OS application specific hooks won't be executed.

Consider that the StartupHook() did not yet run when the Pre-Start Task is executed.



Caution
If the Pre-Start Task is used, global hooks have to consider that the OS might not be completely initialized. OS APIs which are allowed after normal initialization (e.g. TerminateApplication()) are not allowed within global hooks, if the error occurred in the Pre-Start Task.



Caution
If the ProtectionHook() is triggered within the Pre-Start Task, the OS ignores its return value. The only valid return value is PRO_SHUTDOWN.

4.8.4 Dependencies

This feature is of significance in SC3 and SC4 system with active memory protection.

4.9 X-Signals

4.9.1 Description

MICROSAR OS uses cross core signaling (X-Signals) to realize API service calls between cores.

Note
X-Signals are used internally in the OS. The OS uses them to make the usual OS API-services (like task activation, event setting, alarm start, …) work cross core. In order to achieve that, the integrator has to configure (and understand) X-Signals although they do not directly provide any additional services to the application.

The next figure shows the basic principles of an X-Signal




Figure 4-2 X-Signal

Whenever a core executes a service API cross core it writes this request into its own send port queue. Then it signals this request by an interrupt request (X-Signal) to the serving core.

The serving core reads the request from the send port queue and executes the requested service API. The result of the service API is provided in the receive port queue.

X-Signals have the following characteristics:

- An X-Signal is a unidirectional request from one core to another (1:1).
- For each core interconnection one X-Signal is needed.
- All accesses to the (sender / receiver) port queues are lock free.

> Queue Sizes must be configured.

> The Queues may be protected by MPU to achieve freedom of interference between cores.

> X-Signals may be configured to offer only a subset of possible cross core API services. Not configured API services are refused to be served.

> The API error codes for cross core API services are extended.

- Additional error codes for queue handling.
- Additional error code if the requested service is refused to be served.

> X-Signals can be configured to be synchronous or asynchronous.

	Synchronous X-Signal	Asynchronous X-Signal
Call behavior	After the cross core service API has been requested the requester core goes into active waiting loop and polls for the result from the server core (remote procedure call). **Note:** During active wait the interrupts are enabled.	After the cross core service API has been requested the requester core continues its own program execution.
Error signaling	Error handling is induced on the requester core immediately, if the polled API result is not E_OK.	Error handling is induced with the next X-Signal request on the requester core, if the result of the previously requested API is not E_OK. **Note**: Upon potential errors of the previously requested API the current application ID on sender and receiver side meanwhile may have changed.
AUTOSAR standard compliance	Compliant to the AUTOSAR Standard	Deviation to the AUTOSAR Standard

Table 4-2 Comparison between Synchronous and Asynchronous X-Signal



Note
Any cross core “getter” APIs e.g. GetTaskState() are always executed with a synchronous X-Signal.



Note
The sender core as well as the receiver core may cause protection violations. Protection error handling is performed on the core where the violation is detected.



Note
When a cross core API is induced by an X-Signal, all static error checks (e.g. validity of parameters) are done on the caller side.

All dynamic error checks (which depend on runtime states) are executed on the receiver side.



Caution
For correct X-Signal function it is essentially that a sender core of an X-Signal must have read access to the receiver core data structure. Especially if the data is mapped into core local RAM.

There are some platforms e.g. RH850 which does not grant cross core read access to core local RAM out of reset. Within such platforms it is the duty of the application to set up these cross core read accesses before the OS is started.

4.9.1.1 Notes on Synchronous X-Signals

The priority of the receiver ISR determines which other category 2 ISRs of one core may use cross core API services.

Additionally category 2 ISRs may only use cross core API services if they allow nesting.

The following table gives an overview.

Logical Priority	ISR Nesting	Synchronous Cross Core API Calls
ISR with higher priority than X-Signal priority	ISR nesting is allowed	Not allowed
ISR with higher priority than X-Signal priority	ISR nesting is disabled	Not allowed
X-Signal ISR priority	-	-
ISR with lower priority than X-Signal priority	ISR nesting is allowed	Allowed
ISR with lower priority than X-Signal priority	ISR nesting is disabled	Not allowed

Table 4-3 Priority of X-Signal receiver ISR



Caution
If the priority and nesting requirements from the previous table are not fulfilled there may be deadlocks within a multicore system!

4.9.1.2 Notes on Mixed Criticality Systems

MICROSAR OS checks application access rights on sender and on receiver side. This increases isolation of safety-critical parts in mixed criticality systems (e.g. protect a lockstep core from a non-lockstep core).

Consider that these application access checks are not performed for ShutdownAllCores(). Thus switching off the usage of ShutdownAllCores API for non-lockstep cores is recommended. This can be done within the X-Signal configuration.

4.9.2 Activation

X-Signals must be configured explicitly in a multi core environment. See chapter 5.5 for details.

4.10 Timing Hooks

4.10.1 Description

MICROSAR OS supports timing measurement and analysis by external tools. Therefore it provides timing hooks. Timing hooks inform the external tools about several events within the OS:

> Activation and arrival of a task:
  - These allow an external tool to trace all activations of tasks as well as further arrivals (e.g. setting of an event or the release of a semaphore with transfer to another task).
  - This allows external tools to visualize activations and arrivals of tasks to measure the time between them in order to do a schedulability analysis.

> Context switch:
  - These allow an external tool to trace all context switches between tasks and ISRs.
  - This allows external tools to visualize the scheduling of tasks and ISRs and measure their execution time.

> Locking of interrupts, resources or spinlocks:
  - These allow an external tool to trace locks. This is important as locking times of tasks and ISRs influence the execution of other tasks and ISRs. The kind of influence is different for different locks.

> Forcible termination of tasks and ISRs:
  - These allow an external tool to trace killing of tasks and ISRs. So abnormal behavior of the application can be monitored (e.g. timing violations by a task or ISR).

The timing hooks are called within MICROSAR OS code. For hooks, which are not implemented by the user, empty hook definitions are provided.

4.10.2 Activation

An include header has to be specified in the attribute “OsTimingHooksIncludeHeader” located in the “OsDebug” container.

4.10.3 Usage

The timing hooks may be implemented in the configuration specified header. All available macros are introduced in chapter 6.2.12.



Caution
Within the timing hooks trusted access rights are active e.g. access rights to OS variables.



Note: Protection violations during Timing Hooks
If any protection violation occurs during any of the timing hooks the OS will always go into shutdown!

The return value of the ProtectionHook (e.g. PRO_TERMINATEAPPL) will be ignored and overwritten by the OS to PRO_SHUTDOWN.

4.11 Kernel Panic

If MICROSAR OS recognizes an inconsistent internal state it enters the kernel panic mode. In such cases, the OS does not know how to correctly continue execution. Even a regular shutdown cannot be reached. E.g.:

- The protection hook itself causes errors
- The shutdown hook itself causes errors

MICROSAR OS goes into freeze as fast as possible

1. Disable all interrupts
2. Inform the application about the kernel panic by calling the Os_PanicHook() (see 6.2.13)
3. Enter an endless loop



Caution

- The OS cannot recover from kernel panic.
- ProtectionHook() is not called
- ErrorHook() is not called
- There is no stack switch. The Os_PanicHook() runs on the current active stack

4.12 Generate callout stubs

4.12.1 Description

MICROSAR OS offers the feature to generate the function bodies of all configured OS hook functions (all global hooks and application specific hooks).

The function bodies are generated into the file “Os_Callout_Stubs.c”.

4.12.2 Activation

The Configuration attribute “OsGenerateCalloutStubs” has to be set to TRUE.

4.12.3 Usage

Once the C-File has been generated it may be altered by the user. Code parts between certain special comments are permanent and won’t get lost between two generation processes.

If a hook is switched off, the corresponding function body is also removed. But the user code (between the special comments) is preserved. Once the hook is switched on again, the preserved user code is also restored.



Example

```
FUNC(void, OS_STARTUPHOOK_CODE) StartupHook(void)
{
/*********************************************************************
 * DO NOT CHANGE THIS COMMENT!           <USERBLOCK OS_Callout_Stubs_StartupHook>
 *********************************************************************/

   /* user code starts here */
   /* code between those comments is preserved even if the file is newly generated
      Or even if the hook is switched off in the meanwhile */

/*********************************************************************
 * DO NOT CHANGE THIS COMMENT!           </USERBLOCK>
 *********************************************************************/

}
```

4.13 Exception Context Manipulation

4.13.1 Description

MICROSAR OS offers the feature to read and modify the interrupted context in case of a hardware exception. This feature shall be applied in ProtectionHook in the combination with PRO_IGNORE_EXCEPTION as the return value. One typical use case for this feature is to recover from an ECC error in memory.

4.13.2 Usage

The following figure shows the usage of this feature.




Figure 4-3 Usage of manipulating exception context

Inside ProtectionHook the user first needs to call Os_GetExceptionContext() to read the previous context. Then the context may be investigated and modified according to user requirements. For instance, the program counter may be adapted to the instruction, which is to be executed directly after the exception. Note that the content of the context is depending on the platform. In general, the context contains all the processor registers and some other relevant information. More detailed information can be found in the static code, where the type Os_ExceptionContextType is defined. Finally, the modified context can be written back via Os_SetExceptionContext(). When ProtectionHook returns with PRO_IGNORE_EXCEPTION, the processor continues its execution with the manipulated context.

Note
Currently this feature isn't available for all derivatives supported by the MICROSAR OS. For more information please refer to the platform specific Technical Reference [9].



Caution
This feature may only be used within ProtectionHook when the error status is either E_OS_PROTECTION_MEMORY or E_OS_PROTECTION_EXCEPTION

4.14 Category 0 Interrupts

4.14.1 Description

MICROSAR OS implements category 0 ISRs to have minimal interrupt latency time especially in SC2 or SC4 systems. This is an extension to the OS standard.

4.14.2 Usage

4.14.2.1 Implement Category 0 ISRs

MICROSAR OS offers a macro for implementing a category 0 ISR. This is a similar mechanism like the macro for a category 2 ISR defined by the AUTOSAR standard.

MICROSAR OS abstracts the needed compiler keywords.



Implement a category 0 ISR

```
OS_ISR0(<MyCategory0ISR>)
{
}
```

4.14.2.2 Nesting of Category 0 ISRs

Since category 0 ISRs are directly called from interrupt vector table without any OS pro- and epilogue, automatic nesting of category 0 ISRs cannot be supported.

The configuration attribute “OsIsrEnableNesting” is ignored for category 0 ISRs.

Nevertheless the interrupts may be enabled during a category 0 ISR to allow interrupt nesting but OS API functions cannot be used for this purpose. The application has to use compiler intrinsic functions or inline assembler statements.



Example

```
OS_ISR0(<MyCategory0ISR>)
{
   __asm(EI); /* enable nesting of this ISR */

   __asm(DI); /* disable nesting before leaving the function */
}
```

4.14.2.3 Category 0 ISRs before StartOS

There may be the need to activate and serve category 0 ISRs before the OS has been started.

The following sequence should be implemented:

- Call Os_InitMemory()
- Call Os_Init() (within the function the basic interrupt controller settings are initialized e.g. priorities of interrupt sources).
- Enable the interrupt sources of category 0 ISRs by directly manipulating the control registers in the interrupt controller.
- Enable the interrupts by directly manipulating the global interrupt flag and / or current interrupt priority to allow the category 0 ISRs

4.14.2.4 Locations where category 0 ISRs are locked

Category 0 interrupts are disabled OS internally for very short times only.

The following list mentions the locations of these locks:

- Inside APIs that cause a context switch e.g. TerminateTask()
- Partial termination due to exception handled by ProtectionHook
- On Interrupt, Exception and Trap entry and return
- OS initialization routines inside Os_Init() and StartOS()

4.14.3 Notes on Category 0 ISRs



Expert Knowledge

On platforms which have no automatic stack switch upon interrupt request there will be no stack switch at all if a category 0 ISR occurs. Thus the stack consumption of a category 0 ISR should be added to all stacks which can be consumed by category 0 ISRs (see 3.2.15 for an overview).



Expert Knowledge

Category 0 ISRs are consuming timing protection budgets (execution budgets and locking times) of the interrupted Task or category 2 ISR



Note

Although the interrupt priorities are initialized by MICROSAR OS there is no API to enable or acknowledge category 0 ISRs. The interrupt control registers have to be accessed directly.



Caution
If the timing protection interrupt occurs during the runtime of a category 0 ISR, its execution (the timing protection violation handling/protection hook) is delayed until the category 0 ISR has finished.



Caution
MICROSAR OS does not allow OS API usage within category 0 ISRs.

If any OS API is called anyway, MICROSAR OS is not able to detect this and the called API may not work as expected.



Caution
Category 0 ISRs are always executed with trusted rights on supervisor level.



Caution
A category 0 ISR may never lower the interrupt priority of the CPU or the interrupt controller.



Caution
Category 0 ISRs may still occur in case of a shutdown of the OS or even in case the OS has entered the panic hook.



Caution
Be aware that a category 0 ISR will interrupt category 2 ISRs even if they are configured to be non-nestable!



Caution
If the owner application of a category 0 ISR is terminated for any reason, assigned category 0 ISRs are not disabled.



Caution
The macro “OS_ISR0” abstracts the appropriate compiler keyword for implementing the interrupt service routine. Thus the compiler generates code which safes and restore a subset of the general purpose registers.

In certain use cases e.g. usage of the FPU or nested interrupts it may require the user application to save and restore more registers.

4.15 Floating Point Context Extension

4.15.1 Description

If several tasks or ISRs use FPU operations, there is the need to save and restore dedicated FPU registers upon context switches.
e.g. If a task, which uses the FPU, is preempted by another task or ISR which also uses the FPU as well.

MICROSAR OS offers the feature to configure save and restoration of the related floating-point registers upon context switch.

4.15.2 Usage

The parameter OsFpuUsage determines the scale of the feature:

- ALL: Dedicated FPU registers are saved upon each context switch
- INDIVIDUAL: Dedicated FPU registers are saved only for selected tasks or ISRs
- NONE: No dedicated FPU registers are saved upon context switches

The FPU configuration must be already set up by the user for each core before Os_Init() is called.



Note
On platforms with dedicated FPU registers, the OsFpuUsage values ALL and INDIVIDUAL require additional memory and runtime for FPU context handling.
See [9] for details.



Caution
If OsFpuUsage is enabled by configuration, the hardware FPU support must be enabled by appropriate compiler options on some platforms too.

4.16 User defined processor state

MICROSAR OS offers the user the possibility to change the processor state according to his needs by altering the flags which are NOT under control of the OS.
The OS never changes such flags but it saves and restores them during a context switch.



Note
State register flags which are under control of the OS can be looked up in the corresponding platform HSI chapter (see 5.2).

4.17 Interrupt Mapping

4.17.1 Description

MICROSAR OS offers the user the possibility to map certain interrupts to a hardware defined type. These interrupts are routed to the respective hardware specific interrupt controller.

4.17.2 Usage

The optional parameter OsIsrInterruptMapping can be used to configure a mapped interrupt. By default, this parameter is left empty and thus no mapping does apply. More details about interrupt mapping and its configuration can be found in [9].

4.18 Time Slice Scheduling

4.18.1 Description

MICROSAR OS offers an additional time slice scheduling strategy for tasks on the same priority level besides the FIFO strategy specified by AUTOSAR. With this method, tasks will be scheduled in a round robin like manner at configurable points in time.

4.18.2 Activation

Time slice scheduling can be enabled for a task by adding the container OsTaskRoundRobinScheduling to it. This container holds the parameter to configure the number of time slices a task may consume. To activate time slice scheduling, it is required to add exactly one alarm with the action OsAlarmScheduleEventRoundRobin for each core, which has round robin tasks configured.

4.18.3 Usage

Time slice scheduling uses an alarm whose callback function increases the number of time slices the currently running task consumed. After the task consumed the configured amount of time slices scheduling will take place. Therefore, time slice scheduling will only work if the alarm is set up to trigger time slicing events cyclically and has been started.

If a task uses time slice scheduling and its attribute OsTaskSchedule is set to NON or the task uses an internal resource, scheduling will not happen automatically. In these cases it is required to call the OS API Schedule(). However, time slice scheduling will still only take place if the task consumed all of its configured time slices.

If the number of configured time slices is consumed while the task holds a resource or a spinlock with lock method LOCK_WITH_RES_SCHEDULER, scheduling will not happen immediately. It will be delayed until the task releases the resource/spinlock.



Note
When enabling time slice scheduling for a task all tasks that are located on the same core and use the same priority level also have to use time slice scheduling.



Caution
Time slice scheduling as implemented in MICROSAR OS is not meant to provide exact execution budgets to the round robin tasks. It only just counts time slicing events for the currently running task and performs scheduling if the configured number has been reached. This means:

- Runtime of ISRs is accounted for the interrupted task.
- Runtime of preempting tasks is accounted for the preempted task if the preemption is short enough that no time slicing event occurs meanwhile.
- A full time slicing event is accounted for the currently running task even if it has just become active and other tasks have consumed most of the time between the last and the current time slicing event.
- Disabling interrupts may delay time slicing events.

4.18.3.1 Usage with OS resources

OS resources are commonly used to implement critical sections. With a call of GetResource(), the OS will increase the running priority of the calling task to the highest priority of all tasks which are configured to use the resource. With the AUTOSAR standard scheduling strategy, this will effectively prevent any other task, which is configured to use the same OS resource, to enter the running state. With time slice scheduling however, a round robin scheduling is still possible if the highest priority task wich is configured to use the OS resource has time slicing configured. In that case, a task on the same priority level will be able to take the same OS resource. That may happen by a call of GetResource() or, in case of an internal resource, simply by scheduling to that task. As a consequence, a resource may be taken more than once (no possible implementation of a critical section anymore) or GetResource() may return with an error message (dependent on the configuration).



Caution
OS resources may only be used to implement critical sections for round robin tasks if the highest priority task, configured to access the resource, has higher priority than the round robin tasks.

5 Integration

5.1 Compiler Optimization Assumptions

MICROSAR OS makes the following assumptions for compiler optimization:

> Inlining of functions is active

> Not used functions are removed

> If statements with a constant condition (due to configuration) are optimized

5.1.1 Compile Time

To shorten the compile time of the OS the following measures can be taken within the OS configuration:

Systems without active memory protection (SC1/SC2)	Set “OsGenerateMemMap” to “EMPTY”
Systems with memory protection (SC3/SC4)	Set “OsGenerateMemMap” to “COMPLETE” and "OsGenerateMemMapForThreads” to “FALSE”

5.2 Hardware Software Interfaces (HSI)

The Hardware Software Interface describes all hardware registers which are used by the OS. Such registers must not be altered by user software.



Expert Knowledge

User software is allowed to access timer hardware registers in case no OS counter has been configured to use the corresponding timer. To verify that this case applies, check that the */MICROSAR/Os/OsCounter/OsDriver/OsDriverHardwareTimerChannelRef* of no OS counter references the desired timer hardware.

Included within the HSI is the context of the OS. The context is the sum of all registers which are preserved upon a task switch and ISR execution.

The detailed description of the HSI can be found in [9].

5.3 Memory Mapping Concept

MICROSAR OS uses the AUTOSAR MemMap mechanism to locate its own variables but also application variables.



Note
To use the OS memory mapping concept within the AUTOSAR MemMap mechanism the generated OS file “Os_MemMap.h” has to be included into “MemMap.h”.
It should be included after the inclusion of the MemMap headers of all other basic software components.

5.3.1 Provided MemMap Section Specifiers

MICROSAR OS uses and specifies section specifiers as described in the AUTOSAR specification of memory mapping. All section specifiers have one of the following forms:

OS_START_SEC_<SectionType>[_<InitPolicy>][_<Alignment>]

OS_STOP_SEC_<SectionType>[_<InitPolicy>][_<Alignment>]



Note
Due to clarity and understanding this chapter does only refer to section specifiers that shall be handled by the application.
The OS internally used section specifiers are not listed here.

SectionType	InitPolicy	Alignment
<Callout>_CODE	-	-
NONAUTOSAR_CORE<Core Id>_CONST	-	UNSPECIFIED
NONAUTOSAR_CORE<Core Id>_VAR	NOINIT	UNSPECIFIED
<ApplicationName>_VAR	- NOINIT ZERO_INIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
<ApplicationName>_VAR_FAST	- NOINIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
<ApplicationName>_VAR_NOCACHE	- NOINIT	BOOLEAN 8BIT

	ZERO_INIT	16BIT 32BIT UNSPECIFIED
<ApplicationName>_CONST	-	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
<ApplicationName>CONST_FAST	-	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED

SectionType	InitPolicy	Alignment
<Task/IsrName>_VAR	- NOINIT ZERO_INIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
<Task/IsrName>_VAR_FAST	- NOINIT ZERO_INIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
<Task/IsrName>_CONST	-	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
<Task/IsrName>_CONST_FAST	-	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED

SectionType	InitPolicy	Alignment
GLOBALSHARED_VAR	- NOINIT ZERO_INIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED

GLOBALSHARED_VAR_FAST	- NOINIT ZERO_INIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
GLOBALSHARED_VAR_NOCACHE	- NOINIT ZERO_INIT	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
GLOBALSHARED_CONST	-	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
GLOBALSHARED_CONST_FAST	-	BOOLEAN 8BIT 16BIT 32BIT UNSPECIFIED
APPSHARED_0X<application bitmask>_VAR_NOCACHE	NOINIT	UNSPECIFIED
CORESHARED_0X<core bitmask>_VAR_NOCACHE	NOINIT	UNSPECIFIED

Table 5-1 Provided MemMap Section Specifiers



Note

The < application bitmask >: Is a bitmask that specifies all OS applications which are sharing the section.



Note

The < core bitmask >: Is a bitmask that specifies all cores which are sharing the section.

5.3.1.1 Usage of MemMap Macros



Example

```
#define OS_START_SEC_MyAppl_VAR_FAST_NOINIT_UNSPECIFIED
#include "MemMap.h"
uint16 MyApplicationVariable;
#define OS_STOP_SEC_MyAppl_VAR_FAST_NOINIT_UNSPECIFIED
#include "MemMap.h"
```

This code snippet puts the user variable into an OS application section.

5.3.1.2 Resulting sections

The usage of the above described macros will result in the following memory sections:

SectionType	Content / Description
OS_CODE	> OS Code
OS_INTVEC_CODE	> Interrupt vector table in case the system needs one generic vector table for all cores
OS_INTVEC_CORE<Core Id>_CODE	> Interrupt vector table of one specific core
OS_EXCVEC_CORE<Core Id>_CODE	> Exception vector table of one core

Table 5-2 MemMap Code Sections Descriptions

The resulting sections for callouts are generated in dependency of the configuration attribute "/MICROSAR/Os/OsOS/OsGenerateMemMap".

OsGenerateMemMap	Section	Content
USERCODE_AND_STACKS_GROUPED_PER_CORE	OS_USER_CORE<Core Id>_CODE	> Code of all Tasks, ISRs and all other user callouts which are mapped on one core.
COMPLETE	OS_<Callout>_CODE	> Code of one Task or one ISR or one OS Hook or other callouts.

Table 5-3 MemMap Callout Code Sections Descriptions



Note

The MPU may be set up to grant execution from the whole address space.

SectionType	Content / Description
OS_CONST	> OS constant data
OS_CONST_FAST	> OS constant data for fast memory
OS_INTVEC_CONST	> Interrupt vector table in case the system needs one generic vector table for all cores
OS_CORE<Core Id>_CONST	> OS constant data related to one specific core
OS_CORE<Core Id>_CONST_FAST	> OS constant data related to one specific for fast memory
OS_INTVEC_CORE<Core Id>_CONST	> Interrupt vector table of one specific core
OS_EXCVEC_CORE<Core Id>_CONST	> Exception vector table of one core
OS_NONAUTOSAR_CORE<Core Id>_CONST	> OS constant data of a non-AUTOSAR core
OS_NONAUTOSAR_CORE<Core Id>_CONST_FAST	> OS constant data of a non-AUTOSAR core with shord addressing
OS_GLOBALSHARED_CONST	> Constants which shall be shared among core boundaries
OS_GLOBALSHARED_CONST_FAST	> Constants which shall be shared among core boundaries and which use short addressing accesses (e.g. by base address pointer)
OS_<Task/IsrName>_CONST	> Thread specific constants
OS_<Task/IsrName>_CONST_FAST	> Thread specific constants which use short addressing accesses (e.g. by base address pointer)
OS_<ApplicationName>_CONST	> Application specific constants
OS_<ApplicationName>_CONST_FAST	> Application specific constants which use short addressing accesses (e.g. by base address pointer)

Table 5-4 MemMap Const Sections Descriptions



Note
The MPU may be set up to grant read access to const sections from all runtime contexts (trusted and non-trusted)

Section	Content
OS_VAR_NOCACHE	

OS_VAR_NOCACHE_NOINIT	OS global variables. All cores may have to access these variables.
OS_VAR_FAST_NOCACHE	
OS_VAR_FAST_NOCACHE_NOINIT	
OS_CORE<Core Id>_VAR	OS core local variables. These variables are never accessed from foreign cores.
OS_CORE<Core Id>_VAR_FAST	
OS_CORE<Core Id>_VAR_NOINIT	
OS_CORE<Core Id>_VAR_FAST_NOINIT	
OS_CORE<Core Id>_VAR_NOCACHE	
OS_CORE<Core Id>_VAR_FAST_NOCACHE	
OS_CORE<Core Id>_VAR_NOCACHE_NOINIT	
OS_CORE<Core Id>_VAR_FAST_NOCACHE_NOINIT	
OS_PUBLIC_CORE<Core Id>_VAR_NOINIT	OS core local variables. These variables may also be accessed from foreign cores
OS_PUBLIC_CORE<Core Id>_VAR_FAST_NOINIT	
OS_APPSHARED_0X<application bitmask>_VAR_NOCACHE_NOINIT	OS optimized spinlock variables. Only OS applications specified by <application bitmask> have access to them.
OS_CORESHARED_0X<core bitmask>_VAR_NOCACHE_NOINIT	OS Standard/Optimized spinlock variables. IOC data structures. All cores wich are specified by <core bitmask> have access to them.
OS_NONAUTOSAR_CORE<Core Id>_VAR	User core local variables of non-AUTOSAR cores. Access to these from foreign cores may be allowed.
OS_NONAUTOSAR_CORE<Core Id>_VAR_FAST	
OS_NONAUTOSAR_CORE<Core Id>_VAR_NOINIT	
OS_NONAUTOSAR_CORE<Core Id>_VAR_FAST_NOINIT	

Section	Content
OS_GLOBALSHARED_VAR	User global shared variables. All cores have access to them.
OS_GLOBALSHARED_VAR_FAST	
OS_GLOBALSHARED_VAR_NOINIT	
OS_GLOBALSHARED_VAR_FAST_NOINIT	
OS_GLOBALSHARED_VAR_ZERO_INIT	
OS_GLOBALSHARED_VAR_NOCACHE	
OS_GLOBALSHARED_VAR_FAST_NOCACHE	

OS_GLOBALSHARED_VAR_NOCACHE_NOINIT	
OS_GLOBALSHARED_VAR_FAST_NOCACHE_NOINIT	
OS_GLOBALSHARED_VAR_NOCACHE_ZERO_INIT	
OS_<ApplicationName>_VAR	User application private variables. Only application members and other trusted software may have access to them.
OS_<ApplicationName>_VAR_FAST	
OS_<ApplicationName>_VAR_NOINIT	
OS_<ApplicationName>_VAR_FAST_NOINIT	
OS_<ApplicationName>_VAR_FAST_ZERO_INIT	
OS_<ApplicationName>_VAR_NOCACHE	
OS_<ApplicationName>_VAR_FAST_NOCACHE	
OS_<ApplicationName>_VAR_NOCACHE_NOINIT	
OS_<ApplicationName>_VAR_FAST_NOCACHE_NOINIT	
OS_<ApplicationName>_VAR_NOCACHE_ZERO_INIT	

Section	Content
OS_<Task/IsrName>_VAR	User thread private variables. Only the owning thread and other trusted software may have access to them
OS_<Task/IsrName>_VAR_FAST	
OS_<Task/IsrName>_VAR_NOINIT	
OS_<Task/IsrName>_VAR_FAST_NOINIT	
OS_<Task/IsrName>_VAR_ZERO_INIT	
OS_BARRIER_CORE<Core Id>_VAR_NOCACHE_NOINIT	OS synchronization barriers. Only the OS must have access to them. They will be accessed from all cores
OS_BARRIER_CORE<Core Id>_VAR_FAST_NOCACHE_NOINIT	
OS_CORESTATUS_CORE<Core Id>_VAR_ NOCACHE_NOINIT	Startup state of each physical core. Only the OS must have access to them. They will be written by the master core and the owning core itself, and read from all cores.
OS_CORESTATUS_CORE<Core Id>_VAR_FAST_NOCACHE_NOINIT	

Table 5-5 MemMap Variable Sections Descriptions

The resulting sections for stacks are generated in dependency of the configuration attribute “/MICROSAR/Os/OsOS/OsGenerateMemMap”.

OsGenerateMemMap	Section	Content
USERCODE_AND_STACKS_GROUPED_PER_CORE	OS_STACK_CORE<Core Id>_VAR_NOINIT	Contains all stacks of one core. Only the current running software has access to the stack. Software which runs on a foreign core must not have access to it.
COMPLETE	OS_STACK_<StackName>_VAR_NOINIT	Contains one OS stack. Only the current running software has access to the stack. Software which runs on a foreign core must not have access to it.

Table 5-6 MemMap Variable Stack Sections Descriptions



Notes

Sections which contain the keyword “FAST” are intended to be linked into fast RAM.

Sections which contain the keyword “NOCACHE” must never be linked into cacheable memory.

Sections which contain the keyword “NOINIT” contain non-initialized variables.

Sections which contain the keyword “ZERO_INIT” contain zero initialized variables.

5.3.1.3 Access Rights to Variable Sections

The table shows the recommended access rights to the sections.

Section	Local core trusted	Local core non trusted	Foreign core trusted	Foreign core non trusted
OS_VAR_NOCACHE	RW	RO	RW	RO
OS_VAR_NOCACHE_NOINIT				
OS_VAR_FAST_NOCACHE				
OS_VAR_FAST_NOCACHE_NOINIT				
OS_CORE<Core Id>_VAR	RW	RO	RO	RO
OS_CORE<Core Id>_VAR_FAST				
OS_CORE<Core Id>_VAR_NOINIT				
OS_CORE<Core Id>_VAR_FAST_NOINIT				
OS_CORE<Core Id>_VAR_NOCACHE				
OS_CORE<Core Id>_VAR_FAST_NOCACHE				
OS_CORE<Core Id>_VAR_NOCACHE_NOINIT				
OS_CORE<Core Id>_VAR_FAST_NOCACHE_NOINIT				
OS_PUBLIC_CORE<Core Id>_VAR_NOINIT	RW	RO	RW	RO
OS_PUBLIC_CORE<Core Id>_VAR_FAST_NOINIT				
OS_NONAUTOSAR_CORE<Core Id>_VAR	RW	RO	RW	RO
OS_NONAUTOSAR_CORE<Core Id>_VAR_FAST				
OS_NONAUTOSAR_CORE<Core Id>_VAR_NOINIT				
OS_NONAUTOSAR_CORE<Core Id>_VAR_FAST_NOINIT				
OS_GLOBALSHARED_VAR	RW	RW	RW	RW
OS_GLOBALSHARED_VAR_FAST				
OS_GLOBALSHARED_VAR_NOINIT				
OS_GLOBALSHARED_VAR_FAST_NOINIT				
OS_GLOBALSHARED_VAR_ZERO_INIT				
OS_GLOBALSHARED_VAR_NOCACHE				
OS_GLOBALSHARED_VAR_FAST_NOCACHE				
OS_GLOBALSHARED_VAR_NOCACHE_NOINIT				
OS_GLOBALSHARED_VAR_FAST_NOCACHE_NOINIT				
OS_GLOBALSHARED_VAR_NOCACHE_ZERO_INIT				

Section	Local core trusted	Local core non trusted	Foreign core trusted	Foreign core non trusted
OS_<ApplicationName>_VAR	RW	RW	RW	RO
OS_<ApplicationName>_VAR_FAST				
OS_<ApplicationName>_VAR_NOINIT				
OS_<ApplicationName>_VAR_FAST_NOINIT				
OS_<ApplicationName>_VAR_FAST_ZERO_INIT				
OS_<ApplicationName>_VAR_NOCACHE				
OS_<ApplicationName>_VAR_FAST_NOCACHE				
OS_<ApplicationName>_VAR_NOCACHE_NOINIT				
OS_<ApplicationName>_VAR_FAST_NOCACHE_NOINIT				
OS_<ApplicationName>_VAR_NOCACHE_ZERO_INIT				
OS_<Task/IsrName>_VAR	RW	RW	RW	RO
OS_<Task/IsrName>_VAR_FAST				
OS_<Task/IsrName>_VAR_NOINIT				
OS_<Task/IsrName>_VAR_FAST_NOINIT				
OS_<Task/IsrName>_VAR_ZERO_INIT				
OS_BARRIER_CORE<Core Id>_VAR_NOCACHE_NOINIT	RW	RO	RW	RO
OS_BARRIER_CORE<Core Id>_VAR_FAST_NOCACHE_NOINIT				
OS_CORESTATUS_CORE<Core Id>_VAR_ NOCACHE_NOINIT	RW	RO	RW	RO
OS_CORESTATUS_CORE<Core Id>_VAR_FAST_NOCACHE_NOINIT				

Table 5-7 Recommended Section Access Rights



Note
The access to the stack section is handled completely by MICROSAR OS



Note
The table is only valid for cores which have the same diagnostic level. Cores with a lower diagnostic level must never interact with data from a core with a higher diagnostic level.

5.3.1.4 Access Rights to Shared Data Sections

Section	Access Rights
OS_APPSHARED_0X<application bitmask>_VAR_NOCACHE_NOINIT	Only applications which are specified by the <application bitmask> shall have read / write access. The bitmasks of applications may be looked up in “Os_Types_Lcfg.h” > "ApplicationType".
OS_CORESHARED_0X<core bitmask>_VAR_NOCACHE_NOINIT	Only cores which are specified by the <core bitmask> shall have read / write access. The bitmasks of cores may be looked up in “Os_Hal_Lcfg.h” > "CoreIdType".

Table 5-8 Recommended Shared Data Section Access Rights

The shared data sections are used to achieve freedom from interference between cores with different diagnostic coverage capability.

The table below shows the recommended access rights to the sections.

Section	Local core trusted	Local core non trusted	Foreign core trusted	Foreign core non trusted
OS_APPSHARED_0X<application bitmask>_VAR_NOCACHE_NOINIT	RW	RO	RW	RO
OS_CORESHARED_0X<core bitmask>_VAR_NOCACHE_NOINIT				

Table 5-9 Recommended Shared Data Section Core Access Rights

5.3.2 Link Sections

Once variables have been put into OS sections (by usage of the section specifiers described in 5.3.1.1) the sections would have to be linked.

Therefore MICROSAR OS generates linker command files which utilize the linkage of those sections.

Linker Command Filename	Content
Os_Link_<Core>.<FileSuffix>	All data and code sections which are bound to a core
Os_Link.<FileSuffix>	All data and code sections which are global
Os_Link_<Core>_Stacks.<FileSuffix>	all stacks of a core

Table 5-10 List of Generated Linker Command Files



Note
<Core> is the logical core ID
<FileSuffix> is the suffix for linker command files. It depends on the used compiler.

5.3.2.1 Pre-Process Linker Command Files

The generated linker command files uses C pre-processor statements. Some Linkers don't understand pre-processor statements. These Linkers require a pre-processing step on the linker command files.

Windriver DiabData	The pre-processor should be used on command line to pre-process the linker command files e.g.: `dcc.exe -P Os_Link.dld -o Os_Link_new.dld`

5.3.2.2 Simple Linker Defines

The following defines are used to select groups of OS sections from the linker command files.

Select OS code	OS_LINK_CODE
Select an interrupt vector table	OS_LINK_INTVEC_CODE
Select an exception vector table	OS_LINK_EXCVEC_CODE
Select user callouts (Tasks, ISRs, Hooks)	OS_LINK_CALLOUT_CODE
Select constants related to an interrupt vector table	OS_LINK_INTVEC_CONST
Select constants related to an exception vector table	OS_LINK_EXCVEC_CONST
Select OS stacks	OS_LINK_KERNEL_STACKS



Example

```
#define OS_LINK_INTVEC_CODE
#include Os_Link_Core0.lsl
```

Selects the interrupt vector table from the included linker command file for linking.

5.3.2.3 Hierachical Linker Defines

The linker command files are intended to be included into a main linker command file.
Single sections or group of sections can be selected for linkage by usage of C-like defines.
This mechanism is similar to the MemMap mechanism of AUTOSAR.
The linker defines of MICROSAR OS uses a hierarchical syntax.
The more one walks down in the hierarchy the less sections are selected.



Note

Once one have made the decision for a specific hierarchical level one will have to stick to this level throughout the linker defines group. Otherwise there may be multiple section definitions.

5.3.2.4 Selecting OS constants

These are hierarchical linker defines

Prefix	Optional Hierarchy level 1
OS_LINK_CONST_KERNEL	_NEAR _FAR

Table 5-11 OS constants linker define group



Example

```
#define OS_LINK_CONST_KERNEL
#include Os_Link_Core0.lsl
```

Selects all OS constants.



Example

```
#define OS_LINK_CONST_KERNEL_NEAR
#include Os_Link_Core0.lsl
```

Selects all near addressable OS constants only.

5.3.2.5 Selecting OS variables

These are hierarchical linker defines

Prefix	Optional Hierarchy level 1	Optional Hierarchy level 2	Optional Hierarchy level 3
OS_LINK_VAR_KERNEL	_NEAR _FAR	_CACHE _NOCACHE	_INIT _NOINIT

Table 5-12 OS variables linker define group



Example

```
#define OS_LINK_VAR_KERNEL
#include Os_Link_Core0.lsl
```

Selects all OS variables.



Example

```
#define OS_LINK_VAR_KERNEL_NEAR_CACHE
#include Os_Link_Core0.lsl
```

Selects all OS variables which are near addressable and cacheable.

5.3.2.6 Selecting special OS Variables

These are hierarchical linker defines

Prefix	Optional Hierarchy level 1
OS_LINK_KERNEL_BARRIERS	_NEAR _FAR
OS_LINK_KERNEL_CORESTATUS	
OS_LINK_KERNEL_TRACE	

Table 5-13 OS Barriers and Core status linker define group



Example

```
#define OS_LINK_KERNEL_BARRIERS
#include Os_Link_Core0.lsl
```

Selects all OS Barriers.



Example

```
#define OS_LINK_KERNEL_CORESTATUS
#include Os_Link_Core0.lsl
```

Selects all OS core state variables.

Prefix	Optional Hierarchy level 1	Owner Bitmask	Optional Hierarchy level 2
OS_LINK_VAR	_APPSHARED	_0X<application bitmask>	_NEAR _FAR
	_CORESHARED	_0X<core bitmask>	



Example

```
#define OS_LINK_VAR_APPSHARED
#include Os_Link.lsl
```

Selects all OS application shared variables

5.3.2.7 Selecting User Constant Sections

These are hierarchical linker defines

Prefix	Optional Hierarchy level 1	Owner Name	Optional Hierarchy level 2
OS_LINK_CONST	_APP	<Owner Name>	_NEAR _FAR
	_TASK		
	_ISR		
	_GLOBALSHARED	---	

Table 5-14 User constants linker define group



Example

```
#define OS_LINK_CONST_APP_<ApplicationName>
#include Os_Link_Core0.lsl
```

Selects all constants which belong to the OS application <ApplicationName>



Example

```
#define OS_LINK_CONST_ISR_<ISRName>_FAR
#include Os_Link_Core0.lsl
```

Selects all constants which belong to the ISR <ISRName> which have far addressing

5.3.2.8 Selecting User Variable Sections

These are hierarchical linker defines

Prefix	Optional Hierarchy level 1	Owner Name	Optional Hierarchy level 2	Optional Hierarchy level 3	Optional Hierarchy level 4
OS_LINK_VAR	_APP	<Owner Name>	_NEAR _FAR	_CACHE _NOCACHE	_INIT _NOINIT _ZEROINIT
	_TASK				
	_ISR				
	_GLOBALSHARED	---			

Table 5-15 User variables linker define group



Example

```
#define OS_LINK_VAR_APP_<ApplicationName>
#include Os_Link_Core0.lsl
```

Selects all variables which belong to the OS application <ApplicationName>

© 2020 Vector Informatik GmbH



Example

```
#define OS_LINK_VAR_APP_<ApplicationName>_FAR_CACHE_INIT
#include Os_Link_Core0.lsl
```

Selects all variables which belong to the OS application <ApplicationName> which have far addressing, are cacheable and are initialized

5.3.3 Section Symbols

The linker command files described in 0 also generate section start and stop symbols which can be used to configure start and end addresses of MPU regions, peripheral regions or access check region objects.

The generated linker section start and stop symbols have the following syntax:

_OS_<SectionType>_START

_OS_<SectionType>_END

_OS_<SectionType>_LIMIT

The symbol _OS_<SectionType>_END points to the last accessible address of a region.

The symbol _OS_<SectionType>_LIMIT points to the first address after the region.



Example

Const data which belongs to section OS_MyAppl_CONST is included within the symbols

_OS_MyAppl_CONST_START

_OS_MyAppl_CONST_END

_OS_MyAppl_CONST_LIMIT

Data which belongs to section OS_MyAppl_VAR_FAST is included within the symbols

_OS_MyAppl_VAR_FAST_START

_OS_MyAppl_VAR_FAST_END

_OS_MyAppl_VAR_FAST_LIMIT

Data which belongs to section OS_MyTask_VAR_FAST is included within the symbols

_OS_MyTask_VAR_FAST_START

_OS_MyTask_VAR_FAST_END

_OS_MyTask_VAR_FAST_LIMIT

5.3.3.1 Aggregation of Data Sections

Additional start and stop linker symbols are generated which contain all data sections of applications, tasks and ISRs. These symbols can be used to configure start and end addresses of MPU regions, peripheral regions or access check region objects.

These start and stop linker symbols have the syntax:

_OS_<SectionOwner>_VAR_ALL_START

_OS_<SectionOwner>_VAR_ALL_END

_OS_<SectionOwner>_VAR_ALL_LIMIT

<SectionOwner> is name of applications, tasks and CAT2 ISRs used in configurator.

The symbol _OS_<SectionOwner>_VAR_ALL_END points to the last accessible address of a region.

The symbol _OS_<SectionOwner>_VAR_ALL__LIMIT points to the first address after the region.



Example

All data sections which belong to application “MyAppl” are included within the symbols

_OS_MyAppl_VAR_ALL_START

_OS_MyAppl_VAR_ALL_END

_OS_MyAppl_VAR_ALL_LIMIT

All data sections which belong to task “MyTask” are included within the symbols

_OS_MyTask_VAR_ALL_START

_OS_MyTask_VAR_ALL_END

_OS_MyTask_VAR_ALL_LIMIT

All data sections which belong to CAT2 ISR “MyISR” are included within the symbols

_OS_MyISR_VAR_ALL_START

_OS_MyISR_VAR_ALL_END

_OS_MyISR_VAR_ALL_LIMIT

5.4 Static Code Analysis



Note

When running tools for static code analysis (e.g. MISRA, MSSV), the pre-processor definition OS_STATIC_CODE_ANALYSIS has to be set during analysis. It switches off compiler specific keywords and inline assembler parts. Typically code analysis tools cannot deal with such code parts.

5.5 Configuration of X-Signals

This chapter describes how X-Signals are configured for cross core API calls. Note that X-Signals are used only to provide the Cross Core API functions as described in this document and in the Autosar OS Standard. They do not provide functionality to the application directly. See chapter 4.9 for a better understanding of X-Signals.

1. Add an “OsCoreXSignalChannel” to an “OsCore” object. This core will be the sender of the X-Signal.
2. Specify the queue size of the channel with the “OsCoreXSignalChannelSize” attribute.
3. Add an X-Signal receiver ISR. It must be of category 2.
4. Assign this ISR to be the X-Signal receiver “OsCore/OsCoreXSignalChannelReceiverIsr”.
5. Configure an appropriate interrupt priority for the receiver ISR (see the following chapter for VTT details and [9] for platform specific details). The configured priority must follow the rules listed in Table 4-3.
6. Choose an appropriate interrupt source for the receiver ISR (see the following chapter for VTT details and [9] for platform specific details).
7. Add the "OsIsrXSignalReceiver" to the receiver ISR and select the provided APIs (callable from the sender core) with the "OsIsrXSignalReceiverProvidedApis" attribute.



Note
The DaVinci Configurator provides solving actions which support the correct configuration of X-Signals.

5.5.1 VTT OS

Logical Priority	A low number for OsIsrInterruptPriority attribute means a low logical priority
X-Signal ISR Interrupt Priority	Beside the rules listed in Table 4-3 the OsIsrInterruptPriority can be chosen freely.
X-Signal ISR Interrupt Source	Any interrupt source, which is not used by other modules, may be used for the X-Signal ISR.

5.6 OS generated objects

In dependency of its configuration MICROSAR OS may add other OS configuration objects to it.

5.6.1 System Application

Type	OsApplication
Name	SystemApplication_<CoreName>
Condition	Is added when the OsCore <CoreName> is configured to be an AUTOSAR core.
Features	> A system application contains the OS objects > IdleTask_<CoreName> > TpCounter_<CoreName> > XSignalIsr_<CoreName> > CounterIsr_TpCounter_<CoreName>



User configured OS objects
The System Application shall not contain any user configured OS objects in case of SC2, SC3 and SC4 systems. As defined by AUTOSAR the user shall configure additional Applications for user defined OS objects.

5.6.2 Idle Task

Type	OsTask
Name	IdleTask_<CoreName>
Condition	Is added when the OsCore <CoreName> is configured to be an AUTOSAR core.
Features	> Has the lowest priority of all tasks assigned to the same core. > Is fully preemptive. > Is implemented by the OS



Idle Task Priority
The generator has a special treatment for the idle task. The idle task has the virtual priority 0xFFFFFFFF to differentiate it from regular tasks. It will be generated to have the lowest priority, even if there are tasks configured with priority 0.



User Code Execution
The idle task is implemented by the OS to simplify scheduling and idle treatment. The OS does not rely on execution of the idle task. Implement an additional task with priority 0, if user code execution during idle time is needed.

5.6.3 Timer ISR

Type	OsIsr
Name	CounterIsr_<CoreName>
Condition	Is added if a hardware OsCounter is configured to have a driver (attribute “OsCounterDriver”).
Features	> Is Implemented by the OS. > Handles the system timer counter, alarms and scheduletables which are assigned to the core.

5.6.4 System Timer Counter

Type	OsCounter
Name	SystemTimer
Condition	Is added optionally within the recommended configuration.
Features	> Is used for OSEK backward compatibility

5.6.5 Timing Protection Counter

Type	OsCounter
Name	TpCounter_<CoreName>
Condition	Is added when OsTask/IsrTimingProtection parameters are configured on the core.
Features	> Handles all times related to timing protection

5.6.6 Timing protection ISR

Type	OsIsr
Name	CounterIsr_TpCounter_<CoreName>
Condition	Is added when OsTask/IsrTimingProtection parameters are configured on the core.
Features	> Interrupt service routine of the timing protection feature

5.6.7 Resource Scheduler

Type	OsResource
Name	RES_SCHEDULER_<CoreName>
Condition	For each core the resource scheduler is added when OsUseResScheduler is set to TRUE.
Features	> Is automatically assigned to all tasks of core <CoreName>

5.6.8 X-Signal ISR

Type	OsIsr
Name	XSignalIsr_<CoreName>
Condition	Is added when an X-Signal channel is configured on the core.
Features	> Handles cross core requests.

5.6.9 IOC Spinlocks

Type	OsSpinlock
Name	IocSpinlock_<IOC Name>
Condition	Is added when an IOC is configured which requires cross core communication.
Features	> Each IOC has its own spinlock to reduce core wait times

5.7 VTT OS Specifics

5.7.1 Configuration

As described in [6] all VTT configuration parameters are derived from the hardware target. The only exceptions are the ISR objects for the VTT OS.

- ➔ ISRs from other Vector MICROSAR BSW vVIRTUALtarget driver modules (e.g. VTTCan) are inserted automatically by the respective BSW module.
- ➔ ISRs from other modules and user ISRs have to be added separately.
- ➔ Interrupt levels for all ISRs have to be configured manually. VTT OS knows interrupt levels from 1 to 200 (where 1 is the lowest priority and 200 the highest).

5.7.2 CANoe Interface

A VTT OS is simulated within the CANoe simulation software. There are a set of API functions which are capable to communicate with CANoe (e.g. sending a message on the CAN bus).

These API functions are prefixed with “CANoeAPI_”.

The available set of API functions can be looked up in the delivered header “CANoeApi.h”.

5.7.2.1 Idle Task behavior with VTT OS

Any idle task which runs within the VTT OS must call the function “CANoeAPI_ConsumeTicks” (see description in CANoeApi.h).



Caution
If the call of “CANoeAPI_ConsumeTicks” is missing within the idle task, the CANoe windows application won’t respond any longer!

There are two possible solutions which solves this problem:

1. The OS generated idle task (see 5.6.2) calls this function by default. The application has to ensure that this idle task is entered cyclically.
2. It may be that the OS idle task is never executed, because there is a higher priority application idle task. This application idle task must implement a cyclic call of “CANoeAPI_ConsumeTicks” instead of the OS idle task.

5.8 User include files

Within some features of MICROSAR OS it may be necessary to provide foreign data types to the OS.

This can be done by referencing user headers within the OS configuration.

The features “IOC” and “trusted functions stub generation” are relying on such include mechanisms.

	Configuration	Content
IOC	IOC include files are configured with the IOC attribute "OsIocIncludeHeader“. A list of include files may be specified here.	The headers have to provide > Definitions of foreign OS data types which are used within IOC communication.
Trusted Functions	Include files which are needed for trusted function feature are configured within the application attribute “OsAppCalloutStubsIncludeHeader”. A list of include files may be specified here.	The headers have to provide > The definitions of foreign OS data types which are used as trusted functions parameters or return values.



Caution
All user include files need to implement a double inclusion preventer!

5.9 Preprocessing of assembler language files

Dependent on the hardware platform, MICROSAR OS may use preprocessing of assembly language files. However, some of the supported compiler tool chains do not allow to preprocess assembly language files with the normal C preprocessor. Therefore, the compiler or the assembler may state some error messages.

In such a case, another preprocessor may be used.



Example
The following compiler tool suite does not support preprocessing of assembly language files: TI compiler (Texas Instruments).

The following tool of the GNU compiler collection has shown to work correctly on the files delivered with MICROSAR OS:

cpp (tdm-1) 4.9.2

It should be used in the following way:

```
cpp.exe -P -DOS_CFG_DERIVATIVEGROUP_<YourDerivativeGroup>
        -DOS_CFG_COMPILER_TEXASINSTRUMENTS
        -I$(PATH_OS_IMPLEMENTATION) -I$(PATH_OS_GENDATA)
        <YourAssemblyFile>.asm -o $(PATH_OUTPUT)
```

5.10 Stack Summary

The DaVinci configurator provides an overview of all internal calculated stacks in a separated table in /MICROSAR/Os/OsOS/OsStackSummary.

For example, this overview table can be used to determine which task uses which stack and how the size is configured.



Note
This stack summary is automatically created and updated during configuration by the OS generator. Manual configuration of stacks in this summary is not supported.

The size must be configured at the stack size parameter of the container which is referenced as user (e.g. OsTaskStackSize).



Basic Knowledge
For shared stacks the biggest configured stack size of all users is used to set up the stack size in the summary.

6 API Description

This chapter lists all API service functions which are provided by MICROSAR OS.

6.1 Specified OS services

The OS provides the following services which are specified within the AUTOSAR OS specification.

6.1.1 StartCore

Prototype	
`void StartCore (CoreIdType CoreID, StatusType *Status)`	
Parameter	
CoreID [in]	The core to start.
Status [out]	Status code.
Return code	
void	> E_OK No Error. E_OS_ID (EXTENDED status:) > - Core ID is invalid. > - Core is no AUTOSAR core. E_OS_ACCESS (EXTENDED status:) The function was called after starting the OS. E_OS_STATE (EXTENDED status:) The Core is already activated.
Functional Description	
OS service StartCore().	
Particularities and Limitations	
> Pre-Condition: Supervisor mode. Pre-Condition: Given object pointer(s) are valid. Starts the core given by CoreID that is controlled by the AUTOSAR OS. This API is allowed to be used from AUTOSAR and non-AUTOSAR cores.	
Call context	
> - > This function is Synchronous > This function is Non-Reentrant	

Table 6-1 StartCore

6.1.2 StartNonAutosarCore

Prototype	
`void StartNonAutosarCore (CoreIdType CoreID, StatusType *Status)`	
Parameter	
CoreID	The core to start.
Status [out]	Status code.
Return code	
void	E_OK No Error. E_OS_ID (EXTENDED status:) Core ID is invalid. E_OS_STATE (EXTENDED status:) The Core is already activated.
Functional Description	
OS service StartNonAutosarCore().	
Particularities and Limitations	
Pre-Condition: Supervisor mode. Starts the core given by CoreID that is not controlled by the AUTOSAR OS.	
Call context	
> - > This function is Synchronous > This function is Non-Reentrant	

Table 6-2 StartNonAutosarCore

6.1.3 GetCoreID

Prototype	
`CoreIdType` **`GetCoreID`** `(void)`	
Parameter	
void	none
Return code	
CoreIdType	Unique ID of the calling core.
Functional Description	
OS service GetCoreID().	
Particularities and Limitations	
Pre-Condition: None Returns the unique logical core identifier of the core on which the function is called. The mapping of physical cores to logical CoreIDs is implementation specific. This API is allowed to be used from AUTOSAR cores only. If the API is required on a non-AUTOSAR core, it is possible to configure the core as an AUTOSAR core but start it as a non-AUTOSAR core using the StartNonAutosarCore() API.	
Call context	
> ANY > This function is Synchronous > This function is Reentrant	

Table 6-3 GetCoreID

6.1.4 GetNumberOfActivatedCores

Prototype	
`uint32 GetNumberOfActivatedCores (void)`	
Parameter	
void	none
Return code	
uint32	Number of cores activated by the StartCore() function.
Functional Description	
OS service GetNumberOfActivatedCores().	
Particularities and Limitations	
Pre-Condition: None The function returns the number of cores activated by the StartCore() function. AUTOSAR specifies this function to be usable from task and ISR call level. But this function does not explicitly perform any call context checks. There is no need to, because it is a primitive getter function.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-4 GetNumberOfActivatedCores

6.1.5 GetActiveApplicationMode

Prototype	
`AppModeType` **`GetActiveApplicationMode`** `(void)`	
Parameter	
void	none
Return code	
AppModeType	Current Application Mode
Functional Description	
OS service GetActiveApplicationMode().	
Particularities and Limitations	
Pre-Condition: None This service returns the current application mode.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-5 GetActiveApplicationMode

6.1.6 StartOS

Prototype	
`void StartOS (AppModeType Mode)`	
Parameter	
Mode [in]	The application mode in which the OS shall start.
Return code	
void	none
Functional Description	
OS service StartOS().	
Particularities and Limitations	
> Pre-Condition: Supervisor mode. Pre-Condition: Os_Init() has been called before. Starts the operating system in a given application mode.	
Call context	
> - > This function is Synchronous > This function is Non-Reentrant	

Table 6-6 StartOS

6.1.7 ShutdownOS

Prototype	
`void ShutdownOS (StatusType Error)`	
Parameter	
Error	Error code which shall be passed to the ShutdownHook()
Return code	
void	none
Functional Description	
OS service ShutdownOS().	
Particularities and Limitations	
Pre-Condition: None This function shall shutdown the core on which it was called. Only allowed in trusted applications. In case that ShutdownOS() is called from an invalid context, OS_STATUS_CALLEVEL is reported via the ProtectionHook.	
Call context	
> TASK|ISR2|ERRHOOK|STARTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-7 ShutdownOS

6.1.8 ShutdownAllCores

Prototype	
`void` **`ShutdownAllCores`** `(StatusType Error)`	
Parameter	
Error [in]	This is the error code which shall be passed to the ShutdownHook().
Return code	
void	none
Functional Description	
OS service ShutdownAllCores().	
Particularities and Limitations	
Pre-Condition: None Propagates a shutdown request to all started AUTOSAR cores and performs a shutdown itself afterwards. Only allowed in trusted applications.	
Call context	
> TASK|ISR2|ERRHOOK|STARTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-8 ShutdownAllCores

6.1.9 ControlIdle

Prototype	
`StatusType ControlIdle (CoreIdType CoreID, IdleModeType IdleMode)`	
Parameter	
CoreID [in]	Selects the core which idle mode is set
IdleMode [in]	The mode which shall be performed during idle time
Return code	
StatusType	E_OK No error. E_OS_ID (EXTENDED status): Invalid core and/or invalid IdleMode. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service ControlIdle().	
Particularities and Limitations	
Pre-Condition: None This API allows the caller to select the idle mode action which is performed during idle time of the OS (e.g. if no Task/ISR is active). The real idle modes are hardware dependent and not standardized. The default idle mode on each core is IDLE_NO_HALT.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Non-Reentrant	

Table 6-9 ControlIdle

6.1.10 GetSpinlock

Prototype	
`StatusType GetSpinlock (SpinlockIdType SpinlockId)`	
Parameter	
SpinlockId [in]	The spinlock which shall be locked.
Return code	
StatusType	> E_OK No error. E_OS_ID (EXTENDED status:) Invalid SpinlockID. E_OS_INTERFERENCE_DEADLOCK (EXTENDED status:) Spinlock already occupied by a task/ISR of the same core. E_OS_NESTING_DEADLOCK (EXTENDED status:) Invalid Spinlock allocation order. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient.
Functional Description	
OS service GetSpinlock().	
Particularities and Limitations	
Pre-Condition: None Allocates the requested spinlock for the caller. If it is already locked, the function performs active around until the spinlock becomes available again.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-10 GetSpinlock

6.1.11 ReleaseSpinlock

Prototype	
`StatusType ReleaseSpinlock (SpinlockIdType SpinlockId)`	
Parameter	
SpinlockId [in]	The spinlock which shall be released.
Return code	
StatusType	E_OK No error. E_OS_ID (EXTENDED status:) Invalid SpinlockID. E_OS_STATE (EXTENDED status:) The caller is not the owner of the given spinlock. E_OS_NOFUNC (EXTENDED status:) The caller tries to release a spinlock while another spinlock has to be released before. E_OS_RESOURCE (EXTENDED status:) Spinlock and Resource API not used in LIFO order. E_OS_ACCESS (Service Protection:) Caller's access rights are not sufficient. This error may occur in combination with trusted functions.
Functional Description	
OS service ReleaseSpinlock().	
Particularities and Limitations	
Pre-Condition: None ReleaseSpinlock releases a spinlock variable that was occupied before. Before terminating a task/ISR all spinlock variables that have been occupied with GetSpinlock() shall be released. The error E_OS_CALLEVEL is already checked by E_OS_STATE. See Os_SpinlockRelease() for details.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-11 ReleaseSpinlock

6.1.12 TryToGetSpinlock

Prototype	
`StatusType` **`TryToGetSpinlock`** `(SpinlockIdType SpinlockId, TryToGetSpinlockType *Success)`	
Parameter	
SpinlockId [in]	The spinlock which shall be locked.
Success [out]	The result of the allocation attempt.
Return code	
StatusType	> E_OK No error. E_OS_ID (EXTENDED status:) Invalid SpinlockID. E_OS_INTERFERENCE_DEADLOCK (EXTENDED status:) Spinlock already occupied by a task/ISR of the same core. E_OS_NESTING_DEADLOCK (EXTENDED status:) Invalid Spinlock allocation order. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient.
Functional Description	
OS service TryToGetSpinlock().	
Particularities and Limitations	
Pre-Condition: None Allocates the requested spinlock for the caller. If it is already locked, the function returns.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-12 TryToGetSpinlock

6.1.13 DisableAllInterrupts

Prototype	
`void DisableAllInterrupts (void)`	
Parameter	
void	none
Return code	
void	none
Functional Description	
OS service DisableAllInterrupts()..	
Particularities and Limitations	
Pre-Condition: Not already in DisableAllInterrupts() sequence. Disables category 1 and category 2 ISRs. If timing protection is configured, the timing protection interrupt is not affected.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|ALARMHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-13 DisableAllInterrupts

6.1.14 EnableAllInterrupts

Prototype	
`void EnableAllInterrupts (void)`	
Parameter	
void	none
Return code	
void	none
Functional Description	
OS service EnableAllInterrupts().	
Particularities and Limitations	
Pre-Condition: In DisableAllInterrupts() sequence. Restores the state saved by DisableAllInterrupts().	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|ALARMHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-14 EnableAllInterrupts

6.1.15 SuspendAllInterrupts

Prototype	
`void` **`SuspendAllInterrupts`** `(void)`	
Parameter	
void	none
Return code	
void	none
Functional Description	
OS service SuspendAllInterrupts().	
Particularities and Limitations	
Pre-Condition: Not in DisableAllInterrupts() sequence. Saves the recognition status of all interrupts and disables all interrupts for which the hardware supports disabling. This API can be called nested.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|ALARMHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-15 SuspendAllInterrupts

6.1.16 ResumeAllInterrupts

Prototype	
`void` **`ResumeAllInterrupts`** `(void)`	
Parameter	
void	none
Return code	
void	none
Functional Description	
OS service ResumeAllInterrupts().	
Particularities and Limitations	
> Pre-Condition: In SuspendAllInterrupts() sequence.Pre-Condition: Correct nesting sequence of suspend interrupt API. Restores the recognition status of all interrupts saved by the SuspendAllInterrupts() service.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|ALARMHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-16 ResumeAllInterrupts

6.1.17 SuspendOSInterrupts

Prototype	
`void` **`SuspendOSInterrupts`** `(void)`	
Parameter	
void	none
Return code	
void	none
Functional Description	
OS service SuspendOSInterrupts().	
Particularities and Limitations	
Pre-Condition: Not in DisableAllInterrupts() sequence. Saves the recognition status of interrupts of category 2 and disables the recognition of these interrupts. This API can be called nested.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|ALARMHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-17 SuspendOSInterrupts

6.1.18 ResumeOSInterrupts

Prototype	
`void` **`ResumeOSInterrupts`** `(void)`	
Parameter	
void	none
Return code	
void	none
Functional Description	
OS service ResumeOSInterrupts().	
Particularities and Limitations	
> Pre-Condition: In SuspendOSInterrupts() sequence.Pre-Condition: Correct nesting sequence of suspend interrupt API. Restores the recognition status of interrupts saved by the SuspendOSInterrupts() service.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|ALARMHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-18 ResumeOSInterrupts

6.1.19 ActivateTask

Prototype	
`StatusType` **`ActivateTask`** `(TaskType TaskID)`	
Parameter	
TaskID [in]	The task which shall be activated.
Return code	
StatusType	> E_OK No error. E_OS_LIMIT Too many task activations. E_OS_ID (EXTENDED status:) Invalid TaskID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given task's owner application is not accessible.
Functional Description	
OS service ActivateTask().	
Particularities and Limitations	
Pre-Condition: None The task TaskID is transferred from the SUSPENDED state into the READY state. The operating system ensures that the task code is being executed from the first statement.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-19 ActivateTask

6.1.20 TerminateTask

Prototype	
`StatusType` **`TerminateTask`** `(void)`	
Parameter	
void	none
Return code	
StatusType	E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_RESOURCE (EXTENDED status:) Task still occupies resources. E_OS_SPINLOCK (EXTENDED status:) Task still holds spinlocks. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service TerminateTask().	
Particularities and Limitations	
Pre-Condition: None This service causes the termination of the calling task. The calling task is transferred from the RUNNING state into the SUSPENDED state. This service only returns in case it detects an error.	
Call context	
> TASK > This function is Synchronous > This function is Reentrant	

Table 6-20 TerminateTask

6.1.21 ChainTask

Prototype	
`StatusType` **`ChainTask`** `(TaskType TaskID)`	
Parameter	
TaskID [in]	The task which shall be activated.
Return code	
StatusType	> E_OS_LIMIT Too many task activations. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_RESOURCE (EXTENDED status:) Task still occupies resources. E_OS_SPINLOCK (EXTENDED status:) Task still holds spinlocks. E_OS_ID (EXTENDED status:) Invalid TaskID. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given task's owner application is not accessible.
Functional Description	
OS service ChainTask().	
Particularities and Limitations	
Pre-Condition: None After termination of the calling task the given task is activated. This service only returns in case it detects an error.	
Call context	
> TASK > This function is Synchronous > This function is Reentrant	

Table 6-21 ChainTask

6.1.22 Schedule

Prototype	
`StatusType` **`Schedule`** `(void)`	
Parameter	
void	none
Return code	
StatusType	E_OK No Error. E_OS_CALLEVEL (EXTENDED status:) The service was called from any context which is not allowed. E_OS_RESOURCE (EXTENDED status:) The service was called from a task which holds an OS resource. E_OS_SPINLOCK (EXTENDED status:) The service was called from a task which holds a spinlock. E_OS_DISABLEDINT (EXTENDED status:) The service was called with disabled interrupts.
Functional Description	
OS service Schedule().	
Particularities and Limitations	
Pre-Condition: Interrupts are enabled.	
Call context	
> TASK > This function is Synchronous > This function is Reentrant	

Table 6-22 Schedule

6.1.23 GetTaskID

Prototype	
`StatusType GetTaskID (TaskRefType TaskID)`	
Parameter	
TaskID [out]	The current task ID.
Return code	
StatusType	E_OK No error. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service GetTaskID().	
Particularities and Limitations	
Pre-Condition: None Returns the ID of the task which is currently RUNNING on the local core.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-23 GetTaskID

6.1.24 GetTaskState

Prototype	
`FUNC(StatusType, OS_CODE) GetTaskState (TaskType TaskID, TaskStateRefType State)`	
Parameter	
TaskID [in]	The task to be queried.
State [out]	The task's state.
Return code	
StatusType	> E_OK No error. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_ID (EXTENDED status:) Invalid TaskID. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given task's owner application is not accessible.
Functional Description	
OS service GetTaskState().	
Particularities and Limitations	
Pre-Condition: The given task has to be assigned to the current core. Returns the current scheduling state of a task (RUNNING, READY, ...).	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-24 GetTaskState

6.1.25 GetISRID

Prototype	
`ISRType` **`GetISRID`** `(void)`	
Parameter	
void	none
Return code	
ISRType	> Identifier of running ISR INVALID_ISR If called from > - invalid call-context, > - from a task or > - a hook which was called inside a task context.
Functional Description	
OS service GetISRID().	
Particularities and Limitations	
Pre-Condition: None Return the identifier of the currently executing ISR.	
Call context	
> TASK|ISR2|ERRHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-25 GetISRID

6.1.26 SetEvent

Prototype	
`StatusType SetEvent (TaskType TaskID, EventMaskType Mask)`	
Parameter	
TaskID [in]	The task which shall be modified.
Mask [in]	The events which shall be set.
Return code	
StatusType	E_OK No error. E_OS_ID (EXTENDED status) Invalid TaskID. E_OS_ACCESS (EXTENDED status). Task is no extended task (Service Protection). Task's owner application is not accessible. Caller's access rights are not sufficient. E_OS_STATE (EXTENDED status:) Events cannot be set as the referenced task is in the SUSPENDED state. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_SYS_DISABLED (EXTENDED status:) Events are not enabled in the configuration.
Functional Description	
OS service SetEvent().	
Particularities and Limitations	
Pre-Condition: None The events of the given task are set according to the given event mask.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-26 SetEvent

6.1.27 ClearEvent

Prototype	
`StatusType` **`ClearEvent`** `(EventMaskType Mask)`	
Parameter	
Mask [in]	The events which shall be set.
Return code	
StatusType	E_OK No error. E_OS_ACCESS (EXTENDED status:) Task is no extended task. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_SYS_DISABLED (EXTENDED status:) Events are not enabled in the configuration.
Functional Description	
OS service ClearEvent().	
Particularities and Limitations	
Pre-Condition: None The events of the calling task are cleared according to the given event mask.	
Call context	
> TASK > This function is Synchronous > This function is Reentrant	

Table 6-27 ClearEvent

6.1.28 GetEvent

Prototype	
`StatusType` **`GetEvent`** `(TaskType TaskID, EventMaskRefType Mask)`	
Parameter	
TaskID [in]	The task which shall be queried.
Mask [out]	Events which are set.
Return code	
StatusType	E_OK No error. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_ID (EXTENDED status:) Invalid TaskID. E_OS_ACCESS (EXTENDED status:) Task is no extended task. (Service Protection:). Task's owner application is not accessible. Caller's access rights are not sufficient. E_OS_STATE (EXTENDED status:) Referenced task is in SUSPENDED state. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_SYS_DISABLED (EXTENDED status:) Events are not enabled in the configuration.
Functional Description	
OS service GetEvent().	
Particularities and Limitations	
Pre-Condition: Task is assigned to the current core. This service returns the state of all event bits of the given task, not the events that the task is waiting for.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-28 GetEvent

6.1.29 WaitEvent

Prototype	
`StatusType` **`WaitEvent`** `(EventMaskType Mask)`	
Parameter	
Mask [in]	Mask of the events waited for.
Return code	
StatusType	E_OK No error. E_OS_ACCESS (EXTENDED status:) Task is no extended task. E_OS_RESOURCE (EXTENDED status:) Task still occupies resources. E_OS_SPINLOCK (EXTENDED status:) Task still holds spinlocks. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_SYS_DISABLED (EXTENDED status:) Events are not enabled in the configuration.
Functional Description	
OS service WaitEvent().	
Particularities and Limitations	
Pre-Condition: None The state of the current task is set to WAITING, unless at least one of the given events is set.	
Call context	
> TASK > This function is Synchronous > This function is Reentrant	

Table 6-29 WaitEvent

6.1.30 IncrementCounter

Prototype	
`StatusType IncrementCounter (CounterType CounterID)`	
Parameter	
CounterID [in]	The counter to be incremented.
Return code	
StatusType	> E_OK No Error. E_OS_ID (EXTENDED status:) CounterID is not a valid software counter ID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_CORE (EXTENDED status:) The given object belongs to a foreign core. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given counter's owner application is not accessible. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service IncrementCounter().	
Particularities and Limitations	
Pre-Condition: None	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-30 IncrementCounter

6.1.31 GetCounterValue

Prototype	
`StatusType` **`GetCounterValue`** `(CounterType CounterID, TickRefType Value)`	
Parameter	
CounterID [in]	The counter to be read.
Value [out]	Contains the current tick value of the counter.
Return code	
StatusType	> E_OK No Error. E_OS_ID (EXTENDED status:) Invalid CounterID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_ACCESS (Service Protection:) > - Counter's owner application is not accessible. > - Caller's access rights are not sufficient. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service GetCounterValue().	
Particularities and Limitations	
Pre-Condition: None	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-31 GetCounterValue

6.1.32 GetElapsedValue

Prototype	
`FUNC(StatusType, OS_CODE) GetElapsedValue (CounterType CounterID, TickRefType Value, TickRefType ElapsedValue)`	
Parameter	
CounterID [in]	The counter to be read.
Value [in,out]	**in:** The previously read tick value of the counter. **out:** The current tick value of the counter.
ElapsedValue [out]	The difference to the previous read value.
Return code	
StatusType	> E_OK No Error. E_OS_ID (EXTENDED status:) Invalid CounterID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_VALUE (EXTENDED status:) The given Value was not valid. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_ACCESS (Service Protection:) > - Counter's owner application is not accessible. > - Caller's access rights are not sufficient. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service GetElapsedValue().	
Particularities and Limitations	
Pre-Condition: None	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-32 GetElapsedValue

6.1.33 GetAlarmBase

Prototype	
`FUNC(StatusType, OS_CODE) GetAlarmBase (AlarmType AlarmID, AlarmBaseRefType Info)`	
Parameter	
AlarmID [in]	Reference to the alarm element.
Info [out]	Contains information about the counter on successful return.
Return code	
StatusType	> E_OK No error. E_OS_ID (EXTENDED status:) Invalid AlarmID. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given task's owner application is not accessible.
Functional Description	
OS service GetAlarmBase().	
Particularities and Limitations	
Pre-Condition: Given object pointer(s) are valid. The system service GetAlarmBase reads the alarm base characteristics. The return value Info is a structure in which the information of data type AlarmBaseType is stored.	
Call context	
> TASK|ISR2|PRETHOOK|POSTTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-33 GetAlarmBase

6.1.34 GetAlarm

Prototype	
`FUNC(StatusType, OS_CODE) GetAlarm (AlarmType AlarmID, TickRefType Tick)`	
Parameter	
AlarmID [in]	Reference to the alarm element.
Tick [out]	Relative value in ticks before the alarm expires.
Return code	
StatusType	> E_OK No error. E_OS_NOFUNC Alarm is not in use. E_OS_ID (EXTENDED status:) Invalid AlarmID. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given task's owner application is not accessible.
Functional Description	
OS service GetAlarm().	
Particularities and Limitations	
The given alarm is assigned to the local core. It is up to the application to decide whether for example a CancelAlarm may still be useful. If AlarmID is not in use, Tick is not defined. Allowed on task level, ISR, and in several hook routines.	
Call context	
> TASK|ISR2|PRETHOOK|POSTTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-34 GetAlarm

6.1.35 SetRelAlarm

Prototype	
`StatusType SetRelAlarm (AlarmType AlarmID, TickType Increment, TickType Cycle)`	
Parameter	
AlarmID [in]	Reference to the alarm element.
Increment [in]	Relative value in ticks.
Cycle [in]	Cycle value in case of cyclic alarm. In case of single alarms, cycle shall be zero.
Return code	
StatusType	> E_OK No error. E_OS_STATE Alarm is already in use. E_OS_ID (EXTENDED status:) Invalid AlarmID. E_OS_VALUE Returned if: > - Value of increment is zero > - (EXTENDED status:) Value of Increment outside of the admissible limits (lower than zero or greater than maxallowedvalue). > - (EXTENDED status:) Value of Cycle unequal to 0 and outside of the admissible counter limits (less than mincycle or greater than maxallowedvalue). E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given alarm's owner application is not accessible. other See Os_XSigSend_SetRelAlarm() and Os_XSigRecv_SetRelAlarm().
Functional Description	
OS service SetRelAlarm().	
Particularities and Limitations	
Pre-Condition: None The system service occupies the alarm AlarmID element. After increment ticks have elapsed, the task assigned to the alarm AlarmID is activated or the assigned event (only for extended tasks) is set or the alarm-callback routine is called.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-35 SetRelAlarm

6.1.36 SetAbsAlarm

Prototype	
`StatusType SetAbsAlarm (AlarmType AlarmID, TickType Start, TickType Cycle)`	
Parameter	
AlarmID [in]	Reference to the alarm element.
Start [in]	Absolute value in ticks.
Cycle [in]	Cycle value in case of cyclic alarm. In case of single alarms, cycle shall be zero.
Return code	
StatusType	> E_OK No error. E_OS_STATE Alarm is already in use. E_OS_ID (EXTENDED status:) Invalid AlarmID. E_OS_VALUE (EXTENDED status:) Returned if: > - Value of Start outside of the admissible counter limit (less than zero or greater than maxallowedvalue). > - Value of Cycle unequal to 0 and outside of the admissible counter limits (less than mincycle or greater than maxallowedvalue). E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given alarm's owner application is not accessible. other See Os_XSigSend_SetAbsAlarm() and Os_XSigRecv_SetAbsAlarm().
Functional Description	
OS service SetAbsAlarm().	
Particularities and Limitations	
Pre-Condition: None The system service occupies the alarm AlarmID element. When start ticks are reached, the task assigned to the alarm AlarmID is activated or the assigned event (only for extended tasks) is set or the alarm-callback routine is called.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-36 SetAbsAlarm

6.1.37 CancelAlarm

Prototype	
`StatusType CancelAlarm (AlarmType AlarmID)`	
Parameter	
AlarmID [in]	Reference to the alarm element.
Return code	
StatusType	> E_OK No error. E_OS_NOFUNC Alarm is not in use. E_OS_ID (EXTENDED status:) Invalid AlarmID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given alarm's owner application is not accessible.
Functional Description	
OS service CancelAlarm().	
Particularities and Limitations	
Pre-Condition: None The system service cancels the alarm AlarmID.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-37 CancelAlarm

6.1.38 GetResource

Prototype	
`StatusType GetResource (ResourceType ResID)`	
Parameter	
ResID [in]	The resource which shall be occupied.
Return code	
StatusType	> E_OK No error. E_OS_ID (EXTENDED status:) Invalid ResID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_CORE (EXTENDED status:) The given object belongs to a foreign core. E_OS_ACCESS (EXTENDED status:) > - Statically assigned priority of the caller is higher than the calculated ceiling priority. > - Attempt to get a resource which is already occupied. (Service Protection:) > - Caller's access rights are not sufficient. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service GetResource().	
Particularities and Limitations	
Pre-Condition: None This API serves to enter critical sections in the code. A critical section shall always be left using ReleaseResource().	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-38 GetResource

6.1.39 ReleaseResource

Prototype	
`StatusType` **`ReleaseResource`** `(ResourceType ResID)`	
Parameter	
ResID [in]	The resource which shall be released.
Return code	
StatusType	> E_OK No error. E_OS_ID (EXTENDED status:) Invalid ResID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_CORE (EXTENDED status:) The given object belongs to a foreign core. > E_OS_NOFUNC (EXTENDED status:) - Attempt to release a resource which has not been occupied by the caller before. - Attempt to release a nested resource in wrong order. - Spinlock and Resource API not used in LIFO order. > E_OS_ACCESS (Service Protection:) Caller's access rights are not sufficient. > E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service ReleaseResource().	
Particularities and Limitations	
This API is the counterpart of GetResource() and serves to leave critical sections in the code.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-39 ReleaseResource

6.1.40 StartScheduleTableRel

Prototype	
`StatusType **StartScheduleTableRel** (ScheduleTableType ScheduleTableID, TickType Offset)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table to be started.
Offset [in]	The relative offset when the schedule table shall be started.
Return code	
StatusType	> E_OK No error. E_OS_STATE Schedule table has already been started. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_VALUE (EXTENDED status:) Offset is bigger than (OsCounterMaxAllowedValue - InitialOffset) or is equal to zero E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service StartScheduleTableRel().	
Particularities and Limitations	
Pre-Condition: None The schedule table is started at a relative offset to the current time.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-40 StartScheduleTableRel

6.1.41 StartScheduleTableAbs

Prototype	
`StatusType StartScheduleTableAbs (ScheduleTableType ScheduleTableID, TickType Start)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table to be started
Start [in]	The absolute time when the schedule table shall be started
Return code	
StatusType	> E_OK No error. E_OS_STATE Schedule table has already been started. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_VALUE (EXTENDED status:) Offset is bigger than OsCounterMaxAllowedValue E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service StartScheduleTableAbs().	
Particularities and Limitations	
Pre-Condition: None The schedule table is started at an absolute time.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-41 StartScheduleTableAbs

6.1.42 StopScheduleTable

Prototype	
`StatusType` **`StopScheduleTable`** `(ScheduleTableType ScheduleTableID)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table to be stopped.
Return code	
StatusType	> E_OK No error. E_OS_NOFUNC Schedule table has already been stopped. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service StopScheduleTable().	
Particularities and Limitations	
Pre-Condition: None The schedule table is stopped immediately.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-42 StopScheduleTable

6.1.43 NextScheduleTable

Prototype	
`StatusType NextScheduleTable (ScheduleTableType ScheduleTableID_From, ScheduleTableType ScheduleTableID_To)`	
Parameter	
ScheduleTableID_From [in]	The ID of the schedule table which is requested to stop at its end
ScheduleTableID_To [in]	The ID of the schedule table which starts after the other one has stopped
Return code	
StatusType	> E_OK No error. E_OS_NOFUNC Schedule table ScheduleTableID_From has not been started. E_OS_STATE Schedule table ScheduleTableID_To has already been requested to start at the end of another schedule table. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID_From/To. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service NextScheduleTable().	
Particularities and Limitations	
Pre-Condition: None Requests the switch of schedule table processing from one schedule table to another after the first one has reached its end.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-43 NextScheduleTable

6.1.44 GetScheduleTableStatus

Prototype	
`FUNC(StatusType, OS_CODE) GetScheduleTableStatus ( ScheduleTableType ScheduleTableID, ScheduleTableStatusRefType ScheduleStatus)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table for which the status shall be requested.
ScheduleStatus [out]	Reference to ScheduleTableStatusType.
Return code	
StatusType	> E_OK No error. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_PARAM_POINTER (EXTENDED status:) ScheduleStatus is a pointer to null. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service GetScheduleTableStatus().	
Particularities and Limitations	
Pre-Condition: None This service queries the state of a schedule table (also with respect to synchronization).	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-44 GetScheduleTableStatus

6.1.45 StartScheduleTableSynchron

Prototype	
`StatusType` **`StartScheduleTableSynchron`** `(ScheduleTableType ScheduleTableID)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table which shall start synchronously
Return code	
StatusType	> E_OK No error. E_OS_STATE Schedule table ScheduleTableID has already been started. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID. E_OS_CORE (EXTENDED status:) The given object belongs to a foreign core. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service StartScheduleTableSynchron().	
Particularities and Limitations	
Pre-Condition: None This service starts an explicitly synchronized schedule table synchronously. As a result the schedule table enters the state SCHEDULETABLE_WAITING and waits for a synchronization count to be provided.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-45 StartScheduleTableSynchron

6.1.46 SyncScheduleTable

Prototype	
`StatusType SyncScheduleTable (ScheduleTableType ScheduleTableID, TickType Value)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table to the synchronized
Value [in]	The current value of the synchronization counter
Return code	
StatusType	> E_OK No error. E_OS_STATE The state of the schedule table ScheduleTableId is equal to SCHEDULETABLE_STOPPED or SCHEDULETABLE_NEXT. E_OS_ID (EXTENDED status:) Invalid ScheduleTableID. E_OS_CORE (EXTENDED status:) The given object belongs to a foreign core. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_VALUE (EXTENDED status:) The Value is out of range E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service SyncScheduleTable().	
Particularities and Limitations	
Pre-Condition: None This service provides the schedule table with a synchronization count and starts the synchronization.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-46 SyncScheduleTable

6.1.47 SetScheduleTableAsync

Prototype	
`StatusType` **`SetScheduleTableAsync`** `(ScheduleTableType ScheduleTableID)`	
Parameter	
ScheduleTableID [in]	The ID of the schedule table which shall no longer be synchronized.
Return code	
StatusType	> E_OK No error. E_OS_STATE Current state of ScheduleTableID is SCHEDULETABLE_STOPPED, SCHEDULETABLE_NEXT or SCHEDULETABLE_WAITING. E_OS_ID (EXTENDED status:) > - Invalid ScheduleTableID. > - OsScheduleTblSyncStrategy of ScheduleTableID is not equal to EXPLICIT E_OS_CORE (EXTENDED status:) The given object belongs to a foreign core. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence. E_OS_ACCESS (Service Protection:) > - Caller's access rights are not sufficient. > - Given schedule table's owner application is not accessible.
Functional Description	
OS service SetScheduleTableAsync().	
Particularities and Limitations	
Pre-Condition: None This service stops the synchronization of a schedule table.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-47 SetScheduleTableAsync

6.1.48 GetApplicationID

Prototype	
`ApplicationType` **`GetApplicationID`** `(void)`	
Parameter	
void	none
Return code	
ApplicationType	Identifier of the OS-Application.
Functional Description	
OS service GetApplicationID().	
Particularities and Limitations	
Pre-Condition: None This service determines the OS-Application where the caller (Task/ISR/Hook) originally belongs to (was configured to). All system objects (e.g. system hooks, idle task, ...) belong to kernel applications. Kernel applications are regular applications and have valid identifiers. Therefore INVALID_OSAPPLICATION is never returned because there is always a valid application active.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-48 GetApplicationID

6.1.49 GetCurrentApplicationID

Prototype	
`ApplicationType` **`GetCurrentApplicationID`** `(void)`	
Parameter	
void	none
Return code	
ApplicationType	Identifier of the OS-Application.
Functional Description	
OS service GetCurrentApplicationID().	
Particularities and Limitations	
Pre-Condition: None This service determines the OS-Application where the caller (Task/ISR/Hook) of the service is currently executing. Note that, if the caller is not within a CallTrustedFunction() call, the value is equal to the result of GetApplicationID().	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-49 GetCurrentApplicationID

6.1.50 GetApplicationState

Prototype	
`StatusType GetApplicationState (ApplicationType Application, ApplicationStateRefType Value)`	
Parameter	
Application [in]	The OS-Application from which the state is requested.
Value [out]	The current state of the application.
Return code	
StatusType	E_OK No error. E_OS_ID (EXTENDED status:) Invalid Application. E_OS_PARAM_POINTER (EXTENDED status:) Given pointer is NULL. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service GetApplicationState().	
Particularities and Limitations	
Pre-Condition: None This service returns the current state of an OS-Application.	
Call context	
> TASK|ISR2|ERRHOOK|PRETHOOK|POSTTHOOK|STARTHOOK|SHUTHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-50 GetApplicationState

6.1.51 CheckObjectAccess

Prototype	
`ObjectAccessType CheckObjectAccess (ApplicationType ApplID, ObjectTypeType ObjectType, Os_ObjectIdType ObjectID)`	
Parameter	
ApplID [in]	OS-Application identifier.
ObjectType [in]	Type of the following parameter.
ObjectID [in]	The object to be examined.
Return code	
ObjectAccessType	> ACCESS if the ApplID has access to the object. NO_ACCESS If: > - ApplID doesn't have access to the object. > - ApplID is invalid. > - ObjectID is invalid.
Functional Description	
OS service CheckObjectAccess().	
Particularities and Limitations	
Pre-Condition: None This service determines if the OS-Application, given by ApplID, is allowed to use the IDs of a Task, Resource, Counter, Alarm or Schedule Table in API calls.	
Call context	
> TASK|ISR2|ERRHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-51 CheckObjectAccess

6.1.52 CheckObjectOwnership

Prototype	
`ApplicationType` **`CheckObjectOwnership`** `(ObjectTypeType ObjectType, Os_ObjectIdType ObjectID)`	
Parameter	
ObjectType [in]	Type of the following parameter.
ObjectID [in]	The object to be examined.
Return code	
ApplicationType	Identifier of the owner OS-Application. INVALID_OSAPPLICATION if the object does not exist.
Functional Description	
OS service CheckObjectOwnership().	
Particularities and Limitations	
Pre-Condition: None This service determines to which OS-Application a given Task, ISR, Counter, Alarm or Schedule Table belongs.	
Call context	
> TASK|ISR2|ERRHOOK|PROTHOOK > This function is Synchronous > This function is Reentrant	

Table 6-52 CheckObjectOwnership

6.1.53 AllowAccess

Prototype	
`StatusType` **`AllowAccess`** `(void)`	
Parameter	
void	none
Return code	
StatusType	E_OK No error. E_OS_STATE The application is not in the restarting state. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service AllowAccess().	
Particularities and Limitations	
Pre-Condition: None This service sets the state of the current OS-Application from APPLICATION_RESTARTING to APPLICATION_ACCESSIBLE.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-53 AllowAccess

6.1.54 TerminateApplication

Prototype	
`StatusType` **`TerminateApplication`** `(ApplicationType Application, RestartType RestartOption)`	
Parameter	
Application [in]	The identifier of the OS-Application to be terminated. If the caller belongs to Application the call results in a self-termination.
RestartOption [in]	Either RESTART for doing a restart of the OS-Application or NO_RESTART if OS-Application shall not be restarted.
Return code	
StatusType	> E_OK No errors E_OS_STATE The state of Application does not allow terminating it: > - The application is already terminated. > - The application is restarting AND the caller does not belong to the application. > - The application is restarting AND the caller does belong to the application AND the RestartOption is RESTART. E_OS_ID (EXTENDED status:) Application was not valid. E_OS_VALUE (EXTENDED status:) RestartOption was neither RESTART nor NO_RESTART. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_ACCESS (EXTENDED status:) The caller belongs to a non-trusted OS-Application AND the caller does not belong to given Application TerminateApplication() shall return E_OS_ACCESS. E_OS_DISABLEDINT (EXTENDED status:) Caller is in interrupt API sequence.
Functional Description	
OS service TerminateApplication().	
Particularities and Limitations	
Pre-Condition: None This service terminates the OS-Application to which the calling Task/ISR/application specific error hook belongs.	
Call context	
> TASK|ISR2|ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-54 TerminateApplication

6.1.55 CallTrustedFunction

Prototype	
`StatusType CallTrustedFunction (TrustedFunctionIndexType FunctionIndex, TrustedFunctionParameterRefType FunctionParams)`	
Parameter	
FunctionIndex [in]	Index of the function to be called.
FunctionParams [in]	Pointer to the parameters for the function. If no parameters are provided, a NULL pointer has to be passed.
Return code	
StatusType	> E_OK No error. E_OS_SERVICEID No function defined for this index. E_OS_CALLEVEL (EXTENDED status:) Called from invalid context. E_OS_ACCESS (EXTENDED status:) The given object belongs to a foreign core. E_OS_ACCESS (Service Protection:) > - Owner application is not accessible.
Functional Description	
OS service CallTrustedFunction().	
Particularities and Limitations	
Pre-Condition: None Each trusted OS-Application may export services which are callable from other OS-Applications.	
Call context	
> TASK|ISR2 > This function is Synchronous > This function is Reentrant	

Table 6-55 CallTrustedFunction

6.1.56 Check Task Memory Access

Prototype	
`FUNC(AccessType, OS_CODE) CheckTaskMemoryAccess( TaskType TaskID, MemoryStartAddressType Address, MemorySizeType Size )`	
Parameter	
`TaskID`	ID of task
`Address`	Start address of checked address range
`Size`	Size of checked address range
Return code	
`AccessType`	Returns the access rights of the Task to the given address range OS_MEM_ACCESS_TYPE_NON No access, invalid TaskID or address range overflow.
Functional Description	
The service distinguishes the memory access rights of a given Task.	
Particularities and Limitations	
> The access checks are based upon the “OsAccessCheckRegion” configuration objects. > The return value of this functions is typically used with the AUTOSAR OS specified macros > OSMEMORY_IS_READABLE > OSMEMORY_IS_WRITEABLE > OSMEMORY_IS_EXECUTABLE > OSMEMORY_IS_STACKSPACE	

Table 6-56 API Service CheckTaskMemoryAccess

6.1.57 Check ISR Memory Access

Prototype	

`FUNC(AccessType, OS_CODE) CheckISRMemoryAccess(`
`  ISRType ISRID,`
`  MemoryStartAddressType Address,`
`  MemorySizeType Size`
`)`	

Parameter	
`ISRID`	ID of category 2 ISR
`Address`	Start address of checked address range
`Size`	Size of checked address range
Return code	
`AccessType`	Returns the access rights of the ISR to the given address range OS_MEM_ACCESS_TYPE_NON No access, invalid TaskID or address range overflow.
Functional Description	
The service distinguishes the memory access rights of a given category 2 ISR	
Particularities and Limitations	
> The access checks are based upon the “OsAccessCheckRegion” configuration objects. > The return value of this functions is typically used with the AUTOSAR OS specified macros > OSMEMORY_IS_READABLE > OSMEMORY_IS_WRITEABLE > OSMEMORY_IS_EXECUTABLE > OSMEMORY_IS_STACKSPACE	

Table 6-57 API Service CheckISRMemoryAccess

6.1.58 OSErrorGetServiceId

Prototype	
`OSServiceIdType` **`OSErrorGetServiceId`** `(void)`	
Parameter	
void	none
Return code	
OSServiceIdType	none
Functional Description	
OS service OSErrorGetServiceId().	
Particularities and Limitations	
Pre-Condition: None Provides the service identifier where the error has been risen.	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-58 OSErrorGetServiceId

6.1.59 OSError_Os_DisableInterruptSource_ISRID

Prototype	
`ISRType` **`OSError_Os_DisableInterruptSource_ISRID`** `(void)`	
Parameter	
void	none
Return code	
ISRType	Requested parameter value.
Functional Description	
Returns parameter ISRID of a faulty Os_DisableInterruptSource call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-59 OSError_Os_DisableInterruptSource_ISRID

6.1.60 OSError_Os_EnableInterruptSource_ISRID

Prototype	
`ISRType` **`OSError_Os_EnableInterruptSource_ISRID`** `(void)`	
Parameter	
void	none
Return code	
ISRType	Requested parameter value.
Functional Description	
Returns parameter ISRID of a faulty Os_EnableInterruptSource call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-60 OSError_Os_EnableInterruptSource_ISRID

6.1.61 OSError_Os_EnableInterruptSource_ClearPending

Prototype	
`boolean` **`OSError_Os_EnableInterruptSource_ClearPending`** `(void)`	
Parameter	
void	none
Return code	
boolean	Requested parameter value.
Functional Description	
Returns parameter ClearPending of a faulty Os_EnableInterruptSource call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-61 OSError_Os_EnableInterruptSource_ClearPending

6.1.62 OSError_Os_ClearPendingInterrupt_ISRID

Prototype	
`ISRType` **`OSError_Os_ClearPendingInterrupt_ISRID`** `(void)`	
Parameter	
void	none
Return code	
ISRType	Requested parameter value.
Functional Description	
Returns parameter ISRID of a faulty Os_ClearPendingInterrupt call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-62 OSError_Os_ClearPendingInterrupt_ISRID

6.1.63 OSError_Os_IsInterruptSourceEnabled_ISRID

Prototype	
`ISRType` **`OSError_Os_IsInterruptSourceEnabled_ISRID`** `(void)`	
Parameter	
void	none
Return code	
ISRType	Requested parameter value.
Functional Description	
Returns parameter ISRID of a faulty Os_IsInterruptSourceEnabled call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-63 OSError_Os_IsInterruptSourceEnabled_ISRID

6.1.64 OSError_Os_IsInterruptSourceEnabled_IsEnabled

Prototype	
`boolean *` **`OSError_Os_IsInterruptSourceEnabled_IsEnabled`** `(void)`	
Parameter	
void	none
Return code	
boolean *	Requested parameter value.
Functional Description	
Returns parameter IsEnabled of a faulty Os_IsInterruptSourceEnabled call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-64 OSError_Os_IsInterruptSourceEnabled_IsEnabled

6.1.65 OSError_Os_IsInterruptPending_ISRID

Prototype	
`ISRType` **`OSError_Os_IsInterruptPending_ISRID`** `(void)`	
Parameter	
void	none
Return code	
ISRType	Requested parameter value.
Functional Description	
Returns parameter ISRID of a faulty Os_IsInterruptPending call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-65 OSError_Os_IsInterruptPending_ISRID

6.1.66 OSError_Os_IsInterruptPending_IsPending

Prototype	
`boolean *` **`OSError_Os_IsInterruptPending_IsPending`** `(void)`	
Parameter	
void	none
Return code	
boolean *	Requested parameter value.
Functional Description	
Returns parameter IsPending of a faulty Os_IsInterruptPending_IsPending call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-66 OSError_Os_IsInterruptPending_IsPending

6.1.67 OSError_CallTrustedFunction_FunctionIndex

Prototype	
`TrustedFunctionIndexType` **`OSError_CallTrustedFunction_FunctionIndex`** `(void)`	
Parameter	
void	none
Return code	
TrustedFunctionIndexType	Requested parameter value.
Functional Description	
Returns parameter FunctionIndex of a faulty CallTrustedFunction call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-67 OSError_CallTrustedFunction_FunctionIndex

6.1.68 OSError_CallTrustedFunction_FunctionParams

Prototype	
`TrustedFunctionParameterRefType` **`OSError_CallTrustedFunction_FunctionParams`** `(void)`	
Parameter	
void	none
Return code	
TrustedFunctionParameterRefType	Requested parameter value.
Functional Description	
Returns parameter FunctionParams of a faulty CallTrustedFunction call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-68 OSError_CallTrustedFunction_FunctionParams

6.1.69 OSError_CallNonTrustedFunction_FunctionIndex

Prototype	
`Os_NonTrustedFunctionIndexType` **`OSError_CallNonTrustedFunction_FunctionIndex`** `(void)`	
Parameter	
void	none
Return code	
Os_NonTrustedFunctionIndexType	Requested parameter value.
Functional Description	
Returns parameter FunctionIndex of a faulty CallTrustedFunction call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-69 OSError_CallNonTrustedFunction_FunctionIndex

6.1.70 OSError_CallNonTrustedFunction_FunctionParams

Prototype	
`Os_NonTrustedFunctionParameterRefType` **`OSError_CallNonTrustedFunction_FunctionParams`** `(void)`	
Parameter	
void	none
Return code	
Os_NonTrustedFunctionParameterRefType	Requested parameter value.
Functional Description	
Returns parameter FunctionParams of a faulty CallNonTrustedFunction call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-70 OSError_CallNonTrustedFunction_FunctionParams

6.1.71 OSError_StartScheduleTableRel_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_StartScheduleTableRel_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty StartScheduleTableRel call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-71 OSError_StartScheduleTableRel_ScheduleTableID

6.1.72 OSError_StartScheduleTableRel_Offset

Prototype	
`TickType` **`OSError_StartScheduleTableRel_Offset`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter Offset of a faulty StartScheduleTableRel call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-72 OSError_StartScheduleTableRel_Offset

6.1.73 OSError_StartScheduleTableAbs_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_StartScheduleTableAbs_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty StartScheduleTableAbs call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-73 OSError_StartScheduleTableAbs_ScheduleTableID

6.1.74 OSError_StartScheduleTableAbs_Start

Prototype	
`TickType` **`OSError_StartScheduleTableAbs_Start`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter Start of a faulty StartScheduleTableAbs call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-74 OSError_StartScheduleTableAbs_Start

6.1.75 OSError_StopScheduleTable_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_StopScheduleTable_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty StopScheduleTable call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-75 OSError_StopScheduleTable_ScheduleTableID

6.1.76 OSError_NextScheduleTable_ScheduleTableID_From

Prototype	
`ScheduleTableType` **`OSError_NextScheduleTable_ScheduleTableID_From`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID_From of a faulty NextScheduleTable call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-76 OSError_NextScheduleTable_ScheduleTableID_From

6.1.77 OSError_NextScheduleTable_ScheduleTableID_To

Prototype	
`ScheduleTableType` **`OSError_NextScheduleTable_ScheduleTableID_To`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID_To of a faulty NextScheduleTable call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-77 OSError_NextScheduleTable_ScheduleTableID_To

6.1.78 OSError_StartScheduleTableSynchron_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_StartScheduleTableSynchron_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty StartScheduleTableSynchron call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-78 OSError_StartScheduleTableSynchron_ScheduleTableID

6.1.79 OSError_SyncScheduleTable_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_SyncScheduleTable_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty SyncScheduleTable call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-79 OSError_SyncScheduleTable_ScheduleTableID

6.1.80 OSError_SyncScheduleTable_Value

Prototype	
`TickType` **`OSError_SyncScheduleTable_Value`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter Value of a faulty SyncScheduleTable call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-80 OSError_SyncScheduleTable_Value

6.1.81 OSError_SetScheduleTableAsync_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_SetScheduleTableAsync_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty SetScheduleTableAsync call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-81 OSError_SetScheduleTableAsync_ScheduleTableID

6.1.82 OSError_GetScheduleTableStatus_ScheduleTableID

Prototype	
`ScheduleTableType` **`OSError_GetScheduleTableStatus_ScheduleTableID`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleTableID of a faulty GetScheduleTableStatus call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-82 OSError_GetScheduleTableStatus_ScheduleTableID

6.1.83 OSError_GetScheduleTableStatus_ScheduleStatus

Prototype	
`ScheduleTableStatusRefType` **`OSError_GetScheduleTableStatus_ScheduleStatus`** `(void)`	
Parameter	
void	none
Return code	
ScheduleTableType	Requested parameter value.
Functional Description	
Returns parameter ScheduleStatus of a faulty GetScheduleTableStatus call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-83 OSError_GetScheduleTableStatus_ScheduleStatus

6.1.84 OSError_IncrementCounter_CounterID

Prototype	
`CounterType` **`OSError_IncrementCounter_CounterID`** `(void)`	
Parameter	
void	none
Return code	
CounterType	Requested parameter value.
Functional Description	
Returns parameter CounterID of a faulty IncrementCounter call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-84 OSError_IncrementCounter_CounterID

6.1.85 OSError_GetCounterValue_CounterID

Prototype	
`CounterType` **`OSError_GetCounterValue_CounterID`** `(void)`	
Parameter	
void	none
Return code	
CounterType	Requested parameter value.
Functional Description	
Returns parameter CounterID of a faulty GetCounterValue call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-85 OSError_GetCounterValue_CounterID

6.1.86 OSError_GetCounterValue_Value

Prototype	
`TickRefType` **`OSError_GetCounterValue_Value`** `(void)`	
Parameter	
void	none
Return code	
TickRefType	Requested parameter value.
Functional Description	
Returns parameter Value of a faulty GetCounterValue call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-86 OSError_GetCounterValue_Value

6.1.87 OSError_GetElapsedValue_CounterID

Prototype	
`CounterType` **`OSError_GetElapsedValue_CounterID`** `(void)`	
Parameter	
void	none
Return code	
CounterType	Requested parameter value.
Functional Description	
Returns parameter CounterID of a faulty GetElapsedValue call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-87 OSError_GetElapsedValue_CounterID

6.1.88 OSError_GetElapsedValue_Value

Prototype	
`TickRefType` **`OSError_GetElapsedValue_Value`** `(void)`	
Parameter	
void	none
Return code	
TickRefType	Requested parameter value.
Functional Description	
Returns parameter Value of a faulty GetElapsedValue call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-88 OSError_GetElapsedValue_Value

6.1.89 OSError_GetElapsedValue_ElapsedValue

Prototype	
`TickRefType` **`OSError_GetElapsedValue_ElapsedValue`** `(void)`	
Parameter	
void	none
Return code	
TickRefType	Requested parameter value.
Functional Description	
Returns parameter ElapsedValue of a faulty GetElapsedValue call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-89 OSError_GetElapsedValue_ElapsedValue

6.1.90 OSError_TerminateApplication_Application

Prototype	
`ApplicationType` **`OSError_TerminateApplication_Application`** `(void)`	
Parameter	
void	none
Return code	
ApplicationType	Requested parameter value.
Functional Description	
Returns parameter Application of a faulty TerminateApplication call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-90 OSError_TerminateApplication_Application

6.1.91 OSError_TerminateApplication_RestartOption

Prototype	
`RestartType` **`OSError_TerminateApplication_RestartOption`** `(void)`	
Parameter	
void	none
Return code	
RestartType	Requested parameter value.
Functional Description	
Returns parameter RestartOption of a faulty TerminateApplication call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-91 OSError_TerminateApplication_RestartOption

6.1.92 OSError_GetApplicationState_Application

Prototype	
`ApplicationType` **`OSError_GetApplicationState_Application`** `(void)`	
Parameter	
void	none
Return code	
ApplicationType	Requested parameter value.
Functional Description	
Returns parameter Application of a faulty GetApplicationState call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-92 OSError_GetApplicationState_Application

6.1.93 OSError_GetApplicationState_Value

Prototype	
`ApplicationStateRefType` **`OSError_GetApplicationState_Value`** `(void)`	
Parameter	
void	none
Return code	
ApplicationStateRefType	Requested parameter value.
Functional Description	
Returns parameter Value of a faulty GetApplicationState call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-93 OSError_GetApplicationState_Value

6.1.94 OSError_GetSpinlock_SpinlockId

Prototype	
`SpinlockIdType` **`OSError_GetSpinlock_SpinlockId`** `(void)`	
Parameter	
void	none
Return code	
SpinlockIdType	Requested parameter value.
Functional Description	
Returns parameter SpinlockId of a faulty GetSpinlock call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-94 OSError_GetSpinlock_SpinlockId

6.1.95 OSError_ReleaseSpinlock_SpinlockId

Prototype	
`SpinlockIdType` **`OSError_ReleaseSpinlock_SpinlockId`** `(void)`	
Parameter	
void	none
Return code	
SpinlockIdType	Requested parameter value.
Functional Description	
Returns parameter SpinlockId of a faulty ReleaseSpinlock call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-95 OSError_ReleaseSpinlock_SpinlockId

6.1.96 OSError_TryToGetSpinlock_SpinlockId

Prototype	
`SpinlockIdType` **`OSError_TryToGetSpinlock_SpinlockId`** `(void)`	
Parameter	
void	none
Return code	
SpinlockIdType	Requested parameter value.
Functional Description	
Returns parameter SpinlockId of a faulty TryToGetSpinlock call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-96 OSError_TryToGetSpinlock_SpinlockId

6.1.97 OSError_TryToGetSpinlock_Success

Prototype	
`TryToGetSpinlockType const *` **`OSError_TryToGetSpinlock_Success`** `(void)`	
Parameter	
void	none
Return code	
TryToGetSpinlockType const *	Requested parameter value.
Functional Description	
Returns parameter Success of a faulty TryToGetSpinlock call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-97 OSError_TryToGetSpinlock_Success

6.1.98 OSError_ControlIdle_CoreID

Prototype	
`CoreIdType` **`OSError_ControlIdle_CoreID`** `(void)`	
Parameter	
void	none
Return code	
CoreIdType	Requested parameter value.
Functional Description	
Returns parameter CoreID of a faulty ControlIdle call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-98 OSError_ControlIdle_CoreID

6.1.99 OSError_Os_GetExceptionContext_Context

Prototype	
`Os_ExceptionContextRefType` **`OSError_Os_GetExceptionContext_Context`** `(void)`	
Parameter	
void	none
Return code	
Os_ExceptionContextRefType	Requested parameter value.
Functional Description	
Returns parameter Context of a faulty Os_GetExceptionContext call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-99 OSError_Os_GetExceptionContext_Context

6.1.100 OSError_Os_SetExceptionContext_Context

Prototype	
`Os_ExceptionContextRefType` **`OSError_Os_SetExceptionContext_Context`** `(void)`	
Parameter	
void	none
Return code	
Os_ExceptionContextRefType	Requested parameter value.
Functional Description	
Returns parameter Context of a faulty Os_SetExceptionContext call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-100 OSError_Os_SetExceptionContext_Context

6.1.101 OSError_ControlIdle_IdleMode

Prototype	
`IdleModeType` **`OSError_ControlIdle_IdleMode`** `(void)`	
Parameter	
void	none
Return code	
IdleModeType	Requested parameter value.
Functional Description	
Returns parameter IdleMode of a faulty ControlIdle call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-101 OSError_ControlIdle_IdleMode

6.1.102 OSError_IocSend_IN

Prototype	
`void const * OSError_IocSend_IN (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter IN of a faulty IocSend call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-102 OSError_IocSend_IN

6.1.103 OSError_IocWrite_IN

Prototype	
`void const * OSError_IocWrite_IN (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter IN of a faulty IocWrite call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-103 OSError_IocWrite_IN

6.1.104 OSError_IocSendGroup_IN

Prototype	
`void const * OSError_IocSendGroup_IN (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter IN of a faulty IocSendGroup call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-104 OSError_IocSendGroup_IN

6.1.105 OSError_IocWriteGroup_IN

Prototype	
`void const * OSError_IocWriteGroup_IN (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter IN of a faulty IocWriteGroup call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-105 OSError_IocWriteGroup_IN

6.1.106 OSError_IocReceive_OUT

Prototype	
`void const * OSError_IocReceive_OUT (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter OUT of a faulty IocReceive call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-106 OSError_IocReceive_OUT

6.1.107 OSError_IocRead_OUT

Prototype	
`void const * OSError_IocRead_OUT (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter OUT of a faulty IocRead call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-107 OSError_IocRead_OUT

6.1.108 OSError_IocReceiveGroup_OUT

Prototype	
`void const * OSError_IocReceiveGroup_OUT (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter OUT of a faulty IocReceiveGroup call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-108 OSError_IocReceiveGroup_OUT

6.1.109 OSError_IocReadGroup_OUT

Prototype	
`void const * OSError_IocReadGroup_OUT (void)`	
Parameter	
void	none
Return code	
void const *	Requested parameter value.
Functional Description	
Returns parameter OUT of a faulty IocReadGroup call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-109 OSError_IocReadGroup_OUT

6.1.110 OSError_StartOS_Mode

Prototype	
`AppModeType` **`OSError_StartOS_Mode`** `(void)`	
Parameter	
void	none
Return code	
AppModeType	Requested parameter value.
Functional Description	
Returns parameter Mode of a faulty StartOS call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-110 OSError_StartOS_Mode

6.1.111 OSError_ActivateTask_TaskID

Prototype	
`TaskType` **`OSError_ActivateTask_TaskID`** `(void)`	
Parameter	
void	none
Return code	
TaskType	Requested parameter value.
Functional Description	
Returns parameter TaskID of a faulty ActivateTask call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-111 OSError_ActivateTask_TaskID

6.1.112 OSError_ChainTask_TaskID

Prototype	
`TaskType` **`OSError_ChainTask_TaskID`** `(void)`	
Parameter	
void	none
Return code	
TaskType	Requested parameter value.
Functional Description	
Returns parameter TaskID of a faulty ChainTask call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-112 OSError_ChainTask_TaskID

6.1.113 OSError_GetTaskID_TaskID

Prototype	
`TaskRefType` **`OSError_GetTaskID_TaskID`** `(void)`	
Parameter	
void	none
Return code	
TaskRefType	Requested parameter value.
Functional Description	
Returns parameter TaskID of a faulty GetTaskID call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-113 OSError_GetTaskID_TaskID

6.1.114 OSError_GetTaskState_TaskID

Prototype	
`TaskType` **`OSError_GetTaskState_TaskID`** `(void)`	
Parameter	
void	none
Return code	
TaskType	Requested parameter value.
Functional Description	
Returns parameter TaskID of a faulty GetTaskState call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-114 OSError_GetTaskState_TaskID

6.1.115 OSError_GetTaskState_State

Prototype	
`TaskStateRefType` **`OSError_GetTaskState_State`** `(void)`	
Parameter	
void	none
Return code	
TaskStateRefType	Requested parameter value.
Functional Description	
Returns parameter State of a faulty GetTaskState call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-115 OSError_GetTaskState_State

6.1.116 OSError_SetEvent_TaskID

Prototype	
`TaskType` **`OSError_SetEvent_TaskID`** `(void)`	
Parameter	
void	none
Return code	
TaskType	Requested parameter value.
Functional Description	
Returns parameter TaskID of a faulty SetEvent call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-116 OSError_SetEvent_TaskID

6.1.117 OSError_SetEvent_Mask

Prototype	
`EventMaskType` **`OSError_SetEvent_Mask`** `(void)`	
Parameter	
void	none
Return code	
EventMaskType	Requested parameter value.
Functional Description	
Returns parameter Mask of a faulty SetEvent call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-117 OSError_SetEvent_Mask

6.1.118 OSError_ClearEvent_Mask

Prototype	
`EventMaskType` **`OSError_ClearEvent_Mask`** `(void)`	
Parameter	
void	none
Return code	
EventMaskType	Requested parameter value.
Functional Description	
Returns parameter Mask of a faulty ClearEvent call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-118 OSError_ClearEvent_Mask

6.1.119 OSError_GetEvent_TaskID

Prototype	
`TaskType` **`OSError_GetEvent_TaskID`** `(void)`	
Parameter	
void	none
Return code	
TaskType	Requested parameter value.
Functional Description	
Returns parameter TaskID of a faulty GetEvent call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-119 OSError_GetEvent_TaskID

6.1.120 OSError_GetEvent_Mask

Prototype	
`EventMaskRefType` **`OSError_GetEvent_Mask`** `(void)`	
Parameter	
void	none
Return code	
EventMaskRefType	Requested parameter value.
Functional Description	
Returns parameter Mask of a faulty GetEvent call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-120 OSError_GetEvent_Mask

6.1.121 OSError_WaitEvent_Mask

Prototype	
`EventMaskType` **`OSError_WaitEvent_Mask`** `(void)`	
Parameter	
void	none
Return code	
EventMaskType	Requested parameter value.
Functional Description	
Returns parameter Mask of a faulty WaitEvent call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-121 OSError_WaitEvent_Mask

6.1.122 OSError_GetAlarmBase_AlarmID

Prototype	
`AlarmType` **`OSError_GetAlarmBase_AlarmID`** `(void)`	
Parameter	
void	none
Return code	
AlarmType	Requested parameter value.
Functional Description	
Returns parameter AlarmID of a faulty GetAlarmBase call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-122 OSError_GetAlarmBase_AlarmID

6.1.123 OSError_GetAlarmBase_Info

Prototype	
`AlarmBaseRefType` **`OSError_GetAlarmBase_Info`** `(void)`	
Parameter	
void	none
Return code	
AlarmBaseRefType	Requested parameter value.
Functional Description	
Returns parameter Info of a faulty GetAlarmBase call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-123 OSError_GetAlarmBase_Info

6.1.124 OSError_GetAlarm_AlarmID

Prototype	
`AlarmType OSError_GetAlarm_AlarmID (void)`	
Parameter	
void	none
Return code	
AlarmType	Requested parameter value.
Functional Description	
Returns parameter AlarmID of a faulty GetAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-124 OSError_GetAlarm_AlarmID

6.1.125 OSError_GetAlarm_Tick

Prototype	
`TickRefType OSError_GetAlarm_Tick (void)`	
Parameter	
void	none
Return code	
TickRefType	Requested parameter value.
Functional Description	
Returns parameter Tick of a faulty GetAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-125 OSError_GetAlarm_Tick

6.1.126 OSError_SetRelAlarm_AlarmID

Prototype	
`AlarmType` **`OSError_SetRelAlarm_AlarmID`** `(void)`	
Parameter	
void	none
Return code	
AlarmType	Requested parameter value.
Functional Description	
Returns parameter AlarmID of a faulty SetRelAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-126 OSError_SetRelAlarm_AlarmID

6.1.127 OSError_SetRelAlarm_increment

Prototype	
`TickType` **`OSError_SetRelAlarm_increment`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter increment of a faulty SetRelAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-127 OSError_SetRelAlarm_increment

6.1.128 OSError_SetRelAlarm_cycle

Prototype	
`TickType` **`OSError_SetRelAlarm_cycle`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter cycle of a faulty SetRelAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-128 OSError_SetRelAlarm_cycle

6.1.129 OSError_SetAbsAlarm_AlarmID

Prototype	
`AlarmType` **`OSError_SetAbsAlarm_AlarmID`** `(void)`	
Parameter	
void	none
Return code	
AlarmType	Requested parameter value.
Functional Description	
Returns parameter AlarmID of a faulty SetAbsAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-129 OSError_SetAbsAlarm_AlarmID

6.1.130 OSError_SetAbsAlarm_start

Prototype	
`TickType` **`OSError_SetAbsAlarm_start`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter start of a faulty SetAbsAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-130 OSError_SetAbsAlarm_start

6.1.131 OSError_SetAbsAlarm_cycle

Prototype	
`TickType` **`OSError_SetAbsAlarm_cycle`** `(void)`	
Parameter	
void	none
Return code	
TickType	Requested parameter value.
Functional Description	
Returns parameter cycle of a faulty SetAbsAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-131 OSError_SetAbsAlarm_cycle

6.1.132 OSError_CancelAlarm_AlarmID

Prototype	
`AlarmType` **`OSError_CancelAlarm_AlarmID`** `(void)`	
Parameter	
void	none
Return code	
AlarmType	Requested parameter value.
Functional Description	
Returns parameter AlarmID of a faulty CancelAlarm call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-132 OSError_CancelAlarm_AlarmID

6.1.133 OSError_GetResource_ResID

Prototype	
`ResourceType` **`OSError_GetResource_ResID`** `(void)`	
Parameter	
void	none
Return code	
ResourceType	Requested parameter value.
Functional Description	
Returns parameter ResID of a faulty GetResource call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-133 OSError_GetResource_ResID

6.1.134 OSError_ReleaseResource_ResID

Prototype	
`ResourceType` **`OSError_ReleaseResource_ResID`** `(void)`	
Parameter	
void	none
Return code	
ResourceType	Requested parameter value.
Functional Description	
Returns parameter ResID of a faulty ReleaseResource call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-134 OSError_ReleaseResource_ResID

6.1.135 OSError_Os_GetUnhandledIrq_InterruptSource

Prototype	
`Os_InterruptSourceIdRefType` **`OSError_Os_GetUnhandledIrq_InterruptSource`** `(void)`	
Parameter	
void	none
Return code	
Os_InterruptSourceIdRefType	Requested parameter value.
Functional Description	
Returns parameter InterruptSource of a faulty Os_GetUnhandledIrq call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-135 OSError_Os_GetUnhandledIrq_InterruptSource

6.1.136 OSError_Os_GetUnhandledExc_ExceptionSource

Prototype	
`Os_ExceptionSourceIdRefType` **`OSError_Os_GetUnhandledExc_ExceptionSource`** `(void)`	
Parameter	
void	none
Return code	
Os_ExceptionSourceIdRefType	Requested parameter value.
Functional Description	
Returns parameter ExceptionSource of a faulty Os_GetUnhandledExc call.	
Particularities and Limitations	
Pre-Condition: None --no details--	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-136 OSError_Os_GetUnhandledExc_ExceptionSource

6.1.137 OSError_BarrierSynchronize_BarrierID

Prototype	
`Os_BarrierIdType` **`OSError_BarrierSynchronize_BarrierID`**`(void)`	
Parameter	
`void`	none
Return code	
`Os_BarrierIdType`	Requested parameter value
Functional Description	
Returns parameter BarrierID of a faulty Os_BarrierSynchronize call.	
Particularities and Limitations	
> Pre-Condition: None	
Call context	
> ERRHOOK > This function is Synchronous > This function is Reentrant	

Table 6-137 OSError_BarrierSynchronize_BarrierID

6.2 Additional OS services

The OS provides the following additional services which are not part of the AUTOSAR OS specification.

6.2.1 Os_GetVersionInfo

Prototype	
`void` **`Os_GetVersionInfo`** `(Std_VersionInfoType *versioninfo)`	
Parameter	
`versioninfo [out]`	Version information (decimal coded).
Return code	
`void`	none
Functional Description	
AUTOSAR Get Version Information API.	
Particularities and Limitations	
Given object pointer(s) are valid. Returns the Published information of MICROSAR OS.	
Call context	
> ANY > This function is Synchronous > This function is Reentrant	

Table 6-138 Os_GetVersionInfo

6.2.2 Peripheral Access API

The API consists of read, write and bit manipulating functions for 8, 16 and 32 bit accesses.

6.2.2.1 Read Functions

Prototype	

`FUNC(uint8, OS_CODE) Os_ReadPeripheral8(`
`  Os_PeripheralIdType PeripheralID,`
`  P2CONST(uint8, AUTOMATIC, OS_APPL_DATA) Address`
`)`	

`FUNC(uint16, OS_CODE) Os_ReadPeripheral16(`
`  Os_PeripheralIdType PeripheralID,`
`  P2CONST(uint16, AUTOMATIC, OS_APPL_DATA) Address`
`)`	

`FUNC(uint32, OS_CODE) Os_ReadPeripheral32(`
`  Os_PeripheralIdType PeripheralID,`
`  P2CONST(uint32, AUTOMATIC, OS_APPL_DATA) Address`
`)`	

Parameter	
`PeripheralID`	The ID of a configured peripheral region. The symbolic name may be passed here.
`Address`	The address of the peripheral register which shall be read.
Return code	

`uint8`
`uint16`
`uint32`
	The content of the peripheral register which has been passed in the Address parameter.

Functional Description	
The function distinguishes the address range of the passed peripheral region. It checks whether the parameter “Address” is within this range. Then it checks whether the calling OS application has access rights to the passed peripheral region. If all checks did pass the API returns the content of the passed address	
Particularities and Limitations	
> If one of the performed checks within the API is not passed the OS treats it as a memory protection violation. The ProtectionHook() is called. > The data alignment of the “Address” parameter is not checked by the service function. Misaligned accesses may lead to exceptions.	

Table 6-139 Read Peripheral API



Note
The former names of the API functions osReadPeripheral8(), osReadPeripheral16() and osReadPeripheral32() may also be used (the OS is backward compatible).

© 2020 Vector Informatik GmbH

6.2.2.2 Write Functions

Prototype	

`FUNC(void, OS_CODE) Os_WritePeripheral8(`
`  Os_PeripheralIdType PeripheralID,`
`  P2VAR(uint8, AUTOMATIC, OS_APPL_DATA) Address,`
`  uint8 Value`
`)`	

`FUNC(void, OS_CODE) Os_WritePeripheral16(`
`  Os_PeripheralIdType PeripheralID,`
`  P2VAR(uint16, AUTOMATIC, OS_APPL_DATA) Address,`
`  uint16 Value`
`)`	

`FUNC(void, OS_CODE) Os_WritePeripheral32(`
`  Os_PeripheralIdType PeripheralID,`
`  P2VAR(uint32, AUTOMATIC, OS_APPL_DATA) Address,`
`  uint32 Value`
`)`	

Parameter	
`PeripheralID`	The ID of a configured peripheral region. The symbolic name may be passed here.
`Address`	The address of the peripheral register which shall be written.
`Value uint8`	Value which shall be written to the peripheral register.
`Value uint16`	
`Value uint32`	
Return code	
`void`	none
Functional Description	
The function distinguishes the address range of the passed peripheral region. It checks whether the parameter “Address” is within this range. Then it checks whether the calling OS application has access rights to the passed peripheral region. If all checks did pass the OS writes the Value into the peripheral register.	
Particularities and Limitations	
> If one of the performed checks within the API is not passed the OS treats it as a memory protection violation. The ProtectionHook() is called. > The data alignment of the “Address” parameter is not checked by the service function. Misaligned accesses may lead to exceptions.	

Table 6-140 Write Peripheral APIs



Note
The former names of the API functions osWritePeripheral8(), osWritePeripheral16() and osWritePeripheral32() may also be used (the OS is backward compatible).

6.2.2.3 Bitmask Functions

Prototype

```
FUNC(void, OS_CODE) Os_ModifyPeripheral8(
  Os_PeripheralIdType PeripheralID,
  P2VAR(uint8, AUTOMATIC, OS_APPL_DATA) Address,
  uint8 ClearMask,
  uint8 SetMask
)
```

```
FUNC(void, OS_CODE) Os_ModifyPeripheral16(
  Os_PeripheralIdType PeripheralID,
  P2VAR(uint16, AUTOMATIC, OS_APPL_DATA) Address,
  uint16 ClearMask,
  uint16 SetMask
)
```

```
FUNC(void, OS_CODE) Os_ModifyPeripheral32(
  Os_PeripheralIdType PeripheralID,
  P2VAR(uint32, AUTOMATIC, OS_APPL_DATA) Address,
  uint32 ClearMask,
  uint32 SetMask
)
```

Parameter

PeripheralID	The ID of a configured peripheral region. The symbolic name may be passed here.
Address	The address of the peripheral register which shall be modified.
ClearMask uint8 ClearMask uint16 ClearMask uint32	The mask for the AND operation.
SetMask uint8 SetMask uint16 SetMask uint32	The mask for the OR operation.

Return code

void	none

Functional Description

The function distinguishes the address range of the passed peripheral region. It checks whether the parameter “Address” is within this range. Then it checks whether the calling OS application has access rights to the passed peripheral region.

If all checks did pass the OS performs the following operation:

```
Address = (Address & ClearMask) | SetMask;
```

Particularities and Limitations

> If one of the performed checks within the API is not passed the OS treats it as a memory protection violation. The ProtectionHook() is called.

> The data alignment of the “Address” parameter is not checked by the service function. Misaligned accesses may lead to exceptions.

Table 6-141 Bitmask Peripheral API



Note
The former names of the API functions osModifyPeripheral8(), osModifyPeripheral16() and osModifyPeripheral32() may also be used (the OS is backward compatible).

6.2.3 Pre-Start Task

Prototype
`FUNC(void, OS_CODE) Os_EnterPreStartTask(void)`
Parameter
none
Return code
none
Functional Description
The function schedules and dispatches to the pre-start task. The core is initialized that non-trusted function calls can be used safely within this task.
Particularities and Limitations
> Has to be called on a core which is started as an AUTOSAR core. > The core which calls this function must have a configured pre-start task. > Must only be called once. > Must be called prior to `StartOS()` but after `Os_Init()`

Table 6-142 API Service Os_EnterPreStartTask

6.2.4 Non-Trusted Functions (NTF)

Prototype	

`FUNC(StatusType, OS_CODE) Os_CallNonTrustedFunction(`
`  Os_NonTrustedFunctionIndexType FunctionIndex,`
`  Os_NonTrustedFunctionParameterRefType FunctionParams`
`)`	

Parameter	
`FunctionIndex`	The Index of the non-trusted function.
`FunctionParams`	Pointer to parameters which are passed to the non-trusted function.
Return code	
`E_OK`	No error.
`E_OS_SERVICEID`	No function defined for this index.
`E_OS_CALLEVEL`	Called from invalid context. (EXTENDED status)
`E_OS_ACCESS`	The given object belongs to a foreign core. (EXTENDED status)
`E_OS_ACCESS`	Owner OS application is not accessible. (Service Protection)
`E_OS_SYS_NO_NTFSTACK`	No further NTF-Stacks available. (EXTENDED status)
Functional Description	
Performs a call to the non-trusted function passed in „`FunctionIndex`“.	
Particularities and Limitations	
> The non-trusted function will not be able to return any values. It has no access rights to the data structure of the caller referenced by the “`FunctionParams`” parameter. > This API service may be called with disabled interrupts.	

Table 6-143 Call Non-Trusted Function API

6.2.5 Fast Trusted Functions

Prototype	
`FUNC(StatusType, OS_CODE) Os_CallFastTrustedFunction ( Os_FastTrustedFunctionIndexType FunctionIndex, Os_FastTrustedFunctionParameterRefType FunctionParams )`	
Parameter	
`FunctionIndex`	Index of the function to be called.
`FunctionParams`	Pointer to the parameters for the function. If no parameters are provided a NULL pointer has to be passed.
Return code	
`E_OK`	No error.
`E_OS_SERVICEID`	No function defined for this index.
Functional Description	
Performs a call to the fast trusted function passed in „`FunctionIndex`“.	
Particularities and Limitations	
> May be called with interrupts disabled	

6.2.6 Interrupt Source API

6.2.6.1 Disable Interrupt Source

Prototype	
`FUNC(StatusType, OS_CODE) Os_DisableInterruptSource( ISRType ISRID )`	
Parameter	
`ISRID`	The ID of a category 2 ISR.
Return code	
`E_OK`	No error.
`E_OS_ID`	ISRID is not a valid category 2 ISR identifier (EXTENDED status)
`E_OS_CALLEVEL`	Wrong call context of the API function (EXTENDED status)
`E_OS_ACCESS`	The calling application is not the owner of the ISR passed in ISRID (Service Protection)
Functional Description	
MICROSAR OS disables the interrupt source by modifying the interrupt controller registers.	
Particularities and Limitations	
> May be called for category 2 ISRs only.	

Table 6-144 API Service Os_DisableInterruptSource



Caution

Depending on target platform (e.g. ARM platforms), the ISR may still become active although Os_DisableInterruptSource has returned E_OK.

This may be caused by hardware racing conditions e.g. when the interrupt is requested immediately before the effect of Os_DisableInterruptSource becomes active.

6.2.6.2 Enable Interrupt Source

Prototype	

`FUNC(StatusType, OS_CODE) Os_EnableInterruptSource(`
`  ISRType ISRID,`
`  boolean ClearPending`
`)`	

Parameter	
`ISRID`	The ID of a category 2 ISR.
`ClearPending`	Defines whether the pending flag shall be cleared (TRUE) or not (FALSE).
Return code	
`E_OK`	No error.
`E_OS_ID`	ISRID is not a valid category 2 ISR identifier ID (EXTENDED status)
`E_OS_CALLEVEL`	Wrong call context of the API function (EXTENDED status)
`E_OS_VALUE`	The parameter “ClearPending” is not a boolean value (EXTENDED status)
`E_OS_ACCESS`	The calling application is not the owner of the ISR passed in ISRID (Service Protection)
`E_OS_SYS_UNIMPLEMEN-TED_FUNCTIONALITY`	Hardware does not support to clear pending interrupts (EXTENDED status)
Functional Description	
MICROSAR OS enables the interrupt source by modifying the interrupt controller registers. Additionally it may clear the interrupt pending flag	
Particularities and Limitations	
> May be called for category 2 ISRs only	

Table 6-145 API Service Os_EnableInterruptSource

6.2.6.3 Clear Pending Interrupt

Prototype	
`FUNC(StatusType, OS_CODE) Os_ClearPendingInterrupt( ISRType ISRID )`	
Parameter	
`ISRID`	The ID of a category 2 ISR.
Return code	
`E_OK`	No errors
`E_OS_ID`	ISRID is not a valid category 2 ISR identifier (EXTENDED status)
`E_OS_CALLEVEL`	Wrong call context of the API function (EXTENDED status)
`E_OS_ACCESS`	The calling application is not the owner of the ISR passed in ISRID (Service Protection)
`E_OS_SYS_UNIMPLEMENTED_FUNCTIONALITY`	Hardware does not support to clear pending interrupts (EXTENDED status)
Functional Description	
MICROSAR OS clears the interrupt pending flag by modifying the interrupt controller registers.	
Particularities and Limitations	
> May be called for category 2 ISRs only	

Table 6-146 API Service Os_ClearPendingInterrupt

Note

In order to minimize the risk of spurious interrupts, Os_ClearPendingInterrupt shall be called only after the ISR (IsrId) has been disabled and before it is enabled again.

Note

The API service tries to clear the pending flag only. The interrupt cause has to be reset by the application software. Otherwise the flag may be set again immediately after it has been cleared by the API. This may be the case e.g. with level triggered ISRs.

6.2.6.4 Check Interrupt Source Enabled

Prototype	

`FUNC(StatusType, OS_CODE) Os_IsInterruptSourceEnabled(`
`  ISRType ISRID,`
`  P2VAR(boolean, AUTOMATIC, OS_VAR_NOINIT) IsEnabled`
`)`	

Parameter	
`ISRID`	The ID of a category 2 ISR.
`IsEnabled`	Defines wether the source of the ISR is enabled (TRUE) or not (FALSE)
Return code	
`E_OK`	No errors
`E_OS_ID`	ISRID is not a valid category 2 ISR identifier (EXTENDED status)
`E_OS_CALLEVEL`	Wrong call context of the API function (EXTENDED status)
`E_OS_ACCESS`	The calling application is not the owner of the ISR passed in ISRID (Service Protection)
`E_OS_PARAM_POINTER`	Given pointer parameter (isEnabled) is NULL (EXTENDED status)
Functional Description	
MICROSAR OS checks if the interrupt source is enabled reading the interrupt controller registers and update the boolean addressed by IsEnabled accordingly	
Particularities and Limitations	
> May be called for category 2 ISRs only	

Table 6-147 API Service Os_IsInterruptSourceEnabled

6.2.6.5 Check Interrupt Pending

Prototype	

`FUNC(StatusType, OS_CODE) Os_IsInterruptPending(`
`  ISRType ISRID,`
`  P2VAR(boolean, AUTOMATIC, OS_VAR_NOINIT) IsPending`
`)`	

Parameter	
`ISRID`	The ID of a category 2 ISR.
`IsPending`	Defines wether the ISR has been already requesterd (TRUE) or not (FALSE)
Return code	
`E_OK`	No errors
`E_OS_ID`	ISRID is not a valid category 2 ISR identifier (EXTENDED status)
`E_OS_CALLEVEL`	Wrong call context of the API function (EXTENDED status)
`E_OS_ACCESS`	The calling application is not the owner of the ISR passed in ISRID (Service Protection)
`E_OS_PARAM_POINTER`	Given pointer parameter (isPending) is NULL (EXTENDED status)
`E_OS_SYS_UNIMPLEMEN-TED_FUNCTIONALITY`	Hardware does not support to check if there are pending interrupts
Functional Description	
MICROSAR OS checks if the ISR has been already requested, reading the interrupt controller registers and update the boolean addressed by IsPending accordingly	
Particularities and Limitations	
> May be called for category 2 ISRs only	

Table 6-148 API Service Os_IsInterruptPending

6.2.6.6 Initial Enable Interrupt Sources

Prototype	

`FUNC(StatusType, OS_CODE) Os_InitialEnableInterruptSources(`
`  boolean ClearPending`
`)`	

Parameter	
`ClearPending`	Defines whether the pending flag shall be cleared (TRUE) or not (FALSE).
Return code	
`E_OK`	No error.
`E_OS_CALLEVEL`	Wrong call context of the API function (EXTENDED status)
`E_OS_VALUE`	The parameter “ClearPending” is not a boolean value (EXTENDED status)
`E_OS_SYS_UNIMPLEMEN-TED_FUNCTIONALITY`	Hardware does not support to clear pending interrupts (EXTENDED status)
Functional Description	
MICROSAR OS enables the interrupt sources of all category 2 ISRs by modifying the interrupt controller registers. Additionally it may clear the interrupt pending flags.	
Particularities and Limitations	
> API function can only be called in the context of a trusted and privileged task.	

Table 6-149 API Service Os_InitialEnableInterruptSources

6.2.7 Detailed Error API

6.2.7.1 Get detailed Error

Prototype	
`FUNC(StatusType, OS_CODE) Os_GetDetailedError( Os_ErrorInformationRefType ErrorRef )`	
Parameter	
`ErrorRef`	Output parameter of type Os_ErrorInformationRefType
Return code	
`E_OK`	No error.
`E_OS_CALLEVEL`	Called from invalid context. (EXTENDED status)
`E_OS_PARAM_POINTER`	Given parameter pointer is NULL. (EXTENDED status)
Functional Description	
Returns error information of the last error occurred on the local core.	
Particularities and Limitations	
> The ErrorRef output parameter is a struct which holds the 8 bit AUTOSAR error code, the detailed error code and the service ID of the causing API service.	

Table 6-150 API Service Os_GetDetailedError

6.2.7.2 Unhandled Interrupt Requests

Prototype	
`FUNC(StatusType, OS_CODE) Os_GetUnhandledIrq( Os_InterruptSourceIdRefType InterruptSource )`	
Parameter	
`InterruptSource`	Output parameter of type Os_InterruptSourceIdRefType
Return code	
`E_OK`	No error.
`E_OS_CORE`	Called from a non-AUTOSAR core (EXTENDED status)
`E_OS_PARAM_POINTER`	Null pointer passed as argument (EXTENDED status)
`E_OS_STATE`	No unhandled interrupt reported since start up (EXTENDED status)
Functional Description	
In case of an unhandled interrupt request the triggering interrupt source can be distinguished with this service.	
Particularities and Limitations	
> The return value of this function may be interpreted differently for different controller families. Please refer to [9] for additional details.	

Table 6-151 API Service Os_GetUnhandledIrq

6.2.7.3 Unhandled Exception Requests

Prototype	
`FUNC(StatusType, OS_CODE) Os_GetUnhandledExc( Os_ExceptionSourceIdRefType ExceptionSource )`	
Parameter	
`ExceptionSource`	Output parameter of type Os_ExceptionSourceIdRefType
Return code	
`E_OK`	No error.
`E_OS_CORE`	Called from a non-AUTOSAR core (EXTENDED status)
`E_OS_PARAM_POINTER`	Null pointer passed as argument (EXTENDED status)
`E_OS_STATE`	No unhandled exception reported since start up. (EXTENDED status)
Functional Description	
In case of an unhandled exception request the triggering exception source can be distinguished with this service.	
Particularities and Limitations	
> The return value of this function may be interpreted differently for different controller families. Please refer to [9] for additional details.	

Table 6-152 API Service Os_GetUnhandledExc

6.2.8 Stack Usage API

All Service API functions which calculate stack usage are working in the same way.

- The service performs error checks:
  - validity of passed parameters
  - existence of OS Hook routine (if hook stacks are queried)
  - cross core checks (when stack sizes are queried of stacks which are located on a foreign core)
  - if one of these checks fails, the OS initiates error handling (ErrorHook() is called)
- Calculates the maximum stack usage of the queried stack since call of StartOS()
- Returns the stack usage in bytes
- Stack Usage API services may be called from any context
- Stack Usage API services may be used cross core

Stack usage service API Prototypes	Parameter
`FUNC(uint32, OS_CODE) Os_GetTaskStackUsage (TaskType TaskID)`	Task ID
`FUNC(uint32, OS_CODE) Os_GetISRStackUsage (ISRType IsrID)`	ISR ID
`FUNC(uint32, OS_CODE) Os_GetKernelStackUsage (CoreIdType CoreID)`	Core ID
`FUNC(uint32, OS_CODE) Os_GetStartupHookStackUsage(CoreIdType CoreID)`	Core ID
`FUNC(uint32, OS_CODE) Os_GetErrorHookStackUsage (CoreIdType CoreID)`	Core ID
`FUNC(uint32, OS_CODE) Os_GetShutdownHookStackUsage(CoreIdType CoreID)`	Core ID
`FUNC(uint32, OS_CODE) Os_GetProtectionHookStackUsage(CoreIdType CoreID)`	Core ID

Table 6-153 Overview: Stack Usage Functions



Caution
Any stack usage function must not be used cross core with interrupts disabled.

6.2.9 RTE Interrupt API

MICROSAR OS provides optimized interrupt en-/disable functions for exclusive usage by the RTE module of Vector.

API Name	Alias (for backward compatibility)	Comment
Os_DisableLevelAM()	osDisableLevelAM()	non nestable service to disable all category 2 interrupts callable from any mode
Os_DisableLevelKM()	osDisableLevelKM()	non nestable service to disable all category 2 interrupts callable from kernel mode
Os_DisableLevelUM()	osDisableLevelUM()	non nestable service to disable all category 2 interrupts callable from user mode
Os_EnableLevelAM()	osEnableLevelAM()	non nestable service to enable all category 2 interrupts callable from any mode
Os_EnableLevelKM()	osEnableLevelKM()	non nestable service to enable all category 2 interrupts callable from kernel mode
Os_EnableLevelUM()	osEnableLevelUM()	non nestable service to enable all category 2 interrupts callable from user mode
Os_DisableGlobalAM()	osDisableGlobalAM()	non nestable service to disable all interrupts callable from any mode
Os_DisableGlobalKM()	osDisableGlobalKM()	non nestable service to disable all interrupts callable from kernel mode
Os_DisableGlobalUM()	osDisableGlobalUM()	non nestable service to disable all interrupts callable from user mode
Os_EnableGlobalAM()	osEnableGlobalAM()	non nestable service to enable all interrupts callable from any mode
Os_EnableGlobalKM()	osEnableGlobalKM()	non nestable service to enable all interrupts callable from kernel mode
Os_EnableGlobalUM()	osEnableGlobalUM()	non nestable service to enable all interrupts callable from user mode

Caution
RTE interrupt handling functions should not be used by the application and are listed here to avoid naming collisions.

Caution
When nesting other OS interrupt locking/unlocking APIs and RTE interrupt APIs erroneous behavior is possible. One error that may be reported by the OS in this case is “OS_STATUS_DISABLEDINT”.

6.2.10 Time Conversion Macros

Based on counter configuration attributes conversion macros are generated which are capable to convert from time into counter ticks and vice versa.

There are a set of conversion macros for each configured OS counter



Caution
The conversion macros embody multiplication operations which may lead to a data type overflow. The macros are not capable to detect these overflows



Caution
Although the results of the macros are mathematically rounded the result will still be an integer (e.g. results smaller than 0.5 are used as 0).

6.2.10.1 Convert from Time into Counter Ticks

OS_NS2TICKS_<Counter Name>(x)	x is given in nanoseconds
OS_US2TICKS_<Counter Name>(x)	x is given in microseconds
OS_MS2TICKS_<Counter Name>(x)	x is given in milliseconds
OS_SEC2TICKS_<Counter Name>(x)	x is given in seconds

Table 6-154 Conversion Macros from Time to Counter Ticks

6.2.10.2 Convert from Counter Ticks into Time

OS_TICKS2NS_<Counter Name>(x)	The result is in nanoseconds
OS_TICKS2US_<Counter Name>(x)	The result is in microseconds
OS_TICKS2MS_<Counter Name>(x)	The result is in milliseconds
OS_TICKS2SEC_<Counter Name>(x)	The result is in seconds

Table 6-155 Conversion Macros from Counter Ticks to Time

6.2.11 OS Initialization

Prototype
`FUNC(void, OS_CODE) Os_Init(void)`
Parameter
none
Return code
none
Functional Description
The function performs all the basic OS initialization which includes > Variable initialization > Interrupt controller initialization > System MPU initialization in SC3 and SC4 systems (if supported by platform) > Synchronization barriers in multi core systems
Particularities and Limitations
> A function call to this service must be available on all available cores (even for cores which are intended to be a non-AUTOSAR core) > After call of `Os_Init()` the AUTOSAR interrupt API may be used. > After Call of `Os_Init()` the API GetCoreID may be used. > Pre-Condition: >> Os_Init may only be called if the interrupts are globally disabled. >> Either disable the interrupts by using the global flag or, in case of Cortex M platform, disable the interrupts by setting the highest possible interrupt level (BASEPRI register).

Table 6-156 API Service Os_Init

Prototype
`FUNC(void, OS_CODE) Os_InitMemory(void)`
Parameter
none
Return code
none
Functional Description
> This is an API function which is provided within all BSWs of Vector. It initializes variables of the BSW. Within the OS module this function is currently empty
Particularities and Limitations
> This service must be called on all available cores (even for cores which are intended to be a non-AUTOSAR core)

Table 6-157 API Service Os_InitMemory

6.2.12 Timing Hooks

Implementation of all timing hooks must conform to the following guidelines:

> They are expected to be implemented as a macro.

> Reentrancy is possible on multicore systems with different caller core IDs.

> Calls of any operating system API functions are prohibited within the hooks.



Note
All hooks are called from within an OS API service. Interrupts are disabled

6.2.12.1 Timing Hooks for Activation and Termination

6.2.12.1.1 Task Activation

Macro	
`#define OS_VTH_ACTIVATION(TaskId, DestCoreId, CallerCoreId)`	
Parameter	
`TaskId`	Identifier of the task which is activated
`DestCoreId`	Identifier of the core on which the task is activated
`CallerCoreId`	Identifier of the core which performs the activation (has called ActivateTask(), has called ChainTask() or has performed an alarm/schedule table action to activate a task)
Return code	
none	
Functional Description	
This hook is called on the caller core when that core has successfully performed the activation of TaskId on the destination core. On single core systems both core IDs are identical.	
Particularities and Limitations	
> Due to internal implementation `DestCoreId` and `CallerCoreId` are always the same.	

6.2.12.1.2 Task Activation Exeeding Limit

Macro	
`#define OS_VTH_ACTIVATION_LIMIT(TaskId, DestCoreId, CallerCoreId)`	
Parameter	
`TaskId`	Identifier of the task which is activated
`DestCoreId`	Identifier of the core on which the task is activated
`CallerCoreId`	Identifier of the core which performs the activation (has called ActivateTask(), has called ChainTask() or has performed an alarm/schedule table action to activate a task)
Return code	
none	
Functional Description	
This hook is called on the caller core when that core has failed the activation of TaskId on the destination core because number of activations exceeds the limit.	
Particularities and Limitations	
> Due to internal implementation `DestCoreId` and `CallerCoreId` are always the same.	

6.2.12.1.3 Set Event

Macro	
`#define OS_VTH_SETEVENT(TaskId, EventMask, StateChanged, DestCoreId, CallerCoreId)`	
Parameter	
`TaskId`	Identifier of the task which receives this event
`EventMask`	A bit mask with the events which shall be set
`StateChanged`	TRUE: The task state has changed from WAITING to READY FALSE: The task state hasn't changed
`DestCoreId`	Identifier of the core on which the task receives the event
`CallerCoreId`	Identifier of the core which performs the event setting (has called SetEvent() or performed an alarm/schedule table action to set an event)
Return code	
none	
Functional Description	
This hook is called on the caller core when that core has successfully performed the event setting on the destination core.	
Particularities and Limitations	
> Due to internal implementation `DestCoreId` and `CallerCoreId` are always the same.	

6.2.12.1.4 Wait Event Not Waiting

Macro	
`#define OS_VTH_WAITEVENT_NOWAIT(TaskId, EventMask, DestCoreId, CallerCoreId)`	
Parameter	
`TaskId`	Identifier of the task which is waiting for the event
`EventMask`	A bit mask with the events for which the task is waiting
`DestCoreId`	Identifier of the core on which the task is waiting for the event
`CallerCoreId`	Identifier of the core which performs the wait event (has called WaitEvent())
Return code	
none	
Functional Description	
This hook is called on the caller core when that core has successfully performed the wait event call on the destination core and the events waiting are already set and calling task stays in state RUNNING.	
Particularities and Limitations	
> Due to internal implementation `DestCoreId` and `CallerCoreId` are always the same.	

6.2.12.1.5 Timing Hook for Context Switch

Macro	
`#define OS_VTH_SCHEDULE(FromThreadId, FromThreadReason, ToThreadId, ToThreadReason, CallerCoreId)`	
Parameter	
`FromThreadId`	Identifier of the thread (task, ISR) which has run on the caller core before the switch took place
`FromThreadReason`	The reason, why thread “FromThreadId” is no longer running: OS_VTHP_TASK_TERMINATION > The thread is a task, which has just been terminated. OS_VTHP_ISR_END > The thread is an ISR, which has reached its end. OS_VTHP_TASK_WAITEVENT > The thread is a task, which waits for an event. OS_VTHP_TASK_WAITSEMA > The thread is a task, which waits for the release of a semaphore. OS_VTHP_THREAD_PREEMPT > The thread is interrupted by another one, which has higher priority.
`ToThreadId`	The identifier of the thread, which runs from now on
`ToThreadReason`	The reason, why thread “ToThreadId” becomes running: OS_VTHP_TASK_ACTIVATION > The thread is a task, which was activated. OS_VTHP_ISR_START > The thread is an ISR, which now starts execution. OS_VTHP_TASK_SETEVENT > The thread is a task, which has just received an event it was waiting for. It resumes execution right behind the call of WaitEvent(). OS_VTHP_TASK_GOTSEMA > The thread is a task, which has just got the semaphore it was waiting for. OS_VTHP_THREAD_RESUME: > The thread is a task or ISR, which was preempted before and becomes running again as all higher priority tasks and ISRs do not run anymore. OS_VTHP_THREAD_CLEANUP: > The thread is an ISR which has been forcibly terminated. The implementation of the ISR will not be entered but just some OS internal cleanup code which is needed to switch to the next thread.
`CallerCoreId`	Identifier of the core which performs the thread switch
Return code	
none	

Functional Description
This hook is called on a core when it performs a thread switch (from one task or ISR to another task or ISR).
Particularities and Limitations
> None

6.2.12.1.6 Forcible Termination

Macro	
`#define OS_VTH_FORCED_TERMINATION(ThreadId, CallerCoreId)`	
Parameter	
`ThreadId`	Identifier of the thread (task or ISR) which has been forcibly terminated
`CallerCoreId`	Identifier of the core which performs forcible termination
Return code	
none	
Functional Description	
This hook is called in case a thread (task or ISR) has been forcibly terminated. The thread may not have finished its computations as some error detection mechanism has decided before to forcibly terminate the thread.	
Particularities and Limitations	
> none	

6.2.12.2 Timing Hooks for Locking Purposes

6.2.12.2.1 Get Resource

Macro	
`#define OS_VTH_GOT_RES(ResId, CallerCoreId)`	
Parameter	
`ResId`	Identifier of the resource which has been taken
`CallerCoreId`	Identifier of the core where GetResorce() was called
Return code	
none	
Functional Description	
The OS calls this hook on a successful call of the API function GetResource(). The priority of the calling task or ISR has been increased so that other tasks and ISRs on the same core may need to wait until they can be executed.	

Particularities and Limitations
> none

6.2.12.2.2 Release Resource

Macro	
`#define OS_VTH_REL_RES(ResId, CallerCoreId)`	
Parameter	
`ResId`	Identifier of the resource which has been released
`CallerCoreId`	Identifier of the core where ReleaseResorce() was called
Return code	
None	
Functional Description	
The OS calls this hook on a successful call of the API function ReleaseResource(). The priority of the calling task or ISR has been decreased so that other tasks and ISRs on the same core may become running as a result.	
Particularities and Limitations	
> none	

6.2.12.2.3 Request Spinlock

Macro	
`#define OS_VTH_REQ_SPINLOCK(SpinlockId, CallerCoreId)`	
Parameter	
`SpinlockId`	Identifier of the spinlock which has been requested
`CallerCoreId`	Identifier of the core where GetSpinlock() was called
Return code	
none	
Functional Description	
The OS calls this hook on any attempt to get a spinlock. The calling task or ISR may end up in entering a busy waiting loop. In such case other tasks or ISRs of lower priority have to wait until this task or ISR has taken and released the spinlock.	
Particularities and Limitations	
> The hook is not called for optimized spinlocks > The hook is called only on multicore operating system implementations	

6.2.12.2.4 Request Internal Spinlock

Macro	
`#define OS_VTH_REQ_ISPINLOCK(SpinlockId, CallerCoreId)`	
Parameter	
`SpinlockId`	Identifier of the spinlock which has been requested
`CallerCoreId`	Identifier of the core where the internal spinlock was requested
Return code	
none	
Functional Description	
The OS calls this hook on any attempt to get a spinlock for the OS itself. The OS may end up in entering a busy waiting loop. In such case other program parts on this core have to wait until the OS has taken and released the spinlock.	
Particularities and Limitations	
> Only called for Spinlocks which used internally by the OS	

6.2.12.2.5 Get Spinlock

Macro	
`#define OS_VTH_GOT_SPINLOCK(SpinlockId, CallerCoreId)`	
Parameter	
`SpinlockId`	Identifier of the spinlock which has been taken
`CallerCoreId`	Identifier of the core where GetSpinlock() or TryToGetSpinlock() were called
Return code	
none	
Functional Description	
The OS calls this hook whenever a spinlock has successfully been taken. If a previosly attempt of getting the spinlock was not successful immediately (entered busy waiting loop), this hook means that the core leaves the busy waiting loop. From now on no other thread may get the spinlock until the current task or ISR has released it.	
Particularities and Limitations	
> The hook is not called for optimized spinlocks > The hook is called only on multicore operating system implementations	

6.2.12.2.6 Get Internal Spinlock

Macro	
`#define OS_VTH_GOT_ISPINLOCK(SpinlockId, CallerCoreId)`	
Parameter	
`SpinlockId`	Identifier of the spinlock which has been taken
`CallerCoreId`	Identifier of the core where the internal spinlock has been taken
Return code	
None	
Functional Description	
The OS calls this hook whenever a spinlock has successfully been taken by the OS itself. If a previosly attempt of getting the spinlock was not successful immediately (entered busy waiting loop), this hook means that the core leaves the busy waiting loop. From now on no other thread may get the spinlock until the OS has released it.	
Particularities and Limitations	
> Only called for Spinlocks which used internally by the OS	

6.2.12.2.7 Release Spinlock

Macro	
`#define OS_VTH_REL_SPINLOCK(SpinlockId, CallerCoreId)`	
Parameter	
`SpinlockId`	Identifier of the spinlock which has been released
`CallerCoreId`	Identifier of the core where ReleaseSpinlock() was called
Return code	
none	
Functional Description	
The OS calls this hook on a release of a spinlock. Other tasks and ISR may take the spinlock now.	
Particularities and Limitations	
> The hook is not called for optimized spinlocks > The hook is called only on multicore operating system implementations	

6.2.12.2.8 Release Internal Spinlock

Macro	
`#define OS_VTH_REL_ISPINLOCK(SpinlockId, CallerCoreId)`	
Parameter	
`SpinlockId`	Identifier of the spinlock which has been released
`CallerCoreId`	Identifier of the core where the internal spinlock has been released
Return code	
none	
Functional Description	
The OS calls this hook on a release of a spinlock. Other tasks and ISR may take the spinlock now.	
Particularities and Limitations	
> Only called for Spinlocks which used internally by the OS	

6.2.12.2.9 Disable Interrupts

Macro	
`#define OS_VTH_DISABLEDINT(IntLockId, CallerCoreId)`	
Parameter	
`IntLockId`	OS_VTHP_CAT2INTERRUPTS: Interrupts have been disabled by means of the current interrupt level. That interrupt level has been changed in order to disable all category 2 interrupts, which also prevents task switch and alarm/schedule table management. OS_VTHP_ALLINTERRUPTS: Interrupts have been disabled by means of the global interrupt enable/disable flag. Additionally to the effects described above, also category 1 interrupts are disabled.
`CallerCoreId`	Identifier of the core where interrupts are disabled
Return code	
none	
Functional Description	
The OS calls this hook if the application has called an API function to disable interrupts. The parameter IntLockId describes whether category 1 interrupts may still occur. Mind that the two types of interrupt locking (as described by the IntLockId) are independent from each other so that the hook may be called twice before the hook OS_VTH_ENABLEDINT is called, dependent on the application.	
Particularities and Limitations	
> The hook is not called for operating system internal interrupt locks	

6.2.12.2.10 Enable Interrupts

Macro	
`#define OS_VTH_ENABLEDINT(IntLockId, CallerCoreId)`	
Parameter	
`IntLockId`	OS_VTHP_CAT2INTERRUPTS > Interrupts had been disabled by means of the current interrupt level until this hook was called. The OS releases this lock right after the hook has returned. OS_VTHP_ALLINTERRUPTS > Interrupts had been disabled by means of the global interrupt enable/disable flag before this hook was called. The OS releases this lock right after the hook has returned.
`CallerCoreId`	Identifier of the core where interrupts are disabled
Return code	
None	
Functional Description	
The OS calls this hook if the application has called an API function to enable interrupts. Mind that the two types of interrupt locking (as described by the IntLockId) are independent from each other so that interrupts may still be disabled by means of the other locking type after this hook has returned.	
Particularities and Limitations	
> The hook is not called for operating system internal interrupt locks	

6.2.13 PanicHook

Prototype
`FUNC(void, OS_PANICHOOK_CODE) Os_PanicHook(void)`
Parameter
none
Return code
none
Functional Description
Called upon kernel panic mode.
Particularities and Limitations
> Trusted access rights > Interrupts are disabled > No OS API service calls are allowed

6.2.14 Barriers

Prototype	

`FUNC(StatusType, OS_CODE) Os_BarrierSynchronize(`
`  Os_BarrierIdType BarrierID`
`)`	

Parameter	
BarrierID	The barrier to which the task shall be synchronized.
Return code	
E_OK	No error
E_OS_ID	Invalid BarrierID (EXTENDED status)
E_OS_CALLEVEL	Called from invalid context (EXTENDED status)
E_OS_SYS_NO_BARRIER_PARTICIPANT	> The given barrier is not configured for the local core (EXTENDED status) > Task is not configured to participate in the barrier (EXTENDED status)
Functional Description	
Synchronize the calling task at the barrier given in "BarrierID". The calling task blocks until all other participating tasks have called this API method with the same "BarrierID".	
Particularities and Limitations	
> none	
Call context	
> Task	

Table 6-158 Barriers

6.2.15 Exception Context Manipulation

6.2.15.1 Os_GetExceptionContext

Prototype	
`FUNC(StatusType, OS_CODE) Os_GetExceptionContext( Os_ExceptionContextRefType Context )`	
Parameter	
Context	Current exception context.
Return code	
E_OK	No error
E_OS_PARAM_POINTER	given pointer is a NULL_PTR (EXTENDED status)
E_OS_CALLEVEL	Called from invalid context (EXTENDED status)
E_OS_SYS_UNIMPLEMENTED_FUNCTIONALITY	Context manipulation is not supported on this hardware (EXTENDED status)
Functional Description	
Getter function for the exception context. Returns the context structure of the thread interrupted by an exception.	
Particularities and Limitations	
> none	
Call context	
> ProtectionHook	

Table 6-159 Os_GetExceptionContext

6.2.15.2 Os_SetExceptionContext

Prototype	

`FUNC(StatusType, OS_CODE) Os_SetExceptionContext(`
`  Os_ExceptionContextRefType Context`
`)`	

Parameter	
Context	Context to set.
Return code	
E_OK	No error
E_OS_PARAM_POINTER	given pointer is a NULL_PTR (EXTENDED status)
E_OS_CALLEVEL	Called from invalid context (EXTENDED status)
E_OS_SYS_UNIMPLEMENTED_FUNCTIONALITY	Context manipulation is not supported on this hardware (EXTENDED status)
Functional Description	
Setter function for the exception context. Writes the given context into the exception context structure.	
Particularities and Limitations	
> none	
Call context	
> ProtectionHook	

Table 6-160 Os_SetExceptionContext

6.2.16 Os_GetCoreStartState

Prototype

```
FUNC(void, OS_CODE) Os_GetCoreStartState(
  CoreIdType CoreID,
  Os_CoreStartStateType *CoreState,
  StatusType *Status
);
```

Parameter

CoreID [in]	The core which shall be queried.
CoreState [out]	Core state.
Status [out]	Status code.

Return code

Status	> E_OK No Error. > E_OS_PARAM_POINTER Given pointer is NULL (EXTENDED status) > E_OS_ID Invalid CoreID (EXTENDED status)
CoreState	> OS_CORESTARTSTATE_START_UNREQUESTED The start of the core has not been requested. > OS_CORESTARTSTATE_START_REQUESTED_ASR The start of the AUTOSAR core has been requested. > OS_CORESTARTSTATE_START_REQUESTED_NONASR The start of the non-AUTOSAR core has been requested. > OS_CORESTARTSTATE_STARTED_ASR The AUTOSAR core has been started. > OS_CORESTARTSTATE_STARTED_NONASR The non-AUTOSAR master core has been started.

Functional Description

This service returns the current start state of a given core.

This service supports AUTOSAR as well as non-AUTOSAR cores.

This API is allowed to be used from AUTOSAR cores.

Particularities and Limitations

> Has to be called on a core which is started as an AUTOSAR core.
> Can be called before StartOs() or StartCore().
> Must be called after Os_Init().

The state OS_CORESTARTSTATE_STARTED_NONASR can only be returned if the queried non-AUTOSAR core has called Os_Init().

For all other non-AUTOSAR cores only the start request can be evaluated.

Call context

> - ANY
> - This function is Synchronous
> - This function is Reentrant

Table 6-161 Os_GetCoreStartState

The following table gives an overview about the valid context for MICROSAR OS additional API service calls.

Calling Context / API Service	Task	Category 1 ISR	Category 2 ISR	Error Hook	PreTask Hook	PostTask Hook	Startup Hook	Shutdown Hook	Alarm Callback	Protection Hook	Before Start of OS	Pre-Start Task	IOC callbacks
Peripheral Access APIs	X		X	X			X	X				X	
Generated IOC APIs	X		X										
Os_EnterPreStartTask											X		
Os_CallNonTrustedFunction	X		X									X	
Os_DisableInterruptSource	X		X										
Os_EnableInterruptSource	X		X										
Os_ClearPendingInterrupt	X		X										
Os_GetDetailedError				X									
Os_GetUnhandledIrq	X		X	X	X	X	X	X	X	X			
Os_GetUnhandledExc	X		X	X	X	X	X	X	X	X			
Stack Usage APIs	X		X	X	X	X	X	X	X	X			
Time Conversion Macros	X		X	X	X	X	X	X	X	X			
Os_Init											X		
CheckISRMemoryAccess	X		X	X						X			
CheckTaskMemoryAccess	X		X	X						X			
CallTrustedFunction	X		X									X	
Os_CallFastTrustedFunction	X		X									X	
Os_BarrierSynchronize	X												
Os_GetExceptionContext										X			
Os_SetExceptionContext										X			

Table 6-162 Calling Context Overview

7 Configuration

MICROSAR OS is configured with Vectors “DaVinci Configurator”.

The descriptions of all OS configuration attributes are described with tool tips within the configuration tool.

They can easily be look up during configuration of the OS component.



Note
The configuration with OIL (OSEK implementation language) is not supported.

8 Glossary

Term	Description
Non-trusted function (NTF)	A non-trusted function is a functional service provided by a non-trusted OS application. It runs in the non-privileged mode of the processor with restricted memory rights.
Application	Any software parts that uses the OS. This may include other software modules or customer software (don't confuse this with the OS-application object).
Pre-start task	An OS task which may run before StartOS has been called. Within the pre-start task the usage of non-trusted functions is allowed.
OS-application	An OS object of type application.
Category 2 Lock Level	The priority of the highest category 2 ISR
Category 1 Lock Level	The priority of the highest category 1 ISR
TP Lock Level	The priority the timing protection interrupt
X-Signal	MICROSAR OS mechanism which realizes cross core service APIs.
Kernel Panic	An inconsistent state of the OS results in kernel panic mode. The OS does not know how to proceed correctly. It goes into freeze as fast as possible (interrupts are disabled, the panic hook is called and afterwards an endless loop is entered).
Thread	Umbrella Term for OS Task, OS hooks and OS ISR objects
Memory Protection Unit (MPU)	A programmable hardware component responsible for monitoring memory accesses made by CPU and/or peripheral devices and triggering an exception upon detection of illegal accesses.

9 Contact

Visit our website for more information on

- News
- Products
- Demo software
- Support
- Training data
- Addresses

www.vector.com