

Signal Processing Algorithms and Proof of Concept Simulation for Bistatic Radar Imaging: Range Azimuth Kinematic Matching

Kalyan K. Parameshwaran¹ and Paul McManamon¹

¹ESA-ESTEC Internship Programme, 2020, European Space Research and Technology Centre (ESTEC), Noordwijk, The Netherlands

Abstract

This paper presents a signal processing chain and kinematic tracking algorithm developed for bistatic radar imaging in a spaceborne transmitter-receiver configuration, together with a proof-of-concept software simulation used to validate the approach prior to hardware trials. The processing chain comprises intermediate-frequency (IF) signal formation, matched-filter range compression, range-azimuth (Bscope) image formation, and a gated constant-velocity kinematic tracker that associates range-azimuth detections with a predicted target track across successive antenna sweeps. Bistatic-specific quantities, namely bistatic angle, bistatic range sum, and the isorange (Cassini/ellipse) locus, are computed directly from the transmit and receive range legs and the time-varying transmitter-receiver baseline. A software demonstrator implementing the full pipeline was built and used to exercise the tracker under nominal constant-velocity motion, injected maneuvers, and intermittent illumination (coasting) conditions. The demonstrator is a simulation of the algorithm chain using synthetically generated IF and detection data, not a recording from physical radar hardware; we present it explicitly as such and discuss what it does and does not demonstrate about the algorithm's field readiness. Under simulated nominal conditions, track confidence converges and gating correctly rejects false associations outside a 2.4 km bistatic gate; under injected maneuvers, track confidence degrades and recovers within several sweep cycles, consistent with the expected behaviour of a constant-velocity kinematic prior. The paper details the algorithm design, the simulation methodology, the results obtained, and the additional steps, principally validation against measured or high-fidelity emulated RF data, required before the algorithm can be considered proof-of-concept in the conventional (hardware-validated) sense.

1 Introduction

Bistatic radar configurations, in which the transmitter and receiver are physically separated, for example on two independent spacecraft, offer several advantages over monostatic systems for wide-area imaging and surveillance: receiver stealth, forward-scatter enhancement of certain target classes, and improved geometric diversity for track disambiguation. These advantages come at the cost of substantially more complex signal processing, because the receiver must jointly resolve range, azimuth, and Doppler information referenced to a time-varying, noncollocated transmit and receive geometry, and must maintain a coherent kinematic estimate of target motion across antenna sweeps that may be sparse, intermittent, or geometrically distorted relative to the monostatic case. This paper documents the signal processing chain and kinematic tracking algorithm developed during an internship at the European Space Research and Technology Centre (ESTEC) focused on bistatic radar imaging concepts for spaceborne platforms. The objective of the work was twofold:

(i) to specify a processing pipeline, from raw intermediate frequency (IF) samples through to a maintained range azimuth track, that is explicit about the bistatic geometry rather than treating it as a monostatic approximation; and (ii) to build a software proof of concept that exercises every stage of that pipeline end to end so that algorithmic behaviour, including gating, coasting, confidence evolution, and response to maneuvers, could be inspected and iterated on before committing to hardware in the loop testing.

We use the term 'proof of concept' in this paper in its software/algorithmic sense: a working implementation of the full processing and tracking chain, driven by synthetically generated IF and detection data with representative noise and geometry, used to demonstrate that the algorithm behaves as designed. It is not a claim of validation against recorded RF hardware measurements, and Section 6 discusses explicitly what remains to be shown before such a claim could be made.

2 Bistatic Geometry and System Model

The system model places the receiver at the origin of a local range azimuth frame, with the boresight range axis along +y. A transmit satellite (Tx) and receive satellite (Rx) are positioned on a common circular baseline arc, parameterised by angles θ_{Tx} and θ_{Rx} measured from the frame origin; the instantaneous transmitter-receiver separation, or baseline length L , follows from these two angles and the arc radius. The target is modelled as a point scatterer with Cartesian position (x, y) and constant velocity kinematic state (v_x, v_y) , consistent with a first order motion prior; an optional maneuver injection rotates the velocity vector at a fixed turn rate to test tracker robustness against a violated motion assumption (Section 5.3).

For a target at range vector r relative to the receiver, the two oneway propagation legs are R_t , the transmitter to target range, and R_r , the target to receiver range. The bistatic range sum $\Sigma R = R_t + R_r$ is the fundamental range observable in a bistatic system: the total propagation path length recovered from the two way time delay after mixing the received echo with a reference of the direct path signal. The bistatic angle β , defined at the target between the transmitter and receiver look directions, follows from the law of cosines applied to the triangle formed by Tx, Rx, and the target:

$$\beta = \arccos((R_t^2 + R_r^2 - L^2) / (2 R_t R_r)) \quad (1)$$

This relation is evaluated every processing cycle from the current R_t , R_r , and L , and is reported alongside range, azimuth, and radial velocity as part of the kinematic telemetry (Table 1).

A locus of constant bistatic range sum ΣR , for fixed transmitter and receiver positions, forms an ellipse with foci at Tx and Rx: the isobistatic range ellipse. This locus is the bistatic analogue of the monostatic constant range circle and is used both as a visualisation aid and, more importantly, as a geometric consistency check: a detection whose (R_t, R_r) pair does not place it near the ellipse consistent with the current track prediction is a candidate for gate rejection (Section 4.2).

3 Signal Chain: From IF Samples to Range Profile

The processing chain begins with an intermediate frequency (IF) time domain buffer produced after downconversion and mixing of the received echo against a local reference derived from the direct path transmit signal (or, in a fully bistatic architecture, a synchronised reference chain at the receiver). In the absence of a target illuminated by the current antenna look direction, this buffer is dominated by a stationary noise floor; when the sweeping receive beam intersects the target azimuth, a coherent return is superimposed at a delay corresponding to the current bistatic range sum.

Range compression is performed by a matched filter matched to the transmitted waveform, producing a range profile, that is, energy as a function of one-way equivalent range, over a fixed number of range bins spanning the system's unambiguous range window. The profile is maintained as a rolling buffer so that a target return persists visually and algorithmically across the few processing cycles needed for peak detection and centroiding, after which a range estimate and an estimated signal-to-noise ratio (SNR) are extracted from the profile peak.

The range-azimuth image (Bscope) is formed by associating each range-compressed profile with the antenna azimuth at the time of acquisition, and accumulating successive profiles into a persistent two-dimensional buffer as the antenna sweeps between its azimuth limits. This is the standard way a scanning radar builds a two-dimensional image from a sequence of one-dimensional range returns, and it is the domain in which the kinematic tracker (Section 4) operates.

3.1 Detection and SNR Model

In the demonstrator, detections are generated with an SNR drawn from an elevated range (representative of a correctly illuminated, matched-filter-compressed return) when the target lies within the current antenna beam, and from a markedly lower range (representative of noise floor sidelobes and clutter) otherwise. This is a deliberately simple two-state SNR model, adequate for exercising the gating and confidence logic described next, but it is not a substitute for a physically derived radar

range equation, propagation loss model, or clutter model; a limitation returned to in Section 6.

4 Kinematic Tracking and RangeAzimuth Matching

The tracker maintains an independent kinematic state, position and velocity, that is propagated forward each cycle under a constantvelocity assumption, and is only updated when a rangeazimuth detection is judged, by the gating test below, to be consistent with the current prediction. This separation of a maintained track from raw detections is what allows the system to coast through periods of intermittent illumination (Section 4.3) rather than losing the target the moment a single sweep fails to produce a qualifying return.

4.1 ConstantVelocity Prediction

Between detections, the track position is propagated as

$$x(t + \Delta t) = x(t) + v_x \Delta t, \quad y(t + \Delta t) = y(t) + v_y \Delta t, \quad (2)$$

with the velocity components held fixed. This firstorder model is appropriate for the sweeptosweep intervals involved and is the same order of model used in the target truth simulation for

nominal (nonmaneuvering) motion, which is why gating against it is effective during straightline motion and is expected to degrade transiently during a maneuver (Section 5.3).

4.2 Association Gating

A new detection is associated with the existing track if the Euclidean distance between the detection's estimated (x, y) position and the track's predicted position falls within a fixed gate threshold

(2.4 km in the demonstrator configuration). Detections outside the gate are treated as clutter or as belonging to a different object and are not used to update the track; this is a nearestneighbour, fixedgate simplification of the more general validationgate association used in multitarget tracking (e.g. Mahalanobisdistance gating under an explicit error covariance), adopted here for clarity of the proofofconcept rather than as a claim of optimality.

4.3 Track Confidence and Coasting

A scalar confidence metric is maintained alongside the kinematic state, increasing toward an upper bound on successive successful gate associations and decaying when the track is coasting (propagating without a fresh association). Three qualitative states are reported: Matched, when the elapsed time since the last successful association (coast time) is below a short threshold; Coasting, for an intermediate coast time during which the constantvelocity prediction is still considered reliable; and Acquiring, once coast time exceeds a longer threshold, indicating the track should be treated

as unreliable pending reacquisition. This mirrors the qualitative trackquality states used operationally in scanning trackers to decide when to widen a search gate or hand off to reacquisition logic.

4.4 Calibration State

A separate calibration flag distinguishes an initial period, during which the bistatic geometry and IF reference chain are being aligned, from a subsequent locked state in which range and azimuth estimates are considered geometrically consistent. Kinematic telemetry (Table 1) is only considered meaningful once this calibration state has locked.

5 Proof of Concept Simulation

The algorithm chain described in Sections 3 and 4 was implemented in full as an interactive software demonstrator, driving a simulated bistatic scenario with a moving target, a sweeping receive beam, and a repositionable Tx/Rx baseline. The purpose of the demonstrator is to exercise every processing and tracking stage together, including IF generation, range compression, Bscope accumulation, gating, coasting, and bistatic geometry computation, under controllable, repeatable conditions, and to visualise the resulting behaviour directly rather than only inspecting summary statistics.

5.1 Demonstrator Configuration

Both the baseline geometry and the target's initial kinematic state are operatorconfigurable; the target can also be given an impulsive maneuver (a rotation of its velocity vector at a fixed turn rate) at an arbitrary time to test the tracker's response to a violated constantvelocity assumption, and the entire scenario can be reset to a known initial condition for repeatable trials.

5.2 Nominal (ConstantVelocity) Behaviour

Under nominal straightline target motion, the demonstrator was run through repeated sweep cycles from a cold start (uncalibrated, zero confidence). The calibration flag transitions from Calibrating to Locked within the first few sweeps, after which range, azimuth, bistatic angle, and bistatic range sum telemetry become stable and consistent with the underlying target truth state. Track confidence rises monotonically toward its upper bound as successive detections fall inside the 2.4 km gate, and

Table 1: Demonstrator configuration parameters. Baseline and range values are scaled for interactive demonstration and algorithm exercising, not representative of a specific mission range budget.

Parameter	Symbol	Value (demonstrator)
Azimuth sweep extent	AZ_MIN, AZ_MAX	-60° to $+60^\circ$

Parameter	Symbol	Value (demonstrator)
Sweep rate	n/a	34°/s
Unambiguous range window	RANGE_MAX	22 km
Transmitter to receiver baseline	L	8 km (variable, operator adjustable)
Association gate threshold	n/a	2.4 km
IF buffer length	n/a	220 samples
Range profile bins	n/a	90 bins
Illuminated target SNR (simulated)	n/a	14 to 22 dB
Non illuminated SNR (simulated)	n/a	2 to 7 dB

Table 1: Demonstrator configuration parameters. Baseline and range values are scaled for interactive

demonstration and algorithm exercising, not representative of a specific mission range budget.

the qualitative track state reports Matched for the great majority of sweep cycles, consistent with the target remaining within the antenna's illuminated azimuth range for an extended interval.

5.3 Response to an Injected Maneuver

When a maneuver is injected midrun, the target's velocity vector rotates over a short interval while the tracker continues to predict forward under its unchanged, premaneuver constantvelocity estimate. This produces a transient growth in the miss distance between predicted and detected position, observable directly as a widening gap between the coasting (predicted) track marker and the newly detected returns on the Bscope. In the demonstrator's gating logic, this is reflected as a drop in track confidence and, if the miss distance exceeds the 2.4 km gate for consecutive cycles, a transition of the track state from Matched to Coasting or Acquiring. Once the target returns to straightline motion postmaneuver, subsequent detections reenter the gate and confidence recovers over several sweep cycles as the constantvelocity prediction reconverges on the new heading. This behaviour is the expected qualitative signature of a fixedgate, constantvelocity tracker under a kinematicmodel mismatch, and its reproduction in the demonstrator is treated as a successful proofofconcept of the tracking logic rather than as evidence of a specific quantitative maneuverhandling capability.

5.4 Sensitivity to Baseline Geometry

Because the Tx and Rx positions are operatoradjustable along the baseline arc, the demonstrator also allows direct inspection of how the bistatic angle β and the isorange ellipse eccentricity change as the baseline is widened or narrowed relative to the Tx_{target} and Rx_{target} ranges. As expected

from the geometric relation in Section 2, β grows as the baseline is widened relative to the target ranges, and the isorange ellipse becomes visibly more eccentric; this qualitative behaviour matches the closedform geometric relation used to compute β and provides an internal consistency check on the implementation, independent of any radarspecific measurement.

6 Discussion and Limitations

The work reported here validates the algorithmic design and its software implementation: the gating logic rejects outofgate detections, the confidence metric and qualitative track state behave as intended under nominal and maneuvering conditions, and the bistatic geometry computations are internally consistent under a range of operatoradjusted baselines. These are meaningful and necessary results before any hardware trial is attempted, but they are results about the algorithm's logic, not about its performance against real or highfidelity emulated radar returns, and the paper's claims should be read with that scope in mind.

Three limitations are worth stating explicitly. First, the SNR and detection model used to drive the demonstrator is a simplified twostate model (Section 3.1) rather than a physically derived link budget incorporating antenna gain patterns, propagation loss, target radar crosssection, and clutter statistics; a more representative syntheticdata or hardwareintheloop trial would be needed before drawing conclusions about detection performance at a specific range or SNR. Second, the association gate is a fixedradius nearestneighbour test rather than a covarianceaware (e.g. Mahalanobis) gate, and does not currently address multitarget association or falsetrack initiation under dense clutter. Third, the demonstrator uses idealised, noise-free antenna pointing and a simplified circulararc baseline model; a spaceborne implementation would need to account for orbit determination error, antenna pointing error, and time synchronisation error between the transmit and receive platforms, all of which directly degrade the bistatic range and angle estimates derived in Section 2.

Addressing these limitations, in particular replacing the synthetic twostate SNR model with either recorded RF data or a physically grounded linkbudget simulation, and validating the gating and tracking logic against that more representative data, is the natural next step toward a proofofconcept in the hardwarevalidated sense, and is proposed as future work.

7 Conclusion

We have presented a signal processing and kinematic tracking algorithm for bistatic radar imaging, explicit about the transmitterreceiver geometry throughout, from IF signal formation and range compression through to a gated constantvelocity tracker that computes bistatic angle and bistatic range sum each cycle. A software proof of concept implementing the complete chain was built and exercised under nominal motion, injected maneuvers, and varying baseline geometry, and reproduced the qualitative behaviour expected of the design in each case: stable convergence under nominal motion, graceful confidence degradation and recovery under a kinematic model mismatch, and geometrically consistent bistatic angle and isorange computations under a range of baseline configurations. This establishes the algorithmic and software foundation for the next phase of the work, which is validation against representative or recorded RF data ahead of any hardware demonstration.

Acknowledgements

This work was carried out as part of an internship at the European Space Research and Technology Centre (ESTEC), European Space Agency, in 2020. K.K. Parameshwaran thanks ESTEC colleagues who provided guidance on bistatic radar system concepts during the internship period.

References

- [1] N. J. Willis, Bistatic Radar, 2nd ed., SciTech Publishing, 2005.
- [2] M. Cherniakov (ed.), Bistatic Radar: Emerging Technology, Wiley, 2008.
- [3] S. Blackman and R. Popoli, Design and Analysis of Modern Tracking Systems, Artech House, 1999.
- [4] Y. BarShalom, X. R. Li, and T. Kirubarajan, Estimation with Applications to Tracking and Navigation, Wiley, 2001.
- [5] M. I. Skolnik, Introduction to Radar Systems, 3rd ed., McGrawHill, 2001.
- [6] European Space Agency, ESTEC internship programme documentation, 2020.

Appendix A: Processing Cycle Pseudocode

The following summarises the percycle processing order implemented in the demonstrator, corresponding to Sections 3 and 4. It is presented to make explicit the order of operations linking signal formation to the kinematic tracker, not as production quality code.

1. Advance simulation time by Δt ; propagate target truth state under constant velocity (plus

- any active maneuver rotation).
2. Advance antenna sweep azimuth; determine whether the target's current true azimuth falls within the illuminated beam.
 3. Generate the IF sample buffer for the current cycle: noise floor everywhere, plus a coherent return at the delay corresponding to the current bistatic range sum ΣR if illuminated.
 4. Apply the matched filter to the IF buffer to form the current range profile; update the persistent range profile buffer.
 5. Extract the profile peak (range, amplitude); estimate SNR; if amplitude exceeds the detection threshold, form a candidate detection at (current azimuth, peak range).
 6. Propagate the track's predicted position under its own constant velocity state.
 7. If a candidate detection exists, compute its Euclidean distance to the predicted track position; if within the 2.4 km gate, accept the association: update track position and velocity from the detection, reset coast time, increment confidence.
 8. If no detection is associated this cycle, increment coast time and decay confidence; recompute the qualitative track state (Matched / Coasting / Acquiring) from the updated coast time.
 9. Recompute R_t , R_r , β , and ΣR from the current Tx/Rx/target geometry; update the Bscope, telemetry readouts, and isorange ellipse for display.
- This ordering, truth propagation, IF formation, range compression, detection extraction, gated association, and geometry recomputation, is repeated every processing cycle for the duration of a run, and is the same ordering used to produce the results in Section 5.

Appendix B: Symbol Summary

Table 2: Symbols and quantities used in Sections 25.

Table 2: Symbols and quantities used in Sections 2-5.

Parameter	Symbol	Value (demonstrator)
Transmitter to target range	R_t	computed each cycle from geometry
Target to receiver range	R_r	computed each cycle from geometry
Bistatic range sum	$\Sigma R = R_t + R_r$	primary bistatic range observable
Bistatic angle	β	law of cosines from R_t , R_r , L
Transmitter receiver baseline	L	operator adjustable arc separation
Association gate radius	n/a	2.4 km, fixed nearest neighbour test
Track coast time	n/a	time since last successful association
Track confidence	n/a	bounded scalar, rises on match, decays on coast