

# Device: ARRI Amira



## Introduction

At the current moment two Device Cores are utilised in order to communicate with the ARRI Amira camera. The ARRI Amira CAP and the ARRI Amira SSCP Device Core.



**ARRI Amira CAP**

ARRI Amira CAP (Camera Access Protocol) control via TCP/IP. Allows remote control of parameters in your ARRI Amira camera.



**ARRI Amira**

ARRI Amira camera control via TCP/IP. Allows remote control of video parameters in your ARRI Amira camera via SSCP (Sony Simple Camera Protocol). The camera acts as a TCP client connecting to the SKAARHOJ controller acting as a TCP server.



UniSketch OS v. 2.2.1.2.4 is required for the ARRI Amira CAP Device to work.

Two Device Cores IPs are set on the controller.

These must match the IP of the camera it self.

Multicam must be enabled on the camera, and the SSCP device IP must match the IP settings of the controller!

CAP server must be enabled and CAP server password must be set to "skaarri"

When connected via CAP the SKAARHOJ controller will appear in the CAP Client List as "SkaarhojRCP"

# SKAARHOJ DEVICE CORES

Examples are given below

**Controller IP Settings**

**IP:**  
192 . 168 . 10 . 27

**Subnet Mask:**  
255 . 255 . 255 . 0

**Gateway:**  
192 . 168 . 10 . 1

**DNS:**  
192 . 168 . 10 . 1

**ARRI Amira CAP**

192 . 168 . 10 . 246

**ARRI Amira**

192 . 168 . 10 . 246

**HOME** **NETWORK / WIFI**

MENU

BACK

WiFi mode Client  
WiFi host password →  
WiFi network Not connected →  
Wireless region setting Europe →  
LAN IP mode Static  
**LAN static IP 192.168.010.246**  
LAN static subnet 255.255.255.000

**HOME** **CAMERA ACCESS PROTOCOL (CAP)**

MENU

BACK

**CAP server enabled**

CAP server password →  
CAP client list →

# SKAARHOJ DEVICE CORES

