

## A.4.1E SMS/CBS 7-bit Lao Alphabet (0x1E)

### A.4.1E.1 SMS/CBS 7-bit Lao Alphabet (0x1E) base table

|           |           |           |           |   | <b>b7</b> | 0          | 0           | 0          | 0          | 1          | 1          | 1         | 1          |
|-----------|-----------|-----------|-----------|---|-----------|------------|-------------|------------|------------|------------|------------|-----------|------------|
|           |           |           |           |   | <b>b6</b> | 0          | 0           | 1          | 1          | 0          | 0          | 1         | 1          |
|           |           |           |           |   | <b>b5</b> | 0          | 1           | 0          | 1          | 0          | 1          | 0         | 1          |
| <b>b4</b> | <b>b3</b> | <b>b2</b> | <b>b1</b> |   |           | 0          | 1           | 2          | 3          | 4          | 5          | 6         | 7          |
| 0         | 0         | 0         | 0         | 0 |           |            | ☐<br>0E8C   | SP<br>0020 | 0<br>0030  | ຸ<br>0EA1  | ຸ<br>0EB2  |           | p<br>0070  |
| 0         | 0         | 0         | 1         | 1 |           | ◌̣<br>0ECD | ◌̣<br>005F  | ຸ<br>0E9A  | 1<br>0031  | ຸ<br>0EA2  | ◌̣<br>0EB4 | a<br>0061 | q<br>0071  |
| 0         | 0         | 1         | 0         | 2 |           |            | ຸ<br>0E8D   | ຸ<br>0E9B  | 2<br>0032  | ຸ<br>0EBD  | ◌̣<br>0EB5 | b<br>0062 | r<br>0072  |
| 0         | 0         | 1         | 1         | 3 |           | ກ<br>0E81  | ☐<br>0E8E   | #<br>0023  | 3<br>0033  | ◌̣<br>0EBC | ◌̣<br>0EB8 | c<br>0063 | s<br>0073  |
| 0         | 1         | 0         | 0         | 4 |           | ຂ<br>0E82  | ☐<br>0E8F   | ຸ<br>0E9C  | 4<br>0034  | ຸ<br>0EA3  | ◌̣<br>0EB9 | d<br>0064 | t<br>0074  |
| 0         | 1         | 0         | 1         | 5 |           |            | ☐<br>0E90   | ຸ<br>0E9D  | 5<br>0035  | ວ<br>0EA5  | ◌̣<br>0EB6 | e<br>0065 | u<br>0075  |
| 0         | 1         | 1         | 0         | 6 |           | ຄ<br>0E84  | ☐<br>0E91   | ຸ<br>0E9E  | 6<br>0036  | ວ<br>0EA7  | ◌̣<br>0EB7 | f<br>0066 | v<br>0076  |
| 0         | 1         | 1         | 1         | 7 |           |            | ☐<br>0E92   | ຸ<br>0E9F  | 7<br>0037  | ຸ<br>0EAA  |            | g<br>0067 | w<br>0077  |
| 1         | 0         | 0         | 0         | 8 |           | ☐<br>0E86  | ☐<br>0E93   | ☐<br>0EA0  | 8<br>0038  | ☐<br>0EA9  | ◌̣<br>0EC0 | h<br>0068 | x<br>0078  |
| 1         | 0         | 0         | 1         | 9 |           | ງ<br>0E87  | ດ<br>0E94   | ກ<br>0EDE  | 9<br>0039  | ☐<br>0EA8  | ◌̣<br>0EC1 | i<br>0069 | y<br>0079  |
| 1         | 0         | 1         | 0         | A |           | LF<br>000A | ຕ<br>0E95   | *<br>002A  | :<br>003A  | ຫ<br>0EAB  | ຸ<br>0EC3  | j<br>006A | z<br>007A  |
| 1         | 0         | 1         | 1         | B |           | ຈ<br>0E88  | SS2<br>---- | ⁂<br>002B  | ⁂<br>003B  | ☐<br>0EAC  | ຸ<br>0EC4  | k<br>006B | ◌̣<br>0EC8 |
| 1         | 1         | 0         | 0         | C |           | ☐<br>0E89  | ຸ<br>0E96   | ,<br>002C  |            | ອ<br>0EAD  | ◌̣<br>0EBB | l<br>006C | ◌̣<br>0EC9 |
| 1         | 1         | 0         | 1         | D |           | CR<br>000D | ທ<br>0E97   | ຸ<br>0EDF  | ະ<br>0EB0  | ຸ<br>0EAE  | ຸ<br>0EC2  | m<br>006D | ◌̣<br>0ECA |
| 1         | 1         | 1         | 0         | E |           | ຸ<br>0E8A  | ☐<br>0E98   | .<br>002E  | ◌̣<br>0EB1 |            |            | n<br>006E | ◌̣<br>0ECB |
| 1         | 1         | 1         | 1         | F |           |            | ຸ<br>0E99   | /<br>002F  | ?<br>003F  | ☐<br>0EBA  | ☐<br>0ECE  | o<br>006F | ງ<br>0EC6  |

In the event that an MS receives a code where a symbol is not represented in the above table then the MS shall display the REPLACEMENT CHARACTER (U+FFFD). The Lao alphabet has two (interrelated) coding exceptions: 1) Some vowel characters have a "logical order exception"; 2) Some vowels that are written with several vowel characters do not have a combined character encoded.

SP: In Lao, spaces are not used between words, only between phrases.

LF: LINE FEED; moves to the next line (with implied carriage return).

CR: CARRIAGE RETURN; CR is not used as CR but is used as a filler after the actual SMS/CBS message text. CR should not occur inside a message text, but if it does, it must be converted to LF. Note though that <SS2,CR> is actually CSI (see next table), and that "CR" is not a filler, nor LF.

SS2: SINGLE SHIFT TWO; This code shifts the next 7-bit code unit to refer to an extension of this table (subclause A.4.1E.1).

When splitting a message text into submessages, there must be no cut right after an SS2.

#### A.4.1E.2 SMS/CBS 7-bit Lao Alphabet (0x1E) extension (SS2) table

|           |           |           |           |           |             |             |                      |           |           |           |           |           |   |
|-----------|-----------|-----------|-----------|-----------|-------------|-------------|----------------------|-----------|-----------|-----------|-----------|-----------|---|
|           |           |           |           |           | <b>b7</b>   | 0           | 0                    | 0         | 0         | 1         | 1         | 1         | 1 |
|           |           |           |           |           | <b>b6</b>   | 0           | 0                    | 1         | 1         | 0         | 0         | 1         | 1 |
|           |           |           |           |           | <b>b5</b>   | 0           | 1                    | 0         | 1         | 0         | 1         | 0         | 1 |
| <b>b4</b> | <b>b3</b> | <b>b2</b> | <b>b1</b> | <b>1B</b> | <b>0</b>    | <b>1</b>    | <b>2</b>             | <b>3</b>  | <b>4</b>  | <b>5</b>  | <b>6</b>  | <b>7</b>  |   |
| 0         | 0         | 0         | 0         | 0         | @<br>0040   | <<br>003C   | ໔<br>0ED4            | ໐<br>0EB3 | <br>007C  | P<br>0050 | ¼<br>00BC | Δ<br>26A0 |   |
| 0         | 0         | 0         | 1         | 1         | £<br>00A3   | =<br>003D   | ໕<br>0ED5            |           | A<br>0041 | Q<br>0051 | ½<br>00BD | ∞<br>221E |   |
| 0         | 0         | 1         | 0         | 2         | \$<br>0024  | ><br>003E   | ໖<br>0ED6            |           | B<br>0042 | R<br>0052 | ¾<br>00BE | ²<br>00B2 |   |
| 0         | 0         | 1         | 1         | 3         | ¥<br>00A5   | ₹<br>20B9   | ໗<br>0ED7            | ໙<br>0EDC | C<br>0043 | S<br>0053 | “<br>201C | ³<br>00B3 |   |
| 0         | 1         | 0         | 0         | 4         | §<br>00A7   | ^<br>005E   | ໘<br>0ED8            | ໙<br>0EDD | D<br>0044 | T<br>0054 | ”<br>201D |           |   |
| 0         | 1         | 0         | 1         | 5         | "<br>0022   | ฿<br>0E3F   | ລ<br>0ED9            |           | E<br>0045 | U<br>0055 | ¤<br>00A4 |           |   |
| 0         | 1         | 1         | 0         | 6         | €<br>20AC   | ₭<br>20AD   | ໐<br>0E4F            |           | F<br>0046 | V<br>0056 | Ω<br>03A9 |           |   |
| 0         | 1         | 1         | 1         | 7         | %<br>0025   | (<br>0028   | ໑<br>0E5B            |           | G<br>0047 | W<br>0057 | μ<br>03BC |           |   |
| 1         | 0         | 0         | 0         | 8         | &<br>0026   | )<br>0029   | {<br>007B            |           | H<br>0048 | X<br>0058 | °<br>00B0 |           |   |
| 1         | 0         | 0         | 1         | 9         | '<br>0027   | ໑<br>0EAF   | }<br>007D            |           | I<br>0049 | Y<br>0059 | ×<br>00D7 |           |   |
| 1         | 0         | 1         | 0         | A         | FF<br>000C  | ໑<br>0E5A   | ໑໔<br>0ED1,2044,0ED4 | ≈<br>2248 | J<br>004A | Z<br>005A | ÷<br>00F7 |           |   |
| 1         | 0         | 1         | 1         | B         | -<br>2212   | SS3<br>---- | ໑໒<br>0ED1,2044,0ED2 | ≠<br>2260 | K<br>004B | ໑<br>0ECC | ±<br>00B1 |           |   |
| 1         | 1         | 0         | 0         | C         | !<br>0021   | ໐<br>0ED0   | ໑໔<br>0E53,2044,0ED4 | [<br>005B | L<br>004C |           | ‰<br>2030 |           |   |
| 1         | 1         | 0         | 1         | D         | CSI<br>009B | ໑<br>0ED1   | ≤<br>2A7D            | ~<br>007E | M<br>004D |           | «<br>00AB |           |   |
| 1         | 1         | 1         | 0         | E         | -<br>002D   | ໒<br>0ED2   | ≥<br>2A7E            | ]<br>005D | N<br>004E |           | »<br>00BB |           |   |
| 1         | 1         | 1         | 1         | F         |             | ໓<br>0ED3   | \<br>005C            | ·<br>00B7 | O<br>004F |           | '<br>2019 |           |   |

In the event that an MS receives a code where a symbol is not represented in the above table then the MS shall display the REPLACEMENT CHARACTER (U+FFFD).

FF: FORM FEED; This code is defined as a Page Break character (with implied carriage return). Any mobile station which does not have pagination shall treat it as a LF (with implied carriage return).

CSI: CONTROL SEQUENCE INTRODUCER; enables decimal character references, enables styling. An MS which does not support CSI shall convert it to REPLACEMENT CHARACTER.

SS3: SINGLE SHIFT THREE; This code is reserved for the extension to another extension table. When splitting a message text into submessages, there must be no cut right after an SS3.

U+2044 FRACTION SLASH; the sequence may need to be isolated from adjacent digits by ZWNJ.