A.4.12 SMS/CBS 7-bit Hebrew Alphabet (0x12)

A.4.12.1 SMS/CBS 7-bit Hebrew Alphabet (0x12) base table

				b7	0	0	0	0	1	1	1	1
				b6	0	0	1	1	0	0	1	1
				b5	0	1	0	1	0	1	0	1
b4	b3	b2	b1		0	1	2	3	4	5	6	7
0	0	0	0	0	@ 0040	– 2212	**SP** 0020	0 0030	׳ FB1D	׿ 05DF	״ FB1F	p 0070
0	0	0	1	1	£ 00A3	_ 005F	! 0021	1 0031	א 05D0	נ 05E0	a 0061	q 0071
0	0	1	0	2	$ 0024	֤ 05B4	" 0022	2 0032	ב 05D1	o 05E1	b 0062	r 0072
0	0	1	1	3	¥ 00A5	֨ 05B8	# 0023	3 0033	ג 05D2	ע 05E2	c 0063	s 0073
0	1	0	0	4	§ 00A7	֣ 05B3	€ 20AC	4 0034	ד 05D3	ע FB20	d 0064	t 0074
0	1	0	1	5	₪ 20AA	֧ 05C7	% 0025	5 0035	ה 05D4	ף 05E3	e 0065	u 0075
0	1	1	0	6	ֻ 05BB	ֹ 05B9	& 0026	6 0036	ו 05D5	פ 05E4	f 0066	v 0076
0	1	1	1	7	ְ 05B0	ֺ 05BA	' 0027	7 0037	ז 05D6	ץ 05E5	g 0067	w 0077
1	0	0	0	8	׈ 05C8	ֽ 05BD	(0028	8 0038	ח 05D7	צ 05E6	h 0068	x 0078
1	0	0	1	9	ֵ 05B5	ּ 05BC	) 0029	9 0039	ט 05D8	ק 05E7	i 0069	y 0079
1	0	1	0	A	**LF** 000A	׉ 05C9	* 002A	: 003A	י 05D9	ר 05E8	j 006A	z 007A
1	0	1	1	B	ֶ 05B6	**SS2** ----	+ 002B	; 003B	ך 05DA	ש 05E9	k 006B	‚ 2E32
1	1	0	0	C	ִ 05B1	׌ 05C1	, 002C	< 003C	כ 05DB	ת 05EA	l 006C	⁝ 2E35
1	1	0	1	D	**CR** 000D	׍ 05C2	- 002D	= 003D	ל 05DC	װ 05F0	m 006D	⸴ 2E41
1	1	1	0	E	֫ 05B7	׳ 05F3	. 002E	> 003E	ם 05DD	ױ 05F1	n 006E	⁏ 204F
1	1	1	1	F	ֲ 05B2	״ 05F4	/ 002F	? 003F	מ 05DE	ײ 05F2	o 006F	⸮ 2E2E

In the event that an MS receives a code where a symbol is not represented in the above table then the MS shall display the REPLACEMENT CHARACTER (U+FFFD). Hebrew letters are displayed right-to-left.
Simplified Unicode bidi algorithm for SMS/CBS: Bidi AL must be handled as bidi R; all bidi EN and AN handled as L; all ET, ES, CS handled as ON, and 'paragraph direction' is always LTR, there are no bidi controls that span a text range. Bidi mirroring done *only* by using the data in BidiMirroring.txt.

LF: LINE FEED; moves to the next line (with implied carriage return).

CR: CARRIAGE RETURN; CR is not used as CR but is used as a filler after the actual SMS/CBS message text. CR should not occur inside a message text, but if it does, it must be converted to LF. Note though that <SS2,CR> is actually CSI (se next table), and that “CR” is not a filler, nor LF.

SS2: SINGLE SHIFT TWO; This code shifts the next 7-bit code unit to refer to an extension of this table (subclause A.4.12.2).
When splitting a message text into submessages, there must be no cut right after an SS2.

Bidi: There are no bidi control codes for SMS/CBS. The bidi algorithm is modified for readability without the need for bidi controls and security (the bidi controls are a security issue).

A.4.12.2 SMS/CBS 7-bit Hebrew Alphabet (0x12) extension (SS2) table

				b7	*0*	*0*	*0*	*0*	*1*	*1*	*1*	*1*
				b6	*0*	*0*	*1*	*1*	*0*	*0*	*1*	*1*
				b5	*0*	*1*	*0*	*1*	*0*	*1*	*0*	*1*
b4	***b3***	***b2***	***b1***	**1B**	**0**	**1**	**2**	**3**	**4**	**5**	**6**	**7**
0	*0*	*0*	*0*	**0**	א FB21	שׁ FB2A	׀ FB39	פ FB44	| 007C	P 0050	¼ 00BC	⚠ 26A0
0	*0*	*0*	*1*	**1**	ד FB22	שׂ FB2B	ך FB3A	צ FB46	A 0041	Q 0051	½ 00BD	∞ 221E
0	*0*	*1*	*0*	**2**	ה FB23	שּׁ FB2C	כ FB3B	ק FB47	B 0042	R 0052	¾ 00BE	² 00B2
0	*0*	*1*	*1*	**3**	כ FB24	שּׂ FB2D	ל FB3C	ר FB48	C 0043	S 0053	“ 201C	³ 00B3
0	*1*	*0*	*0*	**4**	ל FB25	^ 005E	מ FB3E	ש FB49	D 0044	T 0054	” 201D	
0	*1*	*0*	*1*	**5**	ם FB26	אַ FB2E	נ FB40	ת FB4A	E 0045	U 0055	¤ 00A4	
0	*1*	*1*	*0*	**6**	ר FB27	אָ FB2F	ס FB41	וֹ FB4B	F 0046	V 0056	Ω 03A9	
0	*1*	*1*	*1*	**7**	ת FB28	א FB30	ף FB43	בֿ FB4C	G 0047	W 0057	µ 03BC	
1	*0*	*0*	*0*	**8**	אּ FB4F	בּ FB31	{ 007B	כֿ FB4D	H 0048	X 0058	° 00B0	
1	*0*	*0*	*1*	**9**	ׄ 05EF	גּ FB32	} 007D	פֿ FB4E	I 0049	Y 0059	× 00D7	
1	*0*	*1*	*0*	**A**	**FF** 000C	דּ FB33		≈ 2248	J 004A	Z 005A	÷ 00F7	
1	*0*	*1*	*1*	**B**	: 05C3	**SS3** ----		≠ 2260	K 004B	֯ 05BF	± 00B1	
1	*1*	*0*	*0*	**C**	׀ 05C0	הּ FB34		[005B	L 004C	֮ FB1E	‰ 2030	
1	*1*	*0*	*1*	**D**	**CSI** 009B	וּ FB35	⩽ 2A7D	~ 007E	M 004D		« 00AB	
1	*1*	*1*	*0*	**E**	ׅ 05C6	זּ FB36	⩾ 2A7E	] 005D	N 004E	־ 05BE	» 00BB	
1	*1*	*1*	*1*	**F**	׭ FB29	טּ FB38	\ 005C	· 00B7	O 004F		’ 2019	

In the event that an MS receives a code where a symbol is not represented in the above table then the MS shall display the REPLACEMENT CHARACTER (U+FFFD). The precomposed letter with vowel are included here not just for Yiddish, but because the Unicode normalisation NFC will create them from the decomposed form.

FF: FORM FEED; This code is defined as a Page Break character (with implied carriage return). Any mobile station which does not have pagination shall treat is as a LF (with implied carriage return).

CSI: CONTROL SEQUENCE INTRODUCER; enables decimal character references, enables styling. An MS which does not support CSI shall convert it to REPLACEMENT CHARACTER.

SS3: SINGLE SHIFT THREE; This code is reserved for the extension to another extension table. When splitting a message text into submessages, there must be no cut right after an SS3.