Measurement Description

- 3 terminal transistor: Gate, Drain, Source
- For measurements, please assume the following:
  - Gate connected to PMU1-channel1
  - Drain connected to PMU1-channel2
  - Source connected to PMU2-channel1
- Measure-Stress-Measure sequence repeated for given list of cumulative stress times

Measure

- Bidirectional staircase ramp for Gate, Drain at vdrain V and Source at zero
- Parametrized by trf=2e-7, tplateu=1e-5, vdrain=0.1, vgate_start=0, vgate_stop=2, vgate_step=0.1
- Spot-mean measurement only at plateus

SegArb Segments and Sequences - Ch1 Segment ARB Definition

	StartVCh1 (V)	StopVCh1 (V)	SegTime (s)	MeasEnabled (0/1)	SSRCtrlCh1 (0/1)	SegTrigOut (0/1)	SegMeasType
1	0	0	1E-05	1	1	1	2
2	0	0.1	2E-07	0	1	0	2
3	0.1	0.1	1E-05	1	1	1	2
4	0.1	0.2	2E-07	0	1	0	2
5	0.2	0.2	1E-05	1	1	1	2
6	0.2	0.3	2E-07	0	1	0	2
7	0.3	0.3	1E-05	1	1	1	2
8	0.3	0.4	2E-07	0	1	0	2
9	0.4	0.4	1E-05	1	1	1	2

Seq1 Seq2 Seq3 Seq4

Waveform Sequence List

	SeqListCh1	SeqLoopsCh1
1	1	1
2	2	1
3	1	1
4	2	4
5	1	1
6	2	5
7	1	1
8	3	4
9	1	1
10	3	5

Add Seq Remove Seq Load Simple Pulse



Stress

- Mode: ‘DC’ → constant voltage vstress V at Gate, Drain and Source at 0 V
- Mode: ‘AC’ → square pulses parametrized by trf, thigh, duty-cycle, vstdby, vstress (same as above) → no of cycles calculated from the stress time, thigh and duty-cycle