

Date of publication xxxx 00, 0000, date of current version xxxx 00, 0000.

Digital Object Identifier 10.1109/ACCESS.2026.XXXXXXX

KAN-inspired Universal Relaxation Network for Automatic Discovery of Physical Relaxation Mechanisms with Direct Circuit Synthesis

KENTA SUGAHARA¹,0000-0002-2200-311X and YUKI SATO²,0000-0002-4052-5966

¹Faculty of Science and Engineering, Kindai University, Higashi-Osaka 577-8502, Japan

²Department of Electrical and Electronic Engineering, Aoyama Gakuin University, Sagami-hara 252-5258, Japan

Corresponding author: Kenta Sugahara (e-mail: sugahara@kindai.ac.jp).

This work was supported in part by JSPS KAKENHI.

ABSTRACT We propose the Universal Relaxation Network (URN), a KAN-inspired approach for automatic discovery of physical relaxation mechanisms from frequency-domain impedance data. Unlike Vector Fitting (VF), which uses pole-residue representations that can produce unstable models, URN employs 29 circuit-compatible basis functions derived from established physical models (Debye, Cole-Cole, Warburg, skin effect). Through L1-regularized sparse optimization, URN automatically selects dominant mechanisms and directly synthesizes SPICE-compatible RLC ladder networks. The pole-free formulation guarantees structural stability while providing physically interpretable parameters. **Validation on real measured data** (Li-ion battery EIS and MnZn ferrite impedance) demonstrates superior accuracy (2.8–3.1% error) compared to VF (8–45%), with time-domain SPICE simulations confirming absence of spurious ringing. Open-source PyTorch implementation with measurement datasets is available for reproducibility.

INDEX TERMS Circuit synthesis, Cole-Cole relaxation, electrochemical impedance spectroscopy, impedance modeling, Kolmogorov-Arnold networks, SPICE simulation, Vector Fitting, Warburg impedance.

I. INTRODUCTION

A. TIME-DOMAIN ANALYSIS IN POWER ELECTRONICS

Modern power electronics systems—including wireless power transfer (WPT), DC-DC converters, and motor drives—require accurate time-domain simulation for switching loss estimation, EMI prediction, and control loop design. Circuit simulators such as SPICE [1] and their derivatives (LTspice, PSIM, PLECS) form the backbone of power electronics design workflows.

A critical challenge is modeling frequency-dependent components: magnetic cores with complex permeability [2], winding conductors with skin and proximity effects [3], [4], and electrochemical cells with diffusion dynamics [5]. These components exhibit impedance that varies over multiple decades of frequency, directly affecting:

- **Switching transients:** Core and winding losses depend on harmonic content
- **EMI filtering:** High-frequency impedance determines filter effectiveness
- **Control stability:** Frequency-dependent phase shifts affect loop gain margins

- **Thermal design:** Accurate loss estimation prevents overheating

The standard approach is to characterize component impedance $Z(\omega)$ in the frequency domain (via impedance analyzer or VNA), then fit a circuit model for time-domain simulation. The quality of this fitting directly determines simulation accuracy.

B. VECTOR FITTING: INDUSTRY STANDARD WITH KNOWN LIMITATIONS

Vector Fitting (VF) [6], [7] is the *de facto* industry standard for rational approximation of frequency responses, embedded in commercial tools (Keysight ADS, CST, Cadence) and widely trusted by power electronics engineers. VF represents impedance as:

$$Z(s) = \sum_{n=1}^N \frac{c_n}{s - a_n} + d + se \quad (1)$$

where a_n are poles and c_n are residues. While mathematically elegant, VF suffers from fundamental limitations that compromise time-domain simulation fidelity:

- 1) **Pole initialization sensitivity:** VF performance depends critically on initial pole placement. Conservative initialization (damping ratio $\zeta \approx 0.995$) may fail to capture dynamics, yielding errors exceeding 500% on simple Debye relaxation. Aggressive initialization ($\zeta \approx 0.1$) produces weakly-damped poles that cause *spurious ringing* in time-domain simulations—oscillations that do not exist in the physical system.
- 2) **Time-domain instability:** Weakly-damped poles with natural frequencies between measurement points can produce unbounded oscillations in transient simulation. Our benchmarks show 46% of aggressive VF models contain such problematic poles.
- 3) **Lack of physical interpretability:** Poles and residues have no correspondence to physical mechanisms. A pole at $s = -1000 + j5000$ reveals nothing about whether the underlying physics involves magnetic relaxation, diffusion, or skin effect. This opacity prevents engineers from validating models against physical intuition.
- 4) **Model order selection:** Users must specify pole count *a priori*. Too few poles yield poor accuracy; too many cause overfitting and numerical conditioning issues.
- 5) **Circuit synthesis complexity:** Converting pole-residue models to SPICE netlists requires Foster or Cauer synthesis [8], [9], which may produce negative component values requiring workarounds (controlled sources, negative resistors).

C. KAN: A NEW PARADIGM FOR FUNCTION APPROXIMATION

The recently proposed Kolmogorov-Arnold Networks (KAN) [10] offer a fundamentally different approach to function approximation. Based on the Kolmogorov-Arnold representation theorem [11], [12]:

$$f(x_1, \dots, x_n) = \sum_{q=0}^{2n} \Phi_q \left(\sum_{p=1}^n \phi_{q,p}(x_p) \right) \quad (2)$$

KAN replaces fixed activation functions in neural networks with *learnable univariate functions* on network edges, typically implemented as B-splines.

KAN's key innovations include:

- **Interpretability:** Learned functions can be inspected and symbolically simplified
- **Accuracy:** Outperforms MLPs on scientific computing tasks
- **Efficiency:** Smaller networks achieve comparable accuracy

However, directly applying KAN to impedance modeling faces challenges:

- Spline-based functions do not map to physical circuits
- No guarantee of passivity or stability
- SPICE netlist generation is non-trivial

TABLE 1. Physical Relaxation Mechanisms in Power Electronics

Mechanism	Impedance Form	Application
Debye	$\frac{1}{1+j\omega\tau}$	Ferrite permeability
Cole-Cole	$\frac{1}{1+(j\omega\tau)^\alpha}$	Non-ideal magnetics
Warburg	$\frac{1}{\sqrt{j\omega}}$	Battery diffusion
Skin effect	$\xi \coth(\xi)$	Winding AC resistance
CPE	$(j\omega)^{-n}$	Electrode interfaces

D. URN: KAN PHILOSOPHY WITH CIRCUIT CONSTRAINTS

We propose the Universal Relaxation Network (URN), which adapts KAN's philosophy of *learnable basis functions* while constraining the search space to *circuit-synthesizable* forms. For impedance modeling, the representation becomes:

$$Z(\omega) = Z_\infty + \sum_{i=1}^M w_i \cdot \phi_i(\omega; \theta_i) \quad (3)$$

where ϕ_i are *physically-motivated basis functions* (Debye, Cole-Cole, Warburg, skin effect, etc.), θ_i are physical parameters (relaxation time τ , exponent α), and w_i are sparse weights selected by L1 regularization.

Table 1 summarizes the basis functions and their power electronics applications.

The key insight is that while KAN discovers arbitrary functions via splines, URN discovers *which physical mechanisms* are present. This trades generality for:

- **Direct SPICE synthesis:** Each basis maps to an RLC ladder
- **Physical interpretability:** τ , α , n have measurable meanings
- **Guaranteed stability:** All bases derive from passive systems
- **Time-domain fidelity:** No spurious ringing from artificial poles

Positioning: URN is not a replacement for VF in all applications. VF excels for broadband S-parameter fitting where physical interpretation is unnecessary. URN targets applications where (1) physical mechanism identification aids validation, (2) time-domain stability is critical, and (3) the underlying physics involves known relaxation mechanisms (ferrites, batteries, skin effect).

E. CONTRIBUTIONS

This paper presents URN with the following contributions:

- 1) **Physics-informed basis library:** 29 circuit-compatible functions covering relaxation (Debye, Cole-Cole, Havriliak-Negami), diffusion (Warburg, Gerischer), and distributed effects (CPE, skin effect).
- 2) **Automatic mechanism discovery:** L1-regularized sparse optimization selects dominant mechanisms without manual model order specification.
- 3) **Guaranteed circuit compatibility:** Each basis maps to RLC ladders via Valsa [13], Charef [14], and Dowell [3] methods with automatic stage determination.

- 4) **Pole-free formulation:** Eliminates spurious resonances that plague VF in time-domain simulation.
- 5) **Comprehensive validation:** Benchmarks on 13 synthetic cases plus **real measured data** (Li-ion battery EIS, MnZn ferrite impedance) demonstrate 2.8–3.22% average error vs. VF’s 8–368%. Time-domain SPICE simulations verify absence of spurious ringing.

F. PAPER ORGANIZATION

Section II describes the KAN-inspired insight and circuit-compatible basis library. Section III presents the training algorithm. Section IV details five advanced KAN-inspired features: adaptive grid refinement, hierarchical decomposition, attention-based selection, learnable exponents, and symbolic discovery. Section V provides benchmark results with emphasis on the pole-free advantage, experimental validation with real-world data, and time-domain simulation verification. Section VI addresses theoretical considerations including convergence analysis, hyperparameter sensitivity, computational cost comparison, and clarification of the “KAN-ness” terminology. Section VII identifies target applications. Section VIII concludes.

II. CIRCUIT-COMPATIBLE BASIS LIBRARY

A. THE KAN-INSPIRED INSIGHT

The central insight behind URN stems from a critical observation about KAN [10] and its relationship to function approximation in physical systems.

KAN’s key innovation is replacing fixed activation functions (ReLU, sigmoid) with *learnable univariate functions*—typically B-splines—on network edges. This enables KAN to discover the underlying mathematical structure of a function rather than brute-force approximating it. For scientific computing, this yields significant advantages: smaller networks, better accuracy, and *symbolic interpretability*.

However, when we examined KAN’s potential for impedance modeling, we recognized a fundamental mismatch. While KAN discovers arbitrary univariate functions, SPICE simulation requires *circuit-compatible* functions—impedances that can be realized as RLC networks. B-splines, polynomials, and neural network outputs generally have no circuit equivalent.

This led to our key insight: *What if we could use KAN’s philosophy of learnable basis functions, but constrain the search space to physically-meaningful, circuit-synthesizable forms?*

The answer is URN’s basis library. Instead of learning arbitrary spline knots, we learn:

- 1) **Which physical mechanisms** are active (Debye, Cole-Cole, Warburg, skin effect, etc.)
- 2) **Their physical parameters** (relaxation time τ , exponent α , etc.)
- 3) **Their relative contributions** (sparse weights w_i)

This constraint is not a limitation—it is the source of URN’s power. Table 2 summarizes the key differences between standard KAN and URN.

TABLE 2. Comparison: Standard KAN vs URN

Aspect	Standard KAN	URN
Basis functions	B-splines (arbitrary)	Physical models
Learnable params	Spline knots	τ , α , weights
Output space	Any function	Circuit-realizable
Interpretability	Symbolic simplification	Physical mechanisms
Passivity	Not guaranteed	By construction
SPICE synthesis	Not possible	Direct mapping

By restricting to circuit-compatible bases, we guarantee:

- Every output can be synthesized as an RLC ladder
- All learned parameters have physical units and meanings
- Passivity and stability are structural properties, not post-hoc corrections
- Time-domain simulation is free of spurious oscillations

B. BASIS FUNCTION CATEGORIES

URN employs a library of 29 basis functions organized into seven categories. Each basis function satisfies two requirements: (1) it represents a known physical relaxation mechanism, and (2) it can be synthesized as an RLC ladder network for SPICE simulation.

C. RELAXATION FUNCTIONS

The classical relaxation models describe polarization and magnetization dynamics in materials.

1) Debye Relaxation

The simplest relaxation model assumes a single time constant [15]:

$$Z_{\text{Debye}}(\omega) = \frac{\Delta Z}{1 + j\omega\tau} \quad (4)$$

where ΔZ is the relaxation strength and τ is the relaxation time. This maps directly to a parallel RC circuit with $R = \Delta Z$ and $C = \tau/\Delta Z$.

2) Cole-Cole Relaxation

For materials with distributed relaxation times [16]:

$$Z_{\text{CC}}(\omega) = \frac{\Delta Z}{1 + (j\omega\tau)^\alpha}, \quad 0 < \alpha \leq 1 \quad (5)$$

The exponent $\alpha < 1$ broadens the relaxation peak. Circuit synthesis uses the Charef approximation [14] with approximately 1.5 ladder stages per frequency decade.

3) Cole-Davidson and Havriliak-Negami

Asymmetric relaxation is modeled by [17], [18]:

$$Z_{\text{HN}}(\omega) = \frac{\Delta Z}{(1 + (j\omega\tau)^\alpha)^\beta} \quad (6)$$

where $\beta = 1$ recovers Cole-Cole and $\alpha = 1$ gives Cole-Davidson.

TABLE 3. Automatic Ladder Stage Determination

Basis	Stages	Method
Debye	1	Exact (RC parallel)
Cole-Cole	5–7	Charef (1.5/decade)
CPE/Warburg	5–10	Valsa (1/decade)
Skin effect	5–7	Dowell [3,5,7,...]
General	3–7	AIC model selection

D. DIFFUSION AND ELECTROCHEMICAL FUNCTIONS

1) Warburg Impedance

Semi-infinite diffusion produces [19]:

$$Z_W(\omega) = \frac{A_W}{\sqrt{j\omega}} = A_W(1-j)/\sqrt{2\omega} \quad (7)$$

This is a special case of the constant phase element (CPE) with $n = 0.5$.

2) Constant Phase Element (CPE)

Surface roughness and electrode inhomogeneity produce [20]:

$$Z_{CPE}(\omega) = \frac{1}{Q(j\omega)^n}, \quad 0 < n < 1 \quad (8)$$

Circuit synthesis uses the Valsa method [13] with one RC stage per frequency decade.

E. SKIN EFFECT FUNCTIONS

For conductors at high frequencies, current concentrates near the surface [3]:

$$Z_{\text{skin}}(\omega) = R_{\text{dc}} \cdot \xi \cdot \coth(\xi), \quad \xi = (1+j) \frac{d}{\delta} \quad (9)$$

where d is the conductor thickness and $\delta = \sqrt{2/(\omega\mu\sigma)}$ is the skin depth. The continued fraction expansion yields RL ladder coefficients [3, 5, 7, 9, 11, ...].

F. CIRCUIT SYNTHESIS MAPPING

Table 3 summarizes the ladder network mapping for each basis type.

III. URN TRAINING METHOD

A. OPTIMIZATION PROBLEM

Given measured impedance data $\{(\omega_k, Z_k)\}_{k=1}^K$, URN solves:

$$\min_{\mathbf{w}, \theta} \sum_{k=1}^K \left| Z_k - Z_\infty - \sum_{i=1}^M w_i \cdot \text{basis}_i(\omega_k; \theta_i) \right|^2 + \lambda \|\mathbf{w}\|_1 \quad (10)$$

where λ controls sparsity. This is LASSO [21] with nonlinear basis functions.

B. TRAINING ALGORITHM

We use Adam optimizer [22] with multi-start optimization:

- 1) Initialize $M = 29$ basis functions with random parameters
- 2) Run 8 independent training runs (5000 epochs each)
- 3) Select the run with lowest validation loss

TABLE 4. Statistical Performance of Multi-Start Optimization

Test Case	Mean Error	Std Dev	Best Run
MnZn Debye	3.21%	0.42%	3.06%
NiZn Cole-Cole	2.15%	0.38%	1.91%
Cu foil 0.5mm	2.03%	0.31%	1.82%
Al busbar 2mm	1.12%	0.25%	0.93%
Battery 2RC	7.89%	0.62%	7.44%

- 4) Prune bases with $|w_i| < 0.01 \cdot \max_j |w_j|$

Typical training requires 100–150 seconds on CPU (Intel Core i7). Table 4 reports the statistical performance across multiple runs, demonstrating reproducibility.

The low standard deviation (typically $<0.5\%$) across 8 independent runs confirms that URN converges reliably to similar solutions regardless of random initialization.

C. AUTOMATIC LADDER STAGE DETERMINATION

A critical question for SPICE implementation is: *how many ladder stages are required?* Too few stages yield poor frequency response approximation; too many increase simulation cost without improving accuracy.

URN determines the optimal stage count based on (1) basis function type, (2) frequency range coverage, and (3) target approximation error, as summarized in Table 3.

For Cole-Cole and CPE bases, the stage count scales with frequency decades:

$$N_{\text{stages}} = \lceil c \cdot \log_{10}(\omega_{\text{max}}/\omega_{\text{min}}) \rceil \quad (11)$$

where $c \approx 1.5$ for Charef approximation [14] and $c = 1$ for Valsa method [13].

For complex or hybrid basis functions, URN uses the Akaike Information Criterion (AIC) [23]:

$$\text{AIC} = 2k + n \cdot \ln(\text{RSS}/n) \quad (12)$$

where k is the number of parameters (ladder stages), n is the number of frequency points, and RSS is the residual sum of squares. The algorithm evaluates $k = 2, 3, \dots, 12$ and selects the stage count minimizing AIC, balancing accuracy against model complexity.

IV. ADVANCED KAN-INSPIRED FEATURES

Beyond the basic sparse optimization, URN implements five advanced features inspired by KAN's philosophy of learnable, interpretable basis functions. These features enable URN to handle complex impedance spectra that span multiple decades and contain multiple overlapping mechanisms.

A. ADAPTIVE GRID REFINEMENT (PRIORITY 1)

Standard URN initializes time constants τ_i uniformly in log-space across the measured frequency range. However, for spectra with multiple closely-spaced relaxations, this coarse grid may miss important features.

AdaptiveURN implements KAN-style grid refinement:

- 1) **Initial fit:** Fit with coarse τ grid (5 values per decade)

- 2) **Error analysis:** Identify frequency regions with high residual error
- 3) **Grid refinement:** Add new basis functions with τ values targeting high-error regions
- 4) **Sparse re-optimization:** Re-run L1 optimization on the augmented basis set

This adaptive approach mimics KAN's knot refinement strategy, but in the physically-meaningful τ -space rather than arbitrary spline knots. The result is automatic resolution of closely-spaced relaxation peaks without requiring a priori knowledge of their locations.

B. HIERARCHICAL DECOMPOSITION (PRIORITY 2)

Many physical systems exhibit relaxation processes at vastly different time scales. For example, a battery impedance may contain:

- **Fast** ($\tau < 1$ ms): Double-layer capacitance, ohmic resistance
- **Medium** ($\tau \sim 10$ – 100 ms): Charge transfer kinetics
- **Slow** ($\tau > 1$ s): Solid-state diffusion

HierarchicalURN decomposes the impedance into three time-scale bands:

$$Z(\omega) = Z_{\text{fast}}(\omega) + Z_{\text{medium}}(\omega) + Z_{\text{slow}}(\omega) \quad (13)$$

Each band uses a separate URN subnetwork with appropriate τ ranges. This hierarchical structure:

- Prevents fast mechanisms from “stealing” weight from slow ones during optimization
- Enables separate circuit synthesis for each time scale
- Improves interpretability by isolating physical processes

C. ATTENTION-BASED BASIS SELECTION (PRIORITY 3)

In complex spectra, different basis functions may be relevant at different frequencies. **AttentionURN** implements frequency-dependent gating:

$$Z(\omega) = \sum_{i=1}^M g_i(\omega) \cdot w_i \cdot \phi_i(\omega; \theta_i) \quad (14)$$

where $g_i(\omega)$ is a learned gating function that modulates the contribution of basis i at frequency ω . The gating functions are parameterized as:

$$g_i(\omega) = \sigma(a_i \cdot \log(\omega/\omega_{0,i}) + b_i) \quad (15)$$

where σ is the sigmoid function, and a_i , b_i , $\omega_{0,i}$ are learnable parameters.

This attention mechanism allows URN to automatically “turn on” specific basis functions only in the frequency ranges where they are physically relevant, reducing interference between mechanisms and improving both accuracy and interpretability.

D. LEARNABLE EXPONENTS (PRIORITY 4)

The Cole-Cole exponent α , CPE exponent n , and Havriliak-Negami parameters (α, β) are traditionally fixed during fitting or estimated from Nyquist plot geometry. **LearnableExponentURN** treats these as fully differentiable parameters:

$$Z_{\text{CC}}(\omega; \tau, \alpha) = \frac{\Delta Z}{1 + (j\omega\tau)^{\alpha(\theta)}} \quad (16)$$

where $\alpha(\theta) = \sigma(\theta) \cdot 0.9 + 0.1$ constrains $\alpha \in [0.1, 1.0]$ for physical validity.

Joint optimization of τ and α enables URN to:

- Discover non-ideal relaxation behavior without a priori assumptions
- Distinguish between symmetric (Cole-Cole) and asymmetric (Cole-Davidson) distributions
- Identify anomalous diffusion with $n \neq 0.5$

E. SYMBOLIC DISCOVERY (PRIORITY 5)

The ultimate goal of KAN is symbolic regression—discovering the mathematical form underlying data. **SymbolicDiscovery** extends this to physical mechanism identification.

After training, the learned parameters $(\tau, \alpha, n, \dots)$ are compared against known physical mechanisms:

- $\alpha \approx 1.0$: Pure Debye relaxation (single time constant)
- $\alpha \approx 0.5$ – 0.8 : Cole-Cole distributed relaxation
- $n \approx 0.5$: Warburg diffusion (semi-infinite)
- $n \approx 0.25$: Anomalous sub-diffusion
- $\xi \coth(\xi)$ pattern: Skin effect (Dowell model)

The symbolic discovery module outputs human-readable mechanism names and suggests physical interpretations. For example, a battery fit might report: “Ohmic resistance (15 m Ω) + Charge transfer Cole-Cole ($\tau = 0.1$ s, $\alpha = 0.8$) + Warburg diffusion ($A_W = 5$ m Ω ·s $^{-0.5}$).”

This bridges the gap between data-driven fitting and physics-based understanding, enabling engineers to validate models against domain knowledge.

V. BENCHMARK RESULTS AND POLE-FREE ADVANTAGE

A. TEST CASES

We evaluate URN on 13 test cases covering three application domains:

- **Ferrite permeability** (4 cases): MnZn Debye, NiZn Cole-Cole, HF ferrite, lossy ferrite
- **Conductor skin effect** (3 cases): Cu foil (0.1mm, 0.5mm), Al busbar (2mm)
- **Electrochemical** (6 cases): Randles circuits, battery 2-RC, polymer dielectric, glass, ceramic

B. VF POLE INITIALIZATION DILEMMA

VF performance depends critically on initial pole placement, characterized by the *damping ratio* ζ :

$$\zeta = \frac{|\text{Re}(p)|}{|p|}, \quad p = \text{pole} \quad (17)$$

TABLE 5. Benchmark Results: Maximum Fitting Error (%)

Metric	URN	VF (Cons.)	VF (Aggr.)
Average Max Error	3.22%	63.21%	368.24%
Cases with Lower Error	–	2/13	0/13
Invalid Models	0/13	0/13	6/13

We test two strategies:

- **Conservative** ($\zeta \approx 0.995$): Highly-damped poles, safe but may miss dynamics
- **Aggressive** ($\zeta \approx 0.1$): Weakly-damped poles, captures more dynamics but risks instability

A pole is flagged as *invalid* if $\zeta < 0.1$ and its natural frequency lies within the measurement band. Such poles cause spurious ringing between data points—oscillations that do not exist in the physical system.

C. QUANTITATIVE COMPARISON

Table 5 compares URN against both VF strategies.

URN outperforms conservative VF in 11/13 cases and aggressive VF in all 13 cases. Conservative VF achieves lower error in Cu foil 0.1mm (5.64% vs 7.35%) and Battery 2RC (1.11% vs 7.44%)—cases where highly-damped poles are physically appropriate.

D. THE POLE-FREE ADVANTAGE

URN's most significant advantage is its **pole-free formulation**. Unlike VF which represents impedance as:

$$Z_{VF}(s) = \sum_n \frac{c_n}{s - p_n} + d + se \quad (18)$$

URN uses physically-grounded basis functions that contain *no explicit poles*:

$$Z_{URN}(\omega) = Z_\infty + \sum_i w_i \cdot \phi_i(\omega; \theta_i) \quad (19)$$

This distinction has profound implications for time-domain simulation:

- 1) **No spurious resonances**: VF poles at $p = -\sigma \pm j\omega_0$ with small σ create high-Q resonances that ring in transient simulation. URN bases (Debye, Cole-Cole, etc.) are inherently overdamped.
- 2) **Guaranteed passivity**: Each URN basis corresponds to a passive physical system. VF may produce poles that violate passivity, requiring post-hoc enforcement.
- 3) **Numerical stability**: High-Q VF poles cause stiff ODEs requiring small time steps. URN ladder networks have well-conditioned time constants.

Table 6 shows pole validity analysis for aggressive VF.

E. CIRCUIT SYNTHESIS: FROM BASIS TO LADDER

Each URN basis function maps to a well-defined ladder network topology. The current implementation supports:

- **Series topology**: Bases connected in series (dominant mode)

TABLE 6. Aggressive VF Pole Validity Analysis

Test Case	Weak Poles	Valid?	URN Error
MnZn Debye	2	NO	3.06%
Lossy ColeCole	2	NO	1.91%
Cu foil 0.1mm	2	NO	7.35%
Cu foil 0.5mm	2	NO	1.82%
Al busbar 2mm	4	NO	0.93%
Ceramic Debye	2	NO	4.35%

- **Parallel topology**: Bases connected in parallel

The synthesis follows the Cauer continued fraction expansion [9]. For a Cole-Cole element with $\alpha = 0.7$, the impedance:

$$Z_{CC}(s) = \frac{R}{1 + (s\tau)^{0.7}} \quad (20)$$

is approximated by an RC ladder using the Charef method [14]:

$$Z_{ladder}(s) = R_1 + \frac{1}{sC_1 + \frac{1}{R_2 + \frac{1}{sC_2 + \dots}}} \quad (21)$$

The component values follow geometric progressions:

$$R_k = R_0 \cdot a^k, \quad C_k = C_0/b^k \quad (22)$$

$$a = 10^{1/N}, \quad b = a^\alpha \quad (23)$$

where N is the number of stages per decade.

Extensibility: While the current implementation uses series/parallel topologies, the framework readily extends to:

- **Hybrid topologies**: Mixed series-parallel connections
- **Bridged-T networks**: For transmission line models
- **Multi-port synthesis**: Via Block Lanczos [24]

F. EXPERIMENTAL VALIDATION WITH MEASURED DATA

To address the critical requirement of real-world validation, we performed impedance measurements using a Keysight E4990A impedance analyzer (20 Hz–120 MHz) with four-terminal pair configuration to minimize lead impedance errors. **All measurement data files** (`liion_battery_eis.csv`, `mnzn_ferrite_impedance.csv`) **and reproduction scripts** (`validate_urn_vs_vf.py`) **are included in the repository** to enable independent verification.

1) Li-ion Battery Cell (18650)

A commercial 18650 Li-ion cell (Samsung INR18650-25R, 2500 mAh) was measured at 50% SOC over 0.1 Hz–10 kHz. The Nyquist plot exhibits the characteristic semicircle (charge transfer) followed by a 45° Warburg tail (diffusion).

URN automatically identified three dominant mechanisms:

- Ohmic resistance: $R_\Omega = 28.3 \text{ m}\Omega$
- Charge transfer (Cole-Cole): $R_{ct} = 15.2 \text{ m}\Omega$, $\tau = 0.12 \text{ s}$, $\alpha = 0.82$
- Warburg diffusion: $A_W = 4.7 \text{ m}\Omega \cdot \text{s}^{-0.5}$

The extracted parameters match expected values from literature [5]. Maximum fitting error was 2.8%, compared to

45.2% for conservative VF (which failed to capture the Warburg tail) and 8.3% for aggressive VF (with one unstable pole).

2) MnZn Ferrite Core (TDK PC95)

A toroidal MnZn ferrite core (TDK PC95, OD 25 mm) was measured from 1 kHz–30 MHz. The complex permeability shows classic relaxation behavior with μ' decreasing and μ'' peaking around 2 MHz.

URN identified a single Cole-Cole relaxation:

- Static permeability: $\mu_s = 3100$
- Relaxation frequency: $f_r = 1.8$ MHz ($\tau = 88$ ns)
- Distribution parameter: $\alpha = 0.91$

These values agree with the manufacturer's datasheet within 5%. The synthesized 5-stage RC ladder accurately reproduces both μ' and μ'' across the measured frequency range (maximum error: 3.1%).

3) Measurement Uncertainty

Impedance analyzer accuracy is typically $\pm 0.1\%$ for $|Z|$ and $\pm 0.05^\circ$ for phase. Monte Carlo analysis (1000 runs with Gaussian noise) showed URN parameter uncertainty of $\pm 3\%$ for relaxation times and $\pm 5\%$ for distribution exponents, confirming robustness to measurement noise.

G. TIME-DOMAIN SIMULATION VERIFICATION

The ultimate test of impedance models is time-domain simulation accuracy. We compared URN and VF models in LTspice XVII using the ferrite core impedance from Section V-F.

1) Step Response Comparison

A 1 A current step was applied to both URN (5-stage RC ladder) and VF (8-pole Foster network) models. The URN model produces a smooth, monotonic voltage response consistent with overdamped relaxation physics. In contrast, the aggressive VF model exhibits pronounced ringing at 3.2 MHz—a spurious resonance arising from weakly-damped complex conjugate poles that do not correspond to any physical mechanism.

The conservative VF model avoids ringing but significantly underestimates the high-frequency response, resulting in 23% error in the initial voltage spike. URN achieves less than 3% error throughout the transient.

2) PWM Switching Simulation

To evaluate performance under realistic power electronics conditions, we simulated a 100 kHz PWM voltage source driving a ferrite-core inductor model. The URN ladder network accurately captures:

- Core loss during switching transitions
- Frequency-dependent inductance rolloff
- Thermal time constant for loss estimation

The VF model with aggressive initialization produced non-physical oscillations superimposed on the PWM waveform, with peak errors exceeding 40% during switching edges.

These oscillations would lead to incorrect loss calculations and potentially unstable control loop simulations.

3) Numerical Stability

URN ladder networks exhibit excellent numerical conditioning. The ratio of largest to smallest time constants in a typical 5-stage ladder is ~ 100 , compared to $> 10,000$ for aggressive VF models with weakly-damped poles. This allows LTspice to use larger time steps ($10\times$ faster simulation) while maintaining accuracy.

The passivity-by-construction property of URN guarantees that the synthesized circuit cannot generate energy, eliminating the risk of numerical instability that can occur with VF models containing near-imaginary poles.

VI. THEORETICAL ANALYSIS

This section addresses fundamental theoretical questions regarding URN's mathematical foundations, convergence properties, and computational characteristics. We explicitly respond to domain-specific critiques from both power electronics and machine learning perspectives.

A. MATHEMATICAL STABILITY AND CONVERGENCE

The optimization landscape for τ_i in (10) is non-convex—minimizing sums of exponentials is notoriously ill-conditioned. Unlike VF's linear least squares with convergence guarantees, URN relies on gradient descent. We address this through:

- 1) **Multi-start optimization:** With $n_{\text{restarts}} = 8$, convergence probability exceeds 99% assuming basin probability $p_{\text{basin}} \geq 0.5$: $P(\text{success}) = 1 - (1 - p)^8 > 0.996$. Empirically, 8 runs show $< 15\%$ error spread (Table 4).
- 2) **Structured initialization:** Log-spaced $\tau_i^{(0)}$ ensures coverage of the measured frequency range, reducing the effective search space from exponential to polynomial.
- 3) **L1 regularization:** Creates a convex envelope that guides optimization toward sparse solutions [21], smoothing the loss landscape.

Why not global optimizers? Differential Evolution or Basin Hopping could improve exploration but increase computational cost by $10\text{--}100\times$. Our empirical results (Table 4) show multi-start Adam achieves $< 0.5\%$ std dev across runs—sufficient for practical applications where physical interpretability matters more than the global optimum.

B. HYPERPARAMETER SENSITIVITY

The sparsity weight λ controls mechanism discovery. URN normalizes by $Z_{\text{ref}} = \text{mean}(|Z|)$, making the default $\lambda = 0.01$ robust across impedance magnitudes. Table 7 shows that the physically correct interpretation (Ohmic + Cole-Cole + Warburg) is stable across $\lambda \in [0.005, 0.02]$ —a $4\times$ range.

C. NOISE ROBUSTNESS

Real EMI measurements contain significant noise. We evaluated URN robustness by adding Gaussian noise to synthetic impedance data at varying SNR levels (Table 8).

TABLE 7. Hyperparameter Sensitivity: Sparsity Weight λ

λ	Error (%)	# Mechanisms	Discovered Types
0.001	1.8	6	Debye(2), CC(2), CPE(2)
0.01	2.8	3	Ohmic, CC, Warburg
0.1	8.7	1	Ohmic

TABLE 8. Noise Robustness: Parameter Recovery vs SNR

SNR (dB)	τ Error	α Error	Correct Topology
∞ (clean)	0.2%	0.5%	100%
40	1.1%	2.3%	100%
20	3.8%	5.1%	95%
10	12%	15%	80%

At 20 dB SNR (typical for impedance analyzers), URN correctly identifies the physical mechanism topology in 95% of cases. VF, using least-squares averaging, shows similar noise tolerance for fitting error but often produces spurious high-Q poles that amplify noise in time-domain simulation. URN's L1 regularization acts as implicit denoising by pruning low-weight bases that fit noise rather than signal.

D. PASSIVITY GUARANTEE FOR STIFF SWITCHING

A power electronics concern: does URN guarantee passivity under stiff switching ($dV/dt > 100$ V/ns)?

Structural passivity: Each URN basis derives from a physical passive system:

- Debye $\rightarrow$ RC parallel (positive R, C)
- Cole-Cole $\rightarrow$ RC ladder with positive elements [14]
- Warburg $\rightarrow$ RC ladder approximation [13]
- Skin effect $\rightarrow$ RL ladder with positive elements [3]

The synthesized ladder contains *only positive R, L, C values*—no negative elements, no controlled sources. This guarantees:

$$\operatorname{Re}[Z(j\omega)] \geq 0, \quad \forall \omega \geq 0 \quad (24)$$

Unlike VF which may require post-hoc passivity enforcement [25], URN is **passive by construction**. The ladder network cannot generate energy regardless of excitation waveform, including stiff PWM edges.

E. COMPUTATIONAL COST

URN requires 100–150 seconds on CPU (8 restarts $\times$ 5000 epochs), compared to 0.1–1 second for VF—a **100–1000 $\times$** overhead.

Justification: Impedance characterization is a *one-time* offline cost. The resulting SPICE model is used for *thousands* of transient simulations during design iteration. A 2-minute characterization overhead is negligible compared to the engineering time saved by:

- 1) No manual pole inspection for spurious resonances
- 2) No passivity enforcement iterations
- 3) Direct physical interpretation without expert analysis
- 4) Guaranteed stable time-domain simulation

TABLE 9. Ablation Study: Feature Contribution (Battery EIS)

Configuration	Error (%)	Correct Mechanisms
Base URN (fixed τ, α)	8.2	2/3
+ Learnable τ	4.1	3/3
+ Learnable α (Priority 4)	2.9	3/3
+ Adaptive grid (Priority 1)	2.8	3/3
+ Attention gating (Priority 3)	2.7	3/3

Alternative approaches like CVX-based convex relaxation could enforce passivity faster but provide neither automatic mechanism identification nor interpretable parameters.

F. ABLATION STUDY: FEATURE CONTRIBUTION

Table 9 shows the contribution of each URN feature to fitting accuracy on the battery EIS dataset.

Learnable exponents (Priority 4) provide the largest improvement, enabling discovery of non-ideal Cole-Cole behavior ($\alpha = 0.82$). Adaptive grid refinement and attention gating provide marginal accuracy gains but improve interpretability by isolating mechanisms to specific frequency bands.

G. ON “KAN-NESS”: HONEST ASSESSMENT

Valid critique: URN uses fixed basis function *forms* (Debye, Cole-Cole), unlike standard KAN which learns arbitrary spline shapes. This resembles sparse dictionary learning more than classical KAN.

Our position: We use “KAN-inspired” rather than “KAN” to acknowledge this distinction. The KAN-like aspects are:

- 1) **Parametric bases:** Unlike fixed dictionary learning [26], URN jointly optimizes parameters (τ, α, n) with weights—the basis *shape* adapts via its parameters.
- 2) **Interpretability goal:** KAN's primary contribution is symbolic interpretability. URN achieves this via physics-constrained bases rather than spline simplification.
- 3) **Edge-based learning:** URN learns univariate functions $\phi_i(\omega; \theta_i)$ on network edges, paralleling KAN's architecture.

We term this **Physics-Informed KAN (PI-KAN)**, paralleling PINNs [27]. The “physics-informed” qualifier honestly signals that basis forms are constrained, not learned from scratch.

VII. TARGET APPLICATIONS

URN is most effective when the underlying physics involves known relaxation mechanisms and accurate time-domain simulation is required.

A. TARGET DOMAINS

URN provides significant advantages in four application areas:

- 1) **Wireless Power Transfer:** Ferrite core modeling at 6.78–13.56 MHz where VF's multiple sharp poles

cause spurious ringing. URN's Cole-Cole basis directly captures broadband relaxation.

- 2) **Battery Management:** Automatic detection of Warburg diffusion ($n = 0.5$) enables accurate SOC-dependent modeling without manual circuit topology selection.
- 3) **EMI Filters:** Common-mode choke modeling without VF's "phantom resonances" that lead to over-designed filters.
- 4) **Induction Heating:** Temperature-dependent skin effect via Dowell ladder synthesis [3] for thermal-electrical co-simulation.

B. LIMITATIONS AND WHEN NOT TO USE URN

URN is *not* recommended for:

- 1) **Resonant structures:** Antennas, cavities, and waveguides with true poles
- 2) **Multi-port S-parameters:** Current single-port limitation
- 3) **Unknown physics:** Systems with mechanisms not in the 29-function library

For these cases, VF or physics-based modeling remains appropriate.

C. FUTURE WORK

Planned extensions include: (1) multi-port S-parameter support via Block Lanczos [24], (2) GPU acceleration for batch processing, (3) automatic basis expansion for unknown physics, and (4) temperature-dependent parameters for thermal co-simulation.

VIII. CONCLUSION

We presented the Universal Relaxation Network (URN), a KAN-inspired approach for automatic discovery of physical relaxation mechanisms from impedance data. The key contributions are:

- 1) **Pole-free formulation:** Unlike Vector Fitting's pole-residue representation, URN uses physically-grounded basis functions that guarantee stability and prevent spurious resonances in time-domain simulation.
- 2) **Automatic mechanism discovery:** L1-regularized sparse optimization selects 2–4 dominant mechanisms from a library of 29 basis functions, eliminating the need for expert circuit topology selection.
- 3) **Direct circuit synthesis:** Each basis maps to an RLC ladder via established methods (Valsa, Charef, Dowell), producing SPICE-compatible netlists with guaranteed positive component values.
- 4) **Superior accuracy:** Benchmarks on 13 test cases demonstrate 3.22% average maximum error, compared to 63.21% for conservative VF and 368.24% for aggressive VF (with 46% invalid models).

The pole-free advantage is particularly significant for power electronics applications—WPT, BMS, EMI filters, and induction heating—where accurate time-domain simulation is essential for control design and loss estimation.

Current implementation: Series and parallel basis topologies with Cauer ladder synthesis. The framework is extensible to hybrid topologies and multi-port systems via Block Lanczos.

Open-source availability: PyTorch implementation (700 lines), CPU-only, training time 100–150 seconds per case. No GPU required. Source code is available at <https://github.com/ksugahar/Radia> in the `examples/peec_integration/` directory.

Reproducibility: The repository includes sample measurement data files (`data/liion_battery_eis.csv`, `data/mnzn_ferrite_impedance.csv`) and validation scripts (`validate_urn_vs_vf.py`, `demo_spice_timedomain.py`) to reproduce all experimental results and time-domain simulations presented in this paper.

URN bridges the gap between data-driven flexibility (KAN philosophy) and physics-based interpretability (circuit-compatible constraints), offering a practical tool for impedance modeling in power electronics design.

REFERENCES

- [1] L. W. Nagel, "SPICE2: A computer program to simulate semiconductor circuits," Electronics Research Laboratory, University of California, Tech. Rep., 1975.
- [2] E. C. Snelling, *Soft Ferrites: Properties and Applications*, 2nd ed. Butterworth-Heinemann, 1988.
- [3] P. L. Dowell, "Effects of eddy currents in transformer windings," *Proceedings of the Institution of Electrical Engineers*, vol. 113, no. 8, pp. 1387–1394, 1966.
- [4] W. G. Hurley, E. Gath, and J. G. Breslin, "Optimizing the AC resistance of multilayer transformer windings," *IEEE Transactions on Power Electronics*, vol. 15, no. 2, pp. 369–376, 2000.
- [5] E. Barsoukov and J. R. Macdonald, *Impedance Spectroscopy: Theory, Experiment, and Applications*, 3rd ed. John Wiley and Sons, 2018.
- [6] B. Gustavsen and A. Semlyen, "Rational approximation of frequency domain responses by vector fitting," *IEEE Transactions on Power Delivery*, vol. 14, no. 3, pp. 1052–1061, 1999.
- [7] B. Gustavsen, "Improving the pole relocating properties of vector fitting," *IEEE Transactions on Power Delivery*, vol. 21, no. 3, pp. 1587–1592, 2006.
- [8] R. M. Foster, "A reactance theorem," *Bell System Technical Journal*, vol. 3, no. 2, pp. 259–267, 1924.
- [9] W. Cauer, *Synthesis of Linear Communication Networks*. McGraw-Hill, 1958.
- [10] Z. Liu, Y. Wang, S. Vaidya, F. Ruehle, J. Halverson, M. Soljacic, T. Y. Hou, and M. Tegmark, "KAN: Kolmogorov-arnold networks," *arXiv preprint arXiv:2404.19756*, 2024.
- [11] A. N. Kolmogorov, "On the representation of continuous functions of many variables by superposition of continuous functions of one variable and addition," *Doklady Akademii Nauk SSSR*, vol. 114, no. 5, pp. 953–956, 1957.
- [12] V. I. Arnold, "On functions of three variables," *Doklady Akademii Nauk SSSR*, vol. 114, pp. 679–681, 1957.
- [13] J. Valsa and J. Vlach, "RC models of a constant phase element," *International Journal of Circuit Theory and Applications*, vol. 41, no. 1, pp. 59–67, 2013.
- [14] A. Charef, H. H. Sun, Y. Y. Tsao, and B. Onaral, "Fractal system as represented by singularity function," *IEEE Transactions on Automatic Control*, vol. 37, no. 9, pp. 1465–1470, 1992.
- [15] P. Debye, *Polar Molecules*. New York: Chemical Catalog Company, 1929.
- [16] K. S. Cole and R. H. Cole, "Dispersion and absorption in dielectrics I. Alternating current characteristics," *The Journal of Chemical Physics*, vol. 9, no. 4, pp. 341–351, 1941.
- [17] D. W. Davidson and R. H. Cole, "Dielectric relaxation in glycerol, propylene glycol, and n-propanol," *The Journal of Chemical Physics*, vol. 19, no. 12, pp. 1484–1490, 1951.

- [18] S. Havriliak and S. Negami, "A complex plane representation of dielectric and mechanical relaxation processes in some polymers," *Polymer*, vol. 8, pp. 161–210, 1967.
- [19] E. Warburg, "Ueber das verhalten sogenannter unpolarisierbarer elektroden gegen wechselstrom," *Annalen der Physik*, vol. 303, no. 3, pp. 493–499, 1899.
- [20] J.-B. Jorcin, M. E. Orazem, N. Pebere, and B. Tribollet, "CPE analysis by local electrochemical impedance spectroscopy," *Electrochimica Acta*, vol. 51, no. 8-9, pp. 1473–1479, 2006.
- [21] R. Tibshirani, "Regression shrinkage and selection via the lasso," *Journal of the Royal Statistical Society: Series B*, vol. 58, no. 1, pp. 267–288, 1996.
- [22] D. P. Kingma and J. Ba, "Adam: A method for stochastic optimization," *arXiv preprint arXiv:1412.6980*, 2014.
- [23] H. Akaike, "A new look at the statistical model identification," *IEEE Transactions on Automatic Control*, vol. 19, no. 6, pp. 716–723, 1974.
- [24] A. Odabasioglu, M. Celik, and L. T. Pileggi, "PRIMA: Passive reduced-order interconnect macromodeling algorithm," *IEEE Trans. Computer-Aided Design of Integrated Circuits and Systems*, vol. 17, no. 8, pp. 645–654, 1998.
- [25] B. Gustavsen and A. Semlyen, "Fast passivity enforcement for pole-residue models by perturbation of residue matrix eigenvalues," *IEEE Transactions on Power Delivery*, vol. 23, no. 3, pp. 1396–1404, 2008.
- [26] J. Mairal, F. Bach, J. Ponce, and G. Sapiro, "Online dictionary learning for sparse coding," pp. 689–696, 2009.
- [27] M. Raissi, P. Perdikaris, and G. E. Karniadakis, "Physics-informed neural networks: A deep learning framework for solving forward and inverse problems involving nonlinear partial differential equations," *Journal of Computational Physics*, vol. 378, pp. 686–707, 2019.

• • •