

1. Problem 8.4.2 of the text.

A *linear-time reduction* R must complete its output $R(x)$ in $\mathcal{O}(|x|)$ steps. Prove that there are no **P**-complete problems under linear-time reductions. (Such a problem would be in **TIME** (n^k) for some fixed $k > 0$.)

2. Part (a) of Problem 8.4.7 of the text. (Your circuits should use only AND-, OR-, and NOT-gates. Don't worry if you can't solve Part (b); I believe it is misstated—in any case it is not solved in the paper by Dymond and Cook that is cited.)

(a) Prove that **CIRCUIT VALUE** remains **P**-complete even if the circuit is planar. (Show how wires can cross with no harm to the computed value.)

3. Prove that **CIRCUIT VALUE** remains **P**-complete even if the circuit is monotone (that is, contains only AND- and OR-gates). (Hint: recall the solution to Problem 1 of Homework Assignment 2.)
-