

Customer		Date	
Project Title		Code No.	
Project Description			
Release Code File (fill "00H" or "FFH" for unused area)			
Binary filename		Binary file checksum	
		User-ROM checksum (computed by G+IDE tool)	
Important Check			
The OTP body will be referencing the code option during power-on. User needs to select the correct code option in the G+ IDE under the Mask/OTP option field. ☐ Check; by ticking off this box, customer understands that the G+IDE options are fully met and verified			
Hardware / Software			
The hardware/software programming check list intends to provide specific directions to use Generalplus's device. It is the customer's responsibility to check and confirm all the information in the list. No responsibility is assumed by Generalplus if any item is not checked by the customer. Make sure the following conditions are met and verified. ● EMU Board VLCD setting is different from OTP and is fully tested on OTP chip. ● Working Voltage: 2.0V~3.6V (Vreg=Regulator OFF), 2.0V~5.5V (Vreg=Regulator ON). ● If selecting X'TAL32K, PortC[5:4] must select as X32O and X32I. ● When LVD function is enabled, LVD Interrupt must be disabled when entering halt mode. It can be enabled only at normal mode. ● The reset pin needs to be internally or externally pull-high. If the reset pin is not set pull-high, IO state will be floating. ● Stack area located at \$180~\$1FF. ● When LCD is turned on and system enters the halt mode, P_LCD_VLCD_Ctrl (0x0019.b5/b4) must be set "11" or "10". ● Timer0 source control (0x0022.b6) must be set "1". ● When timer is not used for wakeup AND when LCD is turned off, 32768Hz ROSC should be turned off before entering sleep mode. ● Refer to the Programming guide 1.3 Differences between GPL813V00A and GPL813P01X. ● PortE data must be latched before setting wakeup source and entering sleep mode. That is, the following code must be presented prior to setting wakeup source and entering sleep mode: LDA \$04 ; latch PortE. ☐ Check; by ticking off this box, customer understands that the above conditions are fully met and verified.			
General Programming Checklist			
The general programming checklist intends to provide some general characteristics about GENERALPLUS devices. It is the customer's responsibility to check all the information in the list. No responsibility is assumed by GENERALPLUS for any non-checked box even this confirmation sheet has been approved by GENERALPLUS. Make sure the following conditions are met and verified: ● CPU stack pointer must be reset after system power-on. ● All RAM must be initialized after power on. ● Do not enable interrupt before initializing RAM. ● Sleep port must be cleared and re-initialized before entering sleep mode. ● The used RAM not over the stack reserved area. ● Correct RAM/ROM size and start addresses. ● No current drain on I/O in sleep mode. ● No I/O remains floating in sleep mode. ● Non-used I/O ports should be masked off (for input process).			

- Example (suppose PortC[3:0] as input and PortC [7:4] are invalid):
LDA PortC ; read I/O port C Data
AND #0FH ; mask off high nibble

☐ Check; by ticking off this box, customer understands that the above conditions are fully met and verified.

Development Tool / Board Version	
Programming guide title and version	
User's guide title and version	
Other documents (if any)	
Customer's Signature	

Note: Please send/fax this form to GENERALPLUS. GENERALPLUS will return it back with signature.