

# Cheatsheet External Interrupts

DI(FH) Andreas Pötscher, HTL Litec

## EICRA EICRB

*External Interrupt Controll Register A B*

| Bit           | 7     | 6     | 5     | 4     | 3     | 2     | 1     | 0     |
|---------------|-------|-------|-------|-------|-------|-------|-------|-------|
| <b>EICRA:</b> | ISC31 | ISC30 | ISC21 | ISC20 | ISC11 | ISC10 | ISC01 | ISC00 |

| Bit           | 7     | 6     | 5     | 4     | 3     | 2     | 1     | 0     |
|---------------|-------|-------|-------|-------|-------|-------|-------|-------|
| <b>EICRB:</b> | ISC71 | ISC70 | ISC61 | ISC60 | ISC51 | ISC50 | ISC41 | ISC40 |

## ISCn1 ISCn0

*Interrupt Source Control*

| Bit<br>ISCn1 | Bit<br>ISCn0 | Bedeutung:                                                                                          |
|--------------|--------------|-----------------------------------------------------------------------------------------------------|
| 0            | 0            | Low-Level: Der Low-Pegel am Pin INTn erzeugt den Interrupt (level-triggered Interrupt).             |
| 0            | 1            | Any Edge: Sowohl eine steigende als auch eine fallende Flanke am Pin INTn erzeugen einen Interrupt. |
| 1            | 0            | Falling edge: Die fallende Flanke am Pin INTn erzeugt einen Interrupt                               |
| 1            | 1            | Rising edge: Die steigende Flanke am Pin INTn erzeugt einen Interrupt.                              |

## EIMSK

*External Interrupt Mask Register*

| Bit           | 7    | 6    | 5    | 4    | 3    | 2    | 1    | 0    |
|---------------|------|------|------|------|------|------|------|------|
| <b>EIMSK:</b> | INT7 | INT6 | INT5 | INT4 | INT3 | INT2 | INT1 | INT0 |

## **INTn**

- **1** aktiviert den externen Interrupt
- **0** deaktiviert den externen Interrupt

## **Interrupt Vektor**

*INT0\_vect, INT1\_vect, INT2\_vect, ....*