

2. **The term we throw away.** A reflector antenna has largest dimension $D = 0.8\text{m}$ and operates at 6GHz. The quadratic term dropped from the expansion of R leaves a worst-case phase error $\Delta\phi = \pi D^2/(4\lambda r)$.

(a) Find λ .

$\lambda =$

(b) A test range puts the source at $r = 20\text{m}$. Find $\Delta\phi$ in degrees.

$\Delta\phi =$

(c) Find the smallest r for which $\Delta\phi \leq 22.5^\circ$ ($\pi/8$). Compare it to $2D^2/\lambda$.

$r_{\min} =$

(d) The range in part (b) is too short. Is the measured *pattern* wrong because the amplitude approximation failed, the phase approximation failed, or both?

3. **Uniform line source.** A $\hat{\mathbf{z}}$ -directed filament carries a uniform current I_0 over $-L/2 \leq z' \leq L/2$, with $L = 3\lambda$. Recall the space factor $S(\theta) = |\sin(u)/u|$ with $u = \frac{kL}{2} \cos(\theta)$.

- (a) Evaluate the radiation integral to show where $S(\theta)$ comes from.

$$N_z =$$

- (b) Find the angles of the first nulls.

$$\theta_{\text{null}} =$$

- (c) Estimate the half-power beamwidth with $0.886\lambda/L$, then check it against the exact half-power condition $u = 1.392$.

rule of thumb =

 exact =


- (d) The design is changed to $L = 6\lambda$. What happens to the beamwidth, and what happens to the first sidelobe level? Justify both from the Fourier relationship.

4. **Steering with a phase slope.** A uniform line source of length $L = 4\lambda$ is fed with a progressive phase so that the pattern peak moves off broadside to $\theta_0 = 60^\circ$. The excitation is $I(z') = I_0 e^{-jkz' \cos(\theta_0)}$.

- (a) Show from the radiation integral that the peak lands at θ_0 , and state the peak angle for this design.

$$\theta_{\text{peak}} =$$

- (b) Find the total phase difference (in degrees) between the two ends of the aperture.

$$\Delta\phi =$$

- (c) The steered beamwidth is approximately $0.886\lambda/(L\sin(\theta_0))$. Evaluate it and compare with the broadside value.

$$\text{HPBW} =$$

5. **The half-wave dipole.** The sinusoidal current $I(z') = I_0 \sin\left(k\left(\frac{L}{2} - |z'|\right)\right)$ with $L = \lambda/2$ produces the far-field pattern

$$|F(\theta)| = \left| \frac{\cos\left(\frac{\pi}{2} \cos(\theta)\right)}{\sin(\theta)} \right|$$

- (a) Evaluate $|F|$ at $\theta = 90^\circ$ and at $\theta = 0^\circ$, and interpret each.

$$|F(90^\circ)| = \boxed{}$$

$$|F(0^\circ)| = \boxed{}$$

- (b) Evaluate $|F|$ at $\theta = 45^\circ$, in dB relative to the peak.

$$|F(45^\circ)| = \boxed{}$$

- (c) An infinitesimal dipole has $|F| = \sin(\theta)$, which at 45° is 0.707 (−3.0 dB). The half-wave dipole is 1 dB further down at the same angle. Explain physically why the half-wave pattern is *sharper*, in terms of the current distribution.

- (d) The radiation integral is exact once $\vec{J}$ is known. State what makes $\vec{J}$ hard to know, and name the numerical method that solves for it.

6. **Reading the Fourier relationship.** Four aperture distributions of the *same* length L produce first sidelobes of -13.3 dB , -23 dB , -26.5 dB , and -31.5 dB . Work these parts from the **taper table in Lesson 6**, which pairs each distribution with its first-sidelobe level and also records the price: relative to uniform illumination, a taper broadens the main beam by roughly $1.3\times$ to $1.6\times$.

(a) Match each level to its distribution: uniform, cosine taper, cosine-squared taper, triangular.

(b) All four have the same L . Rank their half-power beamwidths, put an approximate broadening factor on each, and explain the trade.

(c) Your requirement is a 2° beam with sidelobes below -25 dB . Which knob sets which requirement? Size the aperture, in wavelengths, both before and after you apply the taper you chose.

L (uniform) =

L (tapered) =

Documentation: _____