Learning Objective 2.1: I can describe what a Software Defined Radio is, contrast it with a traditional hardware radio, and identify the SDR platforms used in this course (RTL-SDR, HackRF, PlutoSDR, ADALM-PHASER).

Learning Objective 2.2: I can identify the roles of the RF frontend, ADC/DAC, and host in an SDR signal chain and describe sample-rate, bandwidth, and dynamic-range trade-offs.

Use the course SDR table from the lesson page. Show your work. Write a **Documentation** line at the end (**None** if you did not collaborate).

1. **Choosing a radio.** The course SDRs are the RTL-SDR Blog V4 (0.5 to 1766 MHz, 2.56 MS/s, 8 bits, receive only), the HackRF One (1 to 6000 MHz, 20 MS/s, 8 bits, half duplex), the PlutoSDR (325 to 3800 MHz, about 4 MS/s sustained over USB, 12 bits, full duplex), and the ADALM-PHASER (10.0 to 10.5 GHz, digitized by a PlutoSDR).

    (a) For each task, name a course SDR that can do it, and give the specification that rules out each of the others.

    (i) Receive ship AIS at 162 MHz.

    (ii) Display the whole FM broadcast band, 88 to 108 MHz, at once.

    (iii) Transmit a 915 MHz test signal into a cable and receive it at the same time.

    (iv) Find the direction of a 10.3 GHz beacon.

    (b) Explain how an SDR differs from a hardware FM radio, and why the same RTL-SDR can decode both broadcast FM and aircraft ADS-B.

2. **The mixer and I and Q.** We set a PlutoSDR's center frequency, its LO, to 433.0 MHz, and a key fob transmits at 433.92 MHz.

   (a) Find the two frequencies at the mixer output, and say which one the low-pass filter keeps.

   kept:

   removed:

   (b) With a single real mixer, a second transmitter would also come out at 0.92 MHz. Find its frequency, and explain how the PlutoSDR's I and Q outputs tell the two apart.

3. **Sample rate and data rate.** A team captures a 10 MHz-wide test signal centered on 2437 MHz with a HackRF. The usable window is somewhat narrower than f_s, because the radio's filters roll off near its edges.

   (a) Find the lowest sample rate whose window just holds the signal. Then choose a rate 25% higher, to leave margin at the edges, and find the band that window covers.

   lowest: _____

   chosen: _____

   band: _____

   (b) GNU Radio stores each complex sample in 8 bytes. At 12.5 MS/s, find the data rate through the flowgraph and the size of a 10 s File Sink capture.

   rate: _____

   file: _____

   (c) The HackRF sends 8-bit I and 8-bit Q over USB. Find the USB data rate at 12.5 MS/s, and how many times larger the flowgraph's rate is.

   USB: _____

   ratio: _____

   (d) A teammate suggests the RTL-SDR instead. Give two separate reasons it cannot make this capture.

4. **Bits and clipping.** Use the L4 flowgraph, `L04-adc-bits.grc`, and its plots on the lesson page.

   (a) How many levels does the ADC block round to with 8 bits, the RTL-SDR's and HackRF's resolution, and with 12 bits, the PlutoSDR's?

   8 bits: ____

   12 bits: ____

   (b) At 8 bits the weak tone at -0.49 MHz is not visible. Switching the menu to 12 bits makes it appear, about 40 dB above the floor. Did the weak signal change? Describe what changed on the spectrum, and why.

   (c) On a real 8-bit radio, a strong local station sits at -10 dBFS and a weak signal we want is hidden in the floor. How far can the gain rise before the strong station clips? Would raising it that far reveal the weak signal? Explain, and name one thing that would help.

   (d) In the L4 flowgraph, name two things on the plots that show the ADC is clipping.

Documentation: _____