USAF ACADEMY
DEPARTMENT OF ELECTRICAL AND COMPUTER ENGINEERING
LESSONS 18–19 LAB - ADS-B AND AIS
Lab Packet
Spring 2027

Name: _____ **Section:** _____ **Date:** _____

Learning Objective 6.7: I can receive and decode ADS-B messages from aircraft transponders.
Learning Objective 6.8: I can receive and decode AIS messages from marine vessels.

This packet is the L18–L19 Lab, in three parts, and you turn it in once, complete, before Lesson 20. Do **Part 1** on your own before the lab period: run the lesson flowgraphs and work out the settings for the lab's AIS recording. **Part 2** is your own measurements, recorded in class: Questions 3 to 5 with an RTL-SDR and live aircraft, and Questions 6 to 8 on the lab's AIS recording. Do **Part 3** on your own after the lab: explain what you saw.

Grading. You submit the packet once, we grade it against Objectives 6.7 and 6.8 on the course's 1 / 0 scale, and you may revise it under course policy. Paste screenshots where a question asks for one.

Receive only. Nothing in this lab transmits. The RTL-SDR receives only, and the AIS recording is simulated, written by a GNU Radio flowgraph rather than captured from an antenna. Never connect the ADS-B or AIS generators to a transmitter: 1090 MHz and the AIS channels carry safety-of-life traffic.

The flowgraphs are on the L18 and L19 lesson pages: `L18-adsb-tx.grc`, `L18-adsb-rx.grc`, and `L19-ais-rx.grc`. The lab's AIS recording, `L18-L19-lab-ais.sigmf-data` and its `.sigmf-meta`, is on the lab page. Its meta file gives the datatype `cf32_le`, a sample rate of 192000, and a center frequency of 162025000.

Part 1: Pre-Lab (individual, before the lab period)

1. **Noise on the lesson recording.** Put `L18-adsb-tx.grc` and `L18-adsb-rx.grc` in one folder, run the generator once, then run the receiver.

   (a) Raise the Added noise slider from 0 to 0.28 in steps of 0.04, waiting about 10 s at each step, and record which aircraft are still in the table at each step. The table starts over each time the slider moves.

Added noise	0	0.04	0.08	0.12	0.16	0.20	0.24	0.28
Aircraft								

   (b) Paste a screenshot of the receiver at the step where only two aircraft remain.

2. AIS settings for the lab recording. Your AIS receiver in Question 6 plays `L18-L19-lab-ais.sigmf-data`, whose meta file is described above.

(a) Find the center frequency of each channel's Frequency Xlating FIR Filter.

A: _____

B: _____

(b) Choose `decim` for 48 kS/s after the filter, and find the samples per bit and the Quadrature Demod gain.

decim: _____

sps: _____

gain: _____

Part 2: Measurements (in class)

3. **Build an ADS-B front end.** Start GRC with an empty canvas and build the front end the lab page lists: a Soapy RTLSDR Source at 1090 MHz and 2 MS/s, Complex to Mag, and a triggered QT GUI Time Sink.

   (a) Paste a screenshot of your flowgraph on the GRC canvas. Every connection must be black, not red.

   (b) Paste a screenshot of the time sink frozen on a live preamble. Record the trigger level you chose, the noise floor, and the pulse heights of the strongest and weakest messages you saw.

4. **Live aircraft.** Copy the Mode S Decoder and its two Function Probes and QT GUI Labels from `L18-adsb-rx.grc` into your flowgraph, connect the decoder to Complex to Mag, and run it for 10 minutes with the antenna at a window.

   (a) Record up to five aircraft, and find each one on a public flight tracker such as ADS-B Exchange or FlightAware. Mark whether the tracker agrees.

ICAO	Callsign	Altitude (ft)	Speed (kt)	Latitude, longitude	Tracker agrees?

   (b) Paste a screenshot of the running window with the Messages label and the table.

5. Gain. With the decoder running live, set the RF gain to each value in turn, wait 60 s, and record the Messages label and the number of aircraft in the table.

RF gain (dB)	49.6	40	30	20	10
Passed parity in 60 s					
Aircraft					

(a) Describe which aircraft dropped out first as the gain fell, and how their altitude or position compared with the ones that stayed.

6. Build an AIS receiver. Start GRC with an empty canvas and build the two-channel receiver the lab page lists for `L18-L19-lab-ais.sigmf-data`, with your Question 2 settings and the Squelch slider at -30 dB.

(a) Paste a screenshot of your flowgraph on the GRC canvas. Every connection must be black, not red.

(b) Run it for one pass through the 5 s recording and record the Frames label. How many ships are in the table?

ships: [ ]

7. The ships. Read the decoder's printout in the GRC console and the table.

(a) Record every ship. The flag country comes from the first three digits of the MMSI, its Maritime Identification Digits; look them up in the ITU's MID table.

MMSI	Name	Flag	Destination	Latitude, longitude	Speed, course

(b) Copy one complete `!AIVDM` sentence from the console, paste it into `pyais` or an online AIVDM decoder, and record whether its fields match your table.

8. The squelch. Set the Squelch slider to each value in turn, wait for two passes through the recording, and mark which ships are in the table.

Squelch (dB)	-40	-30	-20	-15	-10	-5	0
Ships decoded							

(a) At -40 dB, describe the time plot and the Frames label, and explain why fewer frames pass there than at -30 dB.

Part 3: Writeup (individual, after the lab)

9. Analysis.

(a) Compare your two receivers. Explain why the ADS-B receiver needs only the magnitude of each sample, while the AIS receiver needs an FM demodulator and timing recovery.

(b) Use your squelch table to rank the four ships by received strength, and explain what each step of the table tells you. Then explain how you would choose the squelch for a real recording.

(c) Compare your live aircraft with the flight tracker. Explain any aircraft the tracker showed that you did not decode, and any differences in altitude or position.

Documentation: _____