

1)
// What will be the output if the choice entered by user is 50

```
#include<stdio.h>
int main ()
{
    enum {num1=50, num2, num3};
    int n1= 0, n2= 0, n3= 0;
    int ans;
    switch(num1)
    {
        case '2':
        case '1':

            ans = (n1=num3)-num2, n1++;
            switch(ans)
            {
                case 1:
                    --ans && (n2=num2), n2++;
                    break;
                case 2:
                    ans++ || (n3=num3), ++n3;
                    break;
            }
            printf ("%d %d %d %d", ans, n1, n2, n3);
            break;
        default:
            printf("invalid");
    }
    return 0;
}
```

- A) 0 53 1 0
- B) Invalid
- C) 0 3 1 0
- D) 0 2 0 1

Answer: A

2)

Syntax 1. typedef enum courses {DAC=1, KDAC, DMC, DESD, DBDA, DITISS} preferences;

Syntax 2. enum {DAC, KDAC=1, DMC, DESD, DBDA, DITISS} preferences;

Syntax 3. typedef enum {DAC, KDAC, DMC, DESD, DBDA=1, DITISS} preferences;

Which of the following is true for the above enum declarations.

A) For syntax 2, preferences is the name of the enum.

and for syntax 3, preferences is the variable of the enum.

B) For syntax 1, DAC=1 will give syntax error.

C) For syntax 2, preferences is the variable of the enum
and for syntax 3, preferences is the name of the enum.

D) For syntax 1, preferences is the variable of the enum.

Answer: C

3)

What will be the output of the following code?

```
#include<stdio.h>
enum demo {a, b=2, c};
int main ()
{
    printf ("%d %d %d %d\n", !c, ~a, b>>1, sizeof (a + b*c));
    return 0;
}
```

A) 1 1 2 4

B) 1 -1 1 6

C) 0 -1 4 4

D) 0 -1 1 4

Answer: D

4)

```
#include<stdio.h>
enum colors {red=-2, white, yellow, blue};
int main ()
{
    enum colors pink;
    pink = (red + yellow, red + white);

    enum colors orange;
    orange = (red + yellow),(red + white);

    printf ("%d %d %d %d\n", orange, pink, yellow, white);
    return 0;
}
```

- A) -6 -5 -4 -3
- B) Error: Expected '('
- C) -1 3 0 -1
- D) -2 -3 0 -1

Answer: D

5. What will the output of the following code?

```
#include<stdio.h>
typedef enum {APTI, C=11, DS, CPP} MODULE;
int main ()
{
    typedef MODULE SUBJECT;
    SUBJECT s1;
    s1 = APTI;
    printf("%d",~!!s1);
    return 0;
}
```

- A) -1
- B) 0
- C) -2
- D) 1

Answer: A