

Brazilian Synchrotron Light Laboratory

Gabriel Rezende

Overview of ID tracking methods

Campinas - SP
September 2026

Contents

1	Introduction	2
2	Eliaume formalism	2
2.1	Equations of motion	2
2.2	First-order solutions to the equations of motion	3
2.3	Second-order solutions to the equations of motion	3
2.4	Kickmaps	4
2.5	Symplecticity conditions	5
2.6	Application for a sinusoidal field	6
2.7	Application for an adjustable-phase undulator	6
3	Conclusion	6

1 Introduction

This document presents a detailed overview of insertion devices tracking methods. The first section is an introduction to the Ellaume formalism, derivations and predicted effects on the beam. The second section presents the tracking method based on Runge-Kutta integration and compares results with those obtained from the Ellaume formalism. Finally, last section presents an symplectic integration method proposed by Wu, Forest and Robin and also compares the results with the two first methods. The main goal of this document is to provide a complete overview of the methods used to track insertion devices in the SIRIUS storage ring and to compare their results.

2 Ellaume formalism

2.1 Equations of motion

Using SIRIUS coordinate system, the equations of motion for a particle in a magnetic field can be expressed as:

$$\frac{d\vec{p}}{dt} = q\vec{v} \times \vec{B} \quad (1)$$

$\vec{p}$ is the momentum of the electron, $q = -e$ is the electron's charge, $\vec{v}$ is its velocity, and $\vec{B}$ is the magnetic field along the electron's path. The velocity can be written as:

$$\vec{v} = \frac{dx}{dt}\hat{x} + \frac{dy}{dt}\hat{y} + \frac{ds}{dt}\hat{s} = \left(\frac{ds}{dt}\right) \left(\frac{dx}{ds}\hat{x} + \frac{dy}{ds}\hat{y} + \hat{s}\right) \quad (2)$$

defining

$$x' := \frac{dx}{ds}, \quad y' := \frac{dy}{ds} \quad (3)$$

and assuming the electron is ultra-relativistic, we have:

$$c^2 = \vec{v}^2 = \left(\frac{ds}{dt}\right)^2 (x'^2 + y'^2 + 1) \quad (4)$$

then, it is found the following expression for ds/dt :

$$\frac{ds}{dt} = \frac{c}{\sqrt{x'^2 + y'^2 + 1}} \quad (5)$$

which gives the expression for the velocity:

$$\vec{v} = \frac{c}{\sqrt{x'^2 + y'^2 + 1}} (x'\hat{x} + y'\hat{y} + \hat{s}) \quad (6)$$

Substituting this expression into the Lorentz force equation, we have:

$$\frac{d\vec{p}}{dt} = \frac{-ec}{\sqrt{x'^2 + y'^2 + 1}} [(y'B_s - B_y)\hat{x} - (x'B_s - B_x)\hat{y} + (x'B_y - y'B_x)\hat{s}] \quad (7)$$

Keeping the result of equation (7), now let's express the momentum of a relativistic electron:

$$\vec{p} = \gamma m_e \vec{v} = \frac{\gamma m_e c}{\sqrt{x'^2 + y'^2 + 1}} (x'\hat{x} + y'\hat{y} + \hat{s}) \quad (8)$$

and it's time derivative:

$$\frac{d\vec{p}}{dt} = \frac{ds}{dt} \frac{d\vec{p}}{ds} = \frac{\gamma m_e c^2}{\sqrt{x'^2 + y'^2 + 1}} \left[-(x'^2 + y'^2 + 1)^{-3/2} (x'x'' + y'y'') (x'\hat{x} + y'\hat{y} + \hat{s}) + \frac{x''\hat{x} + y''\hat{y}}{\sqrt{x'^2 + y'^2 + 1}} \right] \quad (9)$$

Then, using the magnetic rigidity $R = \gamma m_e c / e$ and equating the $\hat{s}$ component of equations (7) and (9), we have:

$$\frac{x'x'' + y'y''}{(x'^2 + y'^2 + 1)^{3/2}} = \frac{1}{R} (x'B_y - y'B_x) \quad (10)$$

substituting equation above into equation (9), the remaining two vector components are related by

$$-\frac{1}{R} (x'B_y - y'B_x) (x'\hat{x} + y'\hat{y}) + \frac{x''\hat{x} + y''\hat{y}}{\sqrt{x'^2 + y'^2 + 1}} = \frac{-1}{R} [(y'B_s - B_y)\hat{x} + (x'B_s - B_x)\hat{y}] \quad (11)$$

Solving this equation for x'' and y'' , we have the following equations of motion:

$$\begin{aligned} x'' &= -\frac{\sqrt{x'^2 + y'^2 + 1}}{R} [x'y'B_x - (x'^2 + 1)B_y + y'B_s] \\ y'' &= -\frac{\sqrt{x'^2 + y'^2 + 1}}{R} [(y'^2 + 1)B_x - x'y'B_y - x'B_s] \end{aligned} \quad (12)$$

2.2 First-order solutions to the equations of motion

Assuming the transverse velocity of the electrons is zero, the equations of motion reduce to:

$$\begin{aligned} x'' &= \frac{1}{R} B_y \\ y'' &= -\frac{1}{R} B_x \end{aligned} \quad (13)$$

The integration of equation (13) leads to:

$$\begin{aligned} x'(s) &= \frac{1}{R} \int_{-\infty}^s B_y(0, 0, s') ds' \\ y'(s) &= -\frac{1}{R} \int_{-\infty}^s B_x(0, 0, s') ds' \\ x(s) &= \frac{1}{R} \int_{-\infty}^s \int_{-\infty}^{s'} B_y(0, 0, s'') ds'' ds' \\ y(s) &= -\frac{1}{R} \int_{-\infty}^s \int_{-\infty}^{s'} B_x(0, 0, s'') ds'' ds' \end{aligned} \quad (14)$$

These are the so called field integrals. These equations are a good approximation for elements like quadrupoles, sextupoles and correctors, but for a well designed insertion device, the field integrals evaluated in the whole ID are close to zero, and thus the first-order solutions are not enough to describe the net effect of the undulator on the electron beam. In this case, it is necessary to consider the second-order solutions to the equations of motion.

2.3 Second-order solutions to the equations of motion

In the second-order solutions we will keep terms only to the second order of the inverse of the magnetic rigidity $1/R^2$. Looking at equations (14) we can see that all phase space variables are

proportional to $1/R$, so we will keep terms only to the first order of the phase space variables, then the equations of motion become:

$$\begin{aligned} x'' &= \frac{1}{R} (y' B_s - B_y) \\ y'' &= -\frac{1}{R} (B_x - x' B_s) \end{aligned} \quad (15)$$

Next, we are going to Taylor expand the magnetic field around the reference trajectory.

$$\begin{aligned} B_y(x, y, s) &= B_y(0, 0, s) + x \frac{\partial B_y}{\partial x}(0, 0, s) + y \frac{\partial B_y}{\partial y}(0, 0, s) + \mathcal{O}(2) \\ B_x(x, y, s) &= B_x(0, 0, s) + x \frac{\partial B_x}{\partial x}(0, 0, s) + y \frac{\partial B_x}{\partial y}(0, 0, s) + \mathcal{O}(2) \end{aligned} \quad (16)$$

then, combining equations (16) and (15) we obtain the following form for the equations of motion:

$$\begin{aligned} x'' &= -\frac{1}{R} \left[y' B_s^0 - B_y^0 - x \frac{\partial B_y^0}{\partial x} - y \frac{\partial B_y^0}{\partial y} \right] \\ y'' &= -\frac{1}{R} \left[B_x^0 + x \frac{\partial B_x^0}{\partial x} + y \frac{\partial B_x^0}{\partial y} - x' B_s^0 \right] \end{aligned} \quad (17)$$

where the superscript 0 denotes the evaluation in the reference point $(0, 0, s)$. When we insert the first-order solutions (which are valid for the electron motion inside the device, since the field integrals are close to zero only when we integrate over the whole ID), into equation (17), and integrate over the whole ID we obtain the following expressions for kick experienced by the electron:

$$\begin{aligned} \Delta x' &= \int_{-\infty}^{\infty} x'' ds = \frac{1}{R^2} \int_{-\infty}^{\infty} \left[B_s^0 \int_{-\infty}^s B_x^0 ds' + \frac{\partial B_y^0}{\partial x} \int_{-\infty}^s \int_{-\infty}^{s'} B_y^0 ds'' ds' - \frac{\partial B_y^0}{\partial y} \int_{-\infty}^s \int_{-\infty}^{s'} B_x^0 ds'' ds' \right] ds \\ \Delta y' &= \int_{-\infty}^{\infty} y'' ds = \frac{1}{R^2} \int_{-\infty}^{\infty} \left[B_s^0 \int_{-\infty}^s B_y^0 ds' + \frac{\partial B_x^0}{\partial y} \int_{-\infty}^s \int_{-\infty}^{s'} B_x^0 ds'' ds' - \frac{\partial B_x^0}{\partial x} \int_{-\infty}^s \int_{-\infty}^{s'} B_y^0 ds'' ds' \right] ds \end{aligned} \quad (18)$$

Equation (18) gives the kick experienced by an electron due to its wiggling motion through the ID, which is a kickmap. However, the kickmap equation is not in its final form, it is possible to express the kickmap in terms of a potential called Kickmap Potential.

2.4 Kickmaps

In order to transform equation (18) in the usual form, it is necessary to make use of Maxwell equations and integration by parts. First, consider the divergence of the magnetic field in free space $\vec{\nabla} \cdot \vec{B} = 0$

$$\frac{\partial B_x^0}{\partial x} + \frac{\partial B_y^0}{\partial y} + \frac{\partial B_s^0}{\partial s} = 0 \quad (19)$$

which allow us to write B_s as function of the transverse components of the magnetic field:

$$B_s^0 = \int_{-\infty}^s \frac{\partial B_s^0}{\partial s'} ds' = - \int_{-\infty}^s \frac{\partial B_x^0}{\partial x} ds' - \int_{-\infty}^s \frac{\partial B_y^0}{\partial y} ds' \quad (20)$$

Now, consider the integration by parts formula:

$$\int_a^b f(s)g'(s)ds = [f(s)g(s)]_a^b - \int_a^b f'(s)g(s)ds \quad (21)$$

then, the second term of equation (18) can be rewritten as, where it was used also the fact that the second integral of the transverse field components are zero.

$$\begin{aligned} \int_{-\infty}^{\infty} \left[\frac{\partial B_y^0}{\partial x} \int_{-\infty}^s \int_{-\infty}^{s'} B_y^0 ds'' ds' \right] ds &= \left[\int_{-\infty}^s \frac{\partial B_y^0}{\partial x} ds' \int_{-\infty}^s \int_{-\infty}^{s'} B_y^0 ds'' ds' \right]_{-\infty}^{\infty} \\ &\quad - \int_{-\infty}^{\infty} \left[\int_{-\infty}^s \frac{\partial B_y^0}{\partial x} ds' \int_{-\infty}^s B_y^0 ds' \right] ds \\ &= - \int_{-\infty}^{\infty} \left[\int_{-\infty}^s \frac{\partial B_y^0}{\partial x} ds' \int_{-\infty}^s B_y^0 ds' \right] ds \end{aligned} \quad (22)$$

the same simplification can be done for the third term of equation (18):

$$\int_{-\infty}^{\infty} \left[\frac{\partial B_y^0}{\partial y} \int_{-\infty}^s \int_{-\infty}^{s'} B_x^0 ds'' ds' \right] ds = - \int_{-\infty}^{\infty} \left[\int_{-\infty}^s \frac{\partial B_y^0}{\partial y} ds' \int_{-\infty}^s B_x^0 ds' \right] \quad (23)$$

and considering equations (20), (22) and (23), we can rewrite the horizontal kick as:

$$\begin{aligned} \Delta x' &= \frac{1}{R^2} \int_{-\infty}^{\infty} \left[- \int_{-\infty}^s \frac{\partial B_x^0}{\partial x} ds' \int_{-\infty}^s B_x^0 ds' - \int_{-\infty}^s \frac{\partial B_y^0}{\partial y} ds' \int_{-\infty}^s B_x^0 ds' \right. \\ &\quad \left. - \int_{-\infty}^s \frac{\partial B_y^0}{\partial x} ds' \int_{-\infty}^s B_y^0 ds' + \int_{-\infty}^s \frac{\partial B_y^0}{\partial y} ds' \int_{-\infty}^s B_y^0 ds' \right] \\ &= - \frac{1}{R^2} \int_{-\infty}^{\infty} \frac{\partial}{\partial x} \left[\left(\int_{-\infty}^s B_x^0 ds' \right)^2 + \left(\int_{-\infty}^s B_y^0 ds' \right)^2 \right] ds \end{aligned} \quad (24)$$

the vertical kick can also be written in the following form:

$$\Delta y' = - \frac{1}{R^2} \int_{-\infty}^{\infty} \frac{\partial}{\partial y} \left[\left(\int_{-\infty}^s B_x^0 ds' \right)^2 + \left(\int_{-\infty}^s B_y^0 ds' \right)^2 \right] ds \quad (25)$$

Equations (24) and (25) can be expressed in terms of a potential $\Phi(x, y)$, called Kickmap potential, as follows:

$$\Phi(x, y) = \int_{-\infty}^{\infty} \left(\int_{-\infty}^s B_x(x, y, s' ds') \right)^2 + \left(\int_{-\infty}^s B_y(x, y, s' ds') \right)^2 ds \quad (26)$$

$$\begin{aligned} \Delta x' &= - \frac{1}{R^2} \frac{\partial \Phi}{\partial x} \\ \Delta y' &= - \frac{1}{R^2} \frac{\partial \Phi}{\partial y} \end{aligned} \quad (27)$$

2.5 Symplecticity conditions

Once we obtained the kickmap in terms of the kickmap potential, we can check if the kickmap is symplectic.

The symplecticity conditions for a 2n-D map are given by

$$J^T S J = S \quad (28)$$

where S is the $2n \times 2n$ symplectic matrix, defined in block form as

$$S = \text{diag}_{k=1,\dots,n} \left[\begin{pmatrix} 0 & 1 \\ -1 & 0 \end{pmatrix} \right]. \quad (29)$$

where I_n denotes the $n \times n$ identity matrix. J is the Jacobian matrix of the map. Considering a $4D$ map for the kickmap, using equation (27), the symplecticity condition (28) can be expressed as:

$$\frac{\partial^2 \phi}{\partial x \partial y} = \frac{\partial^2 \phi}{\partial y \partial x} \quad (30)$$

The Schwarz theorem states that if the second partial derivatives of a function are continuous, then the mixed partial derivatives are equal. Thus, for any kickmap potential $\Phi(x, y)$ with continuous second partial derivatives, the kickmap is symplectic, that is the case for sinusoidal functions and also polynoms, which are used to describe the kickmap potential.

Considering the $6D$ case, where $\Delta z = 0$ and $\Delta \delta = 0$, the symplecticity condition is also satisfied as long as the symplecticity condition for the $4D$ case is satisfied. This can be seen by writing the Jacobian matrix for the $6D$ case as:

$$J = \begin{pmatrix} J_{4D} & 0 \\ 0 & I_2 \end{pmatrix} \quad (31)$$

2.6 Application for a sinusoidal field

2.7 Application for an adjustable-phase undulator

3 Conclusion

oi