Neural Robust Control on Lie Groups Using Contraction Methods (Extended Version)

Yi Lok Lo[1], Longhao Qian[1] and Hugh H.T. Liu[1]

***Abstract*— In this paper, we propose a learning framework for synthesizing a certified controller for dynamical systems evolving on a Lie Group. A robust control contraction metric (RCCM) and a neural feedback controller are jointly trained to enforce contraction conditions for states defined in a Lie group. Sufficient conditions are derived for the existence of such an RCCM and neural controller, ensuring that the geometric constraints imposed by the manifold structure are respected while guaranteeing that the output trajectories remain bounded within a disturbance–dependent tube. As a case study, a feedback controller for a quadrotor is designed using the proposed framework and its performance is evaluated using numerical simulation and compared with a geometric controller.**

***Index Terms*— Contraction analysis, learning-based control, robust control, nonlinear systems, Lie Groups**

I. Introduction

Contraction analysis provides a powerful framework for studying the incremental stability of nonlinear dynamical systems, establishing global stability properties through differential dynamics [1]. Building on this foundation, control contraction metrics (CCMs) provide constructive conditions for synthesizing stabilizing feedback controllers for nonlinear systems [2]. To address robustness, robust control contraction metrics (RCCMs) extend the CCM framework to systems subject to disturbances. Prior works have established bounds on $\mathcal{L}_\infty$ and $\mathcal{L}_2$ gains between disturbances and trajectory deviations [3], [4]. Furthermore, disturbance estimation techniques have been integrated with contraction-based methods to learn and compensate for model uncertainties [5].

In parallel, rapid advances in machine learning have enabled learning-based approaches for synthesizing controllers for complex nonlinear systems using reinforcement learning [6] and deep neural networks [7]. In particular, several learning-based CCM frameworks have been developed, offering interpretable and certifiable guarantees [8], [9], [10].

Existing CCM and RCCM formulations are primarily developed for systems in Euclidean spaces, yet many robotic applications contain states evolving on manifolds, such as attitudes of aerial vehicles or joint configurations of manipulators. A common workaround uses local coordinates, such as Euler angles [8], [11], but introduces singularities and distortions that can degrade control performance. In contrast, Lie group representations provide globally valid models. Recent works have extended contraction control to submanifolds embedded in Euclidean spaces [12], [13]. In this paper, we present an approach towards certified robust trajectory tracking for systems evolving on Lie groups using a learning framework. The contributions of this paper are summarized as follows:

1) We formulate conditions for RCCMs on Lie groups such that the closed-loop system exhibits input-output stability with a bounded $\mathcal{L}$-infinity gain. Conditions for the existence of solutions are provided.
2) We develop a learning-based framework that jointly synthesizes a neural feedback controller and an RCCM on Lie groups. A quadrotor is used as a case study, and numerical simulations demonstrate robust trajectory tracking capabilities of the learned controller.

Notations: Given a manifold $\mathcal{X}$, $T\mathcal{X}$ and $T_{\boldsymbol{x}}\mathcal{X}$ represent the tangent bundle and tangent space at $\boldsymbol{x} \in \mathcal{X}$ respectively. $\boldsymbol{I}_n$ and $\mathbf{0}$ denote an $n \times n$ identity matrix and a zero matrix of compatible dimensions respectively. For symmetric matrices $\boldsymbol{P}$ and $\boldsymbol{Q}$, $\boldsymbol{P} \succ \boldsymbol{Q}$ ($\boldsymbol{P} \succeq \boldsymbol{Q}$) means $\boldsymbol{P} - \boldsymbol{Q}$ is positive definite (semi-definite). $\langle \boldsymbol{A} \rangle$ denotes $\boldsymbol{A} + \boldsymbol{A}^\top$ for a square matrix $\boldsymbol{A}$, and $\mathrm{vec}(\boldsymbol{B})$ denotes the row-major vectorization of a matrix $\boldsymbol{B}$. $\mathrm{diag}(\cdot)$ denotes the (block-)diagonal matrix operator. Let $\boldsymbol{\phi}^\wedge$ be the skew-symmetric operator for $\boldsymbol{\phi} \in \mathbb{R}^3$ such that $\boldsymbol{\phi}^{\wedge\top} = -\boldsymbol{\phi}^\wedge$. Let $\boldsymbol{S}^\vee$ be the vee-map for a skew-symmetric matrix $\boldsymbol{S}^\top = -\boldsymbol{S} \in \mathbb{R}^{3\times 3}$. For a smooth function $\boldsymbol{Q}(\boldsymbol{x})$, $\partial_{\boldsymbol{f}} \boldsymbol{Q}(\boldsymbol{x}) = \sum_j \frac{\partial \boldsymbol{Q}}{\partial x_j} \boldsymbol{f}_j$ denotes its directional derivative along vector field $\boldsymbol{f}$. The Euclidean 2-norm is denoted as $\|\cdot\|$, and the $\mathcal{L}_\infty$ norm of a function $\boldsymbol{x}(t)$ is defined as $\|\boldsymbol{x}(t)\|_{\mathcal{L}_\infty} = \sup_{t\geq 0} \|\boldsymbol{x}(t)\|$. The truncated $\mathcal{L}_\infty$ norm is defined as $\|\boldsymbol{x}(t)\|_{\mathcal{L}_\infty^{[0,T]}} = \sup_{0\leq t\leq T} \|\boldsymbol{x}(t)\|$. For a positive integer m, denote the set $\mathbb{Z}_m := \{1, ..., m\}$. The vectors $\boldsymbol{e}_i$, for $i \in \mathbb{Z}_3$, represent the Euclidean basis in $\mathbb{R}^3$.

II. Problem statement and Preliminaries

Consider the following nonlinear control-affine system

$$\begin{aligned} \dot{\boldsymbol{x}} &= \boldsymbol{f}(\boldsymbol{x}) + \boldsymbol{B}(\boldsymbol{x})\boldsymbol{u} + \boldsymbol{B}_w(\boldsymbol{x})\boldsymbol{w} \\ \boldsymbol{z} &= \boldsymbol{g}(\boldsymbol{x}, \boldsymbol{u}) \end{aligned} \tag{1}$$

with the state $\boldsymbol{x} \in \mathcal{X} \subseteq \mathbb{R}^n$, control $\boldsymbol{u} \in \mathbb{R}^m$, disturbance $\boldsymbol{w} \in \mathbb{R}^p$ and output $\boldsymbol{z} \in \mathbb{R}^l$. $\boldsymbol{f}$, $\boldsymbol{B}$ and $\boldsymbol{B}_w$ are continuously differentiable vector/matrix functions with compatible dimensions, and matrices $\boldsymbol{B}(\boldsymbol{x})$ and $\boldsymbol{B}_w(\boldsymbol{x})$ have full column rank. We use $\boldsymbol{b}_i$ and $\boldsymbol{b}_{w,j}$ to denote the ith column of $\boldsymbol{B}(\boldsymbol{x})$ and j^{th} column of $\boldsymbol{B}_w(\boldsymbol{x})$ respectively. The state space $\mathcal{X}$ is assumed to be a Lie group, which can be viewed as a submanifold embedded in a higher-dimensional Euclidean

[1]The authors are with the Institute for Aerospace Studies, University of Toronto, 4925 Dufferin St, North York, ON M3H 5T5, Canada enoch.lo@mail.utoronto.ca, longhao.qian@mail.utoronto.ca, hugh.liu@utoronto.ca

space (e.g. $SO(n) = \{\boldsymbol{R} \in \mathbb{R}^{n\times n} \mid \boldsymbol{R}^\top \boldsymbol{R} = \boldsymbol{I}_n, \det \boldsymbol{R} = 1\}$). The state space of the system can be represented as

$$\mathcal{X} = \{\boldsymbol{x} \in \mathbb{R}^n \mid \boldsymbol{h}(\boldsymbol{x}) = \boldsymbol{0}\}, \tag{2}$$

where $\boldsymbol{h} : \mathbb{R}^n \to \mathbb{R}^{n-q}$ is a smooth constraint function. Hence, $\mathcal{X}$ can be regarded as a q-dimensional manifold embedded in $\mathbb{R}^n$. To ensure trajectories remain on $\mathcal{X}$, it is necessary and sufficient that the vector fields $\boldsymbol{f}, \boldsymbol{b}_i\,(i \in \mathbb{Z}_m)$, $\boldsymbol{b}_{w,j}\,(j \in \mathbb{Z}_p)$ be tangent to the manifold $\mathcal{X}$. Equivalently, they must satisfy the transversality conditions. For all $\boldsymbol{x} \in \mathcal{X}$,

$$\partial_{\boldsymbol{f}} \boldsymbol{h}(\boldsymbol{x}) = \boldsymbol{0};\ \partial_{\boldsymbol{b}_i} \boldsymbol{h}(\boldsymbol{x}) = \boldsymbol{0};\ \partial_{\boldsymbol{b}_{w,j}} \boldsymbol{h}(\boldsymbol{x}) = \boldsymbol{0}. \tag{3}$$

It is well-known that any Lie group is parallelizable, admitting a set of global left-invariant vector fields that trivializes its tangent bundle [14]. Therefore, the span of the tangent bundle can be represented as a set of vector fields $\{\boldsymbol{s}_1, ..., \boldsymbol{s}_q\}$. For Lie groups that can be characterized in the general form $G_c \times G_m \times \mathbb{R}^a$, where G_c is a compact Lie group and G_m is a matrix Lie group, a smooth function $\boldsymbol{S}(\boldsymbol{x}) := \left[\boldsymbol{s}_1, ..., \boldsymbol{s}_q\right] \in \mathbb{R}^{n\times q}$ can be defined such that

$$\begin{aligned} &\forall \boldsymbol{x} \in \mathcal{X}, \forall \boldsymbol{v} \in \mathbb{R}^q,\ \exists \boldsymbol{S}(\boldsymbol{x}) : \mathcal{X} \to \mathbb{R}^{n\times q} \\ &\qquad \text{s.t. } \boldsymbol{S}(\boldsymbol{x})\boldsymbol{v} \in T_{\boldsymbol{x}}\mathcal{X} \end{aligned} \tag{4}$$

That is, any tangent vector at $\boldsymbol{x}$ with extrinsic coordinates (in the Euclidean space the manifold embedded) can be obtained from linear combinations of the vector fields $\{\boldsymbol{s}_1, ..., \boldsymbol{s}_q\}$, where $\boldsymbol{v}$ is the intrinsic representation of said tangent vector.

Assumption 1: The system defined in (1) evolves on the Lie group $\mathcal{X}$ in the general form $G_c \times G_m \times \mathbb{R}^a$ such that the transversality conditions in (3) are satisfied at all times. Moreover, the tangent bundle $T\mathcal{X}$ is spanned by smooth vector fields $\boldsymbol{S}(\boldsymbol{x})$, and $\boldsymbol{S}^\top \boldsymbol{S}$ is uniformly bounded.

For systems that satisfy Assumption 1, given a nominal solution $(\boldsymbol{x}^*, \boldsymbol{u}^*, \boldsymbol{w}^*, \boldsymbol{z}^*)$ that satisfies (1), this paper focuses on designing a feedback controller in the form

$$\boldsymbol{u} = \boldsymbol{k}(\boldsymbol{x}, \boldsymbol{x}^*) + \boldsymbol{u}^*, \tag{5}$$

where $\boldsymbol{k} : \mathcal{X} \times \mathcal{X} \to \mathbb{R}^m$ and $\boldsymbol{k}(\boldsymbol{x}, \boldsymbol{x}) = \boldsymbol{0}$. The goal is to minimize the universal $\mathcal{L}_\infty$ gain from disturbance deviation $\boldsymbol{w} - \boldsymbol{w}^*$ to output deviation $\boldsymbol{z} - \boldsymbol{z}^*$. Note that $\boldsymbol{w}^*$ is the nominal disturbance vector including the special case $\boldsymbol{w}^*(t) = \boldsymbol{0}$. In practice, $\boldsymbol{w}^*(t)$ can be disturbance estimates from some disturbance observer. We define the universal $\mathcal{L}_\infty$ gain formally in Definition 1.

Definition 1: A control system (1) with feedback controller (5) achieves a $\mathcal{L}_\infty$ gain bound of α, if for any nominal trajectory $\boldsymbol{x}^*, \boldsymbol{w}^*, \boldsymbol{z}^*$ satisfying (1), any initial condition $\boldsymbol{x}(0)$, any $\boldsymbol{w}$ such that $\|\boldsymbol{w}\|_{\mathcal{L}_\infty} < \infty$ and for any $T > 0$, the condition

$$\|\boldsymbol{z} - \boldsymbol{z}^*\|^2_{\mathcal{L}_\infty^{[0,T]}} \le \alpha^2 \|\boldsymbol{w} - \boldsymbol{w}^*\|^2_{\mathcal{L}_\infty^{[0,T]}} + \beta(\boldsymbol{x}(0), \boldsymbol{x}^*(0)) \tag{6}$$

holds for a function $\beta(\boldsymbol{x}_1, \boldsymbol{x}_2) \ge 0$ and $\beta(\boldsymbol{x}, \boldsymbol{x}) = 0$.

In the case where $\boldsymbol{z}$ lives in the Lie group $\mathcal{Z} \subseteq \mathcal{X} \times \mathbb{R}^m$, output deviations can be measured using Riemannian distances under some Riemannian metrics on $\mathcal{Z}$.

A. Preliminaries

The CCM approach is a framework for designing feedback controllers for control-affine systems that provide incremental stability guarantees through analysis of the associated differential dynamics [2]. When disturbances are considered, the RCCM framework proposed in [4] further analyzes the differential dynamics associated with (1), which is given by

$$\begin{aligned} \delta\dot{\boldsymbol{x}} &= \boldsymbol{A}(\boldsymbol{x}, \boldsymbol{u}, \boldsymbol{w})\delta\boldsymbol{x} + \boldsymbol{B}(\boldsymbol{x})\delta\boldsymbol{u} + \boldsymbol{B}_w(\boldsymbol{x})\delta\boldsymbol{w} \\ \delta\boldsymbol{z} &= \boldsymbol{C}(\boldsymbol{x}, \boldsymbol{u})\delta\boldsymbol{x} + \boldsymbol{D}(\boldsymbol{x}, \boldsymbol{u})\delta\boldsymbol{u} \end{aligned} \tag{7}$$

where $\boldsymbol{A}(\boldsymbol{x}, \boldsymbol{u}, \boldsymbol{w}) = \frac{\partial \boldsymbol{f}}{\partial \boldsymbol{x}} + \sum_{i=1}^m \frac{\partial \boldsymbol{b}_i}{\partial \boldsymbol{x}} u_i + \sum_{j=1}^p \frac{\partial \boldsymbol{b}_{w,j}}{\partial \boldsymbol{x}} w_j$, $\boldsymbol{C}(\boldsymbol{x}, \boldsymbol{u}) = \frac{\partial \boldsymbol{g}}{\partial \boldsymbol{x}}$ and $\boldsymbol{D}(\boldsymbol{x}, \boldsymbol{u}) = \frac{\partial \boldsymbol{g}}{\partial \boldsymbol{u}}$, with u_i and w_j denoting the ith element of $\boldsymbol{u}$ and j^{th} element of $\boldsymbol{w}$ respectively.

The RCCM approach for a system with state vectors that live in Euclidean space ($\mathcal{X} = \mathbb{R}^n$) involves finding a Riemannian metric $\boldsymbol{M}(\boldsymbol{x}) : \mathbb{R}^n \to \mathbb{R}^{n\times n}$ and feedback controller in the form of (5) such that $\boldsymbol{M}(\boldsymbol{x})$ is uniformly bounded (i.e., $\underline{m}\boldsymbol{I}_n \preceq \boldsymbol{M}(\boldsymbol{x}) \preceq \overline{m}\boldsymbol{I}_n$) and the inner product of tangent vectors with respect to the metric $V(\boldsymbol{x}, \delta\boldsymbol{x}) = \delta\boldsymbol{x}^\top \boldsymbol{M}(\boldsymbol{x})\delta\boldsymbol{x}$ decays to some disturbance-dependant bound. Under such conditions, the metric $\boldsymbol{M}$ is termed an RCCM, and its associated feedback controller will then guarantee H_∞-like input-output stability for the closed-loop system [4].

However, for states that live in a general Lie group, constraints are posed on both the states and differential states, such that $\boldsymbol{x} \in \mathcal{X}$, $\delta\boldsymbol{x} \in T\mathcal{X}$. [12] laid the groundwork to search for a CCM that respects the inherent geometry of the underlying submanifold $\mathcal{X}$. First, tangent vectors of the system can be represented with intrinsic coordinates following (4). Therefore, for systems that satisfy Assumption 1, we are able to find smooth functions $\boldsymbol{v} \in \mathbb{R}^q$, $\boldsymbol{E}(\boldsymbol{x}) \in \mathbb{R}^{q\times m}$ and $\boldsymbol{E}_w(\boldsymbol{x}) \in \mathbb{R}^{q\times p}$ such that

$$\delta\boldsymbol{x} = \boldsymbol{S}\boldsymbol{v},\ \boldsymbol{B} = \boldsymbol{S}\boldsymbol{E},\ \boldsymbol{B}_w = \boldsymbol{S}\boldsymbol{E}_w. \tag{8}$$

Moreover, instead of finding a CCM $\boldsymbol{M}(\boldsymbol{x}) \in \mathbb{R}^{n\times n}$ that respects the geometry of $\mathcal{X}$, it is proposed to search for a lower-dimensional metric $\boldsymbol{\mathcal{M}}(\boldsymbol{x}) : \mathbb{R}^n \to \mathbb{R}^{q\times q}$ and project it to its full dimensions using

$$\boldsymbol{M}(\boldsymbol{x}) = \boldsymbol{P}_S(\boldsymbol{x})\boldsymbol{\mathcal{M}}(\boldsymbol{x})\boldsymbol{P}_S^\top(\boldsymbol{x}), \tag{9}$$

where $\boldsymbol{P}_S = \boldsymbol{S}(\boldsymbol{S}^\top\boldsymbol{S})^{-1}$ is the projection operator. The existence and smoothness of $\boldsymbol{P}_S(\boldsymbol{x})$ are guaranteed by Assumption 1. $\boldsymbol{\mathcal{M}}(\boldsymbol{x})$ should be uniformly bounded such that there exist two positive constants $\underline{\mathfrak{m}}, \overline{\mathfrak{m}}$ satisfying

$$\underline{\mathfrak{m}}\boldsymbol{I}_q \preceq \boldsymbol{\mathcal{M}}(\boldsymbol{x}) \preceq \overline{\mathfrak{m}}\boldsymbol{I}_q. \tag{10}$$

With this method, the tangent vectors respect the constraints from the tangent bundle and the Riemannian metric remains a smooth varying inner product on the tangent space of the state manifold $\mathcal{X}$, such that $\forall \delta\boldsymbol{x} \in T\mathcal{X}$

$$V = \boldsymbol{v}^\top \boldsymbol{S}^\top \boldsymbol{P}_S \boldsymbol{\mathcal{M}} \boldsymbol{P}_S^\top \boldsymbol{S}\boldsymbol{v} = \boldsymbol{v}^\top \boldsymbol{\mathcal{M}}\boldsymbol{v}. \tag{11}$$

Some notations on Riemannian geometry are introduced before moving on to the main results. Given a Lie group state space manifold $\mathcal{X}$, the set of all possible paths between a and b along $\mathcal{X}$ is denoted as $\Gamma_{\mathcal{X}}(a, b)$, where each $\boldsymbol{c} \in \Gamma_{\mathcal{X}}(a, b)$

represents a smooth mapping $\boldsymbol{c}(s) : [0,1] \to \mathcal{X}$ satisfying $\boldsymbol{c}(0) = a$, $\boldsymbol{c}(1) = b$. Therefore, $\boldsymbol{c}(s) \in \mathcal{X}$ and $\frac{\partial \boldsymbol{c}}{\partial s}(s) = \boldsymbol{S}(\boldsymbol{c}(s))\boldsymbol{v} \in T\mathcal{X}$ for all $s \in [0,1]$. Given the state manifold $\mathcal{X}$ equipped with a Riemannian metric $\boldsymbol{\mathcal{M}}$, the Riemannian energy of a path $\boldsymbol{c}$ is defined as $\mathcal{E}(\boldsymbol{c}) = \int_0^1 \boldsymbol{v}^\top \boldsymbol{\mathcal{M}}(\boldsymbol{c}(s))\boldsymbol{v}\, ds$. The notation $\mathcal{E}(a,b)$ also denotes the minimum energy of a path joining a, b such that $\mathcal{E}(a,b) = \inf_{\boldsymbol{c}\in\Gamma_{\mathcal{X}}(a,b)} \mathcal{E}(\boldsymbol{c})$.

Some preliminaries on Matrix Lie groups are also provided. We define $\mathrm{Tr}(\cdot)$ to be the matrix trace and $\otimes$ as the Kronecker product. $\cdot^\wedge$ and $\cdot^\vee$ denote hat-map and vee-map respectively, which maps a Euclidean vector to its Lie algebra linearly, and vice versa. We consider Lie groups in the form $\mathbb{R}^a \times G_c \times G_m$, where G_c is a compact Lie group and G_m is a matrix Lie group. As compact Lie groups are isomorphic to matrix Lie groups, given a matrix Lie group $\mathcal{G}$ with matrix elements $\boldsymbol{G} \in \mathcal{G}$ embedded in $\mathbb{R}^{d\times d}$, representing a dimension q_G manifold, there exists an associated Lie algebra $\mathfrak{g}$ diffeomorphic to $\mathbb{R}^{q_G}$. We then define a matrix $\boldsymbol{E}_{vec} \in \mathbb{R}^{d^2\times q_G}$ such that each column $\boldsymbol{E}_{vec,i}$ represents the vectorized basis vector

$$\boldsymbol{E}_{vec,i} = \mathrm{vec}(\boldsymbol{e}_i^\wedge) \tag{12}$$

for all $i \in \mathbb{Z}_{q_G}$. Therefore, for each $\boldsymbol{\Xi} \in \mathfrak{g}$, we can find $\boldsymbol{v} \in \mathbb{R}^{q_G}$ such that $\mathrm{vec}(\boldsymbol{\Xi}) = \boldsymbol{E}_{vec}\boldsymbol{v}$, where $\boldsymbol{v}$ represents the left-trvialized intrinsic coordinates of tangent vector as in ([Sv]). Therefore, $\boldsymbol{S}$ matrix for matrix Lie groups can be found as

$$\begin{aligned}\mathrm{vec}(\dot{\boldsymbol{G}}) &= \mathrm{vec}(\boldsymbol{G}\boldsymbol{\Xi}) = (\boldsymbol{I}_d \otimes \boldsymbol{G})\,\mathrm{vec}(\boldsymbol{\Xi}) \\ &= (\boldsymbol{I}_d \otimes \boldsymbol{G})\boldsymbol{E}_{vec}\boldsymbol{v} = \boldsymbol{S}\boldsymbol{v},\end{aligned} \tag{13}$$

using the identity vectorization identities. Therefore, each column of $\boldsymbol{S}$ matrix can be found as $\boldsymbol{S}_i = \mathrm{vec}(\boldsymbol{G}\boldsymbol{e}_i^\wedge)$ for all $i \in \mathbb{Z}_{q_G}$. Moreover,

For the Euclidean space $\mathbb{R}^a$, the $\boldsymbol{S}$ and $\boldsymbol{E}_{vec}$ matrix and is just the identity $\boldsymbol{I}_a$ as the hat map in Euclidean space is trivially $\boldsymbol{e}_i^\wedge = \boldsymbol{e}_i$. For a state space $\mathcal{X} = \mathcal{G}_\infty \times ... \times \mathcal{G}_\parallel \times \mathbb{R}^a$ composed of multiple compact Lie groups and the Euclidean, the $\boldsymbol{S}$ and $\boldsymbol{E}_{vec}$ can be built by block diagonalization of each of their respective tangent vector span and basis vector span matrices.

Moreover, a left-invariant metric tensor $g_{\mathcal{G}}(\cdot,\cdot) : \mathfrak{g} \times \mathfrak{g} \to \mathbb{R}$ can be characterized on a matrix Lie group $\mathcal{G}$ using Lie algebra, where $g_{\mathcal{G}}(\boldsymbol{\Xi}_1, \boldsymbol{\Xi}_2) = \mathrm{Tr}(\boldsymbol{\Xi}_1^\top \boldsymbol{\Xi}_2) = \mathrm{vec}(\boldsymbol{\Xi}_1)^\top \mathrm{vec}(\boldsymbol{\Xi}_2) = \boldsymbol{v}_1^\top \boldsymbol{E}_{vec}^\top \boldsymbol{E}_{vec}\boldsymbol{v}_2$. Therefore, given some paths $\boldsymbol{c}(s) \in \Gamma_{\mathcal{G}}(a,b)$, the length can be defined as $L_{\mathcal{G}}(a,b) = \int_0^1 \sqrt{\boldsymbol{v}(s)^\top \boldsymbol{E}_{vec}^\top \boldsymbol{E}_{vec}\boldsymbol{v}(s)}ds$ and the geodesic is defined as $\boldsymbol{\gamma}_{\mathcal{G}}(t) = \arg_{\boldsymbol{c}\in\Gamma_{\mathcal{G}}(a,b)} \min L(\boldsymbol{c})$. This works trivially for Euclidean space as well with $\boldsymbol{E}_{vec} = \boldsymbol{I}_a$.

III. Neural Robust Control on Lie Groups Using Contraction Methods

In this section, we present our main results. Conditions for the closed-loop system to achieve a given $\mathcal{L}_\infty$ gain bound are first proposed. Then, a learning-based framework is implemented to find an RCCM and a feedback controller that satisfy these conditions and minimize the gain bound.

A. RCCMs on Lie groups

Ref. [3] developed linear matrix inequalities (LMIs) to guarantee the existence of a $\mathcal{L}_\infty$ gain bound $\alpha > 0$ for systems in Euclidean space. We now extend this result to systems evolving on general Lie groups.

We first start by analyzing the differential closed-loop system associated with (1) expressed in intrinsic coordinates $\boldsymbol{v}$. Given a feedback controller $\boldsymbol{u}$ in the form of (5), the differential feedback controller can be found as $\delta\boldsymbol{u} = \boldsymbol{K}(\boldsymbol{x})\delta\boldsymbol{x}$, where $\boldsymbol{K} = \frac{\partial \boldsymbol{k}}{\partial \boldsymbol{x}}$. The dynamics of the differential closed-loop system represented in intrinsic coordinates is given by

$$\begin{aligned}\dot{\boldsymbol{v}} &= \frac{d}{dt}(\boldsymbol{P}_S^\top \delta\boldsymbol{x}) = \dot{\boldsymbol{P}}_S^\top \boldsymbol{S}\boldsymbol{v} + \boldsymbol{P}_S^\top \delta\dot{\boldsymbol{x}} \\ &= (\dot{\boldsymbol{P}}_S^\top + \boldsymbol{P}_S^\top \boldsymbol{A} + \boldsymbol{E}\boldsymbol{K})\boldsymbol{S}\boldsymbol{v} + \boldsymbol{E}_w\delta\boldsymbol{w} \\ &= \boldsymbol{\mathcal{A}}\boldsymbol{v} + \boldsymbol{E}_w\delta\boldsymbol{w}, \\ \delta\boldsymbol{z} &= (\boldsymbol{C} + \boldsymbol{D}\boldsymbol{K})\boldsymbol{S}\boldsymbol{v} = \boldsymbol{\mathcal{C}}\boldsymbol{v},\end{aligned} \tag{14}$$

where $\dot{\boldsymbol{P}}_S^\top = \partial_{\dot{\boldsymbol{x}}}\boldsymbol{P}_S^\top$ with $\dot{\boldsymbol{x}}$ given by (1), $\boldsymbol{\mathcal{A}} = (\dot{\boldsymbol{P}}_S^\top + \boldsymbol{P}_S^\top \boldsymbol{A} + \boldsymbol{E}\boldsymbol{K})\boldsymbol{S}$ and $\boldsymbol{\mathcal{C}} = (\boldsymbol{C} + \boldsymbol{D}\boldsymbol{K})\boldsymbol{S}$.

Proposition 1: A closed-loop system satisfying Assumption 1 has a universal $\mathcal{L}_\infty$ gain bound of $\alpha > 0$, if there exists a uniformly bounded symmetric metric $\boldsymbol{\mathcal{M}}(\boldsymbol{x})$, a feedback controller $\boldsymbol{u}$ in the form of (5) and positive constants μ, λ, such that for any $\boldsymbol{x}, \boldsymbol{w}$, we have

$$\boldsymbol{R}_1 = \begin{bmatrix} \dot{\boldsymbol{\mathcal{M}}} + \langle \boldsymbol{\mathcal{M}}\boldsymbol{\mathcal{A}} \rangle + 2\lambda\boldsymbol{\mathcal{M}} & \boldsymbol{\mathcal{M}}\boldsymbol{E}_w \\ \boldsymbol{E}_w^\top \boldsymbol{\mathcal{M}} & -\mu\boldsymbol{I}_p \end{bmatrix} \preceq \boldsymbol{0}, \tag{15}$$

$$\boldsymbol{R}_2 = \begin{bmatrix} 2\lambda\boldsymbol{\mathcal{M}} - \alpha^{-1}\boldsymbol{\mathcal{C}}^\top\boldsymbol{\mathcal{C}} & \boldsymbol{0} \\ \boldsymbol{0} & (\alpha-\mu)\boldsymbol{I}_p \end{bmatrix} \succeq \boldsymbol{0}, \tag{16}$$

where $\dot{\boldsymbol{\mathcal{M}}} = \partial_{\dot{\boldsymbol{x}}}\boldsymbol{\mathcal{M}}$ with $\dot{\boldsymbol{x}}$ given by (1).

Proof: According to the derivations in [3], we first define a smoothly parametrized path $\boldsymbol{c}(t) \in \Gamma_{\mathcal{X}}(\boldsymbol{x}(t), \boldsymbol{x}^*(t))$ at each $t = t_i \in [0,\infty)$. We choose for each $t = t_i$

$$\boldsymbol{c}(t) = \boldsymbol{\gamma}_{\boldsymbol{\mathcal{M}}}(t) = \arg_{\boldsymbol{c}\in\Gamma_{\mathcal{X}}(\boldsymbol{x},\boldsymbol{x}^*)} \min \mathcal{E}(\boldsymbol{c}(t)), \tag{17}$$

where $\boldsymbol{\gamma}_{\boldsymbol{\mathcal{M}}}$ is the geodesic under metric $\boldsymbol{\mathcal{M}}$ such that $\mathcal{E}(\boldsymbol{x}(t), \boldsymbol{x}^*(t)) = \mathcal{E}(\boldsymbol{\gamma}_{\boldsymbol{\mathcal{M}}}(t))$. Note that $\boldsymbol{c}(t,0) = \boldsymbol{x}(t)$ and $\boldsymbol{c}(t,1) = \boldsymbol{x}^*(t)$. We then construct parametrized paths of input, disturbance and output according to the system (1) and the feedback controller according to (5). For $s \in [0,1]$,

$$\begin{aligned}\boldsymbol{c}(t,s) &= \boldsymbol{\gamma}_{\boldsymbol{\mathcal{M}}}(t,s), \\ \boldsymbol{\nu}(t,s) &= \boldsymbol{k}(\boldsymbol{c}(t,s), \boldsymbol{x}^*(t)) + \boldsymbol{u}^*(t), \\ \boldsymbol{\omega}(t,s) &= (1-s)\boldsymbol{w}^*(t) + s\boldsymbol{w}(t), \\ \boldsymbol{\zeta}(t,s) &= \boldsymbol{g}(\boldsymbol{c}(t,s), \boldsymbol{\nu}(t,s)).\end{aligned} \tag{18}$$

For any fixed time $t = t_i$, differentiate the smooth paths with respect to s, denoting $\frac{\partial}{\partial s}$ with subscript s, to get

$$\begin{aligned}\boldsymbol{c}_s(t,s) &= \tfrac{\partial \boldsymbol{\gamma}_{\boldsymbol{\mathcal{M}}}}{\partial s}(t,s), \\ \boldsymbol{\nu}_s(t,s) &= \boldsymbol{K}(\boldsymbol{c}(t,s))\boldsymbol{c}_s(t,s), \\ \boldsymbol{\omega}_s(t,s) &= \boldsymbol{w}(t) - \boldsymbol{w}^*(t), \\ \boldsymbol{\zeta}_s(t,s) &= \boldsymbol{C}(\boldsymbol{c}(t,s), \boldsymbol{\nu}(t,s))\boldsymbol{c}_s(t,s) \\ &\quad + \boldsymbol{D}(\boldsymbol{c}(t,s), \boldsymbol{\nu}(t,s))\boldsymbol{\nu}_s(t,s).\end{aligned} \tag{19}$$

where $\frac{\partial \gamma_{\mathcal{M}}}{\partial s}(t,s) = \boldsymbol{S}(\gamma_{\mathcal{M}}(t,s))\boldsymbol{\vartheta}(t,s) \in T_{\gamma_{\mathcal{M}}(t,s)}\mathcal{X}$, and $\boldsymbol{\vartheta}(t,s)$ represents parameterized tangent vectors in intrinsic coordinates according to the definition in (4). Suppose for $t \in [t_i, t_i+\epsilon)$, we fix the the control and disturbance to their values at $t = t_i$, and the states $\boldsymbol{c}(t,s)$ evolve according to system (1) for each s with initial conditions $\boldsymbol{c}(t_i,s)$, we can show that (19) obeys the differential dynamics in (14)

$$\begin{aligned} \dot{\boldsymbol{\vartheta}} &= \boldsymbol{\mathcal{A}}\boldsymbol{\vartheta} + \boldsymbol{E}_w\boldsymbol{\omega}_s, \\ \boldsymbol{\zeta}_s &= \boldsymbol{\mathcal{C}}\boldsymbol{\vartheta}. \end{aligned} \tag{20}$$

Now, left-multiply and right-multiply the vector $[\boldsymbol{\vartheta}^\top \boldsymbol{\omega}_s^\top]$ and its transpose respectively to the LMI (15) gives us the inequality $\boldsymbol{\vartheta}^\top\big(\dot{\boldsymbol{\mathcal{M}}} + \langle \boldsymbol{\mathcal{M}}\boldsymbol{\mathcal{A}}\rangle\big)\boldsymbol{\vartheta} + 2\boldsymbol{\vartheta}^\top\boldsymbol{\mathcal{M}}\boldsymbol{E}_w\boldsymbol{\omega}_s + 2\lambda\boldsymbol{\vartheta}^\top\boldsymbol{\mathcal{M}}\boldsymbol{\vartheta} - \mu\boldsymbol{\omega}_s^\top\boldsymbol{\omega}_s \le 0$. Combining with (20) gives us

$$\frac{d}{dt}(\boldsymbol{\vartheta}^\top\boldsymbol{\mathcal{M}}\boldsymbol{\vartheta}) \le -2\lambda\boldsymbol{\vartheta}^\top\boldsymbol{\mathcal{M}}\boldsymbol{\vartheta} + \mu\boldsymbol{\omega}_s^\top\boldsymbol{\omega}_s. \tag{21}$$

Integrating (21) over $s \in [0,1]$ and interchanging integration and differentiation results in

$$\frac{d}{dt}\mathcal{E}(\boldsymbol{c}(t)) \le -2\lambda\mathcal{E}(\boldsymbol{c}(t)) + \mu\|\boldsymbol{w}(t) - \boldsymbol{w}^*(t)\|^2 \tag{22}$$

for $t \in [t_i, t_i+\epsilon]$. For sufficiently small ϵ, (22) indicates

$$\begin{aligned} \mathcal{E}(\boldsymbol{c}(t)) \le\ & \mathcal{E}(\boldsymbol{c}(t_i))e^{-2\lambda(t-t_i)} \\ & + \mu\int_{t_i}^{t} e^{-2\lambda(t-\tau)}\|\boldsymbol{w}(\tau) - \boldsymbol{w}^*(\tau)\|^2 d\tau \end{aligned} \tag{23}$$

by the comparison lemma. Given that $\mathcal{E}(\gamma_{\mathcal{M}}(t)) \le \mathcal{E}(\boldsymbol{c}(t))$ by definition of $\gamma_{\mathcal{M}}$ and $\mathcal{E}(\boldsymbol{c}(t_i)) = \mathcal{E}(\gamma_{\mathcal{M}}(t_i))$ by construction, we can conclude $\mathcal{E}(\gamma_{\mathcal{M}}(t)) \le \mathcal{E}(\gamma_{\mathcal{M}}(t_i))e^{-2\lambda(t-t_i)} + \mu\int_{t_i}^{t} e^{-2\lambda(t-\tau)}\|\boldsymbol{w}(\tau) - \boldsymbol{w}^*(\tau)\|^2 d\tau$. Since t_i is arbitrary, taking $\epsilon \to 0$ gives us

$$\frac{d}{dt}\mathcal{E}(\gamma_{\mathcal{M}}(t)) \le -2\lambda\mathcal{E}(\gamma_{\mathcal{M}}(t)) + \mu\|\boldsymbol{w}(t) - \boldsymbol{w}^*(t)\|^2 \tag{24}$$

for all $t \in [0,\infty)$. Integrating (24) from 0 to t gives

$$\mathcal{E}(\gamma_{\mathcal{M}}(t)) \le \mathcal{E}(\gamma_{\mathcal{M}}(0))e^{-2\lambda t} + \frac{\mu}{2\lambda}\|\boldsymbol{w} - \boldsymbol{w}^*\|^2_{\mathcal{L}_\infty^{[0,t]}}. \tag{25}$$

We then left- and right-multiply the vector $[\boldsymbol{\vartheta}^\top \boldsymbol{\omega}_s^\top]$ and its transpose respectively to the LMI (16), which by rearranging gives us the inequality $\alpha^{-1}\boldsymbol{\zeta}_s^\top\boldsymbol{\zeta}_s \le 2\lambda\boldsymbol{\vartheta}^\top\boldsymbol{\mathcal{M}}\boldsymbol{\vartheta} + (\alpha - \mu)\boldsymbol{\omega}_s^\top\boldsymbol{\omega}_s \le 0$. Integrating this inequality gives

$$\frac{1}{\alpha}\int_0^1 \|\boldsymbol{\zeta}_s(t,s)\|^2 ds \le 2\lambda\mathcal{E}(\boldsymbol{c}(t)) + (\alpha-\mu)\|\boldsymbol{w}(t) - \boldsymbol{w}^*(t)\|^2. \tag{26}$$

Applying the Cauchy-Schwarz inequality, we have $\int_0^1 \|\boldsymbol{\zeta}_s(t,s)\|^2 ds \ge \|\int_0^1 \boldsymbol{\zeta}_s(t,s)ds\|^2 = \|\boldsymbol{z}(t) - \boldsymbol{z}^*(t)\|^2$. Choosing $\boldsymbol{c}(t) = \gamma_{\mathcal{M}}(t)$ and the $\mathcal{L}_\infty$ norm for $\boldsymbol{w}$, we get

$$\|\boldsymbol{z}(t) - \boldsymbol{z}^*(t)\|^2 \le 2\alpha\lambda\mathcal{E}(\gamma_{\mathcal{M}}(t)) + \alpha(\alpha-\mu)\|\boldsymbol{w} - \boldsymbol{w}^*\|^2_{\mathcal{L}_\infty^{[0,t]}}. \tag{27}$$

Combining inequalities (25) and (27), we get $\|\boldsymbol{z}(t) - \boldsymbol{z}^*(t)\|^2 \le \alpha^2\|\boldsymbol{w} - \boldsymbol{w}^*\|^2_{\mathcal{L}_\infty^{[0,t]}} + 2\alpha\lambda\mathcal{E}(\gamma_{\mathcal{M}}(0))e^{-2\lambda t}$ for any t. Therefore, for any $T > 0$,

$$\|\boldsymbol{z} - \boldsymbol{z}^*\|^2_{\mathcal{L}_\infty^{[0,T]}} \le \alpha^2\|\boldsymbol{w} - \boldsymbol{w}^*\|^2_{\mathcal{L}_\infty^{[0,T]}} + \beta(\boldsymbol{x}(0), \boldsymbol{x}^*(0)) \tag{28}$$

where $\beta(\boldsymbol{x}, \boldsymbol{x}^*) = 2\alpha\lambda\mathcal{E}(\boldsymbol{x}, \boldsymbol{x}^*)$. ■

Remark: A closed-loop system satisfying Assumption 1 and the LMI's in (15), (16) implies that the differential system (7) has a differential $\mathcal{L}_\infty$ gain bound of $\alpha > 0$ according to the definition in [3], such that for any $t \in [0,T]$,

$$\|\delta\boldsymbol{z}(t)\|^2 \le \alpha^2\|\delta\boldsymbol{w}\|^2_{\mathcal{L}_\infty^{[0,T]}} + 2\lambda\alpha V(\boldsymbol{x}(0), \delta\boldsymbol{x}(0)). \tag{29}$$

Proof: First, left-multiply the vector $[\boldsymbol{v}^\top, \delta\boldsymbol{w}^\top]$ and right-multiply its transpose to the LMI (16). After rearranging, we get the inequality

$$\delta\boldsymbol{z}^\top\delta\boldsymbol{z} \le \alpha(2\lambda V + (\alpha-\mu)\delta\boldsymbol{w}^\top\delta\boldsymbol{w}). \tag{30}$$

Moreover, performing the same left and right multiplication to the LMI (15), it gives us the inequality $\boldsymbol{v}^\top\big(\dot{\boldsymbol{\mathcal{M}}} + \langle\boldsymbol{\mathcal{M}}\boldsymbol{\mathcal{A}}\rangle\big)\boldsymbol{v} + 2\boldsymbol{v}^\top\boldsymbol{\mathcal{M}}\boldsymbol{E}_w\delta\boldsymbol{w} + 2\lambda\boldsymbol{v}^\top\boldsymbol{\mathcal{M}}\boldsymbol{v} - \mu\delta\boldsymbol{w}^\top\delta\boldsymbol{w} \le 0$. Defining a function $V(\boldsymbol{x}(t), \boldsymbol{v}(t))$ as in (11), we can obtain the following inequality

$$\dot{V}(\boldsymbol{x}(t), \delta\boldsymbol{x}(t)) \le -2\lambda V(\boldsymbol{x}(t), \delta\boldsymbol{x}(t)) + \mu\delta\boldsymbol{w}^\top\delta\boldsymbol{w} \tag{31}$$

This implies $\dot{V} \le 0$ when $V \ge \frac{\mu}{2\lambda}\|\delta\boldsymbol{w}\|^2$, and therefore $V(\boldsymbol{x}(t), \delta\boldsymbol{x}(t)) \le \max\{V(\boldsymbol{x}(0), \delta\boldsymbol{x}(0)), \frac{\mu}{2\lambda}\|\delta\boldsymbol{w}\|^2_{\mathcal{L}_\infty^{[0,T]}}\} \le V(\boldsymbol{x}(0), \delta\boldsymbol{x}(0)) + \frac{\mu}{2\lambda}\|\delta\boldsymbol{w}\|^2_{\mathcal{L}_\infty^{[0,T]}}$ for any $t \in [0,T]$. Plugging this inequality into (31), we get

$$\|\delta\boldsymbol{z}(t)\|^2 \le \alpha^2\|\delta\boldsymbol{w}\|^2_{\mathcal{L}_\infty^{[0,T]}} + 2\lambda\alpha V(\boldsymbol{x}(0), \delta\boldsymbol{x}(0)) \tag{32}$$

for any $t \in [0,T]$. ■

The metric $\boldsymbol{\mathcal{M}}$ that satisfies LMIs (15) and (16) is termed an RCCM and the associated feedback controller will guarantee input-output stability for the closed-loop system.

Corollary 2: The output vector $\boldsymbol{z}$ lives in $\mathbb{R}^l$ in our derivations. A tube-like invariant set can be characterized in the output Euclidean space such that after transient effects,

$$\boldsymbol{z} \in \Omega(\boldsymbol{z}^*) = \{\boldsymbol{y} \in \mathbb{R}^l \mid \|\boldsymbol{y} - \boldsymbol{z}^*\| \le \alpha\overline{w}\} \tag{33}$$

where $\overline{w} = \|\boldsymbol{w} - \boldsymbol{w}^*\|_{\mathcal{L}_\infty}$. In the case where the output space lives in a Lie group and $\boldsymbol{z} \in \mathcal{Z} \subseteq \mathcal{X} \times \mathbb{R}^m$, output deviations can be measured using Riemannian metrics on $\mathcal{Z}$. Similar to (4), we can decompose tangent vectors on $\mathcal{Z}$ such that $\delta\boldsymbol{z} = \boldsymbol{S}_z(\boldsymbol{z})\boldsymbol{v}_z \in T_{\boldsymbol{z}}\mathcal{Z}$. The uniform boundedness of $\boldsymbol{S}_z$ still holds, as $\boldsymbol{S}$ is uniformly bounded from Assumption 1 and the span of the tangent bundle $T\mathbb{R}^m$ is just $\boldsymbol{I}_m$.

A natural choice for Riemannian metrics on Lie groups will be inner products of the left-trivialized coordinates $\boldsymbol{v}_z$. We choose the metric $g(\boldsymbol{v}_{z,1}, \boldsymbol{v}_{z,2}) = \boldsymbol{v}_{z,1}^\top\boldsymbol{Q}\boldsymbol{v}_{z,2} = \delta\boldsymbol{z}_1^\top\boldsymbol{P}_{S_z}(\boldsymbol{z})\boldsymbol{Q}\boldsymbol{P}_{S_z}^\top(\boldsymbol{z})\delta\boldsymbol{z}_2$, where $\boldsymbol{P}_{S_z} = \boldsymbol{S}_z(\boldsymbol{S}_z^\top\boldsymbol{S}_z)^{-1}$. $\boldsymbol{Q}$ is a weighting matrix for each left-trivialized coordinate, so that the input-output gain can be tuned for each channel. Therefore, a generalized version of LMI (16) is proposed as

$$\boldsymbol{R}_2' = \begin{bmatrix} 2\lambda\boldsymbol{\mathcal{M}} - \alpha^{-1}\boldsymbol{\mathcal{C}}^\top\boldsymbol{P}_{S_z}\boldsymbol{Q}\boldsymbol{P}_{S_z}^\top\boldsymbol{\mathcal{C}} & \boldsymbol{0} \\ \boldsymbol{0} & (\alpha-\mu)\boldsymbol{I}_p \end{bmatrix} \succeq \boldsymbol{0}, \tag{34}$$

This guarantees the Riemannian length between $\boldsymbol{z}$ and $\boldsymbol{z}^*$ has a universal $\mathcal{L}_\infty$ gain bound of α, and a similar invariant set can be characterized on the output manifold such that

$$\boldsymbol{z} \in \Omega_{\mathcal{Z}}(\boldsymbol{z}^*) = \{\boldsymbol{y} \in \mathcal{Z} \mid d_g(\boldsymbol{y}, \boldsymbol{z}^*) \le \alpha\overline{w}\}. \tag{35}$$

where $d_g(\boldsymbol{z}, \boldsymbol{z}^*)$ is the Riemannian distance between $\boldsymbol{z}, \boldsymbol{z}^*$ under metric g.

Proof: Revisiting the proof of Proposition 1, we now have $\boldsymbol{\zeta}_s(t,s) = \boldsymbol{S}_z(\boldsymbol{\zeta}(t,s))\boldsymbol{\vartheta}_z$ for the derivative of the parametrized output in (19). Following similar procedures of left- and right-multiplication of vector $[\boldsymbol{\vartheta}^\top \boldsymbol{\omega}_s^\top]$ and its transpose respectively to the LMI (34), a generalized version of inequality (26) can be obtained as

$$\frac{1}{\alpha} E_{\mathcal{Z}}(\boldsymbol{\zeta}(t)) \leq 2\lambda E(\boldsymbol{c}(t)) + (\alpha - \mu)\|\boldsymbol{w}(t) - \boldsymbol{w}^*(t)\|^2, \quad (36)$$

where $E_{\mathcal{Z}}(\boldsymbol{\zeta}(t)) = \int_0^1 g(\boldsymbol{\vartheta}_z(t,s), \boldsymbol{\vartheta}_z(t,s))ds$. Defining the set $\Gamma_{\mathcal{Z}}(\boldsymbol{z}, \boldsymbol{z}^*) = \{\boldsymbol{\zeta}(s) = \boldsymbol{g}\big(\boldsymbol{c}(s), \boldsymbol{k}(\boldsymbol{c}(s), \boldsymbol{x}^* + \boldsymbol{u}^*) \mid \boldsymbol{c} \in \Gamma_{\mathcal{X}}(\boldsymbol{x}, \boldsymbol{x}^*)\}$, we have, by Hopf-Rinow theorem, for all $\boldsymbol{\zeta}(t) \in \Gamma_{\mathcal{Z}}(\boldsymbol{z}(t), \boldsymbol{z}^*(t))$

$$d_g^2(\boldsymbol{z}(t), \boldsymbol{z}^*(t)) \leq E_{\mathcal{Z}}(\boldsymbol{\zeta}(t)) \quad (37)$$

where $d_g(\boldsymbol{z}(t), \boldsymbol{z}^*(t))$ is the Riemannian distance between $\boldsymbol{z}, \boldsymbol{z}^*$ under metric g. We therefore have

$$\frac{1}{\alpha} d_g^2(\boldsymbol{z}(t), \boldsymbol{z}^*(t)) \leq 2\lambda E(\boldsymbol{c}(t)) + (\alpha - \mu)\|\boldsymbol{w}(t) - \boldsymbol{w}^*(t)\|^2. \quad (38)$$

It then follows easily that

$$d_g^2(\boldsymbol{z}, \boldsymbol{z}^*)_{\mathcal{L}_\infty^{[0,T]}} \leq \alpha^2 \|\boldsymbol{w} - \boldsymbol{w}^*\|^2_{\mathcal{L}_\infty^{[0,T]}} + \beta(\boldsymbol{x}(0), \boldsymbol{x}^*(0)). \quad (39)$$

We can therefore characterize a tube-like bound on the output manifold similar to (33) such that

$$\boldsymbol{z} \in \Omega_{\mathcal{Z}}(\boldsymbol{z}^*) = \{\boldsymbol{y} \in \mathcal{Z} \mid d_g(\boldsymbol{z}, \boldsymbol{z}^*) \leq \alpha \overline{w}\}. \quad (40)$$

■

B. Conditions for existence of solutions

From (15), $\dot{\boldsymbol{\mathcal{M}}} + \langle \boldsymbol{\mathcal{M}}\boldsymbol{\mathcal{A}} \rangle + 2\lambda \boldsymbol{\mathcal{M}}$ depends on $\boldsymbol{u}$ and $\boldsymbol{w}$, which are not known prior to implementation. Adopting from [2], extra conditions are proposed to remove these dependencies. Through musical isomorphism $\boldsymbol{\mathcal{W}} = \boldsymbol{\mathcal{M}}^{-1}$ and coordinate change $\boldsymbol{\eta} = \boldsymbol{\mathcal{M}}\boldsymbol{v} \in \mathbb{R}^q$, a dual contraction condition that preserves contraction guarantees is obtained. For all $\boldsymbol{\eta} \neq \boldsymbol{0}$, $\boldsymbol{\eta}^\top \boldsymbol{E} = \boldsymbol{0}$, we have $\boldsymbol{\eta}^\top(-\dot{\boldsymbol{\mathcal{W}}} + \langle(\dot{\boldsymbol{P}}_S^\top + \boldsymbol{P}_S^\top \boldsymbol{A})\boldsymbol{S}\boldsymbol{\mathcal{W}}\rangle + 2\lambda\boldsymbol{\mathcal{W}})\boldsymbol{\eta} < 0$, which can be rewritten as

$$\boldsymbol{E}_\perp^\top(-\dot{\boldsymbol{\mathcal{W}}} + \langle(\dot{\boldsymbol{P}}_S^\top + \boldsymbol{P}_S^\top \boldsymbol{A})\boldsymbol{S}\boldsymbol{\mathcal{W}}\rangle + 2\lambda\boldsymbol{\mathcal{W}})\boldsymbol{E}_\perp \prec \boldsymbol{0}, \quad (41)$$

where $\boldsymbol{E}_\perp$ is any annhilator matrix of $\boldsymbol{E}$ with full column rank such that $\boldsymbol{E}_\perp^\top \boldsymbol{E} = \boldsymbol{0}$. Denoting for some vector $\boldsymbol{a} \in \mathbb{R}^n$, $\boldsymbol{S}_{\boldsymbol{a}} = (\partial_{\boldsymbol{a}} \boldsymbol{P}_S^\top + \boldsymbol{P}_S^\top \frac{\partial \boldsymbol{a}}{\partial \boldsymbol{x}})\boldsymbol{S}$, the following conditions are proposed. For all $i \in \mathbb{Z}_m$ and $j \in \mathbb{Z}_p$,

$$\boldsymbol{C}_1 = \boldsymbol{E}_\perp^\top \left(-\partial_{\boldsymbol{f}} \boldsymbol{\mathcal{W}} + \langle \boldsymbol{S}_{\boldsymbol{f}} \boldsymbol{\mathcal{W}}\rangle + 2\lambda \boldsymbol{\mathcal{W}}\right) \boldsymbol{E}_\perp \prec \boldsymbol{0}, \quad (42)$$

$$\boldsymbol{C}_{2,i} = \boldsymbol{E}_\perp^\top \big(- \partial_{\boldsymbol{b}_i} \boldsymbol{\mathcal{W}} + \langle \boldsymbol{S}_{\boldsymbol{b}_i} \boldsymbol{\mathcal{W}}\rangle\big) \boldsymbol{E}_\perp = \boldsymbol{0}, \quad (43)$$

$$\boldsymbol{C}_{3,j} = \boldsymbol{E}_\perp^\top \big(- \partial_{\boldsymbol{b}_{w,j}} \boldsymbol{\mathcal{W}} + \langle \boldsymbol{S}_{\boldsymbol{b}_{w,j}} \boldsymbol{\mathcal{W}}\rangle\big) \boldsymbol{E}_\perp = \boldsymbol{0}. \quad (44)$$

Proposition 3: Conditions (43) and (44) remove the dependence on $\boldsymbol{u}$ and $\boldsymbol{w}$, respectively, in $\boldsymbol{R}_1$ of (15). Together with the LMI in (42), these conditions guarantee the existence of a feedback controller of the form (5), with differential control law $\delta\boldsymbol{u} = \boldsymbol{K}\delta\boldsymbol{x}$ and some appropriately chosen constants α, μ, such that (15) and (16) hold.

Proof: It is clear that the dual contraction condition in (41) can be decomposed into

$$\boldsymbol{C}_1 + \sum_{i=1}^m \boldsymbol{C}_{2,i} \cdot u_i + \sum_{j=1}^p \boldsymbol{C}_{3,j} \cdot w_j \prec \boldsymbol{0} \quad (45)$$

such that conditions (42), (43) and (44) guarantees the LMI in (41) holds. Note that these three conditions are independent of $\boldsymbol{u}$ and $\boldsymbol{w}$. Formally, (42) makes sure the uncontrolled system is contracting in directions orthogonal to the span of the control inputs, while (43) and (44) enforce $\boldsymbol{b}_i$ and $\boldsymbol{b}_{w,j}$ to be Killing vector fields. As shown in Proposition 2 of [2], satisfying the above conditions is equivalent to the existence of a differential feedback controller in the form $\delta\boldsymbol{u} = \boldsymbol{K}(\boldsymbol{x})\delta\boldsymbol{x}$ that satisfies $\dot{\boldsymbol{\mathcal{M}}} + \langle \boldsymbol{\mathcal{M}}\boldsymbol{\mathcal{A}}\rangle + 2\lambda\boldsymbol{\mathcal{M}} \prec \boldsymbol{0}$. Consequently, $\delta\boldsymbol{u}$ is path integrable and the control can be found in the general form (5). Finally, if the upper-left block of $\boldsymbol{R}_1$ is negative definite, an appropriate choice of μ (e.g., via line search) ensures that $\boldsymbol{R}_1 \preceq \boldsymbol{0}$. As $\boldsymbol{\mathcal{M}}$ is uniformly bounded, $\boldsymbol{R}_2 \succeq \boldsymbol{0}$ is satisfied with a sufficiently large α. ■

C. Offline learning of RCCMs and feedback controller

To implement the theoretical results above, the feedback controller (5) and the dual metric $\boldsymbol{\mathcal{W}}$ are formulated as neural networks and learned simultaneously. The state, control and disturbance variables are limited to compact subsets of their respective spaces to make learning feasible. The neural controller is modelled as $\boldsymbol{k}_{nn}(\boldsymbol{x}, \boldsymbol{x}^*) = \boldsymbol{K}_1(\boldsymbol{x}, \boldsymbol{x}^*; \theta_{k_1}) \cdot \tanh\big(\boldsymbol{K}_2(\boldsymbol{x}, \boldsymbol{x}^*; \theta_{k_2}) \cdot \boldsymbol{\varepsilon}(\boldsymbol{x}, \boldsymbol{x}^*)\big)$, where θ_{k_1}, θ_{k_2} are neural network parameters for $\boldsymbol{K}_1 \in \mathbb{R}^{m \times 3n}$ and $\boldsymbol{K}_2 \in \mathbb{R}^{3n \times q}$, and $\tanh(\cdot)$ is the hyperbolic tangent function. $\boldsymbol{\varepsilon}(\cdot,\cdot) : \mathcal{X} \times \mathcal{X} \to \mathbb{R}^q$ is an error function for Lie groups represented in Euclidean space with $\boldsymbol{\varepsilon}(\boldsymbol{x}, \boldsymbol{x}) = \boldsymbol{0}$. This can be designed specifically for each Lie group, and further details are provided in Section IV. The feedback controller is therefore implemented as $\boldsymbol{u} = \boldsymbol{k}_{nn}(\boldsymbol{x}, \boldsymbol{x}^*) + \boldsymbol{u}^*$ in the form of (5), where $\boldsymbol{k}_{nn}(\boldsymbol{x}, \boldsymbol{x}) = \boldsymbol{0}\ \forall \boldsymbol{x} \in \mathcal{X}$ by construction. Moreover, the dual metric is modelled as $\boldsymbol{\mathcal{W}}(\boldsymbol{x}) = \boldsymbol{\Theta}(\boldsymbol{x}; \theta_w)^\top \boldsymbol{\Theta}(\boldsymbol{x}; \theta_w) + \overline{\mathfrak{m}}^{-1}\boldsymbol{I}_q$, such that $\boldsymbol{\mathcal{W}}$ is lower-bounded by $\overline{\mathfrak{m}}^{-1}$. α and μ in LMI (15) and (16) are modelled as single neuron parameters $\theta_\alpha, \theta_\mu$ to be trained together, such that $\alpha = \ln\big(1 + e^{\theta_\alpha}\big)$ and $\mu = \ln\big(1 + e^{\theta_\mu}\big)$ to ensure positiveness.

Randomly drawing N samples of $(\boldsymbol{x}_k, \boldsymbol{x}_k^*, \boldsymbol{u}_k^*, \boldsymbol{w}_k)$, $k \in \mathbb{Z}_N$, from their respective compact subspaces, the network parameters $\theta_{k_1}, \theta_{k_2}, \theta_w, \theta_\alpha, \theta_\mu$ are trained with the following training loss. For each training sample, we model the loss as

$$\mathcal{L}_k = \mathcal{L}_{\mathrm{PD}}(-\boldsymbol{R}_1) + \mathcal{L}_{\mathrm{PD}}(\boldsymbol{R}_2) + \mathcal{L}_{\mathrm{PD}}(-\boldsymbol{C}_1) + \sum_{i=1}^m \|\boldsymbol{C}_{2,i}\|_F + \sum_{j=1}^p \|\boldsymbol{C}_{3,j}\|_F + \mathcal{L}_{\mathrm{PD}}(\underline{\mathfrak{m}}^{-1}\boldsymbol{I}_q - \boldsymbol{\mathcal{W}}) + \mathrm{ReLU}(\alpha - \underline{\alpha}) \quad (46)$$

where $\|\cdot\|_F$ denotes the Frobenius norm and $\mathrm{ReLU}(x) = \max(0, x)$ is the rectified linear unit. Given a square matrix $\boldsymbol{A} \in \mathbb{R}^{n \times n}$, $\mathcal{L}_{\mathrm{PD}}(\boldsymbol{A})$ penalizes negative definiteness by

evaluating the quadratic forms of randomly sampled unit vectors and averaging the positive contributions. Loss terms based on LMI (15),(16) are added together as soft training loss. Auxiliary loss terms based on conditions (42), (43) and (44) are introduced to "guide" the training. Consistent with the findings in [8], it becomes more challenging for the neural networks to converge without them. Moreover, $\mathcal{L}_{\mathrm{PD}}(\underline{\mathfrak{m}}^{-1}\boldsymbol{I}_q - \boldsymbol{\mathcal{W}})$ penalizes the learned dual metric if it exceeds the upper bound $\underline{\mathfrak{m}}^{-1}$. This guarantees uniform boundedness of the RCCM as in (10). Lastly, $\mathrm{ReLU}(\alpha - \underline{\alpha})$ is incorporated to the loss to minimize the $\mathcal{L}_\infty$ gain bound.

The total loss is then calculated as $\mathcal{L} = \frac{1}{N}\sum_{k=1}^{N}\mathcal{L}_k$. Choosing hyperparameters $(\underline{\mathfrak{m}}, \overline{\mathfrak{m}}, \underline{\alpha}, \lambda)$, $\boldsymbol{\mathcal{M}}$ and $\boldsymbol{k}_{nn}$ are trained using gradient descent. Although the neural networks are trained using sampled data and residual learning error might exist, theoretical guarantees can still be obtained [10][Theorem 6].

D. Online implementation of neural feedback controller

One of the main advantages of this framework is that online computation of the control law is lightweight, since the computationally intensive task of learning the controller function is performed offline. This avoids integrating the differential control law along geodesics in common implementations [3], [9]. In the closed-loop system, the states are fed back to the controller, and the motion planner provides a nominal trajectory $\boldsymbol{x}^*(t)$ and control input $\boldsymbol{u}^*(t)$ that jointly satisfy the system equation (1). If disturbance estimates are incorporated into motion planning, then $\boldsymbol{w} - \boldsymbol{w}^*$ is given by the disturbance estimation error, potentially reducing $\overline{w}$ and thus the size of the bounding tube of output $\boldsymbol{z}$.

IV. Case Study: A Quadrotor Example

The system dynamics of a rate-controlled quadrotor with mass m is studied in this section. The state vector is defined as $\boldsymbol{x} = [\boldsymbol{p}_I^\top, \boldsymbol{v}_I^\top, \boldsymbol{r}_{IB}^\top]^\top$, where $\boldsymbol{p}_I \in \mathbb{R}^3$ is the inertial position, $\boldsymbol{v}_I \in \mathbb{R}^3$ is the inertial velocity, and $\boldsymbol{r}_{IB} = \mathrm{vec}(\boldsymbol{R}_{IB}) \in \mathbb{R}^9$ is the vectorized rotation matrix from the body-fixed frame of the quadrotor to the inertial frame. The state space is a 9-dimensional Lie group $\mathcal{X} = \mathbb{R}^6 \times SO(3)$ embedded in $\mathbb{R}^{15}$, in which a smooth $\boldsymbol{S}(\boldsymbol{x})$ representing the tangent bundle can be found. For $SO(3)$, we define $\boldsymbol{S}_r(\boldsymbol{x})$ to represent $TSO(3)$

$$\boldsymbol{S}_r(\boldsymbol{x}) = \big[\,\mathrm{vec}(\boldsymbol{R}_{IB}\boldsymbol{e}_1^\wedge)\ \mathrm{vec}(\boldsymbol{R}_{IB}\boldsymbol{e}_2^\wedge)\ \mathrm{vec}(\boldsymbol{R}_{IB}\boldsymbol{e}_3^\wedge)\big], \quad (47)$$

where $\boldsymbol{S}_r^\top\boldsymbol{S}_r = 2\cdot\boldsymbol{I}_3$. Therefore, we have $\boldsymbol{S}(\boldsymbol{x}) = \mathrm{diag}\big(\boldsymbol{I}_6,\ \boldsymbol{S}_r(\boldsymbol{x})\big)$. The control vector is composed of the mass-normalized collective thrust T/m and body angular rates $\boldsymbol{\omega}_B$, such that $\boldsymbol{u} = [T/m\ \boldsymbol{\omega}_B^\top]^\top$. The disturbance vector is composed of the mass-normalized disturbance force $\boldsymbol{f}_d/m$ and angular rate disturbance $\boldsymbol{\omega}_d$ such that $\boldsymbol{w} = [\boldsymbol{f}_d^\top/m,\ \boldsymbol{\omega}_d^\top]^\top$. The output vector is defined as $\boldsymbol{z} = [\boldsymbol{Q}\boldsymbol{p}_I^\top\ \ \boldsymbol{R}\boldsymbol{u}^\top]^\top$, where $\boldsymbol{Q}$ and $\boldsymbol{R}$ are weighting matrices. The system's dynamical equation is therefore defined as

$$\dot{\boldsymbol{x}} = \begin{bmatrix}\boldsymbol{v}_I\\ \boldsymbol{g}_I\\ \boldsymbol{0}\end{bmatrix} + \begin{bmatrix}\boldsymbol{0} & \boldsymbol{0}\\ \boldsymbol{R}_{IB}\boldsymbol{e}_3 & \boldsymbol{0}\\ \boldsymbol{0} & \boldsymbol{S}_r\end{bmatrix}\begin{bmatrix}T/m\\ \boldsymbol{\omega}_B\end{bmatrix} + \begin{bmatrix}\boldsymbol{0} & \boldsymbol{0}\\ \boldsymbol{I}_3 & \boldsymbol{0}\\ \boldsymbol{0} & \boldsymbol{S}_r\end{bmatrix}\begin{bmatrix}\boldsymbol{f}_d/m\\ \boldsymbol{\omega}_d\end{bmatrix} \quad (48)$$

where $\boldsymbol{g}_I = [0, 0, -9,81]^\top$ is the gravitational vector in the inertial frame. One can easily verify that (48) satisfies Assumption 1. The quadrotor mass is set as $1kg$, and the weighting matrices are chosen as $\boldsymbol{Q} = \boldsymbol{I}_3$ and $\boldsymbol{R} = \mathrm{Diag}(0.1, 0.5, 0.5, 0.5)$. Moreover, from inspection of (8), $\boldsymbol{E}(\boldsymbol{x})$, $\boldsymbol{E}_w(\boldsymbol{x})$ can be found as

$$\boldsymbol{E}(\boldsymbol{x}) = \begin{bmatrix}\boldsymbol{0} & \boldsymbol{0}\\ \boldsymbol{R}_{IB}\boldsymbol{e}_3 & \boldsymbol{0}\\ \boldsymbol{0} & \boldsymbol{I}_3\end{bmatrix};\ \boldsymbol{E}_w(\boldsymbol{x}) = \begin{bmatrix}\boldsymbol{0}\\ \boldsymbol{I}_6\end{bmatrix}. \quad (49)$$

The analytical solution for $\boldsymbol{E}_\perp(\boldsymbol{x})$ can also be found as

$$\boldsymbol{E}_\perp(\boldsymbol{x}) = \begin{bmatrix}\boldsymbol{I}_3 & \boldsymbol{0} & \boldsymbol{0}\\ \boldsymbol{0} & \boldsymbol{R}_{IB}\boldsymbol{e}_1 & \boldsymbol{R}_{IB}\boldsymbol{e}_2\\ \boldsymbol{0} & \boldsymbol{0} & \boldsymbol{0}\end{bmatrix}, \quad (50)$$

such that $\boldsymbol{E}_\perp^\top(\boldsymbol{x})\boldsymbol{E}(\boldsymbol{x}) = \boldsymbol{0}$ for all $\boldsymbol{x} \in \mathcal{X}$. Lastly, the error function $\boldsymbol{\varepsilon}(\boldsymbol{x}, \boldsymbol{x}^*)$ in $\boldsymbol{k}_{nn}(\boldsymbol{x}, \boldsymbol{x}^*)$ is designed by adopting the geometric error from [15], where $\boldsymbol{\varepsilon}_r = \frac{1}{2}(\boldsymbol{R}_{IB}^{*\top}\boldsymbol{R}_{IB} - \boldsymbol{R}_{IB}^\top\boldsymbol{R}_{IB}^*)^\vee$. Combining it with the Euclidean error $\boldsymbol{\varepsilon}_p = \boldsymbol{p}_I - \boldsymbol{p}_I^*$ and $\boldsymbol{\varepsilon}_v = \boldsymbol{v}_I - \boldsymbol{v}_I^*$ gives

$$\boldsymbol{\varepsilon}(\boldsymbol{x}, \boldsymbol{x}^*) = \begin{bmatrix}\boldsymbol{\varepsilon}_p^\top & \boldsymbol{\varepsilon}_v^\top & \boldsymbol{\varepsilon}_r^\top\end{bmatrix}^\top. \quad (51)$$

A. Training and simulation results

Each training sample $(\boldsymbol{x}_k, \boldsymbol{x}_k^*, \boldsymbol{u}_k^*, \boldsymbol{w}_k)$ is drawn from compact subsets of $\mathcal{X} \times \mathcal{X} \times \mathbb{R}^m \times \mathbb{R}^p$. For Euclidean states, control and disturbances, samples are drawn within a range. To generate sample states in $SO(3)$, Euler angles are randomly sampled within the range $(-1, -1, -\pi) \leq (\phi, \theta, \psi) \leq (1, 1, \pi)$ and converted into rotation matrices. Moreover, hyperparameters are selected following [8] primarily, where $\underline{\mathfrak{m}} = 0.1$, $\overline{\mathfrak{m}} = 10$, $\lambda = 0.5$ and $\underline{\alpha} = 0.7$. Each neural network is composed of 2 hidden layers with 128 neurons each and a $\tanh$ activation function. Training is performed for 30 epochs with 130K training samples, using the loss function in (46). Our GitHub repository in [16] provides further implementation details.

The RCCM controller is trained with *Adam optimizer*, and an $\mathcal{L}_\infty$ gain bound of $\alpha = 1.268$ is achieved. To verify the tracking performance of the controller, a spiral reference motion $(\boldsymbol{x}^*, \boldsymbol{u}^*)$ is generated using differentially flatness following [17]. The flat variables are chosen as $\boldsymbol{p}_I^*(t) = [0.5t, 3\cos(1.5t), 3\sin(1.5t)]^\top$ and $\psi^*(t) = 0$, where ψ^* is the desired yaw angle. Moreover, artificial disturbances are injected into the system, which are modelled as $\boldsymbol{f}_d(t) = \big(0.8 + 0.2\sin(0.2\pi t)\big)[0.6, 0.7, 0.3]^\top$ and $\boldsymbol{\omega}_d(t) = \big(0.5 + 0.5\sin(2\pi t)\big)[0.1, 0.1, 0.2]^\top$. The $\mathcal{L}_\infty$ norm $\|\boldsymbol{w}(t)\|_{\mathcal{L}_\infty}$ is calculated to be $\overline{w} = 1$, for $\boldsymbol{w}^*(t) = \boldsymbol{0}$.

As a comparative study, three extra test cases are implemented. First, a CCM controller is trained with the

assumption of no noise. We therefore assumed $\boldsymbol{B}_w(\boldsymbol{x}) = \boldsymbol{0}$ and the neural networks are trained with the loss function

$$\mathcal{L} = \frac{1}{N}\sum_{k=1}^{N}\Big(\mathcal{L}_{\mathrm{PD}}(-\mathcal{CCM}) + \mathcal{L}_{\mathrm{PD}}(-\boldsymbol{C}_1) + \sum_{i=1}^{m}\|\boldsymbol{C}_{2,i}\|_F + \mathcal{L}_{\mathrm{PD}}(\underline{\mathrm{m}}^{-1}\boldsymbol{I}_q - \mathcal{W})\Big) \tag{52}$$

where $\mathcal{CCM} = \dot{\mathcal{M}} + \langle \mathcal{MA}\rangle + 2\lambda\mathcal{M}$.

Second, a geometric controller modified from [15] is employed as shown below. Given nominal states $\boldsymbol{x}^* = [\boldsymbol{p}_I^{*\top}\ \boldsymbol{v}_I^{*\top}\ \boldsymbol{r}_{IB}^{*\top}]^\top$ and nominal control $\boldsymbol{u}^* = [T^*/m\ \ \boldsymbol{\omega}_B^{*\top}]^\top$, a desired acceleration vector is obtained as

$$\boldsymbol{a}_{des} = -\boldsymbol{K}_p\boldsymbol{e}_p - \boldsymbol{K}_v\boldsymbol{e}_v + \tfrac{T^*}{m}\boldsymbol{R}_{IB}^*\boldsymbol{e}_3 \tag{53}$$

where $\boldsymbol{K}_p = \mathrm{diag}([0.5, 0.5, 0.5])$ and $\boldsymbol{K}_v = \boldsymbol{I}_3$ are proportional and derivative gains for translational errors. Thrust input is determined by projecting it to the third axis of the desired body orientation such that $T_{geo}/m = \boldsymbol{a}_{des}^\top\boldsymbol{R}_{IB}^*\boldsymbol{e}_3$. Desired body-frame axes are then computed, where $\boldsymbol{z}_{B,des} = \boldsymbol{a}_{des}/\|\boldsymbol{a}_{des}\|$. Given the nominal yaw angle ψ^*, we find the heading vector on the xy-plane to be $\boldsymbol{x}_C = [\cos\psi^*\ \ \sin\psi^*\ \ 0]^\top$. The remaining desired body axes can be found as $\boldsymbol{y}_{B,des} = \frac{\hat{\boldsymbol{z}}_{B,des}\boldsymbol{x}_C}{\|\hat{\boldsymbol{z}}_{B,des}\boldsymbol{x}_C\|}$ and $\boldsymbol{x}_{B,des} = \boldsymbol{y}_{B,des}^\wedge\boldsymbol{z}_{B,des}$. The desired rotation matrix can be computed as

$$\boldsymbol{R}_{IB,des} = \begin{bmatrix}\boldsymbol{x}_{B,des} & \boldsymbol{y}_{B,des} & \boldsymbol{z}_{B,des}.\end{bmatrix} \tag{54}$$

We then define our body rate control input based on geometric rotation error and the feedforward body rate such that

$$\boldsymbol{\omega}_{B,geo} = \boldsymbol{R}_{IB}^\top\boldsymbol{R}_{IB}^*\boldsymbol{\omega}_B^* - \boldsymbol{K}_r\boldsymbol{e}_R, \tag{55}$$

where $\boldsymbol{e}_R = \frac{1}{2}(\boldsymbol{R}_{IB,des}^\top\boldsymbol{R}_{IB} - \boldsymbol{R}_{IB}^\top\boldsymbol{R}_{IB,des})$ and $\boldsymbol{K}_R = \mathrm{diag}(2.4, 2.4, 2.4)$. Combining the inputs gives the control $\boldsymbol{u} = [T_{geo}/m\ \ \boldsymbol{\omega}_{B,geo}^\top]^\top$.

Third, an acceleration-based uncertainty and disturbance estimator (UDE) is implemented with the RCCM controller to reduce the disturbance deviation. The disturbance estimation law is given by

$$\dot{\hat{\boldsymbol{f}}}_d = -\lambda_d\big(\hat{\boldsymbol{f}}_d - (m\dot{\boldsymbol{v}}_I - m\boldsymbol{g}_I - \boldsymbol{R}_{IB}\boldsymbol{e}_3\cdot T)\big), \tag{56}$$

where $\hat{\boldsymbol{f}}_d$ is the estimated disturbance force vector and the UDE gain is chosen to be $\lambda_d = 0.5$. The disturbance estimate is incorporated into differential flatness-based motion planning with $\boldsymbol{w}^* = [\hat{\boldsymbol{f}}_d^\top/m, \boldsymbol{0}]^\top$. The implementation framework is illustrated in Figure 1.

Numerical simulations are performed on the four test cases, all initialized from the same state with an initial error. All controllers achieve bounded tracking performance as illustrated in Fig. 2. However, further examination of the of the output deviation norm $\|\boldsymbol{z}(t) - \boldsymbol{z}^*(t)\|$ in Fig. 3 shows that both the CCM and geometric controllers exceed the prescribed bound of $\alpha\bar{w} = 1.268$, whereas the output $\boldsymbol{z}$ under the RCCM controller remains within the set defined in (33) throughout the simulation. Moreover, the RCCM controller augmented with UDE exhibits the smallest output deviation, as persistent disturbances are effectively rejected after the transient phase, reducing disturbance deviation $\|\boldsymbol{w} - \boldsymbol{w}^*\|$.



Fig. 1. Closed-loop system with a CCM feedback controller and a UDE.



Fig. 2. Quadrotor tracking a spiral trajectory under the four test cases.

V. Conclusion

This paper extends the robust CCM approach to systems evolving on Lie groups, providing sufficient conditions for input–output stability. A learning-based framework is proposed to jointly synthesize the RCCM and the feedback controller. Simulation results on a quadrotor demonstrate superior performance in robustness under disturbances compared to geometric and CCM controllers. Future work will explore improved neural network architectures to reduce learning error and validate the proposed approach experimentally under real-world uncertainties.



Fig. 3. Output deviation norm under the four test cases.

REFERENCES

[1] W. Lohmiller and J.-J. E. Slotine, "On contraction analysis for nonlinear systems," *Automatica*, vol. 34, no. 6, pp. 683–696, 1998.

[2] I. R. Manchester and J.-J. E. Slotine, "Control contraction metrics: Convex and intrinsic criteria for nonlinear feedback design," *IEEE Transactions on Automatic Control*, vol. 62, no. 6, pp. 3046–3053, 2017.

[3] P. Zhao, A. Lakshmanan, K. Ackerman, A. Gahlawat, M. Pavone, and N. Hovakimyan, "Tube-certified trajectory tracking for nonlinear systems with robust control contraction metrics," *IEEE Robotics and Automation Letters*, vol. 7, no. 2, pp. 5528–5535, 2022.

[4] I. R. Manchester and J.-J. E. Slotine, "Robust Control Contraction Metrics: A Convex Approach to Nonlinear State-Feedback H^∞ Control," *IEEE Control Systems Letters*, vol. 2, no. 3, pp. 333–338, 2018.

[5] P. Zhao, Z. Guo, Y. Cheng, A. Gahlawat, H. Kang, and N. Hovakimyan, "Guaranteed trajectory tracking under learned dynamics with contraction metrics and disturbance estimation," *Robotics*, vol. 13, no. 7, p. 99, 2024.

[6] L. Brunke, M. Greeff, A. W. Hall, Z. Yuan, S. Zhou, J. Panerati, and A. P. Schoellig, "Safe learning in robotics: From learning-based control to safe reinforcement learning," *Annual Review of Control, Robotics, and Autonomous Systems*, vol. 5, no. 1, pp. 411–444, 2022.

[7] C. Dawson, S. Gao, and C. Fan, "Safe Control With Learned Certificates: A Survey of Neural Lyapunov, Barrier, and Contraction Methods for Robotics and Control," *IEEE Transactions on Robotics*, vol. 39, no. 3, pp. 1749–1767, 2023.

[8] D. Sun, S. Jha, and C. Fan, "Learning certified control using contraction metric," in *conference on Robot Learning*. PMLR, 2021, pp. 1519–1539.

[9] H. Tsukamoto and S.-J. Chung, "Neural contraction metrics for robust estimation and control: A convex optimization approach," *IEEE Control Systems Letters*, vol. 5, no. 1, pp. 211–216, 2020.

[10] H. Tsukamoto, S.-J. Chung, J.-J. Slotine, and C. Fan, "A theoretical overview of neural contraction metrics for learning-based control with guaranteed stability," in *2021 60th IEEE Conference on Decision and Control (CDC)*. IEEE, 2021, pp. 2949–2954.

[11] S. Singh, B. Landry, A. Majumdar, J.-J. Slotine, and M. Pavone, "Robust feedback motion planning via contraction theory," *The International Journal of Robotics Research*, vol. 42, no. 9, pp. 655–688, 2023.

[12] D. Wu, B. Yi, and I. R. Manchester, "Control contraction metrics on submanifolds," in *2024 IEEE 63rd Conference on Decision and Control (CDC)*. IEEE, 2024, pp. 3735–3740.

[13] B. Vang and R. Tron, "Global attitude control via contraction on manifolds with reference trajectory and optimization," in *2020 59th IEEE Conference on Decision and Control (CDC)*. IEEE, 2020, pp. 2006–2013.

[14] J. M. Lee, "Smooth manifolds," in *Introduction to smooth manifolds*. Springer, 2003, pp. 1–29.

[15] T. Lee, M. Leok, and N. H. McClamroch, "Geometric tracking control of a quadrotor UAV on SE (3)," in *49th IEEE conference on decision and control (CDC)*. IEEE, 2010, pp. 5420–5425.

[16] Y. L. Lo, L. Qian, and H. H.-T. Liu, "Neural Robust Control on Lie Groups Using Contraction Methods," 2026. [Online]. Available: https://github.com/loyilok515/CDC2026

[17] M. Faessler, A. Franchi, and D. Scaramuzza, "Differential flatness of quadrotor dynamics subject to rotor drag for accurate tracking of high-speed trajectories," *IEEE Robotics and Automation Letters*, vol. 3, no. 2, pp. 620–626, 2017.