
DLR-DAAD Research Fellowship No. 734

Microwaves and Radar Institute (DLR-HR), Oberpfaffenhofen

Topography-Dependent Azimuth Reconstruction in Multistatic SAR Systems

Project report



Lucas Ayub Rodrigues Tuler

Instituto Tecnológico de Aeronáutica (ITA), Brazil

Supervision: Nida Sakar (DLR-HR)

Draft — October 2026

Abstract

Multichannel and multistatic synthetic aperture radar (SAR) systems for high-resolution wide-swath (HRWS) imaging sample the azimuth signal of each receiver at a pulse repetition frequency (PRF) below the Doppler bandwidth and recover the unambiguous spectrum by combining the channels in an azimuth reconstruction. The reconstruction filters are derived for a reference geometry. When the receivers are separated by cross-track baselines, a scatterer at a height different from the reference height carries a channel-dependent phase residual, the reconstruction no longer cancels the aliased parts of the spectrum, and azimuth ambiguities appear.

This report studies that topography-dependent mismatch with a numerical simulator of a spaceborne formation ($\lambda = 0.25\,\mathrm{m}$, $r_0 = 766\,\mathrm{km}$, $N_{\mathrm{rx}} = 2$ to 8 receivers, cross-track baselines up to 500 m) and compares correction strategies that use *only the system parameters and a digital elevation model (DEM)*, never the positions of the targets. The sub-aperture topography- and aperture-dependent (SATA) algorithm, applied to each channel before the reconstruction, is shown to be exact only when the terrain has the same height at every ground position folded onto the same Doppler bin, i.e. at positions $X \approx 6.2\,\mathrm{km}$ apart; on general terrain it leaves a structural residual that is predicted from the geometry within about 1 dB. A *joint* reconstruction that places the DEM phase of every folded parcel inside the inversion removes this limitation. Its final version models the channels from the focused line and the DEM and solves a regularised least-squares problem with conjugate gradients.

Over 1040 one-dimensional runs (52 scenes, $N_{\mathrm{rx}} = 2$–8) the median highest ambiguity drops from $-8.4\,\mathrm{dB}$ without correction to $-40.6\,\mathrm{dB}$ with the joint reconstruction (reference $-47.6\,\mathrm{dB}$). The two-dimensional extension, which applies the DEM at every pixel of a 3-D scene, reaches a median of $-44.4\,\mathrm{dB}$ over 640 runs (no correction $-13.9\,\mathrm{dB}$, reference $-47.6\,\mathrm{dB}$). The remaining failures are configurations whose baselines do not separate the folded parcels (two channels, equally spaced baselines) and are a property of the data rather than of the algorithm.

Contents

Abstract i

Symbols and acronyms vii

1 Introduction 1

1.1 Context . . . 1

1.2 Objective . . . 1

1.3 Contributions . . . 2

1.4 Outline . . . 2

2 Acquisition geometry and signal model 3

2.1 Formation and parameters . . . 3

2.2 Signal model . . . 3

2.3 Channel transfer functions and the coefficients C_0, C_1, C_2, Δt . . . 3

2.4 The topographic residual ΔC_0 . . . 7

3 Multichannel azimuth reconstruction and topography 9

3.1 Aliased channels and folded parcels . . . 9

3.2 How topography creates ambiguities . . . 9

3.3 Ambiguity metric . . . 12

4 SATA before the reconstruction 13

4.1 The SATA algorithm . . . 13

4.2 SATA on each channel, then the standard reconstruction . . . 13

4.2.1 Why it is exact only on special terrain . . . 14

4.2.2 Verification . . . 14

4.2.3 SATA on simulated scenes . . . 15

4.2.4 Correction maps that use the target positions . . . 15

5 Joint topography correction and reconstruction 18

5.1 Joint reconstruction in the sub-apertures . . . 18

5.2 Joint reconstruction over the whole line . . . 18

5.3 Properties . . . 20

6 Extension to two dimensions **24**

6.1 Model 24

6.2 The common range band 24

7 Results **28**

7.1 All methods with a DEM only 28

7.2 Why the joint reconstruction is the final method 29

7.3 Sweep of the final joint reconstruction in 1-D 31

7.4 Sweep of the joint reconstruction in 2-D 32

7.5 Limits 34

8 Conclusions and outlook **36**

8.1 Conclusions 36

8.2 Outlook 36

List of Figures

2.1 Bistatic geometry of one channel . . . 4
2.2 DPCA arrangement . . . 4
2.3 Coefficients of the reference point . . . 6
2.4 Bistatic minus monostatic path and its parabola . . . 6
2.5 Change of the coefficients with the height of the scatterer . . . 7
2.6 Origin of the topographic residual . . . 8
2.7 Phase of the topographic residual . . . 8

3.1 Folding of the Doppler spectrum . . . 10
3.2 Aliased channel and reconstructed spectrum . . . 10
3.3 Standard reconstruction of a target at the reference height and above it . . . 11
3.4 Highest ambiguity of the standard reconstruction against height . . . 11

4.1 The SATA kernel . . . 13
4.2 The conflict of one bin . . . 14
4.3 SATA on terrains with and without the period of the folds . . . 16
4.4 Prediction of the level left by SATA . . . 17
4.5 SATA can degrade a target at the reference height . . . 17

5.1 Flowchart of the joint reconstruction in the sub-apertures . . . 19
5.2 The model of the whole-line joint reconstruction . . . 20
5.3 Flowchart of the joint reconstruction over the whole line . . . 21
5.4 SATA + reconstruction versus the joint reconstruction . . . 22
5.5 Convergence of the joint reconstruction . . . 22
5.6 Example: five targets on a mountain . . . 23

6.1 The DEM in radar geometry . . . 25
6.2 The model of the 2-D joint reconstruction . . . 25
6.3 Example of the 2-D sweep . . . 27

7.1 Median highest ambiguity of every method . . . 28
7.2 All the methods on a realistic scene . . . 30
7.3 SATA against the joint reconstruction, every run . . . 31
7.4 1-D sweep by number of channels . . . 31

7.5 Every run of the sweeps 32
7.6 Joint reconstruction with 2, 3, 4 and 8 channels 33
7.7 Example of the 1-D sweep 35
7.8 Sensitivity to DEM errors 35

List of Tables

2.1 Parameters of the simulated system. 3

7.1 Comparison of all methods 28

7.2 2-D sweep by number of channels 32

Symbols and acronyms

Symbol	Meaning
λ	wavelength (0.25 m)
v	platform velocity
r_0	slant range of closest approach of the reference point
θ	look angle ($\approx 20°$)
N_{rx}	number of receive channels (one transmitter, N_{rx} receivers)
$b_{\mathrm{at},i}$, $b_{\mathrm{xt},i}$	along-track and cross-track baseline of receiver i relative to the transmitter
PRF	full (reconstructed) pulse repetition frequency, 2 000 Hz
$\mathrm{PRF}_{\mathrm{op}}$	PRF of each channel, $\mathrm{PRF}/N_{\mathrm{rx}}$
B_{a}	processed azimuth (Doppler) bandwidth, 1 235 Hz
$C_0, C_1, C_2, \Delta t$	coefficients of the bistatic minus monostatic path of a channel (Section 2.3)
$\Delta C_{0,i}(x)$	topographic residual of channel i: C_0 of a scatterer at height $h(x)$ minus C_0 of the reference point
X	ground distance between parcels folded onto the same Doppler bin, $X \approx r_0 \lambda \mathrm{PRF}_{\mathrm{op}}/(2v)$
δx	resolution of one SATA sub-aperture, $\sqrt{\lambda r_0/2}$
$H_i(f)$	transfer function of channel i relative to the monostatic reference
$g(x)$	focused full-rate azimuth line (unknown of the joint reconstruction)
μ	Tikhonov regularisation parameter
Acronym	
CGLS	conjugate gradients for least squares
DEM	digital elevation model
DPCA	displaced phase centre antenna (uniform effective sampling)
HRWS	high-resolution wide-swath
IRF	impulse response function
SATA	sub-aperture topography- and aperture-dependent algorithm

1 Introduction

1.1 Context

A conventional SAR cannot improve its azimuth resolution and its swath width at the same time: a fine azimuth resolution needs a short antenna and therefore a wide Doppler bandwidth, which must be sampled with a high PRF, while a wide swath needs a long interval between pulses. Multichannel systems break this trade-off by receiving each pulse with several apertures displaced along track [1, 2]. Each channel is sampled at a PRF below the Doppler bandwidth and is therefore aliased, but the set of channels samples the azimuth signal at the full rate, and the unambiguous spectrum is recovered by an *azimuth reconstruction*: a bank of filters that combines the channels so that the aliased parts cancel.

Multistatic formations distribute the receivers over several platforms. They lift the limit set by the length of a single antenna and offer flexibility, but the baselines between platforms are no longer small [3, 4]. In particular, a *cross-track* baseline makes the bistatic range history of a scatterer depend on its height. The reconstruction filters are derived for a reference geometry (here: the reference point of the scene at height $h_0 = 0$); a scatterer at another height carries a residual phase that is different in each channel. The filters then no longer match the data, the aliased parts no longer cancel and azimuth ambiguities appear in the image.

The same kind of height-dependent mismatch is known from airborne motion compensation, where the compensation is computed for a reference height and leaves residual errors for the rest of the topography. Prats et al. proposed the sub-aperture topography- and aperture-dependent (SATA) algorithm to correct it with an external DEM [5, 6]: the azimuth signal is split into short sub-apertures, each Doppler frequency of a sub-aperture is associated with a ground position, and the phase residual of that position, read from the DEM, is removed.

1.2 Objective

The fellowship topic is to investigate whether SATA can correct the azimuth ambiguities caused by topography and cross-track baselines in multistatic SAR systems. During the work the question was made precise as:

1. How large are the ambiguities caused by unaccounted topography, as a function of the terrain, the baselines and the number of channels?
2. How much of them can be removed using *only the system parameters and a DEM*, with no knowledge of where the scatterers are?

The second condition is strict on purpose. Several intermediate methods tested during the project reached the reference level only because their correction maps were built from the positions of the simulated targets; such methods are not applicable to real data and are not counted as solutions here (Section 4.2.4).

1.3 Contributions

- A numerical simulator of the multistatic acquisition and of the multichannel reconstruction in one dimension (azimuth) and in two dimensions (azimuth and range, 3-D scenes), with along- and cross-track baselines and arbitrary terrain (Chapters 2 and 3).
- An analysis of SATA applied to each aliased channel before the reconstruction, showing when it is exact and predicting the residual it leaves on general terrain (Chapter 4).
- A joint reconstruction that places the DEM phase inside the inversion, first per sub-aperture and finally over the whole line, solved by regularised least squares with conjugate gradients (Chapter 5), and its 2-D extension (Chapter 6).
- Systematic sweeps over terrains, numbers of channels and baselines, and an audit of every method with a DEM only (Chapter 7).

1.4 Outline

Chapter 2 introduces the acquisition geometry and the topographic residual ΔC_0. Chapter 3 reviews the multichannel reconstruction and explains how topography produces ambiguities. Chapter 4 describes SATA and its limit for aliased channels. Chapter 5 presents the joint reconstruction and Chapter 6 its 2-D version. Chapter 7 collects the results and Chapter 8 concludes. The simulator, the methods and the scripts that produce every figure of this report are available at github.com/lucas-ayub/dlr-project.

2 Acquisition geometry and signal model

2.1 Formation and parameters

One platform transmits and receives (channel 0); the other $N_{\mathrm{rx}} - 1$ receivers fly behind it. Receiver i is displaced by $b_{\mathrm{at},i}$ along track and by $b_{\mathrm{xt},i}$ across track (horizontally, towards the scene) relative to the transmitter (Figure 2.1). The along-track baselines satisfy the displaced phase centre (DPCA) condition (Figure 2.2), so that the effective phase centres of the N_{rx} channels are uniformly spaced and the multichannel sampling is uniform at the full PRF; the study is about the cross-track baselines, which are drawn at random in $[0, {b_{\mathrm{xt}}}^{\max}]$ (with the largest equal to ${b_{\mathrm{xt}}}^{\max}$) or taken from fixed sets. Channel 0 is always the transmitter ($b_{\mathrm{at}} = b_{\mathrm{xt}} = 0$). The parameters are listed in Table 2.1.

Table 2.1: Parameters of the simulated system.

Wavelength λ	0.25 m
Platform altitude H	720 km
Slant range of the reference point r_0	766.2 km
Look angle θ	20°
Platform velocity / effective velocity	7 688.5 m/s / 7 408.5 m/s
Antenna length	12 m
Processed Doppler bandwidth B_{a}	1 235 Hz
Full PRF	2 000 Hz
Channel PRF $\mathrm{PRF}_{\mathrm{op}} = \mathrm{PRF}/N_{\mathrm{rx}}$	1 000 Hz to 250 Hz ($N_{\mathrm{rx}} = 2$ to 8)
DPCA along-track spacing $2v/\mathrm{PRF}$	7.69 m
Cross-track baselines ${b_{\mathrm{xt}}}^{\max}$	100 m, 300 m and 500 m, and fixed sets

2.2 Signal model

The simulator works with point targets. In the 1-D study the targets lie on a terrain profile $h(x)$ along azimuth; each target is placed on the iso-range surface of the reference point (same monostatic slant range r_0), so that only its height changes the bistatic geometry. The reference point is at $x = 0$, $h = 0$. In the 2-D study (Chapter 6) the terrain is a surface $h(x, y)$ and the data are range compressed. The azimuth signal of channel i is

$$s_i(t) = \sum_p a_p \, w(t - t_p) \, \exp\left(-\mathrm{j} \frac{2\pi}{\lambda} \left[r_{\mathrm{T},p}(t) + r_{\mathrm{R},i,p}(t) \right] \right), \tag{2.1}$$

with a_p the complex amplitude of scatterer p, w the antenna pattern and $r_{\mathrm{T}} + r_{\mathrm{R},i}$ the bistatic path (Figure 2.1).

2.3 Channel transfer functions and the coefficients C_0, C_1, C_2, Δt

The reconstruction (Chapter 3) needs, for every channel i, its transfer function $H_i(f)$: the factor by which the Doppler spectrum of channel i differs from the spectrum the monostatic system (transmitter and receiver at the transmitter) would record for the same scatterer. This




Figure 2.1: Geometry of one channel. The transmitter (Tx) and receiver i (Rx$_i$) fly on parallel tracks at the same altitude H, separated by $b_{\mathrm{at},i}$ along track and $b_{\mathrm{xt},i}$ across track. The echo of channel i travels $r_{\mathrm{T}}(t) + r_{\mathrm{R},i}(t)$. The time of closest approach t_p and the range r_0 fix the position of the scatterer on the line; its height h is what the topography adds. Not to scale.




Figure 2.2: DPCA arrangement seen from above ($N_{\mathrm{rx}} = 4$). Receiver i trails the transmitter by $b_{\mathrm{at},i} = 2id$, so the phase centre of the pair (the mid-point) trails it by id. At every pulse the four phase centres occupy four equally spaced positions; between pulses the platform moves $D = N_{\mathrm{rx}}d$ and the pattern repeats. Together the channels sample the ground every d, like a single channel at the full PRF.

section derives H_i from the range histories of the reference point; the derivation follows the Doppler-domain approach of [3, 4].

Step 1: two parabolas (time domain). Let $M(t) = 2r_{\mathrm{T}}(t)$ be the monostatic path and $B_i(t) = r_{\mathrm{T}}(t) + r_{\mathrm{R},i}(t)$ the bistatic path of channel i, both for the reference point. Over the aperture each is well described by a parabola around its own minimum:

$$M(t) \approx M_{\min} + m_2\,(t - t_M)^2, \qquad B_i(t) \approx B_{i,\min} + b_{2,i}\,(t - t_{B,i})^2, \tag{2.2}$$

where $M_{\min}$, $B_{i,\min}$ are the smallest path lengths [m], t_M, $t_{B,i}$ the times at which they occur [s] and m_2, $b_{2,i}$ the curvatures [m/s^2]. The corresponding azimuth signals are $s_M(t) = w(t)\exp[-\mathrm{j}2\pi M(t)/\lambda]$ and $s_i(t) = w(t)\exp[-\mathrm{j}2\pi B_i(t)/\lambda]$.

Step 2: from time to Doppler (stationary phase). For a signal $\exp[-\mathrm{j}2\pi P(t)/\lambda]$ with a parabolic path $P(t) = P_{\min} + p_2(t - t_P)^2$, the instantaneous frequency is

$$f(t) = -\frac{1}{\lambda}\frac{\mathrm{d}P}{\mathrm{d}t} = -\frac{2p_2}{\lambda}(t - t_P) \quad \Longrightarrow \quad t_f = t_P - \frac{\lambda f}{2p_2}, \tag{2.3}$$

so every Doppler frequency f is produced at one time t_f (the same relation as the ruler (3.3) of Chapter 3). By the principle of stationary phase the phase of the spectrum at f is the phase of the signal at t_f minus $2\pi f t_f$. With $P(t_f) = P_{\min} + \lambda^2 f^2/(4p_2)$,

$$\Psi_P(f) = -\frac{2\pi}{\lambda}P(t_f) - 2\pi f t_f = -2\pi\Big[\frac{P_{\min}}{\lambda} + t_P\,f - \frac{\lambda f^2}{4p_2}\Big]. \tag{2.4}$$

The amplitude of the spectrum is set by the antenna pattern and is the same for the two paths.

Step 3: the ratio of the two spectra (Doppler domain). Applying (2.4) to B_i and to M and taking the difference of the phases gives the transfer function of channel i:

$$H_i(f) = \mathrm{e}^{\mathrm{j}[\Psi_{B_i}(f) - \Psi_M(f)]} = \exp\Big(-\mathrm{j}2\pi\Big[\frac{C_{0,i}}{\lambda} + (\Delta t_i - C_{1,i})\,f + C_{2,i}\,\lambda f^2\Big]\Big), \tag{2.5}$$

with

$$C_{0,i} = B_{i,\min} - M_{\min}, \qquad \Delta t_i - C_{1,i} = t_{B,i} - t_M, \qquad C_{2,i} = \frac{1}{4m_2} - \frac{1}{4b_{2,i}}. \tag{2.6}$$

In the simulator the two paths are sampled at the full PRF: Δt_i is the time between the samples where M and B_i are smallest and $C_{1,i}$ the sub-sample correction given by the linear terms of the two fitted parabolas, so that $\Delta t_i - C_{1,i}$ is the time between the two minima.

Physical meaning. Each coefficient corresponds to one effect of the bistatic geometry:

- $C_{0,i}$ [m], the difference of the shortest paths, is a *constant phase* $2\pi C_{0,i}/\lambda$. It is set by the cross-track baseline, and it is the coefficient that changes with the height of the scatterer (Section 2.4).
- $\Delta t_i - C_{1,i}$ [s], the delay between the two minima, is a *linear phase* in Doppler, i.e. a shift in time. It is set by the along-track baseline ($\approx b_{\mathrm{at},i}/(2v)$) and is what makes the channels sample the azimuth signal at displaced positions (DPCA).
- $C_{2,i}$ [s^2/m], the difference of the inverse curvatures, is a *quadratic phase*: a small residual azimuth chirp.

For a scatterer other than the reference point the same derivation holds with its own paths; what changes, to first order, is $C_{0,i}$ (Section 2.4).

Figure 2.3 shows the four coefficients of the reference point. C_0 is the difference of the closest-approach distances of the receiver and of the transmitter, $\approx -b_{\mathrm{xt}} \sin\theta$ ($-171\,\mathrm{m}$ for $b_{\mathrm{xt}} = 500\,\mathrm{m}$), and does not depend on b_{at}; $\Delta t = b_{\mathrm{at}}/(2v)$ (0.5 ms, 1.0 ms and 1.5 ms for the three DPCA receivers) and does not depend on b_{xt}; C_1 is below $0.2\,\mu\mathrm{s}$ and C_2 below $4 \times 10^{-7}\,\mathrm{s}^2/\mathrm{m}$, which at the edge of the processed band, $f = B_{\mathrm{a}}/2$, give phases of $2\pi C_1 f < 1 \times 10^{-3}$ rad and $2\pi C_2 \lambda f^2 \approx 0.2$ rad. Figure 2.4 checks the parabolic model (2.2) for one target: the bistatic minus the monostatic path varies by a few millimetres over the aperture (5.6 mm for $b_{\mathrm{xt}} = 300\,\mathrm{m}$) and the parabola reproduces it within 10^{-4} mm.




Figure 2.3: C_0, C_1, C_2 and Δt of the reference point for the receivers 1, 2 and 3 of the DPCA formation ($b_{\mathrm{at}} = 7.7\,\mathrm{m}$, 15.4 m and 23.1 m), as a function of the cross-track baseline b_{xt} (the same for the three receivers). The three curves of C_0 and of C_2 coincide.




Figure 2.4: One target at $x = 0$, $h = 500\,\mathrm{m}$, four channels with $b_{\mathrm{xt}} = [0, 300, 119.8, 100.5]$ m. Left: bistatic minus monostatic path of every channel against the time from closest approach, minus its constant offset (C_0, given in the legend); dots: simulated geometry; lines: the fitted parabola. Right: difference between the simulated curve and the parabola.

2.4 The topographic residual ΔC_0

For a scatterer at height h the coefficient C_0 of channel i differs from the one of the reference point. The difference is the *topographic residual*

$$\Delta C_{0,i}(h) = C_{0,i}(\text{scatterer}) - C_{0,i}(\text{reference point}) \approx -\frac{b_{\text{xt},i}\, h}{r_0 \tan\theta}, \qquad \varphi_i(h) = \frac{2\pi}{\lambda}\Delta C_{0,i}(h), \quad (2.7)$$

i.e. the interferometric phase of the cross-track baseline; it vanishes for the transmitter channel ($b_{\text{xt}} = 0$), since the targets are on the iso-range surface. The simulator computes $\Delta C_{0,i}$ exactly from the range histories; the approximation (2.7) agrees within about 2 %. For a scatterer at 500 m and $b_{\text{xt}} = [63.7, 27.0, 4.1, 1.7]$ m the residuals are $[-113.9, -48.2, -7.3, -3.0]$ mm, i.e. up to half a wavelength. The other coefficients change much less with height: the topography acts as a channel-dependent *constant* phase over the aperture of each scatterer, a fact used by the joint reconstruction (Chapter 5). Figure 2.5 quantifies this: up to 3 km of height and $b_{\text{xt}} = 500$ m, ΔC_0 follows (2.7) within a few per cent, and at the edge of the processed band the phase produced by ΔC_0 (about 80 rad at 3 km with $b_{\text{xt}} = 300$ m) is four orders of magnitude larger than the one produced by ΔC_2 (4×10^{-3} rad) and seven larger than the one produced by ΔC_1 (4×10^{-6} rad); Δt does not change with height.




Figure 2.5: Change of the coefficients of receiver 1 when the scatterer is at height h instead of the reference point. Left: ΔC_0 (dots: exact, from the range histories; lines: (2.7)) for three cross-track baselines. Right ($b_{\text{xt}} = 300$ m): phase produced by each term of (2.5) at the edge of the processed band, $f = B_{\text{a}}/2$, on a logarithmic scale.

Figure 2.6 shows where (2.7) comes from. Moving from the reference point to a scatterer at height h on the same range arc of the transmitter is a displacement $s = h/\sin\theta$ perpendicular to the line of sight of the transmitter, which does not change its path. The line of sight of receiver i is rotated by $\Delta\theta = b_{\text{xt},i}\cos\theta/r_0$, so its path changes by $s\,\Delta\theta = b_{\text{xt},i}h/(r_0\tan\theta)$.

The sensitivity is $\partial\varphi_i/\partial h = 2\pi b_{\text{xt},i}/(\lambda r_0 \tan\theta) \approx 9.0 \times 10^{-5}\, b_{\text{xt},i}$ rad/m, which also sets the tolerance to DEM errors (Section 7.5).




Figure 2.6: Left: plane perpendicular to the track (not to scale). The reference point and the scatterer are at the same range r_0 from the transmitter, at different heights: climbing h along the arc is a displacement $s = h/\sin\theta$. Right: zoom around the scatterer. Since $s \ll r_0$ the lines of sight of each platform to the two points are parallel; s is perpendicular to the line of sight of the transmitter, but the one of the receiver is rotated by $\Delta\theta$, and its path becomes $s\,\Delta\theta$ shorter (thick orange segment).




Figure 2.7: Phase of the topographic residual (2.7) against height. With $b_{\mathrm{xt}} = 300\,\mathrm{m}$ the sensitivity is 1.55° per metre of height: a 230 m hill already produces a full cycle.

3 Multichannel azimuth reconstruction and topography

3.1 Aliased channels and folded parcels

Each channel is sampled at $\mathrm{PRF}_{\mathrm{op}} = \mathrm{PRF}/N_{\mathrm{rx}}$, below the Doppler bandwidth $B_{\mathrm{a}} = 1\,235\,\mathrm{Hz}$. In the Doppler domain of the channel, every frequency $\phi \in [-\mathrm{PRF}_{\mathrm{op}}/2, \mathrm{PRF}_{\mathrm{op}}/2)$ is the sum of N_{rx} *parcels* of the full-rate spectrum U, taken at

$$f_q = \phi + q\,\mathrm{PRF}_{\mathrm{op}} - \tfrac{N_{\mathrm{rx}}-1}{2}\mathrm{PRF}_{\mathrm{op}}, \qquad q = 0, \dots, N_{\mathrm{rx}} - 1, \tag{3.1}$$

each weighted by the transfer function H_i of the channel relative to the monostatic reference:

$$S_i(\phi) = \sum_q H_i(f_q)\, U(f_q) \quad \Longleftrightarrow \quad \boldsymbol{s}(\phi) = \mathbf{H}(\phi)\, \boldsymbol{u}(\phi), \tag{3.2}$$

with $\boldsymbol{s}$ the N_{rx} channel spectra and $\boldsymbol{u}$ the N_{rx} parcels. The standard reconstruction [1, 2] inverts this square system at every ϕ, $\hat{\boldsymbol{u}} = \mathbf{P}(\phi)\boldsymbol{s}(\phi)$ with $\mathbf{P} = \mathbf{H}^{-1}$, and places the parcels at their true Doppler frequency to obtain the full-rate signal. The entries of $\mathbf{H}$ are the transfer functions (2.5) of the reference point, $H_{iq}(\phi) = H_i(f_q)$.

Through the Doppler–angle relation, a Doppler frequency f seen from the platform at azimuth position x_c corresponds to the ground position

$$x(f) = x_c + r_0 \tan\!\big(\arcsin(\lambda f/2v)\big) \approx x_c + \frac{\lambda r_0}{2v}\, f, \tag{3.3}$$

which we call the *ruler*. Parcels one $\mathrm{PRF}_{\mathrm{op}}$ apart therefore come from ground positions

$$X \approx \frac{\lambda r_0\, \mathrm{PRF}_{\mathrm{op}}}{2v} \qquad (6.23\,\mathrm{km} \text{ for } \mathrm{PRF}_{\mathrm{op}} = 500\,\mathrm{Hz}), \tag{3.4}$$

apart, i.e. 0.81 s of azimuth time. This distance is the key length of the problem: one bin of an aliased channel mixes the echoes of the terrain at x, $x \pm X$, $x \pm 2X$, … (Figure 3.1).

Figure 3.2 shows the two sides of this for one target on flat terrain and four channels. A single channel at $\mathrm{PRF}_{\mathrm{op}} = 500\,\mathrm{Hz}$ sees the processed band $B_{\mathrm{a}} = 1\,235\,\mathrm{Hz}$ folded two to three times onto its own band; the standard reconstruction combines the four channels and recovers the full-rate spectrum of the reference.

3.2 How topography creates ambiguities

For a scatterer at height h, channel i carries the extra constant phase $\mathrm{e}^{-\mathrm{j}\varphi_i}$ of (2.7), so the data are $\boldsymbol{s} = \mathbf{D}\mathbf{H}\boldsymbol{u}$ with $\mathbf{D} = \mathrm{diag}(\mathrm{e}^{-\mathrm{j}\varphi_i})$, and the standard reconstruction returns

$$\hat{\boldsymbol{u}} = \mathbf{H}^{-1}\mathbf{D}\,\mathbf{H}\,\boldsymbol{u} = \mathbf{L}\,\boldsymbol{u}. \tag{3.5}$$

In the DPCA configuration $\mathbf{H}$ is, up to diagonal factors, a discrete Fourier matrix over the channels, and the leakage matrix becomes Toeplitz,

$$L_{q'q} = c_{q'-q}, \qquad c_m = \frac{1}{N_{\mathrm{rx}}} \sum_{i=0}^{N_{\mathrm{rx}}-1} \exp\!\Big[\mathrm{j}\Big(\frac{2\pi i m}{N_{\mathrm{rx}}} - \varphi_i\Big)\Big]. \tag{3.6}$$




Figure 3.1: Folding of the azimuth spectrum in an aliased channel ($N_{rx} = 4$). The four parcels of one channel bin come, through the ruler (3.3), from ground positions X apart, which in general have different heights.




Figure 3.2: One target at $h = 0$, four channels ($b_{xt} = [0, 300, 119.8, 100.5]$ m). Left: power spectrum of one channel at PRF$_{op}$ = 500 Hz (averaged over 25 bins): the folded parcels overlap. Right: spectrum of the reference and of the standard reconstruction at the full PRF; the grey band is the processed band B_a and the dotted lines are the borders of the four parcels, PRF$_{op}$ apart.

c_0 is the gain of the true parcel and c_m, $m \neq 0$, the amplitude that parcel q leaks into parcel $q + m$, which appears in the image as an ambiguity displaced by mX ($0.81\,\mathrm{s}{\cdot}m$). If all channels have the same phase, $c_m = 0$ for $m \neq 0$ and the reconstruction is exact; with cross-track baselines the phases differ and the ambiguity level grows with the spread of $b_{\mathrm{xt},i}h$. Weighted by the fraction of the target bandwidth that falls in the leaking parcels, $|c_m|$ predicts the ambiguity of the uncorrected reconstruction within 0.15 dB for heights above 50 m.

Figure 3.3 shows the effect on one target. At $h = 0$ the channels carry no residual and the standard reconstruction is the reference (up to the band limitation to B_a); at 500 m copies of the target appear at multiples of the ambiguity time, 0.81 s. Figure 3.4 gives the highest ambiguity against the height of the target for three sets of baselines: it grows by 20 dB per decade of height (for small phases $|c_m|$ is proportional to φ_i, hence to $b_{\mathrm{xt}}h$) and saturates between -15 dB and -5 dB once the phases of the channels are of the order of a radian, i.e. above about 100 m with ${b_{\mathrm{xt}}}^{\max} = 300$ m.




Figure 3.3: Azimuth impulse response of one target ($b_{\mathrm{xt}} = [0, 300, 119.8, 100.5]$ m) after the standard reconstruction (no SATA) and of the reference. Dotted lines: the ambiguity positions, ± 1 and ± 2 times 0.81 s. Left: target at the reference height, the two responses coincide. Right: target at 500 m.




Figure 3.4: Highest ambiguity of the standard reconstruction (no SATA) for one target at height h, four channels, three sets of cross-track baselines. At $h = 0$ the three sets give -63.6 dB, the level of the reference limited to the processed band B_a.

Two consequences recur in the rest of the report:

- The amplitudes c_m are the discrete Fourier transform of the channel phases. Baselines for

which several φ_i coincide modulo 2π, or that are equally spaced, make the system badly conditioned at certain heights: the channels no longer separate the parcels.

- With two channels there is no redundancy at all: two parcels, two equations.

3.3 Ambiguity metric

All results are reported as the *highest ambiguity*: the largest value of the azimuth impulse response, in dB relative to the peak of the reference, inside ± 20 ms of the ambiguity positions of every target (± 1 and ± 2 times the ambiguity distance of the channel PRF). The reference is the monostatic full-rate signal of the same scene, processed with the same band limitation; its own value (sidelobes of neighbouring targets, band edge) is the floor that any reconstruction can reach. Repeating the measurement with orders up to ± 5 for six and eight channels did not change the conclusions.

4 SATA before the reconstruction

4.1 The SATA algorithm

SATA was developed for airborne motion compensation [5, 6]. Its idea is that a short piece of the azimuth signal is a low-resolution image of the ground: inside a sub-aperture, each Doppler frequency belongs to one ground position through the ruler (3.3). The topography-dependent phase can therefore be removed frequency by frequency, with the value of the DEM at the position that frequency points to. The steps, for one channel, are (Figure 4.1):

1. cut the azimuth line into sub-apertures with triangular windows and 50 % overlap;
2. Fourier transform each sub-aperture (with zero padding);
3. for every bin f, compute the ground position $x(f)$ with the ruler and multiply the bin by $\exp\big(+\mathrm{j}\,2\pi\Delta C_{0,i}(x(f))/\lambda\big)$, with $\Delta C_{0,i}$ read from the DEM;
4. inverse transform and overlap-add.

The length of the sub-aperture balances two errors: it must be short enough that the frequency-to-position mapping is sharp, and long enough that the frequency resolution resolves the ground. The optimum gives a ground resolution $\delta x = \sqrt{\lambda r_0/2} = 309.5\,\mathrm{m}$; at $\mathrm{PRF}_{\mathrm{op}} = 500\,\mathrm{Hz}$ this is a block of 20 samples (40 ms), a hop of 10 samples and a zero-padded FFT of 128 points.




Figure 4.1: The SATA kernel applied to one channel. The only external information is the DEM; the ruler associates each sub-aperture bin with a ground position.

4.2 SATA on each channel, then the standard reconstruction

The natural way to use SATA in a multichannel system is to correct every channel with its own $\Delta C_{0,i}$ and then run the standard reconstruction. Two variants were implemented:

Whole band each bin of the channel is labelled with the position of its base-band parcel; the corrected channels go through the standard reconstruction.

Per sub-band for every output sub-band k, each bin is labelled with the position of the parcel of sub-band k (absolute Doppler), and sub-band k of the output is reconstructed only from the channels corrected for k.

Both variants are the identity with a zero map ($< 10^{-15}$), rotate the line by the right phase with a constant map, and the kernel agrees with the original SATA implementation within 0.44 % rms.

4.2.1 Why it is exact only on special terrain

The channel is aliased: one bin holds the parcels q of the positions $x_q = x_b + \rho f_q$, X apart (Figure 3.1). SATA multiplies the whole bin by a *single* phase, the one of the labelled position x_r. After the correction, parcel q keeps the error

$$\varepsilon_{iq} = \varphi_i(x_q) - \varphi_i(x_r) = -\frac{2\pi\, b_{\mathrm{xt},i}\,\big[h(x_q) - h(x_r)\big]}{\lambda\, r_0 \tan\theta}, \tag{4.1}$$

and the standard reconstruction returns $\hat{\boldsymbol{u}} = \mathbf{L}\boldsymbol{u}$ with $\mathbf{L} = \mathbf{H}^{-1}\mathrm{diag}(\mathrm{e}^{-\mathrm{j}\varepsilon})\mathbf{H}$: the same leakage structure as (3.6), now driven by the *height differences between folded positions*. Hence:

- $\mathbf{L} = \mathbf{I}$, whatever the baselines, only if $h(x) = h(x \pm X) = h(x \pm 2X) = \ldots$: flat terrain, or a terrain periodic with period X;
- for two channels, a -30 dB ambiguity tolerates only about 7 m of height difference between folded positions with $b_{\mathrm{xt}} = 100$ m, and 1.4 m with 500 m;
- in the whole-band variant only the fraction of the target spectrum that falls in the labelled parcel receives the phase of its own position (about 78 %, 52 %, 39 %, 26 % and 20 % for $N_{\mathrm{rx}} = 2, 3, 4, 6, 8$); in the per-sub-band variant the output parcel is right but all the others leak into it.




Figure 4.2: The conflict of one bin. Its parcels come from places X apart, with different heights. SATA on the channel applies one phase to the whole bin; the joint reconstruction applies the phase of each place to its own parcel, inside the system of equations.

Correcting each parcel needs the parcels separated, and separating them needs the phases corrected: the two steps cannot be done one after the other. This is what the joint reconstruction of Chapter 5 does in a single system.

4.2.2 Verification

The analysis was checked in three ways (83 automatic checks, all passing):

- **Positive control.** On flat terrain at 500 m, and on the terrain $h = 100 - 100\cos(2\pi x/X)$, whose period is exactly X, SATA whole band, SATA per sub-band and the joint reconstruction coincide (Figure 4.3, left).

- **Negative control.** The same cosine with period $1.5X$: SATA leaves -30 dB to -10 dB (whole band) and -24 dB to -6 dB (per sub-band) over the 20 baseline sets, while the joint reconstruction stays within 3 dB to 6 dB of the reference in 19 of them (10 dB in the last) (Figure 4.3, right).
- **Prediction.** The level left by SATA, computed only from the fold addresses and the DEM, matches the simulation within 1.3 dB rms (whole band) and 0.7 dB rms (per sub-band) over 680 runs (Figure 4.4). The residual is structural, not an implementation error.

SATA can even make things worse: a single target at $h = 0$ on a terrain of period 50 km ($b_{\mathrm{xt}} \leq 100$ m) reaches -63.7 dB without correction, but -36.3 dB after SATA whole band and -27.8 dB per sub-band, because the neighbouring terrain folded onto the same bins is not at $h = 0$.

A complementary run removes the aliasing (each channel at $\mathrm{PRF}_{\mathrm{op}} = 2\,000$ Hz $> B_{\mathrm{a}}$): there SATA alone brings smooth terrains close to the reference (peak of the worst target within 0.3 dB to 1.4 dB) and is limited only on steep terrain by its 310 m cell. The limit discussed above is therefore a consequence of the aliasing, not of SATA itself.

4.2.3 SATA on simulated scenes

Figure 4.3 puts the analysis to the test with five targets on a cosine terrain and four channels ($b_{\mathrm{xt}} \leq 100$ m). The left column uses a period of 6.23 km, equal to X: the positions folded onto the same bin (red circles) have the same height, and SATA whole band and per sub-band reach -44.4 dB, the same level as the joint reconstruction (-43.9 dB; reference -48.8 dB). The right column changes only the period, to $1.5X$: the folded positions now have different heights, and SATA leaves -19.0 dB (whole band) and -13.5 dB (per sub-band), close to the uncorrected -12.1 dB, while the joint reconstruction does not change (-44.0 dB).

The residual left by SATA is not an implementation detail. Writing the leakage matrix $\mathbf{L}$ of Section 4.2.1 with the heights of the DEM at the folded positions predicts the level it leaves without any simulation; over the 680 runs of the audit (Section 7.1) the prediction agrees with the simulation within 1.3 dB rms for SATA whole band and 0.7 dB rms per sub-band (Figure 4.4).

The extreme case is a single target at the height of the reference point on a gently varying terrain (Figure 4.5): without correction there is nothing to correct (-63.7 dB), but SATA gives every bin the phase of the terrain at the labelled position, and the energy of the target receives the phase of other places: -36.3 dB whole band and -27.8 dB per sub-band. The joint reconstruction leaves the target untouched (-63.5 dB).

4.2.4 Correction maps that use the target positions

During the project, maps were also built from the simulated targets: the ΔC_0 of each target written at its cell and copied at the folded positions $\pm X$ (*block map with copies*), or the value of the nearest target. With such maps SATA per channel reaches the oracle for isolated targets, because the map then encodes exactly which parcel is occupied. A real scene provides no such information. These maps are kept in the code for reference but are *not* part of any method evaluated in Chapter 7; every method there receives only the system parameters and the DEM, and removing the target list from the configuration given to the methods does not change a single bit of their output.




Figure 4.3: Five targets on $h = 100 - 100\cos(2\pi x/P)$, four channels, $b_{\text{xt}} = [0, 100, 39.9, 33.5]$ m. Left: $P = X = 6.23$ km; right: $P = 1.5X$. Top: terrain, targets, and the three positions x, $x \pm X$ folded onto the same channel bin for the middle target (red circles). Below: azimuth impulse responses of the reference and, from top to bottom, of no SATA, SATA whole band, SATA per sub-band and the joint reconstruction over the whole line. Every method reads only the DEM.




Figure 4.4: Highest ambiguity left by SATA, predicted only from the geometry and the DEM (the leakage of the folded parcels) against the simulation, for the 680 runs of the audit, coloured by the number of channels.




Figure 4.5: One target at the reference point ($x = 0$, $h = 0$) on the terrain $h = 100 - 100\cos(2\pi x/50\,\mathrm{km})$, four channels, $b_{xt} = [0, 100, 39.9, 33.5]$ m. Top: the terrain near the target (left) and along the whole azimuth line (right). Bottom: impulse responses; every method reads only the DEM.

5 Joint topography correction and reconstruction

The analysis of Section 4.2.1 shows that the correct phase (the ΔC_0 read from the DEM) is already known; what fails is applying it per channel before the parcels are separated. The joint reconstruction moves the DEM phase inside the inversion.

5.1 Joint reconstruction in the sub-apertures

With the same sub-apertures as SATA, for every sub-aperture and every bin ϕ of the N_{rx} channel spectra the model (3.2) is written with the phase of each parcel at its own ground position:

$$S_i(\phi) = \sum_q H_i(f_q)\, \exp\!\Big(-\mathrm{j}\frac{2\pi}{\lambda}\Delta C_{0,i}(x_q)\Big)\, U_q, \qquad x_q = x_c + \frac{\lambda r_0}{2v} f_q, \tag{5.1}$$

and solved for the parcels U_q, which are then placed at their true Doppler, transformed back and overlap-added at the full PRF. The steps are summarised in Figure 5.1. With $\Delta C_0 = 0$ this is the standard reconstruction ($\sim 10^{-7}$); with one target it equals the oracle. Its limit is the resolution of the sub-aperture: the DEM is read once per bin of a 40 ms block, i.e. the terrain phase is taken as constant over about ± 600 m of ground. A slope s with a cross-track baseline is equivalent to shifting the phase centre of the channel by $b_{\mathrm{xt}} s/(2\tan\theta)$; when that shift is not small compared with the block, the per-bin model breaks. With $\Delta\varphi = \frac{2\pi}{\lambda}\frac{b_{\mathrm{xt}}{}^{\max}\, s\, \delta x}{r_0 \tan\theta}$ the phase change inside one SATA cell, the method stays within about 10 dB of the reference for $\Delta\varphi \lesssim 0.5$ rad and fails by 10 to 35 dB above 1 rad.

5.2 Joint reconstruction over the whole line

The final version removes the sub-apertures. The topographic residual of a scatterer is a constant phase over its whole aperture (Chapter 2); in the *focused* full-rate line $g(x)$ it is therefore a pointwise multiplication. The channels are modelled as

$$\boldsymbol{s}_i = \mathcal{D}\Big\{k_i * \big[\, g(x)\, \mathrm{e}^{-\mathrm{j}\varphi_i(x)}\big]\Big\}, \qquad \varphi_i(x) = \frac{2\pi}{\lambda}\Delta C_{0,i}\big(h(x)\big), \tag{5.2}$$

where $\varphi_i(x)$ comes from the DEM only, k_i is the response of channel i to the reference point (the azimuth chirp filtered by the reference-point filter H_i of the standard reconstruction) and $\mathcal{D}$ is the decimation to $\mathrm{PRF}_{\mathrm{op}}$ (Figure 5.2). Writing (5.2) as $\boldsymbol{s} = \mathbf{A}\boldsymbol{g}$, the line is estimated by Tikhonov-regularised least squares,

$$\hat{\boldsymbol{g}} = \arg\min_{\boldsymbol{g}} \sum_i \big\|\boldsymbol{s}_i - \mathbf{A}_i\boldsymbol{g}\big\|^2 + \mu^2\|\boldsymbol{g}\|^2, \tag{5.3}$$

solved with conjugate gradients for least squares (CGLS) [7, 8]. Every iteration costs one application of $\mathbf{A}$ and of its adjoint $\mathbf{A}^{\mathsf{H}}$ (two FFTs per channel each). The regularisation is $\mu = 0.03\,\sigma_{\max}$, with $\sigma_{\max}$ estimated by a few power iterations, and the problem is solved in two passes (iterated Tikhonov: the second pass solves for what the first one left), which turns the filter factor $\sigma^2/(\sigma^2+\mu^2)$ into $1-(1-\sigma^2/(\sigma^2+\mu^2))^2$. Each pass runs up to 60 iterations. The output is re-chirped with the reference response, $U = k * \hat{g}$, so that it has the same form as the standard reconstruction. The complete algorithm is in Figure 5.3.




Figure 5.1: The joint reconstruction in the sub-apertures. Green: preparation, done once. Blue: the loop over the blocks of 20 samples; inside each block a small least-squares system is solved for every bin. Violet: finishing. The DEM is read once per bin, at the position the ruler gives to each parcel.




Figure 5.2: The model $\mathbf{A}$ and its adjoint. Each operation is done in the domain where it is simple: the relief phase is a multiplication in *position*, the chirp and the channel filter a multiplication in *Doppler frequency*, the sampling a selection of samples in *time*; the FFTs only move between the domains. The adjoint is the usual SAR processor: it focuses each channel, removes its relief phase and sums the channels.

5.3 Properties

- **Consistency.** With a zero DEM the method reproduces the standard reconstruction within 0.1 % rms.
- **Information used.** Only the channels, the system geometry and the DEM. The positions of the targets are never used (Section 4.2.4).
- **Self-test of the DEM.** The part of the channels that the model does not explain is −41 dB to −39 dB with the right DEM and −20 dB to −7 dB with a wrong one (mirrored or shifted by 1 km), which makes it a natural alarm for DEM errors.
- **Cost.** About 3.3 s per line with four channels in the 1-D simulator (median over 680 runs), against 0.15 s for SATA whole band.
- **Convergence.** Figure 5.5 follows the iterations on the example of Figure 5.6. The first iteration is the adjoint, i.e. the channels focused, corrected and summed (−10.2 dB, close to no SATA); about ten iterations bring the ambiguities below −39 dB, and the second pass gains another 1 dB (−43.5 dB after 2 × 60 iterations). The unexplained part of the channels falls to −38 dB in the same way.
- **Ill-conditioned configurations.** Where the baselines do not separate the parcels (two channels, equally spaced baselines, certain heights with long baselines) the information is not in the data; the regularisation then leaves the ambiguity instead of amplifying noise.

Figure 5.6 shows the example used throughout the development: five targets on a 1 000 m Gaussian mountain with $b_{xt} = [0, 134.9, 20.5, 8.3]$ m. The highest ambiguity goes from −8.7 dB without correction to −43.5 dB with the joint reconstruction; the reference is −48.7 dB, and −43.9 dB once it is limited to the processed band B_a, as every reconstruction is.





Figure 5.3: The joint reconstruction over the whole line. Green: preparation, done once. Blue: the CGLS iterations, in two passes (iterated Tikhonov); each iteration applies $\mathbf{A}$ and $\mathbf{A}^{\mathsf{H}}$ once (two FFTs per channel each). Violet: back to the raw full-rate line, in the same form as the standard reconstruction.

(a) SATA on each channel, then the standard reconstruction



(b) Joint reconstruction over the whole line (final version)




Figure 5.4: Where the DEM phase enters. (a) SATA gives each channel bin a single phase before the parcels are separated. (b) The joint reconstruction puts the phase of every ground position in the model of the channels and inverts model and topography together.




Figure 5.5: Joint reconstruction over the whole line on the example of Figure 5.6 (five targets on a 1 000 m mountain, four channels). Left: highest ambiguity against the total number of conjugate-gradient iterations, with one pass and with two passes, against the reference and no SATA. Right: part of the channels that the model does not explain, $\|\boldsymbol{s} - \mathbf{A}\hat{\boldsymbol{g}}\|/\|\boldsymbol{s}\|$, during the first pass.




Figure 5.6: Five targets on a 1 000 m Gaussian mountain, four channels. Top left: azimuth impulse responses of the reference, of the standard reconstruction (no SATA) and of the joint reconstruction over the whole line. Right: the scene and the formation. The joint reconstruction reads only the DEM.

6 Extension to two dimensions

The 1-D study keeps every target at the slant range of the reference point. In a real scene the terrain varies in range as well, the residual $\Delta C_{0,i}$ depends on both coordinates, the echoes migrate in range and the range envelope of each channel is shifted by half its path difference. A second simulator handles 3-D scenes with along- and cross-track baselines and range-compressed data, and the joint reconstruction is extended to it.

6.1 Model

The unknown is the focused image $g[n, m]$ (Figure 6.2) on azimuth positions x_n (full PRF) and slant ranges of closest approach r_m. The range-compressed data of channel i are modelled as

$$\boldsymbol{s}_i = \mathcal{D}\Big\{ K_i \cdot \mathcal{F}_r\big[\, Q_i \cdot \mathcal{F}_a(S_i\, g)\big]\Big\} \;+\; (\text{envelope term}), \tag{6.1}$$

with

- S_i, the terrain screen at every pixel, $\exp\big(-\mathrm{j}2\pi\Delta C_{0,i}(x, r)/\lambda\big)$, computed from the DEM in radar geometry (the ground range of each pixel is found by a fixed-point iteration, Figure 6.1, which converges for range slopes below $\tan\theta$, i.e. without layover);
- $Q_i(f; r)$, what changes with the range of closest approach in the range-Doppler domain: the azimuth chirp relative to the reference range and the differences of the coefficients $C_0, C_1, C_2, \Delta t$ of the channel;
- $K_i(f, f_r)$, the 2-D kernel: the 2-D FFT of the simulated echo of the reference point in channel i at the full PRF (chirp, range migration, window of the pair, co-registration by $C_{0,i}/2$);
- the envelope term, the first-order shift of the range envelope by $\frac{1}{2}[\Delta C_{0,i} + C_{0,i}(r) - C_{0,i}(r_{\mathrm{ref}})]$, valid while this shift is small compared with the range resolution.

The image is kept on a range grid twice as fine as the data, because a phase that varies with range shifts the range spectrum. The adjoint passes the adjoint test to 2.6×10^{-7}; the solver is the same CGLS as in 1-D ($\mu = 0.03\,\sigma_{\max}$, two passes of up to 60 iterations).

6.2 The common range band

A cross-track baseline shifts the range spectrum seen by the channel, the spectral shift known from interferometry:

$$\nu_i = \frac{c\, b_{\mathrm{xt},i} \cos\theta}{2\lambda\, r \tan(\theta - \alpha)}, \tag{6.2}$$

with α the range slope of the terrain; on flat terrain this is 0.202 MHz per 100 m of baseline. Range frequencies that only some channels observe are not determined by the data (fewer equations than folded parcels), and the joint reconstruction leaves the full ambiguity there. In a control case (one target, flat terrain, $b_{\mathrm{xt}} = [0, 300, 119.8, 100.5]$ m, exact model) the full band reaches -40.5 dB, whereas the band common to all four channels reaches -66.1 dB, equal to the reference in the same band. The output is therefore limited, pixel by pixel, to the range frequencies that





Figure 6.1: The DEM in radar geometry: a pixel at slant range r lies on the terrain at another ground range than on flat terrain. The ground range is found by the fixed-point iteration $y \leftarrow \sqrt{r^2 - [H - h(x,y)]^2}$, which contracts while the range slope stays below $\tan\theta$.

model: from the focused image to the range-compressed data of channel i



adjoint: repeat the spectrum, 2-D matched filter, remove the relief, sum the channels




Figure 6.2: The model of the 2-D joint reconstruction and its adjoint (the envelope term is omitted). The relief acts per pixel, the range-dependent focusing per range line in the range-Doppler domain, and the 2-D kernel of the channel in the two-dimensional frequency domain.

every channel observes there, and the reference and the uncorrected reconstruction are compared in the same band. The price is range resolution, a fraction $b_{\mathrm{xt}}/{b_{\mathrm{xt}}}^{\mathrm{crit}}$ of the band; with the 5 MHz bandwidth of the sweeps the median pixel keeps 93 % of the band and the worst pixel 45 %. A wider system bandwidth (e.g. 50 MHz) would reduce this loss about tenfold.

Figure 6.3 shows a 3-D case: 49 targets on an isolated 1 000 m mountain with four channels and ${b_{\mathrm{xt}}}^{\mathrm{max}} = 300\,\mathrm{m}$.




Figure 6.3: A page of the 2-D sweep: 49 targets on an isolated 1 000 m mountain (Gaussian, $\sigma = 1.5$ km in azimuth and 4 km in ground range), $N_{\mathrm{rx}} = 4$, $b_{\mathrm{xt}} = [0, 300, 119.8, 100.5]$ m. Top left: reference and joint reconstruction; bottom left: reference and no correction; right: the scene and the ΔC_0 of the channel with the largest baseline, which is all the joint reconstruction reads. This is one of the harder cases (the joint reconstruction leaves −25.1 dB, an improvement of 14.6 dB).

7 Results

All numbers in this chapter are the highest ambiguity of Section 3.3, in dB relative to the peak of the reference. Every method receives only the system parameters and the DEM. The scenes cover along-track ramps (3° to 20°), sines and cosines of several periods, and realistic terrains (hills, mountains, escarpments, plateaus, fractal alpine relief, glacial valleys, ridges, canyons, volcanoes), each with one, a few and many point targets (up to 49). The baselines are $N_{\mathrm{rx}} = 2, 3, 4, 6, 8$ with ${b_{\mathrm{xt}}}^{\max} = 100\,\mathrm{m}$, 300 m and 500 m (random, the largest exactly ${b_{\mathrm{xt}}}^{\max}$), plus five fixed four-channel sets: two random ones (up to 100 m and up to 500 m), two equally spaced ones ($[0, 10, 20, 30]$ and $[0, 50, 100, 150]$ m) and one with baselines on both sides of the transmitter ($[0, -50, 50, 100]$ m). Channel 0 is always the transmitter.

7.1 All methods with a DEM only

Table 7.1 and Figure 7.1 compare the methods on 680 runs (34 scenes × 20 baseline sets; median reference −48.7 dB).

Table 7.1: All methods with the DEM only (680 runs).

Method	Median highest ambiguity [dB]	Runs within 10 dB of the reference [%]
No correction (standard reconstruction)	−8.7	3.5
SATA whole band, then reconstruction	−15.4	2.5
SATA per sub-band	−10.8	1.2
Joint reconstruction in the sub-apertures	−30.9	36.3
Joint reconstruction over the whole line	**−41.4**	**81.9**




Figure 7.1: Median highest ambiguity of every method over the 680 runs of the audit. SATA per channel stays close to the uncorrected reconstruction; the joint reconstruction over the whole line gets within a few dB of the reference.

Head to head, the joint reconstruction over the whole line is better than SATA whole band in all 680 runs (median improvement 25.7 dB) and better than SATA per sub-band in all of them (median 30.5 dB). SATA per channel improves on the uncorrected reconstruction by a median of

only 5.5 dB (whole band) and 0.2 dB (per sub-band), consistently with Section 4.2.1.

A distributed scene (about 11 900 scatterers, oracle −34.2 dB, measured as error-to-signal ratio) confirms the ranking: with $b_{\mathrm{xt}} \sim U(0, 100)$ m SATA per channel gives −22.5 dB to −8.7 dB and the whole-line joint −34.1 dB to −33.2 dB; with $U(0, 500)$ m, −13 dB to −6 dB and −33.6 dB to −31.4 dB.

7.2 Why the joint reconstruction is the final method

Figure 7.2 compares all the methods on one realistic scene: five targets on random mountains (relief 1 000 m), four channels with ${b_{\mathrm{xt}}}^{\max} = 300$ m. No SATA leaves −4.6 dB; SATA whole band −14.6 dB; SATA per sub-band −8.6 dB; the joint reconstruction over the whole line −43.6 dB, 5 dB from the reference (−48.7 dB). Figure 7.3 shows that this is not a particular case: over the 680 runs of the audit the joint reconstruction is better than SATA in every run, by a median of 25.7 dB (whole band) and 30.5 dB (per sub-band).

The reasons, collected from the previous chapters:

1. **SATA has the right phase in the wrong place.** SATA reads the correct correction, the ΔC_0 of the DEM. But on an aliased channel each bin is the sum of parcels from positions $X \approx 6.2$ km apart, and a per-channel correction can give that sum only one phase (Figure 4.2). The standard reconstruction that follows assumes that every channel is now exact, so the error of the other parcels becomes leakage between the parcels. SATA is exact only when the terrain has the same height at all the folded positions (Figure 4.3), it can damage a target that needed no correction (Figure 4.5), and the level it leaves is predicted by the geometry (Figure 4.4): it is a property of the order of the operations, not of the implementation. Applying SATA after the reconstruction does not help either, since one phase cannot undo a sum that has already been formed.
2. **The joint reconstruction solves both problems together.** Separating the parcels needs the phases corrected, and correcting each parcel needs the parcels separated. The joint reconstruction writes the phase of every ground position *inside* the model of the channels (Figure 5.4) and inverts model and topography together. With a flat DEM it is the standard reconstruction; on the periodic terrains where SATA is exact it gives the same result as SATA; everywhere else it keeps working.
3. **The whole-line version removes the last approximation.** The joint reconstruction in the sub-apertures still reads the DEM once per bin of a 40 ms block, i.e. it takes the terrain phase as constant over about ±600 m, and fails on steep terrain with long baselines (median −30.9 dB in the audit). Over the whole line the residual of every scatterer is a pointwise phase on the focused line, with no cell at all (median −41.4 dB).
4. **It uses only what a real case has.** The method receives the channels, the system geometry and the DEM; the positions of the targets are never used, and the unexplained part of the channels gives a check of the DEM.
5. **It degrades gracefully.** Where the baselines do not separate the parcels the regularisation leaves the ambiguity instead of amplifying noise, and the cost (a few seconds per line in the 1-D simulator) is that of a few tens of FFTs per channel and iteration.




Figure 7.2: Five targets 2.6 km apart on random mountains (relief 1 000 m, correlation length 3 km), four channels, $b_{\text{xt}} = [0, 300, 119.8, 100.5]$ m. Top: the targets and the terrain near them (left) and along the whole azimuth line (right). Below: impulse responses of the reference and of no SATA, SATA whole band, SATA per sub-band and the joint reconstruction over the whole line. Every method reads only the DEM.




Figure 7.3: Highest ambiguity of the joint reconstruction over the whole line against SATA whole band (left) and SATA per sub-band (right), for the 680 runs of the audit (every method with the DEM only), coloured by the number of channels. Every point is below the diagonal.

7.3 Sweep of the final joint reconstruction in 1-D

The complete 1-D sweep runs the reference, the uncorrected reconstruction and the joint reconstruction over the whole line on 52 scenes × 20 baseline sets = 1040 runs. The medians are −47.6 dB (reference), −8.4 dB (no correction) and −40.6 dB (joint); 78 % of the runs are within 10 dB of the reference. Figure 7.4 splits the result by the number of channels and Figure 7.5 shows every run.




Figure 7.4: 1-D sweep by number of channels. Left: medians of the highest ambiguity. Right: fraction of runs in which the joint reconstruction is within 10 dB and 3 dB of the reference. The reference level rises with N_{rx} because PRF_{op} falls and more ambiguity orders fall inside the band.

The 83 runs that are not resolved (above −30 dB and more than 10 dB from the reference) are almost all configurations whose baselines cannot separate the parcels: 53 have two channels and 25 the equally spaced baselines $[0, 50, 100, 150]$ m; only 5 have four random baselines (3 with ${b_{xt}}^{max} = 300$ m, 2 with 500 m). Figure 7.7 shows a typical resolved case on a fractal alpine relief. Figure 7.6 shows the role of the number of channels on one scene with 49 targets on random mountains and ${b_{xt}}^{max} = 300$ m: with three or more channels the joint reconstruction is within




Figure 7.5: Every run of the 1-D and 2-D sweeps: highest ambiguity of the joint reconstruction against the uncorrected reconstruction, coloured by the number of channels. Points below the diagonal are improvements.

1 dB to 4 dB of the reference; with two channels there is no redundancy and it stops at −22.3 dB (reference −38.5 dB), still 8 dB better than no SATA.

7.4 Sweep of the joint reconstruction in 2-D

The 2-D sweep uses 32 3-D scenes (ramps along azimuth, range and oblique; sines and cosines; realistic and fractal terrains without layover; one target on a flank, five on a diagonal or a 7×7 grid) with the same 20 baseline sets, 640 runs in total. The medians are −47.6 dB (reference), −13.9 dB (no correction) and −44.4 dB (joint), all in the common range band. The joint reconstruction is never worse than the uncorrected one.

Table 7.2: 2-D sweep by number of channels: median gap between the joint reconstruction and the reference, and fraction of runs within 3 dB of the reference.

N_{rx}	runs	reference [dB]	no corr. [dB]	joint [dB]	joint − ref. [dB]	within 3 dB [%]
2	96	−60.8	−17.4	−39.3	22.9	6
3	96	−55.5	−13.8	−53.9	1.1	65
4	256	−45.2	−15.1	−44.6	0.3	84
6	96	−41.5	−12.2	−41.4	0.2	91
8	96	−39.1	−9.5	−39.1	0.2	96

With three or more channels the joint reconstruction is within a fraction of a dB of the reference in the median (Table 7.2). Of the 24 unresolved runs, 10 have two channels and 9 the equally spaced baselines $[0, 50, 100, 150]$ m; the others are 7×7 grids on a mountain, a valley or a volcano with long baselines.




Figure 7.6: 49 targets 250 m apart on random mountains (relief 1 000 m), largest cross-track baseline 300 m, channel 0 on the transmitter. Top: the targets and the terrain near them (left) and along the whole azimuth line (right). Below: impulse responses of the reference and of the joint reconstruction over the whole line for $N_{\mathrm{rx}} = 2$, 3, 4 and 8.

7.5 Limits

DEM errors. The phase error is $\approx 9.0 \times 10^{-5}\, b_{\mathrm{xt}}\, \delta h$ rad, so the tolerance falls with the baseline (Figure 7.8). With an rms height error of 5 m, the joint reconstruction stays at -36 dB for $b_{\mathrm{xt}} = 135$ m but rises to -20 dB for 300 m.

To do: Confirm the scene and the error model behind Figure 7.8 (taken from the audit notes) and add the error-free point for ${b_{\mathrm{xt}}}^{\max} = 300$ m.

Noise. Relative to the standard reconstruction, the joint reconstruction raises the output noise by 0.3 dB to 4 dB in normal configurations, by 12 dB with equally spaced baselines and by 8 dB with two channels and 300 m. The regularisation keeps these numbers bounded where the problem is ill conditioned.

Configurations without redundancy. With two channels, or with baselines whose phases coincide at some heights, the data do not contain the information to separate the parcels. This is a property of the formation and should be considered in its design.

Not yet tested. Real antenna patterns (the model uses the simulated reference chirp), real orbits and baselines varying along the orbit, layover, distributed scenes in 2-D, noise combined with DEM errors, and real data.




Figure 7.7: A page of the 1-D sweep: seven targets on a fractal alpine relief (0 m to 2 000 m, slopes up to 54°), $N_{\mathrm{rx}} = 4$, $b_{\mathrm{xt}} = [0, 300, 119.8, 100.5]$ m. The joint reconstruction (top left) reaches the reference level (−37.6 dB against −38.2 dB); without correction the highest ambiguity is −5.1 dB. Bottom right: the ΔC_0 of every channel along the whole line, read from the DEM.




Figure 7.8: Joint reconstruction over the whole line with a random DEM error (five targets on the mountain of Figure 5.6).

8 Conclusions and outlook

8.1 Conclusions

- Cross-track baselines turn topography into a channel-dependent phase that the standard multichannel reconstruction cannot absorb, $\varphi_i \approx 2\pi b_{\mathrm{xt},i} h/(\lambda r_0 \tan\theta)$. Without correction the median highest ambiguity of the sweeps is $-8.4\,\mathrm{dB}$ in 1-D and $-13.9\,\mathrm{dB}$ in 2-D, against a reference near $-48\,\mathrm{dB}$.
- SATA computes the right phase from the DEM, but applied to each aliased channel before the reconstruction it can give only one phase to the parcels of positions $X \approx 6.2\,\mathrm{km}$ apart that share a Doppler bin. It is exact only when the terrain has the same height at all those positions; elsewhere it leaves a structural residual that is predicted from the geometry within about 1 dB, and with a DEM only it improves the median by 5.5 dB at best.
- Placing the DEM phase inside the inversion solves this. The joint reconstruction over the whole line models every channel from the focused line and the DEM and inverts it by regularised least squares. Using only the system parameters and the DEM it reaches a median of $-40.6\,\mathrm{dB}$ in 1-D (78 % of the runs within 10 dB of the reference, about 90 % for four or more channels) and $-44.4\,\mathrm{dB}$ in 2-D, where with three or more channels it is within 1 dB of the reference in the median.
- The remaining failures are formations whose baselines do not separate the folded parcels (two channels, equally spaced baselines). The regularisation leaves the ambiguity there instead of amplifying noise.
- The accuracy is limited by the DEM: the phase error grows as $b_{\mathrm{xt}}\,\delta h$, so long baselines need accurate DEMs.

8.2 Outlook

- Validation with realistic antenna patterns, orbits and baselines that vary along the orbit, and eventually with real multistatic data.
- 2-D: distributed scenes, layover and shadow, finer range resolution (envelope interpolation) and wide swaths (range-dependent kernels in blocks).
- Joint estimation of a DEM correction, using the unexplained part of the channels as the cost.
- Use of the conditioning analysis (Section 3.2) as a design rule for the cross-track baselines of a formation.
- Computational cost: block-wise or GPU implementation of the model and its adjoint for full scenes.

Bibliography

[1] G. Krieger, N. Gebert, and A. Moreira, "Unambiguous SAR signal reconstruction from nonuniform displaced phase center sampling," *IEEE Geoscience and Remote Sensing Letters*, vol. 1, no. 4, pp. 260–264, 2004. (cited on pages 1 and 9)

[2] N. Gebert, G. Krieger, and A. Moreira, "Digital beamforming on receive: Techniques and optimization strategies for high-resolution wide-swath SAR imaging," *IEEE Transactions on Aerospace and Electronic Systems*, vol. 45, no. 2, pp. 564–592, 2009. (cited on pages 1 and 9)

[3] N. Sakar, M. Rodriguez-Cassola, P. Prats-Iraola, and A. Moreira, "Azimuth reconstruction algorithm for multistatic SAR formations with large along-track baselines," *IEEE Transactions on Geoscience and Remote Sensing*, vol. 58, no. 3, pp. 1931–1940, 2020. (cited on pages 1 and 5)

[4] N. Sakar, *Processing Approaches for Multistatic Large Along-Track Baseline SAR Constellations*. PhD thesis, Technische Universität München, Munich, Germany, 2022. (cited on pages 1 and 5)

[5] P. Prats, A. Reigber, and J. J. Mallorqui, "Topography-dependent motion compensation for repeat-pass interferometric SAR systems," *IEEE Geoscience and Remote Sensing Letters*, vol. 2, no. 2, pp. 206–210, 2005. (cited on pages 1 and 13)

[6] P. Prats Iraola, *Airborne Differential SAR Interferometry*. PhD thesis, Universitat Politècnica de Catalunya, Barcelona, Spain, Nov. 2005. (cited on pages 1 and 13)

[7] M. R. Hestenes and E. Stiefel, "Methods of conjugate gradients for solving linear systems," *Journal of Research of the National Bureau of Standards*, vol. 49, no. 6, pp. 409–436, 1952. (cited on page 18)

[8] L. N. Trefethen and D. Bau, *Numerical Linear Algebra*. Philadelphia: SIAM, 1997. (cited on page 18)