

合同号Contract number:

1002001450

港机项目定值换算				
Conversion of fixed value for ZPMC projects				
额定参数输入 Rated parameter input	主变 main transformer	辅变 Auxiliary transformer		
变压器额定容量Sn = Transformer rated capacity Sn =	1600	250	KVA	
系统额定电压Un = System rated voltage Un=	11	11	KV	
CT一次侧额定电流In= CT primary side rated current In=	125	25	A	
零序CT一次侧额定电流In0= Core balance CT primary side rated current In0=	50	50	A	
定值输出 Setting value output	主变 main transformer	辅变 Auxiliary transformer		时间 time
(正常反时限)过流保护 (I>) = (Normal inverse time limit) overcurrent protection (I>)=	0.67	0.52	*In	时间系数K=0.5 Time coefficient K=0.5
(定时限)短路保护 (I>>) = (Definite time limit) Short circuit protection (I>>)=	2.69	2.10	*In	0.1s
过压保护 U>= Overvoltage protection U>=	1.1	1.1	*Un	0.5s
欠压保护 U<= Undervoltage protection U<=	0.9	0.9	*Un	0.5s
接地保护 (Io>) = Grounding protection (Io>)=	0.10	0.10	*In0	0.3s
表格使用说明：根据合同单线图的各种参数，输入到表格定值输入区，便自动生成具体定值。 I>正常反时限设置（IEC Norm. inv.）: SGF1/1=1, SGF1/2=1, SGF1/3=0, 加权值为3; Io>>关闭设置: SGF2/6=1, 加权值为32 定时限描述: IEC Def. Time 零序CT二次为5A时（合成零序），则一次电流值除以5 Table Instructions: Based on the various parameters of the contract single line diagram, input them into the fixed value input area of the table to automatically generate specific fixed values. I> Normal inverse time setting (IEC Norm. inv.): SGF1/1=1, SGF1/2=1, SGF1/3=0, with a weighted value of 3; Io>>Off setting: SGF2/6=1, with a weighted value of 32 Description of time limit: IEC Def. Time When the secondary value of the core balance CT is 5A (synthesized core balance), the primary current value is divided by 5				
上海振华港机整定值计算公式: The calculation formula for the setting value of ZPMC: I>: 1*S/(1.732*Un*In1) I>>: 4*S/(1.732*Un*In1) Io>: 5/In0 上海港机重工整定值计算公式: Calculation formula for setting value of ZPMC: I>: 1.25*S/(1.732*Un*In1) I>>: 5*S/(1.732*Un*In1) Io>: 5/In0 其中 among above S: 变压器额定容量, Un: 系统额定电压, In1: CT一次侧电流, In0: 零序CT一次侧电流 S: Transformer rated capacity, Un: system rated voltage, In1: CT primary side current, In0: core balance CT primary side current 举例: 系统额定电压120KV, 变压器容量2000KVA, CT变比300/5A, 零序CT变比50/1A, 那么继电器140C的整定值 I>: 1*2000/(1.732*12*300)=***In。 Io>: 5/50=0.1In0 For example, if the rated voltage of the system is 120KV, the transformer capacity is 2000KVA, the CT ratio is 300/5A, and the zero sequence CT ratio is 50/1A, then the setting value I of relay 140C is greater thanI>: 1*2000/(1.732*12*300)=***In Io>: 5/50=0.1In0				