Lutron To DMX Bridge

Staff Guides for macOS

For version 0.5.0 · prepared 7 November 2026

Contents

Start Here 3
- Which guide do I need? 3
- What the app does, in one minute 3
- Words used in these guides 3
- Screenshots 4
- What is finished and what is still pending 4
- Contacts (fill in) 5

1. macOS Setup Guide 6
- Before you start 6
- Part 1: Download the app 6
- Part 2: Install the app 7
- Part 3: Open it for the first time (Mac security steps) 7
- Part 4: Connect to the Lutron system (first run only) 9
- Part 5: Connect the lighting console (DMX / Art-Net input) 10
- Part 6: Everyday use 11
- Part 7: Your first-day checks 12

2. Export and Import Settings 13
- What gets saved (and what does not) 13
- Exporting your settings 13
- Importing settings 14
- The automatic safety copy 16
- Recipes 16
- If something goes wrong 17
- Staying safe with these files 18

3. Troubleshooting Guide 19
- Step 0: Look at the five chips 19

A. The app will not open 20
B. Lutron connection problems 20
C. Art-Net DMX input problems 22
E. Reading the Status tab 26
F. The page itself (Server chip) 27
G. Schedule sets and Performance mode problems 27
H. Updates 28
I. Alerts 29
J. Getting help 29
Quick reference: problem to section 30

4. Performance Checklist 31

A. One-time setup (do once, not every show) 31
B. Before the show day (day before, or earlier) 32
C. Opening the app (show day) 33
D. Pre-show checks (aim for 30 minutes before doors) 33
E. Start Performance mode 34
F. Switch on DMX input 35
G. Last checks before the show starts 35
H. During the show 36
I. After the show 36
J. If the app or the Mac stops during the show 38
K. One-page summary (cut out and keep by the Mac) 38

Start Here

These guides are for people who use the app but do not build it. You do not need any technical knowledge.

Written for: version 0.5.0 (released 7 Nov 2026), on a Mac with an Apple chip (M1 or newer).

Which guide do I need?

I want to…	Open this guide
Install the app on a Mac for the first time	**1. macOS Setup Guide**
Save my settings, or move them to another Mac	**2. Export and Import Settings**
Fix something that is not working	**3. Troubleshooting Guide**
Run a show tonight	**4. Performance Checklist** (print this one)

What the app does, in one minute

The app sits between your lighting console and the building's Lutron lighting system.

- Your console sends DMX (over Art-Net on the network).
- The app listens, and passes the levels on to the Lutron lights.
- You control it from a web page that opens in your browser. The page is served by the app on your own Mac. Nothing goes to the internet except an optional check for new versions.

Performance mode is a button that turns off the Lutron timed events (schedules) while a show runs, and puts them back exactly as they were afterwards.

Words used in these guides

Word	What it means
The app	Lutron To DMX Bridge, installed on your Mac
The control page	The web page that the app opens in your browser
The log window	The small window with scrolling text that opens with the app. Do not close it while the app is needed

Word	What it means
Repeater / controller	The Lutron box that controls the lights
Schedule	A timed event inside the Lutron system (for example "lights on at dusk")
Schedule set	A group of schedules that the app can turn off together. **Performance mode** is a schedule set
Chips	The five small coloured labels at the top right of the control page (Lutron, DMX in, Output, Alerts, Server)
Green / amber / red	Green is fine. Amber is worth a look. Red is a problem

Screenshots

These guides contain boxes that look like this:

> 📷 **Screenshot needed:** description of what to capture

Each box marks a place where a screenshot would help. Take them on your own Mac once the app is installed. Press **Shift + Command + 4**, then **Space**, then click the window.

What is finished and what is still pending

Checked against the app's code on 7 Nov 2026. If a feature is marked **pending**, it is not in the released app yet. Do not look for it.

Feature	Status
Install, Gatekeeper steps, Lutron connection, DMX / Art-Net input	In version 0.5.0
Status chips, Status tab, **Clear alerts** button	In version 0.5.0
Lutron latency graph and chip (how fast the repeater answers)	In version 0.5.0
Schedule sets (Performance mode)	In version 0.5.0
Export and import settings	In version 0.5.0
Clear Lutron queue button (Status tab)	**Pending.** Open change #13, not merged, not released

Feature	Status
Level step, % setting (DMX tab)	**Pending.** Open change #12, not merged, not released

Not yet tried on real equipment (so wording and behaviour may differ a little):

- Turning Lutron schedules off and on from the app (this is what Performance mode does). **Test it with one harmless schedule before you rely on it for a show.**
- Export and import of settings, on a Mac.
- The macOS security (Gatekeeper) screens. The wording is written from how macOS normally behaves and may differ on your version.

Contacts (fill in)

Person who runs the lighting system	
Person who set up this app	
Lutron controller address	
Lutron integration user name (do not write the password here)	
Art-Net universe used by the console	
Where the saved settings file is kept	

1. macOS Setup Guide

How to download, install and open Lutron To DMX Bridge on a Mac, and connect it to the Lutron system and to your lighting console.

Time needed: about 15 minutes the first time. After that you only double-click the app.

Before you start

You need:

1. **A Mac with an Apple chip (M1 or newer).** To check: click the Apple menu (top-left), choose **About This Mac**, and look for "Apple" next to **Chip**. The app does not run on older Intel Macs.
2. **The Mac on the same network as the Lutron system.** Wi-Fi works, but a network cable is more dependable for a show.
3. **For a RadioRA 2 system: the integration user name and password.** The person who runs the lighting system has them.
4. **A lighting console that can send Art-Net** (or a DMX-to-Art-Net box). You need to know which Art-Net **universe** it sends.

Part 1: Download the app

1. Open your web browser and go to: **https://github.com/m3636/Lutron-to-DMX-Bridge/releases**
2. Find the newest release at the top of the page. The latest at the time of writing is **0.5.0**.
3. Scroll to **Assets** and click the file ending in **-macOS.zip**, for example `LutronToDMXBridge-0.5.0-macOS.zip`.
   - Do **not** pick the `Windows` file or `SHA256SUMS.txt`.
   - If you see "404" or "Page not found", ask the person who shared this app to give you access.
4. The file goes to your **Downloads** folder.

> 📷 **Screenshot needed:** the Releases page with the "-macOS.zip" file circled.

Part 2: Install the app

1. Open the **Downloads** folder (click **Downloads** in the Finder sidebar).
2. Double-click the `.zip` file. An item called **Lutron To DMX Bridge** appears next to it. Safari may already have done this for you.
3. Open a second Finder window and click **Applications** in the sidebar.
4. **Drag** *Lutron To DMX Bridge* from Downloads into the Applications window.
    - This step matters. If you run the app from Downloads, it cannot update itself later.
5. You can now delete the `.zip` file from Downloads.

> 📷 **Screenshot needed:** the app being dragged into Applications.

Part 3: Open it for the first time (Mac security steps)

Your Mac will block the app the first time. The app is safe, but it is not signed with an Apple developer account, so macOS (Gatekeeper) is cautious. You only do this once. It sometimes takes two or three tries. That is normal.

Steps

1. In **Applications**, double-click **Lutron To DMX Bridge**.
2. A message says the app **cannot be opened**, or that **Apple could not verify** it.
    - Click **Done**.
    - **Do not click "Move to Trash".**
3. Click the Apple menu (top-left) and choose **System Settings**.
4. In the left sidebar, click **Privacy & Security**.
5. Scroll down to the **Security** section. You will see a line like: **"Lutron To DMX Bridge" was blocked to protect your Mac.** Click **Open Anyway**.
6. Type your Mac password (or use Touch ID) when asked.
7. Go back to **Applications** and double-click **Lutron To DMX Bridge** again.
8. A new message asks if you are sure. Click **Open Anyway** (on some versions the button says **Open**).
9. Wait a few seconds. Two things appear:
    - a small **log window** with scrolling text, and
    - your web browser, showing the **control page**.

> 📷 **Screenshot needed:** (a) the "cannot be opened" message, (b) System Settings > Privacy & Security with the "Open Anyway" button, (c) the final "Open Anyway" prompt.

If it does not work

What you see	What to do
The same "cannot be opened" message keeps coming back	Normal. Double-click the app again, and go through steps 3 to 8 once more.
There is no **Open Anyway** button in System Settings	Double-click the app once more, then look in **Privacy & Security** again. The button only shows for about an hour after the last blocked attempt.
Your Mac says the app is **damaged**	Delete the app from Applications, download the zip again and repeat Parts 1 to 3.
Nothing at all happens	Wait 30 seconds. The first start is slow. Then try again.

Other ways, only if the steps above fail

Right-click method. Hold **Control** and click the app (or right-click it). Choose **Open**, then click **Open** in the message. On macOS 15 (Sequoia) and later this often does not work. Use the System Settings steps instead.

Terminal method (last resort). Only do this if someone technical agrees. It removes the "downloaded from the internet" mark from the app:

1. Open **Terminal** (press Command + Space, type *Terminal*, press Return).
2. Paste this line and press Return:

   ```
   xattr -dr com.apple.quarantine "/Applications/Lutron To DMX Bridge.app"
   ```

3. Close Terminal and double-click the app again.

> **Note:** The exact wording of these messages changes between macOS versions. If yours is not word for word the same, look for the nearest match. The idea is always: tell the Mac you trust this app.

The "local network" question

The first time the app runs, your Mac may ask whether it can **find and connect to devices on your local network**. Click **Allow**.

If you click **Don't Allow**, the app cannot find the Lutron system or receive Art-Net. To fix it later: **System Settings > Privacy & Security > Local Network**, then switch on **Lutron To DMX Bridge**. Quit and reopen the app afterwards.

Part 4: Connect to the Lutron system (first run only)

The first time, the control page opens on the **Settings** tab. If your browser did not open, click **Open web GUI** in the log window.

> 📷 **Screenshot needed:** the Settings tab, "Lutron system" card.

1. Under **Lutron system**, open **System type** and choose:
    - **RadioRA 2 (Main Repeater, telnet integration)**: the classic system with a "Main Repeater" box.
    - **RadioRA 3 / RA2 Select / Caseta (LEAP)**: newer systems with a "processor" or "Smart Bridge".
    - Not sure? Ask the person who runs the lighting system.
    - **Simulator (demo, no hardware)** is a pretend house for practice. It never touches real lights.
2. Click **Find my controller**.
    - For RadioRA 2, first tick **Also scan the whole network (slower; needed for RadioRA 2)**. Then click **Find my controller**. Be patient. It can take a minute.
3. When your controller appears in the list, click **Use this one**. The address fills in.
    - If nothing is found, check the Mac is on the same network, then try again.
    - If it still fails, type the controller's address (it looks like `192.168.1.50`) into **Host / IP address**.
4. Enter the login:
    - **RadioRA 2:** type the **Integration user name** and **Integration password**.
    - **RadioRA 3 / RA2 Select / Caseta:** click **Pair**. Within about 3 minutes, press the small button on the back of the Lutron processor or bridge. Come back and wait for the word *Paired*.
5. Click **Save & reconnect**. A message at the bottom says *Connected* when it works.
6. Click the **Devices** tab. Your rooms and lights should appear.

You do not need to do this again. The app remembers.

> **Light names show as numbers (RadioRA 2)?** The app needs the system's "Integration Report" to show names. In **Settings**, the field **Integration Report path (optional)** takes the location of that file. Ask the person who set up the system for it.

> **Slow first start (RadioRA 2)?** On RadioRA 2 the app downloads a file of light names from the repeater. This can be slow. Version 0.5.0 waits longer, retries, and keeps a copy for next time. If the first start fails, wait a minute and click **Save & reconnect** again.

Part 5: Connect the lighting console (DMX / Art-Net input)

Skip this part if you do not use a lighting console. **Ask whoever patched the console before changing anything here.**

> **Read this first.** While DMX input is on, every light you have *mapped* follows the console. A mapped light that the console is not controlling is set to **0** (off). Map only the lights you want the console to own, and switch DMX input on only when the console is ready.

1. Click the **DMX** tab.
2. Under **DMX input**, set:
   - **Source:** *Art-Net (UDP 6454)*.
   - **Universe:** the Art-Net universe your console sends. **Art-Net universes start at 0.** (sACN universes start at 1. Some consoles show Art-Net universes starting at 1, so if nothing arrives, try one lower.)
   - **Listen on IP:** leave as `0.0.0.0` (all network connections).
   - **Max updates / second / zone:** leave the default (5) unless told otherwise.
   - **Max updates / second, all zones:** leave the default (20). Lower it to 10 if the lights lag (see the Troubleshooting Guide).
3. Under **Channel mapping**, decide which light listens to which DMX channel:
   - Click **Auto-assign unmapped zones** to give every unmapped light the next free channels, starting at the **Start** number. Choose **Params** first (for example *intensity (1 ch)*).
   - Or click **Add row** to add one light by hand, and set its **Address**.
   - Untick the **On** box on a row to ignore that light.

4. Read any warnings shown under the settings (for example "channel overlaps"). Fix them.
5. Click **Save & apply** (top right of the DMX tab).
6. To switch the input on, tick **Enable DMX input**, then click **Save & apply**.
7. Start the console sending Art-Net. Look at the **DMX in** chip at the top right. It should turn green and show something like `44 fps · U0`.
8. Watch the **Live monitor** at the bottom of the DMX tab. The little boxes should move when you move a fader on the console.

> 📷 **Screenshot needed:** the DMX tab with the DMX in chip green and the Live monitor moving.

> **The app remembers this setting.** If DMX input was on when you closed the app, it switches itself on again next time the app opens.

> **Which Mac port is used?** The app listens on UDP port **6454** (Art-Net). Nothing else on the Mac should need that port.

Part 6: Everyday use

Tab	What it is for
Devices	Every room and light. Use the switch to turn on or off and the slider to dim. **All on** / **All off** do a whole room.
Scenes	Your own saved looks. Click **Activate** to set many lights at once. These belong to this app, not to Lutron.
Schedules	**Schedule sets** (including Performance mode) at the top, and the list of Lutron schedules below.
DMX	Console input, channel mapping and the live monitor.
Status	Health of the whole system, graphs, and the **Clear alerts** button.
Settings	Lutron connection, updates, **Export & import settings**, Lutron backup.

Starting the app: double-click **Lutron To DMX Bridge** in Applications. If it is already running, double-clicking just reopens the control page.

Stopping the app: click **Quit** in the log window (or close that window) and confirm. Quitting stops DMX control. **The lights stay as they are.**

Keeping it running: *minimise* the log window (the yellow button). Do not close it.

Updating: a blue bar at the top of the control page says when a newer version is out. Click **Update now** at a time that suits you (never in the middle of a show). Your settings and scenes are kept. If a schedule set is active or DMX input is live, the app asks you to confirm first.

Part 7: Your first-day checks

Do these once, with the person who runs the lighting system, **before the first show**:

1. ☐ **Devices** tab: toggle one harmless light on and off. It follows.
2. ☐ **Schedules** tab: the schedule list matches what the lighting system has.
3. ☐ Make a **Performance mode** schedule set (see the Performance Checklist, section A).
4. ☐ Test Performance mode on **one harmless schedule**: activate it, check that the schedule shows *disabled*, restore it, and check it shows *enabled* again. *This has not yet been tried on the real equipment, so do not skip it.*
5. ☐ **DMX** tab: move a console fader and see a light follow.
6. ☐ **Settings > Export & import settings > Download settings file**, and keep the file safe (see guide 2).

Problems? See guide 3, the Troubleshooting Guide.

2. Export and Import Settings

How to save the app's settings to a file, and how to load them back. Use this to:

- keep a safety copy before a big show or an update,
- move the app to a different Mac,
- recover if the settings were lost or broken.

Available in: version 0.5.0 and later. **Not yet tried on a real Mac with the real Lutron system.** Try it once on a quiet day before you rely on it.

What gets saved (and what does not)

Saved in the settings file:

- the Lutron connection (system type, address, port),
- the DMX input settings and the light-to-channel mapping,
- your own scenes,
- your schedule sets, such as Performance mode (and the remembered schedule states, if a set was active when you exported),
- the update preference, and the control page's web address and port.

Not saved:

- the lights, rooms and schedules inside the Lutron system itself (those live in the Lutron equipment; use **Settings > Backup** for a reference copy),
- the app itself,
- log files.

> **Two different things. Export & import settings** saves *this app's* setup. **Backup** (just below it on the Settings tab) saves what the *Lutron system* told the app, as a reference. It contains the installer's name and contact details. Keep it private.

Exporting your settings

1. Open the control page and click **Settings**.
2. Scroll to the card called **Export & import settings**.

3. Decide about the passwords box (see "The credentials box" below). **If unsure, leave it unticked.**
4. Click **Download settings file**.
5. Your browser saves a file named like: `lutron-to-dmx-bridge-config-20261107-183000.json` It goes to your **Downloads** folder, unless your browser asks where to save.
6. Move the file somewhere safe (a USB stick or a private folder). Do not leave it only in Downloads.

> 📷 **Screenshot needed:** the "Export & import settings" card.

> **Where do the files go?** The *Download settings file* button saves only to the place your **browser** downloads files. The app does not keep its own copy of an export. Its own `backups` folder is described below.

The credentials box

The box says **"Include the Lutron integration login, update token and pairing certificates"**.

Box	What is in the file	When to use it
Unticked (default)	No passwords or keys.	Normal safety copies. If you import this file later, the app keeps the login it already has.
Ticked	Includes the Lutron integration user name and password, and any pairing certificates, **in plain text**.	Only when setting up a brand-new Mac so it can connect straight away without asking for the login again.

If you tick the box, a yellow warning appears. It means:

- **Anyone who has the file can control the lights over the network.**
- Do **not** email it, post it in chat, or attach it to a report.
- Move it with AirDrop or a USB stick, and **delete it when you are done**.

Importing settings

Use this on a new Mac, after a reinstall, or to go back to a saved copy.

1. Make sure the app is installed and running (guide 1). The Lutron connection does not need to work yet.
2. Click **Settings**, and scroll to **Export & import settings**.
3. Click **Import from file…**
4. Choose your settings file (a `.json` file).
5. A panel opens titled **Import** . It tells you:
    - which version of the app made the file, and when,
    - whether the login is **included in the file** or **not in the file** (the ones the app has now are kept),
    - a list of **sections**, each with a tick box: the Lutron connection, DMX, scenes, schedule sets and so on. Each section lists what would change, or says *no changes*.
6. Read any yellow warnings. Common ones:
    - a scene uses a light the connected Lutron system does not have,
    - a file path (for example the Integration Report) does not exist on this Mac.
7. Leave the default ticks unless you have a reason. Untick any section you do not want.
8. Click **Import selected**.
9. A green message says **Settings imported**. It lists what was imported and gives the path of an automatic backup of your *previous* settings.
10. Click **Close**. The app reconnects to the Lutron system by itself. Check that the **Lutron** chip turns green.

> 📷 **Screenshot needed:** the import panel with sections and the "Import selected" button.

Rules to know before you import

- **A ticked section is replaced as a whole.** Anything in that section that is not in the file is removed. For example, importing "Scenes" replaces all your scenes with the scenes in the file.
- **The control page's web address and port are not ticked by default.** They decide who can reach the app. Leave them alone unless a technical person asks you to import them.
- **Schedule sets can be blocked.** If a schedule set (for example Performance mode) is **active right now**, and it is not in the file, the *Schedule sets* section cannot be imported. Go to the **Schedules** tab, click **Restore schedules**, and try again. Or untick that section.
- **Bringing back a remembered schedule state.** If the file was made while a set was active, a tick box offers to bring back its saved schedule states. Only tick it if you know

why. It is only available when no set is active now.

- **Files from other versions.**
  - A file from a *newer, incompatible* format is refused. The message tells you to update the app.
  - A file from an *older* format is upgraded automatically.
  - A file from a newer app version is accepted with a warning. Settings this version does not understand are ignored.
- **Old Lutron backup files** (from *Download backup*) can also be imported, but only the app's own settings are used, not the password.

The automatic safety copy

Every time you import, the app first saves your *current* settings to a file named like:

`config-before-import-20261107-183500.json`

Where: `~/Library/Application Support/LutronToDMXBridge/backups/`

This file includes your passwords (it is a full copy). It can only be read by your Mac user.

To undo an import: import that `config-before-import-…` file using the steps above.

How to open that folder on a Mac

1. In the Finder, click **Go** in the menu bar, then **Go to Folder…** (or press **Shift + Command + G**).
2. Paste: `~/Library/Application Support/LutronToDMXBridge/backups`
3. Press Return.

Other things in the `LutronToDMXBridge` folder: `config.json` (the live settings), `logs/` (log files), and Lutron backups made with the *Download backup* button (`lutron-backup-…json`).

Recipes

A. Safety copy before a show or an update

1. **Settings > Export & import settings**, leave the passwords box unticked, click **Download settings file**.
2. Copy the file to a USB stick or a private cloud folder you trust.
3. You are done. Nothing changes in the app.

B. Move the app to a different Mac

On the old Mac

1. Open **Settings > Export & import settings**.
2. Tick **Include the Lutron integration login, update token and pairing certificates** (if you want the new Mac to connect without asking again).
3. Click **Download settings file**.
4. Copy the file to the new Mac by AirDrop or USB stick. **Do not email it.**
5. Delete the file from the old Mac's Downloads folder and from any USB stick afterwards.

On the new Mac

1. Do guide 1, Parts 1 to 3 (download, install, open the first time).
2. You can skip Part 4 (connecting to Lutron). The import fills in the connection.
3. Click **Settings > Export & import settings > Import from file...**, pick the file and click **Import selected**.
4. Read the warnings. Fix anything marked as a missing path (for example, point **Integration Report path** at a file that exists on this Mac).
5. Check the **Lutron** chip is green. Open **Devices** and **Schedules** to confirm.
6. **Delete the settings file** from the new Mac's Downloads folder.

C. Recover after the settings were lost

1. Install the app (guide 1, Parts 1 to 3) if needed.
2. Import your last settings file (recipe B, new Mac steps).
3. If you have no file, set the app up again from guide 1, Part 4 onwards.

If something goes wrong

What you see	What to do
"Cannot read . It is not valid JSON."	The file is damaged or is not a settings file. Use another copy.
"That file is too big to be a settings export."	You picked the wrong file. A settings file is small.
"Cannot import " with a message about a newer format	Update the app (blue bar > **Update now**), then try again.

What you see	What to do
The *Schedule sets* section is greyed out with a reason	A schedule set is active. Restore it first (Schedules tab), or leave that section out.
After import, the **Lutron** chip is red	The login may not have been in the file. Go to **Settings > Lutron system**, type the user name and password, and click **Save & reconnect**. For RadioRA 3 / Select / Caseta, you may need to **Pair** again.
A warning says a path does not exist	Normal on another Mac. Fix the path in **Settings** (for example the Integration Report).
You imported by mistake	Import the `config-before-import-…` file from the `backups` folder (see above).

Staying safe with these files

- A settings file made **without** the passwords box is fairly harmless, but still keep it private. It contains your network addresses.
- A settings file made **with** the passwords box, and every `config-before-import-…` file, contain passwords. Treat them like a password list.
- **Never attach any of these files, or `config.json`, to a bug report.**
- If you must share an example, share a screenshot of the Status tab instead.

3. Troubleshooting Guide

What to do when something is not working. Start with **Step 0**, then jump to the section that matches what you see.

> Items marked **[PENDING]** are not in the released app (version 0.5.0) yet. Ignore them until the app is updated and the feature appears.

Step 0: Look at the five chips

The five coloured chips at the top right of the control page tell you where the problem is. **Green** is fine, **amber** is worth a look, **red** is a problem. Click any chip for details. The **Status** tab shows the same numbers with graphs of the last 2 minutes.

> 📷 **Screenshot needed:** the five chips, all green, with a label on each.

Chip	What it tells you	If it is not green, go to
Lutron	Is the app connected to the lighting system, and how quickly does it answer. Shows a number in ms when healthy.	Section B
DMX in	Is the console's signal arriving. Shows frames per second and the universe.	Section C
Output	How many commands per second the app is sending to the Lutron system. "held" means lights are waiting their turn.	Section D
Alerts	How many warnings and errors have been logged since the app started.	Section I
Server	Is this browser still hearing from the app.	Section F

Quick rule: red or amber *Lutron* means the Lutron side. Red or amber *DMX in* means the console side. If both are fine and lights are still wrong, the problem is the mapping (Section C, part 4).

A. The app will not open

What you see	What to try
"Cannot be opened" or "Apple could not verify"	This is the Mac security check. Follow guide 1, Part 3. Click **Done** (never **Move to Trash**), then **System Settings > Privacy & Security > Open Anyway**, then reopen the app. It can take two or three tries.
No **Open Anyway** button	Double-click the app once more, then check System Settings again. The button only appears for about an hour after the last blocked attempt.
"The app is damaged"	Delete the app, download the zip again from the Releases page, and reinstall (guide 1, Parts 1 to 3).
The app opens but the browser does not	Click **Open web GUI** in the log window. Or type `http://127.0.0.1:8080` into your browser's address bar. If the log window says it chose another port (for example 8081), use that number.
Safari shows an error page, nothing loads	Make sure the log window is still open (you can minimise it). If you closed it, the app stopped. Open the app again.
Another copy is already running	Double-clicking again just opens the control page again. That is normal.
The chips look blank or the page looks wrong after an update	Your browser kept an old copy of the page. Hold **Shift + Command** and press **R** to reload fully.

B. Lutron connection problems

B1. The Lutron chip is red ("offline")

1. Click the **Lutron** chip. It says *Not connected*, or *Reconnecting (attempt N, next try in X s)*.
    - *Reconnecting* means the app is still trying. Wait a minute.
2. Check your Mac is on the right network (Wi-Fi name, or cable plugged in). It must be the network the Lutron system is on.
3. Check **System Settings > Privacy & Security > Local Network**: the switch next to **Lutron To DMX Bridge** must be **on**. If you change it, quit and reopen the app.
4. Open **Settings > Lutron system**. Check:
    - **System type** is correct,
    - **Host / IP address** is the controller's address,
    - **Integration user name** and **Integration password** are right (RadioRA 2).
5. Click **Save & reconnect**.

6. Still red? Click **Find my controller** (tick *Also scan the whole network* for RadioRA 2). If the controller's address has changed, choose it from the list with **Use this one** and click **Save & reconnect**.

B2. Find my controller finds nothing

1. Your Mac must be on the same network (and not a "guest" network) as the Lutron system.
2. Tick **Also scan the whole network** and try again. It takes longer.
3. Local Network permission must be on (see B1, step 3).
4. If the building's network blocks device discovery, type the controller's address by hand. Ask whoever runs the lighting system for it.

B3. The Lutron chip is amber

Amber means the Lutron system is slow to answer. The chip shows the **median round trip in milliseconds**. It turns amber when the slowest 5% of answers take more than 500 ms.

Click the chip to see:

- **Lutron latency**: last, median and 95th percentile (p95).
- **Commands in flight**: commands sent that the Lutron system has not yet confirmed. A number that keeps climbing means the Lutron system is falling behind.

Go to Section D.

B4. Lights have numbers instead of names (RadioRA 2)

The app needs the Integration Report to show names. Ask the person who set up the system for it, then enter its location in **Settings > Lutron system > Integration Report path**, and click **Save & reconnect**.

B5. Log says "Could not download … DbXmlInfo.xml: timed out" (RadioRA 2)

The repeater is slow to hand over its list of lights. The app waits longer, retries, and keeps a copy of the last good download. On the very first start there is no copy yet.

1. Wait one minute, then click **Save & reconnect** again.
2. Do not click it many times in a row. The repeater handles one request at a time.
3. Still failing? Ask someone technical to save the file `http://<repeater address>/DbXmlInfo.xml` from a browser, and use it as the **Integration Report path**.

B6. Lights on the page do not match the real lights

Changes made at a wall keypad show up on the page a moment later. If they never do, check the **Lutron** chip and **Server** chip (Section F).

B7. RadioRA 3 / Select / Caseta only: pairing fails

1. Click **Pair** in Settings, and press the small button on the back of the processor or bridge **within about 3 minutes**.
2. If the app shows a certificate warning and asks you to confirm trust, only agree if you are sure this is your own controller.
3. Wait for the word *Paired*, then click **Save & reconnect**.

C. Art-Net DMX input problems

Work through this list from the top. It is in the order problems usually happen.

C1. Is DMX input switched on?

1. Click the **DMX** tab.
2. **Enable DMX input** must be ticked.
3. **Source** must be **Art-Net (UDP 6454)**.
4. After any change, you must click **Save & apply** (top right of the tab). Changes are not used until you do.

C2. What does the DMX in chip say?

Chip says	Meaning	What to do
off (grey)	DMX input is switched off.	Tick **Enable DMX input** on the DMX tab, then **Save & apply**.
stopped (red)	DMX is enabled but not running. The chip tooltip gives the reason.	Click the chip and read the **Error** line. Fix what it says (for example a wrong **Listen on IP**), then **Save & apply**. If you cannot tell what it means, send the log (Section J).
error (amber)	A problem was reported.	Click the chip and read the **Error** line.
waiting (amber)	Listening, but no packet has ever arrived.	Go to C3.

Chip says	Meaning	What to do
no data N s (amber)	Data was arriving but stopped N seconds ago.	The console, the network cable or the Art-Net box stopped sending. Go to C3.
44 fps · U0 (green)	Receiving Art-Net on universe 0.	Fine. If lights still do not move, go to C4.

C3. Nothing is arriving

Check these in order:

1. **Is the console actually sending Art-Net?** Check its output/network settings. Is output enabled? Is the right universe patched?
2. **Is the Art-Net box or console on the same network as this Mac?** Same Wi-Fi name or the same switch.
3. **Is the universe right?** Click the **DMX in** chip. If it lists **Also seeing universe 1 (listening on 0)**, the console is sending a different universe than the app is listening for. Change **Universe** on the DMX tab to match, then **Save & apply**.
    - **Art-Net universes start at 0** in this app. Some consoles number them from 1, so what the console calls "universe 1" may be 0 here. If in doubt, try the number one lower or higher.
    - (sACN numbers start at 1. If you use sACN, set **Source** to match.)
4. **Is Local Network permission on?** (See B1, step 3.)
5. **Is another lighting program running on this Mac** (for example QLC+)? The app can share the Art-Net port with other programs, so this is rarely the cause. But a second program that is itself *sending* Art-Net can confuse things. If you are not sure, quit it and look again.
6. **Is something blocking it?** A strict office or venue network can block Art-Net broadcast traffic. A direct cable or a small private switch between the console and the Mac is the quickest test.
7. **Wi-Fi?** Art-Net over Wi-Fi often drops packets. For a show, use a cable if you can.
8. **Mac firewall.** If a message ever asks whether to allow **incoming network connections** for the app, click **Allow**. If you clicked **Deny** earlier, open **System Settings > Network > Firewall** and allow the app.
9. **Listen on IP.** Leave this as `0.0.0.0`. If someone changed it to a specific address, check it is this Mac's address on the right network.

Then check the chip again. It should show `44 fps` or similar.

C4. Data arrives (green), but a light does nothing

1. On the **DMX** tab, look at the **Live monitor**. Move the console fader. Does the matching box change?
    - **No:** the console is patched to a different channel than the app expects. Compare the console's patch to the **Channel mapping** table.
    - **Yes:** the signal is arriving. Continue below.
2. In **Channel mapping**, find the light. Is its **On** box ticked? Is its **Address** the channel you expect?
3. Look at the warnings under the settings (for example *channel overlaps*, or *a zone is mapped twice*). Fix them and **Save & apply**.
4. Click the **DMX in** chip. **Mapped lights** should not be 0.
5. Does the **Output** chip show commands per second? If it shows "N held", see Section D.
6. Does the light work from the **Devices** tab? If not, the problem is the Lutron side (Section B).

C5. A light drops to 0 or goes dark when the show starts

This is by design. **While DMX input is on, every mapped light follows the console. A mapped light that no console channel is driving is held at 0.** Starting a lighting program with nothing patched can turn lights off.

- Map only the lights you want the console to own (untick **On** for the rest, or remove the row).
- Switch DMX input on only when the console is ready and outputting.
- The app **remembers** that DMX input was on. When you reopen the app, it starts listening again by itself. If the console is not ready, switch it off first.
- To get normal control back, untick **Enable DMX input** and click **Save & apply**.

C6. Values look wrong (brightness off by a step)

- **intensity** channels use 0 to 255 for 0 to 100%.
- **on_off** channels are on at 128 or above and off below.
- Check the **Params** column of the row is what the console expects.

D. Lights are slow, lag, or keep moving after the console has stopped

The Lutron system can only accept so many commands per second. The console sends 44 frames a second, so the app does not pass on every one. If it is sent more than the repeater can handle, the extra commands queue up *inside the repeater*, and the lights lag behind the console.

D1. What you will see

- Lights follow the console a few seconds late, or in a staggered way.
- Lights keep moving after you stop the fader.
- The **Output** chip shows "N held".
- The **Lutron** chip is amber, showing high latency.
- **Commands in flight** (click the Lutron chip) is high.

D2. What to do

Do these in order. Stop at the first one that fixes it.

1. **Wait ten seconds and see.** A short burst is normal and clears itself.
2. **Slow the console down.** Stop long, fast fades across many lights. Prefer shorter ramps or fewer lights moving at once.
3. **Lower the app's speed limit.** On the **DMX** tab, set **Max updates / second, all zones (0 = no limit)** to **10** (the default is 20). Click **Save & apply**. If your system copes easily, you can raise it again later.
4. **[PENDING, not in 0.5.0] Level step, %.** A new setting on the DMX tab called **Level step, %**. A bigger step means fewer commands (and slightly rougher fades). The default (0.5) is the same as today. It is for when a console fader flutters or when you want fewer commands.
5. **[PENDING, not in 0.5.0] Clear Lutron queue.** A new button on the **Status** tab (next to *Clear alerts*). It drops commands the app is still holding back. It **cannot** recall commands already sent to the repeater, and it cannot stop a fade the repeater has already started. It will say what it could not undo.

D3. After a "DMX storm" (the lights are badly behind or frozen)

A storm is when the repeater has been sent far more than it can take. It then keeps working through its backlog after the console has stopped.

Do these in order:

1. **Stop the source.** Stop any running cue or ramp on the console.
2. **Stop the app sending.** On the **DMX** tab, untick **Enable DMX input** and click **Save & apply**. This stops all new commands.
3. **Wait and watch.** Click the **Lutron** chip, or open the **Status** tab. Watch **Commands in flight** fall to 0 and the **Lutron latency** graph drop back to a low number (the amber line is at 500 ms). This often takes a minute or two.
4. **Test from the Devices tab.** Switch one harmless light on and off. If it responds at once, the repeater has recovered.
5. **Re-enable DMX input** with the speed limits lowered (D2, step 3), and run a gentle cue first.
6. **If the lights are still stuck or the latency stays high after about five minutes, power-cycle the repeater.**
    - **Ask the person who runs the lighting system first.** A power cycle takes the repeater offline for a few minutes. During that time the keypads, schedules and automation connected to it do not work.
    - If the building has more than one repeater, only cycle the one that is not responding.
    - Unplug its power (or switch it off at its supply), wait about 10 seconds, plug it back in.
    - Wait a few minutes. The **Lutron** chip will go red, then reconnect by itself.
    - Afterwards, check that the **Schedules** tab still shows what you expect (see Section G if a schedule set was active).
    - This is general advice for this project. It is not a procedure published by Lutron, so confirm it with whoever installed the system.
7. **Click Clear alerts** on the Status tab to reset the warnings counter.

> 📷 **Screenshot needed:** the Status tab, with the Lutron latency graph showing a spike and recovery.

E. Reading the Status tab

Open **Status**. It has the same sections as the chips, with more detail.

Section	Useful lines
Lutron link	State (Connected / Reconnecting), System and address, Connected for, **Reconnects since start** (should be 0 or small), **Lutron latency** (last, median, p95), **Commands in flight**

Section	Useful lines
DMX input	Source and universe, Sender, **Frames/s**, **Last packet**, **Mapped lights**, **Patch warnings**, **Also seeing universe**, Error
Output to Lutron	**Commands/s** (against the limit), **Held back by the limit**, Sent since start
App	**Schedule set** (shows "None active" or the active set), Warnings / errors, Version, Uptime, This browser
Graphs	Frames per second, commands per second, **Lutron latency**. They show the last 2 minutes and start empty after a page reload
Recent warnings and errors	The latest messages. Handy to read out to the person helping you

Clear alerts resets the Alerts counter and the list. Do this before a show, so any new warning is a real one.

F. The page itself (Server chip)

Server chip	Meaning	What to do
live (green)	Everything fine.	Nothing.
connecting	Starting up.	Wait.
no data N s (amber)	Connected but the app has been silent. It may be busy.	Wait 10 seconds. If it stays, reload the page.
polling (amber)	Live updates dropped. The page asks for updates every 5 seconds.	Reload the page.
offline (red)	The page cannot reach the app.	Is the log window still open? If not, the app has stopped: open it again.

G. Schedule sets and Performance mode problems

What you see	What to do
Activate is greyed out	Another set is active. Restore it first (**Restore schedules**). Only one set can be active at a time.

What you see	What to do
A red card: "Could not change ...", or "is active, but not everything went through"	Some schedules did not turn off. Do not assume they are off. Check each one in the **Schedules** list below. Turn off the rest by hand with their switches. Ask for help if it keeps failing.
"Skipped: ..."	A schedule in the set was renamed or removed in the Lutron system. Edit the set to fix it.
"No confirmation from the system for ..."	The Lutron system did not answer in time. Check the schedule list, then try again.
Restore incomplete ("Some schedules are still not restored")	Press **Restore schedules** again. It keeps what it remembered until every schedule is back.
"Could not restore"	The Lutron system could not be reached. The app keeps the remembered states. Fix the connection (Section B), then press **Restore schedules** again.
Delete is greyed out	The set is active. Restore it first.
The Mac or app crashed during a show	The remembered states are saved to disk *before* anything changes. Open the app again. A banner at the top says *Performance mode ACTIVE*. Click **Restore schedules** there.
Quit the app without restoring	Schedules stay turned off. The Lutron system does not know about this app. Open the app again and click **Restore schedules**.

> **Not yet proven on real equipment.** Turning schedules off and on from the app has been written and tested against a simulator, but has not yet been confirmed on the real Lutron repeaters. After any test, check the **Schedules** list shows the right *enabled* / *disabled* labels. If you are unsure, check in the Lutron app too.

H. Updates

What you see	What to do
Blue bar: "Version X is available"	Optional. Click **Update now** when no show is running.
"Update now" says to move the app first	Drag the app into the **Applications** folder (guide 1, Part 2) and open it from there.
Update asks to confirm	A schedule set is active, or DMX input is live. Finish the show, restore schedules, switch DMX off, then update.

What you see	What to do
"Could not reach GitHub" or "offline"	The Mac has no internet, or GitHub is down. The app works fine without it. Try later.
After an update, **Gatekeeper** appears again	Repeat guide 1, Part 3 once.

Settings, scenes and logs are never touched by an update. The old version is kept in `~/Library/Application Support/LutronToDMXBridge/updates/previous/`.

I. Alerts

The **Alerts** chip counts warnings and errors since the app started (or since **Clear alerts**). It shows e.g. `2 warn` or `1 err`.

1. Open the **Status** tab and read **Recent warnings and errors**.
2. If they look old and the system is working, click **Clear alerts**.
3. If a message repeats, copy it into your message when asking for help.

J. Getting help

Before asking, collect these three things:

1. **The log text.** In the log window, click **Copy log**, and paste it into your message. (**Save log…** saves it as a file. **Open log folder** shows where logs are kept.)
2. **A screenshot of the Status tab.** Include the chips at the top.
3. **What you did, and what you expected.** For example: "At 7:10 I switched DMX input on. The kitchen lights stayed off."

Do not send: a Lutron backup file, a settings export, `config.json`, or anything from the `backups` folder. They contain passwords and the installer's contact details. If the log shows addresses or passwords, remove them first.

To report a problem publicly: https://github.com/m3636/Lutron-to-DMX-Bridge/issues (never attach private files).

Quick reference: problem to section

Problem	Section
App will not open, Mac security message	A
Lutron chip red or amber	B
Find my controller finds nothing	B2
DMX in chip grey, red, or "waiting"	C
Light ignores the console	C4
Lights go dark when DMX starts	C5
Slow, laggy lights, "held" number	D
Lights stuck after a heavy cue	D3
Page shows offline / polling	F
Performance mode did not work or will not restore	G

4. Performance Checklist

Print this page and tick the boxes as you go. It takes you from a closed Mac to a finished show, and back to normal.

Show / date	
Operator	
Mac	
App version (Status tab > App > Version)	
Art-Net universe	

> **Performance mode** is a schedule set (a saved group of Lutron schedules) that you create once. Activating it turns those schedules off for the show. Restoring it afterwards puts them back **exactly as they were**. A schedule that was already off before the show stays off.
>
> **Never leave the show without restoring.** Schedules stay off until you restore them.

A. One-time setup (do once, not every show)

Do this on a quiet day with the person who runs the lighting system.

A1. Create the Performance mode set

1. ☐ Open the control page and click the **Schedules** tab.
2. ☐ In **Schedule sets**, click **New set**.
3. ☐ In **Name**, type `Performance mode`.
4. ☐ For every schedule in the list, choose what the set does:
   - **Turn off while active**: for timed events that would interrupt a show (for example "lights fade at 9 pm", "dusk scene").
   - **Leave alone**: for everything else.
   - **Turn on while active**: rarely needed. Turns a schedule *on* during the show.
   - **Be careful with security, exterior and safety lighting.** Leave those alone unless you are certain.
5. ☐ Click **Save set**.

6. ☐ Check the new set appears with a line **Turns off: …** listing the right schedules.

> 📷 **Screenshot needed:** the schedule set editor with a few schedules set to "Turn off while active".

A2. Test it once on a harmless schedule

This has not been proved on the real equipment yet. Do not skip the test.

1. ☐ Make a second set called `TEST` that turns off **one** harmless schedule.
2. ☐ Click **Activate** on `TEST`. Click **OK** in the question box.
3. ☐ The **Schedules** list shows that schedule as **disabled**. A top banner says **TEST ACTIVE**.
4. ☐ Click **Restore schedules**. The schedule shows **enabled** again (or whatever state it had before).
5. ☐ If anything is different, or a red card appears, stop and ask for help (Troubleshooting Guide, Section G).
6. ☐ Delete the `TEST` set when you are done (**Delete** button on the set).

A3. Make a safety copy of the settings

1. ☐ **Settings > Export & import settings > Download settings file** (passwords box unticked).
2. ☐ Copy the file to a USB stick or a private folder.

B. Before the show day (day before, or earlier)

1. ☐ Plug in the Mac's charger. Plan to run the show **on mains power**.
2. ☐ Stop the Mac sleeping. Open **System Settings** and look under **Battery** (or **Energy**) and **Lock Screen**. Set the options so the Mac does **not** sleep while plugged in, and the screen can turn off without putting the Mac to sleep. The names differ a little between macOS versions. *The app does not stop the Mac sleeping by itself, and a sleeping Mac stops the lights following the console.*
3. ☐ Turn on **Do Not Disturb** (or a Focus) so that no pop-ups cover the screen.
4. ☐ Close other programs that are not needed.
5. ☐ If possible, connect the Mac and the console / Art-Net box by **network cable**, not Wi-Fi.

6. ☐ Check for a new version: **Settings > Updates > Check now**. If there is one, update **now**, not on the day. Then re-test (Section A2). Do **not** update on show day unless you must.
7. ☐ Keep a copy of the settings file (A3) with you.

C. Opening the app (show day)

1. ☐ Switch on the Lutron equipment and the console's network box. Check they are powered.
2. ☐ On the Mac, open **Finder > Applications**.
3. ☐ Double-click **Lutron To DMX Bridge**.
    - If the Mac shows a security message, follow guide 1, Part 3. (It should only happen on the very first run, or after an update.)
4. ☐ Wait up to 30 seconds. The **log window** and the **control page** (in your browser) appear.
    - The log window looks like a small window with scrolling text. **Minimise it** (yellow button). **Never close it.**
    - If the browser does not open, click **Open web GUI** in the log window.
5. ☐ Keep the browser tab open for the whole show. Put it in **full screen** if you like (green button).

> 📷 **Screenshot needed:** the Applications folder with the app, and the log window next to the control page.

D. Pre-show checks (aim for 30 minutes before doors)

D1. Check the chips

Look at the five chips at the top right. All must be green or sensible.

1. ☐ **Lutron** is green and shows a time in ms (for example `45 ms`). It is not amber (slow) and not red (offline).
2. ☐ **Server** says **live**.
3. ☐ **Alerts** says `none`. If it shows warnings, open **Status** and click **Clear alerts** so that any new alert during the show is a real one.
4. ☐ **Output** shows a small number and nothing "held".

5. ☐ **DMX in** shows `off` for now. It will turn green later (Section F).
    - **If it is already on** (the app remembers this setting between runs), make sure the console is ready, or switch it off now (**DMX** tab, untick **Enable DMX input**, **Save & apply**). While it is on, mapped lights the console is not driving are set to 0.

If a chip is wrong, use the Troubleshooting Guide (Section B for Lutron).

D2. Check the lights respond

1. ☐ **Devices** tab: switch one harmless light on, then off. It responds in a second or two.
2. ☐ No red message bar at the top of the page.

D3. Check no other schedule set is active

1. ☐ No coloured banner at the top says "... ACTIVE". If one does, find out who started it and why, before you go on.

D4. Check the DMX settings

1. ☐ **DMX** tab: **Source** is *Art-Net*, and **Universe** matches the console's universe.
2. ☐ The mapping table lists only the lights the console should control. Mapped lights that the console does not drive will be set to **0**.
3. ☐ The warnings area under the settings is empty.
4. ☐ **Max updates / second, all zones** is at the value agreed for this venue (default 20; 10 if the lights have lagged before).
5. ☐ If you changed anything, click **Save & apply**.

E. Start Performance mode

Do this **before** the audience arrives or before the first cue, in a quiet moment.

1. ☐ Click the **Schedules** tab.
2. ☐ In **Schedule sets**, find **Performance mode**. Read the line **Turns off: ...**. Is it the list you expect?
3. ☐ Click **Activate**.
4. ☐ A question box lists the schedules that will be turned **OFF** (and any turned ON). Read it. Click **OK**.
5. ☐ Wait a few seconds. A green card appears: **Performance mode is active**, with a line like "5 schedules changed".

    - A **red** card means something did not go through. **Stop.** Read it. Do not start the show until you have checked each schedule in the list below and turned off the ones that should be off. See Troubleshooting Guide, Section G.
6. ☐ A banner at the top of every tab now says **Performance mode ACTIVE**.
7. ☐ Scroll down the **Schedules** list. Every schedule in the set shows **disabled**.
8. ☐ The **Status** tab, **App** section, shows the schedule set as active.

> 📷 **Screenshot needed:** the green "Performance mode is active" card and the top banner.

F. Switch on DMX input

Do this only when the console is powered, outputting Art-Net, and the right cue (or a blackout you want) is ready. **While DMX input is on, every mapped light follows the console, and a mapped light that the console is not driving is set to 0.**

1. ☐ Console is on and **Art-Net output is enabled**.
2. ☐ Click the **DMX** tab.
3. ☐ Tick **Enable DMX input**.
4. ☐ Click **Save & apply**.
5. ☐ The **DMX in** chip turns green and shows frames per second and the universe, for example `44 fps · U0`.
6. ☐ **Live monitor**: move a console fader and watch the matching box move.
7. ☐ Run a short, gentle check cue. The lights follow the console.
8. ☐ Return the console to its starting state.

If the chip says *waiting* or *no data*, use the Troubleshooting Guide, Section C.

G. Last checks before the show starts

1. ☐ **Lutron** chip green, latency low.
2. ☐ **DMX in** chip green.
3. ☐ **Alerts** still `none`.
4. ☐ **Performance mode ACTIVE** banner showing.
5. ☐ Log window minimised, not closed. Mac plugged in. Do Not Disturb on.

6. ☐ Know who to call (see the contacts sheet in the START-HERE page).

H. During the show

- **Do not** close the log window or quit the app.
- **Do not** start an update, even if the blue bar appears.
- **Do not** change settings.
- Glance at the chips now and then (see the table below). You only need to act if one changes colour.
- If lights start lagging, follow the Troubleshooting Guide, Section D. Short version:

Sign	First action
Output shows "N held" for more than a few seconds, or lights are staggered	Ease off the cue speed. Fewer lights moving at once.
Lutron chip turns amber (slow)	Same. Click the chip. If *Commands in flight* keeps rising, stop the cue source.
DMX in chip turns amber ("no data")	Check the console output and the network cable.
Lutron chip turns red	Do not panic. Lights keep their last level. Check the network cable or Wi-Fi. Wait for it to reconnect by itself.
Page shows **Server: offline**	Check the log window is open. If the app has stopped, reopen it. Lights keep their last level.

- **[PENDING, not in 0.5.0]** After the next update, the Status tab will have a **Clear Lutron queue** button for a backed-up system.
- If the lights are badly behind or stuck, follow *Troubleshooting Guide, Section D3 (after a DMX storm)*. Do not power-cycle the repeater without asking the person who runs the lighting system.

I. After the show

Do these in order. **Do not skip step 3.**

I1. Stop the console driving the lights

1. ☐ Put the console into the state you want the room left in (for example a blackout, or house lights).
2. ☐ Click the **DMX** tab.

3. ☐ **Untick Enable DMX input** and click **Save & apply**.
4. ☐ The **DMX in** chip turns grey and says `off`.
5. ☐ Lights now stay as they are. You can set them from the **Devices** tab, or from the wall keypads.

I2. End Performance mode

1. ☐ Click the **Schedules** tab, or the **Restore schedules** button in the banner at the top.
2. ☐ Click **Restore schedules** on **Performance mode**.
3. ☐ Wait a few seconds. A green card says **Performance mode restored**, and "N schedules put back to how they were".
    - A red card says **Some schedules are still not restored**: click **Restore schedules** again. Keep going until it works.
4. ☐ The top banner has gone.
5. ☐ In the **Schedules** list, schedules that were running before the show show **enabled** again. Schedules that were already off before the show are still **disabled**.
6. ☐ **Status** tab, **App** section, shows the schedule set as `None active`.

> 📷 **Screenshot needed:** the green "restored" card.

I3. Leave the building how you found it

1. ☐ On the **Devices** tab, check key rooms are in the state you want (use **All off** per room if needed).
2. ☐ If the lighting system should run its normal timed events tonight (security, exterior lights), now that schedules are back, check the next scheduled event is one you expect.

I4. Save a note for next time

1. ☐ Look at the **Status** tab. Note anything unusual: **Alerts** count, highest **Lutron latency** (in the graph), **Reconnects since start**.
2. ☐ Write it on this sheet or tell the person who runs the app.
3. ☐ Click **Clear alerts** if you like, so next time starts fresh.

I5. Shut down

1. ☐ Only quit the app if nobody else needs it. If the Mac is staying on, leaving the app running is fine.

2. ☐ To quit: open the log window and click **Quit**. Confirm **OK**. (Quitting stops DMX control. The lights stay as they are.)
3. ☐ Close the browser tab.
4. ☐ Turn the Mac's sleep and Do Not Disturb settings back, if you changed them.

J. If the app or the Mac stops during the show

1. **The lights stay as they are.** Nothing turns off by itself.
2. Reopen the app (Section C).
3. If the banner says **Performance mode ACTIVE**, the schedules are still off. Leave it that way until the show finishes, then restore as in I2.
4. The app remembers whether DMX input was on, so it may start receiving by itself when it reopens. Check the **DMX in** chip. If the console is not ready, untick **Enable DMX input** and **Save & apply** (mapped lights the console is not driving are set to 0). Switch it on again (Section F) when the console is ready.
5. If you lose the app completely, schedules can also be switched back on by hand in the **Schedules** list, or in the Lutron system itself. Ask the person who runs the lighting system.

K. One-page summary (cut out and keep by the Mac)

Open: Applications > Lutron To DMX Bridge. Minimise (never close) the log window.

Check: Lutron green · Server live · Alerts none · DMX in off.

Start: Schedules > Performance mode > **Activate** > OK > banner shows ACTIVE.

Console on: DMX > tick **Enable DMX input** > **Save & apply** > DMX in green.

Show runs: watch the chips, do not touch anything.

Finish: DMX > untick **Enable DMX input** > **Save & apply**.

Restore: Schedules > **Restore schedules** > banner gone.

Shut down: log window > **Quit**.

Lag? Ease the cue. Lower **Max updates / second, all zones** to 10. See Troubleshooting Guide, Section D.