NKTPDLL Reference manual

Generated by Doxygen 1.8.12

Contents

1 Data Structure Index **1**

1.1 Data Structures 1

2 File Index **3**

2.1 File List 3

3 Data Structure Documentation **5**

3.1 lvDeviceStatusStruct Struct Reference 5

3.1.1 Detailed Description 5

3.1.2 Field Documentation 5

3.1.2.1 portname 5

3.1.2.2 devId 6

3.1.2.3 status 6

3.1.2.4 devDataLen 6

3.1.2.5 devData 6

3.2 lvPortStatusStruct Struct Reference 6

3.2.1 Detailed Description 6

3.2.2 Field Documentation 7

3.2.2.1 portname 7

3.2.2.2 status 7

3.2.2.3 curScanAdr 7

3.2.2.4 maxScanAdr 7

3.2.2.5 foundType 7

3.3 lvRegisterStatusStruct Struct Reference 7

3.3.1 Detailed Description . . . 8
3.3.2 Field Documentation . . . 8
3.3.2.1 portname . . . 8
3.3.2.2 devId . . . 8
3.3.2.3 regId . . . 8
3.3.2.4 status . . . 8
3.3.2.5 regType . . . 9
3.3.2.6 regDataLen . . . 9
3.3.2.7 regData . . . 9
3.4 tDateTimeStruct Struct Reference . . . 9
3.4.1 Detailed Description . . . 9
3.4.2 Field Documentation . . . 10
3.4.2.1 Sec . . . 10
3.4.2.2 Min . . . 10
3.4.2.3 Hour . . . 10
3.4.2.4 Day . . . 10
3.4.2.5 Month . . . 10
3.4.2.6 Year . . . 10
3.5 tParamSetStruct Struct Reference . . . 10
3.5.1 Detailed Description . . . 11
3.5.2 Field Documentation . . . 11
3.5.2.1 Unit . . . 11
3.5.2.2 ErrorHandler . . . 11
3.5.2.3 StartVal . . . 12
3.5.2.4 FactoryVal . . . 12
3.5.2.5 ULimit . . . 12
3.5.2.6 LLimit . . . 12
3.5.2.7 Numerator . . . 12
3.5.2.8 Denominator . . . 12
3.5.2.9 Offset . . . 12

4 File Documentation 13

4.1 NKTPDLL.h File Reference . . . 13

4.1.1 Detailed Description . . . 23

4.1.2 Macro Definition Documentation . . . 24

4.1.2.1 NKTPDLL_EXPORT . . . 24

4.1.3 Typedef Documentation . . . 24

4.1.3.1 PortResultTypes . . . 24

4.1.3.2 P2PPortResultTypes . . . 24

4.1.3.3 DeviceResultTypes . . . 24

4.1.3.4 DeviceModeTypes . . . 24

4.1.3.5 RegisterResultTypes . . . 24

4.1.3.6 RegisterDataTypes . . . 24

4.1.3.7 RegisterPriorityTypes . . . 24

4.1.3.8 PortStatusTypes . . . 25

4.1.3.9 DeviceStatusTypes . . . 25

4.1.3.10 RegisterStatusTypes . . . 25

4.1.3.11 DateTimeType . . . 25

4.1.3.12 ParamSetUnitTypes . . . 25

4.1.3.13 ParameterSetType . . . 25

4.1.3.14 GetAllPortsFuncPtr . . . 25

4.1.3.15 GetOpenPortsFuncPtr . . . 25

4.1.3.16 PointToPointPortAddFuncPtr . . . 26

4.1.3.17 PointToPointPortGetFuncPtr . . . 26

4.1.3.18 PointToPointPortDelFuncPtr . . . 26

4.1.3.19 OpenPortsFuncPtr . . . 26

4.1.3.20 ClosePortsFuncPtr . . . 26

4.1.3.21 SetLegacyBusScanningFuncPtr . . . 26

4.1.3.22 GetLegacyBusScanningFuncPtr . . . 26

4.1.3.23 getPortStatusFuncPtr . . . 26

4.1.3.24 getPortErrorMsgFuncPtr . . . 26

4.1.3.25 RegisterReadFuncPtr . . . 27
4.1.3.26 RegisterReadU8FuncPtr . . . 27
4.1.3.27 RegisterReadS8FuncPtr . . . 27
4.1.3.28 RegisterReadU16FuncPtr . . . 27
4.1.3.29 RegisterReadS16FuncPtr . . . 27
4.1.3.30 RegisterReadU32FuncPtr . . . 27
4.1.3.31 RegisterReadS32FuncPtr . . . 27
4.1.3.32 RegisterReadU64FuncPtr . . . 27
4.1.3.33 RegisterReadS64FuncPtr . . . 27
4.1.3.34 RegisterReadF32FuncPtr . . . 28
4.1.3.35 RegisterReadF64FuncPtr . . . 28
4.1.3.36 RegisterReadAsciiFuncPtr . . . 28
4.1.3.37 RegisterWriteFuncPtr . . . 28
4.1.3.38 RegisterWriteU8FuncPtr . . . 28
4.1.3.39 RegisterWriteS8FuncPtr . . . 28
4.1.3.40 RegisterWriteU16FuncPtr . . . 28
4.1.3.41 RegisterWriteS16FuncPtr . . . 28
4.1.3.42 RegisterWriteU32FuncPtr . . . 29
4.1.3.43 RegisterWriteS32FuncPtr . . . 29
4.1.3.44 RegisterWriteU64FuncPtr . . . 29
4.1.3.45 RegisterWriteS64FuncPtr . . . 29
4.1.3.46 RegisterWriteF32FuncPtr . . . 29
4.1.3.47 RegisterWriteF64FuncPtr . . . 29
4.1.3.48 RegisterWriteAsciiFuncPtr . . . 29
4.1.3.49 RegisterWriteReadFuncPtr . . . 29
4.1.3.50 RegisterWriteReadU8FuncPtr . . . 30
4.1.3.51 RegisterWriteReadS8FuncPtr . . . 30
4.1.3.52 RegisterWriteReadU16FuncPtr . . . 30
4.1.3.53 RegisterWriteReadS16FuncPtr . . . 30
4.1.3.54 RegisterWriteReadU32FuncPtr . . . 30

4.1.3.55 RegisterWriteReadS32FuncPtr 30
4.1.3.56 RegisterWriteReadU64FuncPtr 30
4.1.3.57 RegisterWriteReadS64FuncPtr 30
4.1.3.58 RegisterWriteReadF32FuncPtr 31
4.1.3.59 RegisterWriteReadF64FuncPtr 31
4.1.3.60 RegisterWriteReadAsciiFuncPtr 31
4.1.3.61 DeviceGetTypeFuncPtr 31
4.1.3.62 DeviceGetSysTypeFuncPtr 31
4.1.3.63 DeviceGetPartNumberStrFuncPtr 31
4.1.3.64 DeviceGetPCBVersionFuncPtr 31
4.1.3.65 DeviceGetStatusBitsFuncPtr 31
4.1.3.66 DeviceGetErrorCodeFuncPtr 32
4.1.3.67 DeviceGetBootloaderVersionFuncPtr 32
4.1.3.68 DeviceGetBootloaderVersionStrFuncPtr 32
4.1.3.69 DeviceGetFirmwareVersionFuncPtr 32
4.1.3.70 DeviceGetFirmwareVersionStrFuncPtr 32
4.1.3.71 DeviceGetModuleSerialNumberStrFuncPtr 32
4.1.3.72 DeviceGetPCBSerialNumberStrFuncPtr 32
4.1.3.73 DeviceCreateFuncPtr 32
4.1.3.74 DeviceExistsFuncPtr 32
4.1.3.75 DeviceRemoveFuncPtr 33
4.1.3.76 DeviceRemoveAllFuncPtr 33
4.1.3.77 DeviceGetAllTypesFuncPtr 33
4.1.3.78 DeviceGetModeFuncPtr 33
4.1.3.79 DeviceGetLiveFuncPtr 33
4.1.3.80 DeviceSetLiveFuncPtr 33
4.1.3.81 RegisterCreateFuncPtr 33
4.1.3.82 RegisterExistsFuncPtr 33
4.1.3.83 RegisterRemoveFuncPtr 33
4.1.3.84 RegisterRemoveAllFuncPtr 34

4.1.3.85 RegisterGetAllFuncPtr . . . 34
4.1.3.86 PortStatusCallbackFuncPtr . . . 34
4.1.3.87 SetCallbackPtrPortInfoFuncPtr . . . 34
4.1.3.88 DeviceStatusCallbackFuncPtr . . . 34
4.1.3.89 SetCallbackPtrDeviceInfoFuncPtr . . . 35
4.1.3.90 RegisterStatusCallbackFuncPtr . . . 35
4.1.3.91 SetCallbackPtrRegisterInfoFuncPtr . . . 35
4.1.3.92 LabViewPortStatusType . . . 35
4.1.3.93 SetLVUserEventPortInfoFuncPtr . . . 36
4.1.3.94 LabViewDeviceStatusType . . . 36
4.1.3.95 SetLVUserEventDeviceInfoFuncPtr . . . 36
4.1.3.96 LabViewRegisterStatusType . . . 36
4.1.3.97 SetLVUserEventRegisterInfoFuncPtr . . . 36
4.1.4 Enumeration Type Documentation . . . 36
4.1.4.1 tPortResultTypes . . . 36
4.1.4.2 tP2PPortResultTypes . . . 36
4.1.4.3 tDeviceResultTypes . . . 38
4.1.4.4 tDeviceModeTypes . . . 38
4.1.4.5 tRegisterResultTypes . . . 39
4.1.4.6 tRegisterDataTypes . . . 39
4.1.4.7 tRegisterPriorityTypes . . . 40
4.1.4.8 tPortStatusTypes . . . 40
4.1.4.9 tDeviceStatusTypes . . . 41
4.1.4.10 tRegisterStatusTypes . . . 41
4.1.4.11 tParamSetUnitTypes . . . 41
4.1.5 Function Documentation . . . 42
4.1.5.1 getAllPorts() . . . 42
4.1.5.2 getOpenPorts() . . . 43
4.1.5.3 pointToPointPortAdd() . . . 43
4.1.5.4 pointToPointPortGet() . . . 43

4.1.5.5 pointToPointPortDel() . . . 44
4.1.5.6 openPorts() . . . 45
4.1.5.7 closePorts() . . . 45
4.1.5.8 setLegacyBusScanning() . . . 46
4.1.5.9 getLegacyBusScanning() . . . 46
4.1.5.10 getPortStatus() . . . 46
4.1.5.11 getPortErrorMsg() . . . 47
4.1.5.12 registerRead() . . . 47
4.1.5.13 registerReadU8() . . . 48
4.1.5.14 registerReadS8() . . . 49
4.1.5.15 registerReadU16() . . . 49
4.1.5.16 registerReadS16() . . . 50
4.1.5.17 registerReadU32() . . . 50
4.1.5.18 registerReadS32() . . . 51
4.1.5.19 registerReadU64() . . . 52
4.1.5.20 registerReadS64() . . . 52
4.1.5.21 registerReadF32() . . . 53
4.1.5.22 registerReadF64() . . . 53
4.1.5.23 registerReadAscii() . . . 54
4.1.5.24 registerWrite() . . . 55
4.1.5.25 registerWriteU8() . . . 55
4.1.5.26 registerWriteS8() . . . 56
4.1.5.27 registerWriteU16() . . . 57
4.1.5.28 registerWriteS16() . . . 57
4.1.5.29 registerWriteU32() . . . 58
4.1.5.30 registerWriteS32() . . . 58
4.1.5.31 registerWriteU64() . . . 59
4.1.5.32 registerWriteS64() . . . 60
4.1.5.33 registerWriteF32() . . . 60
4.1.5.34 registerWriteF64() . . . 61

4.1.5.35 registerWriteAscii() . . . 61
4.1.5.36 registerWriteRead() . . . 62
4.1.5.37 registerWriteReadU8() . . . 63
4.1.5.38 registerWriteReadS8() . . . 63
4.1.5.39 registerWriteReadU16() . . . 64
4.1.5.40 registerWriteReadS16() . . . 65
4.1.5.41 registerWriteReadU32() . . . 65
4.1.5.42 registerWriteReadS32() . . . 66
4.1.5.43 registerWriteReadU64() . . . 67
4.1.5.44 registerWriteReadS64() . . . 67
4.1.5.45 registerWriteReadF32() . . . 68
4.1.5.46 registerWriteReadF64() . . . 69
4.1.5.47 registerWriteReadAscii() . . . 69
4.1.5.48 deviceGetType() . . . 70
4.1.5.49 deviceGetSysType() . . . 71
4.1.5.50 deviceGetPartNumberStr() . . . 71
4.1.5.51 deviceGetPCBVersion() . . . 72
4.1.5.52 deviceGetStatusBits() . . . 72
4.1.5.53 deviceGetErrorCode() . . . 73
4.1.5.54 deviceGetBootloaderVersion() . . . 73
4.1.5.55 deviceGetBootloaderVersionStr() . . . 74
4.1.5.56 deviceGetFirmwareVersion() . . . 74
4.1.5.57 deviceGetFirmwareVersionStr() . . . 75
4.1.5.58 deviceGetModuleSerialNumberStr() . . . 75
4.1.5.59 deviceGetPCBSerialNumberStr() . . . 76
4.1.5.60 deviceCreate() . . . 77
4.1.5.61 deviceExists() . . . 77
4.1.5.62 deviceRemove() . . . 77
4.1.5.63 deviceRemoveAll() . . . 78
4.1.5.64 deviceGetAllTypes() . . . 78

4.1.5.65 deviceGetMode() . . . 79
4.1.5.66 deviceGetLive() . . . 79
4.1.5.67 deviceSetLive() . . . 80
4.1.5.68 registerCreate() . . . 80
4.1.5.69 registerExists() . . . 81
4.1.5.70 registerRemove() . . . 81
4.1.5.71 registerRemoveAll() . . . 82
4.1.5.72 registerGetAll() . . . 82
4.1.5.73 setCallbackPtrPortInfo() . . . 83
4.1.5.74 setCallbackPtrDeviceInfo() . . . 83
4.1.5.75 setCallbackPtrRegisterInfo() . . . 83
4.1.5.76 setLVUserEventPortInfo() . . . 83
4.1.5.77 setLVUserEventDeviceInfo() . . . 84
4.1.5.78 setLVUserEventRegisterInfo() . . . 84

Index **85**

Chapter 1

Data Structure Index

1.1 Data Structures

Here are the data structures with brief descriptions:

lvDeviceStatusStruct
: LvDeviceStatusStruct, A LabView userevent data package 5

lvPortStatusStruct
: LvPortStatusStruct, A LabView userevent data package 6

lvRegisterStatusStruct
: LvRegisterStatusStruct, A LabView userevent data package 7

tDateTimeStruct
: The tDateTime struct 24 hour format 9

tParamSetStruct
: The tParameterSet struct 10

Chapter 2

File Index

2.1 File List

Here is a list of all files with brief descriptions:

NKTPDLL.h
NKTP DLL Interface, a communication DLL for interfacing to NKT Photonics products being controlled via the Interbus protocol. The NKTPDLL abstracts the burden of telegram creation and communication handling when communicating/controlling the NKT Photonics products . . 13

Chapter 3

Data Structure Documentation

3.1 lvDeviceStatusStruct Struct Reference

lvDeviceStatusStruct, A LabView userevent data package

Data Fields

- char portname [32]

  Zero terminated string giving the originating portname.
- unsigned char devId

  The originating device id (module address).
- DeviceStatusTypes status

  The current port status as tDeviceStatusTypes.
- unsigned char devDataLen

  Number of databytes in devData.
- unsigned char devData [255]

  device data as specified in status.

3.1.1 Detailed Description

lvDeviceStatusStruct, A LabView userevent data package

3.1.2 Field Documentation

3.1.2.1 portname

```
char lvDeviceStatusStruct::portname[32]
```

Zero terminated string giving the originating portname.

3.1.2.2 devId

```
unsigned char lvDeviceStatusStruct::devId
```

The originating device id (module address).

3.1.2.3 status

```
DeviceStatusTypes lvDeviceStatusStruct::status
```

The current port status as tDeviceStatusTypes.

3.1.2.4 devDataLen

```
unsigned char lvDeviceStatusStruct::devDataLen
```

Number of databytes in devData.

3.1.2.5 devData

```
unsigned char lvDeviceStatusStruct::devData[255]
```

device data as specified in status.

3.2 lvPortStatusStruct Struct Reference

lvPortStatusStruct, A LabView userevent data package

Data Fields

- char portname [32]

  Zero terminated string giving the originating portname.
- PortStatusTypes status

  The current port status as tPortStatusTypes.
- unsigned char curScanAdr

  When status is PortScanProgress or PortScanDeviceFound this indicates the current module address scanned or found.
- unsigned char maxScanAdr

  When status is PortScanProgress or PortScanDeviceFound this indicates the last module address to be scanned.
- unsigned char foundType

  When status is PortScanDeviceFound this value will represent the found module type.

3.2.1 Detailed Description

lvPortStatusStruct, A LabView userevent data package

3.2.2 Field Documentation

3.2.2.1 portname

```
char lvPortStatusStruct::portname[32]
```

Zero terminated string giving the originating portname.

3.2.2.2 status

```
PortStatusTypes lvPortStatusStruct::status
```

The current port status as tPortStatusTypes.

3.2.2.3 curScanAdr

```
unsigned char lvPortStatusStruct::curScanAdr
```

When status is PortScanProgress or PortScanDeviceFound this indicates the current module address scanned or found.

3.2.2.4 maxScanAdr

```
unsigned char lvPortStatusStruct::maxScanAdr
```

When status is PortScanProgress or PortScanDeviceFound this indicates the last module address to be scanned.

3.2.2.5 foundType

```
unsigned char lvPortStatusStruct::foundType
```

When status is PortScanDeviceFound this value will represent the found module type.

3.3 lvRegisterStatusStruct Struct Reference

lvRegisterStatusStruct, A LabView userevent data package

Data Fields

- char portname [32]

  Zero terminated string giving the originating portname.
- unsigned char devId

  The originating device id (module address).
- unsigned char regId

  The originating register id.
- RegisterStatusTypes status

  The current register status as a tRegisterStatusTypes value.
- RegisterDataTypes regType

  The tRegisterDataTypes, not used internally but could be used in a common callback function to determine data type. Set when the register is created with registerCreate.
- unsigned char regDataLen

  Number of databytes.
- unsigned char regData [255]

  The register data.

3.3.1 Detailed Description

lvRegisterStatusStruct, A LabView userevent data package

3.3.2 Field Documentation

3.3.2.1 portname

```
char lvRegisterStatusStruct::portname[32]
```

Zero terminated string giving the originating portname.

3.3.2.2 devId

```
unsigned char lvRegisterStatusStruct::devId
```

The originating device id (module address).

3.3.2.3 regId

```
unsigned char lvRegisterStatusStruct::regId
```

The originating register id.

3.3.2.4 status

```
RegisterStatusTypes lvRegisterStatusStruct::status
```

The current register status as a tRegisterStatusTypes value.

3.3.2.5 regType

```
RegisterDataTypes lvRegisterStatusStruct::regType
```

The tRegisterDataTypes, not used internally but could be used in a common callback function to determine data type. Set when the register is created with registerCreate.

3.3.2.6 regDataLen

```
unsigned char lvRegisterStatusStruct::regDataLen
```

Number of databytes.

3.3.2.7 regData

```
unsigned char lvRegisterStatusStruct::regData[255]
```

The register data.

3.4 tDateTimeStruct Struct Reference

The tDateTime struct 24 hour format.

Data Fields

- unsigned char Sec
  Seconds.
- unsigned char Min
  Minutes.
- unsigned char Hour
  Hours.
- unsigned char Day
  Day.
- unsigned char Month
  Months.
- unsigned char Year
  Years.

3.4.1 Detailed Description

The tDateTime struct 24 hour format.

3.4.2 Field Documentation

3.4.2.1 Sec

```
unsigned char tDateTimeStruct::Sec
```

Seconds.

3.4.2.2 Min

```
unsigned char tDateTimeStruct::Min
```

Minutes.

3.4.2.3 Hour

```
unsigned char tDateTimeStruct::Hour
```

Hours.

3.4.2.4 Day

```
unsigned char tDateTimeStruct::Day
```

Day.

3.4.2.5 Month

```
unsigned char tDateTimeStruct::Month
```

Months.

3.4.2.6 Year

```
unsigned char tDateTimeStruct::Year
```

Years.

3.5 tParamSetStruct Struct Reference

The tParameterSet struct.

Data Fields

- ParamSetUnitTypes Unit

  Unit type as defined in tParamSetUnitTypes.
- unsigned char ErrorHandler

  Warning/Errorhandler not used.
- unsigned short StartVal

  Setpoint for Settings parameterset, unused in Measurement parametersets.
- unsigned short FactoryVal

  Factory Setpoint for Settings parameterset, unused in Measurement parametersets.
- unsigned short ULimit

  Upper limit.
- unsigned short LLimit

  Lower limit.
- signed short Numerator

  Numerator(X) for calculation.
- signed short Denominator

  Denominator(Y) for calculation.
- signed short Offset

  Offset for calculation.

3.5.1 Detailed Description

The tParameterSet struct.

Note

This is how calculation on parametersets is done internally by modules:
DAC_value = (value ∗ (X/Y)) + Offset; Where value is either ParameterSetType::StartVal or ParameterSetType::FactoryVal
value = (ADC_value ∗ (X/Y)) + Offset; Where value often is available via another measurement register

3.5.2 Field Documentation

3.5.2.1 Unit

```
ParamSetUnitTypes tParamSetStruct::Unit
```

Unit type as defined in tParamSetUnitTypes.

3.5.2.2 ErrorHandler

```
unsigned char tParamSetStruct::ErrorHandler
```

Warning/Errorhandler not used.

3.5.2.3 StartVal

```
unsigned short tParamSetStruct::StartVal
```

Setpoint for Settings parameterset, unused in Measurement parametersets.

3.5.2.4 FactoryVal

```
unsigned short tParamSetStruct::FactoryVal
```

Factory Setpoint for Settings parameterset, unused in Measurement parametersets.

3.5.2.5 ULimit

```
unsigned short tParamSetStruct::ULimit
```

Upper limit.

3.5.2.6 LLimit

```
unsigned short tParamSetStruct::LLimit
```

Lower limit.

3.5.2.7 Numerator

```
signed short tParamSetStruct::Numerator
```

Numerator(X) for calculation.

3.5.2.8 Denominator

```
signed short tParamSetStruct::Denominator
```

Denominator(Y) for calculation.

3.5.2.9 Offset

```
signed short tParamSetStruct::Offset
```

Offset for calculation.

Chapter 4

File Documentation

4.1 NKTPDLL.h File Reference

NKTP DLL Interface, a communication DLL for interfacing to NKT Photonics products being controlled via the Interbus protocol. The NKTPDLL abstracts the burden of telegram creation and communication handling when communicating/controlling the NKT Photonics products.

Data Structures

- struct tDateTimeStruct

  The tDateTime struct 24 hour format.
- struct tParamSetStruct

  The tParameterSet struct.
- struct lvPortStatusStruct

  lvPortStatusStruct, A LabView userevent data package
- struct lvDeviceStatusStruct

  lvDeviceStatusStruct, A LabView userevent data package
- struct lvRegisterStatusStruct

  lvRegisterStatusStruct, A LabView userevent data package

Macros

- #define NKTPDLL_EXPORT __declspec(dllimport)

Typedefs

- typedef unsigned char PortResultTypes
- typedef unsigned char P2PPortResultTypes
- typedef unsigned char DeviceResultTypes
- typedef unsigned char DeviceModeTypes
- typedef unsigned char RegisterResultTypes
- typedef unsigned char RegisterDataTypes
- typedef unsigned char RegisterPriorityTypes
- typedef unsigned char PortStatusTypes
- typedef unsigned char DeviceStatusTypes
- typedef unsigned char RegisterStatusTypes
- typedef struct tDateTimeStruct DateTimeType

  The tDateTime struct 24 hour format.
- typedef unsigned char ParamSetUnitTypes
- typedef struct tParamSetStruct ParameterSetType

  The tParameterSet struct.

Enumerations

- enum tPortResultTypes {
  OPSuccess = 0, OPFailed = 1, OPPortNotFound = 2, OPNoDevices = 3,
  OPApplicationBusy = 4 }

  The tPortResultTypes enum.
- enum tP2PPortResultTypes {
  P2PSuccess = 0, P2PInvalidPortname = 1, P2PInvalidLocalIP = 2, P2PInvalidRemoteIP = 3,
  P2PPortnameNotFound = 4, P2PPortnameExists = 5, P2PApplicationBusy = 6 }

  The tPointToPointPortStatus enum.
- enum tDeviceResultTypes {
  DevResultSuccess = 0, DevResultWaitTimeout = 1, DevResultFailed = 2, DevResultDeviceNotFound = 3,
  DevResultPortNotFound = 4, DevResultPortOpenError = 5, DevResultApplicationBusy = 6 }

  The tDeviceResultTypes enum.
- enum tDeviceModeTypes {
  DevModeDisabled = 0, DevModeAnalyzeInit = 1, DevModeAnalyze = 2, DevModeNormal = 3,
  DevModeLogDownload = 4, DevModeError = 5, DevModeTimeout = 6, DevModeUpload = 7 }

  The tDeviceModeTypes enum.
- enum tRegisterResultTypes {
  RegResultSuccess = 0, RegResultReadError = 1, RegResultFailed = 2, RegResultBusy = 3,
  RegResultNacked = 4, RegResultCRCErr = 5, RegResultTimeout = 6, RegResultComError = 7,
  RegResultTypeError = 8, RegResultIndexError = 9, RegResultPortClosed = 10, RegResultRegisterNotFound = 11,
  RegResultDeviceNotFound = 12, RegResultPortNotFound = 13, RegResultPortOpenError = 14, RegResult↩
  ApplicationBusy = 15 }

  The tRegisterResultTypes enum.
- enum tRegisterDataTypes {
  RegData_Unknown = 0, RegData_Mixed = 1, RegData_U8 = 2, RegData_S8 = 3,
  RegData_U16 = 4, RegData_S16 = 5, RegData_U32 = 6, RegData_S32 = 7,
  RegData_F32 = 8, RegData_U64 = 9, RegData_S64 = 10, RegData_F64 = 11,
  RegData_Ascii = 12, RegData_Paramset = 13, RegData_B8 = 14, RegData_H8 = 15,
  RegData_B16 = 16, RegData_H16 = 17, RegData_B32 = 18, RegData_H32 = 19,
  RegData_B64 = 20, RegData_H64 = 21, RegData_DateTime = 22 }

  The tRegisterDataTypes enum.
- enum tRegisterPriorityTypes { RegPriority_Low = 0, RegPriority_High = 1 }

  The tRegisterPriorityTypes enum.
- enum tPortStatusTypes {
  PortStatusUnknown = 0, PortOpening = 1, PortOpened = 2, PortOpenFail = 3,
  PortScanStarted = 4, PortScanProgress = 5, PortScanDeviceFound = 6, PortScanEnded = 7,
  PortClosing = 8, PortClosed = 9, PortReady = 10 }

  The tPortStatusTypes enum.
- enum tDeviceStatusTypes {
  DeviceModeChanged = 0, DeviceLiveChanged = 1, DeviceTypeChanged = 2, DevicePartNumberChanged = 3,
  DevicePCBVersionChanged = 4, DeviceStatusBitsChanged = 5, DeviceErrorCodeChanged = 6, DeviceBl↩
  VerChanged = 7,
  DeviceFwVerChanged = 8, DeviceModuleSerialChanged = 9, DevicePCBSerialChanged = 10, DeviceSys↩
  TypeChanged = 11 }

  The tDeviceStatusTypes enum.
- enum tRegisterStatusTypes {
  RegSuccess = 0, RegBusy = 1, RegNacked = 2, RegCRCErr = 3,
  RegTimeout = 4, RegComError = 5 }

  The tRegisterStatusTypes enum.

- enum tParamSetUnitTypes {
  UnitNone = 0, UnitmV = 1, UnitV = 2, UnituA = 3,
  UnitmA = 4, UnitA = 5, UnituW = 6, UnitcmW = 7,
  UnitdmW = 8, UnitmW = 9, UnitW = 10, UnitmC = 11,
  UnitcC = 12, UnitdC = 13, Unitpm = 14, Unitdnm = 15,
  Unitnm = 16, UnitPerCent = 17, UnitPerMille = 18, UnitcmA = 19,
  UnitdmA = 20, UnitRPM = 21, UnitdBm = 22, UnitcBm = 23,
  UnitmBm = 24, UnitdB = 25, UnitcB = 26, UnitmB = 27,
  Unitdpm = 28, UnitcV = 29, UnitdV = 30, Unitlm = 31,
  Unitdlm = 32, Unitclm = 33, Unitmlm = 34 }

  The tParamSetUnitTypes enum.

Port functions

- typedef void(__cdecl * GetAllPortsFuncPtr) (char *portnames, unsigned short *maxLen)
- typedef void(__cdecl * GetOpenPortsFuncPtr) (char *portnames, unsigned short *maxLen)
- typedef P2PPortResultTypes(__cdecl * PointToPointPortAddFuncPtr) (const char *portname, const char *hostAddress, const unsigned short hostPort, const char *clientAddress, const unsigned short clientPort, const unsigned char protocol, const unsigned char msTimeout)
- typedef P2PPortResultTypes(__cdecl * PointToPointPortGetFuncPtr) (const char *portname, char *hostAddress, unsigned char *hostMaxLen, unsigned short *hostPort, char *clientAddress, unsigned char *clientMaxLen, unsigned short *clientPort, unsigned char *protocol, unsigned char *msTimeout)
- typedef P2PPortResultTypes(__cdecl * PointToPointPortDelFuncPtr) (const char *portname)
- typedef PortResultTypes(__cdecl * OpenPortsFuncPtr) (const char *portnames, const char autoMode, const char liveMode)
- typedef PortResultTypes(__cdecl * ClosePortsFuncPtr) (const char *portnames)
- typedef void(__cdecl * SetLegacyBusScanningFuncPtr) (const char legacyScanning)
- typedef unsigned char(__cdecl * GetLegacyBusScanningFuncPtr) ()
- typedef PortResultTypes(__cdecl * getPortStatusFuncPtr) (const char *portname, PortStatusTypes *portStatus)
- typedef PortResultTypes(__cdecl * getPortErrorMsgFuncPtr) (const char *portname, char *errorMessage, unsigned short *maxLen)
- NKTPDLL_EXPORT void getAllPorts (char *portnames, unsigned short *maxLen)

  Returns a comma separated string with all existing ports.
- NKTPDLL_EXPORT void getOpenPorts (char *portnames, unsigned short *maxLen)

  Returns a comma separated string with all allready opened ports.
- NKTPDLL_EXPORT P2PPortResultTypes pointToPointPortAdd (const char *portname, const char *hostAddress, const unsigned short hostPort, const char *clientAddress, const unsigned short clientPort, const unsigned char protocol, const unsigned char msTimeout)

  Creates or Modifies a point to point port.
- NKTPDLL_EXPORT P2PPortResultTypes pointToPointPortGet (const char *portname, char *hostAddress, unsigned char *hostMaxLen, unsigned short *hostPort, char *clientAddress, unsigned char *clientMaxLen, unsigned short *clientPort, unsigned char *protocol, unsigned char *msTimeout)

  Retrieve an already created point to point port setting.
- NKTPDLL_EXPORT P2PPortResultTypes pointToPointPortDel (const char *portname)

  Delete an already created point to point port.
- NKTPDLL_EXPORT PortResultTypes openPorts (const char *portnames, const char autoMode, const char liveMode)

  Opens the provided portname(s), or all available ports if an empty string provided. Repeatedly calls is allowed to reopen and/or rescan for devices.

  .
- NKTPDLL_EXPORT PortResultTypes closePorts (const char *portnames)

  Closes the provided portname(s), or all opened ports if an empty string provided.
- NKTPDLL_EXPORT void setLegacyBusScanning (const char legacyScanning)

Sets legacy busscanning on or off.

- NKTPDLL_EXPORT unsigned char getLegacyBusScanning ()

  Gets legacy busscanning status.

- NKTPDLL_EXPORT PortResultTypes getPortStatus (const char *portname, PortStatusTypes *portStatus)

  Retrieve tPortStatusTypes for a given port.

- NKTPDLL_EXPORT PortResultTypes getPortErrorMsg (const char *portname, char *errorMessage, unsigned short *maxLen)

  Retrieve error message for a given port. An empty string indicates no error.

Dedicated - Register read functions.

It is not necessary to open the port, create the device or register before using those functions, since they will do a dedicated action. Even though an already opened port would be preffered in time critical situations where a lot of reads or writes is required.

- typedef RegisterResultTypes(__cdecl * RegisterReadFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, void *readData, unsigned char *readSize, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadU8FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, unsigned char *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadS8FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, signed char *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadU16FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, unsigned short *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadS16FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, signed short *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadU32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, unsigned long *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadS32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, signed long *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadU64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, unsigned long long *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadS64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, signed long long *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadF32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, float *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadF64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, double *value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterReadAsciiFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, char *readStr, unsigned char *maxLen, const short index)
- NKTPDLL_EXPORT RegisterResultTypes registerRead (const char *portname, const unsigned char devId, const unsigned char regId, void *readData, unsigned char *readSize, const short index)

  Reads a register value and returns the result in readData area.

- NKTPDLL_EXPORT RegisterResultTypes registerReadU8 (const char *portname, const unsigned char devId, const unsigned char regId, unsigned char *value, const short index)

  Reads an unsigned char (8bit) register value and returns the result in value.

- NKTPDLL_EXPORT RegisterResultTypes registerReadS8 (const char *portname, const unsigned char devId, const unsigned char regId, signed char *value, const short index)

  Reads a signed char (8bit) register value and returns the result in value.

- NKTPDLL_EXPORT RegisterResultTypes registerReadU16 (const char *portname, const unsigned char devId, const unsigned char regId, unsigned short *value, const short index)

  Reads an unsigned short (16bit) register value and returns the result in value.

- NKTPDLL_EXPORT RegisterResultTypes registerReadS16 (const char *portname, const unsigned char devId, const unsigned char regId, signed short *value, const short index)

Reads a signed short (16bit) register value and returns the result in value.

- NKTPDLL_EXPORT RegisterResultTypes registerReadU32 (const char *portname, const unsigned char devId, const unsigned char regId, unsigned long *value, const short index)

  Reads an unsigned long (32bit) register value and returns the result in value.
- NKTPDLL_EXPORT RegisterResultTypes registerReadS32 (const char *portname, const unsigned char devId, const unsigned char regId, signed long *value, const short index)

  Reads a signed long (32bit) register value and returns the result in value.
- NKTPDLL_EXPORT RegisterResultTypes registerReadU64 (const char *portname, const unsigned char devId, const unsigned char regId, unsigned long long *value, const short index)

  Reads an unsigned long long (64bit) register value and returns the result in value.
- NKTPDLL_EXPORT RegisterResultTypes registerReadS64 (const char *portname, const unsigned char devId, const unsigned char regId, signed long long *value, const short index)

  Reads a signed long long (64bit) register value and returns the result in value.
- NKTPDLL_EXPORT RegisterResultTypes registerReadF32 (const char *portname, const unsigned char devId, const unsigned char regId, float *value, const short index)

  Reads a float (32bit) register value and returns the result in value.
- NKTPDLL_EXPORT RegisterResultTypes registerReadF64 (const char *portname, const unsigned char devId, const unsigned char regId, double *value, const short index)

  Reads a double (64bit) register value and returns the result in value.
- NKTPDLL_EXPORT RegisterResultTypes registerReadAscii (const char *portname, const unsigned char devId, const unsigned char regId, char *readStr, unsigned char *maxLen, const short index)

  Reads a Ascii string register value and returns the result in readStr area.

Dedicated - Register write functions.

It is not necessary to open the port, create the device or register before using those functions, since they will do a dedicated action. Even though an already opened port would be preffered in time critical situations where a lot of reads or writes is required.

- typedef RegisterResultTypes(__cdecl * RegisterWriteFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const void *writeData, const unsigned char writeSize, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteU8FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned char value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteS8FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed char value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteU16FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned short value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteS16FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed short value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteU32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteS32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed long value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteU64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long long value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteS64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed long long value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteF32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const float value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteF64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const double value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteAsciiFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const char *writeStr, const char writeEOL, const short index)

- NKTPDLL_EXPORT RegisterResultTypes registerWrite (const char *portname, const unsigned char devId, const unsigned char regId, const void *writeData, const unsigned char writeSize, const short index)

  Writes a register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteU8 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned char value, const short index)

  Writes an unsigned char (8bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteS8 (const char *portname, const unsigned char devId, const unsigned char regId, const signed char value, const short index)

  Writes a signed char (8bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteU16 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned short value, const short index)

  Writes an unsigned short (16bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteS16 (const char *portname, const unsigned char devId, const unsigned char regId, const signed short value, const short index)

  Writes a signed short (16bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteU32 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long value, const short index)

  Writes an unsigned long (32bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteS32 (const char *portname, const unsigned char devId, const unsigned char regId, const signed long value, const short index)

  Writes a signed long (32bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteU64 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long long value, const short index)

  Writes an unsigned long long (64bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteS64 (const char *portname, const unsigned char devId, const unsigned char regId, const signed long long value, const short index)

  Writes a signed long long (64bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteF32 (const char *portname, const unsigned char devId, const unsigned char regId, const float value, const short index)

  Writes a float (32bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteF64 (const char *portname, const unsigned char devId, const unsigned char regId, const double value, const short index)

  Writes a double (64bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteAscii (const char *portname, const unsigned char devId, const unsigned char regId, const char *writeStr, const char writeEOL, const short index)

  Writes a string register value.

Dedicated - Register write/read functions (A write immediately followed by a read)

It is not necessary to open the port, create the device or register before using those functions, since they will do a dedicated action. Even though an already opened port would be preffered in time critical situations where a lot of reads or writes is required.

- typedef RegisterResultTypes(__cdecl * RegisterWriteReadFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const void *writeData, const unsigned char writeSize, void *readData, unsigned char *readSize, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadU8FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned char writeValue, unsigned char *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadS8FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed char writeValue, signed char *readValue, const short index)

- typedef RegisterResultTypes(__cdecl * RegisterWriteReadU16FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned short writeValue, unsigned short *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadS16FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed short writeValue, signed short *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadU32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long writeValue, unsigned long *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadS32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed long writeValue, signed long *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadU64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long long writeValue, unsigned long long *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadS64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const signed long long writeValue, signed long long *read↩ Value, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadF32FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const float writeValue, float *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadF64FuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const double writeValue, double *readValue, const short index)
- typedef RegisterResultTypes(__cdecl * RegisterWriteReadAsciiFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const char *writeStr, const char writeEOL, char *readStr, unsigned char *maxLen, const short index)
- NKTPDLL_EXPORT RegisterResultTypes registerWriteRead (const char *portname, const unsigned char devId, const unsigned char regId, const void *writeData, const unsigned char writeSize, void *readData, unsigned char *readSize, const short index)

  Writes and Reads a register value before returning.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU8 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned char writeValue, unsigned char *readValue, const short index)

  Writes and Reads an unsigned char (8bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS8 (const char *portname, const unsigned char devId, const unsigned char regId, const signed char writeValue, signed char *readValue, const short index)

  Writes and Reads a signed char (8bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU16 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned short writeValue, unsigned short *readValue, const short index)

  Writes and Reads an unsigned short (16bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS16 (const char *portname, const unsigned char devId, const unsigned char regId, const signed short writeValue, signed short *readValue, const short index)

  Writes and Reads a signed short (16bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU32 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long writeValue, unsigned long *readValue, const short index)

  Writes and Reads an unsigned long (32bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS32 (const char *portname, const unsigned char devId, const unsigned char regId, const signed long writeValue, signed long *readValue, const short index)

  Writes and Reads a signed long (32bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU64 (const char *portname, const unsigned char devId, const unsigned char regId, const unsigned long long writeValue, unsigned long long *readValue, const short index)

Writes and Reads an unsigned long long (64bit) register value.

- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS64 (const char *portname, const unsigned char devId, const unsigned char regId, const signed long long writeValue, signed long long *readValue, const short index)

  Writes and Reads a signed long long (64bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadF32 (const char *portname, const unsigned char devId, const unsigned char regId, const float writeValue, float *readValue, const short index)

  Writes and Reads a float (32bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadF64 (const char *portname, const unsigned char devId, const unsigned char regId, const double writeValue, double *readValue, const short index)

  Writes and Reads a double (64bit) register value.
- NKTPDLL_EXPORT RegisterResultTypes registerWriteReadAscii (const char *portname, const unsigned char devId, const unsigned char regId, const char *writeStr, const char writeEOL, char *readStr, unsigned char *maxLen, const short index)

  Writes and Reads a string register value.

Dedicated - Device functions

Dedicated - Device functions could be used directly.
It is not necessary to open the port, create the device or register before using those functions, since they will do a dedicated action. Even though an already opened port would be preffered in time critical situations where a lot of reads is required.

- typedef DeviceResultTypes(__cdecl * DeviceGetTypeFuncPtr) (const char *portname, const unsigned char devId, unsigned char *devType)
- typedef DeviceResultTypes(__cdecl * DeviceGetSysTypeFuncPtr) (const char *portname, const unsigned char devId, unsigned char *sysType)
- typedef DeviceResultTypes(__cdecl * DeviceGetPartNumberStrFuncPtr) (const char *portname, const unsigned char devId, char *partnumber, unsigned char *maxLen)
- typedef DeviceResultTypes(__cdecl * DeviceGetPCBVersionFuncPtr) (const char *portname, const unsigned char devId, unsigned char *PCBVersion)
- typedef DeviceResultTypes(__cdecl * DeviceGetStatusBitsFuncPtr) (const char *portname, const unsigned char devId, unsigned long *statusBits)
- typedef DeviceResultTypes(__cdecl * DeviceGetErrorCodeFuncPtr) (const char *portname, const unsigned char devId, unsigned short *errorCode)
- typedef DeviceResultTypes(__cdecl * DeviceGetBootloaderVersionFuncPtr) (const char *portname, const unsigned char devId, unsigned short *version)
- typedef DeviceResultTypes(__cdecl * DeviceGetBootloaderVersionStrFuncPtr) (const char *portname, const unsigned char devId, char *versionStr, unsigned char *maxLen)
- typedef DeviceResultTypes(__cdecl * DeviceGetFirmwareVersionFuncPtr) (const char *portname, const unsigned char devId, unsigned short *version)
- typedef DeviceResultTypes(__cdecl * DeviceGetFirmwareVersionStrFuncPtr) (const char *portname, const unsigned char devId, char *versionStr, unsigned char *maxLen)
- typedef DeviceResultTypes(__cdecl * DeviceGetModuleSerialNumberStrFuncPtr) (const char *portname, const unsigned char devId, char *serialNumber, unsigned char *maxLen)
- typedef DeviceResultTypes(__cdecl * DeviceGetPCBSerialNumberStrFuncPtr) (const char *portname, const unsigned char devId, char *serialNumber, unsigned char *maxLen)
- NKTPDLL_EXPORT DeviceResultTypes deviceGetType (const char *portname, const unsigned char devId, unsigned char *devType)

  Returns the module type for a specific device id (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetSysType (const char *portname, const unsigned char devId, unsigned char *sysType)

  Returns the system type for a specific device id (module address).

- NKTPDLL_EXPORT DeviceResultTypes deviceGetPartNumberStr (const char *portname, const unsigned char devId, char *partnumber, unsigned char *maxLen)

  Returns the partnumber for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetPCBVersion (const char *portname, const unsigned char devId, unsigned char *PCBVersion)

  Returns the PCB version for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetStatusBits (const char *portname, const unsigned char devId, unsigned long *statusBits)

  Returns the status bits for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetErrorCode (const char *portname, const unsigned char devId, unsigned short *errorCode)

  Returns the error code for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetBootloaderVersion (const char *portname, const unsigned char devId, unsigned short *version)

  Returns the bootloader version for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetBootloaderVersionStr (const char *portname, const unsigned char devId, char *versionStr, unsigned char *maxLen)

  Returns the bootloader version (string) for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetFirmwareVersion (const char *portname, const unsigned char devId, unsigned short *version)

  Returns the firmware version for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetFirmwareVersionStr (const char *portname, const unsigned char devId, char *versionStr, unsigned char *maxLen)

  Returns the firmware version (string) for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetModuleSerialNumberStr (const char *portname, const unsigned char devId, char *serialNumber, unsigned char *maxLen)

  Returns the Module serialnumber (string) for a given device (module address).
- NKTPDLL_EXPORT DeviceResultTypes deviceGetPCBSerialNumberStr (const char *portname, const unsigned char devId, char *serialNumber, unsigned char *maxLen)

  Returns the PCB serialnumber (string) for a given device (module address).

Callback - Device functions

Device functions primarly used in callback environments.

- typedef DeviceResultTypes(__cdecl * DeviceCreateFuncPtr) (const char *portname, const unsigned char devId, const char waitReady)
- typedef DeviceResultTypes(__cdecl * DeviceExistsFuncPtr) (const char *portname, const unsigned char devId, unsigned char *exists)
- typedef DeviceResultTypes(__cdecl * DeviceRemoveFuncPtr) (const char *portname, const unsigned char devId)
- typedef DeviceResultTypes(__cdecl * DeviceRemoveAllFuncPtr) (const char *portname)
- typedef DeviceResultTypes(__cdecl * DeviceGetAllTypesFuncPtr) (const char *portname, unsigned char *types, unsigned char *maxTypes)
- typedef DeviceResultTypes(__cdecl * DeviceGetModeFuncPtr) (const char *portname, const unsigned char devId, unsigned char *devMode)
- typedef DeviceResultTypes(__cdecl * DeviceGetLiveFuncPtr) (const char *portname, const unsigned char devId, unsigned char *liveMode)
- typedef DeviceResultTypes(__cdecl * DeviceSetLiveFuncPtr) (const char *portname, const unsigned char devId, const unsigned char liveMode)
- NKTPDLL_EXPORT DeviceResultTypes deviceCreate (const char *portname, const unsigned char devId, const char waitReady)

Creates a device in the internal devicelist. If the openPorts function has been called with the liveMode = 1 the kernel immediatedly starts to monitor the device.

- NKTPDLL_EXPORT DeviceResultTypes deviceExists (const char *portname, const unsigned char devId, unsigned char *exists)

  Checks if a specific device already exists in the internal devicelist.

- NKTPDLL_EXPORT DeviceResultTypes deviceRemove (const char *portname, const unsigned char devId)

  Remove a specific device from the internal devicelist.

- NKTPDLL_EXPORT DeviceResultTypes deviceRemoveAll (const char *portname)

  Remove all devices from the internal devicelist. No confirmation given, the list is simply cleared.

- NKTPDLL_EXPORT DeviceResultTypes deviceGetAllTypes (const char *portname, unsigned char *types, unsigned char *maxTypes)

  Returns a list with device types (module types) from the internal devicelist.

- NKTPDLL_EXPORT DeviceResultTypes deviceGetMode (const char *portname, const unsigned char devId, unsigned char *devMode)

  Returns the internal device mode for a specific device id (module address).

- NKTPDLL_EXPORT DeviceResultTypes deviceGetLive (const char *portname, const unsigned char devId, unsigned char *liveMode)

  Returns the internal device live status for a specific device id (module address).

- NKTPDLL_EXPORT DeviceResultTypes deviceSetLive (const char *portname, const unsigned char devId, const unsigned char liveMode)

  Sets the internal device live status for a specific device id (module address).

Callback - Register functions

- typedef RegisterResultTypes(__cdecl * RegisterCreateFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const RegisterPriorityTypes priority, const RegisterDataTypes dataType)
- typedef RegisterResultTypes(__cdecl * RegisterExistsFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, unsigned char *exists)
- typedef RegisterResultTypes(__cdecl * RegisterRemoveFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId)
- typedef RegisterResultTypes(__cdecl * RegisterRemoveAllFuncPtr) (const char *portname, const unsigned char devId)
- typedef RegisterResultTypes(__cdecl * RegisterGetAllFuncPtr) (const char *portname, const unsigned char devId, unsigned char *regs, unsigned char *maxRegs)
- NKTPDLL_EXPORT RegisterResultTypes registerCreate (const char *portname, const unsigned char devId, const unsigned char regId, const RegisterPriorityTypes priority, const RegisterDataTypes dataType)

  Creates a register in the internal registerlist. If the openPorts function has been called with the liveMode = 1 the kernel immediatedly starts to monitor the register.

- NKTPDLL_EXPORT RegisterResultTypes registerExists (const char *portname, const unsigned char devId, const unsigned char regId, unsigned char *exists)

  Checks if a specific register already exists in the internal registerlist.

- NKTPDLL_EXPORT RegisterResultTypes registerRemove (const char *portname, const unsigned char devId, const unsigned char regId)

  Remove a specific register from the internal registerlist.

- NKTPDLL_EXPORT RegisterResultTypes registerRemoveAll (const char *portname, const unsigned char devId)

  Remove all registers from the internal registerlist. No confirmation given, the list is simply cleared.

- NKTPDLL_EXPORT RegisterResultTypes registerGetAll (const char *portname, const unsigned char devId, unsigned char *regs, unsigned char *maxRegs)

  Returns a list with register ids (register addresses) from the internal registerlist.

Callback - Support functions

- typedef void(__cdecl * PortStatusCallbackFuncPtr) (const char *portname, const PortStatusTypes status, const unsigned char curScanAdr, const unsigned char maxScanAdr, const unsigned char foundType)

  Defines the PortStatusCallbackFuncPtr for the openPorts and closePorts functions.
- typedef void(__cdecl * SetCallbackPtrPortInfoFuncPtr) (PortStatusCallbackFuncPtr callback)
- typedef void(__cdecl * DeviceStatusCallbackFuncPtr) (const char *portname, const unsigned char devId, const DeviceStatusTypes status, const unsigned char devDataLen, const void *devData)

  Defines the DeviceStatusCallbackFuncPtr for the devices created with the deviceCreate function or created automatically via the openPorts function (Having autoMode = 1).
- typedef void(__cdecl * SetCallbackPtrDeviceInfoFuncPtr) (DeviceStatusCallbackFuncPtr callback)
- typedef void(__cdecl * RegisterStatusCallbackFuncPtr) (const char *portname, const unsigned char devId, const unsigned char regId, const RegisterStatusTypes status, const RegisterDataTypes regType, const unsigned char regDataLen, const void *regData)

  Defines the RegisterStatusCallbackFuncPtr for the registers created or connected with the registerCreate function.
- typedef void(__cdecl * SetCallbackPtrRegisterInfoFuncPtr) (RegisterStatusCallbackFuncPtr callback)
- NKTPDLL_EXPORT void setCallbackPtrPortInfo (PortStatusCallbackFuncPtr callback)

  Enables/Disables callback for port status changes.
- NKTPDLL_EXPORT void setCallbackPtrDeviceInfo (DeviceStatusCallbackFuncPtr callback)

  Enables/Disables callback for device status changes.
- NKTPDLL_EXPORT void setCallbackPtrRegisterInfo (RegisterStatusCallbackFuncPtr callback)

  Enables/Disables callback for register status changes.

LabView - Support functions

- typedef struct lvPortStatusStruct LabViewPortStatusType

  lvPortStatusStruct, A LabView userevent data package
- typedef void(__cdecl * SetLVUserEventPortInfoFuncPtr) (unsigned long *lvUserEventRef)
- typedef struct lvDeviceStatusStruct LabViewDeviceStatusType

  lvDeviceStatusStruct, A LabView userevent data package
- typedef void(__cdecl * SetLVUserEventDeviceInfoFuncPtr) (unsigned long *lvUserEventRef)
- typedef struct lvRegisterStatusStruct LabViewRegisterStatusType

  lvRegisterStatusStruct, A LabView userevent data package
- typedef void(__cdecl * SetLVUserEventRegisterInfoFuncPtr) (unsigned long *lvUserEventRef)
- NKTPDLL_EXPORT void setLVUserEventPortInfo (unsigned long *lvUserEventRef)

  Enables/Disables labView user events for port status changes. Disable events by parsing in a zero value.
- NKTPDLL_EXPORT void setLVUserEventDeviceInfo (unsigned long *lvUserEventRef)

  Enables/Disables labView user events for device status changes. Disable events by parsing in a zero value.
- NKTPDLL_EXPORT void setLVUserEventRegisterInfo (unsigned long *lvUserEventRef)

  Enables/Disables labView user events for register status changes. Disable events by parsing in a zero value.

4.1.1 Detailed Description

NKTP DLL Interface, a communication DLL for interfacing to NKT Photonics products being controlled via the Interbus protocol. The NKTPDLL abstracts the burden of telegram creation and communication handling when communicating/controlling the NKT Photonics products.

Author

HCH

Date

23 June 2017

See also

http://www.nktphotonics.com/lasers-fibers/en/support/software-drivers/

4.1.2 Macro Definition Documentation

4.1.2.1 NKTPDLL_EXPORT

```
#define NKTPDLL_EXPORT __declspec(dllimport)
```

4.1.3 Typedef Documentation

4.1.3.1 PortResultTypes

```
typedef unsigned char PortResultTypes
```

4.1.3.2 P2PPortResultTypes

```
typedef unsigned char P2PPortResultTypes
```

4.1.3.3 DeviceResultTypes

```
typedef unsigned char DeviceResultTypes
```

4.1.3.4 DeviceModeTypes

```
typedef unsigned char DeviceModeTypes
```

4.1.3.5 RegisterResultTypes

```
typedef unsigned char RegisterResultTypes
```

4.1.3.6 RegisterDataTypes

```
typedef unsigned char RegisterDataTypes
```

4.1.3.7 RegisterPriorityTypes

```
typedef unsigned char RegisterPriorityTypes
```

4.1.3.8 PortStatusTypes

```
typedef unsigned char PortStatusTypes
```

4.1.3.9 DeviceStatusTypes

```
typedef unsigned char DeviceStatusTypes
```

4.1.3.10 RegisterStatusTypes

```
typedef unsigned char RegisterStatusTypes
```

4.1.3.11 DateTimeType

```
typedef struct tDateTimeStruct DateTimeType
```

The tDateTime struct 24 hour format.

4.1.3.12 ParamSetUnitTypes

```
typedef unsigned char ParamSetUnitTypes
```

4.1.3.13 ParameterSetType

```
typedef struct tParamSetStruct ParameterSetType
```

The tParameterSet struct.

Note

This is how calculation on parametersets is done internally by modules:
DAC_value = (value * (X/Y)) + Offset; Where value is either ParameterSetType::StartVal or ParameterSetType::FactoryVal
value = (ADC_value * (X/Y)) + Offset; Where value often is available via another measurement register

4.1.3.14 GetAllPortsFuncPtr

```
typedef void(__cdecl * GetAllPortsFuncPtr) (char *portnames, unsigned short *maxLen)
```

4.1.3.15 GetOpenPortsFuncPtr

```
typedef void(__cdecl * GetOpenPortsFuncPtr) (char *portnames, unsigned short *maxLen)
```

4.1.3.16 PointToPointPortAddFuncPtr

```
typedef P2PPortResultTypes(__cdecl * PointToPointPortAddFuncPtr) (const char *portname, const
char *hostAddress, const unsigned short hostPort, const char *clientAddress, const unsigned
short clientPort, const unsigned char protocol, const unsigned char msTimeout)
```

4.1.3.17 PointToPointPortGetFuncPtr

```
typedef P2PPortResultTypes(__cdecl * PointToPointPortGetFuncPtr) (const char *portname, char
*hostAddress, unsigned char *hostMaxLen, unsigned short *hostPort, char *clientAddress, unsigned
char *clientMaxLen, unsigned short *clientPort, unsigned char *protocol, unsigned char *ms↩
Timeout)
```

4.1.3.18 PointToPointPortDelFuncPtr

```
typedef P2PPortResultTypes(__cdecl * PointToPointPortDelFuncPtr) (const char *portname)
```

4.1.3.19 OpenPortsFuncPtr

```
typedef PortResultTypes(__cdecl * OpenPortsFuncPtr) (const char *portnames, const char auto↩
Mode, const char liveMode)
```

4.1.3.20 ClosePortsFuncPtr

```
typedef PortResultTypes(__cdecl * ClosePortsFuncPtr) (const char *portnames)
```

4.1.3.21 SetLegacyBusScanningFuncPtr

```
typedef void(__cdecl * SetLegacyBusScanningFuncPtr) (const char legacyScanning)
```

4.1.3.22 GetLegacyBusScanningFuncPtr

```
typedef unsigned char(__cdecl * GetLegacyBusScanningFuncPtr) ()
```

4.1.3.23 getPortStatusFuncPtr

```
typedef PortResultTypes(__cdecl * getPortStatusFuncPtr) (const char *portname, PortStatusTypes
*portStatus)
```

4.1.3.24 getPortErrorMsgFuncPtr

```
typedef PortResultTypes(__cdecl * getPortErrorMsgFuncPtr) (const char *portname, char *error↩
Message, unsigned short *maxLen)
```

4.1.3.25 RegisterReadFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadFuncPtr) (const char *portname, const unsigned
char devId, const unsigned char regId, void *readData, unsigned char *readSize, const short
index)
```

4.1.3.26 RegisterReadU8FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadU8FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, unsigned char *value, const short index)
```

4.1.3.27 RegisterReadS8FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadS8FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, signed char *value, const short index)
```

4.1.3.28 RegisterReadU16FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadU16FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, unsigned short *value, const short index)
```

4.1.3.29 RegisterReadS16FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadS16FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, signed short *value, const short index)
```

4.1.3.30 RegisterReadU32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadU32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, unsigned long *value, const short index)
```

4.1.3.31 RegisterReadS32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadS32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, signed long *value, const short index)
```

4.1.3.32 RegisterReadU64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadU64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, unsigned long long *value, const short index)
```

4.1.3.33 RegisterReadS64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadS64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, signed long long *value, const short index)
```

4.1.3.34 RegisterReadF32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadF32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, float *value, const short index)
```

4.1.3.35 RegisterReadF64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadF64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, double *value, const short index)
```

4.1.3.36 RegisterReadAsciiFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterReadAsciiFuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, char *readStr, unsigned char *maxLen, const
short index)
```

4.1.3.37 RegisterWriteFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteFuncPtr) (const char *portname, const unsigned
char devId, const unsigned char regId, const void *writeData, const unsigned char writeSize,
const short index)
```

4.1.3.38 RegisterWriteU8FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteU8FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned char value, const short index)
```

4.1.3.39 RegisterWriteS8FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteS8FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed char value, const short index)
```

4.1.3.40 RegisterWriteU16FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteU16FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned short value, const short index)
```

4.1.3.41 RegisterWriteS16FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteS16FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed short value, const short index)
```

4.1.3.42 RegisterWriteU32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteU32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned long value, const short index)
```

4.1.3.43 RegisterWriteS32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteS32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed long value, const short index)
```

4.1.3.44 RegisterWriteU64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteU64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned long long value, const short
index)
```

4.1.3.45 RegisterWriteS64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteS64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed long long value, const short
index)
```

4.1.3.46 RegisterWriteF32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteF32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const float value, const short index)
```

4.1.3.47 RegisterWriteF64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteF64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const double value, const short index)
```

4.1.3.48 RegisterWriteAsciiFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteAsciiFuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const char *writeStr, const char writeEOL,
const short index)
```

4.1.3.49 RegisterWriteReadFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadFuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const void *writeData, const unsigned char
writeSize, void *readData, unsigned char *readSize, const short index)
```

4.1.3.50 RegisterWriteReadU8FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadU8FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned char writeValue, unsigned char
*readValue, const short index)
```

4.1.3.51 RegisterWriteReadS8FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadS8FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed char writeValue, signed char
*readValue, const short index)
```

4.1.3.52 RegisterWriteReadU16FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadU16FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned short writeValue, unsigned
short *readValue, const short index)
```

4.1.3.53 RegisterWriteReadS16FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadS16FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed short writeValue, signed short
*readValue, const short index)
```

4.1.3.54 RegisterWriteReadU32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadU32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned long writeValue, unsigned long
*readValue, const short index)
```

4.1.3.55 RegisterWriteReadS32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadS32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed long writeValue, signed long
*readValue, const short index)
```

4.1.3.56 RegisterWriteReadU64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadU64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const unsigned long long writeValue, unsigned
long long *readValue, const short index)
```

4.1.3.57 RegisterWriteReadS64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadS64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const signed long long writeValue, signed long
long *readValue, const short index)
```

4.1.3.58 RegisterWriteReadF32FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadF32FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const float writeValue, float *readValue,
const short index)
```

4.1.3.59 RegisterWriteReadF64FuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadF64FuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const double writeValue, double *readValue,
const short index)
```

4.1.3.60 RegisterWriteReadAsciiFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterWriteReadAsciiFuncPtr) (const char *portname,
const unsigned char devId, const unsigned char regId, const char *writeStr, const char writeE↩
OL, char *readStr, unsigned char *maxLen, const short index)
```

4.1.3.61 DeviceGetTypeFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetTypeFuncPtr) (const char *portname, const unsigned
char devId, unsigned char *devType)
```

4.1.3.62 DeviceGetSysTypeFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetSysTypeFuncPtr) (const char *portname, const
unsigned char devId, unsigned char *sysType)
```

4.1.3.63 DeviceGetPartNumberStrFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetPartNumberStrFuncPtr) (const char *portname, const
unsigned char devId, char *partnumber, unsigned char *maxLen)
```

4.1.3.64 DeviceGetPCBVersionFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetPCBVersionFuncPtr) (const char *portname, const
unsigned char devId, unsigned char *PCBVersion)
```

4.1.3.65 DeviceGetStatusBitsFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetStatusBitsFuncPtr) (const char *portname, const
unsigned char devId, unsigned long *statusBits)
```

4.1.3.66 DeviceGetErrorCodeFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetErrorCodeFuncPtr) (const char *portname, const
unsigned char devId, unsigned short *errorCode)
```

4.1.3.67 DeviceGetBootloaderVersionFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetBootloaderVersionFuncPtr) (const char *portname,
const unsigned char devId, unsigned short *version)
```

4.1.3.68 DeviceGetBootloaderVersionStrFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetBootloaderVersionStrFuncPtr) (const char *portname,
const unsigned char devId, char *versionStr, unsigned char *maxLen)
```

4.1.3.69 DeviceGetFirmwareVersionFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetFirmwareVersionFuncPtr) (const char *portname,
const unsigned char devId, unsigned short *version)
```

4.1.3.70 DeviceGetFirmwareVersionStrFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetFirmwareVersionStrFuncPtr) (const char *portname,
const unsigned char devId, char *versionStr, unsigned char *maxLen)
```

4.1.3.71 DeviceGetModuleSerialNumberStrFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetModuleSerialNumberStrFuncPtr) (const char *portname,
const unsigned char devId, char *serialNumber, unsigned char *maxLen)
```

4.1.3.72 DeviceGetPCBSerialNumberStrFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetPCBSerialNumberStrFuncPtr) (const char *portname,
const unsigned char devId, char *serialNumber, unsigned char *maxLen)
```

4.1.3.73 DeviceCreateFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceCreateFuncPtr) (const char *portname, const unsigned
char devId, const char waitReady)
```

4.1.3.74 DeviceExistsFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceExistsFuncPtr) (const char *portname, const unsigned
char devId, unsigned char *exists)
```

4.1.3.75 DeviceRemoveFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceRemoveFuncPtr) (const char *portname, const unsigned
char devId)
```

4.1.3.76 DeviceRemoveAllFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceRemoveAllFuncPtr) (const char *portname)
```

4.1.3.77 DeviceGetAllTypesFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetAllTypesFuncPtr) (const char *portname, unsigned
char *types, unsigned char *maxTypes)
```

4.1.3.78 DeviceGetModeFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetModeFuncPtr) (const char *portname, const unsigned
char devId, unsigned char *devMode)
```

4.1.3.79 DeviceGetLiveFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceGetLiveFuncPtr) (const char *portname, const unsigned
char devId, unsigned char *liveMode)
```

4.1.3.80 DeviceSetLiveFuncPtr

```
typedef DeviceResultTypes(__cdecl * DeviceSetLiveFuncPtr) (const char *portname, const unsigned
char devId, const unsigned char liveMode)
```

4.1.3.81 RegisterCreateFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterCreateFuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, const RegisterPriorityTypes priority, const
RegisterDataTypes dataType)
```

4.1.3.82 RegisterExistsFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterExistsFuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId, unsigned char *exists)
```

4.1.3.83 RegisterRemoveFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterRemoveFuncPtr) (const char *portname, const
unsigned char devId, const unsigned char regId)
```

4.1.3.84 RegisterRemoveAllFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterRemoveAllFuncPtr) (const char *portname, const
unsigned char devId)
```

4.1.3.85 RegisterGetAllFuncPtr

```
typedef RegisterResultTypes(__cdecl * RegisterGetAllFuncPtr) (const char *portname, const
unsigned char devId, unsigned char *regs, unsigned char *maxRegs)
```

4.1.3.86 PortStatusCallbackFuncPtr

```
typedef void(__cdecl * PortStatusCallbackFuncPtr) (const char *portname, const PortStatusTypes
status, const unsigned char curScanAdr, const unsigned char maxScanAdr, const unsigned char
foundType)
```

Defines the PortStatusCallbackFuncPtr for the openPorts and closePorts functions.

Parameters

portname	Zero terminated string giving the current portname.
status	The current port status as a PortStatusTypes with a tPortStatusTypes value.
curScanAdr	When status is PortScanProgress or PortScanDeviceFound this indicates the current module address scanned or found.
maxScanAdr	When status is PortScanProgress or PortScanDeviceFound this indicates the last module address to be scanned.
foundType	When status is PortScanDeviceFound this value will represent the found module type.

Note

Please note that due to risk of circular runaway leading to stack overflow, it is not allowed to call functions in the DLL from within the callback function. If a call is made to a function in the DLL the function will therefore return an application busy error.

4.1.3.87 SetCallbackPtrPortInfoFuncPtr

```
typedef void(__cdecl * SetCallbackPtrPortInfoFuncPtr) (PortStatusCallbackFuncPtr callback)
```

4.1.3.88 DeviceStatusCallbackFuncPtr

```
typedef void(__cdecl * DeviceStatusCallbackFuncPtr) (const char *portname, const unsigned char
devId, const DeviceStatusTypes status, const unsigned char devDataLen, const void *devData)
```

Defines the DeviceStatusCallbackFuncPtr for the devices created with the deviceCreate function or created automatically via the openPorts function (Having autoMode = 1).

Parameters

portname	Zero terminated string giving the current portname.
devId	The device id (module address).
status	The current port status as a DeviceStatusTypes with a tDeviceStatusTypes value.

Note

Please note that due to risk of circular runaway leading to stack overflow, it is not allowed to call functions in the DLL from within the callback function. If a call is made to a function in the DLL the function will therefore return an application busy error.

4.1.3.89 SetCallbackPtrDeviceInfoFuncPtr

```
typedef void(__cdecl * SetCallbackPtrDeviceInfoFuncPtr) (DeviceStatusCallbackFuncPtr callback)
```

4.1.3.90 RegisterStatusCallbackFuncPtr

```
typedef void(__cdecl * RegisterStatusCallbackFuncPtr) (const char *portname, const unsigned
char devId, const unsigned char regId, const RegisterStatusTypes status, const RegisterData↩
Types regType, const unsigned char regDataLen, const void *regData)
```

Defines the RegisterStatusCallbackFuncPtr for the registers created or connected with the registerCreate function.

Parameters

portname	Zero terminated string giving the current portname.
status	The current register status as a RegisterStatusTypes with a tRegisterStatusTypes value.
regType	The RegisterDataTypes, not used internally but could be used in a common callback function to determine data type.
regDataLen	Number of databytes.
regData	The register data.

Note

Please note that due to risk of circular runaway leading to stack overflow, it is not allowed to to call functions in the DLL from within the callback function. If a call is made to a function in the DLL the function will therefore return an application busy error.

4.1.3.91 SetCallbackPtrRegisterInfoFuncPtr

```
typedef void(__cdecl * SetCallbackPtrRegisterInfoFuncPtr) (RegisterStatusCallbackFuncPtr callback)
```

4.1.3.92 LabViewPortStatusType

```
typedef struct lvPortStatusStruct LabViewPortStatusType
```

lvPortStatusStruct, A LabView userevent data package

4.1.3.93 SetLVUserEventPortInfoFuncPtr

```
typedef void(__cdecl * SetLVUserEventPortInfoFuncPtr) (unsigned long *lvUserEventRef)
```

4.1.3.94 LabViewDeviceStatusType

```
typedef struct lvDeviceStatusStruct LabViewDeviceStatusType
```

lvDeviceStatusStruct, A LabView userevent data package

4.1.3.95 SetLVUserEventDeviceInfoFuncPtr

```
typedef void(__cdecl * SetLVUserEventDeviceInfoFuncPtr) (unsigned long *lvUserEventRef)
```

4.1.3.96 LabViewRegisterStatusType

```
typedef struct lvRegisterStatusStruct LabViewRegisterStatusType
```

lvRegisterStatusStruct, A LabView userevent data package

4.1.3.97 SetLVUserEventRegisterInfoFuncPtr

```
typedef void(__cdecl * SetLVUserEventRegisterInfoFuncPtr) (unsigned long *lvUserEventRef)
```

4.1.4 Enumeration Type Documentation

4.1.4.1 tPortResultTypes

```
enum tPortResultTypes
```

The tPortResultTypes enum.

Enumerator

OPSuccess	0 - Successfull operation.
OPFailed	1 - The openPorts function has failed.
OPPortNotFound	2 - The specified portname could not be found.
OPNoDevices	3 - No devices found on the specified port.
OPApplicationBusy	4 - The function is not allowed to be invoked from within a callback function.

4.1.4.2 tP2PPortResultTypes

```
enum tP2PPortResultTypes
```

The tPointToPointPortStatus enum.

Enumerator

P2PSuccess	0 - Successfull operation.
P2PInvalidPortname	1 - Invalid portname provided.
P2PInvalidLocalIP	2 - Invalid local IP provided.
P2PInvalidRemoteIP	3 - Invalid remote IP provided.
P2PPortnameNotFound	4 - Portname not found.
P2PPortnameExists	5 - Portname already exists.
P2PApplicationBusy	6 - The function is not allowed to be invoked from within a callback function.

4.1.4.3 tDeviceResultTypes

`enum tDeviceResultTypes`

The tDeviceResultTypes enum.

Enumerator

DevResultSuccess	0 - Successfull operation.
DevResultWaitTimeout	1 - The function deviceCreate, timed out waiting for the device being ready.
DevResultFailed	2 - The function deviceCreate, failed.
DevResultDeviceNotFound	3 - The specified device could not be found in the internal device list.
DevResultPortNotFound	4 - The function deviceCreate, failed due to not being able to find the specified port.
DevResultPortOpenError	5 - The function deviceCreate, failed due to port not being open.
DevResultApplicationBusy	6 - The function is not allowed to be invoked from within a callback function.

4.1.4.4 tDeviceModeTypes

`enum tDeviceModeTypes`

The tDeviceModeTypes enum.

Enumerator

DevModeDisabled	0 - The device is disabled. Not being polled and serviced.
DevModeAnalyzeInit	1 - The analyze cycle has been started for the device.
DevModeAnalyze	2 - The analyze cycle is in progress. All default registers being read to determine its state.
DevModeNormal	3 - The analyze cycle has completed and the device is ready.
DevModeLogDownload	4 - A log is being downloaded from the device.
DevModeError	5 - The device is in an error state.
DevModeTimeout	6 - The connection to the device has been lost.
DevModeUpload	7 - The device is in upload mode and can not be used normally.

4.1.4.5 tRegisterResultTypes

`enum tRegisterResultTypes`

The tRegisterResultTypes enum.

Enumerator

RegResultSuccess	0 - Successfull operation.
RegResultReadError	1 - Arises from a registerWrite function with index $>$ 0, if the pre-read fails.
RegResultFailed	2 - The function registerCreate has failed.
RegResultBusy	3 - The module has reported a BUSY error, the kernel automatically retries on busy but have given up.
RegResultNacked	4 - The module has Nacked the register, which typically means non existing register.
RegResultCRCErr	5 - The module has reported a CRC error, which means the received message has CRC errors.
RegResultTimeout	6 - The module has not responded in time. A module should respond in max. 75ms
RegResultComError	7 - The module has reported a COM error, which typically means out of sync or garbage error.
RegResultTypeError	8 - The datatype does not seem to match the register datatype.
RegResultIndexError	9 - The index seem to be out of range of the register length.
RegResultPortClosed	10 - The specified port is closed error. Could happen if the USB is unplugged in the middel of a sequence.
RegResultRegisterNotFound	11 - The specified register could not be found in the internal register list for the specified device.
RegResultDeviceNotFound	12 - The specified device could not be found in the internal device list.
RegResultPortNotFound	13 - The specified portname could not be found.
RegResultPortOpenError	14 - The specified portname could not be opened. The port might be in use by another application.
RegResultApplicationBusy	15 - The function is not allowed to be invoked from within a callback function.

4.1.4.6 tRegisterDataTypes

`enum tRegisterDataTypes`

The tRegisterDataTypes enum.

Enumerator

RegData_Unknown	0 - Unknown/Undefined data type.
RegData_Mixed	1 - Mixed content data type.
RegData_U8	2 - 8 bit unsigned data type (unsigned char).
RegData_S8	3 - 8 bit signed data type (char).
RegData_U16	4 - 16 bit unsigned data type (unsigned short).
RegData_S16	5 - 16 bit signed data type (short).
RegData_U32	6 - 32 bit unsigned data type (unsigned long).
RegData_S32	7 - 32 bit signed data type (long).
RegData_F32	8 - 32 bit floating point data type (float).

Enumerator

RegData_U64	9 - 64 bit unsigned data type (unsigned long long).
RegData_S64	10 - 64 bit signed data type (long long).
RegData_F64	11 - 64 bit floating point data type (double).
RegData_Ascii	12 - Zero terminated ascii string data type.
RegData_Paramset	13 - Parameterset data type. ParameterSetType
RegData_B8	14 - 8 bit binary data type (unsigned char).
RegData_H8	15 - 8 bit hexadecimal data type (unsigned char).
RegData_B16	16 - 16 bit binary data type (unsigned short).
RegData_H16	17 - 16 bit hexadecimal data type (unsigned short).
RegData_B32	18 - 32 bit binary data type (unsigned long).
RegData_H32	19 - 32 bit hexadecimal data type (unsigned long).
RegData_B64	20 - 64 bit binary data type (unsigned long long).
RegData_H64	21 - 64 bit hexadecimal data type (unsigned long long).
RegData_DateTime	22 - Datetime data type. DateTimeType

4.1.4.7 tRegisterPriorityTypes

`enum tRegisterPriorityTypes`

The tRegisterPriorityTypes enum.

Enumerator

RegPriority_Low	0 - The register is polled with low priority.
RegPriority_High	1 - The register is polled with high priority.

4.1.4.8 tPortStatusTypes

`enum tPortStatusTypes`

The tPortStatusTypes enum.

Enumerator

PortStatusUnknown	0 - Unknown status.
PortOpening	1 - The port is opening.
PortOpened	2 - The port is now open.
PortOpenFail	3 - The port open failed.
PortScanStarted	4 - The port scanning is started.
PortScanProgress	5 - The port scanning progress.
PortScanDeviceFound	6 - The port scan found a device.
PortScanEnded	7 - The port scanning ended.
PortClosing	8 - The port is closing.
PortClosed	9 - The port is now closed.
PortReady	10 - The port is open and ready.

4.1.4.9 tDeviceStatusTypes

`enum tDeviceStatusTypes`

The tDeviceStatusTypes enum.

Enumerator

DeviceModeChanged	0 - devData contains 1 unsigned byte DeviceModeTypes
DeviceLiveChanged	1 - devData contains 1 unsigned byte, 0=live off, 1=live on.
DeviceTypeChanged	2 - devData contains 1 unsigned byte with DeviceType (module type).
DevicePartNumberChanged	3 - devData contains a zero terminated string with partnumber.
DevicePCBVersionChanged	4 - devData contains 1 unsigned byte with PCB version number.
DeviceStatusBitsChanged	5 - devData contains 1 unsigned long with statusbits.
DeviceErrorCodeChanged	6 - devData contains 1 unsigned short with errorcode.
DeviceBlVerChanged	7 - devData contains a zero terminated string with Bootloader version.
DeviceFwVerChanged	8 - devData contains a zero terminated string with Firmware version.
DeviceModuleSerialChanged	9 - devData contains a zero terminated string with Module serialnumber.
DevicePCBSerialChanged	10 - devData contains a zero terminated string with PCB serialnumber.
DeviceSysTypeChanged	11 - devData contains 1 unsigned byte with SystemType (system type).

4.1.4.10 tRegisterStatusTypes

`enum tRegisterStatusTypes`

The tRegisterStatusTypes enum.

Enumerator

RegSuccess	0 - Register operation was successfull.
RegBusy	1 - Register operation resulted in a busy.
RegNacked	2 - Register operation resulted in a nack, seems to be non existing register.
RegCRCErr	3 - Register operation resulted in a CRC error.
RegTimeout	4 - Register operation resulted in a timeout.
RegComError	5 - Register operation resulted in a COM error. Out of sync. or garbage error.

4.1.4.11 tParamSetUnitTypes

`enum tParamSetUnitTypes`

The tParamSetUnitTypes enum.

Enumerator

UnitNone	0 - none/unknown
UnitmV	1 - mV
UnitV	2 - V

Enumerator

UnituA	3 - µA
UnitmA	4 - mA
UnitA	5 - A
UnituW	6 - µW
UnitcmW	7 - mW/100
UnitdmW	8 - mW/10
UnitmW	9 - mW
UnitW	10 - W
UnitmC	11 - ℃/1000
UnitcC	12 - ℃/100
UnitdC	13 - ℃/10
Unitpm	14 - pm
Unitdnm	15 - nm/10
Unitnm	16 - nm
UnitPerCent	17 - %
UnitPerMille	18 - %■
UnitcmA	19 - mA/100
UnitdmA	20 - mA/10
UnitRPM	21 - RPM
UnitdBm	22 - dBm
UnitcBm	23 - dBm/10
UnitmBm	24 - dBm/100
UnitdB	25 - dB
UnitcB	26 - dB/10
UnitmB	27 - dB/100
Unitdpm	28 - pm/10
UnitcV	29 - V/100
UnitdV	30 - V/10
Unitlm	31 - lm (lumen)
Unitdlm	32 - lm/10
Unitclm	33 - lm/100
Unitmlm	34 - lm/1000

4.1.5 Function Documentation

4.1.5.1 getAllPorts()

```
NKTPDLL_EXPORT void getAllPorts (
            char * portnames,
            unsigned short * maxLen )
```

Returns a comma separated string with all existing ports.

Parameters

portnames	Pointer to a preallocated string area where the function will store the comma separated string.
maxLen	Size of preallocated string area. The returned string may be truncated to fit into the allocated area.

4.1.5.2 getOpenPorts()

```
NKTPDLL_EXPORT void getOpenPorts (
            char * portnames,
            unsigned short * maxLen )
```

Returns a comma separated string with all allready opened ports.

Parameters

portnames	Pointer to a preallocated string area where the function will store the comma separated string.
maxLen	Size of preallocated string area. The returned string may be truncated to fit into the allocated area.

4.1.5.3 pointToPointPortAdd()

```
NKTPDLL_EXPORT P2PPortResultTypes pointToPointPortAdd (
            const char * portname,
            const char * hostAddress,
            const unsigned short hostPort,
            const char * clientAddress,
            const unsigned short clientPort,
            const unsigned char protocol,
            const unsigned char msTimeout )
```

Creates or Modifies a point to point port.

Parameters

portname	Zero terminated string giving the portname. ex. "AcoustikPort1"
hostAddress	Zero terminated string giving the local ip address. ex. "192.168.1.67"
hostPort	The local port number.
clientAddress	Zero terminated string giving the remote ip address. ex. "192.168.1.100"
clientPort	The remote port number.
protocol	• 0 Specifies TCP protocol. • 1 Specifies UDP protocol.
msTimeout	Telegram timeout value in milliseconds, typically set to 100ms.

Returns

tP2PPortResultTypes

4.1.5.4 pointToPointPortGet()

```
NKTPDLL_EXPORT P2PPortResultTypes pointToPointPortGet (
            const char * portname,
            char * hostAddress,
```

```
            unsigned char * hostMaxLen,
            unsigned short * hostPort,
            char * clientAddress,
            unsigned char * clientMaxLen,
            unsigned short * clientPort,
            unsigned char * protocol,
            unsigned char * msTimeout )
```

Retrieve an already created point to point port setting.

Parameters

portname	Zero terminated string giving the portname (case sensitive). ex. "AcoustikPort1"
hostAddress	Pointer to a preallocated string area where the function will store the zero terminated string, describing the local ip address.
hostMaxLen	Pointer to an unsigned char giving the size of the preallocated hostAddress area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.
hostPort	Pointer to a preallocated short where the function will store the local port number.
clientAddress	Pointer to a preallocated string area where the function will store the zero terminated string, describing the remote ip address.
clientMaxLen	Pointer to an unsigned char giving the size of the preallocated clientAddress area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.
clientPort	Pointer to a preallocated short where the function will store the client port number.
protocol	Pointer to a preallocated char where the function will store the protocol. • 0 Specifies TCP protocol. • 1 Specifies UDP protocol.
msTimeout	Pointer to a preallocated char where the function will store the timeout value.

Returns

tP2PPortResultTypes

4.1.5.5 pointToPointPortDel()

```
NKTPDLL_EXPORT P2PPortResultTypes pointToPointPortDel (
            const char * portname )
```

Delete an already created point to point port.

Parameters

portname	Zero terminated string giving the portname (case sensitive). ex. "AcoustikPort1"

Returns

tP2PPortResultTypes

4.1.5.6 openPorts()

```
NKTPDLL_EXPORT PortResultTypes openPorts (
            const char * portnames,
            const char autoMode,
            const char liveMode )
```

Opens the provided portname(s), or all available ports if an empty string provided. Repeatedly calls is allowed to reopen and/or rescan for devices.
.

Parameters

portnames	Zero terminated comma separated string giving the portnames to open (case sensitive). An empty string opens all available ports.
autoMode	• 0 the openPorts function only opens the port. Busscanning and device creation is NOT automatically handled. • 1 the openPorts function will automatically start the busscanning and create the found devices in the internal devicelist. The port is automatically closed if no devices found.
liveMode	• 0 the openPorts function disables the continuously monitoring of the registers. No callback possible on register changes. Use registerRead, registerWrite & registerWriteRead functions. • 1 the openPorts function will keep all the found or created devices in live mode, which means the Interbus kernel keeps monitoring all the found devices and their registers. Please note that this will keep the modules watchdog alive as long as the port is open.

Returns

tPortResultTypes

Note

The function may timeout after 2 seconds waiting for port ready status and return OPFailed.
In case autoMode is specified this timeout is extended to 20 seconds to allow for busscanning to complete.

4.1.5.7 closePorts()

```
NKTPDLL_EXPORT PortResultTypes closePorts (
            const char * portnames )
```

Closes the provided portname(s), or all opened ports if an empty string provided.

Parameters

portnames	Zero terminated comma separated string giving the portnames to close (case sensitive). An empty string closes all open ports.

Returns

tPortResultTypes

Note

The function may timeout after 2 seconds waiting for port close to complete and return OPFailed.

4.1.5.8 setLegacyBusScanning()

```
NKTPDLL_EXPORT void setLegacyBusScanning (
            const char legacyScanning )
```

Sets legacy busscanning on or off.

Parameters

legacyScanning	• 0 the busscanning is set to normal mode and allows for rolling masterId. In this mode the masterId is changed for each message to allow for out of sync. detection. • 1 the busscanning is set to legacy mode and fixes the masterId at address 66(0x42). Some older modules does not accept masterIds other than 66(ox42).

See also

getLegacyBusScanning

4.1.5.9 getLegacyBusScanning()

```
NKTPDLL_EXPORT unsigned char getLegacyBusScanning ( )
```

Gets legacy busscanning status.

Returns

An unsigned char, with legacyScanning status. 0 the busscanning is currently in normal mode. 1 the busscanning is currently in legacy mode.

See also

setLegacyBusScanning

4.1.5.10 getPortStatus()

```
NKTPDLL_EXPORT PortResultTypes getPortStatus (
            const char * portname,
            PortStatusTypes * portStatus )
```

Retrieve tPortStatusTypes for a given port.

Parameters

portname	Zero terminated string giving the portname (case sensitive). ex. "COM1"
portStatus	Pointer to a PortStatusTypes where the function will store the port status.

Returns

tPortResultTypes

4.1.5.11 getPortErrorMsg()

```
NKTPDLL_EXPORT PortResultTypes getPortErrorMsg (
            const char * portname,
            char * errorMessage,
            unsigned short * maxLen )
```

Retrieve error message for a given port. An empty string indicates no error.

Parameters

portname	Zero terminated string giving the portname (case sensitive). ex. "COM1"
errorMessage	Pointer to a preallocated string area where the function will store the zero terminated error string.
maxLen	Pointer to an unsigned short giving the size of the preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.

Returns

tPortResultTypes

4.1.5.12 registerRead()

```
NKTPDLL_EXPORT RegisterResultTypes registerRead (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            void * readData,
            unsigned char * readSize,
            const short index )
```

Reads a register value and returns the result in readData area.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
readData	Pointer to a preallocated data area where the function will store the register value.

Parameters

readSize	Size of preallocated data area, modified by the function to reflect the actual length of the returned register value. The returned register value may be truncated to fit into the allocated area.
index	Data index. Typically -1, but could be used to extract data from a specific position in the register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

See also

registerReadU8, registerReadS8 etc.

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.13 registerReadU8()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadU8 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            unsigned char * value,
            const short index )
```

Reads an unsigned char (8bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to an unsigned char where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.14 registerReadS8()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadS8 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            signed char * value,
            const short index )
```

Reads a signed char (8bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to a signed char where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.15 registerReadU16()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadU16 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            unsigned short * value,
            const short index )
```

Reads an unsigned short (16bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to an unsigned short where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.16 registerReadS16()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadS16 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            signed short * value,
            const short index )
```

Reads a signed short (16bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to a signed short where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.17 registerReadU32()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadU32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            unsigned long * value,
            const short index )
```

Reads an unsigned long (32bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to an unsigned long where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.18 registerReadS32()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadS32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            signed long * value,
            const short index )
```

Reads a signed long (32bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to a signed long where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.19 registerReadU64()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadU64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            unsigned long long * value,
            const short index )
```

Reads an unsigned long long (64bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to an unsigned long long where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.20 registerReadS64()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadS64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            signed long long * value,
            const short index )
```

Reads a signed long long (64bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to a signed long long where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.21 registerReadF32()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadF32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            float * value,
            const short index )
```

Reads a float (32bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to a float where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.22 registerReadF64()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadF64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            double * value,
            const short index )
```

Reads a double (64bit) register value and returns the result in value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	Pointer to a double where the function will store the register value.
index	Value index. Typically -1, but could be used to extract a value in a multi value register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.23 registerReadAscii()

```
NKTPDLL_EXPORT RegisterResultTypes registerReadAscii (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            char * readStr,
            unsigned char * maxLen,
            const short index )
```

Reads a Ascii string register value and returns the result in readStr area.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
readStr	Pointer to a preallocated string area where the function will store the register value.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.
index	Value index. Typically -1, but could be used to extract a string in a mixed type register. Index is byte counted.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.24 registerWrite()

```
NKTPDLL_EXPORT RegisterResultTypes registerWrite (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const void * writeData,
            const unsigned char writeSize,
            const short index )
```

Writes a register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeData	Pointer to a data area from where the write value will be extracted.
writeSize	Size of data area, ex. number of bytes to write. Write size is limited to max 240 bytes
index	Data index. Typically -1, but could be used to write data at a specific position in the register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

See also

registerWriteU8, registerWriteS8 etc.

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.25 registerWriteU8()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteU8 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned char value,
            const short index )
```

Writes an unsigned char (8bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).

Parameters

devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.26 registerWriteS8()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteS8 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed char value,
            const short index )
```

Writes a signed char (8bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.27 registerWriteU16()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteU16 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned short value,
            const short index )
```

Writes an unsigned short (16bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.28 registerWriteS16()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteS16 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed short value,
            const short index )
```

Writes a signed short (16bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.29 registerWriteU32()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteU32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned long value,
            const short index )
```

Writes an unsigned long (32bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.30 registerWriteS32()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteS32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed long value,
            const short index )
```

Writes a signed long (32bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.31 registerWriteU64()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteU64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned long long value,
            const short index )
```

Writes an unsigned long long (64bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.32 registerWriteS64()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteS64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed long long value,
            const short index )
```

Writes a signed long long (64bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.33 registerWriteF32()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteF32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const float value,
            const short index )
```

Writes a float (32bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.34 registerWriteF64()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteF64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const double value,
            const short index )
```

Writes a double (64bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
value	The register value to write.
index	Value index. Typically -1, but could be used to write a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.35 registerWriteAscii()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteAscii (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const char * writeStr,
            const char writeEOL,
            const short index )
```

Writes a string register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeStr	The zero terminated string to write. WriteStr will be limited to 239 characters and the terminating zero, totally 240 bytes.
writeEOL	• 0 Do NOT append End Of Line character (a null character) to the string. • 1 Append End Of Line character to the string.
index	Value index. Typically -1, but could be used to write a value in a mixed type register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write.

4.1.5.36 registerWriteRead()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteRead (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const void * writeData,
            const unsigned char writeSize,
            void * readData,
            unsigned char * readSize,
            const short index )
```

Writes and Reads a register value before returning.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeData	Pointer to a data area from where the write value will be extracted.
writeSize	Size of write data area, ex. number of bytes to write.
readData	Pointer to a preallocated data area where the function will store the register read value.
readSize	Size of preallocated read data area, modified by the function to reflect the actual length of the read register value. The read register value may be truncated to fit into the allocated area.
index	Data index. Typically -1, but could be used to write/read data at/from a specific position in the register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

See also

registerWriteReadU8, registerWriteReadS8 etc.

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.37 registerWriteReadU8()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU8 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned char writeValue,
            unsigned char * readValue,
            const short index )
```

Writes and Reads an unsigned char (8bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to an unsigned char where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.38 registerWriteReadS8()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS8 (
            const char * portname,
```

```
            const unsigned char devId,
            const unsigned char regId,
            const signed char writeValue,
            signed char * readValue,
            const short index )
```

Writes and Reads a signed char (8bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to a signed char where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.39 registerWriteReadU16()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU16 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned short writeValue,
            unsigned short * readValue,
            const short index )
```

Writes and Reads an unsigned short (16bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to an unsigned short where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.40 registerWriteReadS16()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS16 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed short writeValue,
            signed short * readValue,
            const short index )
```

Writes and Reads a signed short (16bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to a signed short where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.41 registerWriteReadU32()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned long writeValue,
            unsigned long * readValue,
            const short index )
```

Writes and Reads an unsigned long (32bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to an unsigned long where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.42 registerWriteReadS32()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed long writeValue,
            signed long * readValue,
            const short index )
```

Writes and Reads a signed long (32bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to a signed long where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.43 registerWriteReadU64()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadU64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const unsigned long long writeValue,
            unsigned long long * readValue,
            const short index )
```

Writes and Reads an unsigned long long (64bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to an unsigned long long where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.44 registerWriteReadS64()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadS64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const signed long long writeValue,
            signed long long * readValue,
            const short index )
```

Writes and Reads a signed long long (64bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to a signed long long where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.45 registerWriteReadF32()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadF32 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const float writeValue,
            float * readValue,
            const short index )
```

Writes and Reads a float (32bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to a float where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.46 registerWriteReadF64()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadF64 (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const double writeValue,
            double * readValue,
            const short index )
```

Writes and Reads a double (64bit) register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeValue	The register value to write.
readValue	Pointer to a double where the function will store the register read value.
index	Value index. Typically -1, but could be used to write and read a value in a multi value register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.47 registerWriteReadAscii()

```
NKTPDLL_EXPORT RegisterResultTypes registerWriteReadAscii (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const char * writeStr,
            const char writeEOL,
            char * readStr,
            unsigned char * maxLen,
            const short index )
```

Writes and Reads a string register value.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
writeStr	The zero terminated string to write. WriteStr will be limited to 239 characters and the terminating zero, totally 240 bytes.
writeEOL	• 0 Do NOT append End Of Line character (a null character) to the string. • 1 Append End Of Line character to the string.
readStr	Pointer to a preallocated string area where the function will store the register read value.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.
index	Value index. Typically -1, but could be used to write and read a string in a mixed type register. Index is byte counted. Index >= 0 activates a read-modify-write sequence: The complete register content is being read, then the indexed content is modified and finally the complete content is written to the register.

Returns

A status result value tRegisterResultTypes

Note

It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated write followed by a dedicated read.

4.1.5.48 deviceGetType()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetType (
            const char * portname,
            const unsigned char devId,
            unsigned char * devType )
```

Returns the module type for a specific device id (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	Given device id to retrieve device type for (module type).
devType	Pointer to an unsigned char where the function stores the device type.

Returns

A status result value tDeviceResultTypes

Note

Register address 0x61
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.49 deviceGetSysType()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetSysType (
            const char * portname,
            const unsigned char devId,
            unsigned char * sysType )
```

Returns the system type for a specific device id (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	Given device id to retrieve system type for (system type).
sysType	Pointer to an unsigned char where the function stores the system type.

Returns

A status result value tDeviceResultTypes

Note

Register address 0x6B
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.50 deviceGetPartNumberStr()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetPartNumberStr (
            const char * portname,
            const unsigned char devId,
            char * partnumber,
            unsigned char * maxLen )
```

Returns the partnumber for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
partnumber	Pointer to a preallocated string area where the function will store the partnumber.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.

Returns

A status result value RegisterResultTypes

Note

Register address 0x8E **Not all modules have a partnumber register.**
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.51 deviceGetPCBVersion()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetPCBVersion (
            const char * portname,
            const unsigned char devId,
            unsigned char * PCBVersion )
```

Returns the PCB version for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
PCBVersion	Pointer to a preallocated unsigned char where the function will store the PCB version.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x62
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.52 deviceGetStatusBits()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetStatusBits (
            const char * portname,
            const unsigned char devId,
            unsigned long * statusBits )
```

Returns the status bits for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
statusBits	Pointer to a preallocated unsigned long where the function will store the status bits.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x66
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.53 deviceGetErrorCode()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetErrorCode (
            const char * portname,
            const unsigned char devId,
            unsigned short * errorCode )
```

Returns the error code for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
errorCode	Pointer to a preallocated unsigned short where the function will store the error code.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x67
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.54 deviceGetBootloaderVersion()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetBootloaderVersion (
            const char * portname,
            const unsigned char devId,
            unsigned short * version )
```

Returns the bootloader version for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
version	Pointer to a preallocated unsigned short where the function will store the bootloader version.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x6D
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.55 deviceGetBootloaderVersionStr()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetBootloaderVersionStr (
            const char * portname,
            const unsigned char devId,
            char * versionStr,
            unsigned char * maxLen )
```

Returns the bootloader version (string) for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
versionStr	Pointer to a preallocated string area where the function will store the bootloader version.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x6D
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.56 deviceGetFirmwareVersion()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetFirmwareVersion (
            const char * portname,
            const unsigned char devId,
            unsigned short * version )
```

Returns the firmware version for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
version	Pointer to a preallocated unsigned short where the function will store the firmware version.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x64
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.57 deviceGetFirmwareVersionStr()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetFirmwareVersionStr (
            const char * portname,
            const unsigned char devId,
            char * versionStr,
            unsigned char * maxLen )
```

Returns the firmware version (string) for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
versionStr	Pointer to a preallocated string area where the function will store the firmware version.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x64
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.58 deviceGetModuleSerialNumberStr()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetModuleSerialNumberStr (
            const char * portname,
            const unsigned char devId,
            char * serialNumber,
            unsigned char * maxLen )
```

Returns the Module serialnumber (string) for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
serialNumber	Pointer to a preallocated string area where the function will store the serialnumber version.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x65
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.59 deviceGetPCBSerialNumberStr()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetPCBSerialNumberStr (
            const char * portname,
            const unsigned char devId,
            char * serialNumber,
            unsigned char * maxLen )
```

Returns the PCB serialnumber (string) for a given device (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
serialNumber	Pointer to a preallocated string area where the function will store the serialnumber version.
maxLen	Size of preallocated string area, modified by the function to reflect the actual length of the returned string. The returned string may be truncated to fit into the allocated area.

Returns

A status result value tRegisterResultTypes

Note

Register address 0x6E
It is not necessary to open the port, create the device or register before using this function, since it will do a dedicated read.

4.1.5.60 deviceCreate()

```
NKTPDLL_EXPORT DeviceResultTypes deviceCreate (
            const char * portname,
            const unsigned char devId,
            const char waitReady )
```

Creates a device in the internal devicelist. If the openPorts function has been called with the liveMode = 1 the kernel immediatedly starts to monitor the device.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
waitReady	• 0 Don't wait for the device being ready. • 1 Wait up to 2 seconds for the device to complete its analyze cycle (All standard registers being successfully read).

Returns

A status result value tDeviceResultTypes

4.1.5.61 deviceExists()

```
NKTPDLL_EXPORT DeviceResultTypes deviceExists (
            const char * portname,
            const unsigned char devId,
            unsigned char * exists )
```

Checks if a specific device already exists in the internal devicelist.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
exists	Pointer to an unsigned char where the function will store the exists status. • 0 Device does not exists. • 1 Device exists.

Returns

A status result value tDeviceResultTypes

4.1.5.62 deviceRemove()

```
NKTPDLL_EXPORT DeviceResultTypes deviceRemove (
```

```
            const char * portname,
            const unsigned char devId )
```

Remove a specific device from the internal devicelist.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).

Returns

A status result value tDeviceResultTypes

4.1.5.63 deviceRemoveAll()

```
NKTPDLL_EXPORT DeviceResultTypes deviceRemoveAll (
            const char * portname )
```

Remove all devices from the internal devicelist. No confirmation given, the list is simply cleared.

Parameters

portname	Zero terminated string giving the portname (case sensitive).

Returns

A status result value tDeviceResultTypes

4.1.5.64 deviceGetAllTypes()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetAllTypes (
            const char * portname,
            unsigned char * types,
            unsigned char * maxTypes )
```

Returns a list with device types (module types) from the internal devicelist.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
types	Pointer to a preallocated area where the function stores the list of module types. The default list size is 256 bytes long (0-255) where each position indicates module address, containing 0 for no module or the module type for addresses having a module. ex. 00h 61h 62h 63h 64h 65h 00h 00h 00h 00h 00h 00h 00h 00h 00h 60h 00h 00h etc. Indicates module type 61h at address 1, module type 62h at address 2 etc. and module type 60h at address 15
maxTypes	Pointer to an unsigned char giving the maximum number of types to retrieve. The returned list may be truncated to fit into the allocated area.

Returns

A status result value tDeviceResultTypes

4.1.5.65 deviceGetMode()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetMode (
            const char * portname,
            const unsigned char devId,
            unsigned char * devMode )
```

Returns the internal device mode for a specific device id (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	Given device id to retrieve device mode for.
devMode	Pointer to an DeviceModeTypes where the function stores the device mode value tDeviceModeTypes

Returns

A status result value tDeviceResultTypes

Note

Requires the port being already opened with the openPorts function and the device being already created, either automatically or with the deviceCreate function.

4.1.5.66 deviceGetLive()

```
NKTPDLL_EXPORT DeviceResultTypes deviceGetLive (
            const char * portname,
            const unsigned char devId,
            unsigned char * liveMode )
```

Returns the internal device live status for a specific device id (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	Given device id to retrieve liveMode.
liveMode	Pointer to an unsigned char where the function stores the live status. • 0 liveMode off • 1 liveMode on

Returns

A status result value tDeviceResultTypes

Note

Requires the port being already opened with the openPorts function and the device being already created, either automatically or with the deviceCreate function.

4.1.5.67 deviceSetLive()

```
NKTPDLL_EXPORT DeviceResultTypes deviceSetLive (
            const char * portname,
            const unsigned char devId,
            const unsigned char liveMode )
```

Sets the internal device live status for a specific device id (module address).

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	Given device id to set liveMode on.
liveMode	An unsigned char giving the new live status. • 0 liveMode off • 1 liveMode on

Returns

A status result value tDeviceResultTypes

Note

Requires the port being already opened with the openPorts function and the device being already created, either automatically or with the deviceCreate function.

4.1.5.68 registerCreate()

```
NKTPDLL_EXPORT RegisterResultTypes registerCreate (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            const RegisterPriorityTypes priority,
            const RegisterDataTypes dataType )
```

Creates a register in the internal registerlist. If the openPorts function has been called with the liveMode = 1 the kernel immediatedly starts to monitor the register.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
priority	The tRegisterPriorityTypes (monitoring priority).
dataType	The tRegisterDataTypes, not used internally but could be used in a common callback function to determine data type.

Returns

A status result value tRegisterResultTypes

4.1.5.69 registerExists()

```
NKTPDLL_EXPORT RegisterResultTypes registerExists (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId,
            unsigned char * exists )
```

Checks if a specific register already exists in the internal registerlist.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).
exists	Pointer to an unsigned char where the function will store the exists status. • 0 Register does not exists. • 1 Register exists.

Returns

A status result value tRegisterResultTypes

4.1.5.70 registerRemove()

```
NKTPDLL_EXPORT RegisterResultTypes registerRemove (
            const char * portname,
            const unsigned char devId,
            const unsigned char regId )
```

Remove a specific register from the internal registerlist.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regId	The register id (register address).

Returns

A status result value tRegisterResultTypes

4.1.5.71 registerRemoveAll()

```
NKTPDLL_EXPORT RegisterResultTypes registerRemoveAll (
            const char * portname,
            const unsigned char devId )
```

Remove all registers from the internal registerlist. No confirmation given, the list is simply cleared.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).

Returns

A status result value tRegisterResultTypes

4.1.5.72 registerGetAll()

```
NKTPDLL_EXPORT RegisterResultTypes registerGetAll (
            const char * portname,
            const unsigned char devId,
            unsigned char * regs,
            unsigned char * maxRegs )
```

Returns a list with register ids (register addresses) from the internal registerlist.

Parameters

portname	Zero terminated string giving the portname (case sensitive).
devId	The device id (module address).
regs	Pointer to a preallocated area where the function stores the list of register ids (register addresses).
maxRegs	Pointer to an unsigned char giving the maximum number of register ids to retrieve. Modified by the function to reflect the actual number of register ids returned. The returned list may be truncated to fit into the allocated area.

Returns

A status result value tRegisterResultTypes

4.1.5.73 setCallbackPtrPortInfo()

```
NKTPDLL_EXPORT void setCallbackPtrPortInfo (
            PortStatusCallbackFuncPtr callback )
```

Enables/Disables callback for port status changes.

Parameters

callback	The PortStatusCallbackFuncPtr function pointer. Disable callbacks by parsing in a zero value.

4.1.5.74 setCallbackPtrDeviceInfo()

```
NKTPDLL_EXPORT void setCallbackPtrDeviceInfo (
            DeviceStatusCallbackFuncPtr callback )
```

Enables/Disables callback for device status changes.

Parameters

callback	The DeviceStatusCallbackFuncPtr function pointer. Disable callbacks by parsing in a zero value.

4.1.5.75 setCallbackPtrRegisterInfo()

```
NKTPDLL_EXPORT void setCallbackPtrRegisterInfo (
            RegisterStatusCallbackFuncPtr callback )
```

Enables/Disables callback for register status changes.

Parameters

callback	The RegisterStatusCallbackFuncPtr function pointer. Disable callbacks by parsing in a zero value.

4.1.5.76 setLVUserEventPortInfo()

```
NKTPDLL_EXPORT void setLVUserEventPortInfo (
            unsigned long * lvUserEventRef )
```

Enables/Disables labView user events for port status changes. Disable events by parsing in a zero value.

Parameters

lvUserEventRef	A LabView "MagicCookie" to identify userevent type.

4.1.5.77 setLVUserEventDeviceInfo()

```
NKTPDLL_EXPORT void setLVUserEventDeviceInfo (
            unsigned long * lvUserEventRef )
```

Enables/Disables labView user events for device status changes. Disable events by parsing in a zero value.

Parameters

lvUserEventRef	A LabView "MagicCookie" to identify userevent type.

4.1.5.78 setLVUserEventRegisterInfo()

```
NKTPDLL_EXPORT void setLVUserEventRegisterInfo (
            unsigned long * lvUserEventRef )
```

Enables/Disables labView user events for register status changes. Disable events by parsing in a zero value.

Parameters

lvUserEventRef	A LabView "MagicCookie" to identify userevent type.

Index

closePorts
NKTPDLL.h, 45
ClosePortsFuncPtr
NKTPDLL.h, 26
curScanAdr
lvPortStatusStruct, 7

DateTimeType
NKTPDLL.h, 25
Day
tDateTimeStruct, 10
Denominator
tParamSetStruct, 12
devData
lvDeviceStatusStruct, 6
devDataLen
lvDeviceStatusStruct, 6
devId
lvDeviceStatusStruct, 5
lvRegisterStatusStruct, 8
deviceCreate
NKTPDLL.h, 76
DeviceCreateFuncPtr
NKTPDLL.h, 32
deviceExists
NKTPDLL.h, 77
DeviceExistsFuncPtr
NKTPDLL.h, 32
deviceGetAllTypes
NKTPDLL.h, 78
DeviceGetAllTypesFuncPtr
NKTPDLL.h, 33
deviceGetBootloaderVersion
NKTPDLL.h, 73
DeviceGetBootloaderVersionFuncPtr
NKTPDLL.h, 32
deviceGetBootloaderVersionStr
NKTPDLL.h, 74
DeviceGetBootloaderVersionStrFuncPtr
NKTPDLL.h, 32
deviceGetErrorCode
NKTPDLL.h, 73
DeviceGetErrorCodeFuncPtr
NKTPDLL.h, 31
deviceGetFirmwareVersion
NKTPDLL.h, 74
DeviceGetFirmwareVersionFuncPtr
NKTPDLL.h, 32
deviceGetFirmwareVersionStr
NKTPDLL.h, 75
DeviceGetFirmwareVersionStrFuncPtr
NKTPDLL.h, 32
deviceGetLive
NKTPDLL.h, 79
DeviceGetLiveFuncPtr
NKTPDLL.h, 33
deviceGetMode
NKTPDLL.h, 79
DeviceGetModeFuncPtr
NKTPDLL.h, 33
deviceGetModuleSerialNumberStr
NKTPDLL.h, 75
DeviceGetModuleSerialNumberStrFuncPtr
NKTPDLL.h, 32
deviceGetPCBSerialNumberStr
NKTPDLL.h, 76
DeviceGetPCBSerialNumberStrFuncPtr
NKTPDLL.h, 32
deviceGetPCBVersion
NKTPDLL.h, 72
DeviceGetPCBVersionFuncPtr
NKTPDLL.h, 31
deviceGetPartNumberStr
NKTPDLL.h, 71
DeviceGetPartNumberStrFuncPtr
NKTPDLL.h, 31
deviceGetStatusBits
NKTPDLL.h, 72
DeviceGetStatusBitsFuncPtr
NKTPDLL.h, 31
deviceGetSysType
NKTPDLL.h, 71
DeviceGetSysTypeFuncPtr
NKTPDLL.h, 31
deviceGetType
NKTPDLL.h, 70
DeviceGetTypeFuncPtr
NKTPDLL.h, 31
DeviceModeTypes
NKTPDLL.h, 24
deviceRemove
NKTPDLL.h, 77
deviceRemoveAll
NKTPDLL.h, 78
DeviceRemoveAllFuncPtr
NKTPDLL.h, 33
DeviceRemoveFuncPtr
NKTPDLL.h, 32
DeviceResultTypes

NKTPDLL.h, 24
deviceSetLive
NKTPDLL.h, 80
DeviceSetLiveFuncPtr
NKTPDLL.h, 33
DeviceStatusCallbackFuncPtr
NKTPDLL.h, 34
DeviceStatusTypes
NKTPDLL.h, 25

ErrorHandler
tParamSetStruct, 11

FactoryVal
tParamSetStruct, 12
foundType
lvPortStatusStruct, 7

getAllPorts
NKTPDLL.h, 42
GetAllPortsFuncPtr
NKTPDLL.h, 25
getLegacyBusScanning
NKTPDLL.h, 46
GetLegacyBusScanningFuncPtr
NKTPDLL.h, 26
getOpenPorts
NKTPDLL.h, 42
GetOpenPortsFuncPtr
NKTPDLL.h, 25
getPortErrorMsg
NKTPDLL.h, 47
getPortErrorMsgFuncPtr
NKTPDLL.h, 26
getPortStatus
NKTPDLL.h, 46
getPortStatusFuncPtr
NKTPDLL.h, 26

Hour
tDateTimeStruct, 10

LLimit
tParamSetStruct, 12
LabViewDeviceStatusType
NKTPDLL.h, 36
LabViewPortStatusType
NKTPDLL.h, 35
LabViewRegisterStatusType
NKTPDLL.h, 36
lvDeviceStatusStruct, 5
devData, 6
devDataLen, 6
devId, 5
portname, 5
status, 6
lvPortStatusStruct, 6
curScanAdr, 7
foundType, 7
maxScanAdr, 7
portname, 7
status, 7
lvRegisterStatusStruct, 7
devId, 8
portname, 8
regData, 9
regDataLen, 9
regId, 8
regType, 8
status, 8

maxScanAdr
lvPortStatusStruct, 7
Min
tDateTimeStruct, 10
Month
tDateTimeStruct, 10

NKTPDLL.h, 13
closePorts, 45
ClosePortsFuncPtr, 26
DateTimeType, 25
deviceCreate, 76
DeviceCreateFuncPtr, 32
deviceExists, 77
DeviceExistsFuncPtr, 32
deviceGetAllTypes, 78
DeviceGetAllTypesFuncPtr, 33
deviceGetBootloaderVersion, 73
DeviceGetBootloaderVersionFuncPtr, 32
deviceGetBootloaderVersionStr, 74
DeviceGetBootloaderVersionStrFuncPtr, 32
deviceGetErrorCode, 73
DeviceGetErrorCodeFuncPtr, 31
deviceGetFirmwareVersion, 74
DeviceGetFirmwareVersionFuncPtr, 32
deviceGetFirmwareVersionStr, 75
DeviceGetFirmwareVersionStrFuncPtr, 32
deviceGetLive, 79
DeviceGetLiveFuncPtr, 33
deviceGetMode, 79
DeviceGetModeFuncPtr, 33
deviceGetModuleSerialNumberStr, 75
DeviceGetModuleSerialNumberStrFuncPtr, 32
deviceGetPCBSerialNumberStr, 76
DeviceGetPCBSerialNumberStrFuncPtr, 32
deviceGetPCBVersion, 72
DeviceGetPCBVersionFuncPtr, 31
deviceGetPartNumberStr, 71
DeviceGetPartNumberStrFuncPtr, 31
deviceGetStatusBits, 72
DeviceGetStatusBitsFuncPtr, 31
deviceGetSysType, 71
DeviceGetSysTypeFuncPtr, 31
deviceGetType, 70
DeviceGetTypeFuncPtr, 31
DeviceModeTypes, 24
deviceRemove, 77

deviceRemoveAll, 78
DeviceRemoveAllFuncPtr, 33
DeviceRemoveFuncPtr, 32
DeviceResultTypes, 24
deviceSetLive, 80
DeviceSetLiveFuncPtr, 33
DeviceStatusCallbackFuncPtr, 34
DeviceStatusTypes, 25
getAllPorts, 42
GetAllPortsFuncPtr, 25
getLegacyBusScanning, 46
GetLegacyBusScanningFuncPtr, 26
getOpenPorts, 42
GetOpenPortsFuncPtr, 25
getPortErrorMsg, 47
getPortErrorMsgFuncPtr, 26
getPortStatus, 46
getPortStatusFuncPtr, 26
LabViewDeviceStatusType, 36
LabViewPortStatusType, 35
LabViewRegisterStatusType, 36
NKTPDLL_EXPORT, 24
openPorts, 44
OpenPortsFuncPtr, 26
P2PPortResultTypes, 24
ParamSetUnitTypes, 25
ParameterSetType, 25
pointToPointPortAdd, 43
PointToPointPortAddFuncPtr, 25
pointToPointPortDel, 44
PointToPointPortDelFuncPtr, 26
pointToPointPortGet, 43
PointToPointPortGetFuncPtr, 26
PortResultTypes, 24
PortStatusCallbackFuncPtr, 34
PortStatusTypes, 24
registerCreate, 80
RegisterCreateFuncPtr, 33
RegisterDataTypes, 24
registerExists, 81
RegisterExistsFuncPtr, 33
registerGetAll, 82
RegisterGetAllFuncPtr, 34
RegisterPriorityTypes, 24
registerRead, 47
registerReadAscii, 54
RegisterReadAsciiFuncPtr, 28
registerReadF32, 53
RegisterReadF32FuncPtr, 27
registerReadF64, 53
RegisterReadF64FuncPtr, 28
RegisterReadFuncPtr, 26
registerReadS16, 50
RegisterReadS16FuncPtr, 27
registerReadS32, 51
RegisterReadS32FuncPtr, 27
registerReadS64, 52
RegisterReadS64FuncPtr, 27
registerReadS8, 48
RegisterReadS8FuncPtr, 27
registerReadU16, 49
RegisterReadU16FuncPtr, 27
registerReadU32, 50
RegisterReadU32FuncPtr, 27
registerReadU64, 51
RegisterReadU64FuncPtr, 27
registerReadU8, 48
RegisterReadU8FuncPtr, 27
registerRemove, 81
registerRemoveAll, 82
RegisterRemoveAllFuncPtr, 33
RegisterRemoveFuncPtr, 33
RegisterResultTypes, 24
RegisterStatusCallbackFuncPtr, 35
RegisterStatusTypes, 25
registerWrite, 54
registerWriteAscii, 61
RegisterWriteAsciiFuncPtr, 29
registerWriteF32, 60
RegisterWriteF32FuncPtr, 29
registerWriteF64, 61
RegisterWriteF64FuncPtr, 29
RegisterWriteFuncPtr, 28
registerWriteRead, 62
registerWriteReadAscii, 69
RegisterWriteReadAsciiFuncPtr, 31
registerWriteReadF32, 68
RegisterWriteReadF32FuncPtr, 30
registerWriteReadF64, 69
RegisterWriteReadF64FuncPtr, 31
RegisterWriteReadFuncPtr, 29
registerWriteReadS16, 65
RegisterWriteReadS16FuncPtr, 30
registerWriteReadS32, 66
RegisterWriteReadS32FuncPtr, 30
registerWriteReadS64, 67
RegisterWriteReadS64FuncPtr, 30
registerWriteReadS8, 63
RegisterWriteReadS8FuncPtr, 30
registerWriteReadU16, 64
RegisterWriteReadU16FuncPtr, 30
registerWriteReadU32, 65
RegisterWriteReadU32FuncPtr, 30
registerWriteReadU64, 67
RegisterWriteReadU64FuncPtr, 30
registerWriteReadU8, 63
RegisterWriteReadU8FuncPtr, 29
registerWriteS16, 57
RegisterWriteS16FuncPtr, 28
registerWriteS32, 58
RegisterWriteS32FuncPtr, 29
registerWriteS64, 59
RegisterWriteS64FuncPtr, 29
registerWriteS8, 56
RegisterWriteS8FuncPtr, 28
registerWriteU16, 56

RegisterWriteU16FuncPtr, 28
registerWriteU32, 58
RegisterWriteU32FuncPtr, 28
registerWriteU64, 59
RegisterWriteU64FuncPtr, 29
registerWriteU8, 55
RegisterWriteU8FuncPtr, 28
setCallbackPtrDeviceInfo, 83
SetCallbackPtrDeviceInfoFuncPtr, 35
setCallbackPtrPortInfo, 83
SetCallbackPtrPortInfoFuncPtr, 34
setCallbackPtrRegisterInfo, 83
SetCallbackPtrRegisterInfoFuncPtr, 35
setLVUserEventDeviceInfo, 84
SetLVUserEventDeviceInfoFuncPtr, 36
setLVUserEventPortInfo, 83
SetLVUserEventPortInfoFuncPtr, 35
setLVUserEventRegisterInfo, 84
SetLVUserEventRegisterInfoFuncPtr, 36
setLegacyBusScanning, 46
SetLegacyBusScanningFuncPtr, 26
tDeviceModeTypes, 38
tDeviceResultTypes, 38
tDeviceStatusTypes, 41
tP2PPortResultTypes, 36
tParamSetUnitTypes, 41
tPortResultTypes, 36
tPortStatusTypes, 40
tRegisterDataTypes, 39
tRegisterPriorityTypes, 40
tRegisterResultTypes, 38
tRegisterStatusTypes, 41
NKTPDLL_EXPORT
NKTPDLL.h, 24
Numerator
tParamSetStruct, 12

Offset
tParamSetStruct, 12
openPorts
NKTPDLL.h, 44
OpenPortsFuncPtr
NKTPDLL.h, 26

P2PPortResultTypes
NKTPDLL.h, 24
ParamSetUnitTypes
NKTPDLL.h, 25
ParameterSetType
NKTPDLL.h, 25
pointToPointPortAdd
NKTPDLL.h, 43
PointToPointPortAddFuncPtr
NKTPDLL.h, 25
pointToPointPortDel
NKTPDLL.h, 44
PointToPointPortDelFuncPtr
NKTPDLL.h, 26
pointToPointPortGet
NKTPDLL.h, 43
PointToPointPortGetFuncPtr
NKTPDLL.h, 26
PortResultTypes
NKTPDLL.h, 24
PortStatusCallbackFuncPtr
NKTPDLL.h, 34
PortStatusTypes
NKTPDLL.h, 24
portname
lvDeviceStatusStruct, 5
lvPortStatusStruct, 7
lvRegisterStatusStruct, 8

regData
lvRegisterStatusStruct, 9
regDataLen
lvRegisterStatusStruct, 9
regId
lvRegisterStatusStruct, 8
regType
lvRegisterStatusStruct, 8
registerCreate
NKTPDLL.h, 80
RegisterCreateFuncPtr
NKTPDLL.h, 33
RegisterDataTypes
NKTPDLL.h, 24
registerExists
NKTPDLL.h, 81
RegisterExistsFuncPtr
NKTPDLL.h, 33
registerGetAll
NKTPDLL.h, 82
RegisterGetAllFuncPtr
NKTPDLL.h, 34
RegisterPriorityTypes
NKTPDLL.h, 24
registerRead
NKTPDLL.h, 47
registerReadAscii
NKTPDLL.h, 54
RegisterReadAsciiFuncPtr
NKTPDLL.h, 28
registerReadF32
NKTPDLL.h, 53
RegisterReadF32FuncPtr
NKTPDLL.h, 27
registerReadF64
NKTPDLL.h, 53
RegisterReadF64FuncPtr
NKTPDLL.h, 28
RegisterReadFuncPtr
NKTPDLL.h, 26
registerReadS16
NKTPDLL.h, 50
RegisterReadS16FuncPtr
NKTPDLL.h, 27
registerReadS32

NKTPDLL.h, 51
RegisterReadS32FuncPtr
NKTPDLL.h, 27
registerReadS64
NKTPDLL.h, 52
RegisterReadS64FuncPtr
NKTPDLL.h, 27
registerReadS8
NKTPDLL.h, 48
RegisterReadS8FuncPtr
NKTPDLL.h, 27
registerReadU16
NKTPDLL.h, 49
RegisterReadU16FuncPtr
NKTPDLL.h, 27
registerReadU32
NKTPDLL.h, 50
RegisterReadU32FuncPtr
NKTPDLL.h, 27
registerReadU64
NKTPDLL.h, 51
RegisterReadU64FuncPtr
NKTPDLL.h, 27
registerReadU8
NKTPDLL.h, 48
RegisterReadU8FuncPtr
NKTPDLL.h, 27
registerRemove
NKTPDLL.h, 81
registerRemoveAll
NKTPDLL.h, 82
RegisterRemoveAllFuncPtr
NKTPDLL.h, 33
RegisterRemoveFuncPtr
NKTPDLL.h, 33
RegisterResultTypes
NKTPDLL.h, 24
RegisterStatusCallbackFuncPtr
NKTPDLL.h, 35
RegisterStatusTypes
NKTPDLL.h, 25
registerWrite
NKTPDLL.h, 54
registerWriteAscii
NKTPDLL.h, 61
RegisterWriteAsciiFuncPtr
NKTPDLL.h, 29
registerWriteF32
NKTPDLL.h, 60
RegisterWriteF32FuncPtr
NKTPDLL.h, 29
registerWriteF64
NKTPDLL.h, 61
RegisterWriteF64FuncPtr
NKTPDLL.h, 29
RegisterWriteFuncPtr
NKTPDLL.h, 28
registerWriteRead
NKTPDLL.h, 62
registerWriteReadAscii
NKTPDLL.h, 69
RegisterWriteReadAsciiFuncPtr
NKTPDLL.h, 31
registerWriteReadF32
NKTPDLL.h, 68
RegisterWriteReadF32FuncPtr
NKTPDLL.h, 30
registerWriteReadF64
NKTPDLL.h, 69
RegisterWriteReadF64FuncPtr
NKTPDLL.h, 31
RegisterWriteReadFuncPtr
NKTPDLL.h, 29
registerWriteReadS16
NKTPDLL.h, 65
RegisterWriteReadS16FuncPtr
NKTPDLL.h, 30
registerWriteReadS32
NKTPDLL.h, 66
RegisterWriteReadS32FuncPtr
NKTPDLL.h, 30
registerWriteReadS64
NKTPDLL.h, 67
RegisterWriteReadS64FuncPtr
NKTPDLL.h, 30
registerWriteReadS8
NKTPDLL.h, 63
RegisterWriteReadS8FuncPtr
NKTPDLL.h, 30
registerWriteReadU16
NKTPDLL.h, 64
RegisterWriteReadU16FuncPtr
NKTPDLL.h, 30
registerWriteReadU32
NKTPDLL.h, 65
RegisterWriteReadU32FuncPtr
NKTPDLL.h, 30
registerWriteReadU64
NKTPDLL.h, 67
RegisterWriteReadU64FuncPtr
NKTPDLL.h, 30
registerWriteReadU8
NKTPDLL.h, 63
RegisterWriteReadU8FuncPtr
NKTPDLL.h, 29
registerWriteS16
NKTPDLL.h, 57
RegisterWriteS16FuncPtr
NKTPDLL.h, 28
registerWriteS32
NKTPDLL.h, 58
RegisterWriteS32FuncPtr
NKTPDLL.h, 29
registerWriteS64
NKTPDLL.h, 59
RegisterWriteS64FuncPtr

NKTPDLL.h, 29
registerWriteS8
NKTPDLL.h, 56
RegisterWriteS8FuncPtr
NKTPDLL.h, 28
registerWriteU16
NKTPDLL.h, 56
RegisterWriteU16FuncPtr
NKTPDLL.h, 28
registerWriteU32
NKTPDLL.h, 58
RegisterWriteU32FuncPtr
NKTPDLL.h, 28
registerWriteU64
NKTPDLL.h, 59
RegisterWriteU64FuncPtr
NKTPDLL.h, 29
registerWriteU8
NKTPDLL.h, 55
RegisterWriteU8FuncPtr
NKTPDLL.h, 28

Sec
tDateTimeStruct, 10
setCallbackPtrDeviceInfo
NKTPDLL.h, 83
SetCallbackPtrDeviceInfoFuncPtr
NKTPDLL.h, 35
setCallbackPtrPortInfo
NKTPDLL.h, 83
SetCallbackPtrPortInfoFuncPtr
NKTPDLL.h, 34
setCallbackPtrRegisterInfo
NKTPDLL.h, 83
SetCallbackPtrRegisterInfoFuncPtr
NKTPDLL.h, 35
setLVUserEventDeviceInfo
NKTPDLL.h, 84
SetLVUserEventDeviceInfoFuncPtr
NKTPDLL.h, 36
setLVUserEventPortInfo
NKTPDLL.h, 83
SetLVUserEventPortInfoFuncPtr
NKTPDLL.h, 35
setLVUserEventRegisterInfo
NKTPDLL.h, 84
SetLVUserEventRegisterInfoFuncPtr
NKTPDLL.h, 36
setLegacyBusScanning
NKTPDLL.h, 46
SetLegacyBusScanningFuncPtr
NKTPDLL.h, 26
StartVal
tParamSetStruct, 11
status
lvDeviceStatusStruct, 6
lvPortStatusStruct, 7
lvRegisterStatusStruct, 8
tDateTimeStruct, 9
Day, 10
Hour, 10
Min, 10
Month, 10
Sec, 10
Year, 10
tDeviceModeTypes
NKTPDLL.h, 38
tDeviceResultTypes
NKTPDLL.h, 38
tDeviceStatusTypes
NKTPDLL.h, 41
tP2PPortResultTypes
NKTPDLL.h, 36
tParamSetStruct, 10
Denominator, 12
ErrorHandler, 11
FactoryVal, 12
LLimit, 12
Numerator, 12
Offset, 12
StartVal, 11
ULimit, 12
Unit, 11
tParamSetUnitTypes
NKTPDLL.h, 41
tPortResultTypes
NKTPDLL.h, 36
tPortStatusTypes
NKTPDLL.h, 40
tRegisterDataTypes
NKTPDLL.h, 39
tRegisterPriorityTypes
NKTPDLL.h, 40
tRegisterResultTypes
NKTPDLL.h, 38
tRegisterStatusTypes
NKTPDLL.h, 41

ULimit
tParamSetStruct, 12
Unit
tParamSetStruct, 11

Year
tDateTimeStruct, 10