In this assignment, you will implement a simple matrix-matrix multiplication kernel. The kernel takes a matrix `A` of size `M×K` and a matrix `B` of size `K×N`, and produces a matrix `C`. Do not perform any memory optimizations. You will do this in the next assignment.

Instructions

1. Place the files provided with this assignment in a single directory. The files are:
   - `main.cu`: contains setup and sequential code
   - `kernel.cu`: where you will implement your code (you should only modify this file)
   - `common.h`: for shared declarations across `main.cu` and `kernel.cu`
   - `timer.h`: to assist with timing
   - `Makefile`: used for compilation

2. Edit `kernel.cu` where TODO is indicated to implement the following:
   - Allocate device memory
   - Copy data from the host to the device
   - Configure and invoke the CUDA kernel
   - Copy the results from the device to the host
   - Free device memory
   - Perform the computation in the kernel

3. Compile your code by running: `make`

4. Test your code by running: `./mm`
   - If you are using the HPC cluster, do not forget to use the submission system. Do not run on the head node!
   - For testing on different matrix sizes, you can provide your own values for matrix dimensions as follows: `./mm <M> <N> <K>` (example: `./mm 256 512 128`)

Submission

Submit your modified `kernel.cu` file via Moodle by the due date. Do not submit any other files or compressed folders.