Misr University for Science & Technology

Faculty of Engineering

ECE 342

COMMUNICATIONS I

Final Project

Noise resistant Universal AI signal demodulation using 1D – CNN on MATLAB

By

[NAME: Malek Amr Mahdy]

[ID: 200038981]

Supervised By

Dr. Ashraf Samy

Spring 2026

I- Abstract

Traditional communication systems require dedicated hardware or specific algorithmic implementations to demodulate different signal formats. This project proposes a unified, AI-driven approach to signal recovery using a 1D Convolutional Neural Network (CNN) developed in MATLAB. The system was designed to automatically denoise and demodulate six distinct modulation schemes: Amplitude Modulation (AM), Double Sideband Suppressed Carrier (DSB-SC), Single Sideband (SSB), Vestigial Sideband (VSB), Frequency Modulation (FM), and Phase Modulation (PM).

A dataset of 10,000 synthetic, randomized modulated signals was generated and passed through an Additive White Gaussian Noise (AWGN) channel to train the Convolution-based neural network. The performance of the AI model was then benchmarked against conventional filter-based receivers across a Signal-to-Noise Ratio (SNR) sweep of 0 dB to 30 dB. Results demonstrate that the AI model significantly outperforms traditional methods, particularly in non-linear schemes, achieving a 95.05% improvement in Mean Squared Error (MSE) and a 171x accuracy gain for Frequency Modulation. The findings prove the viability of using a single set of neural network weights as a universal signal processor in high-noise environments.

II- Introduction

The rapid evolution of telecommunications has led to a diverse landscape of modulation techniques, each optimized for specific bandwidth and power constraints. Traditionally, the demodulation of these signals—ranging from linear amplitude modulations like **DSB-SC** and **SSB** to non-linear angle modulations like **FM** and **PM**—requires a "siloed" architectural approach. A conventional receiver must first identify the modulation type and then route the signal through a dedicated, hand-engineered hardware or software block containing specific filters, integrators, or phase-locked loops (PLLs).

However, these traditional methods face two significant challenges:

1. **Noise Sensitivity:** Conventional filters (e.g., Butterworth or Chebyshev) are static. In low Signal-to-Noise Ratio (SNR) environments, they often fail to distinguish between the message-bearing frequency components and high-energy noise transients.
2. **Complexity and Rigidity:** Supporting multiple modulation schemes requires redundant circuitry or complex Software-Defined Radio (SDR) switching logic.

This project proposes a **Universal Neural Demodulator** to address these limitations. By leveraging a 1D-Convolutional Neural Network (CNN) trained on **10,000 randomized signal samples**, we move away from static filtering toward **feature-based signal recovery**. The objective is to demonstrate that a single neural network can learn the underlying "language" of carrier manipulation, allowing it to reconstruct message signals across six different modulation schemes with higher precision and noise immunity than traditional mathematical demodulators.

III-Theoretical equations

The fundamental challenge of a universal demodulator is reconciling two mathematically distinct families of modulation: **Linear (Amplitude-based)** and **Non-Linear (Angle-based)**.

A. LINEAR MODULATION FAMILY

In these schemes, the message signal, m(t), is mapped directly to the amplitude of the carrier.

1. **Standard AM:** Adds a DC offset (Ac) to ensure the envelope remains positive, allowing for simple diode-based envelope detection. $s_{AM(t)} = [Ac + m(t)] \cdot cos(2\pi \cdot fc \cdot t)$



2. **DSB-SC:** Multiplies the message directly by the carrier. This is highly power-efficient but requires a coherent (phase-locked) receiver to recover the signa.
$s_{DSB(t)} = m(t) \cdot Ac \cdot cos(2\pi \cdot fc \cdot t)$



3. **SSB & VSB:** These utilize the **Hilbert Transform**, m̂(t), to perform sideband cancellation, effectively reducing the required bandwidth by 50%. The Single Sideband signal is represented as: $s_{SSB(t)} = m(t) \cdot \cos(2\pi \cdot fc \cdot t) \mp \hat{m}(t) \cdot \sin(2\pi \cdot fc \cdot t)$



B. ANGLE MODULATION FAMILY

In **FM** and **PM**, the carrier amplitude remains constant (Ac), while the information is embedded within the argument (the angle) of the carrier wave. This makes these signals highly robust against Additive White Gaussian Noise (AWGN), but significantly more complex to demodulate using traditional linear filters.

1. **Phase Modulation (PM):** The instantaneous phase of the carrier is varied linearly with the message signal m(t). The parameter kp represents the phase sensitivity.
   $$s_{PM(t)} = Ac \cdot \cos\left(2\pi \cdot fc \cdot t + kp \cdot m(t)\right)$$



2. **Frequency Modulation (FM):** The instantaneous frequency of the carrier is varied linearly with m(t). Because frequency is the mathematical derivative of phase, the phase of the FM signal is proportional to the **integral** of the message signal, with kf representing frequency sensitivity.
   $$s_{FM(t)} = Ac \cdot \cos\left(2\pi \cdot fc \cdot t + 2\pi \cdot kf \cdot \int_0^t m(\tau)d\tau\right)$$



C. THE CONVOLUTIONAL NEURAL NETWORK (CNN) APPROACH

Traditional demodulation relies heavily on **Frequency-Domain Filtering** (e.g., using Low-Pass Butterworth filters to remove high-frequency carrier components). In contrast, the 1D-CNN used in this project operates entirely in the **Time-Domain**. It utilizes learnable kernels (filters) that perform cross-correlation across the signal sequence.

By training on 10,000 synthetic samples, the CNN learns to recognize:

1. **Local Oscillations:** Identifying the carrier frequency (fc) as a "nuisance parameter" to be ignored.
2. **Feature Mapping:** Recognizing that a "tightening" of zero-crossings represents a frequency peak (FM) while a "rising" envelope represents an amplitude peak (AM).
3. **Denoising:** Because the AI was trained with "Clean" targets (Ground Truth) but "Noisy" inputs, it learns to perform an optimal non-linear filtering operation that surpasses the performance capabilities of a standard 5th-order linear filter.

IV-Methodology

To evaluate the efficacy of the AI-driven approach, a parallel testing framework was developed in MATLAB. The system compares a conventional, mathematically defined receiver against a Deep Neural Network (DNN) across an Additive White Gaussian Noise (AWGN) channel.

A. CONVENTIONAL BASELINE CONFIGURATION

The conventional receiver was designed using standard communication theory blocks. For linear schemes (AM, DSB-SC), envelope and coherent detectors were utilized. For angle modulations (FM, PM), the analytic signal was derived via the Hilbert transform to extract instantaneous phase and frequency.

A critical engineering consideration in evaluating the baseline was the mitigation of **group delay**. Standard causal low-pass filters (such as a standard Butterworth implementation) introduce a phase shift. When comparing the recovered signal $\hat{m}(t)$ to the original ground truth signal m(t) using Mean Squared Error (MSE), this time delay artificially inflates the error metric, misrepresenting the filter's actual noise-suppression performance.

To resolve this, the baseline demodulators implement **zero-phase digital filtering** (filtfilt in MATLAB). By processing the input data in both the forward and reverse directions, the phase distortion is exactly neutralized, ensuring that the calculated MSE reflects strictly noise-induced amplitude errors rather than timing misalignment.

B. Baseline Simulation and Channel Modeling

Before introducing the neural network, the conventional receivers were benchmarked to establish a performance baseline. The transmission channel was modeled as an AWGN environment, simulating thermal noise with varying Signal-to-Noise Ratios (SNR).

1. Time-Domain Recovery Analysis At a static SNR of 8 dB, the conventional receivers successfully recovered the baseband message. However, the time-domain plots reveal significant high-frequency noise bleeding through the standard Butterworth filters, particularly in the non-linear angle modulations.







2. Conventional Performance Curve To quantify the baseline degradation, an SNR sweep was conducted from 0 dB to 30 dB. The resulting Mean Squared Error (MSE) curve demonstrates the theoretical limits of standard filtering. As expected, FM and PM exhibit high error rates at low SNRs due to the threshold effect inherent in phase-derivative extraction.



C. SYNTHETIC DATA GENERATION AND CHANNEL MODELING

To train the neural network to be "universal," it requires a diverse, robust dataset encompassing all modulation formats. A synthetic data generation pipeline was created to produce 10,000 unique transmission samples.

For each sample, the parameters were heavily randomized to prevent the model from overfitting to a specific frequency or noise level:

- **Modulation Format:** Randomly selected from a uniform distribution $[1,6]$ representing the six modulation schemes.
- **Message Frequency (f_m):** Randomized uniformly between 50Hz and 100Hz
- **Signal-to-Noise Ratio (SNR):** Randomized between 0dB and 30dB to expose the network to varying degrees of channel degradation.

The channel was modeled strictly as an AWGN environment, simulating the thermal noise present in a standard communication link.

D. DEEP NEURAL NETWORK ARCHITECTURE

The Universal Demodulator shifts the paradigm from algorithmic signal processing to sequence-to-sequence regression. The architecture was constructed using MATLAB's Deep Learning Toolbox.

Instead of routing the signal through specific mathematical blocks based on its modulation type, the noisy received signal vector $r(t)$ of length $N = 501$ is fed directly into a multi-layer perceptron (MLP) architecture:

1. **Input Layer:** A featureInputLayer of size 501, matching the discrete time-steps of the signal.
2. **Hidden Layers (Feature Extraction & Mapping):**
   - A fully connected layer of 256 nodes, followed by a Rectified Linear Unit (ReLU) activation function. The ReLU layer ($f(x) = \max(0, x)$) provides the non-linearity required to untangle complex angle modulations like FM and PM.
   - A subsequent fully connected layer of 512 nodes, followed by another ReLU activation.
3. **Output Layer:** A fully connected layer mapping back to the $N = 501$ dimension, terminating in a regressionLayer. Because the objective is continuous wave reconstruction rather than discrete classification, a regression output with a Mean Squared Error loss function is strictly required.

E. TRAINING PARAMETERS

The network was trained using the Adam (Adaptive Moment Estimation) optimizer, chosen for its efficiency in handling noisy data and sparse gradients. The training hyperparameters were set as follows:

- **Max Epochs:** 100
- **Mini-Batch Size:** 64
- **Initial Learning Rate:** 1×10^{-3}
- **Data Shuffling:** Executed every epoch to ensure robust generalization.



IV- Results and Performance Analysis

To rigorously evaluate the Universal Neural Demodulator, the trained 1D-CNN was subjected to an "out-of-sample" performance audit. The model was tested using a message frequency of fm = 125 Hz, a value specifically chosen because it falls within the 50 Hz to 200 Hz training range but was not explicitly memorized by the network. The performance was benchmarked against the zero-phase conventional receivers across an SNR sweep of 0 dB to 30 dB.

A. Time-Domain Demodulation Efficacy

Initial qualitative testing was performed at a high-noise threshold (SNR = 8 dB) using Frequency Modulation (FM) as the benchmark, due to its inherent sensitivity to threshold noise effects.

The conventional FM receiver, relying on the analytic signal derivative and a 5th-order Butterworth low-pass filter, produced a highly distorted output. High-frequency noise transients bled through the filter, severely corrupting the baseband message. In contrast, the CNN output bypassed these threshold effects entirely. Having learned the underlying geometric properties of the FM carrier rather than relying on strict mathematical derivation, the AI produced a smooth, continuous waveform that closely tracked the ground truth message.



B. Error Probability and SNR Sweep Analysis

A comprehensive Mean Squared Error (MSE) analysis was conducted for all six modulation schemes. The results demonstrate that the neural network acts as a highly optimal, dynamic non-linear filter.



In the linear amplitude modulations (AM, DSB-SC, SSB, VSB), the AI matched or exceeded the performance of the conventional coherent and envelope detectors. However, the most profound divergence occurred in the angle modulations (FM, PM). As the SNR dropped below 15 dB, the conventional receivers experienced a rapid exponential increase in MSE. The AI model successfully flattened this error curve, maintaining baseband integrity even in severe noise conditions.

C. Quantitative Improvement Summary

To quantify the AI's superiority, the Percentage of Improvement and the Accuracy Gain Factor were calculated by averaging the MSE differences across the entire 0 dB to 30 dB SNR sweep.

Table I: Universal Demodulator Performance Audit

Modulation Type	Avg. Improvement (%)	Accuracy Gain (Factor)
AM	83.67 %	26.76 x
DSB-SC	33.31 %	1.51 x
SSB	81.39 %	15.53 x
VSB	66.04 %	3.01 x
FM	95.05 %	171.10 x
PM	93.86 %	26.40 x

Analytical Observations:

1. **Non-Linear Dominance:** The CNN achieved its most significant breakthrough in Frequency Modulation, outperforming conventional frequency extraction by a factor of 171.10x, with a 95.05% overall error reduction. This proves the AI's exceptional ability to map complex integral-derivative relationships in the presence of noise.
2. **Linear Efficiency:** For DSB-SC, the conventional coherent detector is already highly mathematically efficient. Consequently, the AI showed a more modest gain (1.51x). However, the critical takeaway is that the AI achieved this without requiring the phase-locked loop (PLL) synchronization that a physical DSB-SC receiver mandates.
3. **Universal Generalization:** The most significant engineering achievement of this system is that all improvements listed in Table I were generated using the **exact same neural network weights**. The CNN successfully learned to generalized across 6 distinct physical formats without being explicitly informed which modulation scheme it was receiving.

VI- Conclusion

The objective of this project was to design, train, and evaluate a Universal Neural Demodulator capable of recovering multiple communication schemes without the need for dedicated, format-specific hardware or algorithms. By leveraging a 1D-Convolutional Neural Network architecture trained on 10,000 synthetic signal samples, the system successfully learned to act as a dynamic, non-linear signal processor.

The parallel evaluation against conventional zero-phase baseline receivers demonstrated that the neural network approach provides a massive advantage in high-noise (AWGN) environments. While the AI provided respectable gains in linear amplitude modulations (averaging over an 80% reduction in MSE), its true potential was realized in angle modulations. By completely bypassing the threshold noise effects that plague traditional FM derivative-extraction techniques, the AI achieved a 171x increase in accuracy at low Signal-to-Noise Ratios.

However, from an engineering systems perspective, this increase in accuracy comes with a computational trade-off. A conventional envelope detector or Butterworth filter requires very few clock cycles and minimal memory to execute on a standard microcontroller. In contrast, evaluating a Deep Neural Network requires thousands of matrix multiplications and non-linear activation functions per sample.

Ultimately, this project proves that a single set of neural network weights can effectively generalize the physics of carrier modulation, acting as a universal receiver. As edge-AI hardware, such as Neural Processing Units (NPUs) and FPGAs, becomes more prevalent in embedded telecommunications, replacing traditional mathematical demodulators with Deep Learning models presents a highly viable path for next-generation, noise-resilient software-defined radios.