Alliance Error Messages

Page Information

Last updated: 09.01.2016

Table of Contents

Chapter 1: Monitoring for Errors in FTP Sessions and Retrieving Responses

Alliance FTP command interface

Alliance provides approximately 60 FTP commands to perform all aspects of an FTP session in your CL applications. You can open a session, set logging levels, sign on with a user ID and password, put and get files, and do all of the other FTP operations that you might want to do. Each Alliance FTP command can be monitored for errors, and provides detailed feedback in return variables.

See the Alliance API Reference guide and sample applications in QCLSRC for more information about the Alliance FTP commands.

Monitoring for failures with `MONMSG`

For example, the command `FTPPASS` sends a password to an FTP server during the logon phase of an FTP session. If an error occurs during the session you can monitor for it with the `MONMSG` command like this:

```
FTPPASS     PASS(&PASS) APIRTN(&APIRTN) FTPRTN(&FTPRTN) +
TEXT(&TEXT)

MONMSG      MSGID(FTP0000) EXEC(DO)
  /* Error handling goes here */
ENDDO
```

A failure in the execution of the command will generate an exception message with a message ID in the range of FTP0001 to FTP0200. Once you trap the error condition you can use any of the Alliance notification commands or APIs to send error messages. There is more on this in the following sections.

Monitoring for FTP return code errors

All of the Alliance FTP commands support a return code with the FTP server response. When you retrieve a file to a remote FTP server it usually responds with a 226 success code. This code is available via the FTP return code variable. Your application could implement it like this:

```
DCL         VAR(&APIRTN) TYPE(*CHAR) LEN(4)
DCL         VAR(&FTPRTN) TYPE(*CHAR) LEN(4)
DCL         VAR(&TEXT) TYPE(*CHAR) LEN(9999)

FTPGET      RMTFILE('Order.csv') +
             LCLFILE('MYLIB/ORDER') OPTION(*YES) +
          APIRTN(&APIRTN) FTPRTN(&FTPRTN) TEXT(&TEXT)

MONMSG      MSGID(FTP0000) EXEC(DO)
    /* Error handling goes here */
ENDDO

IF (&FTPRTN *NE '0226') THEN(DO)
   /* Houston, we have a problem */
ENDDO
```

Note that the FTP response code can be very helpful. For example, you can use the **FTPMKDIR** command to create a directory on a remote FTP server. But you may want to ignore the error if the directory already exists. By examining the FTP response code you can know if the directory already exists, or if the directory was created.

Retrieving responses from an FTP server

Some of the Alliance FTP commands return responses from the remote FTP server. For example, the FTPLS command makes a list of files on the remote FTP server. In addition to returning the FTP return code the command also returns the list of files in a variable. The code might look like this:

```
DCL         VAR(&LIST) TYPE(*CHAR) LEN(9999)
DCL         VAR(&LENGTH) TYPE(*CHAR) LEN(5)
DCL         VAR(&APIRTN) TYPE(*CHAR) LEN(4)
DCL         VAR(&FTPRTN) TYPE(*CHAR) LEN(4)
DCL         VAR(&TEXT) TYPE(*CHAR) LEN(9999)

CHGVAR      VAR(&LIST) VALUE(' ')
CHGVAR      VAR(&LENGTH) VALUE('09999')

FTPLS       FILE('Ord*') LIST(&LIST) LISTLEN(&LENGTH) +
         APIRTN(&APIRTN) FTPRTN(&FTPRTN) TEXT(&TEXT)

IF (&FTPRTN *EQ '0200') THEN(DO)
   /* Now we have a list of files in variable &LIST */
ENDDO
```

Note that it is a bit easier to parse character fields in ILE CL, but the list is always returned in any version of CL that you use.

Chapter 2: Alliance Bindable Service Program

Alliance provides a service program named **FTPCLN** that you can bind to your ILE RPG and Cobol programs. It implements a complete set of procedures for FTP operations, including procedures for SSL FTP sessions. You can turn any of your applications into a complete FTP client. All of the Alliance FTP procedures return the response codes from the remote FTP server, the response text from the server, and any data that you would normally like to receive. Since every Alliance FTP procedure returns the success or failure of the session you can dynamically manipulate the session, or terminate it if needed.

See the Alliance API Reference guide and sample applications in **QRPGLESRC** for more information about the **FTPCLN** service program and procedures.

Monitoring for failures with the Alliance service program **FTPCLN**

When you bind the service program **FTPCLN** to your ILE application you can receive the responses for every FTP operation. Here is an extract from one of the sample ILE RPG programs:

```
Eval       FileName = 'Test01.csv' + NullChar
Eval       LocalName = '/tmp/Test01.csv' + NullChar
Eval       Replace = 1
Eval       FTPCode = 0
Eval       ReplyCode = 0
Eval       ReplyText = NullChar
Eval       ReplyLength = %size(ReplyText)

CallP      FTMGet          (FileName :
                           LocalName :
                           Replace :
                           FTPCode :
                           ReplyText :
                           ReplyLength :
                           ReplyCode)

ReplyCode      Ifne        0
* Error handling goes here . . .
               Eval        *inlr = *on
               Return
               Endif

FTPCode        Ifne        '0226'
* Error handling goes here . . .
               Eval        *inlr = *on
               Return
               Endif
```

Retrieving FTP response codes from an FTP server

All of the Alliance FTP procedures allow you to receive the actual FTP server response code and response text. Your application can take the appropriate action based on the FTP response code. While there are maximum sizes of the response text variables in CL, you do not have these limitations in the ILE procedure interface.

Retrieving FTP response text from an FTP server

Some of the Alliance FTP procedures return responses from the remote FTP server. For example, the FTMLs procedure makes a list of files on the remote FTP server. In addition to returning the FTP return code the procedure also returns the list of files in a variable. Your ILE RPG or Cobol application can then process the list of files directly in your program. For example, you can selectively retrieve files based on the name or other file information.

Chapter 3: Alliance Callable APIs

For simpler FTP tasks you might want to consider using the Alliance callable API programs. These programs allow you to make a simple call and return a single success code. The callable API program **`FTMEXECI`** is often used when you need to be creative with the target file name. The local file name might be an IBM i database file name or IFS file name, and the

remote file name can be formatted any way you want. (Of course, you can accomplish the same thing with the Alliance FTP commands and service program procedures). Here is an example:

```
DCL         VAR(&DEFINITION) TYPE(*CHAR) LEN(10)
DCL         VAR(&LOCAL     ) TYPE(*CHAR) LEN(64)
DCL         VAR(&REMOTE    ) TYPE(*CHAR) LEN(64)
DCL         VAR(&TEXT      ) TYPE(*CHAR) LEN(80)
DCL         VAR(&RETURN    ) TYPE(*CHAR) LEN(2)

CHGVAR      VAR(&DEFINITION) VALUE('BOFA')
CHGVAR      VAR(&LOCAL) VALUE('MYLIB/POSPAY')
CHGVAR      VAR(&REMOTE) VALUE('POSTIVEPAY' *TCAT &DATE)

CALL        PGM(FTMEXECI) PARM(&DEFINITION &LOCAL +
              &REMOTE &TEXT &RETURN)

IF          COND(&RETURN *NE '00') THEN(DO)
SNDPGMMSG   MSG('ERROR received in FTP session with Bank of America.
             Contact programming support') TOMSGQ(*SYSOPR)
ENDDO
```

There are several Alliance API programs to help you accomplish tasks related to FTP sessions. You can make lists of files on a remote FTP server into a database file, retrieve user IDs and passwords in decrypted format, dynamically change FTP definitions, and a number of other tasks. See the Alliance FTP Manager Reference manual for a list of APIs, and the sample code in **QCLSRC** .

Chapter 4: Notification Command Support

Alliance FTP Manager provides a number of helpful commands and utilities for sending your own error messages. The Alliance **SENDMAIL** command sends an SMTP email directly to your email server. You can also use one of the several callable API programs for sending email. There is full support for email lists, and for sending spool files, database files, IFS files, and save files with these APIs. Alliance contains a complete set of SMTP and POP email clients for managing email on the IBM i.

If your data center implements a monitoring application such as HP OpenView, Tivoli, or similar application, you can use the Alliance SNMP commands to send trap messages to the monitor. Alliance will do this automatically for you if you use one of the automation facilities. But you can also do this directly from your applications using one of the Alliance SNMP commands. See the Alliance FTP Manager reference manual for more information.

Chapter 5: Messages

GID	TEXT
AES1000	Product license error.
AES1001	Invalid ciphertext length. Length must be a multiple of 16.
AES1002	The validation of the HMAC failed.
AES1003	Invalid license or license expired.
AES1004	Invalid length for the plaintext. Length must be a multiple of 16.
AES1005	Invalid license or license expired.
AES1006	Invalid license or license expired.
AES1007	Invalid license or license expired.
AES1008	Invalid license or license expired.
AES1009	Invalid license or license expired.
AES1010	Invalid length for the plaintext. Length must be a multiple of 16.
AES1011	Invalid license or license expired.
AES1012	Invalid length for the plaintext. Length must be a multiple of 16.
AES1013	Invalid license or license expired.
AES1014	Invalid length for the ciphertext. Length must be a multiple of 16.
AES1015	Invalid license or license expired.
AES1016	Invalid length for the plaintext. Length must be a multiple of 16.
AES3000	Key expansion returned zero rounds. Conact software support.
AES3001	Key expansion returned zero rounds. Conact software support.
AES3002	HMAC failed to verify.
AES3003	SHA-1 error, NULL context pointer.

GID	TEXT
AES3004	SHA-1 error, NULL message array pointer.
AES3005	SHA-1 error, context state error (computed).
AES3006	SHA-1 error, context state error (corrupted).
AES3007	SHA-1 error, message is too long.
AES3008	SHA-1 error, NULL context pointer.
AES4000	Invalid license or license expired.
AES4022	Invalid value for the number of bits in CFB mode.
ATC0000	Error on record write.
ATC0045	Message file not found.
ATC1000	Error on call to external program.
ATC1001	Function not supported.
ATC1002	Display repositioned.
ATC1003	Beginning of file reached.
ATC1004	End of file reached.
ATC1005	No records to display.
ATC1006	Press ***Enter*** to process options.
ATC1007	Invalid option entered.
ATC1008	Invalid file I/O request was encountered.
ATC1019	Record deleted.
ATC1020	Record NOT deleted.
ATC1021	End job requested for job.
ATC1099	The document is required.
ATC1100	Subject is blank.
ATC1101	This document already exists. Press ***F3*** to exit and try again.
ATC1103	Print failed for this record.

GID	TEXT
ATC1107	Document printed.
ATC1125	Record added to file.
ATC1126	New name already exists. Select a different name or press ***F3*** to exit.
ATC1127	New name is blank.
ATC1135	List has been printed.
ATC1136	Record is not available for change.
ATC1137	Record printed.
ATC1138	Record deleted.
ATC1139	Record changed.
ATC1140	Record viewed.
ATC1154	Print failed for record .
ATC1159	To Name is blank.
ATC1161	Record has been renamed.
ATC1162	To name already exists.
ATC1163	Name is blank.
ATC1168	Record is printed.
ATC1169	Select only one item from the list.
ATC1170	Select not allowed with other options.
ATC1199	Record already exists.
ATC1200	User description is blank.
ATC1201	Allow Telnet access must be `1` for **`Yes`** or `2` for **`No`**.
ATC1202	Force password option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1203	Password is blank.
ATC1204	Default directory is blank.

GID	TEXT
ATC1205	Restrict Telnet commands option must be `1` for `Yes` or `2` for `No`.
ATC1206	Telnet command list is blank.
ATC1207	Restrict Telnet RCMD commands must be `1` for `Yes` or `2` for `No`.
ATC1208	RCMD list name is blank.
ATC1209	Telnet user ID is blank.
ATC1210	Telnet command list does not exist.
ATC1211	Telnet remote command list does not exist.
ATC1220	Command list description is blank.
ATC1221	Create directory option is invalid.
ATC1222	Delete directory option is invalid.
ATC1223	Change directory option is invalid.
ATC1224	List files option is invalid.
ATC1225	Delete files option is invalid.
ATC1226	Send files option is invalid.
ATC1227	Receive files option is invalid.
ATC1228	Rename files option is invalid.
ATC1229	Execute command option is invalid.
ATC1230	Command list name is blank.
ATC1240	Remote command list description is blank.
ATC1250	Remote command list name is blank.
ATC1254	Remote command is blank.
ATC1255	Remote command list name is blank.
ATC1256	IP address list description is blank.
ATC1257	IP address list name is blank.

GID	TEXT
ATC1258	IP address already exists.
ATC1259	IP address is blank.
ATC1260	IP address description is blank.
ATC1270	Library list description is blank.
ATC1271	At least one library must be specified.
ATC1272	Library does not exist.
ATC1273	List name already exists.
ATC1274	List name is blank.
ATC1275	Restrict library access option must be `1` for `Yes` or `2` for `No`.
ATC1276	Library list name is required.
ATC1277	Library list does not exist.
ATC1278	Command list does not exist.
ATC1279	IP address list does not exist.
ATC1280	Unregistered user does not exist in Telnet user file.
ATC1281	Anonymous user does not exist in Telnet user file.
ATC1282	Restrict IP address option must be `1` for `Yes` or `2` for `No`.
ATC1283	IP address and IP table are blank.
ATC1284	IP address is invalid.
ATC1285	Telnet command list does not exist.
ATC1286	User profile does not exist.
ATC1287	IP address contains invalid characters. Use only 0-9, dot (.), and blanks.
ATC1288	For IP address control, enter IP address or IP Table, but not both.
ATC1289	IP Table does not exist.
ATC1290	Device control option must be `1` or `2`.

GID	TEXT
ATC1291	For device control enter device name or device table.
ATC1292	For device control enter either device name or device table.
ATC1293	Device table does not exist.
ATC1300	Telnet security option must be `1`, `2` or `3`.
ATC1301	Enable Telnet request security must be `1` for **`Yes`** or `2` for **`No`**.
ATC1302	Allow Telnet must be `1` for **`Yes`** or `2` for **`No`**.
ATC1308	IP address control option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1309	IP address table is blank.
ATC1310	Logging option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1311	Intruder alert option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1312	Telnet logon alert option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1313	IP address table does not exist.
ATC1314	Logon warning threshold must be in the range 001 to 999.
ATC1315	Logon alert threshold must be in the range 001 to 999.
ATC1316	End Telnet option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1317	Telnet request alert option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1318	Request warning level must be in the range of 001 to 999.
ATC1319	Request alert level must be in the range of 001 to 999.
ATC1320	End Telnet option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1321	Library name is blank.
ATC1322	User address is blank.
ATC1323	Data queue library is blank.
ATC1324	Intruder counts have been reset.
ATC1325	Unable to retrieve counts, not reset.
ATC1326	Message queue does not exist, or not authorized.

GID	TEXT
ATC1327	Data queue does not exist, or not authorized.
ATC1329	Device description is blank.
ATC1330	Device name is blank.
ATC1331	Device name already exists.
ATC1332	Device name is blank.
ATC1333	Description is blank.
ATC1339	From date is blank.
ATC1340	To date is blank.
ATC1341	The From date is later than the To date.
ATC1342	The From time is blank.
ATC1343	The To time is blank.
ATC1344	The From time is later than the To time.
ATC1345	Accept/Reject option must be `1` , `2` , or `3` .
ATC1346	Date is invalid. Enter valid date in YYYYMMDD format.
ATC1347	Time is invalid. Enter valid time in HHMMSS format.
ATC1348	Error submitting audit report. See job log for details.
ATC1349	Audit report submitted to job queue.
ATC1359	Include accepted option must be `1` for **`Yes`** or `2` for **`No`** .
ATC1360	If specified, reject code must be in the range of `01` to `99` .
ATC1361	If specified, accept code must be in the range of `01` to `99` .
ATC1399	Description is blank.
ATC1400	Status must `1` for **`Active`** , or `2` for **`Inactive`** .
ATC1401	Logging must be `1` for **`Active`** , or `2` for **`Inactive`** .
ATC1402	Script file name is blank.
ATC1403	Script file library is blank.

GID	TEXT
ATC1404	Script file member is blank.
ATC1405	Substitution option must be `1` for `Yes` or `2` for `No`.
ATC1406	If substitution is Yes, local file or remote file is required.
ATC1407	FTP user name is blank.
ATC1408	FTP password is blank.
ATC1409	Message queue name is blank.
ATC1410	Message queue library is blank.
ATC1411	E-mail address is invalid. User ID and address is required.
ATC1412	Data queue name and library are required.
ATC1413	Inbound translation table or `*CCSID` is required.
ATC1414	Outbound translation table or `*CCSID` is required.
ATC1415	Remote system or IP address is required.
ATC1416	CCSID must be *DFT or a valid value.
ATC1417	FTP session name is blank.
ATC1418	FTP session name already exists.
ATC1419	SEU and PDM editors not found. Use alternative editor to maintain scripts.
ATC1420	Work with scripts completed normally.
ATC1421	Unmonitored exception in program. See job log for details.
ATC1422	Error calling API `FTMEXEC`. See job log for more information.
ATC1423	Internal error calling AN0037 for global options. Job cancelled.
ATC1424	AN0100C: Error encountered in library scan job. Continuing job.
ATC1425	AN0100C: Normal shutdown requested for FTP Manager library scan.

GID	TEXT
ATC1426	AN0100C: ERROR: Unmonitored exception in FTP Manager library scan.
ATC1427	AN0120C: Invalid file found in scan library .
ATC1428	AN0120C: Error processing before command for file in library .
ATC1429	AN0120C: Error processing after command for file in library .
ATC1430	AN0120C: Error deleting file in library . Trying backup.
ATC1431	AN0120C: Unable to delete or move file in library .
ATC1432	Request successful.
ATC1433	AN0120C: ERROR: Unmonitored exception in FTP Manager library scan.
ATC1434	Unable to retrieve session record for .
ATC1435	Session record is not active.
ATC1436	FTP Manager session starting for .
ATC1437	Error: Unable to create FTP work script in file SCRIPTW.
ATC1438	Error: Unable to copy FTP script to work file SCRIPTW.
ATC1439	Error: FTP command failed for session. See job log for more information.
ATC1440	Error: FTP session completed with return code.
ATC1441	FTP session successful.
ATC1442	Error: Unmonitored exception in program **FTMEXEC** for session.
ATC1443	Product license error. Please contact your software vendor.
ATC1444	FTP Manager subsystem started.
ATC1445	Subsystem not active, or ENDSBS command ended in error.
ATC1446	FTP Manager subsystem ended.
ATC1447	Message file ANCMSG not found.

GID	TEXT
ATC1448	Session name is blank or invalid.
ATC1449	FTP session completed successfully.
ATC1450	Error: Error code , text: .
ATC1451	FTP Manager:
ATC1452	Library not found for scan operaton.
ATC1453	AN0200C: Error encountered in directory scan job. Continuing job.
ATC1454	AN0200C: Normal shutdown requested for FTP Manager directory scan.
ATC1455	AN0200C: ERROR: Unmonitored exception in FTP Manager directory scan.
ATC1456	AN6053E: Invalid number of parameters.
ATC1457	AN6053E: Path name too long. Maximum length of path is 255.
ATC1458	AN6053E: Invalid directory name.
ATC1459	AN6053E: Unable to open file ANSTML.
ATC1460	AN0211C: Error on call to program AN6053E to make a directory list.
ATC1461	AN0211C: Invalid file found in scan directory .
ATC1462	AN0211C: Error translating file in directory to upper case.
ATC1463	AN0211C: Error creating file name for file in directory .
ATC1464	AN0211C: Error creating file in library for directory copy.
ATC1465	AN0211C: Error copying stream file . File not processed. See job log.
ATC1466	AN0211C: ERROR: Unmonitored exception in FTP Manager directory scan.
ATC1467	Error: Unmonitored exception in program **FTMEXECR** for session .
ATC1468	Remote system or ***INTNETADR** is required.

GID	TEXT
ATC1469	Invalid remote system name. Enter a name or **`*INTNETADR`** .
ATC1479	FTP definition is blank.
ATC1480	FTP definition does not exist.
ATC1481	Library scan option is not enabled. Normal termination.
ATC1482	Directory scan option is not enabled. Normal termination.
ATC1483	Remote system cannot be contacted.
ATC1484	Remote verify option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC1485	Session retry option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC1486	Session retry count must be in the range of 001 to 999.
ATC1487	Retry interval must be in the range of 0001 to 9999.
ATC1488	Unable to contact remote system with PING.
ATC1489	Retrying session after second delay.
ATC1490	Error submitting library scan job for file /.
ATC1491	AN0121C: ERROR: Unmonitored exception in FTP Manager library scan.
ATC1492	Compression option must be **`1`** for **`None`** , **`2`** for **`Gzip`** , or **`3`** for **`Zip`** .
ATC1493	Convert to ASCII option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC1494	Compressed file name is blank. Provide a name, *FILE or *GEN.
ATC1495	Compression error for session during IFS copy.
ATC1496	If IP address entered, remote system must be **`*INTNETADR`** .
ATC1497	End option must be **`1`** for **`Controlled`** or **`2`** for **`Immediate`** .
ATC1498	Controlled shutdown started for Alliance jobs.
ATC1499	User cancelled option. No action taken.

GID	TEXT
ATC1500	AN0300C: Normal shutdown requested for FTP Manager spool distribution.
ATC1501	Subsystem already active. Press HELP.
ATC1502	User cancelled. Schedule entry not added.
ATC1503	Error adding schedule entry. See job log for details. Entry not added.
ATC1504	Resubmit option must be `1` for `Yes` or `2` for `No`.
ATC1505	Alliance CrossData/400 is not installed.
ATC1506	Alliance FTP Security is not installed.
ATC1507	SNMP option must be `1` for `Yes` or `2` for `No`.
ATC1508	Error submitting group transfer job for file /, group .
ATC1509	AN0120C: Unable to move file in library .
ATC1510	Invalid record length of input file, must not exceed 9,999.
ATC1511	Error attempting to PING system .
ATC1512	FTP session ended in error. Return code:
ATC1513	FTP Manager directory session starting for .
ATC1514	Error: FTP directory session completed with return code .
ATC1515	FTP directory session successful.
ATC1516	Error: Unmonitored exception in program FTMDIR for session .
ATC1517	FTP directory error for output file library. Session: .
ATC1518	FTP directory error for output file. Session: .
ATC1519	FTP directory error while adding member for output file. Session: .
ATC1520	FTP directory error while adding data to output file. Session: .
ATC1521	Error retrieving FTP directory profile .
ATC1522	Error opening output file for FTP directory listing.

GID	TEXT
ATC1523	Error opening listing output file for FTP directory.
ATC1524	FTP directory session ended in error. Return code:
ATC1525	Error in user exit program / processing file .
ATC1526	Reply-to address is required if Email address is specified.
ATC1527	Email address is required if Reply-to is specified.
ATC1528	Alliance Application Monitor is not installed.
ATC1529	Error writing backup history.
ATC1530	File name is blank.
ATC1531	Library name is blank.
ATC1532	Member name is blank.
ATC1533	File already exists in target library.
ATC1534	Error restoring file. See job log for details.
ATC1535	File successfully restored.
ATC1536	Unmonitored error on file restore. See job log for details.
ATC1537	Operation cancelled. No action taken.
ATC1538	Custom library list option must be `1` for `Yes` or `2` for `No` .
ATC1539	Library list name is blank.
ATC1540	Library list name is not valid.
ATC1541	Library list description is blank.
ATC1542	Library list is blank.
ATC1543	File not available for restore operation.
ATC1544	Error reading month from month table.
ATC1545	Month must be in the range of 01 to 12.
ATC1546	Description is blank.
ATC1547	File name start must be in the range of 000 to 999.

GID	TEXT
ATC1548	File length must be in the range of 000 to 999.
ATC1549	Year start position must be in the range of 000 to 999.
ATC1550	Month start position must be in the range of 000 to 999.
ATC1551	Day start position must be in the range of 000 to 999.
ATC1552	Hour start position must be in the range of 000 to 999.
ATC1553	Minute start position must be in the range of 000 to 999.
ATC1554	Second start position must be in the range of 000 to 999.
ATC1555	Size start position must be in the range of 000 to 999.
ATC1556	Size length position must be in the range of 000 to 999.
ATC1557	Month table is blank.
ATC1558	Month table does not exist.
ATC1559	AN6051E: Invalid number of arguments.
ATC1560	IFS file name too long. Maximum of 256 bytes is supported.
ATC1561	Unable to open IFS file. The file does not exist, or not authorized.
ATC1562	AN6051C: Unmonitored error in IFS file transation job. See job log for details.
ATC1563	AN6051C: IFS translate routine received error on fgetpos() function.
ATC1564	AN6051C: IFS translate routine received error on fsetpos() function.
ATC1565	AN6051C: IFS translate routine received error on file read operation.
ATC1566	AN6051C: IFS translate routine received error on file write operation.
ATC1567	AN6051C: IFS translate routine received error calling program AN6051E.
ATC1568	FTP option must be `1` for **`Yes`** or `2` for **`No`**.

GID	TEXT
ATC1569	FTP session name is required.
ATC1570	FTP session name is invalid.
ATC1571	IFS directory scan received error in FTP for session , file .
ATC1572	FTMIPADDR: unmonitored exception in program. See job log for details.
ATC1573	AN0404C: ERROR calling program AN0404C to retrieve IP address.
ATC1574	Host name and IP address are blank.
ATC1575	Port number is blank.
ATC1576	Unable to resolve host name to IP address.
ATC1577	Host name resolved but is not type AF_INIT.
ATC1578	Host name resolved but IP address not available.
ATC1579	Error creating socket.
ATC1580	Unable to connect to remote host.
ATC1581	FTMPORT: ERROR calling program AN6052E to check the port.
ATC1582	FTMPORT: unmonitored exception in program. See job log for details.
ATC1583	If remote system is **`*INTNETADR`** an IP address is required.
ATC1584	Verify remote system must be Yes to use an alternate system.
ATC1585	Using alternate system /.
ATC1586	Email distribution list description is blank.
ATC1587	Email address is blank.
ATC1588	Email address description is blank.
ATC1589	Email option must be **`1`** , **`2`** or **`3`** .
ATC1590	Email recipient address is required if email option is **`Yes`** .
ATC1591	Email recipient address is required if email option is **`Yes`** .

GID	TEXT
ATC1592	Reply-to address is required if Email option is **`Yes`** .
ATC1593	Message text or message file is required if email option is **`Yes`** .
ATC1594	Message library is required if message file is defined.
ATC1595	Message file member is required if message file is defined.
ATC1596	Output queue processing type must be **`6`** for Email option **`1`** (***HELP***).
ATC1597	Attachment type must be 1, 2, 3 or 4.
ATC1598	AN0120C: Empty file found in scan library .
ATC1599	View toggled for all records.
ATC1600	View toggled for errors only.
ATC1601	If program name is specified, library name is required.
ATC1602	If library name is specified, program name is required.
ATC1603	Error calling user exit program /. Program does not exist.
ATC1604	Error calling user exit program /. Program failed.
ATC1605	Error backup library established for file.
ATC1606	FTMFSTAT: Error calling internal program AN0078. Contact programming support.
ATC1607	FTMFSTAT: Unmonitored exception in program. See job log for details.
ATC1608	Convert nulls option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC1609	Unable to retrieve FTP definition for Remove Nulls option.
ATC1610	Error reading record from conversion file in session
ATC1611	Record length too long for conversion in session .
ATC1612	No records found in conversion file for session .
ATC1613	Internal error calling program AN0080 in session .
ATC1614	Remove IFS nulls option must be **`1`** for **`Yes`** or **`2`** for **`No`** .

GID	TEXT
ATC1615	ERROR renaming IFS file for backup. File may not be processed correctly.
ATC1616	ERROR moving IFS file to archive directory. File may not be processed correctly.
ATC1617	Unable to open IFS file for size.
ATC1618	MQSeries option must be `1` for `Yes` or `2` for `No`.
ATC1619	MQSeries queue is blank.
ATC1620	MQSeries type must be `1` for `Stream` or `2` for `Record`.
ATC1621	Data conversion option must be `1` for `Yes` or `2` for `No`.
ATC1622	Conversion table name is blank.
ATC1623	Conversion table library is blank.
ATC1624	MQSeries send successful.
ATC1625	Internal error calling program `AN0410R` to send MQSeries message.
ATC1626	Unmonitored exception in program M `QMSEND`. See job log for details.
ATC1627	Error opening file for MQSeries send.
ATC1628	AN0170C: Unmonitored exception in MQSeries receive program for queue .
ATC1629	Error retrieving MQSeries queue name.
ATC1630	Error opening file for MQSeries receive.
ATC1631	Error translating MQSeries received data.
ATC1632	MQSeries receive definition is not active. Job terminating.
ATC1633	Library does not exist for MQSeries definition .
ATC1634	Error creating file for MQSeries receive definition .
ATC1635	Error adding file member for MQSeries receive definition .
ATC1636	ERROR calling program AN0415R for MQSeries receive definition .

GID	TEXT
ATC1637	Status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC1638	Receive to library is blank.
ATC1639	Receive to file is blank.
ATC1640	Special value must be *GEN.
ATC1641	Member name is blank.
ATC1642	Member name must be blank when file is *GEN.
ATC1643	Add or replace option must be `1` for **`Add`** or `2` to **`Replace`**.
ATC1644	Record length must be in the range of 1 to 32766.
ATC1645	Job name is blank.
ATC1646	Job queue is blank.
ATC1647	Job queue library is blank.
ATC1648	Job description is blank.
ATC1649	Job description library is blank.
ATC1650	Job user option must be `1`, `2` or `3`.
ATC1651	User name is required for this job user option.
ATC1652	Auto start option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1653	Restart option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1654	Data conversion option must be `1` for **`Yes`** or `2` for **`No`**.
ATC1655	Table name is required for this conversion option.
ATC1656	Table library is required for this conversion option.
ATC1657	MQSeries queue name is blank.
ATC1658	Error autostarting MQSeries receive jobs. See job log for details.
ATC1659	MQSeries receiver started.
ATC1660	Error starting MQSeries receive for queue .
ATC1661	Error submitting MQSeries receive job for queue .

GID	TEXT
ATC1662	Job name is a reserved name.
ATC1663	AN6058E: Invalid number of parameters.
ATC1664	AN6058E: File name too long.
ATC1665	AN6058E: File does not exist: .
ATC1666	ERROR renaming PGP file for backup. File may not be processed correctly:
ATC1667	ERROR moving PGP file to archive directory. File may not be processed correctly:
ATC1668	AN6059E: Invalid number of parameters.
ATC1669	AN6059E: File name too long: .
ATC1670	AN6059E: File does not exist: .
ATC1671	Encryption user ID is blank.
ATC1672	ASCII armor option must be `1` for `Yes` or `2` for `No` .
ATC1673	Encryption key user ID is blank.
ATC1674	Alliance EDI Workbench/400 is not installed.
ATC1675	Sign encrypted file option must be `1` for `Yes` or `2` for `No` .
ATC1676	Signing user ID is blank.
ATC1677	PGP encryption error for session .
ATC1678	File name for PGP copy is blank.
ATC1679	Error copying file to IFS directory. See job log for details.
ATC1680	Library name for PGP copy is blank.
ATC1681	Member name for PGP copy is blank.
ATC1682	IFS file name is blank.
ATC1683	Sign option is `*YES` , but signing user ID is blank.
ATC1684	Sign option is `*YES` , but signing user pass phrase is blank.
ATC1685	PGP product license error. Please contact your software vendor.

GID	TEXT
ATC1686	PGP already installed. Press ***F10*** to install again.
ATC1687	Error installing PGP IFS files. See job log for details.
ATC1688	Error installing PGP IFS files. See job log for details.
ATC1689	PGP IFS files installed.
ATC1690	PGP installation option cancelled.
ATC1691	ERROR, umonitored exception in program. See job log for details.
ATC1692	PGP files not installed. Complete PGP installation and try again.
ATC1693	Error copying file to stream file. Creating program described work file and tryi
ATC1694	Error copying file to stream file, unable to exract original file name.
ATC1695	Unable to create work library **`ALLFTM100W`** .
ATC1696	Error creating work file for stream file copy.
ATC1697	Error copying original file to program described work file.
ATC1698	Error copying program described file to IFS file.
ATC1699	Library for file does not exist, or not authorized.
ATC1700	File does not exist, or not authorized.
ATC1701	Member does not exist in file, or not authorized.
ATC1702	Not authorized to use file.
ATC1703	Non-display option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC1704	Password change processed.
ATC1705	Current password not correct.
ATC1706	New password is blank.
ATC1707	New password and verify password not the same.
ATC1708	User profile is blank.

GID	TEXT
ATC1709	User profile does not exist, or not authorized.
ATC1710	Authority granted to user.
ATC1711	PGP files not installed. Install PGP files before using this option.
ATC1712	Error granting authority to file .
ATC1713	PGP user name is blank.
ATC1714	PGP user already exists.
ATC1715	User profile does not exist.
ATC1716	Error granting authority to PGP. See job log for details.
ATC1717	User not authorized to PGP files. (***HELP***)
ATC1718	PGP file management must be `1` for `Alliance` or `2 for` Native IBM i`.
ATC1719	Characteristics start position must be in the range of 0 to 999.
ATC1720	Characteristics length must be in the range of 0 to 999.
ATC1721	Error in session , user not authorized to PGP files.
ATC1722	ERROR: You must be QSECOFR or have group profile authority to QSECOFR.
ATC1723	ERROR changing object authorization.
ATC1724	File name is too long.
ATC1725	No data to encrypt.
ATC1726	Unable to open output file.
ATC1727	DES key field is blank.
ATC1728	DES data is blank.
ATC1729	DES translate option must be `0` or `1` .
ATC1730	DES format option must be `1` or `2` .
ATC1731	Pass phrase is required if override output file is specified.
ATC1732	Output file name only valid when PGP decryption selected.

GID	TEXT
ATC1733	DES initialization vector is blank.
ATC1734	DES key 1 has invalid length.
ATC1735	DES key 2 has invalid length.
ATC1736	DES key 3 has invalid length.
ATC1737	DES initialization vector has invalid length.
ATC1738	DES input data has invalid length.
ATC1739	DES output data has invalid length.
ATC1740	DES key in error.
ATC1741	ERROR, unmonitored exception in program AN0281. See job log for details.
ATC1742	Plaintext option must be `1` for `Yes` or `2` for `No`.
ATC1743	DES encryption length must be 00001 to 00512.
ATC1744	Scan definition not found.
ATC1745	PDF font is blank.
ATC1746	Invalid font size.
ATC1747	Page width is invalid.
ATC1748	Page height is invalid.
ATC1749	Alliance XML Workbench/400 is not installed.
ATC1750	Customer option must be `1` for `Yes` or `2` for `No`.
ATC1751	Conversion program is blank.
ATC1752	Conversion program library is blank.
ATC1753	Select `CPYFRMSTMF` option or Custom copy option, but not both.
ATC1754	Copy to library is not blank, but no copy option selected (***HELP***).
ATC1755	AN0211C: Error calling custom conversion program for file in directory .

GID	TEXT
ATC1756	AN0211C: Error returned by custom conversion program for file in directory .
ATC1757	AN0172C: Internal error calling custom program AN6064E.
ATC1758	AN0172C: program AN6064E returned error code .
ATC1759	AN0172C: Unmonitored error in program.
ATC1760	PDF files already installed. Press F10 to install again.
ATC1761	Error installing PDF IFS files. See job log for details.
ATC1762	PDF IFS files installed.
ATC1763	PDF installation option cancelled.
ATC1764	ERROR, umonitored exception in program. See job log for details.
ATC1765	Not authorized to function. Press ***HELP*** for more information.
ATC1766	Authorization list option must be `1` for **`Yes`** or `2` for **`No`** .
ATC1767	Directory scan user is required.
ATC1768	Directory scan user does not exist, or not authorized.
ATC1769	No records in input file.
ATC1770	Error processing file. File open failed.
ATC1771	Scan definition not found in file.
ATC1772	Status must be `1` for **`Active`** or `2` for **`Inactive`** .
ATC1773	Retrieval type must be 1, 2 or 3.
ATC1774	Interval must be in the range of 1 to 99999.
ATC1775	Directory FTP definition is blank.
ATC1776	Directory FTP definition not found.
ATC1777	Directory profile is blank.
ATC1778	Directory profile not found.
ATC1779	Script file is blank.

GID	TEXT
ATC1780	Script file library is blank.
ATC1781	Script file member is blank.
ATC1782	FTP retrieval definition is blank.
ATC1783	FTP retrieval definition not found.
ATC1784	File name option must be 1, 2 or 3.
ATC1785	Audit report option must be `1` for `Yes` or `2` for `No` .
ATC1786	Auto scan name is blank.
ATC1787	ERROR starting auto scan jobs. See job log for details.
ATC1788	Error submitting Auto Scan job for scan .
ATC1789	FTP Auto Scan started.
ATC1790	Error starting FTP Auto Scan for scan .
ATC1791	Using local file name <>.
ATC1792	Special values `*CURLIB` and `*LIBL` not supported.
ATC1793	Unmonitored exception in program `CVtDLTFILE` . See job log for details.
ATC1794	AN0173C: Internal error calling custom program `AN6066E` .
ATC1795	AN0173C: program `AN6066E` returned error code .
ATC1796	AN0173C: Unmonitored error in program.
ATC1797	CVTGSKERR: Unmonitored exception in program. See job log for details.
ATC1798	Processing multi-member file.
ATC1799	Error creating list of members for file / .
ATC1800	AN0120C: Error creating translate file in scan library .
ATC1801	AN0120C: Error renaming translate file in scan library .
ATC1802	AN0120C: Error moving translate file in scan library .
ATC1803	AN0120C: Error copying translate file in scan library .

GID	TEXT
ATC1804	AN0120C: Error removing member in file in scan library .
ATC1805	Back up file name set to /.
ATC1806	AN0120C: Error copying FTP file in scan library .
ATC1807	AN0120C: Error removing member in file in scan library .
ATC1808	AN0120C: Error copying FTP file in scan library .
ATC1809	Schedule option must be `1` , `2` or `3` .
ATC1810	Error: Unmonitored exception in program FTMEXECD for session .
ATC1811	Encryption option must be specified on FTP Definition (***HELP***).
ATC1812	AN6068E: File name is too long.
ATC1813	AN6068E: File cannot be opened exclusively, file in use.
ATC1814	Email address is invalid, or invalid email distribution list name.
ATC1815	End of line option must be `1` , `2` or `3` .
ATC1816	ERROR creating work file from ANFDIR. See job log for details. Scan job terminat
ATC1817	ERROR creating FTP directory for scan job . See job log for details.
ATC1818	ERROR processing FTP scan directory. Scan directory may not be complete. See fol
ATC1819	AN0600C: ERROR: Unmonitored exception in FTP Manager directory scan.
ATC1820	IBM i option must be `1` for `Yes` or `2` for `No` .
ATC1821	ERROR retrieving FTP scan directory options. See job log for details.
ATC1822	FTP script not found.
ATC1823	Conversion table does not exist, or not authorized.
ATC1824	If PGP log option is `*YES` the log file, library, and member name are required.

GID	TEXT
ATC1825	Error creating PGP log file. Log option is changed to `*NO` for this session.
ATC1826	Error adding member to PGP log file. Log option is changed to `*NO` for this sessi
ATC1827	AN7070E: File name exceeds maximum file name.
ATC1828	AN7070E: Unable to open input file.
ATC1829	AN7070E: Unable to open output file with CCSID option.
ATC1830	AN7070E: Error unlinking original file. CCSID change failed.
ATC1831	AN7070E: Error renaming converted file. CCSID change failed.
ATC1832	Invalid CCSID value. Must be *DFT or a valid CCSID number.
ATC1833	AN6070E: Error in CCSID conversion.
ATC1834	Spool file distribution user does not exist, or not authorized.
ATC1835	Library scan user does not exist, or not authorized.
ATC1836	Spool file distribution user is blank.
ATC1837	Library scan user is blank.
ATC1838	Output CCSID option must be `1` or `2` .
ATC1839	CCSID must be in the range of 1 to 65533.
ATC1840	CCSID option only valie for PGP decryption option.
ATC1841	Converting decrypted file to CCSID .
ATC1842	Table name is blank.
ATC1843	Table library name is blank.
ATC1844	No spool file action found for spool file.
ATC1845	AN6071E: Error registering exception handler. Job terminated.
ATC1846	AN6071E: Error initializing FTP Manager environment.
ATC1847	AN6072E: File name is too long.

GID	TEXT
ATC1848	AN6072E: Unable to retrieve file characteristics.
ATC1849	AN6072E: Path is a directory, unable to retrieve the size.
ATC1850	AN6073E: File name is greater than maximum of 256.
ATC1851	AN6073E: Error opening IFS file.
ATC1852	AN0174C: Internal error calling custom program AN6069E.
ATC1853	AN0430R GXS: Error initializing FTP environment. Job cancelled.
ATC1854	AN0430R GXS: Error initializing the application log.
ATC1855	AN0430R GXS: Error setting the logging level.
ATC1856	AN0430R GXS: Error setting the remote FTP server port number.
ATC1857	AN0430R GXS: An error occurred setting the FTP environment for SSLC support.
ATC1858	AN0430R GXS: An error occurred setting the SSL Application ID for the session.
ATC1859	AN0430R GXS: Unable to open FTP site [sftp.gegxs.com].
ATC1860	AN0430R GXS: FTP open operation returned error code , text .
ATC1861	AN0430R GXS: Unable to send the user ID to GXS.
ATC1862	AN0430R GXS: FTP USER operation returned error code , text .
ATC1863	AN0430R GXS: Unable to send the password to GXS.
ATC1864	AN0430R GXS: FTP PASS operation returned error code , text .
ATC1865	AN0430R GXS: Unable to change directory to /send.
ATC1866	AN0430R GXS: FTP CD operation returned error code , text .
ATC1867	AN0430R GXS: Unable to set Binary mode for transfer.
ATC1868	AN0430R GXS: FTP BINARY operation returned error code , text .

GID	TEXT
ATC1869	AN0430R GXS: Unable to set Passive mode for transfer.
ATC1870	AN0430R GXS: FTP PASV operation returned error code , text .
ATC1871	AN0430R GXS: Error sending file to GXS.
ATC1872	AN0430R GXS: FTP STOR operation returned error code , text .
ATC1873	AN0430R GXS: Error send PWD command to commit transfer.
ATC1874	AN0430R GXS: FTP PWD operation returned error code , text .
ATC1875	GXS transfer option must be `1` for `Yes` or `2` for `No` .
ATC1876	GXS FTP user ID is blank.
ATC1877	GXS FTP password is blank.
ATC1878	GXS SSL application ID is blank.
ATC1879	GXS retry value must be in the range of `0` to `99` .
ATC1880	Select GXS or standard FTP transfer, but not both.
ATC1881	ERROR calling GXS FTP communications program for file .
ATC1882	GXS application logging must be `1` , `2` or `3` .
ATC1883	AN0433R GXS: Error initializing FTP environment. Job cancelled.
ATC1884	AN0433R GXS: Error initializing the application log.
ATC1885	AN0433R GXS: Error setting the logging level.
ATC1886	AN0433R GXS: Error setting the remote FTP server port number.
ATC1887	AN0433R GXS: An error occurred setting the FTP environment for SSLC support.
ATC1888	AN0433R GXS: An error occurred setting the SSL Application ID for the session.
ATC1889	AN0433R GXS: Unable to open FTP site [sftp.gegxs.com].

GID	TEXT
ATC1890	AN0430R GXS: FTP open operation returned error code , text .
ATC1891	AN0433R GXS: Unable to send the user ID to GXS.
ATC1892	AN0433R GXS: FTP USER operation returned error code , text .
ATC1893	AN0433R GXS: Unable to send the password to GXS.
ATC1894	AN0433R GXS: FTP PASS operation returned error code , text .
ATC1895	AN0433R GXS: Unable to change directory to /receive.
ATC1896	AN0433R GXS: FTP CD operation returned error code , text .
ATC1897	AN0433R GXS: Unable to set local name format.
ATC1898	AN0433R GXS: FTP NAMEFMT operation returned error code , text .
ATC1899	AN0433R GXS: Unable to send site command for GNI.
ATC1900	AN0433R GXS: FTP SITE operation returned error code , text .
ATC1901	AN0433R GXS: Unable to set Passive mode for transfer.
ATC1902	AN0433R GXS: FTP PASV operation returned error code , text .
ATC1903	AN0433R GXS: Unable to set Binary mode for transfer.
ATC1904	AN0433R GXS: FTP BINARY operation returned error code , text .
ATC1905	AN0433R GXS: Unable to set Retrieve file from GXS.
ATC1906	AN0433R GXS: FTP RETR operation returned error code, text .
ATC1907	AN0433R GXS: Unable to send PWD for file transfer confirm.
ATC1908	AN0433R GXS: FTP PWD confirm operation returned error code , text .
ATC1909	Scan type must be 1, 2, 3, 4, 5 or 6.

GID	TEXT
ATC1910	Receive to library is blank.
ATC1911	Auto scan name already in use.
ATC1912	Internal error calling AN0037 for global options. Job cancelled.
ATC1913	AN0602C: Normal shutdown requested for FTP Manager GXS auto scan.
ATC1914	AN0602C: ERROR: Unmonitored exception in FTP Manager GXS auto scan.
ATC1915	AN0602C: The GXS FTP receive program encountered an error.
ATC1916	File name is blank.
ATC1917	Library name is blank.
ATC1918	Member name is blank.
ATC1919	Library does not exist, or not authorized.
ATC1920	File does not exist, or not authorized.
ATC1921	Member does not exist in file, or not authorized.
ATC1922	GXS user ID is blank.
ATC1923	GXS password is blank.
ATC1924	Invalid log option. Log option must be `1`, `2` or `3`.
ATC1925	Retry value must be in the range of 00 to 99.
ATC1926	SSL Application ID is blank.
ATC1927	FTMGXSSND: Error calling program AN0430R. See job log for details.
ATC1928	Call to API program FTMGXSSND completed normally.
ATC1929	Unmonitored exception in program FTMGXSSND. See the joblog for details.
ATC1930	Library name is blank.
ATC1931	Library does not exist, or not authorized.

GID	TEXT
ATC1932	GXS User ID is blank.
ATC1933	GXS password is blank.
ATC1934	Invalid log option. Log option must be `1`, `2` or `3`
ATC1935	SSL Application ID is blank.
ATC1936	The retry option is invalid. The retry value must be from `00` to `99`.
ATC1937	FTMGXSRCV: Error calling program AN0433R. See job log for details.
ATC1938	Call to API program FTMGXSRCV completed normally.
ATC1939	Unmonitored exception in program FTMGXSRCV. See the joblog for details.
ATC1940	Command FTMGXSSND completed successfully.
ATC1941	ERROR in command FTMGXSSND. See job log for details.
ATC1942	Command FTMGXSRCV completed successfully.
ATC1943	ERROR in command FTMGXSRCV. See job log for details.
ATC1944	IBM user ID is blank.
ATC1945	IBM password is blank.
ATC1946	SSL application ID is blank.
ATC1947	Invalid retry value. Must be in the range of `00` to `99`.
ATC1948	Logging level must be `1`, `2` or `3`.
ATC1949	Library name is blank.
ATC1950	AN0603C: The IBM FTP receive program encountered an error.
ATC1951	AN0603C: Normal shutdown requested for FTP Manager IBM auto scan.
ATC1952	AN0603C: ERROR: Unmonitored exception in FTP Manager IBM auto scan.

GID	TEXT
ATC1953	AN0436R IBM: Error initializing FTP environment. Job cancelled.
ATC1954	AN0436R IBM: Error initializing the application log.
ATC1955	AN0436R IBM: Error setting the logging level.
ATC1956	AN0436R IBM: An error occurred setting the FTP environment for SSL support.
ATC1957	AN0436R IBM: An error occurred setting the SSL Application ID for the session.
ATC1958	AN0436R IBM: Unable to open FTP site [IEFTPINT2.SERVICES.IBM.COM].
ATC1959	AN0436R IBM: FTP open operation returned error code, text .
ATC1960	AN0436R IBM: Unable to send the user ID to GXS.
ATC1961	AN0436R IBM: FTP USER operation returned error code, text .
ATC1962	AN0436R IBM: Unable to send the password to IBM.
ATC1963	AN0436R IBM: FTP PASS operation returned error code, text .
ATC1964	AN0436R IBM: Unable to send the SSL Auth command to IBM.
ATC1965	AN0436R IBM: FTP AUTH operation returned error code, text .
ATC1966	AN0436R IBM: Unable to send the SSL PBSZ command to IBM.
ATC1967	AN0436R IBM: FTP PBSZ operation returned error code, text .
ATC1968	AN0436R IBM: Unable to send the SSL PROT command to IBM.
ATC1969	AN0436R IBM: FTP PROT operation returned error code, text .
ATC1970	AN0436R IBM: Unable to send the SITE command to IBM.
ATC1971	AN0436R IBM: FTP SITE operation returned error code, text .

GID	TEXT
ATC1972	AN0436R IBM: Unable to change directory.
ATC1973	AN0436R IBM: FTP CD operation returned error code, text .
ATC1974	AN0436R IBM: Unable to set local name format.
ATC1975	AN0436R IBM: FTP NAMEFMT operation returned error code, text .
ATC1976	AN0436R IBM: Unable to set passive mode.
ATC1977	AN0436R IBM: FTP PASV operation returned error code, text .
ATC1978	AN0436R IBM: Unable to create file list.
ATC1979	AN0436R IBM: FTP NLST operation returned error code, text .
ATC1980	AN0436R IBM: Unable to set passive mode.
ATC1981	AN0436R IBM: FTP PASV operation returned error code, text .
ATC1982	AN0436R IBM: Unable to set local name format to 0.
ATC1983	AN0436R IBM: FTP NAMEFMT operation returned error code, text .
ATC1984	AN0436R IBM: Unable to retrieve file from IBM.
ATC1985	AN0436R IBM: FTP GET operation returned error code, text .
ATC1986	AN0436R IBM: Unable to set binary mode for transfer.
ATC1987	AN0436R IBM: FTP BINARY operation returned error code, text .
ATC1988	Library name is blank.
ATC1989	Library does not exist, or not authorized.
ATC1990	IBM User ID is blank.
ATC1991	IBM password is blank.
ATC1992	Invalid log option. Log option must be `1` , `2` or `3`
ATC1993	SSL Application ID is blank.

GID	TEXT
ATC1994	The retry option is invalid. The retry value must be from `00` to `99`.
ATC1995	FTMIBMRCV: Error calling program AN0436R. See job log for details.
ATC1996	Call to API program FTMGXSRCV completed normally.
ATC1997	Unmonitored exception in program FTMIBMRCV. See the joblog for details.
ATC1998	Command FTMIBMRCV completed successfully.
ATC1999	ERROR in command FTMIBMRCV. See job log for details.
ATC2000	AN0437R IBM: Error initializing FTP environment. Job cancelled.
ATC2001	AN0437R IBM: Error initializing the application log.
ATC2002	AN0437R IBM: Error setting the logging level.
ATC2003	AN0437R IBM: An error occurred setting the FTP environment for SSLC support.
ATC2004	AN0437R IBM: An error occurred setting the SSL Application ID for the session.
ATC2005	AN0437R IBM: Unable to open FTP site [IEFTPINT2.SERVICES.IBM.COM]
ATC2006	AN0437R IBM: FTP open operation returned error code, text.
ATC2007	AN0437R IBM: Unable to send the user ID to GXS.
ATC2008	AN0437R IBM: FTP USER operation returned error code, text.
ATC2009	AN0437R IBM: An error occurred setting the SSL Application ID for the session.
ATC2010	AN0437R IBM: Unable to send the SSL authorization request.
ATC2011	AN0437R IBM: FTP AUTH operation returned error code, text.
ATC2012	AN0437R IBM: Unable to send the Protection Buffer size.

GID	TEXT
ATC2013	AN0437R IBM: FTP PBSZ operation returned error code, text.
ATC2014	AN0437R IBM: Unable to send the Protection Type.
ATC2015	AN0437R IBM: FTP PROT operation returned error code, text.
ATC2016	AN0437R IBM: Unable to send the IBM password.
ATC2017	AN0437R IBM: FTP PASS operation returned error code, text.
ATC2018	AN0437R IBM: Unable to send the SITE SYSTEM command to IBM.
ATC2019	AN0437R IBM: FTP SITE SYSTEM operation returned error code, text.
ATC2020	AN0437R IBM: Unable to set passive mode.
ATC2021	AN0437R IBM: FTP PASV operation returned error code, text.
ATC2022	AN0437R IBM: Unable to send file to IBM network.
ATC2023	AN0437R IBM: FTP STOR operation returned error code, text .
ATC2024	AN0437R IBM: Unable to change directory.
ATC2025	AN0437R IBM: FTP CWD operation returned error code, text.
ATC2026	AN0437R IBM: Unable to set for binary transfer.
ATC2027	AN0437R IBM: FTP BINARY operation returned error code, text.
ATC2028	File name is blank.
ATC2029	Library name is blank.
ATC2030	Member name is blank.
ATC2031	Library does not exist, or not authorized.
ATC2032	File does not exist, or not authorized.
ATC2033	Member does not exist in file, or not authorized.

GID	TEXT
ATC2034	IBM user ID is blank.
ATC2035	IBM password is blank.
ATC2036	Invalid log option. Log option must be `1`, `2` or `3`.
ATC2037	Retry value must be in the range of `00` to `99`.
ATC2038	SSL Application ID is blank.
ATC2039	FTMIBMSND: Error calling program AN0437R. See job log for details.
ATC2040	Call to API program FTMIBMSND completed normally.
ATC2041	Unmonitored exception in program FTMIBMSND. See the joblog for details.
ATC2042	Command FTMIBMSND completed successfully.
ATC2043	ERROR in command FTMIBMSND. See job log for details.
ATC2044	IBM Global Network option must be `1` for `Yes` or `2` for `No`.
ATC2045	Select IBM or standard FTP transfer, but not both.
ATC2046	User ID is blank.
ATC2047	Password is blank.
ATC2048	SSL application ID is blank.
ATC2049	IBM retry value must be in the range of `0` to `99`.
ATC2050	IBM application logging must be `1`, `2` or `3`.
ATC2051	ERROR calling IBM FTP communications program for file.
ATC2052	Select GXS option or IBM option, but not both.
ATC2053	Cannot select Submit Job option with IBM network interface. (***HELP***)
ATC2054	Cannot select Submit Job option with GXS network interface. (***HELP***)
ATC2055	Job log printed to default output queue.
ATC2056	Single quotes not allowed on PGP pass phrase.

GID	TEXT
ATC2057	AN0177C: Internal error calling custom program AN6069E.
ATC2058	AN0177C: Unmonitored error in program.
ATC2059	User exit program and library are both required.
ATC2060	Error in FTP initialization for BellSouth. Job terminated.
ATC2061	Error in log initialization for BellSouth. Job terminated.
ATC2062	Error in log level settings for BellSouth. Job terminated.
ATC2063	Error setting SSL environment for BellSouth. Job terminated.
ATC2064	Error setting SSL ID for BellSouth. Job terminated.
ATC2065	Error Opening connection to BellSouth. Job terminated.
ATC2066	Error on AUTH SSL to BellSouth. Job terminated.
ATC2067	Error on PBSZ transaction to BellSouth. Job terminated.
ATC2068	Error on PROT transaction to BellSouth. Job terminated.
ATC2069	Error sending user ID to BellSouth. Job terminated.
ATC2070	Error sending password to BellSouth. Job terminated.
ATC2071	Error setting local name format for BellSouth. Job terminated.
ATC2072	Error setting record length for BellSouth. Job terminated.
ATC2073	Error retrieving file from BellSouth. Job terminated.
ATC2074	BellSouth receive session completed successfully.
ATC2075	Unmonitored exception in BellSouth API program FTMBELLS. See job log for details
ATC2076	Error sending file to BellSouth. Job terminated.
ATC2077	Unmonitored exception in BellSouth API program FTMBELLT. See job log for details
ATC2078	Error writing to IFS file. Insufficient number of bytes written.
ATC2079	No records in file to convert.
ATC2080	Trim trailing blanks option must be `1` for `Yes` or `2` for `No`.

GID	TEXT
ATC2081	End of line option must be CR/LF for trim trailing blanks.
ATC2082	ASCII conversion option must be Yes for trim trailing blanks.
ATC2083	Error sending support email. See help for options.
ATC2084	Log emailed to Alliance support.
ATC2085	MQSeries interface returned error code: .
ATC2086	Conversion table does not exist, or not authorized.
ATC2087	AN0440R BellSouth: Error in the FTMCCC procedure to send the CCC command.
ATC2088	AN0440R BellSouth: Error attempting to send CCC Clear Command Channel command.
ATC2089	BellSouth user ID is blank.
ATC2090	BellSouth password is blank.
ATC2091	SSL application ID is blank.
ATC2092	Invalid retry value. Must be in the range of `00` to `99`.
ATC2093	Logging level must be `1`, `2` or `3`.
ATC2094	Library name is blank.
ATC2095	Error submitting Auto Scan job for scan.
ATC2096	AN0604C: The IBM FTP receive program encountered an error.
ATC2097	AN0604C: Normal shutdown requested for FTP Manager BellSouth auto scan.
ATC2098	AN0604C: ERROR: Unmonitored exception in FTP Manager BellSouth auto scan.
ATC2099	Error starting Telnet server. Not authorized or server already started.
ATC2100	Unmonitored exception in program. See job log for details.
ATC2101	Telnet server started.

GID	TEXT
ATC2102	Error ending Telnet server. Not authorized, or server not active.
ATC2103	Telnet server ended.
ATC2104	Message file ANCMSG not found.
ATC2105	Resource name is blank.
ATC2106	Modem speed must be 2400, 4800, 9600 or 14400.
ATC2107	Remote support ready for connection.
ATC2108	Error during configuration. See job log for details.
ATC2109	Remote support has ended.
ATC2110	Library name is blank.
ATC2111	Current library is the same as the previous library.
ATC2112	Library does not exist, or not authorized.
ATC2113	Update completed successfully.
ATC2114	History maintenance date is blank.
ATC2115	Application maintenance is complete.
ATC2116	Activation code reset to blank.
ATC2117	Activation code has been changed.
ATC2118	Trial code reset to blanks.
ATC2119	Trial code changed.
ATC2120	Alliance Telnet Security: Error sending message to message queue /. Library does
ATC2121	Alliance Telnet Security: Error sending message to message queue /. Message queu
ATC2122	Alliance Telnet Security: Error sending message to message queue /. See job log
ATC2123	Alliance Telnet Security: Unmonitored exception sending message to message queue

GID	TEXT
ATC2124	Alliance Telnet Security: Error sending message to data queue /. Library does no
ATC2125	Alliance Telnet Security: Error sending message to data queue /. Data queue does
ATC2126	Alliance Telnet Security: Error sending message to data queue /. See job log for
ATC2127	Alliance Telnet Security: Unmonitored error sending message to data queue /. See
ATC2128	Alliance Telnet Security: Error sending e-mail message to user , address . See j
ATC2129	Alliance FTP Manager: Unmonitored error sending e-mail message to user , address
ATC2130	Alliance Telnet Security: Error sending alert mesasge about Telnet shutdown. See
ATC2131	Alliance Telnet Security: Unmonitored error in security program ANC100 for user
ATC2132	Alliance Telnet Security: User logon rejected with no error message in program
ATC2133	Alliance Telnet Security: Unmonitored error in security program ANC101 for user
ATC2134	Alliance Telnet Security: User logon rejected with no error message in program
ATC2135	Alliance Telnet Security: Unmonitored error in security program ANC102 for user
ATC2136	Alliance Telnet Security: User logon rejected with no error message in program
ATC2137	Alliance FTP Manager: Unmonitored error sending SMTP email message to user . See
ATC2200	Library name is blank.
ATC2201	Description is blank.
ATC2202	Status must be `1` for **`Active`** or `2` for **`Inactive`** .

GID	TEXT
ATC2203	Scan library already exists.
ATC2204	Description is blank.
ATC2205	Status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC2206	Conversion option must be `1`, `2`, `3` or `4`.
ATC2207	Output file is blank.
ATC2208	Output library is blank.
ATC2209	Output file member is blank.
ATC2210	Copy option must be `1` for **`Yes`** or `2` for **`No`**.
ATC2211	Stream file is required if copy option is Yes.
ATC2212	Post conversion option must be in the range of `1` to `8`.
ATC2213	Library name required for post conversion option.
ATC2214	File name is blank.
ATC2215	File definition already exists.
ATC2216	Perform FTP option must be `1` or `2`.
ATC2217	FTP session name is required for this option.
ATC2218	FTP session is not valid.
ATC2219	Alliance FTP Manager
ATC2220	Error retrieving session parameters.
ATC2221	User program / not found for file /.
ATC2222	User program / error for file /.
ATC2223	Library scan: Failure on FTP of file / to FTP definition . Press ***HELP***.
ATC2224	Library scan subsystem started.
ATC2225	Library scan subsystem ended.
ATC2226	Subsystem not active, or ENDSBS command ended in error.
ATC2227	Member not found in file /.

GID	TEXT
ATC2228	Unable to list members for file /.
ATC2229	No members exist in file /.
ATC2230	Unmonitored error retrieving member for file /.
ATC2231	API program is blank.
ATC2232	API program library is blank.
ATC2239	Description is blank.
ATC2240	Status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC2241	The copy to library is blank.
ATC2242	The copy to name option must be `1`, `2`, or `3`.
ATC2243	Translation option must be `1` for **`Yes`** or `2` for **`No`**.
ATC2244	Translation table is blank.
ATC2245	Translation table library is blank.
ATC2246	After option must be `1`, `2`, or `3`.
ATC2247	Backup directory is blank.
ATC2248	Directory file name is blank.
ATC2249	Directory file already exists.
ATC2250	Spool file type not supported.
ATC2251	Output queue status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC2252	Interface type must be from 1 to 6.
ATC2253	Logging option must be `1` for **`Yes`** or `2` for **`No`**.
ATC2254	IFS directory is required.
ATC2255	FTP text definition is required for this type.
ATC2256	FTP AFP definition is required for this type.
ATC2257	FTP SCS definition is required for this type.
ATC2258	FTP name option must be `1` or `2`.

GID	TEXT
ATC2259	User exit program required for this interface type.
ATC2260	User exit program library required for this interface type.
ATC2261	HTML header file required for this interface type.
ATC2262	HTML header file library required for this interface type.
ATC2263	HTML header file member required for this interface type.
ATC2264	HTML trailer file required for this interface type.
ATC2265	HTML trailer file library required for this interface type.
ATC2266	HTML trailer file member required for this interface type.
ATC2267	Completion option must be `1`, `2` or `3`.
ATC2268	Output queue name is blank.
ATC2269	Output queue library is blank.
ATC2270	Output queue definition already exists.
ATC2271	Report.Web option is not installed. Contact your software vendor.
ATC2272	Error changing output queue for Alliance processing. See job log.
ATC2273	Unmonitored exception while changing output queue. See job log for details.
ATC2274	Output queue does not exist.
ATC2275	Error in group API program. Unable to retrieve global settings.
ATC2276	Session starting for FTP group .
ATC2277	No FTP sessions defined for FTP group .
ATC2278	Warning: some FTP sessions for group were not successful.
ATC2279	Processing for FTP group completed successfully.
ATC2280	Error: Unmonitored exception in program for group .
ATC2281	Group does not exist. Session not peformed.

GID	TEXT
ATC2282	Group is not active. Session not peformed.
ATC2283	Group name is blank.
ATC2284	File name is blank.
ATC2285	Library name is blank.
ATC2286	Local file name is blank.
ATC2287	Remote file name is blank.
ATC2289	Job description name and library are required.
ATC2290	Job queue name and library are required.
ATC2291	Job description does not exist, or not authorized.
ATC2292	Job queue does not exist, or not authorized.
ATC2293	Group definition not found.
ATC2294	Group not found in schedule concurrent job.
ATC2295	Error in FTP group submitting job for session .
ATC2296	Error clearing file / after library scan. See job log for details.
ATC2297	Spool file name is blank.
ATC2298	Job name is blank.
ATC2299	User name is blank.
ATC2300	User data is blank.
ATC2301	Output queue action record already exists.
ATC2302	Skip empty member option must be `1` for `Yes` or `2` for `No`.
ATC2303	Submit job option must be `1` for `Yes` or `2` for `No`.
ATC2304	Job description is blank.
ATC2305	Job description library is blank.
ATC2306	Job queue name is blank.
ATC2307	Job queue library is blank.

GID	TEXT
ATC2308	Job name is blank or invalid.
ATC2309	Translate option must be `1` or `2` .
ATC2310	Translation table name is blank.
ATC2311	Translation table library is blank.
ATC2312	Error allocating record during translation.
ATC2313	Error in QDCXLATE translation call. See job log for details.
ATC2314	Error in translation of file /. No records in file.
ATC2315	AN0120C: Error translating file in scan library .
ATC2316	Backup output queue is blank.
ATC2317	Backup output queue library is blank.
ATC2318	Error output queue is blank.
ATC2319	Error output queue library is blank.
ATC2320	Output queue does not exist, or not authorized.
ATC2321	Lock option must be `1` for **`Yes`** or `2` for **`No`** .
ATC2322	Append file extension option must be `1` for **`Yes`** or `2` for **`No`** .
ATC2323	A file extension is required if the append file extension option is **`Yes`** .
ATC2324	Backup option must be `1` for **`Yes`** or `2` for **`No`** .
ATC2325	Output queue name required if backup option is **`Yes`** .
ATC2326	Output queue library name required if backup option is **`Yes`** .
ATC2327	ERROR: unmonitored exception sending SNMP trap error message for Alliance FTP Ma
ATC2328	ERROR sending SNMP trap error message for Alliance FTP Manager. See job log for
ATC2339	Error retrieving member name for FTP session .

GID	TEXT
ATC2340	Suppress leading blank lines must be `1` for `Yes` or `2` for `No`.
ATC2341	Local file name is blank.
ATC2342	Remote file name is blank.
ATC2343	Submit group job option must be `1` for `Yes` or `2` for `No`.
ATC2344	Job name is blank.
ATC2345	Job queue is blank.
ATC2346	Job queue library is blank.
ATC2347	Job description is blank.
ATC2348	Job description library is blank.
ATC2349	Group API program is blank.
ATC2350	Group name is blank.
ATC2351	Group does not exist.
ATC2352	Invalid special value. Special value must be `*FILE` or `*GROUP`.
ATC2353	AN0120C: Error creating reformat file in scan library .
ATC2354	AN0120C: Error in program AN0066 for file in scan library .
ATC2355	AN0120C: Error reformatting file in scan library .
ATC2356	AN0120C: Error renaming reformat file in scan library .
ATC2357	AN0120C: Error moving reformat file in scan library .
ATC2358	AN0120C: Error renaming new reformat file in scan library .
ATC2359	Reformat option must be `1` for `Yes` or `2` for `No`.
ATC2360	Reformat record length must be in the range of 00001 to 32766.
ATC2361	Local library name is blank or invalid.
ATC2362	Local file name is blank or invalid.
ATC2363	Encryption option must be `1` or `2`.

GID	TEXT
ATC2364	Pass phrase 1 is blank.
ATC2365	Pass phrase 2 is blank.
ATC2366	Pass phrase 1 and 2 are not the same.
ATC2367	ASCII conversion option must be `1` for `Yes` or `2` for `No`.
ATC2368	PGP encryption error for session during IFS copy.
ATC2369	Email notification must be 1, 2, 3 or 4.
ATC2370	At least one email address is required.
ATC2371	Reply-to email address is blank.
ATC2372	Email subject is blank.
ATC2373	Error retrieving SMTP email option.
ATC2374	Email notification is not active.
ATC2375	Email notification for failed sessions is not active.
ATC2376	Email notification for successful sessions is not active.
ATC2377	Error encountered sending email notification.
ATC2378	Unmonitored error attempting to send email notifcation for FTP session.
ATC2379	Exit program is blank.
ATC2380	Exit program library is blank.
ATC2381	Encryption option is invalid.
ATC2382	Pass phrase is blank.
ATC2383	Pass phrases do not match.
ATC2384	Invalid ASCII conversion option.
ATC2385	Key ring file is blank.
ATC2386	Error encountered sending SMTP email notification to .
ATC2387	Special value must be `*ANY`.
ATC2388	Rename user exit program is blank.

GID	TEXT
ATC2389	Rename user exit library is blank.
ATC2390	Record for FTP definition does not exist.
ATC2391	Unable to retrieve FTP definition. Record may be in use.
ATC2392	FTMIPCHG: Unmonitored exception in program. See job log for details.
ATC2393	File Action is blank.
ATC2394	Library name is blank.
ATC2395	Invalid status. Status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC2396	I/O error on file. Update not performed.
ATC2397	File action not found.
ATC2398	I/O error updating the status. Record not changed.
ATC2400	Alliance FTP Manager notification message follows:
ATC2401	
ATC2402	The previous message was sent by Alliance FTP Manager.
ATC2403	Depending on the nature of the error encountered by FTP Manager,
ATC2404	and the nature of your use of Alliance FTP Manager,
ATC2405	your application may need immediate attention.
ATC2406	See the Alliance FTP Manager installation and user guide for more
ATC2407	information.
ATC2408	
ATC2409	Directory path is blank.
ATC2410	AN0300C: Unmonitored exception in program. See job log. Continuing after delay.
ATC2411	Spool file option must be `1` for **`Yes`** or `2` for **`No`**.

GID	TEXT
ATC2412	Copy to directory option must be `1` for `Yes` or `2` for `No`.
ATC2413	Spool file processing must be enabled for this option.
ATC2414	Directory name is blank.
ATC2415	User exit option must be `1` for `Yes` or `2` for `No`.
ATC2416	User exit program name is blank.
ATC2417	User exit program library is blank.
ATC2418	AN0300C: Unable to retrieve spool file options. Contact programming support.
ATC2419	AN0310C: Error copying spool file to user directory. See job log for details. Co
ATC2429	Output queue definition record / not found. Spool file not processed.
ATC2430	AN0300C: Error processing spool file number for job //. Spool file moved to b
ATC2431	AN0310C: Unmonitored exception in program. See job log. Continuing after delay.
ATC2432	AN0310C: Error copying spool file to work file. Spool file not processed.
ATC2433	AN0320C: User exit program / not found or not authorized. Spool file not process
ATC2434	AN0320C: Error calling user exit program /. See job log for details. Spool file
ATC2435	AN0320C: User exit program / returned error. Contact programming support.
ATC2436	AN0320C: Unmonitored exception in program. See job log for details. Spool file n
ATC2437	AN0300C: Error moving spool file number for job // to backup output queue. See
ATC2438	AN0300C: Error deleting spool file number for job // after processing. See job

GID	TEXT
ATC2439	AN0330C: FTP session returned error code or spool file. See FTP history for d
ATC2440	AN0330C: Unmonitored exception in program. See job log. Continuing after delay.
ATC2441	AN0340C: Error copying spool file to work file. Spool file not processed.
ATC2442	AN0340C: Error adding HTML header source. See job log for details.
ATC2443	AN0340C: Error adding HTML trailer source. See job log for details.
ATC2444	AN0400C: Error in FTP session. See FTP history for details.
ATC2445	AN0400C: Error in QUSRSPLA retrieving spool file attributes.
ATC2446	AN0400C: Error in spool file. Not AFP spool file type.
ATC2447	AN0400C: Error creating 1st user space with QUSCRTUS.
ATC2448	AN0400C: Error creating AFP resources list with QGSLRSC.
ATC2449	AN0400C: Error retrieving AFP resources list with QUSRTVUS.
ATC2450	AN0400C: Error opening spool file with QSPOPNSP.
ATC2451	AN0400C: Error creating 2nd user space with QUSCRTUS.
ATC2452	AN0400C: Error on 1st get spool file data with QSPGETSP.
ATC2453	AN0400C: Error on spool data user space retrieve with QUSRTVUS.
ATC2454	AN0400C: Error on create user space for AFP resource extract with QUSCRTUS.
ATC2455	AN0400C: Error on copy of AFP resource with QGSCPYRS.
ATC2456	AN0400C: Error on user space retrieve for AFP resource with QUSRTVUS.
ATC2457	AN0400C: Error on FTP session of AFP resource with FTMEXECI.
ATC2458	AN0401C: Error retrieving spool file type with QUSRSPLA.

GID	TEXT
ATC2459	AN0350C: Error attempting to retrieve spool file type. Spool file not processed
ATC2460	AN0402C: Error in spool file. Not SCS spool file type.
ATC2461	AN0402C: Error in QUSRSPLA retrieving spool file attributes.
ATC2462	AN0402C: Error opening spool file with QSPOPNSP.
ATC2463	AN0402C: Error creating 2nd user space with QUSCRTUS.
ATC2464	AN0402C: Error on 1st get spool file data with QSPGETSP.
ATC2465	AN0402C: Error on spool data user space retrieve with QUSRTVUS.
ATC2466	AN0402C: Error in FTP session. See FTP history for details.
ATC2467	AN0350C: Error attempting to process AFPDS spool file. See job log for details.
ATC2468	AN0350C: Error attempting to process SCS spool file. See job log for details.
ATC2469	AN0350C: Unmonitored exception in program. See job log for details. Spool file n
ATC2470	AN0400C: Error opening file ANRSRC.
ATC2471	AN0351C: Error copying spool file to work file. Spool file not processed.
ATC2472	AN0351C: FTP session returned error code for spool file . See FTP history for d
ATC2473	AN0351C: Unmonitored exception in program. See job log. Continuing after delay.
ATC2474	Scan interval must be in the range of 00001 to 99999.
ATC2475	Error in Alliance scheduled job for FTP definition. Abnormal end of job.
ATC2476	Alliance scheduled job for FTP definition returned error code. FTP session may
ATC2477	Unmonitored exception in Alliance FTP Manager scheduled job for FTP definition .

GID	TEXT
ATC2478	Library scan option must be `1` for `Yes` or `2` for `No`.
ATC2479	Directory scan option must be `1` for `Yes` or `2` for `No`.
ATC2480	AN0300C: Error sending spool file nbr , job //. Spool file not sent via Email.
ATC2481	AN0370C: Unmonitored exception in program. See job log. Continuing after delay.
ATC2482	AN0370C: Error retrieving output queue definition for spool file.
ATC2483	AN0371C: Error sending spool file via email as text attachment.
ATC2484	AN0371C: Unmonitored exception in program. see job log.
ATC2485	AN0371C: Error calling API211 for email delivery.
ATC2486	AN0371C: Error sending spool file via email as HTML attachment.
ATC2487	AN0371C: Error sending spool file via email as RTF attachment.
ATC2488	AN0371C: Error sending spool file via email as PDF attachment.
ATC2489	AN0372C: Unmonitored exception in program. see job log.
ATC2490	AN0372C: Error calling API207 for email delivery.
ATC2491	AN0373C: Error calling API208 for email delivery.
ATC2492	AN0373C: Unmonitored exception in program. see job log.
ATC2493	AN0374C: Error calling API205 for email delivery.
ATC2494	AN0374C: Error calling API209 for email delivery.
ATC2495	AN0374C: Error calling API200 for email delivery.
ATC2496	AN0374C: Unmonitored exception in program. see job log.
ATC2497	Add or replace option is invalid.
ATC2498	Data conversion option must be `1` , `2` or `3` .

GID	TEXT
ATC2499	Table name is required.
ATC2500	Table library is required.
ATC2501	Stream file code page option must be `1`, `2` or `3`.
ATC2502	Stream file code page must be in the range of 00001 to 32767.
ATC2503	CCSID option must be `1` or `2`.
ATC2504	CCSID must be in the range of 00001 to 65533.
ATC2505	End of line option must be in the range of `1` to `6`.
ATC2506	Tab expansion must be `1` for `Yes` or `2` for `No`.
ATC2507	FTMUSER: Unmonitored exception in program. See job log for details.
ATC2508	Invalid start time hour.
ATC2509	Invalid start time minutes.
ATC2510	Invalid end time hour.
ATC2511	Invalid end time minutes.
ATC2512	Library scan outside of start/end time, scan not processed.
ATC2513	Start time is later than end time.
ATC2514	File action for library scan is outside of start and end times.
ATC2515	File is empty.
ATC2516	Error opening file.
ATC2517	FTP definition not found for pass phrase.
ATC2518	FTMPGPUSER: Unmonitored exception in program. See job log for details.
ATC2519	Option must be `1` for `Yes` or `2` for `No`.
ATC2520	PGP configuration was not updated.
ATC2521	PGP configuration updated.
ATC2522	Action cancelled. PGP configuration not updated.

GID	TEXT
ATC2523	ERROR, unmonitored exception in program. See job log for details.
ATC2524	PGP session failed. See PGP log and job log for more information.
ATC2525	PGP session successful.
ATC2526	Batch option changed to `*YES` .
ATC2527	Starting PGP encryption …
ATC2528	Starting PGP decryption …
ATC2529	Starting PGP signing …
ATC2530	IFS path name is blank.
ATC2531	Translation table name is blank.
ATC2532	Translation table library is blank.
ATC2533	Library name does not exist.
ATC2534	Error creating file. See job log for details.
ATC2535	Error adding member to file.
ATC2536	AN7130: Unmonitored exception in program. See job log for details.
ATC2537	Unable to open output file.
ATC2538	Error writing data to IBM i file.
ATC2539	File name is blank.
ATC2540	Library is blank.
ATC2541	Member name is blank.
ATC2542	Library does not exist, or not authorized.
ATC2543	Record length is blank.
ATC2544	Invalid record length. Less that 00001 or greater than 32766.
ATC2545	FTMIFS400: Error calling program AN6062E. Contact programming support.

GID	TEXT
ATC2546	FTMIFS400: Unmonitored error in IFS to DB2/400 conversion job. See job log for d
ATC2547	FTMIFSTRAN: Unmonitored error in IFS to DB2/400 conversion job. See job log for
ATC2548	Output file library does not exist.
ATC2549	Error creating output file.
ATC2550	Error creating member in output file.
ATC2551	Output created in file.
ATC2552	Unmonitored exception processing command request.
ATC2553	Starting PGP key delete …
ATC2554	PGP key delete successful.
ATC2555	PGPKEYDEL: Unmonitored exception in program. See job log for details.
ATC2556	Starting PGP key add …
ATC2557	PGP key add successful.
ATC2558	PGPKEYADD: Unmonitored exception in program. See job log for details.
ATC2559	Starting PGP key sign …
ATC2560	PGP key sign successful.
ATC2561	PGPKEYSIGN: Unmonitored exception in program. See job log for details.
ATC2562	UNIX variable size option must be 1 for Yes or 2 for No.
ATC2563	ERROR: Email notification to <> failed.
ATC2564	AN0375C: Error retrieving output queue detail. Spool file not processed.
ATC2565	AN0375C: Error retrieving output queue definition for spool file.
ATC2566	AN0375C: Error sending spool file via email as text attachment.

GID	TEXT
ATC2567	AN0375C: Error sending spool file via email as HTML attachment.
ATC2568	AN0375C: Error sending spool file via email as RTF attachment.
ATC2569	AN0375C: Error sending spool file via email as PDF attachment.
ATC2570	AN0375C: Unmonitored exception in program. See job log. Continuing after delay.
ATC2571	Auto scan outside of start/end time, scan not processed.
ATC2572	ERROR, unmonitored exception in AES program. See job log for details.
ATC2573	AES encryption session successful.
ATC2574	AES decryption session successful.
ATC2575	ERROR: Unmonitored exception in AES decription session. See job log for details.
ATC2576	Output file is blank.
ATC2577	AN0180C: Internal error calling custom program **AN6082E** .
ATC2578	AN0180C: program **AN6066E** returned error code .
ATC2579	AN0180C: Unmonitored error in program.
ATC2580	Auto-scan definition not found.
ATC2581	Auto-scan definition not found for update operation.
ATC2582	Invalid put/get option for auto-scan update.
ATC2583	Error updating job information for auto-scan . Job is continuing.
ATC2584	Error retrieving scan definition, option not processed.
ATC2585	Scan definition is not active, option not processed.
ATC2586	Job is not currently active, job not ended.
ATC2587	Job has already ended.

GID	TEXT
ATC2588	Error attempting to end job. See job log for details.
ATC2589	Error: Unmonitored exception while attempting to end job.
ATC2590	Error calling program to end the job. See job lot for details.
ATC2591	End job submitted.
ATC2592	At least one message queue must be defined.
ATC2593	Provide both processing program name and library name.
ATC2594	Email distribution list not found.
ATC2595	Program call error calling email program **API211** . See job log for details.
ATC2596	Email API program AN0211 returned an error. Message probably not delivered.
ATC2597	AN0371C: Error calling AN0116 for email list delivery.
ATC2598	AN0372C: Error calling AN0118 for email list delivery.
ATC2599	Error in BellSouth Autoscan retrieve on attempt to set record length.
ATC2600	Command **RUNSSNRPT** completed successfully.
ATC2601	ERROR in command **RUNSSNRPT** . See job log for details.
ATC2602	Log on exit point option must be **1** for **Yes** or **2** for **No** .
ATC2603	Log on exit point program is blank.
ATC2604	Log on exit point program library is blank.
ATC2605	Request exit point option must be **1** for **Yes** or **2** for **No** .
ATC2606	Request exit point program is blank.
ATC2607	Request exit point program library is blank.
ATC2608	ERROR: Unmonitored exception in program **CVTEXITL** .
ATC2609	ERROR: Unmonitored exception in program **CVTEXITR** .
ATC2610	Error sending FTMCCC clear channel command.
ATC2611	ERROR: Unmonitored exception in program **CVTEXECL** .

GID	TEXT
ATC2612	ERROR: Unmonitored exception in program **CVTEXEC4** .
ATC2613	BellSouth communcations session successful.
ATC2614	File name is blank.
ATC2615	Library name is blank.
ATC2616	Library does not exist, or not authorized.
ATC2617	File does not exist, or not authorized.
ATC2618	Member does not exist in file, or not authorized.
ATC2619	Error creating work library for file conversion.
ATC2620	Error creating work file for conversion. See job log for details.
ATC2621	Table and library are both required for data conversion.
ATC2622	I/O error reading record from database file.
ATC2623	Error, record length greater than 9999 bytes.
ATC2624	Error, record length greater than 9999 bytes.
ATC2625	Error converting data using a table.
ATC2626	Error renaming file for conversion.
ATC2627	Error moving file to work library.
ATC2628	Error renaming work file to original name.
ATC2629	Error renaming work file member to original member name.
ATC2630	Error moving converted work file to original library.
ATC2631	Conversion program **FTMTRAN** completed normally.
ATC2632	ERROR: unmonitored exception in program **FTMTRAN** .
ATC2633	File name too long for copy operation.
ATC2634	Error opening input database file.
ATC2635	Error opening output stream file.
ATC2636	Error writing data to stream file.

GID	TEXT
ATC2637	No records in database file.
ATC2638	File name is blank.
ATC2639	Library name is blank.
ATC2640	Member name is blank.
ATC2641	File, library or member does not exist, or not authorized.
ATC2642	Conversion table does not exist, or not authorized.
ATC2643	IFS file name is blank.
ATC2644	Error calling stream file copy program **AN6076E** . See job log for details.
ATC2645	FTMEDICPY completed successfully.
ATC2646	Unmonitored exception in API program **FTMEDICPY** . See job log for details.
ATC2647	Job submit failed with error code . See job log for details.
ATC2648	Unmonitored exception in job. Report not submitted.
ATC2649	Synchronize option must be **1** for **Yes** or **2** for **No** .
ATC2650	Synchronized access control failed, skipping library.
ATC2651	Synchronized access to library started.
ATC2652	Synchronize option must be **1** for **Yes** or **2** for **No** .
ATC2653	Receive library is required if Synchronize Access if Yes.
ATC2654	Synchronized access control failed, skipping library.
ATC2655	Synchronized access to library started.
ATC2656	Error remoking authority for PGP user. See job log for more information.
ATC2657	Command **FTMSCANLIB** completed successfully.
ATC2658	ERROR in command **FTMSCANLIB** . See job log for details.
ATC2659	Scan directory definition is not active. Directory skipped.
ATC2660	Command **FTMSCANDIR** completed successfully.

GID	TEXT
ATC2661	ERROR in command **FTMSCANDIR** . See job log for details.
ATC2662	AES key must be in hexadecimal notation.
ATC2663	The AES key value is too long.
ATC2664	The key length must be 32, 48 or 64 hexadecimal digits.
ATC2665	The input file could not be opended.
ATC2666	The output file could not be opened.
ATC2667	IFS file is blank.
ATC2668	Pass phrase, AES key, or hex string is required.
ATC2669	Enter only one of pass phrase, AES key, or hex string.
ATC2670	Pass phrase character code must be ***EBCDIC** or ***ASCII** .
ATC2671	Copy from database file must be *YES or *NO.
ATC2672	If copy from database is specified, the file name is required.
ATC2673	If copy from database is specified, the file library name is required.
ATC2674	If copy from database is specified, the file member name is required.
ATC2675	Copy from library does not exist, or not authorized.
ATC2676	Copy from file does not exist, or not authorized.
ATC2677	Copy from file member does not exist, or not authorized.
ATC2678	Not authorized to copy from file or member.
ATC2679	Conversion table does not exist, or not authorized.
ATC2680	Error calling internal routine AN6075E to copy file.
ATC2681	Starting **CPYTOSTMF** with new **ENDLINFMT** .
ATC2682	Starting **CPYTOSTMF 2** with new **ENDLINFMT** .
ATC2683	Error in AES encryption. File not encrypted.
ATC2684	AES encryption session successful.

GID	TEXT
ATC2685	Input string is longer than the maximum 2048 bytes.
ATC2686	AES encryption extension of .END not found.
ATC2687	IFS file name to decrypt is blank.
ATC2688	Pass phrase or hex string is required.
ATC2689	Enter pass phrase or hex string, but not both.
ATC2690	Pass phrase character code must be **`*EBCDIC`** or **`*ASCII`**.
ATC2691	Invalid CCSID value. Must be *DFT or a valid CCSID number.
ATC2692	AN6070E: Error in CCSID conversion.
ATC2693	Remove nulls option must be **`1`** for **`Yes`** or **`2`** for **`No`**.
ATC2694	Error removing nulls from file /.
ATC2695	AN0120C: Error removing nulls in file in scan library .
ATC2696	Clear email option must be **`1`** for **`Yes`** or **`2`** for **`No`**.
ATC2697	IFS file name contains the .PGP extension. Use a name without this extension.
ATC2698	The passed in data length was less than 1 or greater then the 32,767 limit.
ATC2699	Bad AES key length. The key length must be 32 for 256 bit encryption.
ATC2700	Password was too long. A valid password must be less then 128 bytes
ATC2701	Password salt too long. A valid salt password must be 16 bytes in length
ATC2702	UTC not available to generate random seed from system time
ATC2703	Seed value is not valid.
ATC2704	Password verified is too long. It must be 8 bytes.
ATC2705	Bad AES key length. It must be 32 for 256 bit encryption.
ATC2706	Password too long. The password must be 128 bytes or less in length.

GID	TEXT
ATC2707	Password salt too long. A valid salt password must be 16 bytes in length.
ATC2708	Password verifier is too long. The password verified must be 8 bytes.
ATC2709	Invalid password used to encrypt or decrypt.
ATC2710	Encountered an error during password verification initialization.
ATC2711	Encountered an error during password verification initialization.
ATC2712	A pass phrase must be at least 16 bytes in length.
ATC2713	A pass phrase must be at least 16 bytes in length.
ATC2714	Encountered an error writing decrypted text to the output file.
ATC2715	Encountered an error reading encrypted information from the input file.
ATC2716	Encountered an error decrypting file.
ATC2717	The input file could not be opened.
ATC2718	The output file could not be opened.
ATC2719	Pass phrase must be less then 32 characters, including blanks.
ATC2720	The key value is too long.
ATC2721	The key length must be 32, 48 or 64 hexadecimal digits.
ATC2722	Error creating a 64 character hexadecimal sequence.
ATC2723	Encountered an error getting start address.
ATC2724	Encountered an error opening source file.
ATC2725	Encountered an error seeking to start address.
ATC2726	Encountered an error creating new file.
ATC2727	Encountered an error during information initialization.
ATC2728	Encountered an error opening source file.

GID	TEXT
ATC2729	Encountered an error seeking signature.
ATC2730	Password Verification Failed.
ATC2731	Unable to open main Windows executable template.
ATC2732	Unable to create new Windows executable.
ATC2733	Unable to open newly created executable for appending.
ATC2734	Unable to open file to be attached.
ATC2735	Unable to execute ftell().
ATC2736	Conversion to ascii failed.
ATC2737	Conversion to ascii failed.
ATC2739	AES key file could not be opened.
ATC2740	AES key not found in key file.
ATC2741	Error opening AES audit trail file AEHIST
ATC2742	Error writing AES audit trail record AEHIST
ATC2743	Unable to load library aesctr.dll from the Java_allianceAesCtr_crypt256Fs functi
ATC2744	Unable to load function crypt256Fs from the Java_allianceAesCtr_crypt256Fs funct
ATC2745	Unable to load library aesctr.dll from the Java_allianceAesCtr_createSalt functi
ATC2746	Unable to load function createSalt from the Java_allianceAesCtr_createSalt funct
ATC2747	Unable to load library aesctr.dll from the Java_allianceAesCtr_crtVer256 functio
ATC2748	Unable to load function crtVer256 from the Java_allianceAesCtr_crtVer256 functio
ATC2750	ERROR, unmonitored exception in program. See job log for details.
ATC2751	FTP definition uses ASCII translation, translation not allowed.

GID	TEXT
ATC2752	SSL FTP option must be `1` for `Yes` or `2` for `No` .
ATC2753	Select SSL or standard FTP transfer, but not both.
ATC2754	User ID is blank.
ATC2755	Password is blank.
ATC2756	SSL application ID is blank.
ATC2757	SSL retry value must be in the range of `0` to `99` .
ATC2758	SSL application logging must be 1, 2 or 3.
ATC2759	Select GXS, IBM, or SSL option.
ATC2760	Cannot select Submit Job option with SSL FTP network interface. (***HELP***)
ATC2761	ERROR calling SSL FTP communications program for file .
ATC2762	AN0441R SSL: Error initializing FTP environment. Job cancelled.
ATC2763	AN0441R SSL: Error initializing the application log.
ATC2764	AN0441R SSL: Error setting the logging level.
ATC2765	AN0441R SSL: An error occurred setting the FTP environment for SSL support.
ATC2766	AN0441R SSL: An error occurred setting the SSL Application ID for the session.
ATC2767	AN0441R SSL: Unable to open FTP site.
ATC2768	AN0441R SSL: FTP open operation returned error code , text .
ATC2769	AN0441R SSL: Unable to send the SSL authorization request.
ATC2770	AN0441R SSL: FTP AUTH operation returned error code , text .
ATC2771	AN0441R SSL: Unable to send the Protection Buffer size.
ATC2772	AN0441R SSL: FTP PBSZ operation returned error code , text .

GID	TEXT
ATC2773	AN0441R SSL: Unable to send the Protection Type.
ATC2774	AN0441R SSL: FTP PROT operation returned error code , text .
ATC2775	AN0441R SSL: Unable to send the user ID to GXS.
ATC2776	AN0441R SSL: FTP USER operation returned error code , text .
ATC2777	AN0441R SSL: Unable to send the IBM password.
ATC2778	AN0441R SSL: FTP PASS operation returned error code , text .
ATC2779	AN0441R SSL: Unable to change directory.
ATC2780	AN0441R SSL: FTP CWD operation returned error code , text .
ATC2781	AN0441R SSL: Unable to set for binary transfer.
ATC2782	AN0441R SSL: FTP BINARY operation returned error code , text .
ATC2783	AN0441R SSL: Unable to set passive mode.
ATC2784	AN0441R SSL: FTP PASV operation returned error code , text .
ATC2785	AN0441R SSL: Unable to send file to IBM network.
ATC2786	AN0441R SSL: FTP STOR operation returned error code , text .
ATC2787	FTP server name is blank.
ATC2788	I/O error on file read for EDI unwrap, file may be locked.
ATC2789	Error, input file for EDI unwrap is empty.
ATC2790	Error in EDI unwrap. Record length is less than 106.
ATC2791	I/O error on file read for EDI unwrap, file may be locked.
ATC2792	Error in EDI unwrap, record length is zero.
ATC2793	EDI unwrap option must be `1` for **`Yes`** or `2` for **`No`** .

GID	TEXT
ATC2794	Unwrap record length must be in the range of 00106 to 00256.
ATC2795	AN0120C: Error creating EDI file in scan library .
ATC2796	AN0120C: Error converting EDI file in scan library .
ATC2797	AN0120C: Error renaming EDI unwrap file in scan library .
ATC2798	AN0120C: Error moving EDI unwrap file in scan library .
ATC2799	Back up file name set to /.
ATC2800	AN0120C: Error copying EDI unwrap file in scan library .
ATC2801	AN0120C: Error removing member in EDI file in scan library .
ATC2802	Back up file name set to /.
ATC2803	FTP server name is blank.
ATC2804	SSL FTP user ID is blank.
ATC2805	SSL FTP password is blank.
ATC2806	SSL application ID is blank.
ATC2807	Session retries must be in the range of 00 to 99.
ATC2808	Logging option must be 1, 2 or 3.
ATC2809	Receive library and directory are blank.
ATC2810	AN0605C: The FTP SSL receive program encountered an error.
ATC2811	AN0605C: Normal shutdown requested for FTP Manager FTP SSL auto scan.
ATC2812	AN0605C: ERROR: Unmonitored exception in FTP Manager FTP SSL auto scan.
ATC2813	AN0442R SSL: Error initializing FTP environment. Job cancelled.
ATC2814	AN0442R SSL: Error initializing the application log.
ATC2815	AN0442R SSL: Error setting the logging level.

GID	TEXT
ATC2816	AN0442R SSL: An error occurred setting the FTP environment for SSL support.
ATC2817	AN0442R SSL: An error occurred setting the SSL Application ID for the session.
ATC2818	AN0442R SSL: Unable to open FTP site.
ATC2819	AN0442R SSL: FTP open operation returned error code , text .
ATC2820	AN0442R SSL: Unable to send the SSL Auth command.
ATC2821	AN0442R SSL: FTP AUTH operation returned error code , text .
ATC2822	AN0442R SSL: Unable to send the SSL PBSZ command.
ATC2823	AN0442R SSL: FTP PBSZ operation returned error code , text .
ATC2824	AN0442R SSL: Unable to send the SSL PROT command.
ATC2825	AN0442R SSL: FTP PROT operation returned error code , text .
ATC2826	AN0442R SSL: Unable to send the user ID.
ATC2827	AN0442R SSL: FTP USER operation returned error code , text .
ATC2828	AN0442R SSL: Unable to send the password.
ATC2829	AN0442R SSL: FTP PASS operation returned error code , text .
ATC2830	AN0442R SSL: Unable to change directory.
ATC2831	AN0442R SSL: FTP CD operation returned error code , text .
ATC2832	AN0442R SSL: Unable to set passive mode.
ATC2833	AN0442R SSL: FTP PASV operation returned error code , text .
ATC2834	AN0442R SSL: Unable to create file list.
ATC2835	AN0442R SSL: FTP NLST operation returned error code , text .

GID	TEXT
ATC2836	AN0442R SSL: Unable to set binary mode for transfer.
ATC2837	AN0442R SSL: FTP BINARY operation returned error code , text .
ATC2838	AN0442R SSL: Unable to set passive mode.
ATC2839	AN0442R SSL: FTP PASV operation returned error code , text .
ATC2840	AN0442R SSL: Unable to set local name format to 0.
ATC2841	AN0442R SSL: FTP NAMEFMT operation returned error code , text .
ATC2842	AN0442R SSL: Unable to retrieve file from IBM.
ATC2843	AN0442R SSL: FTP GET operation returned error code , text .
ATC2844	AN0442R SSL: Unable to delete file from server.
ATC2845	AN0442R SSL: FTP DELETE operation returned error code , text .
ATC2846	AES key description is blank.
ATC2847	AES key name is blank.
ATC2848	AES key already exists.
ATC2849	AES password is blank.
ATC2850	Password verification is blank.
ATC2851	Password does not match verification password. Please re-enter.
ATC2852	Error encrypting pass phrase.
ATC2853	Error encrypting salt phrase.
ATC2854	Error encrypting password verifier.
ATC2855	Not authorized to function.
ATC2856	Error creating AES key file backup.
ATC2857	Error: Unmonitored exception when saving AES key file.

GID	TEXT
ATC2858	Error: Unable to open input IFS file.
ATC2859	Error: Unable to open output IFS file.
ATC2860	Error: Unable to delete IFS file.
ATC2861	Error: Unable to rename temporary file.
ATC2862	Error: Input file name is too long. Must be less than 256 characters.
ATC2863	Starting conversion of ASCII armor file to *CRLF end of line characters.
ATC2864	Error calling program AN6079E for ASCII Armor *CRLF option.
ATC2865	Error processing *CRLF option for ASCII Armor file.
ATC2866	End of line option must be 1 for LF or 2 for CR/LF.
ATC2867	PGP ASCII Armor CR/LF error for session .
ATC2868	PGP ASCII Armor CR/LF error for session .
ATC2869	Record length greater than 9999.
ATC2870	Error on file read. Record may be allocated.
ATC2871	No records found in file.
ATC2872	Resubmit option must be `1` for `Yes` or `2` for `No`
ATC2873	Password is blank.
ATC2874	Executable file name is blank.
ATC2875	Unmonitored exception calling program AS400SFX to create executable file.
ATC2876	AES create self-decrypting archive successful.
ATC2877	ERROR: unmonitored exception in AES self-decrypting archive program.
ATC2878	Error installing AES IFS files. See job log for details.
ATC2879	AES IFS files installed.

GID	TEXT
ATC2880	AES installation option cancelled.
ATC2881	ERROR, umonitored exception in program. See job log for details.
ATC2882	Alliance AES files not installed. Press ***HELP***.
ATC2883	US Bank option must be `1` for `Yes` or `2` for `No`.
ATC2884	FTP server name is blank.
ATC2885	Select US Bank SSL or standard FTP transfer, but not both.
ATC2886	User ID is blank.
ATC2887	Password is blank.
ATC2888	SSL application ID is blank.
ATC2889	Retry value must be in the range of `0` to `99`.
ATC2890	Application logging must be 1, 2 or 3.
ATC2891	Select GXS, IBM, US Bank, or SSL FTP option.
ATC2892	Cannot select Submit Job option with US Bank network interface. (***HELP***)
ATC2893	Invalid port number.
ATC2894	AN0442R US BANK: Error calling program. See job log for details.
ATC2895	AN0443R US Bank: Error initializing FTP environment. Job cancelled.
ATC2896	AN0443R US Bank: Error initializing the application log.
ATC2897	AN0443R US Bank: Error setting the logging level.
ATC2898	AN0443R US Bank: An error occurred setting the FTP environment for SSL support.
ATC2899	AN0443R US Bank: An error occurred setting the SSL Application ID for the sessio
ATC2900	AN0443R US Bank: Unable to open FTP site.

GID	TEXT
ATC2901	AN0443R US Bank: FTP open operation returned error code , text .
ATC2902	AN0443R US Bank: Unable to send the SSL authorization request.
ATC2903	AN0443R US Bank: FTP AUTH operation returned error code , text .
ATC2904	AN0443R US Bank: Unable to send the Protection Buffer size.
ATC2905	AN0443R US Bank: FTP PBSZ operation returned error code , text .
ATC2906	AN0443R US Bank: Unable to send the Protection Type.
ATC2907	AN0443R US Bank: FTP PROT operation returned error code , text .
ATC2908	AN0443R US Bank: Unable to send the user ID to GXS.
ATC2909	AN0443R US Bank: FTP USER operation returned error code , text .
ATC2910	AN0443R US Bank: Unable to send the IBM password.
ATC2911	AN0443R US Bank: FTP PASS operation returned error code , text .
ATC2912	AN0443R US Bank: Unable to change directory.
ATC2913	AN0443R US Bank: FTP CWD operation returned error code , text .
ATC2914	AN0443R US Bank: Unable to set for binary transfer.
ATC2915	AN0443R US Bank: FTP BINARY operation returned error code , text .
ATC2916	AN0443R US Bank: Unable to set passive mode.
ATC2917	AN0443R US Bank: FTP PASV operation returned error code , text .
ATC2918	AN0443R SSL: Unable to send file to US Bank.
ATC2919	AN0443R SSL: FTP STOR operation for US Bank returned error code , text .

GID	TEXT
ATC2920	AN0443R US Bank: Error sending Site command for US Bank.
ATC2921	AN0443R US Bank: FTP SITE operation returned error code , text .
ATC2922	AN0443R US Bank: Error sending TYPE command for US Bank.
ATC2923	AN0443R US Bank: FTP TYPE operation returned error code , text .
ATC2924	AN0443R US Bank: Error setting PORT number for US Bank.
ATC2925	AN0444R SSL: Error initializing FTP environment for US Bank. Job cancelled.
ATC2926	AN0444R SSL: Error initializing the application log for US Bank.
ATC2927	AN0444R SSL: Error setting the logging level for US Bank.
ATC2928	AN0444R SSL: An error occurred setting the FTP environment for US Bank.
ATC2929	AN0444R SSL: An error occurred setting the SSL Application ID for US Bank.
ATC2930	AN0444R SSL: Unable to open FTP site for US Bank.
ATC2931	AN0444R SSL: FTP open operation for US Bank returned error code , text .
ATC2932	AN0444R SSL: Unable to send the SSL Auth command to US Bank.
ATC2933	AN0444R SSL: FTP AUTH operation for US Bank returned error code , text .
ATC2934	AN0444R SSL: Unable to send the SSL PBSZ command to US Bank.
ATC2935	AN0444R SSL: FTP PBSZ operation for US Bank returned error code , text .
ATC2936	AN0444R SSL: Unable to send the SSL PROT command to US Bank.

GID	TEXT
ATC2937	AN0444R SSL: FTP PROT operation for US Bank returned error code , text .
ATC2938	AN0444R SSL: Unable to send the user ID to US Bank.
ATC2939	AN0444R SSL: FTP USER operation for US Bank returned error code , text .
ATC2940	AN0444R SSL: Unable to send the password to US Bank.
ATC2941	AN0444R SSL: FTP PASS operation for US Bank returned error code , text .
ATC2942	AN0444R SSL: Unable to change directory for US Bank.
ATC2943	AN0444R SSL: FTP CD operation for US Bank returned error code , text .
ATC2944	AN0444R SSL: Unable to set passive mode for US Bank.
ATC2945	AN0444R SSL: FTP PASV operation for US Bank returned error code , text .
ATC2946	AN0444R SSL: Unable to create file list for US Bank.
ATC2947	AN0444R SSL: FTP NLST operation for US Bank returned error code , text .
ATC2948	AN0444R SSL: Unable to set binary mode for US Bank transfer.
ATC2949	AN0444R SSL: FTP BINARY operation for US Bank returned error code , text .
ATC2950	AN0444R SSL: Unable to set passive mode for US Bank.
ATC2951	AN0444R SSL: FTP PASV operation for US Bank returned error code , text .
ATC2952	AN0444R SSL: Unable to set local name format to 0 for US Bank.
ATC2953	AN0444R SSL: FTP NAMEFMT operation for US Bank returned error code , text .
ATC2954	AN0444R SSL: Unable to retrieve file from US Bank.
ATC2955	AN0444R SSL: FTP GET operation for US Bank returned error code , text .

GID	TEXT
ATC2956	AN0444R SSL: Unable to delete file from US Bank server.
ATC2957	AN0444R SSL: FTP DELETE operation for US Bank returned error code , text .
ATC2958	AN0444R US Bank: Error setting PORT number for US Bank.
ATC2959	AN0444R SSL: Unable to send the SITE comman to US Bank.
ATC2960	AN0444R SSL: SITE operation for US Bank returned error code , text .
ATC2961	AN0444R SSL: Unable to set TYPE AN for US Bank.
ATC2962	AN0444R SSL: FTP TYPE operation for US Bank returned error code , text .
ATC2963	ERROR retrieving FTP scan directory optionsfor US Bank. See job log for details.
ATC2964	AN0606C: The US BANK receive program encountered an error.
ATC2965	AN0606C: Normal shutdown requested for FTP Manager US BANK auto scan.
ATC2966	AN0606C: ERROR: Unmonitored exception in FTP Manager US BANK auto scan.
ATC2967	Scan definition not found.
ATC2968	FTP server name is blank.
ATC2969	SSL FTP user ID is blank.
ATC2970	SSL FTP password is blank.
ATC2971	SSL application ID is blank.
ATC2972	Session retries must be in the range of `00` to `99` .
ATC2973	Logging option must be `1` , `2` or `3` .
ATC2974	Receive library is blank.
ATC2975	Port number must be in the range of `00001` to `65535` .
ATC2976	FTP Auto Scan job for US Bank started.

GID	TEXT
ATC2977	Error starting FTP Auto Scan for scan.
ATC2979	IFS file name too long. Maximum of 256 bytes is supported.
ATC2980	Unable to open IFS file. The file does not exist, or not authorized.
ATC2981	Empty file detected, starting empty file processing.
ATC2982	Translation table is required.
ATC2983	AES encryption not installed.
ATC2984	AES self-decrypting archive support not installed.
ATC2985	AES option must be `1` for `Yes` or `2` for `No`.
ATC2986	AES option requires either an AES key name or pass phrase.
ATC2987	AES option requires AES key name or pass phrase, but not both.
ATC2988	AES key name not found in AES key database.
ATC2989	AES self-decrypting archive option must be `1` for `Yes` or `2` for `No`.
ATC2990	AES self-decrypting archive file extension is blank.
ATC2991	Pass phrase code must be `1` for `ASCII` or `2` for `EBCDIC`.
ATC2992	Convert to ASCII must be `1` for `Yes` or `2` for `No`.
ATC2993	Table name is blank.
ATC2994	Table library is blank.
ATC2995	Invalid end of line option.
ATC2996	Trim traling blanks option must be `1` for `Yes` or `2` for `No`.
ATC2997	Specify PGP encryption or AES encryption, but not both.
ATC2998	AES key not found in key database.
ATC2999	Invalid AES pass phrase. Pass phrase must not be longer than 32 bytes.
ATC3000	Starting AES self-decrypting archive processing.

GID	TEXT
ATC3001	AES self-decrypting archive processing complete.
ATC3002	AES encryption product license error. Please contact your software vendor.
ATC3003	Invalid AES encryption option.
ATC3004	AES option requires AES key name or pass phrase.
ATC3005	Enter AES key name or pass phrase, but not both.
ATC3006	AES key not found in AES key file.
ATC3007	Error calling program API205 to convert spool file to text format. See job log f
ATC3008	Program `API205` returned error code when copying spool file.
ATC3009	Error creating work file for AES encryption.
ATC3010	AES encryption failure. See job log for more information.
ATC3011	AES self-decrypting archive failure. See job log for more information.
ATC3012	AES self-decrypting archive extension is required.
ATC3013	IFS file type must be `1` for `Text` , or `2` for `PDF` , or 3 for `RTF` .
ATC3014	ERROR calling PDF converter for spool file .
ATC3015	‘PDF conversion error for spool file .
ATC3016	Prefix only valid generate option.
ATC3017	AN0179C: Internal error calling custom program `AN6081E` .
ATC3018	AN0179C: program `AN6064E` returned error code .
ATC3019	AN0179C: Unmonitored error in program.
ATC3020	File / is not active for library scan.
ATC3021	File / is not defined for scan library processing.
ATC3022	Spool file no longer in the system. Continuing with the next spool file.

GID	TEXT
ATC3023	AN0300C: Error moving spool file number for job // to error output queue. Pres
ATC3024	AN0300C: Error moving spool file number for job // to backup output queue. Pre
ATC3025	Lock specified for file / but file is not available.
ATC3026	Library list defintion not found. Library list not replace.
ATC3027	Error replacing library list with definition . Not replaced.
ATC3028	Special value must be **`*ANY`** .
ATC3099	AN0373C: Error calling **`AN0119`** for email list delivery.
ATC3100	Maximum number of records exceeded.
ATC3101	Conversion table name is blank.
ATC3102	Conversion table library is blank.
ATC3103	ERROR opening ISO 8583 import file ANGENI.
ATC3104	Error initializing the application log.
ATC3105	File is empty or file I/O error.
ATC3106	Error opening export file ANGENE.
ATC3107	Error retrieving key record from ISO8583 export file.
ATC3108	Script already exists.
ATC3109	Script name is blank.
ATC3110	Script description is blank.
ATC3111	Editor must be **`1`** for **`PDM/SEU`** or **`2`** for **`Alliance`** .
ATC3112	User profile is blank or invalid.
ATC3113	User profile does not exist, or not authorized.
ATC3114	Option complete.
ATC3115	Unmonitored exception in program. See job log for details.
ATC3116	Clear Channel Command (CCC) opton must be **`1`** for **`Yes`** or **`2`** for **`No`** .

GID	TEXT
ATC3117	AN0437R IBM: Unable to send the Clear Channel Command (CCC).
ATC3118	AN0437R IBM: FTP CCC operation returned error code , text .
ATC3119	AN0437R IBM: Unable to send the `SITE 1` command to IBM.
ATC3120	AN0437R IBM: FTP SITE 1 operation returned error code , text .
ATC3121	AN0437R IBM: Unable to send the `SITE 2` command to IBM.
ATC3122	AN0437R IBM: FTP SITE 2 operation returned error code , text .
ATC3123	AN0437R IBM: Unable to send the `SITE 3` command to IBM.
ATC3124	AN0437R IBM: FTP SITE 3 operation returned error code , text .
ATC3125	AN0441R SSL: Unable to send the Clear Channel Command (CCC).
ATC3126	AN0441R SSL: FTP CCC operation returned error code , text .
ATC3127	AN0441R SSL: Unable to send the `SITE 1` command.
ATC3128	AN0441R SSL: FTP SITE 1 operation returned error code , text .
ATC3129	AN0441R SSL: Unable to send the `SITE 2` command.
ATC3130	AN0441R SSL: FTP SITE 2 operation returned error code , text .
ATC3131	AN0441R SSL: Unable to send the `SITE 3` command.
ATC3132	AN0441R SSL: FTP SITE 3 operation returned error code , text .
ATC3133	Target file name option must be `1` , `2` or `3` .
ATC3134	Zip file name is blank.

GID	TEXT
ATC3135	At least one IFS file name is required.
ATC3136	Verbose option must be **`*YES`** or **`*NO`** .
ATC3137	Directory path option must be **`*YES`** or **`*NO`** .
ATC3138	Zip compression completed normally.
ATC3139	ERROR, unmonitored exception in Zip compression command **`ALLZIP`** .
ATC3140	AN0440R BELLSOUTH: An error occurred updating the application log.
ATC3141	Processing program parameter type must be **`1`** for **`Standard`** or **`2`** for **`Extended`** .
ATC3142	Output queue option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC3143	Extended parameters only valid with extended processing program option.
ATC3144	Output queue name and library required.
ATC3145	Output queue does not exist, or not authorized.
ATC3146	User program / error for file /.
ATC3147	User program with extended parameters returned error .
ATC3148	ERROR: Output queue / does not exist for change.
ATC3149	ERROR: Unable to change output queue to /.
ATC3150	Output queue name is blank.
ATC3151	Output queue library is blank.
ATC3152	Output queue does not exist, or not authorized.
ATC3153	Binary mode option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC3154	ERROR: Advantis IE send failure for file , log .
ATC3155	FTP server port number must be in the range **`00001`** to **`65534`** .
ATC3156	AN0442R SSL FTP: Error setting PORT number for FTP server.

GID	TEXT
ATC3157	AN0182C: Internal error calling custom program **AN6066E** .
ATC3158	AN0182C: program **AN6066E** returned error code .
ATC3159	AN0182C: Unmonitored error in program.
ATC3160	Alliance Auto-Scan: Umonitored exception in program. See job log.
ATC3161	Command **FTMAUTO** completed successfully.
ATC3162	FTP port number must be in the range of **00001** to **65534** .
ATC3163	AN0441R SSL: Error setting the remote FTP server port number.
ATC3164	Alliance PDF files not installed (press ***HELP***).
ATC3165	Error opening ISO8583 Correlation file ANISO8.
ATC3166	Email distribution list does not exist.
ATC3167	Email distribution list is empty.
ATC3168	Error in call to email API program **API200** to send email message.
ATC3169	FTMDIST: Successful completion.
ATC3170	FTMDIST: Error, unmonitored exception in program. See job log for details.
ATC3171	AES key name is blank.
ATC3172	File does not exist, or not authorized.
ATC3173	File member does not exist, or not authorized.
ATC3174	AES encryption session successful.
ATC3175	ERROR, unmonitored exception in AES program. See job log for details.
ATC3176	ERROR calling program AN0128R for encryption services. See job log for details.
ATC3177	If Copy To File option is ***YES** , **ASCII Armor** option must also be ***YES** .

GID	TEXT
ATC3178	If Copy To File option is ***YES** , file name must be specified.
ATC3179	If Copy To File option is ***YES** , file library name must be specified.
ATC3180	If Copy To File option is ***YES** , file member name must be specified.
ATC3181	Error creating file for copy. See job log for more information.
ATC3182	Error adding member to copy file. See job log for details.
ATC3183	Conversion table for file copy does not exist, or not authorized.
ATC3184	Error copying file to library.
ATC3185	Object is not a file, or does not exist.
ATC3186	Data conversion not allowed for save file.
ATC3187	End of line format must be ***FIXED** for save file.
ATC3188	Trim trailing blanks options must be ***NO** for save file.
ATC3189	Copy from file is specified, but file name is blank.
ATC3190	Copy from file is specified, but library name is blank.
ATC3191	Copy from file is specified, but member name is blank.
ATC3192	Copy from file does not exist, or not authorized.
ATC3193	Copy from file to IFS file failed. See job log for more information.
ATC3194	Conversion table does not exist, or not authorized.
ATC3195	Copy from file to IFS file with conversion failed. See job log for more informat
ATC3196	Error creating save file for copy.
ATC3197	Error copying decrypted file to save file.
ATC3198	Error copying override decrypted file to save file.
ATC3199	AES files already installed. Press ***F10*** to install again.

GID	TEXT
ATC3200	AES key not found in key file.
ATC3201	Library name is blank.
ATC3202	Member name is blank.
ATC3203	File does not exist, or not authorized.
ATC3204	Member does not exist, or not authorized.
ATC3205	Error calling program **AN0128R** for encryption.
ATC3206	AES encryption request successful.
ATC3207	Unmonitored exception in command **AESDB2ENC** for encryption. See job log for details.
ATC3208	AES decryption request successful.
ATC3209	Unmonitored exception in command **AESDB2DEC** for decryption. See job log for details.
ATC3210	Save file name is blank.
ATC3211	Save file library is blank.
ATC3212	Save file does not exist, or not authorized.
ATC3213	File is not a save file.
ATC3214	Error copying save file to IFS work file.
ATC3215	Error encrypting file. See job log for more information.
ATC3216	Error deleting IFS work file.
ATC3217	Error creating target file to contain encrypted data.
ATC3218	Error adding member to target file.
ATC3219	Error copying encrypted save file to target file.
ATC3220	Directory scan file action record is not active. File skipped.
ATC3221	Directory scan file action record not found.
ATC3222	Unmonitored exception in command **AESSAVFENC** for encryption. See job log for details.
ATC3223	Copy to file name is blank.

GID	TEXT
ATC3224	Copy to library name is blank.
ATC3225	Library for target file does not exist.
ATC3226	Error deleting encrypted file from IFS directory.
ATC3227	AES save file encryption request successful.
ATC3228	File specified for save file is wrong type.
ATC3229	Error creating save file to receive decrypted data. See job log for more information.
ATC3230	Error clearing save file to receive decrypted data. See job log for more information.
ATC3231	Error copying the encrypted data to the IFS directory for decryption.
ATC3232	Error decrypting file. See job log for additional information.
ATC3233	Error deleting encrypted IFS file.
ATC3234	Error copying decrypted IFS file to save file.
ATC3235	Error deleting the decrypted IFS save file data.
ATC3236	AES save file decryption request successful.
ATC3237	Unmonitored exception in command **`AESSAVFDEC`** for encryption. See job log for details.
ATC3238	From file does not exist, or not authorized.
ATC3239	From file member does not exist, or not authorized.
ATC3240	Library for save file does not exist, or not authorized.
ATC3241	File not found, or not authorized, for **`Copy From`** option.
ATC3242	Error copying file to IFS directory for decryption. See job log for more information.
ATC3243	Error creating file to receive decrypted data.
ATC3244	Error creating file member to receive decrypted data.
ATC3245	Error copying decrypted data to file.

GID	TEXT
ATC3246	Error deleting decrypted file after copy.
ATC3247	Error deleting encrypted IFS file after copy.
ATC3248	Copy to option must be ***YES** or ***No** .
ATC3249	Copy to library does not exist, or not authorized.
ATC3250	Error creating copy to file. See job log for more information.
ATC3251	Error adding member to copy to file. See job log for more information.
ATC3252	Error copying encrypted data to copy to file. See job log for more information.
ATC3253	Error deleting encrypted IFS file.
ATC3254	Error deleting clear text IfS file.
ATC3255	ERROR encrypting spool file for archive.
ATC3256	ERROR creating library **ALLAES100A** for archived spool files.
ATC3257	ERROR moving encrpted spool file to archive library **ALLAES100A** .
ATC3258	ERROR: Unmonitored exception in Alliance Spool file encryption routine.
ATC3259	ERROR: Spool file already exists in history file.
ATC3260	ERROR: An I/O error occurred trying to add a record to encrypted spool file hist
ATC3261	Error retrieving encrypted spool file history record.
ATC3262	Error creating work file for encrypted spool file data.
ATC3263	Error decrypting spool file. See job log for more information.
ATC3264	ERROR: unmonitored exception is spool file view program.
ATC3265	Spool file decryption in process …
ATC3266	Error creating list of spool files in output queue.
ATC3267	Error retrieving spool file user space header information.

GID	TEXT
ATC3268	Error retrieving spool file information from user space.
ATC3269	Error retrieving output queue header record for this output queue.
ATC3270	ERROR: Output queue definition not found. Alliance encryption processing ended.
ATC3271	This output queue not defined to time-based processing. Job ended.
ATC3272	ERROR: The Alliance job failed on a DELAY job command.
ATC3273	ERROR: An error occurred calling program **AN6090E**. See job log for details.
ATC3274	ERROR: An unmonitored error occurred in Alliance program **AE0301C**.
ATC3275	ERROR submitting output queue encryption program for output queue .
ATC3276	Error starting output queue encryption processing for queue .
ATC3277	User name and output queue name are blank.
ATC3278	User does not exist, or not authorized.
ATC3279	Output queue does not exist, or not authorized.
ATC3280	Options pending, user not changed.
ATC3281	Options pending, output queue not changed.
ATC3282	New list of spool files created.
ATC3283	Error in save file data. Probable incorrect AES key used for decryption.
ATC3284	Session name is blank.
ATC3285	FTP session ID does not exist.
ATC3286	From date is blank or invalid.
ATC3287	To date is blank or invalid.
ATC3288	Delete option must be **1**, **2**, or **3**.

GID	TEXT
ATC3289	**FTMSESNM** completed normally.
ATC3290	ERROR: Unmonitored exception in program **FTMSESNM**. See job log for details.
ATC3291	Sort order must be **1** for **Directory**, or **2** for **Name**.
ATC3292	FTMIPUSER: Unmonitored exception in program. See job log for details.
ATC3293	Spool file printed.
ATC3294	Output queue description is blank.
ATC3295	Status must be **1** for **Active** or **2** for **Inactive**.
ATC3296	Diagnostic loggin must be **1** for **Yes** or **2** for **No**.
ATC3297	After option must be **1**, **2** or **3**.
ATC3298	Backup output queue name is blank.
ATC3299	Backup output queue library is blank.
ATC3300	Error output queue name is blank.
ATC3301	Error output queue library is blank.
ATC3302	Processing option must be **1** or **2**.
ATC3303	Processing time is blank or invalid.
ATC3304	Output queue name is blank.
ATC3305	Output queue library name is blank.
ATC3306	Output queue does not exist, or not authorized.
ATC3307	Output queue definition already exists.
ATC3308	Backup output queue does not exist, or not authorized.
ATC3309	Error backup output queue does not exist, or not authorized.
ATC3310	Error calling system API QP0LROR for file information.
ATC3311	Error allocating space for file list. No space available.
ATC3312	Error calling system API QP0LROR for extended information.

GID	TEXT
ATC3313	Error extending memory for large buffer.
ATC3314	Error calling system API QP0LROR with extended memory.
ATC3315	PGP large file option must be `1` for `Yes` or `2` for `No`.
ATC3316	INFO: PGP large file support enabled for this session.
ATC3317	INFO: PGP large file support disabled for this session.
ATC3318	Day of week option just be `1` for `Yes` or `2` for `No`.
ATC3319	ERROR retrieving FTP scan directory options. See job log for details.
ATC3320	Library scan synchronization definition not found.
ATC3321	Advantis synchronization with auto-scan library in effect.
ATC3322	Auto-scan definition not found.
ATC3323	Synchronization option must be `1` for `Yes` or `2` for `No`.
ATC3324	Auto-scan definition is blank.
ATC3325	Auto-scan definition not found.
ATC3326	Description is blank.
ATC3329	File I/O error reading save file.
ATC3330	Error encrypting Save File record.
ATC3331	Error initializing after Save File encryption.
ATC3332	Error encrypting Save File record.
ATC3333	Error encrypting Save File record.
ATC3334	Tape file name is blank.
ATC3335	Tape file name is blank.
ATC3336	At least one tape device must be specified.
ATC3337	Tape file does not exist, or not authorized.
ATC3338	Tape device 1 does not exist, or not authorized.
ATC3339	Tape device 2 does not exist, or not authorized.

GID	TEXT
ATC3340	Tape device 3 does not exist, or not authorized.
ATC3341	Tape device 4 does not exist, or not authorized.
ATC3342	Error calling program **AN0141R** to save direct to tape.
ATC3343	AES encryption save file direct to tape successful.
ATC3344	ERROR: Unmonitored exception in AES program **AN0255C** .
ATC3345	Error retrieving key pass phrase.
ATC3346	Error creating Save File for restore. See job log for more information.
ATC3347	Error calling program **AN0142R** to restore direct from tape.
ATC3348	AES decrypt save file direct from tape successful.
ATC3349	ERROR: Unmonitored exception in AES program **AN0256C** .
ATC3350	Error clearing save file before restore.
ATC3351	No records restored from encrypted save file.
ATC3352	Error opening tape file for output operation.
ATC3353	Error opening tape file for input operation.
ATC3354	Error writing decrypted data to save file.
ATC3355	Error opening file for output operation.
ATC3356	Error opening file for input operation.
ATC3357	File I/O error reading encrypted file.
ATC3358	Error writing decrypted data to save file.
ATC3359	Error clearing target file for encrypted data.
ATC3360	Error calling program **AN0143R** to encrypt the save file.
ATC3361	Error calling program **AN0144R** to decrypt to a save file.
ATC3362	AES key name or pass phrase required.
ATC3363	AES key name or pass phrase required, but not both.
ATC3364	User description is blank.

GID	TEXT
ATC3365	Manage option must be `1` for **`Yes`** or `2` for **`No`**.
ATC3366	Authorization list description is blank.
ATC3367	Authorization list name is blank.
ATC3368	Authorization list already exists.
ATC3369	User name is blank.
ATC3370	User name already exists in list.
ATC3371	User does not exist, or not authorized.
ATC3372	Not authorized to create list.
ATC3373	Not authorized to delete list.
ATC3374	Not authorized to print list.
ATC3375	Not authorized to manage list.
ATC3376	Not authorized to change list.
ATC3377	Spooled file name is blank.
ATC3378	Job name is blank.
ATC3379	User name is blank.
ATC3380	User data is blank.
ATC3381	Output queue detail record already exists.
ATC3382	Status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC3383	Description is blank.
ATC3384	Output queue override option must be `1` for **`Yes`** or `2` for **`No`**.
ATC3385	Override output queue is blank.
ATC3386	Override output queue library is blank.
ATC3387	Suppress blank lines option must be `1` for **`Yes`** or `2` for **`No`**.
ATC3388	AES key name is blank.

GID	TEXT
ATC3389	AES key not found.
ATC3390	Authorization list is blank.
ATC3391	Authorization list not found in authorization list file.
ATC3392	File I/O error reading input file.
ATC3393	Error encrypting spool file record.
ATC3394	Error decrypting spool file record.
ATC3395	No records restored from encrypted spool file.
ATC3396	Error writing decrypted data to spool file image.
ATC3397	Not authorized to this spool file.
ATC3398	ERROR: unmonitored exception is spool file print program.
ATC3399	Encrypted spool file decrypted and printed.
ATC3400	Not authorized to this function.
ATC3401	Retention days must be in the range of `0001` to `9999` .
ATC3402	Error deleting encrypted spool file /.
ATC3403	ERROR: Unmonitored exception deleting encrypted spool file /.
ATC3404	ERROR: Unmonitored exception in Alliance encrypted spool file purge program.
ATC3405	Alliance AES TCP services not installed (***HELP***).
ATC3406	IFS file does not exist.
ATC3407	Error calling program `AN0186` . See job log for details.
ATC3408	Error encrypting IFS file.
ATC3409	Unmonitored error encrypting IFS file.
ATC3410	IFS file does not exist.
ATC3411	Error calling program `AN0186` . See job log for details.
ATC3412	Error decrypting IFS file.

GID	TEXT
ATC3413	Unmonitored error decrypting IFS file.
ATC3415	Operation must be 1, 2 or 3.
ATC3416	Retention days must be in the range of `0001` to `9999`.
ATC3417	Audit history purge complete.
ATC3418	Unmonitored exception in program `AN6250C` for audit history purge.
ATC3419	Split key must be created by two different users (***HELP***).
ATC3420	Error encrypting IFS file.
ATC3421	INFO: File type is not supported, error ignored.
ATC3422	File encryption successful, but an error occurred deleting the original file.
ATC3423	Error deleting encrypted file. File may remain on the server.
ATC3424	AN0442R SSL: Error sending the account.
ATC3425	AN0442R SSL: FTP ACCT operation returned error code , text .
ATC3426	AN0441R SSL: Unable to send the account.
ATC3427	AN0441R SSL: FTP ACCT operation returned error code , text .
ATC3428	AES spool file encryption option must be `1` for `Yes` or `2` for `No`.
ATC3429	Error retrieving AES spool file option. Contact programming support.
ATC3430	AES spool file encryption not enabled. Job ending normally.
ATC3431	Error opening key list file.
ATC3432	Error creating key list.
ATC3433	Unmonitored exception encountered creating the key list.
ATC3434	Record displayed.
ATC3435	Error deleting PGP key, key may not have been deleted.

GID	TEXT
ATC3436	Unmonitored exception encountered deleting PGP key.
ATC3437	Error adding key to key ring. See job log for details.
ATC3438	Unmonitored exception encountered addng PGP key.
ATC3439	Delete after retrieve option must be `1` for `Yes` or `2` for `No`.
ATC3440	User description is blank.
ATC3441	AES option must be `1` for `Yes` or `2` for `No`.
ATC3442	AES user is blank.
ATC3443	AES user already exists.
ATC3444	AES user control option must be `1` for `Yes` or `2` for `No`.
ATC3445	Not authorized to AES function (***HELP***).
ATC3446	AN0120C: Unable to duplicate file in library .
ATC3447	Not authorized to function.
ATC3448	ERROR calling SSL FTP communications program for file .
ATC3449	AN0211C: Error returned by SSL FTP program for file in directory .
ATC3450	AES key type must be 1, 2, or 3.
ATC3451	Maximum pass phrase length is 32.
ATC3452	Maximum pass phrase length in hex is 64.
ATC3453	For AES block mode keys the minimum pass phrase length is 8 characters.
ATC3454	Invalid hex character at position . Only values 0-9 and A-F allowed.
ATC3455	For AES block mode keys the minimum hex pass phrase length is 16 characters.
ATC3456	Invalid hex character in Salt in position .
ATC3457	Invalid hex character in Password verifier in position .
ATC3458	Salt value is blank.

GID	TEXT
ATC3459	Password verifier is blank.
ATC3460	Salt option must be `1` for `Generate` or `2` for `Manual`.
ATC3461	Password verifier option must be `1` for `Generate` or `2` for `Manual`.
ATC3462	Salt in hex must be 32 hex characters in length.
ATC3463	Error writing to data queue for tape encryption.
ATC3464	Error retrieving user class and authorities.
ATC3465	Unmonitored exception retrieving user authority. See job log for details.
ATC3466	Error receiving data from data queue. See job lot for more information.
ATC3467	Error, time out waiting for data queue. Job ended abnormally.
ATC3468	Audit journal option must be `1` for `Yes` or `2` for `No`.
ATC3469	SECURITY ERROR: Unable to send security audit entry to journal.
ATC3470	SECURITY ERROR: Error sending security audit entry to journal.
ATC3471	Error retrieving audit journal options. Job cancelled.
ATC3472	Error initializing Diffie-Hellman key generation environment. Job cancelled.
ATC3473	Error initializing Diffie-Hellman P value for key generation. Job cancelled.
ATC3474	Error initializing Diffie-Hellman G value for key generation. Job cancelled.
ATC3475	Error loading random number values from `/tmp/random`. Job cancelled.
ATC3476	Error creating Diffie-Hellman key. See interactive report for error text.
ATC3477	Error creating random values in IFS file.
ATC3478	Error copying random data to IFS file.

GID	TEXT
ATC3479	Program error calling **AN6092E** to generate DH key. See job log for more informati
ATC3480	Unmonitored exception in DH key generation program. See job log for more informa
ATC3481	Error calling program **AN6092C** to generate key. See job log for details.
ATC3482	Specify key type before starting Diffie-Hellman key generation.
ATC3483	Error writing IFS backup history.
ATC3484	File already exists in target directory.
ATC3485	Error calling PowerTech exit point.
ATC3486	PowerTech option must be **1** for **Yes** or **2** for **No**.
ATC3487	PowerTech library is required if PowerTech option is **Yes**.
ATC3488	Enable Alliance user control or PowerTech option, but not both.
ATC3489	Error calling PowerTech API for user authorization.
ATC3490	Error received from Alliance user control check.
ATC3491	Encrypt to tape with multi-processing option must be **1** for **Yes** or **2** for **No**.
ATC3492	Decrypt from tape with multi-processing option must be **1** for **Yes** or **2** for **No**.
ATC3493	Error calling program **TAPEENC** to save direct to tape multi-processing.
ATC3494	AES encryption save file direct to tape with multi-processing successful.
ATC3495	ERROR: Unmonitored exception in AES program **AN0258C**.
ATC3496	Shared memory ID already exists.
ATC3497	Unable to acquire shared memory key.
ATC3498	ERROR writing to tape file for multi-process save operation.

GID	TEXT
ATC3499	ERROR EACESS when getting shared memory.
ATC3500	ERROR EDAMAGE when getting shared memory.
ATC3501	ERROR EEXIST when getting shared memory.
ATC3502	ERROR EINVAL when getting shared memory.
ATC3503	ERROR ENOENT when getting shared memory.
ATC3504	ERROR ENOMEM when getting shared memory.
ATC3505	ERROR ENOSPC when getting shared memory.
ATC3506	ERROR EUNKNOWN when getting shared memory.
ATC3507	ERROR of unknown type when getting shared memory.
ATC3508	ERROR EACCES when attaching to shared memory.
ATC3509	ERROR EADDRINUSE when attaching to shared memory.
ATC3510	ERROR EDAMAGE when attaching to shared memory.
ATC3511	ERROR EFAULT when attaching to shared memory.
ATC3512	ERROR EINVAL when attaching to shared memory.
ATC3513	ERROR EOPNOTSUPP when attaching to shared memory.
ATC3514	ERROR ENOMEM when attaching to shared memory.
ATC3515	ERROR EUNKNOWN when attaching to shared memory.
ATC3516	ERROR of unknown type when attaching to shared memory.
ATC3517	ERROR EAGAIN when creating thread.
ATC3518	ERROR EBUSY when creating thread.
ATC3519	ERROR EINVAL when creating thread.
ATC3520	ERROR EPERM when creating thread.
ATC3521	ERROR of unknown type when creating thread.
ATC3522	ERROR EAGAIN type when creating thread.
ATC3523	ERROR EBUSY type when creating thread.

GID	TEXT
ATC3524	ERROR EINVAL type when creating thread.
ATC3525	ERROR EPERM type when creating thread.
ATC3526	ERROR of unknown type when creating thread.
ATC3527	ERROR EAGAIN type when creating thread.
ATC3528	ERROR EBUSY type when creating thread.
ATC3529	ERROR EINVAL type when creating thread.
ATC3530	ERROR EPERM type when creating thread.
ATC3531	ERROR of unknown type when creating thread.
ATC3532	ERROR EAGAIN type when creating thread.
ATC3533	ERROR EBUSY type when creating thread.
ATC3534	ERROR EINVAL type when creating thread.
ATC3535	ERROR EPERM type when creating thread.
ATC3536	ERROR of unknown type when creating thread.
ATC3537	ERROR EAGAIN type when creating thread.
ATC3538	ERROR EBUSY type when creating thread.
ATC3539	ERROR EINVAL type when creating thread.
ATC3540	ERROR EPERM type when creating thread.
ATC3541	ERROR of unknown type when creating thread.
ATC3542	ERROR EAGAIN type when creating thread.
ATC3543	ERROR EBUSY type when creating thread.
ATC3544	ERROR EINVAL type when creating thread.
ATC3545	ERROR of unknown type (unused).
ATC3546	ERROR EPERM type when creating thread.
ATC3547	ERROR of unknown type when creating thread.
ATC3548	ERROR, decryption failed.

GID	TEXT
ATC3549	ERROR, encryption failed.
ATC3550	ERROR, thread destroy failed with EINVAL.
ATC3551	ERROR, thread destroy failed with unknown error.
ATC3552	ERROR, mutex destroy failed with EINVAL error.
ATC3553	ERROR, mutex destroy failed with unknown error.
ATC3554	ERROR, mutex destroy failed with EBUSY error.
ATC3555	ERROR, mutex destroy failed with EINVAL error.
ATC3556	ERROR, mutex destroy failed with unknown error.
ATC3557	ERROR, thread initialization failed with EINVAL error.
ATC3558	ERROR, thread initialization failed with ENOMEM error.
ATC3559	ERROR, thread initialization failed with unknown error.
ATC3560	ERROR, thread detach state failed with EINVAL error.
ATC3561	ERROR, open tape for read failed.
ATC3562	ERROR, Process Args failed with invalid Process parameter.
ATC3563	ERROR, Process Args failed with invalid Save-Restore parameter.
ATC3564	ERROR, Process Args failed with invalid Function parameter.
ATC3565	ERROR, Process Args failed. Both key name and passphrase exist.
ATC3566	ERROR, Process Args failed. Key name or pass phrase required.
ATC3567	ERROR, Process Args failed. Error retriving encryption key.
ATC3568	ERROR, Process Args failed with invalid Process parameter.
ATC3569	ERROR, Process Args failed with invalid Save-Restore parameter.
ATC3570	ERROR, Process Args failed with invalid Function parameter.

GID	TEXT
ATC3571	ERROR, Process Args failed. Both key name and pass phrase provided.
ATC3572	ERROR, Process Args failed. Key name or pass phrase required.
ATC3573	ERROR, Process Args failed. Error retrieving encyrption key.
ATC3574	ERROR EINVAL posting Can Encrypt semaphore.
ATC3575	ERROR ENOSYS posting Can Encrypt semaphore.
ATC3576	ERROR unknown error posting Can Encrypt semaphore.
ATC3577	ERROR EINVAL posting Can Decrypt semaphore.
ATC3578	ERROR ENOSYS posting Can Decrypt semaphore.
ATC3579	ERROR unknown error posting Can Decrypt semaphore.
ATC3580	ERROR EINVAL posting Can Read semaphore.
ATC3581	ERROR ENOSYS posting Can Read semaphore.
ATC3582	ERROR unknown error posting Can Read semaphore.
ATC3583	ERROR EINVAL posting Can Write semaphore.
ATC3584	ERROR ENOSYS posting Can Write semaphore.
ATC3585	ERROR unknown error posting Can Write semaphore.
ATC3586	ERROR EINVAL on main thread wait semaphore.
ATC3587	ERROR ENOSYS on main thread wait semaphore.
ATC3588	ERROR of unknown type on main thread wait semaphore.
ATC3589	ERROR EFAULT retrieving time of day.
ATC3590	ERROR E_INVALID_PARAMETER retrieving time of day.
ATC3591	ERROR EUNKNOWN retrieving time of day.
ATC3592	ERROR of unknown type retrieving time of day.
ATC3593	ERROR EFAULT retrieving time of day.
ATC3594	ERROR E_INVALID_PARAMETER retrieving time of day.

GID	TEXT
ATC3595	ERROR EUNKNOWN retrieving time of day.
ATC3596	ERROR of unknown type retrieving time of day.
ATC3597	ERROR EFAULT retrieving time of day.
ATC3598	ERROR E_INVALID_PARAMETER retrieving time of day.
ATC3599	ERROR EUNKNOWN retrieving time of day.
ATC3600	ERROR of unknown type retrieving time of day.
ATC3601	ERROR EFAULT retrieving time of day.
ATC3602	ERROR E_INVALID_PARAMETER retrieving time of day.
ATC3603	ERROR EUNKNOWN retrieving time of day.
ATC3604	ERROR of unknown type retrieving time of day.
ATC3605	ERROR EACCES on set up of Can Decrypt semaphore.
ATC3606	ERROR EEXIST on set up of Can Decrypt semaphore.
ATC3607	ERROR EINVAL on set up of Can Decrypt semaphore.
ATC3608	ERROR ENAMETOOLONG on set up of Can Decrypt semaphore.
ATC3609	ERROR ENOENT on set up of Can Decrypt semaphore.
ATC3610	ERROR ENOSPC on set up of Can Decrypt semaphore.
ATC3611	ERROR of unknown type on set up of Can Decrypt semaphore.
ATC3612	ERROR EACCES on set up of Can Encrypt semaphore.
ATC3613	ERROR EEXIST on set up of Can Encrypt semaphore.
ATC3614	ERROR EINVAL on set up of Can Encrypt semaphore.
ATC3615	ERROR ENAMETOOLONG on set up of Can Encrypt semaphore.
ATC3616	ERROR ENOENT on set up of Can Encrypt semaphore.
ATC3617	ERROR ENOSPC on set up of Can Encrypt semaphore.

GID	TEXT
ATC3618	ERROR of unknown type on set up of Can Encrypt semaphore.
ATC3619	ERROR EACCES on set up of Can Read semaphore.
ATC3620	ERROR EEXIST on set up of Can Read semaphore.
ATC3621	ERROR EINVAL on set up of Can Read semaphore.
ATC3622	ERROR ENAMETOOLONG on set up of Can Read semaphore.
ATC3623	ERROR ENOENT on set up of Can Read semaphore.
ATC3624	ERROR ENOSPC on set up of Can Read semaphore.
ATC3625	ERROR of unknown type on set up of Can Read semaphore.
ATC3626	ERROR EACCES on set up of Can Write semaphore.
ATC3627	ERROR EEXIST on set up of Can Write semaphore.
ATC3628	ERROR EINVAL on set up of Can Write semaphore.
ATC3629	ERROR ENAMETOOLONG on set up of Can Write semaphore.
ATC3630	ERROR ENOENT on set up of Can Write semaphore.
ATC3631	ERROR ENOSPC on set up of Can Write semaphore.
ATC3632	ERROR of unknown type on set up of Can Write semaphore.
ATC3633	ERROR EACCES on semaphore init.
ATC3634	ERROR EEXIST on semaphore init.
ATC3635	ERROR EINVAL on semaphore init.
ATC3636	ERROR ENAMETOOLONG on semaphore init.
ATC3637	ERROR ENOENT on semaphore init.
ATC3638	ERROR ENOSPC on semaphore init.
ATC3639	ERROR of unknown type on semaphore init.
ATC3640	ERROR EACCES on semaphore unlink operation.
ATC3641	ERROR ENOENT on semaphore unlink operation.

GID	TEXT
ATC3642	ERROR EFAULT on semaphore unlink operation.
ATC3643	ERROR ENAMETOOLONG on semaphore unlink operation.
ATC3644	ERROR of unknown type on semaphore unlink operation.
ATC3645	ERROR EDAMAGE on detach from shared memory.
ATC3646	ERROR EFAULT on detach from shared memory.
ATC3647	ERROR ENOSYS on detach from shared memory.
ATC3648	ERROR EUNKNOWN on detach from shared memory.
ATC3649	ERROR of unknown type on detach from shared memory.
ATC3650	ERROR EACCES on delete of shared memory.
ATC3651	ERROR EDAMAGE on delete of shared memory.
ATC3652	ERROR EFAULT on delete of shared memory.
ATC3653	ERROR EINVAL on delete of shared memory.
ATC3654	ERROR ENOMEM on delete of shared memory.
ATC3655	ERROR EPERM on delete of shared memory.
ATC3656	ERROR EUNKNOWN on delete of shared memory.
ATC3657	ERROR of unknown type on delete of shared memory.
ATC3658	ERROR in 128bit AES enryption.
ATC3659	ERROR Encrypting 128bit AES key.
ATC3660	ERROR creating 128bit AES decryption key.
ATC3661	ERROR opening save file.
ATC3662	ERROR opening tape for write.
ATC3663	ERROR writing to tape. Insufficient number of bytes written.
ATC3664	ERROR processing arguments. Invalid Process parameter.
ATC3665	ERROR opening save file for write.
ATC3666	ERROR writing to save file. Insufficient number of bytes written.

GID	TEXT
ATC3667	ERROR reading from tape. Insufficient number of bytes read.
ATC3668	ERROR processing arguments. Invalid encryption type parameter.
ATC3669	ERROR encrypting pass phrase for AES key.
ATC3670	ERROR creating pass phrase for AES decryption key.
ATC3671	ERROR writing record to save file. Restore operation is not complete.
ATC3672	ERROR in decrypting data. Length less than 1.
ATC3673	ERROR in encrypting data. Length less than 1.
ATC3674	ERROR writing to save file. Length less than 1.
ATC3675	ERROR initializing application log interface.
ATC3699	Write to tape process completed successfully.
ATC3700	ERROR, unmonitored exception in save to tape.
ATC3701	ERROR encrypting for multi-process save operation.
ATC3702	Encrypt for save to tape process completed successfully.
ATC3703	ERROR, unmonitored exception in encrypt for save to tape.
ATC3704	ERROR submitting encrypted save to tape job. See job log for details.
ATC3705	ERROR, unmonitored exception in job AN0213C submitting tape encryption.
ATC3706	Error retrieving tape parameters.
ATC3707	Error calling program TAPEENC to restore direct from tape multi-processing.
ATC3708	AES decrypt save file direct from tape with multiprocessing successful.
ATC3709	ERROR: Unmonitored exception in AES program **AN0259C** .
ATC3710	ERROR submitting decrypted restore from tape job. See job log for details.

GID	TEXT
ATC3711	ERROR submitting restore from tape job. See job log for details.
ATC3712	ERROR, unmonitored exception in job AN0214C submitting tape restore.
ATC3713	Error retrieving tape parameters.
ATC3714	ERROR decrypting for multi-process restore operation.
ATC3715	Decrypt for restore from tape multiprocessing completed successfully.
ATC3716	ERROR, unmonitored exception in decrypt for restore from tape.
ATC3717	ERROR writing to save file for multi-process restore operation.
ATC3718	Write to save file process completed successfully.
ATC3719	ERROR, unmonitored exception in restore from tape.
ATC3720	Error in Twofish encryption initializing key.
ATC3721	Error in Twofish encryption initializing cipher text data.
ATC3722	Error in Twofish block encryption.
ATC3723	Error in Twofish block decryption.
ATC3724	No file objects in library, or not authorized.
ATC3725	Error creating file list. Possible authority problem.
ATC3726	No file objects found in library.
ATC3727	Unmonitored exception occurred during file list build. See job log.
ATC3728	ERROR, program TAPEENC received an error in restore from tape.
ATC3729	ERROR, program TAPEENC received an error in decrypt from tape.
ATC3730	Data group description is blank.
ATC3731	Data group status must be `1` for **`Yes`** or `2` for **`No`**.

GID	TEXT
ATC3732	Data group name is blank.
ATC3733	Data group name already exists.
ATC3734	Data group option must be `1` for **`Yes`** or `2` for **`No`**.
ATC3735	Profile maintenance option must be `1` for **`Yes`** or `2` for **`No`**.
ATC3736	Error retrieving shared memory information. Job cancelled (***HELP***).
ATC3737	Error calling shared memory program **`AN0150`**.
ATC3738	Data group status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC3739	Data group description is blank.
ATC3740	Key field option must be `1` for **`Yes`** or `2` for **`No`**.
ATC3741	Key field name is blank.
ATC3742	Data group file name is blank.
ATC3743	Data group library name is blank.
ATC3744	Data group member name is blank.
ATC3745	Data group field name is blank.
ATC3746	Policy status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC3747	Policy description is blank.
ATC3748	Policy method must be `1` for **`Authomatic`** or `2` for **`Manual`**.
ATC3749	Current encryption key is blank.
ATC3750	New encryption key is blank.
ATC3751	Key generation must be `1` for **`PRNG`** (random number).
ATC3752	Key change interval must be in the range of `0001` to `9999`.
ATC3753	Day of week must be from 1 to 7.
ATC3754	Next change date is invalid.
ATC3755	Next change time is invalid.

GID	TEXT
ATC3756	Save option must be `1` for `Yes` or `2` for `No`.
ATC3757	Save type must be `1` for `Tape` or `2` for `Save file`.
ATC3758	Device name or `*GEN` required.
ATC3759	Policy name is blank.
ATC3760	Policy already exists.
ATC3761	AES key does not exist.
ATC3762	New key cannot be the same as current key.
ATC3763	Object does not exist.
ATC3764	Save file library is blank.
ATC3765	Save file library does not exist.
ATC3766	Invalid date.
ATC3767	Date cannot be before today’s date.
ATC3768	Invalid time.
ATC3769	Special value is invalid.
ATC3770	Data group detail record already exists.
ATC3771	Library does not exist, or not authorized.
ATC3772	File does not exist, or not authorized.
ATC3773	Member does not exist in file, or not authorized.
ATC3774	Select an item, or press ***F3*** to exit.
ATC3775	Error calling internal routine to create file list. See job log for details.
ATC3776	Please wait, building file list …
ATC3777	Library name is blank.
ATC3778	No objects found.
ATC3779	Error creating object list. Possible authority problem.
ATC3780	No objects found in library.

GID	TEXT
ATC3781	Unmonitored exception occurred during object list build. See job log.
ATC3782	Please wait, building list …
ATC3783	Error calling internal routine to create object list. See job log for details.
ATC3784	Error creating member list for file. See job log for details.
ATC3785	No members in file.
ATC3786	Error creating member list.
ATC3787	Please wait, building member list …
ATC3788	Error calling internal routine to create member list. See job log for details.
ATC3789	Error creating field list for file. See job log for details.
ATC3790	Error creating field list.
ATC3791	Please wait, building field list …
ATC3792	Please wait, building field list for key field …
ATC3793	Key field cannot be the same as the encryption field.
ATC3794	Data group name is blank.
ATC3795	Data group name record already exists.
ATC3796	Data group status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC3797	Data group name does not exist.
ATC3798	ERROR changing program visibility. (***HELP***)
ATC4000	Alliance FTP Manager
ATC4001	Main Menu
ATC4002	Installation Menu
ATC4003	Configuration Menu
ATC4004	Maintenance Menu

GID	TEXT
ATC4005	FTP Sessions Menu
ATC4006	Inquiry Menu
ATC4007	Reports Menu
ATC4008	Support Menu
ATC4009	Related Commands Menu
ATC4010	5=FTP to Report.Web
ATC4011	FTP Manager Session Commands Menu
ATC4012	PGP Option Commands Menu
ATC4013	FTP Manager Commands Menu
ATC4014	FTP Manager CL Commands Menu
ATC4015	FTP Manager Operations Menu
ATC4016	FTP Manager Email Menu
ATC4017	FTP Manager POP Email Menu
ATC4018	Sample Code Menu
ATC4019	Alliance PGP Encryption
ATC4020	Operations Menu
ATC4021	NGS-IQ Menu
ATC4022	(C) Townsend Security 1998, 2010
ATC4023	Alliance Data Cloak
ATC4100	Alliance AES/400 Main Menu
ATC4101	Main Menu
ATC4102	Installation Menu
ATC4103	Configuration Menu
ATC4104	AES Commands Menu
ATC4105	Print Management Menu

GID	TEXT
ATC4106	AES Compliance Reports
ATC4107	AES Support Menu
ATC4108	AES NGS-IQ Menu
ATC4109	AES Assessment Menu
ATC4110	AES Database Assessment Menu
ATC4111	SAVF Commands Menu
ATC4112	Tape Commands Menu
ATC4113	IFS Commands Menu
ATC4114	SDA Commands Menu
ATC4115	DB2 Commands Menu
ATC4116	FEM Commands Menu
ATC4119	(C) Townsend Security, 2004, 2007.
ATC4129	Encrypt to Tape Save/Restore Menu
ATC4130	(C) Townsend Security , 2010
ATC4131	Save File Encrypt / Decrypt Menu
ATC4132	Database File Encrypt / Decrypt Menu
ATC4133	IFS File Encrypt / Decrypt Menu
ATC4134	Encrypted Spooled Files Menu
ATC4135	Encrypted Zip / Unzip Menu
ATC4136	Encrypted PDF Menu
ATC4137	PGP Encryption Menu
ATC4138	Encryption APIs
ATC4139	Installation and Configuration
ATC4140	Installation
ATC4141	Configuration

GID	TEXT
ATC4142	Additional Configuration
ATC4143	Reports
ATC4144	Scan and Assess
ATC4145	Alliance Products
ATC4146	Alliance Token Manager
ATC5000	Long file name option must be `1` for `Yes` or `2` for `No`.
ATC5001	FTMEXECDL FTP API starting.
ATC5002	FTMEXECDL FTP session log is .
ATC5003	FTMEXECDL starting PING verification.
ATC5004	FTMEXECDL starting ZIP compression.
ATC5005	FTMEXECDL starting GZIP compression.
ATC5006	FTMEXECDL starting PGP encryption.
ATC5007	FTMEXECDL starting AES encryption.
ATC5008	FTMEXECDL starting FTP substitutions with file .
ATC5009	FTMEXECDL starting FTP session.
ATC5010	FTMEXECDL restarting FTP session after error.
ATC5011	FTMEXECDL end of FTP session processing.
ATC5012	ANGETKEY, ERROR in call to AESGetKey to retrieve AES key.
ATC5013	Specify library or IFS directory, but not both.
ATC5014	AN0442R SSL: Unable to set local name format to 3.
ATC5015	AN0442R SSL: FTP NAMEFMT operation for IFS returned error code , text .
ATC5016	User for Auto-scan is blank or invalid.
ATC5017	Auto-scan user does not exist, or not authorized.
ATC5018	IP address option must be `1` for `Yes` or `2` for `No`.

GID	TEXT
ATC5019	AN0441R SSL: Error setting Original IP Address option.
ATC5020	AESSAVFENC: Error retrieving key from AES key file.
ATC5021	AESSAVFENC: Error encrypting AES key for save file encryption.
ATC5022	AESSAVFENC: Error creating AES decryption key for save file encryption.
ATC5023	AESSAVFENC: Error opening save file for encryption operation.
ATC5024	AESSAVFENC: Error opening output file for save file encryption.
ATC5025	AESSAVFENC: No records in Save file for encryption operation.
ATC5026	AESSAVFENC: Error in AES encryption operation. Job cancelled.
ATC5027	AESSAVFENC: Error writing encrypted save file data to output file.
ATC5028	AESSAVFENC: Error in AES encryption operation. Job cancelled.
ATC5029	AESSAVFENC: Error writing encrypted save file data to output file.
ATC5030	AESSAVFDEC: Error retrieving key from AES key file.
ATC5031	AESSAVFDEC: Error encrypting AES key for save file decryption.
ATC5032	AESSAVFDEC: Error creating AES decryption key for save file decryption.
ATC5033	AESSAVFDEC: Error opening save file for decryption.
ATC5034	AESSAVFDEC: Error opening input file for save file decryption.
ATC5035	AESSAVFDEC: Input encrypted file is empty. Job cancelled.
ATC5036	AESSAVFDEC: Error in decryption operation for save file.
ATC5037	AESSAVFDEC: Error writing decrypted data to save file.

GID	TEXT
ATC5038	AESSAVFDEC: Error decryption data for save file.
ATC5039	AESSAVFDEC: Error writing decrypted data to save file.
ATC5040	Error creating target file to contain encrypted data.
ATC5041	Error adding member to target file.
ATC5042	Error clearing target file for encrypted data.
ATC5043	Error calling program **`AN6097E`** to encrypt the save file.
ATC5044	AES save file encryption request successful.
ATC5045	Unmonitored exception in command **`AESSAVFENC`** for encryption. See job log for deta
ATC5046	Error calling program **`AN6098E`** to decrypt to a save file.
ATC5047	NGS-IQ layout file blank or invalid.
ATC5048	Encrypted field name blank or invalid.
ATC5049	Invalid field length, must be in the range of **`00001`** to **`32766`** .
ATC5050	AES Record ID field name is blank or invalid.
ATC5051	AES key name is blank or invalid.
ATC5052	Source file name is blank or invalid.
ATC5053	Source file library is blank or invalid.
ATC5054	Source file member is blank or invalid.
ATC5055	Object program name is blank or invalid.
ATC5056	Object program library is blank or invalid.
ATC5057	Create option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC5058	Replace option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC5059	NGS-IQ option must be **`1`** for **`Yes`** or **`2`** for **`No`** .
ATC5060	Member exists and replace option is **`No`** .
ATC5061	Error adding member to source file. See job log for more information.

GID	TEXT
ATC5062	Error clearing member in source file. See job log for more information.
ATC5063	Unmonitored exception adding source member. See job log for more information.
ATC5064	Error overriding template file. See job log for more information.
ATC5065	Error opening template file. See job log for more information.
ATC5066	Error overriding output source file. See job log for more information.
ATC5067	Error opening output source file. See job log for more information.
ATC5068	Error reading input template file. Job cancelled.
ATC5069	Error creating NGS-IQ layout file.
ATC5070	An error occurred when attempting to create the NGS-IQ layout file.
ATC5071	Unmonitored exception occurred when attempting to create the NGS-IQ layout file.
ATC5072	Error calling program `AN0002C` to generate layout source.
ATC5073	Compile of NGS-IQ RPG exit program failed. See compile listing.
ATC5074	Unmonitored exception while compiling NGS-IQ RPG exit program.
ATC5075	Error calling program AN0003C to compile RPG program.
ATC5076	Program exists but replace option is No. Job cancelled.
ATC5077	GXS host name is blank.
ATC5078	Key manager description is blank.
ATC5079	Key manager status must be `1` for `Active` or `2` for `Inactive`.
ATC5080	Key manager host name or IP address is blank.
ATC5081	Port number must be in the range of `00001` to `65535`.

GID	TEXT
ATC5082	ERROR opening Key Manager file. Job ended.
ATC5083	ERROR retrieving Key Manager record. Job ended.
ATC5084	ERROR, Key Manager definition is NULL or not provided.
ATC5085	ERROR, Key Manager definition must be from `1` to `10` bytes in length.
ATC5086	ERROR, Key Manager operation is NULL or not valid.
ATC5087	ERROR, Key Manager operation must be insert, update, delete, or select.
ATC5088	ERROR, Invalid length for user name.
ATC5089	ERROR, Invalid length for pass phrase.
ATC5090	ERROR, Invalid length for data element.
ATC5091	ERROR, Input data is NULL or invalid.
ATC5092	ERROR, Input data length is NULL or invalid.
ATC5093	ERROR, Input data length must be greater than 1.
ATC5094	ERROR, Output data is NULL or invalid.
ATC5095	ERROR, Output data size is NULL or invalid.
ATC5096	ERROR, Output data size must be greater than zero.
ATC5097	ERROR, Output data length is NULL or invalid.
ATC5098	ERROR, Return code is NULL or invalid.
ATC5099	ERROR, User name is NULL or invalid.
ATC5100	ERROR, Pass phrase is NULL or invalid.
ATC5101	ERROR, Data element is NULL or invalid.
ATC5102	ERROR, Failure connecting to Protegrity Defiance XC server.
ATC5103	ERROR, Failure in attempt to encrypt with Protegrity Defiance XC server.
ATC5104	Error, key definition is invalid.
ATC5105	Error, key export format is NULL or invalid.

GID	TEXT
ATC5106	Error, invalid format value.
ATC5107	Error, self decrypting archive option is NULL.
ATC5108	Error, invalid self decrypting archive option.
ATC5109	Error, export path is NULL.
ATC5110	Error, export path is too short or too long.
ATC5111	Error, unable to open key file ANAESK.
ATC5112	Error, key record not found in key file ANAESK.
ATC5113	Error decrypting pass phrase.
ATC5114	Error decrypting the random salt value.
ATC5115	Error decrypting the password verifier.
ATC5116	Error opening output IFS file.
ATC5117	Invalid character in Base64 encoding routine.
ATC5118	Error writing key to export file, bytes written invalid.
ATC5119	ERROR, unmonitored exception in AES key export. See job log for details.
ATC5120	ERROR, key name is blank.
ATC5121	ERROR, IFS file name is blank.
ATC5122	ERROR, pass phrase is required for self-decrypting archive option.
ATC5123	ERROR, AES key export received error code .
ATC5124	AES key export completed normally.
ATC5125	ERROR, unmonitored exception in command **`AESEXPORT`** . See job log for details.
ATC5126	Transfer mode must be `1` for **`Text`** or `2` for **`Binary`** .
ATC5127	Cycle count must be in the range of `0001` to `9999` .
ATC5128	Resubmitting process based on cycle count.

GID	TEXT
ATC5129	ERROR: Alliance library scan encountered an error re-submitting the job. See job
ATC5130	Key definition is missing or null.
ATC5131	Key definition must have a length greater than 0 and less that 11.
ATC5132	Input data parameter is missing or null.
ATC5133	Input data length parameter is missing or null.
ATC5134	Input length must be greater than 0
ATC5135	Initialization vector parameter is missing or null.
ATC5136	Output variable is missing or null.
ATC5137	Output size parameter is missing or null.
ATC5138	Output size must be greater than 0.
ATC5139	Output length parameter is missing or null.
ATC5140	HMAC parameter is missing or null.
ATC5141	Output variable is too small to hold the result.
ATC5142	Error opening Alliance key store file ANAESK.
ATC5143	Error retrieving Alliance key. Key name may be invalid.
ATC5144	Error decrypting the pass phrase.
ATC5145	Error decrypting the random salt value.
ATC5146	Error decrypting the password verifier.
ATC5147	Error creating encryption key schedule.
ATC5148	Error encryption with AES CBC.
ATC5149	Initialization vector parameter is missing or null.
ATC5150	Error CEE2523 on first call to Random number generator for IV.
ATC5151	Error CEE2524 on first call to Random number generator for IV.

GID	TEXT
ATC5152	Error CEE2523 on second call to Random number generator for IV.
ATC5153	Error CEE2524 on second call to Random number generator for IV.
ATC5154	Initialization vector option is missing or null.
ATC5155	Invalid value for initialization vector option.
ATC5156	Key definition is missing or null.
ATC5157	Key definition must have a length greater than 0 and less that 11.
ATC5158	Input data parameter is missing or null.
ATC5159	Input data length parameter is missing or null.
ATC5160	Input length must be greater than 0
ATC5161	Initialization vector parameter is missing or null.
ATC5162	Output variable is missing or null.
ATC5163	Output size parameter is missing or null.
ATC5164	Output size must be greater than 0.
ATC5165	Output length parameter is missing or null.
ATC5166	HMAC parameter is missing or null.
ATC5167	Output variable is too small to hold the result.
ATC5168	Error opening Alliance key store file ANAESK.
ATC5169	Error retrieving Alliance key. Key name may be invalid.
ATC5170	Error decrypting the pass phrase.
ATC5171	Error decrypting the random salt value.
ATC5172	Error decrypting the password verifier.
ATC5173	Error creating encryption key schedule.
ATC5174	Error decryption with AES CBC.
ATC5175	Key name and pass phrase are blank.

GID	TEXT
ATC5176	Key instance is null or invalid.
ATC5177	Counter is null or invalid.
ATC5178	Counter option is null or invalid.
ATC5179	Invalid Counter option, must be `0` or `1`.
ATC5180	Mask option is null or invalid.
ATC5181	Invalid mask option, must be `0`, `1`, or `2`.
ATC5182	Mask type is null or invalid.
ATC5183	Invalid mask type, must be `1` or `2`.
ATC5184	Data convertion option is null or invalid.
ATC5185	Invalid data convert option, must be `0` or `1`.
ATC5186	Data conversion table is null or invalid.
ATC5187	Invalid encode option, must be `0` or `1`.
ATC5188	Invalid encode value, must be `0` or `1`.
ATC5189	Encode type if null or invalid.
ATC5190	Invalid encode value, must be `1` or `2`.
ATC5191	Log option is null or invalid.
ATC5192	Invalid log option value, must be `0` or `1`.
ATC5193	Log user name is null or invalid.
ATC5194	Log field name is null or invalid.
ATC5195	User control option is null or invalid.
ATC5196	Invalid user control value, must be `0` or `1`.
ATC5197	User control name is null or invalid.
ATC5198	Field control option is null or invalid.
ATC5199	Invalid field control value, must be `0` or `1`.
ATC5200	Field name is null or invalid.

GID	TEXT
ATC5201	Application control option is null or invalid.
ATC5202	Invalid value for application control option, just be `0` or `1` .
ATC5203	Application name for control is null or invalid.
ATC5204	Store option is null or invalid.
ATC5205	Invalid value for store option, must be `0` or `1` .
ATC5206	Store locator type is null or invalid.
ATC5207	Invalid value for store locator type, must be `1` or `2` .
ATC5208	Key instance name is null or invalid.
ATC5209	Key expiration date is null or invalid.
ATC5210	Error calling program **`AN0129R`** for encryption.
ATC5211	AES encryption request successful.
ATC5212	Unmonitored exception in command **`AESDB2ENCA`** for encryption. See job log for deta
ATC5213	Pass phrase is null or invalid.
ATC5214	Enter key name or pass phrase, but not both.
ATC5215	Pass phrase translation error, see job log.
ATC5216	Invalid pass phrase length, must be from 1 to 32 characters.
ATC5217	Values provided for both key name and pass phrase. Provide only one.
ATC5218	Key name or pass phrase is required.
ATC5219	Error converting counter to **`ASCII`** .
ATC5220	Key type is null or invalid.
ATC5221	Invalid value for key type, must be `1` or `2` .
ATC5222	Error decrypting the pass phrase.
ATC5223	Implicit SSL option must be `1` for **`Yes`** or `2` for **`No`** .
ATC5224	File or member does not exist for text retrieval.

GID	TEXT
ATC5225	Error retrieving member text. See job log for details.
ATC5226	Unmonitored error in program **AN0184C** . Text for member not retrieved.
ATC5227	Error in program **AN0441R** retrieving member text. See job log for details.
ATC5228	Initialization vector is null or invalid.
ATC5229	Initialization vector option is null or invalid.
ATC5230	Initialization vector option must be **0** or **1** .
ATC5231	HMAC validation option is null or invalid.
ATC5232	HMAC validation option must be **0** or **1** .
ATC5233	Path to scan must start with “/”.
ATC5234	Path must be longer than 1 character.
ATC5235	Archive path must start with “/”.
ATC5236	Archive path must be longer than 1.
ATC5237	Memory allocaton failure.
ATC5238	Counter management option must be **1** for **Yes** or **2** for **No** .
ATC5239	Error retrieving Alliance key. Key name may be invalid.
ATC5240	Validate option is null or invalid.
ATC5241	Invalid value for validate option. Must be **1** or **0** .
ATC5242	HMAC value is null.
ATC5243	Error opening Alliance maske file ANMASK.
ATC5244	Error retrieving Mask record. See application log.
ATC5245	Memory allocation error on coding request.
ATC5246	Invalid length for Base16 decode request.
ATC5247	Error opening application control file ANAPPC.
ATC5248	Application does not have permission.

GID	TEXT
ATC5249	Invalid length of application control name.
ATC5250	Error opening user control file ANUSRC.
ATC5251	User does not have permission.
ATC5252	Invalid length of user control name.
ATC5253	Invalid length of file name.
ATC5254	Error opening field control file ANFLDC.
ATC5255	Field does not have permission for this key.
ATC5256	Error writing audit file AEHIST.
ATC5257	Error opening history log file AEHIST.
ATC5258	Log option is enabled, but key name is not defined.
ATC5259	Invalid length for log field.
ATC5260	Invalid length for key instance.
ATC5261	Key instance not found.
ATC5262	User name is blank.
ATC5263	Key name is blank.
ATC5264	Key does not exist in key file.
ATC5265	Status must be `1` for **`Active`** or `2` for **`Inactive`**.
ATC5266	Description is blank.
ATC5267	Invalid special value. Must be **`*ANY`**.
ATC5268	Application name is blank.
ATC5269	Record already exists and cannot be added.
ATC5270	AN0442R SSL: An error occurred setting the Firewall negotiation support.
ATC5271	Firewall option must be `1` for **`Yes`** or `2` for **`No`**.
ATC5272	Hash option is null or invalid.
ATC5273	Invalid value for has option. Must be `0` or `1`.

GID	TEXT
ATC5274	Hash option is invalid or null.
ATC5275	Invalid value for has option. Just be `1` or `2` .
ATC5276	Error in SHA-1 context initialization.
ATC5277	Error in SHA-1 input processing
ATC5278	Error in SHA-1 reset processing
ATC5279	Value for option must be `1` for **`Yes`** or `2` for **`No`** .
ATC5280	SSL option must be `1` for **`Yes`** (enabled) or `2` for **`No`** (disabled).
ATC5281	AN0442R SSL FTP: An error occurred setting the FTP environment for SSL Type supp
ATC5282	At least one SSL option must be enabled.
ATC5283	Directory name too long.
ATC5284	Error opening split file.
ATC5285	Input line longer than maximum.
ATC5286	File name is blank.
ATC5287	IFS file does not exist, or not authorized.
ATC5288	Directory for split files is blank.
ATC5289	Program error in AN6100E to split PGP files.
ATC5290	Command **`ALLPGPSPLT`** completed successfully.
ATC5291	ERROR: Unmonitored exception in command **`ALLPGPSPLT`** processing
ATC5292	Multiple files not detected. No split files created.
ATC5293	Job Run Priority must be in the range of `01` to `99` .
ATC5294	Job Run Priority could Not be changed.
ATC5295	Error creating list of files for assessment.
ATC5296	No files found in library to process.
ATC5297	Unmonitored exception is assessment program **`AN0185C`** .

GID	TEXT
ATC5298	Error creating list of libraries for assessment.
ATC5299	Unmonitored exception is assessment program **AN0186C** .
ATC5300	No libraries found to process.
ATC5301	Status must be 1 or 2.
ATC5302	Library name is blank.
ATC5303	Library name already exists.
ATC5304	Add file option must be **1** for **Yes** or **2** for **No** .
ATC5305	File description is blank.
ATC5306	File status must be **1** for **Active** or **2** for **Excluded** .
ATC5307	Library name is blank.
ATC5308	File name is blank.
ATC5309	File and library already exist.
ATC5310	Error creating list of fields. See job log for details.
ATC5311	Error, unmonitored exception in program **AN0187C** .
ATC5312	Field description is blank.
ATC5313	Field status must be 1, 2, 3 or 4.
ATC5314	Fields in file updated successfully.
ATC5315	Files in library updated successfully.
ATC5316	Search word description is blank.
ATC5317	Search word status must be **1** for **Active** or **2** for **Inactive** .
ATC5318	Search word is blank.
ATC5319	Search word already exists.
ATC5320	Host name is blank.
ATC5321	Error creating program references for library. See job log for details.

GID	TEXT
ATC5322	Error retrieving object type and attribute in program **AN6101E** .
ATC5323	Remote file name is blank.
ATC5324	Local file name is blank.
ATC5325	File type must be ***LIBRARY** or ***IFS** .
ATC5326	Library name is required when file type is ***LIBRARY** .
ATC5327	Directory name is required when file type is ***IFS** .
ATC5328	FTP host name is blank.
ATC5329	Port number must be in the range of 1 to 65535.
ATC5330	FTP user is blank.
ATC5331	FTP password is blank.
ATC5332	Log level must be ***LOW** , ***MEDIUM** or ***HIGH** .
ATC5333	SSL application ID is blank.
ATC5334	Clear Channel Command option must be ***YES** or ***NO** .
ATC5335	Delete option must be ***YES** or ***NO** .
ATC5336	Implicit SSL option must be ***YES** or ***NO** .
ATC5337	Intelligent firewall negotiation option must be ***YES** or ***NO** .
ATC5338	Allow SSLv2 option must be ***YES** or ***NO** .
ATC5339	Allow SSLv3 option must be ***YES** or ***NO** .
ATC5340	Allow TLSv1 option must be ***YES** or ***NO** .
ATC5341	FTP initialization failed at **FTPINIT** .
ATC5342	FTP session failed with **FTMLOG** .
ATC5343	FTP session failed setting log level with **FTPLOGLVL** .
ATC5344	FTP session failed with first trace with **FTMTrace** .
ATC5345	FTP session failed setting server port.
ATC5346	FTP session failed setting SSL session with **FTMSsl** .

GID	TEXT
ATC5347	FTP session failed setting firewall negotiation with **`FTMOrigAdr`** .
ATC5348	FTP session failed setting implicit SSL with **`FTMSslC`** .
ATC5349	Error setting SSL options with **`FTMSslType`** .
ATC5350	Error setting SSL application ID with **`FTMId`** .
ATC5351	Error opening connection to FTP server with **`FTMOpen`** .
ATC5352	Error opening FTP connection:
ATC5353	Error in FTP session in SSL authorization with **`FTMAuth`** .
ATC5354	Error on SSL authorization:
ATC5355	Error in FTP session in SSL buffer size.
ATC5356	Error on SSL buffer size:
ATC5357	Error in FTP session in SSL protection size.
ATC5358	Error on SSL protection type:
ATC5359	Error in FTP session in user name.
ATC5360	Error on FTP session for user name:
ATC5361	Error in FTP session in user password.
ATC5362	Error on FTP session for user password:
ATC5363	Error in FTP session in account.
ATC5364	Error on FTP session for account:
ATC5365	Error in FTP session in Clear Channel Command.
ATC5366	Error on FTP session for Clear Channel Command:
ATC5367	Error in FTP session in Site command 1.
ATC5368	Error on FTP session for Site command 1:
ATC5369	Error in FTP session in Site command 2.
ATC5370	Error on FTP session for Site command 2:
ATC5371	Error in FTP session in Site command 3.

GID	TEXT
ATC5372	Error on FTP session for Site command 3:
ATC5373	Error in FTP session in Change Directory.
ATC5374	Error on FTP session for Change Directory:
ATC5375	Error in FTP session in passive mode.
ATC5376	Error on FTP session for passive mode:
ATC5377	Error in FTP session in binary mode.
ATC5378	Error on FTP session for binary mode:
ATC5379	Error in FTP session in intelligent firewall negotiation.
ATC5380	Error in FTP session in library name format.
ATC5381	Error on FTP session for library name format: .
ATC5382	Error in FTP session in directory name format.
ATC5383	Error on FTP session for directory name format: .
ATC5384	Error in FTP session in file get.
ATC5385	Error on FTP session for file get: .
ATC5386	Error in FTP session in file delete.
ATC5387	Error on FTP session for file delete: .
ATC5388	Program error in AN0446R to get FTP file.
ATC5389	Command **FTPGETFILE** completed successfully.
ATC5390	ERROR, unmonitored exception in command **FTPGETFILE** .
ATC5391	Error in FTP session in file put.
ATC5392	Error on FTP session for file put: .
ATC5393	File or IFS file name required for transfer.
ATC5394	Specify file or IFS file, but not both.
ATC5395	Binary option must be ***YES** or ***NO** .
ATC5396	Program error in AN0447R to put FTP file.

GID	TEXT
ATC5397	Command **FTPPUTFILE** completed successfully.
ATC5398	ERROR, unmonitored exception in command **FTPPUTFILE** .
ATC5399	Program references updated for library.
ATC5400	Library **QTEMP** is not valid for this command.
ATC5401	Program description is blank.
ATC5402	Status must be 1, 2, 3 or 4.
ATC5403	Program library is blank.
ATC5404	Program name is blank.
ATC5405	Record already exists for this program.
ATC5406	Binary transfer option must be ***YES** or ***NO** .
ATC5407	Archive decrypted file option must be **1** or **2** .
ATC5408	Error opening locator file AENEXS.
ATC5409	Maximum value reached for replacement value 5.0S.
ATC5410	Maximum value reached for replacement value 7.0S.
ATC5411	Maximum value reached for replacement value 9.0S.
ATC5412	Maximum value reached for replacement value 15.0S.
ATC5413	Maximum value reached for replacement value 5.0P.
ATC5414	Maximum value reached for replacement value 7.0P.
ATC5415	Maximum value reached for replacement value 9.0P.
ATC5416	Maximum value reached for replacement value 15.0P.
ATC5417	Maximum value reached for replacement value 16Ctr.
ATC5418	Maximum value reached for replacement value 16Bin.
ATC5419	Error opening external store file AESTOR.
ATC5420	Error retrieving stored value from file AESTOR.
ATC5421	AN0448R: Error initializing FTP environment. Job cancelled.

GID	TEXT
ATC5422	AN0448R: Error initializing the application log.
ATC5423	AN0448R: Error setting the logging level.
ATC5424	AN0448R BELLSOUTH: An error occurred updating the application log.
ATC5425	AN0448R FTP: Error setting PORT number for FTP server.
ATC5426	AN0448R FTP: Error setting PORT number for FTP server.
ATC5427	AN0448R: Unable to open FTP site.
ATC5428	AN0448R: FTP open operation returned error code , text .
ATC5429	AN0448R: Unable to send the user ID.
ATC5430	AN0448R: FTP USER operation returned error code , text .
ATC5431	AN0442R: FTP USER operation returned error code , text .
ATC5432	AN0448R: Unable to send the password.
ATC5433	AN0448R: FTP PASS operation returned error code , text .
ATC5434	AN0442R SSL: Unable to change directory.
ATC5435	AN0448R: FTP CD operation returned error code , text .
ATC5436	AN0448R: Unable to set passive mode.
ATC5437	AN0448R: FTP PASV operation returned error code , text .
ATC5438	AN0448R: Unable to create file list.
ATC5439	AN0448R: FTP NLST operation returned error code , text .
ATC5440	AN0442R SSL: Unable to set binary mode for transfer.
ATC5441	AN0448R: FTP BINARY operation returned error code , text .
ATC5442	AN0448R: Unable to set passive mode.
ATC5443	AN0448R: FTP PASV operation returned error code , text .
ATC5444	AN0448R: Unable to set local name format to 0.
ATC5445	AN0448R: FTP NAMEFMT operation returned error code , text .

GID	TEXT
ATC5446	AN0448R: Unable to set local name format to 3.
ATC5447	AN0448R: FTP NAMEFMT operation for IFS returned error code , text .
ATC5448	AN0448R: Unable to retrieve file from IBM.
ATC5449	AN0448R: FTP GET operation returned error code , text .
ATC5450	AN0448R: Unable to delete file from server.
ATC5451	AN0448R: FTP DELETE operation returned error code , text .
ATC5452	AN0607C: The FTP receive program encountered an error.
ATC5453	AN0607C: Normal shutdown requested for FTP Manager FTP auto scan.
ATC5454	AN0607C: ERROR: Unmonitored exception in FTP Manager FTP auto scan.
ATC5455	Count parameter is null.
ATC5456	Invalid value to increment counter.
ATC5457	Pad option is null.
ATC5458	Invalid value for pad option.
ATC5459	Pad type is null.
ATC5460	Invalid value for pad type.
ATC5461	Output size is null.
ATC5462	Output size is too small, minimum size is 1.
ATC5463	Output size is too small for padded characters.
ATC5464	Invalid pad type specified.
ATC5465	Invalid length for unpadding operation. Must be a multiple of 16.
ATC5466	Invalid length for unpadding operation. Must be 16 or longer.
ATC5467	Error, key already exists in key file.
ATC5468	Error writing key to key file. Key not stored.

GID	TEXT
ATC5469	Key not found in key file.
ATC5470	HMAC validation error on retrieved key.
ATC5471	Error opening Protegrity key import file.
ATC5472	Error opening Protegrity key file AEPRTG.
ATC5473	Maximum number of keys (1024) exceeded.
ATC5474	Protegrity key import successful.
ATC5475	Option cancelled.
ATC5476	Unmonitored exception in program. See job log for details.
ATC5477	Input length must be a multiple of 16 for this option.
ATC5478	Error opening Protegrity key file AEPRTG.
ATC5479	Key not found in Protegrity key file.
ATC5480	Encryption key HMAC validation failed.
ATC5481	One key selected for import, but not found in file.
ATC5482	Key size must be **`*AES128`** , **`*AES192`** , or **`*AES256`** .
ATC5483	Invalid padding length. Corrupt data or wrong key to decrypt.
ATC5484	Number of pad characters greater than input length.
ATC5485	Error opening key manager file ANKEYM.
ATC5486	Error, key not found in key manager file.
ATC5487	Error opening GSK SSL environment.
ATC5488	Error in GSK initial setup.
ATC5489	Error in GSK initialization.
ATC5490	Error in GSK secure open.
ATC5491	Error in GSK socket creation.
ATC5492	Error in GSK SSL handshake.
ATC5493	Error creating TCP socket.

GID	TEXT
ATC5494	Error connecting to key management server.
ATC5495	Error sending data on SSL socket.
ATC5496	Error creating select set for data receive.
ATC5497	Error on TCP socket select operation.
ATC5498	TCP data socket not ready on read.
ATC5499	Error on data socket read, zero bytes received.
ATC5500	Error, time out waiting for response from key server.
ATC5501	Key server returned error: Invalid version number.
ATC5502	Key server returned error: Invalid transaction ID.
ATC5503	Key server returned error: Invalid character set.
ATC5504	Key server returned error: IP address authentication failure.
ATC5505	Key server returned error: Error retrieving key or key does not exist.
ATC5506	Key server returned error: Unknown error.
ATC5507	Memory allocation error. Contact programming support.
ATC5508	SSH server option is not enabled. Normal termination.
ATC5509	AN0210C: ERROR: Unmonitored exception in SSH server processing.
ATC5510	User for SSH server is blank.
ATC5511	User profile does not exist, or not authorized.
ATC5512	Alliance SSH Server: ERROR retrieving SSH server options.
ATC5513	Alliance SSH Server: ERROR starting SSH server.
ATC5514	Alliance SSH server normal shutdown.
ATC5515	FTP session type must be `1` for **`FTP`** or `2` for **`SSH sFTP`**.
ATC5516	INFO: Processing standard FTP session.
ATC5517	INFO: Processing SSH Secure FTP session.

GID	TEXT
ATC5518	ERROR calling Secure Shell SSH sFTP session for file /.
ATC5519	ERROR copying FTP script to Alliance SSH directory for FTP session .
ATC5520	FTP session type must be `1` for **`FTP`** or `2` for **`SSH Secure FTP`** .
ATC5521	AN0211C: Error returned by FTMFTPUSR2 for FTP user retrieval for file in direct
ATC5522	AN0211C: Error returned by FTMIPRTV for FTP domain and IP address in file in di
ATC5523	AN0211C: Error returned by AN0200 for FTP script name for file in directory .
ATC5524	AN0211C: Error in AN0211C attempting to copy FTP script, for file in directory
ATC5525	AN0211C: Error in SSH secure FTP session for file in directory .
ATC5526	ERROR, Failure connecting to Protegrity Defiance failover XC server.
ATC5527	SSH server job is not active.
ATC5528	SSH server shutdown in process.
ATC5529	User cancelled shutdown request.
ATC5530	ERROR - Unmonitored exception. See job log for more information.
ATC5531	SSH server is already active, not started.
ATC5532	ERROR submitting SSH server job. See job log for more information.
ATC5533	Alliance SSH server job submitted.
ATC5534	User cancelled option.
ATC5535	ERROR, Unmonitored exception in program. See job log for details.
ATC5536	Alliance SSH server already active, job not started.

GID	TEXT
ATC5537	Alliance SSH Server license error. Job canceled.
ATC5538	ERROR opening output sFTP shell command file.
ATC5539	ERROR writing to output sFTP shell command file.
ATC5540	Error retrieving FTP definition for file /.
ATC5541	FTP Manager sFTP session starting for .
ATC5542	ERROR: sFTP session completed with error code .
ATC5543	Alliance sFTP session successful.
ATC5544	ERROR: Unmonitored exception in program **`FTMSFTP`** for session .
ATC5545	Library scan: Failure on SSH sFTP of file / to FTP definition . Press ***HELP***.
ATC5546	Error retrieving FTP definition for file
ATC5547	ERROR calling Secure Shell SSH sFTP session for file .
ATC5548	IFS directory scan received error in FTP for session , file .
ATC5549	Error in stack entry API QWVRCSTK. No program stack entry retrieved.
ATC5550	Error in stack entry API QWVRCSTK. Zero stack entries returned.
ATC5551	Error: No entry in program stack has permission.
ATC5552	Error in call to QUSRJOBI to retrieve the current user.
ATC5553	ERROR submitting Alliance SSH server to job queue.
ATC5554	Alliance SSH Server submitted.
ATC5555	Default user is blank.
ATC5556	Default user does not exist, or not authorized.
ATC5557	ERROR, Facility ID is null.
ATC5558	ERROR, Time stamp is null.
ATC5559	ERROR, Host is null.

GID	TEXT
ATC5560	ERROR, Tag is null.
ATC5561	ERROR, Content is null.
ATC5562	ERROR, Convert option is null.
ATC5563	ERROR, Conversion table is null.
ATC5564	ERROR, Message is null.
ATC5565	ERROR, Message length is null.
ATC5566	AN0442R SSL: Unable to rename file from server.
ATC5567	AN0442R SSL: FTP RENAME operation returned error code , text .
ATC5568	Key manager record received I/O error on read. Record may be locked.
ATC5569	Key manager record not found for GET request.
ATC5570	Error writing new record to key manager file.
ATC5571	Error updating record in key manager file.
ATC5572	The key manager record was found, but did not have the requested type.
ATC5573	Invalid operation requested.
ATC5574	Error opening AES options file ANAESO.
ATC5575	Error retrieving AES options record.
ATC5576	Error sending entry to security audit journal QAUDJRN.
ATC5577	Encryption key is null.
ATC5578	Key size is null.
ATC5579	Invalid value for key size.
ATC5580	Text for HMAC is null.
ATC5581	Text length is null.
ATC5582	Invalid value for text length. Length must be greater than 0.
ATC5583	HMAC value is null.

GID	TEXT
ATC5584	Master key index is null.
ATC5585	Invalid special value. Use `*GEN` or file name.
ATC5586	Local file name is blank. Use `*GEN` or file name.
ATC5587	Biometric files already installed. Press ***F10*** to install again.
ATC5588	Error installing Biometric files. See job log for details.
ATC5589	Biometric files installed.
ATC5590	User cancelled option. Biometric support not installed.
ATC5591	ERROR, umonitored exception in program. See job log for details.
ATC5592	Error calling program `ALLVSSA` . Biometric support may not be installed.
ATC5593	Failure in biometric user authentication. See return code and text.
ATC5594	Biometric option must be `1` for `Yes` or `2` for `No` .
ATC5595	Biometric excluded user profile does not exist, or not authorized.
ATC5596	Press ***F10*** to update or ***F3*** to cancel.
ATC5597	Access denied by Biometric control. Reason code . Press ***HELP***.
ATC5598	ERROR calling Biometric access control. Access denied.
ATC5599	Value must be `1` for `Yes` or `2` for `No` .
ATC5600	Audit journal already exists, cannot start journaling (***HELP***).
ATC5601	Compliance journaling started.
ATC5602	User cancelled, journaling not started.
ATC5603	ERROR, unmonitored exception in program. See job log for more information.
ATC5604	Error, record not found in configuration file ANAESO.

GID	TEXT
ATC5605	Invalid operation code. This is an internal error, contact software support.
ATC5606	Alliance journal FTMAUD does not exist.
ATC5607	Compliance journaling ended.
ATC5608	User cancelled, journaling not ended.
ATC5609	ERROR, unmonitored exception in program. See job log for more information.
ATC5610	ERROR, Failure in XC Decrypt and failover is active.
ATC5611	ERROR, Failure in XC Decrypt and no failover is defined.
ATC5612	ERROR, Failure connecting to failover server after decrypt.
ATC5613	ERROR in decrypt after failover.
ATC5614	Random number is less than minimum length of 1.
ATC5615	Random number is greater than maximum length of 1024.
ATC5616	Length is null.
ATC5617	Format is null.
ATC5618	Invalid value for format.
ATC5619	Output is null.
ATC5620	Output length is null.
ATC5621	Output size is null.
ATC5622	Output size is null.
ATC5623	Output size is less than minimum.
ATC5624	Key generated and saved.
ATC5625	Error calling program **`AN0110R`** to generate key.
ATC5626	Alliance SDA files not installed (***HELP***).
ATC5627	Invalid key size for CMKY key file.
ATC5628	Invalid number of arguments on program call.

GID	TEXT
ATC5629	Input file name too long.
ATC5630	Output file name too long.
ATC5631	Error opening input file.
ATC5632	Error opening output file.
ATC5633	Error extracting version number from file.
ATC5634	Error reading key name length from input file.
ATC5635	Error reading key name from input file.
ATC5636	Error reading a block of data from input file.
ATC5637	Error writing block of data to output file.
ATC5638	Error opening output file for truncation operation.
ATC5639	Error truncating file to actual length.
ATC5640	Invalid length for file truncation.
ATC5641	Input file name is blank.
ATC5642	Output file name is blank.
ATC5643	Input file is the same as the output file.
ATC5644	Command AESFEMDEC completed normally.
ATC5645	Unmonitored exception in command **AESFEMDEC** . See job log for details.
ATC5646	Security audit journal QAUDJRN does not exist, or not authorized.
ATC5647	Object auditing started.
ATC5648	User cancelled, object auditing not started.
ATC5649	ERROR, unmonitored exception in program. See job log for more information.
ATC5650	No options selected for work.
ATC5651	Biometric validation failure: no match on fingerprint scan.
ATC5652	Biometric validation failure: User not enrolled.

GID	TEXT
ATC5653	Biometric validation failure: Other biometric access failure.
ATC5654	Biometric validation failure: Unspecified error.
ATC5655	Job type not interfactive for biometric operation.
ATC5656	Journal entry type is null.
ATC5657	Journal entry type length must be 2.
ATC5658	Journal entry data is null.
ATC5659	Minimum journal entry data length is 1.
ATC5660	Maximum journal entry data length is 32766.
ATC5661	Journal entry length is null.
ATC5662	Journal entry code is blank.
ATC5663	Security journal QAUDJRN does not exist, or not authorized (***HELP***).
ATC5664	Value must be `1` for `All` or `2` for `Failed Only`.
ATC5665	Configuration record not found. No logging record created.
ATC5666	SECURITY ALERT: Alliance system log failure (***HELP***).
ATC5667	Description is blank.
ATC5668	Value must be `1` for `Allowed` or `2` for `Not allowed`.
ATC5669	User is blank.
ATC5670	User already exists. Enter new name or press ***F12*** to cancel.
ATC5671	Error processing user control authentication (***HELP***).
ATC5672	Unmonitored exception processing user control authentication (***HELP***).
ATC5673	Access denied. User not authorized to function.
ATC5674	Biometric access option must be `1` for `Yes` or `2` for `No`.
ATC5675	Excluded user does not exist, or not authorized.
ATC5676	Press ***F10*** to enable Biometric control, or ***F12*** to cancel.

GID	TEXT
ATC5677	Invalid value for option.
ATC5678	AES encryption global configuration record not found.
ATC5679	Error opening AES options file ANAESO.
ATC5680	Time out must be in the range of 1 to 9999.
ATC5681	Error setting session time out value.
ATC5682	Error creating ALLAESUSR profile. See job log for more information.
ATC5683	Error creating ALLAESRPT profile. See job log for more information.
ATC5684	Error creating ALLAESADM profile. See job log for more information.
ATC5685	Unmonitored exception while creating Alliance AES user profiles.
ATC5686	Error creating authorization list ALLAESUSR. See job log for more information.
ATC5687	Error creating authorization list ALLAESRPT. See job log for more information.
ATC5688	Error creating authorization list ALLAESADM. See job log for more information.
ATC5689	Unmonitored exception while creating authorization lists.
ATC5690	ERROR in 128bit AES encryption during restore recovery.
ATC5691	ERROR writing save file during recovery. Restore operation not complete.
ATC5692	Error program option must be `1` for **`Error Only`**, or `2` for **`Always`**.
ATC5693	Session name is blank.
ATC5694	Library name is blank.
ATC5695	File name is blank.
ATC5696	Member name is blank.

GID	TEXT
ATC5697	File does not exist, or not authorized.
ATC5698	Error calling program **FTMSFTP** to process request.
ATC5699	Command **FTMSFTP** completed normally.
ATC5700	ERROR, unmonitored exception in command **FTMSFTP** .
ATC5701	Local IFS file is blank.
ATC5702	Remote file name is blank.
ATC5703	Error calling program **FTMSFTPD** to process request.
ATC5704	Command **FTMSFTPD** completed normally.
ATC5705	ERROR, unmonitored exception in command **FTMSFTPD** .
ATC5706	ERROR retrieving user information for Alliance PGP authentication.
ATC5707	Value must be **1** for **Yes** or **2** for **No** .
ATC5708	Error, file not transferred to sFTP server.
ATC5709	WARNING: sFTP file transfer may have encountered an error.
ATC5710	WARNING: sFTP file transfer may have encountered an error.
ATC5711	WARNING: sFTP file transfer may have encountered an error.
ATC5712	sFTP session completed normally.
ATC5713	Error submitting AES audit report.
ATC5714	AES Audit report submitted to batch.
ATC5715	Error calling AN8021 to run the AES audit report.
ATC5716	AES Audit report completed successfully.
ATC5717	ERROR, unmonitored exception in AES Audit Report job.
ATC5718	From Date is blank or invalid.
ATC5719	From Time is blank or invalid.

GID	TEXT
ATC5720	To Date is blank or invalid.
ATC5721	To Time is blank or invalid.
ATC5722	User access denied.
ATC5723	Maximum files must be in the range of 1 to 9999.
ATC5724	Rollover option must be `1`, `2` or `3`.
ATC5725	Rollover days must be in the range of 1 to 9999.
ATC5726	ERROR in encryption key rollover. See job log for more information.
ATC5727	Error retrieving key from key file ANAESK.
ATC5728	Error writing existing key to instance file. Key roll cancelled.
ATC5729	Error generating new key instance name. Instance already exists.
ATC5730	Invalid start date for date conversion.
ATC5731	Invalid start date format for date conversion.
ATC5732	Invalid end date for date conversion.
ATC5733	Invalid end date format for date conversion.
ATC5734	Invalid duration format for date conversion.
ATC5735	ERROR on encryption key rollover for key. Date conversion error.
ATC5736	ERROR on encryption key rollover for key. Date conversion error.
ATC5737	ERROR on encryption key rollover for key. Key not changed.
ATC5738	ERROR on encryption key rollover for key. Key was not changed.
ATC5739	Alliance encryption key changed. New key instance is now in effect.
ATC5740	Encryption key change error calling program **`AN0175`**.
ATC5741	Press ***F10*** to change the key, or press ***F3*** or ***F12*** to cancel.

GID	TEXT
ATC5742	Error retrieving encryption key record.
ATC5743	Encryption key not enabled for change (***HELP***).
ATC5744	SSH end of line option must be `1`, `2` or `3`.
ATC5745	FTMSSLLU: Unmonitored exception in program. See job log for details.
ATC5746	File I/O error retrieving the library scan file action record.
ATC5747	Error retrieving library scan file action record. Record not found.
ATC5748	FTMSSLLU: Error encrypting password. Update cancelled.
ATC5749	FTMSSLDU: Unmonitored exception in program. See job log for details.
ATC5750	File I/O error retrieving the directory scan file action record.
ATC5751	Error retrieving directory scan file action record. Record not found.
ATC5752	FTMSSLDU: Error encrypting password. Update cancelled.
ATC5753	FTMSSLAU: Unmonitored exception in program. See job log for details.
ATC5754	File I/O error retrieving the auto-scan record.
ATC5755	Error retrieving auto-scan record. Record not found.
ATC5756	FTMSSLAU: Error encrypting password. Update cancelled.
ATC5757	DIRECTORY NAME IS BLANK.
ATC5758	FTMDFSTAT: ERROR CALLING INTERNAL PROGRAM. CONTACT PROGRAMMING SUPPORT.
ATC5759	FTMDFSTAT: UNMONITORED EXCEPTION IN PROGRAM. SEE JOBLOG FOR DETAILS.
ATC5760	SENDSPLF: Error <> on call to API205 to convert spool file to work file.
ATC5761	SENDSPLF: Error <> on call to API209 to create PDF file.

GID	TEXT
ATC5762	SENDSPLF: Error <> on call to API200 to send email to recipient.
ATC5763	SENDSPLF successful completion.
ATC5764	ERROR: Unmonitored exception in `SENDSPLF` command. See job log for details.
ATC5765	Alliance SSH sFTP password support already installed. Use ***F10*** to override.
ATC5766	Error installing SSH sFTP files. See job log for details.
ATC5767	SSH sFTP password files installed.
ATC5768	SSH sFTP password installation option cancelled.
ATC5769	ERROR, umonitored exception in program. See job log for details.
ATC5770	SSH sFTP password option must be `1` or `2` .
ATC5771	SSH sFTP name is blank.
ATC5772	SSH sFTP path is blank.
ATC5773	SSH sFTP template program not installed (***HELP***).
ATC5774	Error copying SSH sFTP template program.
ATC5775	Error changing ownership to specified user.
ATC5776	Error removing *PUBLIC authority to the SSH sFTP program.
ATC5777	An unmonitored exception occurred when creating the SSH sFTP program.
ATC5778	Error retrieving FTP definition for file /.
ATC5779	SSH user is blank.
ATC5780	Error running QShell to add the SSH user. See job log for details.
ATC5781	Add SSH user completed.
ATC5782	User cancelled option to add SSH user.
ATC5783	Unmonitored error. See job log for more information.

GID	TEXT
ATC5784	SSH server address is blank.
ATC5785	Error running QShell to add user.
ATC5786	SSH Server job complete.
ATC5787	User cancelled SSH server job.
ATC5788	Unmonitored exception. See jog for details.
ATC5789	SSL application id is blank.
ATC5790	Error opening ANAESI key instance file.
ATC5791	Error calling encryption routine DESENCR1. Check library list.
ATC5792	Record not found in encrytion data store.
ATC5793	Error calling decryption routine DESDECR1. Check library list.
ATC5794	Error calling program PGP for Command Line 9 execution.
ATC5795	Unmonitored error while running PGP Command Line 9. See job log.
ATC5796	PGP version must be 1 for NAI v7, or 2 for PGP CL 9.
ATC5797	Error encountered changing command defaults. See job log for details.
ATC5798	PGP default directory is required.
ATC5799	Using PGP Command Line 9.
ATC5800	Suppress close_notify must be 1 or 2.
ATC5801	Error enabling SSL Close_Notify.
ATC5802	INFO: PGP version is NAI 7
ATC5803	INFO: PGP version is CL 9
ATC5804	PGP output file:
ATC5805	Function not supported by this version of PGP.
ATC5806	PGP version must be 1 for NAI 7 or 2 for PGP CL 9.

GID	TEXT
ATC5807	Error creating user profile ALLAES for application ownership.
ATC5808	Error changing user profile ALLAES for application ownership.
ATC5809	Error creating authorization list for application owner.
ATC5810	Error adding user ALLAES to authorization list.
ATC5811	Error adding user QSECOFR to authorization list.
ATC5812	Ownership implemented for user ALLAES.
ATC5813	User cancelled option.
ATC5814	ERROR, umonitored exception in program. See job log for details.
ATC5815	Too many open files in this process.
ATC5816	PGP CL 9 license file PGPPrefs.xml not found in this directory (***HELP***).
ATC5817	Invalid date.
ATC5818	Program name and library are required.
ATC5819	Error in library exit program / processing file .
ATC5820	Library option must be `1` or `2` .
ATC5821	At least one library must be specified.
ATC5822	Decryption masking option must be `1` for `Yes` or `2` for `No` .
ATC5823	Decryption masking type must be 1 or 2.
ATC5824	Error in command `AESSAVFDTS` . Job may not have completed successfully.
ATC5825	Error in command `AESSAVFDFS` . Job may not have completed successfully.
ATC5826	PGP license option cancelled.
ATC5827	ERROR, umonitored exception in program. See job log for details.
ATC5828	ERROR logging sFTP session to QAUDJRN for file /.

GID	TEXT
ATC5829	ERROR logging sFTP session to QAUDJRN for file /.
ATC5830	Key name is blank.
ATC5831	Key type must be 1, 2, 3 or 4.
ATC5832	Tokenization server is not installed (***HELP***).
ATC5833	Alliance encryption key date created date changed to current date.
ATC5834	GetHostByName failed to resolve the IP address.
ATC5835	IP Address was resolved, but not AF_INET connection.
ATC5836	Domain name resolved, but IP address is not available.
ATC5837	Directory scan received error in FTP session.
ATC5838	Error connecting to failover key server.
ATC5839	FTP definition is blank.
ATC5840	FTP definition does not exist.
ATC5841	FTP definition is not active for SSH sFTP auto-scan.
ATC5842	Exclude hidden files option must be `1` for `Yes` or `2` for `No`.
ATC5843	WARNING: No command: sFTP file transfer may have encountered an error.
ATC5844	Retrieval type must be 1 (All) for sFTP scan type.
ATC5845	Error creating SSH sFTP server list of files for definition .
ATC5846	AN0608C: The SSH sFTP scan retrieve program FTMSFTPGET encountered an error.
ATC5847	AN0608C: Normal shutdown requested for FTP Manager FTP SSH auto scan.
ATC5848	AN0608C: ERROR: Unmonitored exception in FTP Manager FTP SSH auto scan.
ATC5849	SSH user is blank.
ATC5850	Delete after receive must be `1` for `Yes` or `2` for `No`.

GID	TEXT
ATC5851	Error, file not removed from sFTP server.
ATC5852	WARNING, file many not have been removed from sFTP server.
ATC5853	WARNING, file may not have been removed from sFTP server.
ATC5854	ERROR, the file could not be removed from the sFTP server.
ATC5855	ERROR, SSH autoscan encountered an error with SSHAUTO script.
ATC5856	ERROR, SSH autoscan encountered an error with SSHDLT script.
ATC5857	Port number must be in the range of 1 to 65535.
ATC5858	Directory name is blank.
ATC5859	Option must be `1` for `Yes` or `2` for `No`.
ATC5860	Error retrieving current directory options.
ATC5861	Changing current directory to root (/).
ATC5862	Retaining job current directory.
ATC5863	Key does not exist in key file.
ATC5864	ERROR creating user home directory.
ATC5865	AN0448R: Error setting passive mode for directory attributes.
ATC5866	AN0448R: FTP PASV operation for directory attributes returned error code , text
ATC5867	AN0448R: Error sending LIST for directory attributes.
ATC5868	AN0448R: FTP LIST operation for directory attributes returned error code , text
ATC5869	RSA Client: Return code is null.
ATC5870	RSA Client: Configuration file is null.
ATC5871	RSA Client: Configuration file name too long.
ATC5872	RSA Client: Key class is null.

GID	TEXT
ATC5873	RSA Client: Key ID is null.
ATC5874	RSA Client: Key is null.
ATC5875	RSA Client: Key size is null.
ATC5876	RSA Client: Response Key ID is null.
ATC5877	RSA Client: Response Key ID length is null.
ATC5878	RSA Client: Response Key length is null.
ATC5879	RSA Client: Key class name longer than maximum.
ATC5880	RSA Client: Key ID name longer than maximum.
ATC5881	RSA Client: Error initializing client library.
ATC5882	RSA Client: Response key ID size is null.
ATC5883	Key definition must have a length greater than 0 and less that 64.
ATC5884	RSA Key ID is longer than 20 bytes.
ATC5885	License is not valid.
ATC5886	Error creating pointer to user space.
ATC5887	Error overriding tape file.
ATC5888	Error on tape open.
ATC5889	Memory allocation error.
ATC5890	Data compression error.
ATC5891	Error on PKCS5 padding.
ATC5892	Error in AES ECB mode encryption.
ATC5893	Error writing file to tape.
ATC5894	Error writing file to tape.
ATC5895	Error creating user space.
ATC5896	Error on call to QaneSava API program.
ATC5897	Error deleting user space.

GID	TEXT
ATC5898	Error on call to QaneRsta API program.
ATC5899	Error initializing application log.
ATC5900	Invalid number of arguments passed to program.
ATC5901	Error in AES ECB mode decryption.
ATC5902	Requested zip action does not match value on tape.
ATC5903	Error on PKCS5 unpadding.
ATC5904	Data uncompression error.
ATC5905	Invalid length for unpadding.
ATC5906	Invalid block length for unpadding. Must be multiple of 16.
ATC5907	KMS client has not been initialized. Call the RSAInit procedure to initialize.
ATC5908	Library name is blank.
ATC5909	Not authorized to library, or library does not exist.
ATC5910	Encryption key name is blank.
ATC5911	At least one tape device is required.
ATC5912	Tape device 1 does not exist, or not authorized.
ATC5913	Tape device 2 does not exist, or not authorized.
ATC5914	Tape device 3 does not exist, or not authorized.
ATC5915	Tape device 4 does not exist, or not authorized.
ATC5916	Tape file is blank.
ATC5917	Tape file library does not exist, or not authorized.
ATC5918	Tape file does not exist, or not authorized.
ATC5919	Tape density is blank or invalid.
ATC5920	Target release is blank or invalid.
ATC5921	Command **SAVLIBDTT** completed successfully.

GID	TEXT
ATC5922	ERROR, Unmonitored exception in command **SAVLIBDTT** . See job log for details.
ATC5923	Tape sequence number is blank or invalid.
ATC5924	Restore library name is blank or invalid.
ATC5925	Command **RSTLIBDFT** completed successfully.
ATC5926	ERROR, Unmonitored exception in command **RSTLIBDFT** . See job log for details.
ATC5927	Error opening key file ANAESK.
ATC5928	Key not found in file ANAESK.
ATC5929	Error opening file ANAESI.
ATC5930	Error retrieving record from file ANAESI.
ATC5931	Key derivation error.
ATC5932	Key derivation error on salt.
ATC5933	Key derivation error on verification.
ATC5934	Requested zip action does not match value on tape.
ATC5935	Encryption key on tape does not match encryption key requested.
ATC5936	Encryption key instance on tape does not match encryption key requested.
ATC5937	Requested zip action does not match value on tape.
ATC5938	Error displaying field list for file.
ATC5939	Error opening field list file.
ATC5940	Error deleting file / on auto purge.
ATC5941	No libraries specified for operation.
ATC5942	Processing library for save.
ATC5943	Error saving library , continuing save.

GID	TEXT
ATC5944	Command **SAVLIBDTTM** completed successfully. libraries not saved.
ATC5945	ERROR, Unmonitored exception in command **SAVLIBDTTM** . See job log for details.
ATC5946	Processing libraries.
ATC5947	Processing library for restore.
ATC5948	Error restoring library , continuing restore.
ATC5949	Command **RSTLIBDFTM** completed successfully. libraries not restored.
ATC5950	ERROR, Unmonitored exception in command **RSTLIBDFTM** . See job log for details.
ATC5951	Assessment product license error. Please contact your software vendor.
ATC5952	Invalid option. Correct option and press ***Enter***.
ATC5953	Input data is null.
ATC5954	Input length is null.
ATC5955	Is Numeric field is null.
ATC5956	Credit card number (PAN) is null.
ATC5957	Luhn field is null.
ATC5958	Input length must be in the range of 13 to 19.
ATC5959	Non-digit character in Luhn check.
ATC5960	Error creating field list in library **QTEMP** . See job log for details.
ATC5961	Unmonitored error in file scan application. See job log for details.
ATC5962	Error calling program **AN0016C** for file scan.
ATC5963	File name is blank.
ATC5964	File does not exist, or not authorized.

GID	TEXT
ATC5965	Command **SCANFILE** successful completion.
ATC5966	Unmonitored error in command **SCANFILE** .
ATC5967	Total number of numeric-only fields:
ATC5968	Total number of card-valid fields:
ATC5969	Total number of LUHN-valid fields:
ATC5970	Invalid file type for scan. Only data files can be scanned.
ATC5971	Command **SCANLIBR** successful completion.
ATC5972	Unmonitored error in command **SCANLIBR** .
ATC5973	Press ***F3*** or ***F12*** to return.
ATC5974	Restore to library does not exist, or not authorized.
ATC5975	No objects specified for operation.
ATC5976	No object types specified for operation.
ATC5977	Key is already active.
ATC5978	Key is already revoked.
ATC5979	Key is pending, no change is allowed until key is complete.
ATC5980	Key is in pending state and not available for use.
ATC5981	Key has been revoked and is not available for use.
ATC5982	Alliance Key Manager key name is required.
ATC5983	Alliance Key Manager, less than 13 bytes received on read.
ATC5984	Alliance Key Manager, too many bytes read from key server.
ATC5985	Alliance Key Manager, invalid transaction ID. Must be 2002.
ATC5986	Alliance Key Manager, error returned from key server. See key server log.
ATC5987	SSH list files script is blank. (***HELP***)
ATC5988	INFO: PGP version is VER1
ATC5989	ERROR in PGP operation. See the job log.

GID	TEXT
ATC5990	Key store file is blank.
ATC5991	Key store password is blank.
ATC5992	Logging option must be ***NONE** or ***VERBOSE** .
ATC5993	Java output must be ***** , ***NONE** , or ***PRINT** .
ATC5994	Java version is blank.
ATC5995	Classpath is blank.
ATC5996	Remote file name is blank.
ATC5997	Remote directory is blank.
ATC5998	Local directory is blank.
ATC5999	Error calling program **FTMSFTPGET** . See job log for details.
ATC6000	Command **FTMSFTPGET** completed normally.
ATC6001	Unmonitored exception in command **FTMSFTPGET** . See job log for details.
ATC6002	File name for zip operation is blank.
ATC6003	Encrypt option must be ***YES** or ***NO** .
ATC6004	Password is required with encryption option is ***YES** .
ATC6005	Include directory in name option must be ***YES** or ***NO** .
ATC6006	Include directory subtree option must be ***ALL** or ***NONE** .
ATC6007	Include directories option must be ***YES** or ***NO** .
ATC6008	Error running zip option. See the joblog for more information (***HELP***).
ATC6009	Command **FTMZIP** completed normally.
ATC6010	ERROR, unmonitored exception in command **FTMZIP** .
ATC6011	Zip files already installed. Press ***F10*** to install again.
ATC6012	Error installing ZIP IFS files. See job log for details.
ATC6013	ZIP IFS files installed.

GID	TEXT
ATC6014	ZIP installation option cancelled.
ATC6015	ERROR, unmonitored exception in program. See job log for details.
ATC6016	AES command completed normally.
ATC6017	Unmonitored exception in AES command.
ATC6018	Passwords do not match, try again.
ATC6019	PGP files already installed. Press ***F10*** to install again.
ATC6020	Error installing PGP IFS files. See job log for details.
ATC6021	PGP IFS files installed.
ATC6022	PGP installation option cancelled.
ATC6023	ERROR, unmonitored exception in program. See job log for details.
ATC6024	ZIP AES option must be `1` for `Yes` or `2` for `No`.
ATC6025	Pass phrase is blank.
ATC6026	Pass phrases do not match, try again.
ATC6027	Option must be `1` for `Yes` or `2` for `No`.
ATC6028	Translation table is blank.
ATC6029	Invalid end of line option.
ATC6030	Zip AES files are not installed (***HELP***).
ATC6031	Error creating ZIP AES archive.
ATC6032	ZIP AES encryption session successful.
ATC6033	Control IFS file does not exist, or not authorized.
ATC6034	File directory check failed on return to original directory.
ATC6035	Decryption requested but password is blank.
ATC6036	Overwrite files option must be `*YES` or `*NO`.
ATC6037	Control file name is blank.

GID	TEXT
ATC6038	Output PDF file name is blank.
ATC6039	Replace option must be **`*YES`** or **`*NO`** .
ATC6040	Encrypt option must be **`*YES`** or **`*NO`** .
ATC6041	User password is required for encryption.
ATC6042	Owner password is required for encryption.
ATC6043	Error running PDF option. See the joblog for more information (***HELP***).
ATC6044	Command **`FTMPDF`** completed normally.
ATC6045	ERROR, unmonitored exception in command **`FTMPDF`** .
ATC6046	Error deleting encrypted spooled file archive.
ATC6047	PDF files already installed. Press ***F10*** to install again.
ATC6048	Error installing PDF IFS files. See job log for details.
ATC6049	PDF IFS files installed.
ATC6050	PDF installation option cancelled.
ATC6051	ERROR, unmonitored exception in program. See job log for details.
ATC6052	PGP authority reset complete.
ATC6053	PGP version is invalid.
ATC6054	PGP key directory is blank.
ATC6055	PGP user is blank.
ATC6056	Pass phrase is blank.
ATC6057	PGP key generation complete.
ATC6058	User cancelled option.
ATC6059	Error, unmonitored exception in program
ATC6060	PGP default directory is blank (***HELP***).
ATC6061	Directory does not exist, or not authorized.

GID	TEXT
ATC6062	SSH sFTP session ended in error. Return code:
ATC6063	Command **FTMSFTPEXC** completed normally.
ATC6064	Unmonitored exception in **FTMSFTPEXC** command for session
ATC9993	(C) Townsend Security, 2004
ATC9994	
ATC9995	
ATC9997	Version 5.20
ATC9998	Message not found in message file.
FTP0000	Error in FTP Manager control program.
FTP0001	Unmonitored exception in program **AN0281C** . See job log for details.
FTP0002	Error, time-out waiting for batch process to initialize.
FTP0003	Error initializing FTP processor session.
FTP0004	Option must be ***YES** or ***NO** .
FTP0005	Error initializing FTP session.
FTP0006	Error submitting FTP session processor. See job log for details.
FTP0007	Command **FTPINIT** completed successfully.
FTP0008	Unmonitored exception in command. See job log for details.
FTP0009	Remote system is blank or invalid.
FTP0010	FTP server data queue does not exist.
FTP0011	FTP client data queue does not exist.
FTP0012	Command **FTPOPEN** completed successfully.
FTP0013	Time out waiting for **FTMOPEN** to complete.
FTP0014	Error processing **FTPOPEN** command.
FTP0015	Error initializing logging routines.

GID	TEXT
FTP0016	Product license error.
FTP0017	Error: library name is ***LIBL** or ***CURLIB** .
FTP0018	The library does not exist, or not authorized.
FTP0019	Error creating file in library.
FTP0020	Error adding member to file.
FTP0021	Error, unmonitored exception attempting to create file in **CVTCRTFILE** .
FTP0022	Command **FTPQUIT** completed successfully.
FTP0023	Error processing **FTPQUIT** command.
FTP0024	FTP user is blank or invalid.
FTP0025	Command **FTPUSER** completed successfully.
FTP0026	Error processing **FTPUSER** command.
FTP0027	Time out waiting for **FTMUSER** to complete.
FTP0028	Password is blank.
FTP0029	Command **FTPPASS** completed successfully.
FTP0030	Error processing **FTPPASS** command.
FTP0031	Path for Change Directory is blank.
FTP0032	Command **FTPCD** completed successfully.
FTP0033	Error processing **FTPCD** command.
FTP0034	Command **FTPABOR** completed successfully.
FTP0035	Error processing **FTPABOR** command.
FTP0036	Path for the Append is blank.
FTP0037	Error processing **FTPAPPE** command.
FTP0038	Command **FTPAPPE** completed successfully.
FTP0039	File name is blank.
FTP0040	Command **FTPDELE** completed successfully.

GID	TEXT
FTP0041	Error processing **FTPDELE** command.
FTP0042	Remote file name for GET is blank.
FTP0043	Command **FTPGET** completed successfully.
FTP0044	Error processing **FTPGET** command.
FTP0045	Command **FTPHELP** completed successfully.
FTP0046	Error processing **FTPHELP** command.
FTP0047	Command **FTPLIST** completed successfully.
FTP0048	Error processing **FTPLIST** command.
FTP0049	File name required for **MGET** command.
FTP0050	Command **FTPMGET** completed successfully.
FTP0051	Error processing **FTPMGET** command.
FTP0052	Directory name is blank.
FTP0053	Command **FTPMKD** completed successfully.
FTP0054	Error processing **FTPMKD** command.
FTP0055	Invalid mode parameter. Mode must be ***STREAM** or ***BLOCK** .
FTP0056	Command **FTPMODE** completed successfully.
FTP0057	Error processing **FTPMODE** command.
FTP0058	Name format must be ***LIBRARY** , ***IFS** , ***LCLLIB** , or ***LCLIFS** .
FTP0059	Command **FTPNAMEFMT** completed successfully.
FTP0060	Error processing **FTPNAMEFMT** command.
FTP0061	Command **FTPLS** completed successfully.
FTP0062	Error processing **FTPLS** command.
FTP0063	Command **FTPMPUT** completed successfully.
FTP0064	Error processing **FTPMPUT** command.

GID	TEXT
FTP0065	Command **FTPNOOP** completed successfully.
FTP0066	Error processing **FTPNOOP** command.
FTP0067	Command **FTPPASV** completed successfully.
FTP0068	Error processing **FTPPASV** command.
FTP0069	IP address is blank or invalid.
FTP0070	Port number is invalid.
FTP0071	Command **FTPPORT** completed successfully.
FTP0072	Error processing **FTPPORT** command.
FTP0073	Command **FTPPWD** completed successfully.
FTP0074	Error processing **FTPPWD** command.
FTP0075	Directory name is blank.
FTP0076	Command **FTPRMD** completed successfully.
FTP0077	Error processing **FTPRMD** command.
FTP0078	File name for rename is blank.
FTP0079	Command **FTPRNFR** completed successfully.
FTP0080	Error processing **FTPRNFR** command.
FTP0081	File name for rename is blank.
FTP0082	Command **FTPRNTO** completed successfully.
FTP0083	Error processing **FTPRNTO** command.
FTP0084	Site command is blank.
FTP0085	Command **FTPSITE** completed successfully.
FTP0086	Error processing **FTPSITE** command.
FTP0087	Command **FTPSTAT** completed successfully.
FTP0088	Error processing **FTPSTAT** command.
FTP0089	File name for STOR operation is blank.

GID	TEXT
FTP0090	Command **FTPSTOR** completed successfully.
FTP0091	Error processing **FTPSTOR** command.
FTP0092	File name for STOU operation is blank.
FTP0093	Command **FTPSTOU** completed successfully.
FTP0094	Error processing **FTPSTOU** command.
FTP0095	Structure type must be ***FILE** or ***RECORD** .
FTP0096	Command **FTPSTRU** completed successfully.
FTP0097	Error processing **FTPSTRU** command.
FTP0098	SSL option must be ***ON** or ***OFF** .
FTP0099	Command **FTPSSL** completed successfully.
FTP0100	Error processing **FTPSSL** command.
FTP0101	Authorization type is blank or invalid.
FTP0102	Command **FTPAUTH** completed successfully.
FTP0103	Error processing **FTPAUTH** command.
FTP0104	SSL command channel application ID is blank.
FTP0105	SSL data channel application ID is blank.
FTP0106	Command **FTPSSLID** completed successfully.
FTP0107	Error processing **FTPSSLID** command.
FTP0108	Protection must be ***PRIVATE** , ***SAFE** , ***CLEAR** or ***CONFID** .
FTP0109	Command **FTPPROT** completed successfully.
FTP0110	Error processing **FTPPROT** command.
FTP0111	Invalid value for protection buffer size.
FTP0112	Command **FTPPBSZ** completed successfully.
FTP0113	Error processing **FTPPBSZ** command.
FTP0114	Log option must be ***ON** or ***OFF** .

GID	TEXT
FTP0115	Command **FTPLOG** completed successfully.
FTP0116	Error processing **FTPLOG** command.
FTP0117	Port number is invalid.
FTP0118	Command **FTPSVRPORT** completed successfully.
FTP0119	Error processing **FTPSVRPORT** command.
FTP0120	Command **FTPLOCFMT** completed successfully.
FTP0121	Error processing **FTPLOCFMT** command.
FTP0122	Invalid record length, must be in the range of 1 to 32766.
FTP0123	Command **FTPRECLEN** completed successfully.
FTP0124	Error processing **FTPRECLEN** command.
FTP0125	FTP command log value must be ***YES** or ***NO** .
FTP0126	Trace API usage value must be ***YES** or ***NO** .
FTP0127	Dump command channel in **EBCDIC** option must be ***YES** or ***NO** .
FTP0128	Dump command channel in **ASCII** option must be ***YES** or ***NO** .
FTP0129	Dump data channel in **EBCDIC** option must be ***YES** or ***NO** .
FTP0130	Dump data channel in **ASCII** option must be ***YES** or ***NO** .
FTP0131	Dump SSL certification information must be ***YES** or ***NO** .
FTP0132	Dump internal data option must be ***YES** or ***NO** .
FTP0133	Command **FTPLOGLVL** completed successfully.
FTP0134	Error processing **FTPLOGLVL** command.
FTP0135	Dump function information option must be ***YES** or ***NO** .
FTP0136	Session name is blank.
FTP0137	Completion code is blank.
FTP0138	FTP completion text is blank.

GID	TEXT
FTP0139	Command **FTPHISTORY** completed successfully.
FTP0140	Error processing **FTPHISTORY** command.
FTP0141	Certificate passthrough option must be ***YES** or ***NO** .
FTP0142	Command **FTPCERTPAS** completed successfully.
FTP0143	Error processing **FTPCERTPAS** command.
FTP0144	The STOU send file option must be ***YES** or ***NO** .
FTP0145	Directory type must be ***LIBRARY** or ***IFS** .
FTP0146	Directory is blank.
FTP0147	Command **FTPLCD** completed successfully.
FTP0148	Error processing **FTPLCD** command.
FTP0149	Original IP address option must be ***ON** or ***OFF** .
FTP0150	Command **FTPORIGADR** completed successfully.
FTP0151	Error processing **FTPORIGADR** command.
FTP0152	SSL V2 type must be ***ON** or ***OFF** .
FTP0153	SSL V3 type must be ***ON** or ***OFF** .
FTP0154	TLS V1 type must be ***ON** or ***OFF** .
FTP0155	Command **FTPSSLTYPE** completed successfully.
FTP0156	Error processing **FTPSSLTYPE** command.
FTP0157	Time out value is invalid.
FTP0158	Command **FTPTIMEOUT** completed successfully.
FTP0159	Error processing **FTPTIMEOUT** command.
FTP1000	Command **FTPSYST** completed successfully.
FTP1001	Error processing **FTPSYST** command.
FTP1002	Transfer type must be ***ASCII** , ***EBCDIC** , ***IMAGE** , or ***LOCAL** .
FTP1003	Byte size must be in the range of 1 to 128.

GID	TEXT
FTP1004	Byte size must be in the range of 1 to 128.
FTP1005	Form code must be ***NONPRINT** , ***TELNET** , or ***CARRIAGE** .
FTP1006	Command **FTPTYPE** completed successfully.
FTP1007	Error processing **FTPTYPE** command.
FTP1008	File name for PUT operation is blank.
FTP1009	Command **FTPPUT** completed successfully.
FTP1010	Error processing **FTPPUT** command.
FTP1011	Replace option must be ***YES** or ***NO** .
FTP1012	Remote file name for RETR is blank.
FTP1013	Replace option must be ***YES** or ***NO** .
FTP1014	Command **FTPRETR** completed successfully.
FTP1015	Error processing **FTPRETR** command.
FTP1016	Verbose option must be ***ON** or ***OFF** .
FTP1017	Command **FTPVERBOSE** completed successfully.
FTP1018	Error processing **FTPVERBOSE** command.
FTP1019	Device path required for **System Mount** command.
FTP1020	Command **FTPSMNT** completed successfully.
FTP1021	Error processing **FTPSMNT** command.
FTP1022	Command **FTPASCII** completed successfully.
FTP1023	Error processing **FTPASCII** command.
FTP1024	Command **FTPEBCDIC** completed successfully.
FTP1025	Error processing **FTPEBCDIC** command.
FTP1026	Command **FTPBINARY** completed successfully.
FTP1027	Error processing **FTPBINARY** command.
FTP1028	Command **FTPCWD** completed successfully.

GID	TEXT
FTP1029	Error processing **FTPCWD** command.
FTP1030	Command **FTPCDUP** completed successfully.
FTP1031	Error processing **FTPCDUP** command.
FTP1032	Command **FTPCLOSE** completed successfully.
FTP1033	Error processing **FTPCLOSE** command.
FTP1034	Command **FTPDIR** completed successfully.
FTP1035	Error processing **FTPDIR** command.
FTP1036	Command **FTPMKDIR** completed successfully.
FTP1037	Error processing **FTPMKDIR** command.
FTP1038	Command **FTPNLST** completed successfully.
FTP1039	Error processing **FTPNLST** command.
FTP1040	Command **FTPREIN** completed successfully.
FTP1041	Error processing **FTPREIN** command.
FTP1042	Restart marker is blank.
FTP1043	Command **FTPREST** completed successfully.
FTP1044	Error processing **FTPREST** command.
FTP1045	Command **FTPREST** completed successfully.
FTP1046	Error processing **FTPREST** command.
FTP1047	File name for rename operation is blank.
FTP1048	New name for file is blank.
FTP1049	Command **FTPRENAME** completed successfully.
FTP1050	Error processing **FTPRENAME** command.
FTP1051	Get operation failed, file already exists.
FTP1052	Time out waiting for response to **FTPQUIT** command.
FTP1053	Error processing **FTPQUIT** command. See application log for more information.

GID	TEXT
FTP3327	Command **FTPCCC** completed successfully.
FTP3328	Error processing **FTPCCC** command.
FTP3349	Error retrieving FTP client options.
FTP3350	Command **FTPCLSNTFY** completed successfully.
FTP3351	Error processing **FTPCLSNTFY** command.
FTP3352	Error retrieving member name. CPF3C23 File is not a database file.
FTP3353	Error retrieving member name. CPF3C26 File has no members.
FTP3354	Error retrieving member name. CPF9812 File not found.
FTP3355	Error retrieving member name. CPF9822 Not authorized to file.
FTP3356	Error retrieving member name. CPF9820 Not authorized to library.
FTP3357	Unknown error received while trying to retrieve member name.