

1 System Model and Practical Challenges in Over-the-Air (OTA)

A system that takes advantage of OTA can be modeled in different ways, also depending on the use case and environment. Most layouts involve a number of End Device (ED)s that transmit to a Fusion Center (FC) or Edge Server (ES). The channel model is also an important aspect, as it can be affected by fading, noise, and path loss. In addition to the system model, there are also practical challenges that can affect the reliability of OTA, such as synchronization errors and waveform design. To enhance the performance of OTA, optimization strategies can be employed, such as power management and transceiver design.

1.a System Architecture and Channel Model

In this section the mathematical model of a network consisting of three EDs will be presented. These devices are deployed at an agricultural field and take advantage of OTA in order to transmit to the FC, by using Pulse Amplitude Modulation (PAM). The physical environment has multipath characteristics and an impulse response with a span of three taps.

- *Modeling the Network:* Description of EDs transmitting to an FC, possibly involving multiple antennas (Multiple-Input Multiple-Output (MIMO))[1], [2], [3], [4], [5].
 - **Sensor 1:** $x_1[n] = [2, -1, 1]$
 - **Sensor 2:** $x_2[n] = [1, 2, -1]$
- *Wireless Channel Model:* Consideration of channel impairments, including fading (e.g., Rayleigh fading), noise (Additive White Gaussian Noise (AWGN)), and path loss[4], [6], [7].

The channel impulse response is given as: $h[n] = [1.0, 0.5, -0.2]$

(Here zero noise is assumed)

To calculate the ideal target function of the OTA aggregated sequence, $s[n]$, the ideal flat channel without multipath is assumed as: $h_{ideal}[n] = [1]$.

$$\begin{aligned} s[n] &= x_1[n] + x_2[n] \Rightarrow \\ s[n] &= [3, 1, 0] \end{aligned} \tag{1}$$

1.b Impact of Practical Impairments on OAC Reliability

In order to calculate the received signal with Inter-Symbol Interference (ISI) at the FC, the linear property of the channel can be taken advantage of.

$$\begin{aligned} y[n] &= s[n] * h[n] \Rightarrow \\ y[n] &= \sum_{m=0}^n s[m]h[n-m] \Rightarrow \\ y[n] &= [3.0, 2.5, -0.1, -0.2, 0]; \end{aligned} \tag{2}$$

It is obvious that because of the ISI the three symbols of 1 are spread to the five symbols of 2.

To calculate the Mean Squared Error (MSE) at each sample the comparison of the actual received signal to the ideal target function shall be made.

$$\begin{aligned}e[n] &= y[n] - n[n] \Rightarrow \\e[n] &= [0.0, 1.5, -0.1, -0.2, 0.0] \\MSE &= \frac{e[n]}{5} \Rightarrow \\MSE &= 0.46\end{aligned}\tag{3}$$

1.b.i Synchronization Errors

Time, Frequency, and Phase Offsets (TO, CFO, PO): The detrimental impact of imperfect time-of-arrivals and phase alignment on signal superposition and computation accuracy [1], [3], [7].

```
1      % This is a comment
2      x = linspace(0, 2*pi, 100);
3      y = sin(x) + 0.5 * randn(size(x)); % Numbers like 0.5 will be in Math Font
4      plot(x, y);
```

1.b.ii Channel State Information (CSI) Imperfection

The need for accurate and fresh Channel State Information (CSI) at transmitters or receivers for many precoding/equalization techniques [1], [2], [7].

1.b.iii Waveform and Filter Design

Addressing time sampling error and intersymbol interference ISI inherent in digital communication transceivers when applied to OTA [7].

1.c Optimization Strategies to Enhance OAC Performance

- *Power Management:* Strategies to mitigate aggregation errors, such as optimizing power control policies to minimize Mean Squared Error MSE or maximize convergence speed [1], [4], [7].
- *Transceiver Design:* Joint design of pre-processing functions, precoders/beamformers, and post-processing functions (decoders) to match the channel to the desired function and minimize distortion [1], [2], [3], [8].

References

- [1] A. Şahin and R. Yang, “A survey on over-the-air computation,” *IEEE Communications Surveys & Tutorials*, vol. 25, no. 3, pp. 1877–1908, 2023, ISSN: 1553-877X, 2373-745X. DOI: 10.1109/COMST.2023.3264649 Accessed: Dec. 4, 2025. [Online]. Available: <https://ieeexplore.ieee.org/document/10092857/>
- [2] K. Yang, T. Jiang, Y. Shi, and Z. Ding, “Federated learning via over-the-air computation,” *IEEE Transactions on Wireless Communications*, vol. 19, no. 3, pp. 2022–2035, Mar. 2020, ISSN: 1536-1276, 1558-2248. DOI: 10.1109/TWC.2019.2961673 Accessed: Dec. 4, 2025. [Online]. Available: <https://ieeexplore.ieee.org/document/8952884/>
- [3] H. Hellström, S. Razavikia, V. Fodor, and C. Fischione, “Optimal receive filter design for misaligned over-the-air computation,” in *2023 IEEE Globecom Workshops (GC Wkshps)*, Kuala Lumpur, Malaysia: IEEE, Dec. 4, 2023, pp. 1529–1535, ISBN: 979-8-3503-7021-8. DOI: 10.1109/GCWkshps58843.2023.10464656 Accessed: Dec. 4, 2025. [Online]. Available: <https://ieeexplore.ieee.org/document/10464656/>
- [4] X. Cao, G. Zhu, J. Xu, Z. Wang, and S. Cui, “Optimized power control design for over-the-air federated edge learning,” *IEEE Journal on Selected Areas in Communications*, vol. 40, no. 1, pp. 342–358, Jan. 2022, ISSN: 0733-8716, 1558-0008. DOI: 10.1109/JSAC.2021.3126060 Accessed: Dec. 4, 2025. [Online]. Available: <https://ieeexplore.ieee.org/document/9606731/>
- [5] J. Zhu, Y. Shi, Y. Zhou, C. Jiang, W. Chen, and K. B. Letaief, “Over-the-air federated learning and optimization,” *IEEE Internet of Things Journal*, vol. 11, no. 10, pp. 16 996–17 020, May 15, 2024, ISSN: 2327-4662, 2372-2541. DOI: 10.1109/JIOT.2024.3352280 Accessed: Dec. 4, 2025. [Online]. Available: <https://ieeexplore.ieee.org/document/10388035/>
- [6] G. Zhu, Y. Du, D. Gunduz, and K. Huang, “One-bit over-the-air aggregation for communication-efficient federated edge learning: Design and convergence analysis,” *IEEE Transactions on Wireless Communications*, vol. 20, no. 3, pp. 2120–2135, Mar. 2021, ISSN: 1536-1276, 1558-2248. DOI: 10.1109/TWC.2020.3039309 Accessed: Dec. 4, 2025. [Online]. Available: <https://ieeexplore.ieee.org/document/9272666/>
- [7] N. G. Evgenidis et al., “Waveform design for over-the-air computing,” *IEEE Transactions on Wireless Communications*, pp. 1–1, 2025, ISSN: 1536-1276, 1558-2248. DOI: 10.1109/TWC.2025.3613838 arXiv: 2405.20877[cs]. Accessed: Dec. 4, 2025. [Online]. Available: <http://arxiv.org/abs/2405.20877>
- [8] M. Goldenbaum and S. Stanczak, “Robust analog function computation via wireless multiple-access channels,” *IEEE Transactions on Communications*, vol. 61, no. 9, pp. 3863–3877, Sep. 2013, ISSN: 0090-6778. DOI: 10.1109/TCOMM.2013.072913.120815 Accessed: Dec. 4, 2025. [Online]. Available: <http://ieeexplore.ieee.org/document/6573232/>