# ! LCD FFC-40 ADAPTER — PRE-FREEZE BENCH ADAPTER — DO NOT FABRICATE !

PANEL-2 J12 (FFC-40, 23 сигнала) -> test pads + panel FFC-40 (HotLCD TFT-H050A1SVIST4R40, ST7262). Монтаж панели: 120.7 x 75.8, плата -120 x 76 x 1.6 (2 слоя). CERN-OHL-S-2.0

Назначение: проверка экрана на P1-стенде ДО PCB. Пин-аут панели — ПРЕДПОЛОЖЕНИЕ, проверять по образцу/мультиметру (0-15); 0R-«перемычки» позволяют переназначить любую линию без перевыпуска платы. Крепление 4 x M3, внешний boost подсветки 18...22 В.

H1
M3

H2
M3

H3
M3

H4
M3

P_R0
TP1
PIR0
R1
0R
GND

P_R1
TP2
PIR1
R2
0R
GND

P_R2
TP3
PIR2
R3
0R
GND

P_R3
TP4
PIR3
R4
0R
R0

P_R4
TP5
PIR4
R5
0R
R1

P_R5
TP6
PIR5
R6
0R
R2

P_R6
TP7
PIR6
R7
0R
R3

P_R7
TP8
PIR7
R8
0R
R4

P_G0
TP9
PIG0
R9
0R
GND

P_G1
TP10
PIG1
R10
0R
GND

P_G2
TP11
PIG2
R11
0R
G0

P_G3
TP12
PIG3
R12
0R
G1

P_G4
TP13
PIG4
R13
0R
G2

P_G5
TP14
PIG5
R14
0R
G3

P_G6
TP15
PIG6
R15
0R
G4

P_G7
TP16
PIG7
R16
0R
G5

P_B0
TP17
PIB0
R17
0R
GND

P_B1
TP18
PIB1
R18
0R
GND

P_B2
TP19
PIB2
R19
0R
GND

P_B3
TP20
PIB3
R20
0R
B0

P_B4
TP21
PIB4
R21
0R
B1

P_B5
TP22
PIB5
R22
0R
B2

P_B6
TP23
PIB6
R23
0R
B3

P_B7
TP24
PIB7
R24
0R
B4

P_PCLK
TP25
PIPCLK
R25
0R
PCLK

P_DE
TP26
PIDE
R26
0R
DE

P_HS
TP27
PIHS
R27
0R
HSYNC

P_VS
TP28
PIVS
R28
0R
VSYNC

P_DISP
TP29
PIDISP
R29
0R
DISP_CTRL

P_LED_K
TP30
PILED_K
R30
0R
BL_CATHODE

P_LED_A
TP31
PILED_A
R31
0R
BL_ANODE

J1
FFC-40_ZIF
GND 1
GND 2
R0 3
R1 4
R2 5
R3 6
R4 7
G0 8
G1 9
G2 10
G3 11
G4 12
G5 13
B0 14
B1 15
B2 16
B3 17
B4 18
GND 19
GND 20
PCLK 21
DE 22
HSYNC 23
VSYNC 24
GND 25
GND 26
LCD_3V3 27
LCD_3V3 28
GND 29
BL_PWM 30
BL_ANODE 31
BL_CATHODE 32
GND 33
GND 34
GND 35
GND 36
GND 37
GND 38
GND 39
GND 40

J2
FFC-40_ZIF
P_LED_K 1
P_LED_A 2
GND 3
+3V3 4
GND 5
P_R0 6
P_R1 7
P_R2 8
P_R3 9
P_R4 10
P_R5 11
P_R6 12
P_R7 13
P_G0 14
P_G1 15
P_G2 16
P_G3 17
P_G4 18
P_G5 19
P_G6 20
P_G7 21
P_B0 22
P_B1 23
P_B2 24
P_B3 25
P_B4 26
P_B5 27
P_B6 28
P_B7 29
GND 30
P_PCLK 31
P_DE 32
P_HS 33
P_VS 34
P_DISP 35
GND 36
+3V3 37
+3V3 38
GND 39
GND 40

R32
10k
DISP_CTRL

DISP_CTRL
R33
0R
+3V3

TP32
DISP_CTRL

TP33
BEEPWM

TP34
+3V3

TP35
TP
GND

+3V3
C1
100n
GND

+3V3
C2
100n
GND

+3V3
C3
100n
GND

BL_EXT_A 1
BL_EXT_K 2
J3
BT2

BL_EXT_A
R34
0R
P_LED_A

BL_EXT_K
R35
0R
P_LED_K

+3V3
PWR_FLAG
+3V3

GND
PWR_FLAG
GND

Bukifon open hardware — CERN-OHL-S-2.0

Sheet: /
File: LCD-ADAPTER.kicad_sch

**Title: PicoMod/Bukifon LCD FFC-40 adapter (HotLCD ST7262) — PRE-FREEZ**

| Size: A1 | Date: | **Rev: 1.0** |
|---|---|---|
| KiCad E.D.A. 10.0.4 | | Id: 1/1 |