

R.O.B. Vision quick reference

R.O.B. is virtual. The UNO Q app and RetroPie link are running. Both Gyromite gate colors responded in Game A. Actual camera decoding has not yet been verified on the UNO Q.

Where	Action	Result
Mission	Select Gyromite, Stack-Up, or Pose Lab	Choose the virtual scene while no game is active.
Mission	Run Demo Sequence	Finite animation; available while paired and idle.
Mission	Home	Reset selected virtual game and pieces.
Mission	Emergency Stop	Live: stop capture and clear game. Preview: cancel local script.
Mission	Fast Gates during live Gyromite	Blue 2, red 1, Release Both 0; press again to release a color. Auto-release after 60 seconds.
Setup	Pair Console / Check Link	Pair RetroPie or refresh its authenticated online status.
Setup	Start Camera Check	Show framing, measured fps, and sampling rectangle.
Setup	Reset & Reconnect	Retry OpenCV capture; USB hub is unaffected.
Setup	Watch Test Flashes	Blink R.O.B.'s red light for detected Test alternation; no movement.
Setup	Gyromite / Stack-Up checks	Send manual pad or movement commands to the live model.

Use [Mission](#) and [Setup](#) on the UNO Q. A local `file://` page is only the preview. The camera requests 60 fps; delivered timing may still miss flashes. At 30 fps the current decoder rejects one-frame command traces rather than guessing.

The game launch hook identifies an exact ROM name. The receiver applies Gyromite virtual pad states as Controller 2 input and releases both on exit or stale network data. Stack-Up moves modeled blocks and has no gate-button return path. See the [user guide](#) and [troubleshooting](#).