

R.O.B. Vision quick reference

R.O.B. is virtual. The UNO Q app and RetroPie link are running. Both Gyromite gate colors responded in Game A. The camera recognized both games' Test modes; movement command decoding is still unverified.

Where	Action	Result
Mission	Select Gyromite, Stack-Up, or Pose Lab	Choose the virtual scene while no game is active.
Mission	Run Demo Sequence	Finite animation; available while paired and idle.
Mission	Home	Reset selected virtual game and pieces.
Mission	Emergency Stop	Live: stop capture and clear game. Preview: cancel local script.
Mission	Fast Gates during live Gyromite	Blue 2, red 1, Release Both 0; press again to release a color. Auto-release after 60 seconds.
Setup	Pair Console / Check Link	Pair RetroPie or refresh its authenticated online status.
Setup	Start Camera Check	Show framing, measured fps, and sampling rectangle.
Setup	Reset & Reconnect	Retry OpenCV capture; USB hub is unaffected.
Setup	Watch Test Signal	Blink R.O.B.'s red light for a detected Test signal; no movement.
Setup	Gyromite / Stack-Up checks	Send manual pad or movement commands to the live model.

In Stack-Up, press Select on the ROBOT BLOCK screen, choose Test, then press Start. The artwork remains visible while the Test signal plays.

Use [Mission](#) and [Setup](#) on the UNO Q. A local `file://` page is only the preview. The camera requests 60 fps; delivered timing may still miss flashes. At 30 fps the current decoder rejects one-frame command traces rather than guessing.

The game launch hook identifies an exact ROM name. The receiver applies Gyromite virtual pad states as Controller 2 input and releases both on exit or stale network data. Stack-Up moves modeled blocks and has no gate-button return path. See the [user guide](#) and [troubleshooting](#).