

ECEN 4/5632 Theory and Application of Digital Filters

Lecture 1, 8-20-26

Peter Mathys*




* With generous help from Gemini Pro and ChatGPT

DSP + ML

Signals, LTI Systems, and Convolution

Week 1 • Lecture 1 • 75 minutes

Classical DSP foundations → modern signal representations → machine learning



Today's learning objectives

00–15 MIN

By the end, students should be able to reason—not just compute.

- **Represent discrete-time signals using impulses, steps, and complex exponentials.**
- Test systems for linearity, time invariance, causality, and BIBO stability.
- Explain why the impulse response completely characterizes an LTI system.
- Compute finite-length convolutions graphically and numerically.
- Connect convolution to filtering and to the operation used by neural networks.


Course habit

For each new equation, ask: What does this let us predict about a real signal?

Why start with LTI systems?

00-15 MIN

Because many useful DSP operations become simple, interpretable building blocks.



Classical DSP gives us...

- Structure: linearity and invariance
- Closed-form analysis
- Stability and causality tests
- Frequency-selective filtering

ML later needs...

- Well-conditioned inputs
- Meaningful local structure
- Efficient operators
- Interpretability and diagnostics

Discrete time: index n is not “time in seconds”


15-35 MIN

n labels samples; physical time appears only after a sampling rate is specified.

$$t_n = nT_s = \frac{n}{f_s}$$

- $x[n]$ is defined only at integer n.
- A shift $x[n-n_0]$ changes the sample index, not the amplitude.
- Normalized angular frequency ω has units rad/sample.

Example sequence $x[n]$





Audio connection

At 48 kHz, one sample is 20.83 μs . A 2400-sample delay is 50 ms.

The unit sample $\delta[n]$ is a coordinate basis

It isolates one sample at one index.

$$\delta[n] = \begin{cases} 1, & n = 0 \\ 0, & n \neq 0 \end{cases}$$



$$x[n] = \sum_{k=-\infty}^{\infty} x[k] \delta[n - k]$$

Interpretation


A sequence is a weighted sum of shifted impulses—the discrete-time analog of expanding a vector in basis vectors.

The unit step $u[n]$ and useful identities

15-35 MIN

Steps describe turn-on behavior; impulses describe changes.

$$u[n] = \begin{cases} 1, & n \geq 0 \\ 0, & n < 0 \end{cases}$$



$$\delta[n] = u[n] - u[n-1]$$

$$u[n] = \sum_{k=-\infty}^n \delta[k]$$

Quick check

What is $u[n+2]$? Where does it turn on?

Complex exponentials are the “natural modes” of LTI systems

15–35 MIN

Today: recognize them. Lecture 2: prove the eigenfunction property.

$$x[n] = A\alpha^n e^{j\omega_0 n}$$

$$e^{j\omega_0 n} = \cos(\omega_0 n) + j\sin(\omega_0 n)$$

What each factor does

- A sets scale / phase
- α^n gives growth or decay
- $e^{j\omega_0 n}$ gives rotation / oscillation

Why DSP cares

- Sinusoids probe frequency response
- Exponentials diagonalize convolution
- Spectra decompose signals into modes

What is a discrete-time system?

A rule that maps an input sequence to an output sequence.

$$y[n] = T\{x[n]\}$$

Examples

- Gain: $y[n] = 2x[n]$
- Delay: $y[n] = x[n-3]$
- Moving average: $y[n] = (x[n] + x[n-1])/2$

Nonlinear / time-varying examples

- Squaring: $y[n] = x^2[n]$
- Compressor / limiter
- Gain that changes with n

Question to ask

Which properties let us predict behavior without simulating every possible input?

Linearity = superposition

Scale inputs → scale outputs. Add inputs → add outputs.

$$T\{ax_1[n] + bx_2[n]\} = aT\{x_1[n]\} + bT\{x_2[n]\}$$

Linear

- $y[n] = 3x[n]$
- $y[n] = x[n] + 0.5x[n-1]$
- Any convolution with fixed $h[n]$

Not linear

- $y[n] = x[n] + 2$
- $y[n] = |x[n]|$
- Dynamic-range compressor

Fast test

A linear system must map zero input to zero output.

Time invariance = “the clock does not matter”

Shift the input; the output shifts by exactly the same amount.

$$T\{x[n - n_0]\} = y[n - n_0] \quad \text{when } y[n] = T\{x[n]\}$$

Time invariant

- Fixed delay
- Fixed FIR / IIR filter
- Static gain

Time varying

- $y[n] = n x[n]$
- Daily adaptive equalizer
- Any rule using absolute sample index n

Audio analogy

An echo with a fixed 100 ms delay is time invariant. An echo whose delay sweeps over time is not.

Causality and BIBO stability

35–55 MIN

Two properties with direct implementation consequences.

Causal system

- $y[n_0]$ depends only on $x[n]$ for $n \leq n_0$
- Can operate in real time
- For LTI: $h[n] = 0$ for $n < 0$

$$|x[n]| \leq B_x < \infty \Rightarrow |y[n]| \leq B_y < \infty$$

BIBO stable system

- Every bounded input gives bounded output
- For LTI: $\sum |h[n]| < \infty$
- Rules out runaway responses

Graduate stretch

Be able to prove the LTI stability condition using $|x * h| \leq B_x \sum |h|$.

Property check: classify these audio systems

35–55 MIN

Think → vote → justify.

For each system: linear? time invariant? causal? BIBO stable?

A $y[n] = x[n-4800]$

Fixed 100 ms delay at 48 kHz

B $y[n] = 0.8x[n] + 0.2x[n-1]$

Two-tap smoother

C $y[n] = |x[n]|$

Full-wave rectifier


D $y[n] = n \cdot x[n]$

Index-dependent gain

Impulse response: one experiment characterizes an LTI system

55-75 MIN

Feed $\delta[n]$; call the output $h[n]$.



$$h[n] = T\{\delta[n]\}$$

- Linearity tells us how scaled impulses behave.
- Time invariance tells us how shifted impulses behave.
- Since any $x[n]$ is a sum of scaled, shifted impulses, $h[n]$ tells us the response to any $x[n]$.

Deriving convolution from impulse decomposition

55-75 MIN

This derivation is worth understanding line by line.

$$x[n] = \sum_k x[k] \delta[n - k] \quad \text{1. Decompose the input into shifted impulses.}$$

$$T\{x[n]\} = \sum_k x[k] T\{\delta[n - k]\} \quad \text{2. Use linearity.}$$

$$T\{\delta[n - k]\} = h[n - k] \quad \text{3. Use time invariance.}$$

$$y[n] = \sum_{k=-\infty}^{\infty} x[k] h[n - k] \equiv x[n] * h[n]$$

Meaning

Each input sample launches a shifted copy of $h[n]$; the output is their sum.

Convolution mechanics: flip → shift → multiply → add

55-75 MIN

For finite sequences, the overlap changes as n moves.



$$y[n] = \sum_k x[k]h[n - k]$$

Graphical view

- Track overlap as n changes
- Good for intuition
- Best with short sequences


Algebraic / code view

- Use nonzero-support limits
- Good for longer signals
- `np.convolve` / `scipy.signal`

Worked convolution: $x[n]=[1,2,1]$, $h[n]=[1,-1]$

55-75 MIN

Assume both start at $n=0$.



Sanity checks

Output length = $3+2-1 = 4$. $\text{Sum}(y)=\text{sum}(x)\text{sum}(h)=0$.


Convolution has algebraic structure

55-75 MIN

Useful facts that save work and explain cascades.

$$x * h = h * x \quad x * (h_1 * h_2) = (x * h_1) * h_2 \quad x * (h_1 + h_2) = x * h_1 + x * h_2$$

commutative associative distributive



Why ML cares

A stack of linear convolution layers with no nonlinearity collapses to one convolution.

Python demo: convolution in one line

55-75 MIN

Then verify the indexing and meaning.

Python

```
import numpy as np

x = np.array([1., 2., 1.])
h = np.array([1., -1.])
y = np.convolve(x, h, mode='full')
print(y)  # [ 1.  1. -1. -1.]
```

SciPy

```
# For long signals, scipy.signal.fftconvolve
from scipy.signal import fftconvolve
y_fast = fftconvolve(x, h, mode='full')
```

Do not skip the math

A library call gives numbers. Convolution theory tells you support, delay, stability, frequency behavior, and what to debug.

ML bridge: PyTorch “convolution” is usually cross-correlation

55-75 MIN

Same local weighted sum, different kernel orientation.

$$\text{DSP convolution: } y[n] = \sum_k x[k]h[n-k] \quad \text{CNN correlation: } y[n] = \sum_k w[k]x[n+k]$$

PyTorch

```
import torch
import torch.nn.functional as F

x = torch.tensor([[[[1., 2., 1.]]]])
w = torch.tensor([[[[1., -1.]]]])
y = F.conv1d(x, w) # correlation convention
```

Key idea

The kernel is learned in ML, but the local linear operation is the same family of operation you are analyzing now.

Concept check

CHECK

No computation should be necessary.

For an LTI system, which statement is always true?

A. If $x[n]$ is bounded, $y[n]$ is bounded.

B. The response to $\delta[n-k]$ is $h[n-k]$.


C. The system must be causal.

D. The impulse response has finite length.

Lecture 1 synthesis

WRAP-UP

The chain of reasoning matters more than memorizing isolated formulas.



- Be able to test system properties with a counterexample or proof.
- Be able to derive convolution from LTI assumptions.
- Be able to compute a short convolution by hand and predict its support.

Next lecture

Complex exponentials turn convolution into multiplication in the frequency domain.

Optional board reserve: index bookkeeping for finite convolution

RESERVE

Use if students need one more example.

$$x[n] \neq 0 \text{ on } [n_x^{\min}, n_x^{\max}], \quad h[n] \neq 0 \text{ on } [n_h^{\min}, n_h^{\max}]$$

$$y[n] \neq 0 \text{ only on } [n_x^{\min} + n_h^{\min}, n_x^{\max} + n_h^{\max}]$$

Length rule

For sequences of lengths L_x and L_h starting at known indices, full convolution has length $L_x + L_h - 1$.

- This predicts where the output can be nonzero before any arithmetic.
- It also helps debug off-by-one errors in code.