

In the following instruction sequence, show  
: the values of the Carry, and Zero flags

MOV AL,F5H

TEST AL,1

اختر أحد الخيارات

- a. CF=0 ; ZF=1 ☐
- b. CF=0 ; ZF= 0 ☒
- c. CF=1 ZF= 1 ☐
- d. CF=1 ZF= 0 ☐

The register that can be used as a default counter in case of string and loop instructions is

اختر أحد الخيارات

a. BX ☐

b. DX ☐

c. AX ☐

d. CX ☒

What is the binary value of AL and CF after  
?the following instructions have executed

MOV AL,C4H

STC ; set CF=1

RCR AL,1

اختر أحد الخيارات

- a. AL=62H CF=0 ☐
- b. AL= E2H CF=0 ☒
- c. AL=62H CF=1 ☐
- d. AL= E2H CF=1 ☐

If AX =1234H and BX=00FFH what is the value stored in AX after the execution of the following instruction

AND AX, BX

اختر أحد الخيارات

a. 0034H ☒

b. 0000H ☐

c. FF12H ☐

d. 12FFH ☐

## سؤال 6

غير مجاب عليه بعد

الدرجة من 1.50

علم هذا السؤال 

The binary value of AL and carry flag (CF) after the following instructions have ..... executed is

MOV AL,10101011B

SAR AL,1

اختر أحد الخيارات

- a. AL=11010101B CF=1 ☒
- b. AL=01010101B CF=1 ☐
- c. AL=01010100B CF=0 ☐
- d. AL=01010100B CF=0 ☐

what is the value of AL after executing the following

MOV AL,-6

MOV CL,2

SAR AL,CL

INC CL

RCR AL,CL

اختر أحد الخيارات

a. DFH ☒

b. A7H ☐

c. IFH ☐

d. BFH ☐

Defined below X memory locations and the offset address of X is 100h. find the content of register AL after execution of ?the following code

```
X DB 88H,44H,50H,90H,55H,23H,51H
```

```
MOV BX,OFFSET X
```

```
MOV SI,2
```

```
MOV AL, [BX][SI]
```

اختر أحد الخيارات

a. AL=55H ☐

b. AL=50H ☒

c. AL=90H ☐

d. AL=44H ☐



what is the value of AL after executing the following code

**MOV AL,3**

**NEG AL**

**JC L**

**INC AL**

**L: DEC AL**

اختر أحد الخيارات

FBH ☐

FCH ☒

FDH ☐

2 ☐



The conditional branch instruction JC .18  
— performs the operations when if

اختر أحد الخيارات

a.  $CF=1$  ☒

b.  $CF=0$  ☐

c.  $PF=0$  ☐

d.  $ZF = 0$  ☐

Defined below X memory locations and the offset address of X is 100h. Find the content of register AL and DL after execution of the following code

```
X DB  FAH, CBH, 1AH, 80H
```

```
MOV BX, OFFSET X
```

```
ADD BX,1
```

```
MOV AL,[BX]
```

```
INC BX
```

```
MOV DL,[BX]
```

اختر أحد الخيارات

a. AL=FAH ; DL=CBH ☐

b. AL=CBH ; DL=1AH ☒

c. AL=FAH; DL=80H ☐

d. AL=1AH; DL=80H ☐

The addressing mode used in the  
: instruction MOV DL,X[SI] is

اختر أحد الخيارات

- a. Base relative addressing mode ☐
- b. Immediate addressing mode ☐
- c. Direct addressing mode ☐
- d. Direct indexed addressing mode ☒

The equivalent code of NOT AX instruction  
is

اختر أحد الخيارات

- a. OR AX,AX; ADD AX,1 ☐
- b. XOR AX,FFH ☐
- c. XOR AX,FFFFH; ADD AX,1 ☒
- d. XOR AX,FFFFH ☐

## سؤال 14

غير مجاب عليه بعد

الدرجة من 1.50

علم هذا السؤال 

The unit that controls the external buses and provides access to instructions and ..... data in the 8086 architecture is

اختر أحد الخيارات

- a. **EU** ☐
- b. **CU** ☐
- c. **BIU** ☒
- d. **ALU** ☐

## سؤال 16

غير مجاب عليه بعد

الدرجة من 1.50

علم هذا السؤال

what is the value of AL register after  
:executing the following codes

MOV AL, -7

MOV AH,0

MOV BL, 2

DIV BL

اختر أحد الخيارات

a. 1FH ☐

b. 7CH ☒

c. FDH ☐

d. 13H ☐



## سؤال 17

غير مجاب عليه بعد

الدرجة من 1.50

علم هذا السؤال 

Which of the following instruction can be used to multiply constants of register DX by 4

اختر أحد الخيارات

- a. MOV CL,2; SHR DX,CL ☐
- b. MOV CL,2; RCL DX,CL ☐
- c. MOV CL,2; SHL DX,CL ☒
- d. MOV CL,2; ROL DX,CL ☐



One of the following instructions does not affect the destination

اختر أحد الخيارات

- a. add dest, 1111h ☐
- b. sub dest, 0FFFFh ☐
- c. cmp dest, 1111h ☐
- d. mov dest, 0000h ☐

## سؤال 19

غير مجاب عليه بعد

الدرجة من 1.50

علم هذا السؤال 

Find the content of AL and zero flag (ZF)  
:after execution of the following code

MOV AL,FEH

ADD AL,2

ADC AL,3

اختر أحد الخيارات

a. AL=2 ZF=1 ☐

b. AL=6 ZF=1 ☐

c. AL=5 ZF=0 ☐

d. AL=4 ZF=0 ☒

Defined below X memory locations and the offset address of X is 100h. find the content of register AL after execution of ?the following code

```
X DB 88H,44H,50H,90H,55H,23H,51H
```

```
MOV BX,OFFSET X
```

```
MOV AL, [BX+4]
```

اختر أحد الخيارات

a. 55 ☒

b. 90 ☐

c. 88 ☐

d. 44 ☐