



Affirmed Networks SNMP MIB and Alarm Reference Guide

Release 9.4.0.0

Updated: October 2019

Inside ...

- Trap Alarms
- MIBs

Affirmed Networks Inc.

35 Nagog Park
Acton, MA 01720
USA

Tel: +1-978-268-0800

www.affirmednetworks.com

Copyright© 2019 Affirmed Networks, Inc. All Rights Reserved.

AFFIRMED & DESIGN[®], ACUITAS SERVICE MANAGEMENT SYSTEM[®], AFFIRMED NETWORKS MOBILE CONTENT CLOUD[™], AFFIRMED OPEN WORKFLOW[™], AFFIRMED MOBILE CONTENT CLOUD[™] and other trademarks and designs are the registered or unregistered trademarks of Affirmed Networks, Inc. and its subsidiaries in the United States and in foreign countries. All other trademarks are the property of their respective owners. The Affirmed Networks, Inc. trademarks may not be used in connection with any product or service that is not Affirmed Networks' in any manner that is likely to cause confusion among customers or in any manner that disparages or discredits Affirmed Networks, Inc.

This document contains information that is the property of Affirmed Networks, Inc. This document may not be copied, reproduced, reduced to any electronic medium or machine readable form, or otherwise duplicated, and the information herein may not be used, disseminated or otherwise disclosed, except with the prior written consent of Affirmed Networks, Inc.

Affirmed NETWORKS, INC. SOFTWARE LICENSE AGREEMENT

AFFIRMED NETWORKS, INC. ("AFFIRMED") IS WILLING TO LICENSE THE ENCLOSED SOFTWARE AND ACCOMPANYING USER DOCUMENTATION (COLLECTIVELY, THE "PROGRAM") TO YOU ONLY UPON THE CONDITION THAT YOU ACCEPT ALL OF THE TERMS AND CONDITIONS OF THIS LICENSE AGREEMENT. PLEASE READ THE TERMS AND CONDITIONS OF THIS LICENSE AGREEMENT CAREFULLY BEFORE OPENING THE PACKAGE (S) OR USING THE AFFIRMED PRODUCTS CONTAINING THE SOFTWARE, AND BEFORE USING THE ACCOMPANYING USER DOCUMENTATION. OPENING THE PACKAGE (S) OR USING THE AFFIRMED PRODUCTS CONTAINING THE PROGRAM WILL INDICATE YOUR ACCEPTANCE OF THE TERMS OF THIS LICENSE AGREEMENT. IF YOU ARE NOT WILLING TO BE BOUND BY THE TERMS OF THIS LICENSE AGREEMENT, AFFIRMED IS UNWILLING TO LICENSE THE PROGRAM TO YOU, IN WHICH EVENT YOU SHOULD RETURN THE PROGRAM WITHIN TEN (10) DAYS FROM SHIPMENT TO THE PLACE FROM WHICH IT WAS ACQUIRED, AND YOUR LICENSE FEE WILL BE REFUNDED. THIS LICENSE AGREEMENT REPRESENTS THE ENTIRE AGREEMENT CONCERNING THE PROGRAM BETWEEN YOU AND AFFIRMED, AND IT SUPERSEDES ANY PRIOR PROPOSAL, REPRESENTATION OR UNDERSTANDING BETWEEN THE PARTIES.

License Grant

Subject to the provisions of this License, Affirmed grants to Licensee, and Licensee accepts, a non-exclusive, non-transferable license to use the object code form of the software supplied by Affirmed, including all patches, error corrections, updates and revisions thereto in machine-readable, object code form only (the "Software"), and the user documentation, including all updates and revisions thereto (the "User Documentation") for Licensee's internal business purposes (including, without limitation, in conjunction with Licensee's provision of services to its customers) on or in conjunction with the hardware product with which it was originally delivered or on a single designated computer. The Software and User Documentation are sometimes collectively referred to as the "Program". *Licensee acknowledges that certain Software provided by Affirmed may contain other restrictions and Licensee must refer to accompanying license certificates for each such Software licensed.* Licensee agrees that Licensee will not pledge, lease, rent, or share Licensee's rights under this License Agreement, and that Licensee will not, without Affirmed's prior written consent, assign or transfer Licensee's rights hereunder. Licensee agrees that Licensee may not duplicate (except as set forth below), decompile, disassemble, reverse engineer, modify, or otherwise translate the Software or permit a third party to do so and that Licensee shall not make the Program available to any other third party, or create works derivative of the Program, without Affirmed's express written consent. Licensee agrees it shall not publish in any fashion any results of benchmark tests run on the Program.

The Program is copyrighted and is only authorized to reproduce one copy of the Software and the User Documentation solely for backup purposes. Licensee is hereby prohibited from otherwise copying or translating, modifying or adapting the Program or, incorporating in whole or any part in any other product or creating derivative works based on all or any part of the Program. Licensee is not authorized to license others to reproduce any copies of the Program, except as expressly provided in this Agreement. Licensee agrees to ensure that all copyright, trademark and other proprietary notices of Affirmed affixed to or displayed on the Program will not be removed or modified. Licensee shall not decompile, disassemble or reverse engineer, the licensed software or any component thereof, except as may be permitted by applicable law, in which case Licensee must notify Affirmed in writing and Affirmed may provide review and assistance.

U.S. Government Restricted Rights. Notice - Distribution and use of products including computer programs and any related documentation and derivative works thereof, to and by the U.S. Government, are subject to the Restricted Rights provisions of FAR 52.227-19, paragraph (c)(2) as applicable, except for purchases by agencies of the Department of Defense (DOD). If the software is acquired under the terms of a Department of Defense or civilian agency contract, the software is a "commercial item" as that term is defined at 48 C.F.R. 2.101 (Oct. 1995), consisting of "commercial computer software" and "commercial computer software documentation" as such terms are used in 48 C.F.R. 12.212 of the

Software License Agreement

Federal Acquisition Regulations and its successors and 48 C.F.R. 227.7202-1 through 227.7202-4 (June 1995) of the DoD FAR Supplement and its successors. All U.S. Government end users acquire the software with only those rights set forth in this Agreement. Manufacturer is Affirmed Networks, Inc., 35 Nagog Park, Acton MA 01720. Unpublished - rights reserved under the copyright laws of the United States.

Affirmed's Rights

Licensee agrees that the Software and the User Documentation are proprietary, confidential products of Affirmed or Affirmed's licensor protected under U.S. copyright law and Licensee will use Licensee's best efforts to maintain their confidentiality. Licensee further acknowledges and agrees that all right, title and interest in and to the Program, including associated intellectual property rights, are and shall remain with Affirmed or Affirmed's licensor. This License Agreement does not convey to Licensee an interest in or to the Program, but only a limited right of use revocable in accordance with the terms of this License Agreement.

License Fees

The license fees paid by Licensee are paid in consideration of the license granted under this License Agreement.

Term

This License Agreement is effective upon Licensee's execution of this License Agreement and payment of the license fees and shall continue until terminated. Licensee may terminate this License Agreement at any time by returning the Program and all copies or portions thereof to Affirmed. Affirmed may terminate this License Agreement upon the breach by Licensee of any term hereof. Upon such termination by Affirmed, Licensee agrees to return to Affirmed the Program and all copies or portions thereof. Termination of this License Agreement shall not prejudice Affirmed's rights to damages or any other available remedy.

Limited Warranty

Affirmed warrants that with normal use and service each Software product shall materially conform to Affirmed's then current published specifications for the most current release of such Software product for a period of ninety (90) days from the date of shipment by Affirmed. Program media is warranted for ninety- (90) days from the date of shipment by Affirmed. Software support beyond these periods is available at additional cost under the terms of Affirmed's Annual Maintenance Service Agreement. During the warranty period, as Licensee's sole and exclusive remedy, Affirmed will correct a Software product's failure to conform to the warranty provided that Licensee has notified Affirmed in writing of the nature of the non-conformity. This warranty shall not apply if any Software product has been (i) modified or altered by anyone other than Affirmed, (ii) abused or misapplied, or (iii) used in combination with hardware or software other than the Affirmed manufactured products for which it was designed. Affirmed shall incur no liability under this warranty if Affirmed's tests disclose that the alleged defect is due to causes not within Affirmed's reasonable control, including alteration or abuse of the goods. If a Program is determined not to be defective or to have a defect due to causes not within Affirmed's reasonable control, Licensee agrees to pay for such repair at the repair price as listed in Affirmed's then current applicable price list. In no event does Affirmed warrant that the use of Software products will be error free or uninterrupted. Affirmed's sole obligation under the Software warranty shall be to provide the remedies described above.

EXCEPT FOR THE EXPRESS WARRANTIES STATED IN THIS WARRANTY, THE PROGRAM IS LICENSED "AS IS", AND Affirmed DISCLAIMS ANY AND ALL OTHER WARRANTIES, WHETHER EXPRESS, IMPLIED OR STATUTORY WITH RESPECT TO THE SOFTWARE PROVIDED UNDER THIS AGREEMENT, INCLUDING, BUT NOT LIMITED TO, ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, ANY WARRANTIES OF NONINFRINGEMENT AS WELL AS ANY WARRANTIES ARISING FROM COURSE OF DEALING, USAGE OR TRADE PRACTICE.

Limitation of Liability

Affirmed's cumulative liability to Licensee or any other party for any loss or damages resulting from any claims, demands, or actions arising out of or relating to this License Agreement shall not exceed the greater of: (i) ten thousand U.S. dollars (\$10,000) or (ii) the total license fee paid to Affirmed for the use of the Program. In no event shall Affirmed be liable for any indirect, incidental, consequential, special, punitive or exemplary damages or lost profits or the loss of software or data, even if Affirmed has been

advised of the possibility of such damages. In the event that the Program contains the intellectual property of a third party pursuant to a license in favor of Affirmed, with a right to sublicense to Licensee, Affirmed hereby disclaims, to the extent permitted by law, such third party's liability of any damages, whether direct, indirect, incidental or consequential, arising out the use of the Program

Export Control

Licensee shall not export or re-export, directly or indirectly, any of the Programs (including any part of a Program or any direct product of such Program), Affirmed's Confidential Information or related technical data (a) into, or to a national resident of, any of those countries listed at the time of any shipment of the Products in the applicable U.S. export regulations as "prohibited or restricted" countries, or any other country to which such exports or re-exports may be restricted (collectively, the "Prohibited Countries") or (b) to anyone on the U.S. Treasury Department's list of Specially Designated Nations or the U.S. Commerce Department's Table of Denial Orders. At Licensee's request, Affirmed shall provide a list of the Prohibited Countries, Specially Designated Nations and/or Table of Denial Orders in order to assist Licensee to comply with such requirement.

Governing Law

This License Agreement shall be construed and governed in accordance with the laws and under the jurisdiction of the Commonwealth of Massachusetts, U.S.A. Any dispute arising out of this Agreement shall be referred to an arbitration proceeding in Boston, Massachusetts, U.S.A. by the American Arbitration Association.

Miscellaneous

If any action is brought by either party to this License Agreement against the other party regarding the subject matter hereof, the prevailing party shall be entitled to recover, in addition to any other relief granted, reasonable attorneys' fees and expenses of arbitration. Should any term of this License Agreement be declared void or unenforceable by any court of competent jurisdiction, such declaration shall have no effect on the remaining terms hereof. The failure of either party to enforce any rights granted hereunder or to take action against the other party in the event of any breach hereunder shall not be deemed a waiver by that party as to subsequent enforcement of rights or subsequent actions in the event of future breaches.

Affirmed has made no commitments or promises orally or in writing with respect to delivery of any future software features or functions. In relation to any future software features or functions, all presentations, RFP responses and/or product outlook documents, information or discussions, either prior to or following the date herein, are for informational purposes only, and Affirmed has no obligation to provide any future releases or upgrades or any features, enhancements or functions, unless specifically agreed to in writing by both parties. Reseller acknowledges that no purchasing decisions are based upon any future software features or functions.

**Third Party
Beneficiary**

If the Program incorporates or otherwise contains any intellectual Property of any third party pursuant to a license agreement in favor of Affirmed and sublicensed to Licensee, such third party shall, to the extent permitted by law, be a third party beneficiary of the terms and conditions of this Agreement.

Contents

Preface

Audience	xix
Release Information	xix
How to Use This Guide	xx
Features in This Release	xxi
Changes in This Release	xxi
New Alarms in This Release	xxi
Conventions	xxii
How to Obtain Product Documentation	xxiii
Technical Assistance Center	xxiii

Chapter 1

Displaying Alarm Information

Alarm Detail	1-2
fmCntnFilterCategoryFileTooBig	1-3
fmCntnFilterCategoryFileNotFound	1-3
fmCntnFilterCategoryFileOverflow	1-3
fmCntnFilterBlacklistFileOverflow	1-3
fmCntnFilterBlacklistFileTooBig	1-4
fmCntnFilterBlacklistFileNotFound	1-4
fmCntnFilterCategoryFileInvalidEntry	1-4
fmCntnFilterBlacklistFileInvalidEntry	1-4
fmCntnHttpProxyServerConnectFail	1-5
anCntnFilterWhitelistFileInvalidEntry	1-5
anCntnFilterWhitelistFileOverflow	1-5
anCntnFilterWhitelistFileTooBig	1-5
anCntnFilterWhitelistFileNotFound	1-6
anCacheDiskOperationalStateAlarm	1-6
anCntnUrlListFileInvalidEntry	1-6
anCntnUrlListFileOverflow	1-6
anCntnUrlListFileNotFound	1-7
anCntnUrlListFileTooBig	1-7
anPlaFileDownloadFail	1-7
anCacheDiskErrorStateAlarm	1-7
anLDAPServerConnectFail	1-8
anLDAPServerConnectLost	1-8
anLDAPPprofNoServerConnected	1-8

anCntnUaProfDefaultAttsMissing	1-9
anSMSCServerConnectFail	1-9
anSMSCProfNotFound	1-9
anSMSCServerConnectLost	1-9
anCntnUaProfFileInvalid	1-10
anSpsServerConnectFail	1-10
anSpsServerConnectLost	1-10
anCntnOnlineCatDBInstallationFailure	1-10
anCntnFilterHashListFileInvalidEntry	1-11
anCntnFilterHashListFileNotFound	1-11
anCntnFilterHashListFileOverflow	1-11
anCntnFilterHashListFileTooBig	1-11
anCntnHealthCheckStateDown	1-12
anCntnCACertExpired	1-12
fmHmCacheOperStateDown	1-12
anTemperatureAlarm	1-12
anVoltageAlarm	1-13
anHotSwapAlarm	1-13
anTelcoAlarm	1-13
anWatchdogAlarm	1-13
anFanAlarm	1-14
anAirFilterAlarm	1-14
anTachAlarm	1-14
anHWAlarm	1-14
anCardNotBootingUp	1-15
anLedStateChange	1-15
anRebootEvent	1-15
anPayloadFailure	1-16
anFmSlotFrequentReboot	1-16
anPortStatusDown	1-16
anPortStatusUP	1-16
anHwNodeDepartureEventData	1-17
anHwExtStorageCreateFailure	1-17
anHwExtStorageSizeMismatch	1-17
anHwNoExtStorageDiskAvailable	1-17
anHwNotEnoughFreeStorageSpace	1-18
anHwExtStorageMoveFilesTimeout	1-18
anHwExtStorageCloseFilesTimeout	1-18
anExtractionPending	1-18
anInsertionPending	1-19
anIsolCpusMismatch	1-19
anIpInterfaceOperStatusDown	1-19
anDataFabricOperStateDown	1-20
anGeoRedundancyStandbyOperStatusDown	1-20
anGeoRedundancyActiveOperStatusDown	1-20
anGeoRedundancyPrimaryNodeStandby	1-21
anGeoRedundancySecondaryNodeActive	1-21
anGeoRedundancyLinkDown	1-21
anGeoRedundancyLinkVersionMismatch	1-22
anDataFabricOperStateDownPathA	1-22
anDataFabricOperStateDownPathB	1-22

anBaseSwitchOperStateDownPathA	1-23
anBaseSwitchOperStateDownPathB	1-23
anBaseSwitchOperStateDown	1-23
anNtpSyncError	1-24
anBaseSwitchReachabilityDiffersPathAPathB	1-24
anDataFabricReachabilityDiffersPathAPathB	1-24
anIpBgpPeerOperStatusDown	1-25
anPacketEngineError	1-25
anPacketEngineCongestion	1-25
anDataFabricPartialReachabilityPathA	1-26
anPacketEngineWatchdogAlarm	1-26
anPacketEngineKNICongfigurationMismatch	1-26
anIpsecTunnelOperStatusDown	1-26
anIpsecTunnelOperStatusUp	1-27
anIpOspfV2NbrDown	1-27
anIpOspfV3NbrDown	1-27
anNatPoolSessionAlarmThreshold	1-28
anNatPoolIpAddressAlarmThreshold	1-28
anNatPoolPortChunkAlarmThreshold	1-28
anBfdSessionDown	1-29
anPortmapFailure	1-29
fmNmAn3000ColdStart	1-29
fmNmAn3000Commit	1-30
an3000WarmStart	1-30
anLinkUp	1-30
anLinkDown	1-30
anNmLoginFailure	1-31
anTaskOverload	1-31
anBladeOverload	1-31
anSystemOverload	1-32
anGtpPeerDown	1-32
anCantPageSubscriberOutOfBuffers	1-32
anDiameterPeerLinkDown	1-33
anDiameterPeerLinkUp	1-33
anRadiusPeerDown	1-33
anRadiusPeerUp	1-34
anGtppPeerDown	1-34
anGtppPeerUp	1-34
anPdnSessionAntiSpoofing	1-34
anSgwServiceUp	1-35
anSgwServiceDown	1-35
anPgwServiceUp	1-35
anPgwServiceDown	1-35
anGgsnServiceUp	1-36
anGgsnServiceDown	1-36
anApnAvailable	1-36
anApnNotAvailable	1-36
anCaleaPeerLinkDown	1-37
anCaleaPeerLinkUp	1-37
anGtpPeerUp	1-37
anCaleaTargetsCleared	1-38

anCaleaInterfacesCleared	1-38
anCaleaUtilizationLow	1-38
anCaleaUtilizationMedium	1-39
anCaleaUtilizationHigh	1-39
anCaleaUtilizationCritical	1-39
anCaleaCCBufferConfiguredSizeBelowThreshold	1-40
anCaleaCCBufferUtilizationThresholdReached	1-40
anCaleaIRIBufferUtilizationThresholdReached	1-40
anCaleaTargetDBMaxSubsLimitReached	1-41
anCaleaIRIBufferConfiguredSizeBelowThreshold	1-41
anCaleaIfOrIfGroupConfigChange	1-41
anCaleaLITargetCreatedOrDeleted	1-42
anCaleaInterfaceGroupStatusDown	1-42
anCaleaCCBufferDataLost	1-42
anCaleaIRIBufferDataLost	1-43
anEmergencyCallAttemptFailed	1-43
anEmergencyCallDropped	1-43
anWagServiceDown	1-44
anWagServiceUp	1-44
anEpdgServiceUp	1-44
anEpdgServiceDown	1-44
anGwSubsGrpFileNotFound	1-45
anCaleaUserBanFeatureConfigChange	1-45
anCaleaCCDataLost	1-45
anCaleaIRIDataLost	1-46
anPfcPeerDown	1-46
anPfcPeerUp	1-46
anCaleaIfGrpSourceProfileConfigChange	1-47
anCaleaIfGrpSourceProfileNotFound	1-47
anCaleaPdhIrNotSupportedForSx3lIfTunnelToCPF	1-47
anCaleaDecryptFail	1-48
fmSWCompMCMSwitchoverEventData	1-48
anRedundancyOperState	1-48
anCpuTosTaskState	1-49
anNewCoreFileDetected	1-49
anfileftpfailure	1-49
anForcedSyncStart	1-50
anForcedSyncFailed	1-50
anPortStatusUp	1-50
anfilepurgedduetodiskfull	1-51
anKernelOptionsModified	1-51
anFormatDisk	1-51
anDiskFull	1-52
anUEPoolThresholdAlarm	1-52
anDataRecordFailure	1-52
anRemoteMountFailed	1-53
anEdrServerConnectionFailed	1-53
anPkix509expiring	1-53
anPkix509expired	1-54
anPkix509revoked	1-54
anPkijunreachable	1-54

anPkiobjadded	1-54
anPkiobjupdated	1-55
anPkiobjremoved	1-55
anPkix509crlnextupdateavailable	1-55
anReleaseMismatch	1-56
anPkiobjupdatenotavailable	1-56
anPkisshauthorizedkeyaddedtouser	1-56
anPkisshauthorizedkeyremovedfromuser	1-57
anPkisshauthorizedkeyaddedtogroup	1-57
anPkisshauthorizedkeyremovedfromgroup	1-57
anPkisshtrustedcakeyaddedtocluster	1-58
anPkisshtrustedcakeyremovedfromcluster	1-58
anPkisshtrustedcakeyaddedtogroup	1-58
anPkisshtrustedcakeyremovedfromgroup	1-59
anPkisshuseraddedtoauthorizedprincipals	1-59
anPkisshuserremovedfromauthorizedprincipals	1-59
anPkisshgroupaddedtoauthorizedprincipals	1-60
anPkisshgroupremovedfromauthorizedprincipals	1-60
anfileexportfailure	1-60
anPkisshnamesaddedtogroupauthorizedprincipals	1-61
anPkissherrorapplyingconfigurationtosshcontrolfiles	1-61
anPkisshnamesremovedfromauthorizedprincipals	1-61
anPkisshnamesaddedtoauthorizedprincipals	1-62
anPkisshnamesremovedfromtogroupauthorizedprincipals	1-62
anPkisshmaximumsecuritylevelset	1-62
anPkisshcompatiblesecuritylevelset	1-63
anPkisshstricthostkeycheckingsetto	1-63
anPkisshstricthostkeycheckingsettoask	1-63
anPkisshstricthostkeycheckingsettoyes	1-64
anPkisshverifyhostkeydnssetto	1-64
anPkisshverifyhostkeydnssettoyes	1-64
anPkisshverifyhostkeydnssettoask	1-65
anPkisshknownhostcakeyremoved	1-65
anPkisshknownhostcakeyadded	1-65
anPkisshknownhostkeyremoved	1-66
anPkisshknownhostkeyadded	1-66
anPkisshlocalhostcertificatereplaced	1-66
anPkisshlocalhostcertificateremoved	1-67
anPkisshlocalhostcertificateadded	1-67
anPkisshrevoked	1-67
anPkimanuallyrevoked	1-68
anPkisshuserkrlreplaced	1-68
anPkisshuserkrladded	1-68
anPkisshuserkrlremoved	1-69
anPkisshcertexpiring	1-69
anPkisshcertexpired	1-69
anNewMemImageFileDetected	1-69
anNewFaultFileDetected	1-70
anNodeRebootRequired	1-70
anRadiusAccountingOnMsgNotSent	1-70
anClusterRebootRequired	1-70

anThresholdCrossingAlarm	1-71
anLicenseCapacityEnforcement	1-71
anLicenseCapacityLimit	1-71
anLicenseLifetimeEnforcement	1-72
anLicenseLifetime	1-72
anLicensePlsSeparation	1-72
anLicensePlsGraceExpired	1-73

Chapter 2

Accessing MIB Information

MIB File Format	2-2
AFFIRMED-SNMP-AN3000-TRAPS-MIB DEFINITIONS ::= BEGIN	2-6
affirmedSnmpAn3000Traps MODULE-IDENTITY	2-9
fmCntnFilterCategoryFileTooBig NOTIFICATION-TYPE	2-10
fmCntnFilterCategoryFileNotFound NOTIFICATION-TYPE	2-10
fmCntnFilterCategoryFileOverflow NOTIFICATION-TYPE	2-11
fmCntnFilterBlacklistFileOverflow NOTIFICATION-TYPE	2-11
fmCntnFilterBlacklistFileTooBig NOTIFICATION-TYPE	2-12
fmCntnFilterBlacklistFileNotFound NOTIFICATION-TYPE	2-12
fmCntnFilterCategoryFileInvalidEntry NOTIFICATION-TYPE	2-13
fmCntnFilterBlacklistFileInvalidEntry NOTIFICATION-TYPE	2-13
fmCntnHttpProxyServerConnectFail NOTIFICATION-TYPE	2-14
anCntnFilterWhitelistFileInvalidEntry NOTIFICATION-TYPE	2-14
anCntnFilterWhitelistFileOverflow NOTIFICATION-TYPE	2-15
anCntnFilterWhitelistFileTooBig NOTIFICATION-TYPE	2-15
anCntnFilterWhitelistFileNotFound NOTIFICATION-TYPE	2-16
anCacheDiskOperationalStateAlarm NOTIFICATION-TYPE	2-16
anCntnUrlListFileInvalidEntry NOTIFICATION-TYPE	2-17
anCntnUrlListFileOverflow NOTIFICATION-TYPE	2-17
anCntnUrlListFileNotFound NOTIFICATION-TYPE	2-18
anCntnUrlListFileTooBig NOTIFICATION-TYPE	2-18
anPlaFileDownloadFail NOTIFICATION-TYPE	2-19
anCacheDiskErrorStateAlarm NOTIFICATION-TYPE	2-19
anLDAPServerConnectFail NOTIFICATION-TYPE	2-20
anLDAPServerConnectLost NOTIFICATION-TYPE	2-21
anLDAPProfNoServerConnected NOTIFICATION-TYPE	2-21
anCntnUaProfDefaultAttsMissing NOTIFICATION-TYPE	2-22
anSMSCServerConnectFail NOTIFICATION-TYPE	2-22
anSMSCProfNotFound NOTIFICATION-TYPE	2-23
anSMSCServerConnectLost NOTIFICATION-TYPE	2-23
anCntnUaProfFileInvalid NOTIFICATION-TYPE	2-24
anSpsServerConnectFail NOTIFICATION-TYPE	2-24
anSpsServerConnectLost NOTIFICATION-TYPE	2-25
anCntnOnlineCatDBInstallationFailure NOTIFICATION-TYPE	2-25
anCntnFilterHashListFileInvalidEntry NOTIFICATION-TYPE	2-26
anCntnFilterHashListFileNotFound NOTIFICATION-TYPE	2-26
anCntnFilterHashListFileOverflow NOTIFICATION-TYPE	2-27
anCntnFilterHashListFileTooBig NOTIFICATION-TYPE	2-27
anCntnHealthCheckStateDown NOTIFICATION-TYPE	2-28
anCntnCACertExpired NOTIFICATION-TYPE	2-29
fmHmCacheOperStateDown NOTIFICATION-TYPE	2-29
anTemperatureAlarm NOTIFICATION-TYPE	2-30

anVoltageAlarm NOTIFICATION-TYPE	2-31
anHotSwapAlarm NOTIFICATION-TYPE	2-32
anTelcoAlarm NOTIFICATION-TYPE	2-33
anWatchdogAlarm NOTIFICATION-TYPE	2-34
anFanAlarm NOTIFICATION-TYPE	2-35
anAirFilterAlarm NOTIFICATION-TYPE	2-36
anTachAlarm NOTIFICATION-TYPE	2-37
anHwAlarm NOTIFICATION-TYPE	2-38
anCardNotBootingUp NOTIFICATION-TYPE	2-38
anLedStateChange NOTIFICATION-TYPE	2-39
anRebootEvent NOTIFICATION-TYPE	2-40
anPayloadFailure NOTIFICATION-TYPE	2-41
anFmSlotFrequentReboot NOTIFICATION-TYPE	2-42
anPortStatusDown NOTIFICATION-TYPE	2-42
anPortStatusUP NOTIFICATION-TYPE	2-43
anHwNodeDepartureEventData NOTIFICATION-TYPE	2-43
anHwExtStorageCreateFailure NOTIFICATION-TYPE	2-44
anHwExtStorageSizeMismatch NOTIFICATION-TYPE	2-45
anHwNoExtStorageDiskAvailable NOTIFICATION-TYPE	2-45
anHwNotEnoughFreeStorageSpace NOTIFICATION-TYPE	2-46
anHwExtStorageMoveFilesTimeout NOTIFICATION-TYPE	2-46
anHwExtStorageCloseFilesTimeout NOTIFICATION-TYPE	2-47
anExtractionPending NOTIFICATION-TYPE	2-47
anInsertionPending NOTIFICATION-TYPE	2-48
anIsolCpusMismatch NOTIFICATION-TYPE	2-48
anIpInterfaceOperStatusDown NOTIFICATION-TYPE	2-49
anDataFabricOperStateDown NOTIFICATION-TYPE	2-49
anGeoRedundancyStandbyOperStatusDown NOTIFICATION-TYPE	2-50
anGeoRedundancyActiveOperStatusDown NOTIFICATION-TYPE	2-50
anGeoRedundancyPrimaryNodeStandby NOTIFICATION-TYPE	2-51
anGeoRedundancySecondaryNodeActive NOTIFICATION-TYPE	2-51
anGeoRedundancyLinkDown NOTIFICATION-TYPE	2-52
anGeoRedundancyLinkVersionMismatch NOTIFICATION-TYPE	2-52
anDataFabricOperStateDownPathA NOTIFICATION-TYPE	2-53
anDataFabricOperStateDownPathB NOTIFICATION-TYPE	2-53
anBaseSwitchOperStateDownPathA NOTIFICATION-TYPE	2-54
anBaseSwitchOperStateDownPathB NOTIFICATION-TYPE	2-54
anBaseSwitchOperStateDown NOTIFICATION-TYPE	2-55
anNtpSyncError NOTIFICATION-TYPE	2-55
anBaseSwitchReachabilityDiffersPathAPathB NOTIFICATION-TYPE	2-56
anDataFabricReachabilityDiffersPathAPathB NOTIFICATION-TYPE	2-56
anIpBgpPeerOperStatusDown NOTIFICATION-TYPE	2-57
anPacketEngineError NOTIFICATION-TYPE	2-58
anPacketEngineCongestion NOTIFICATION-TYPE	2-59
anDataFabricPartialReachabilityPathA NOTIFICATION-TYPE	2-60
anPacketEngineWatchdogAlarm NOTIFICATION-TYPE	2-61
anPacketEngineKNICongfigurationMismatch NOTIFICATION-TYPE	2-62
anIpsecTunnelOperStatusDown NOTIFICATION-TYPE	2-62
anIpsecTunnelOperStatusUp NOTIFICATION-TYPE	2-63
anIpOspfV2NbrDown NOTIFICATION-TYPE	2-63
anIpOspfV3NbrDown NOTIFICATION-TYPE	2-64

anNatPoolSessionAlarmThreshold NOTIFICATION-TYPE	2-64
anNatPoolIpAddressAlarmThreshold NOTIFICATION-TYPE	2-65
anNatPoolPortChunkAlarmThreshold NOTIFICATION-TYPE	2-66
anBfdSessionDown NOTIFICATION-TYPE	2-67
anPortmapFailure NOTIFICATION-TYPE	2-68
fmNmAn3000ColdStart NOTIFICATION-TYPE	2-68
fmNmAn3000Test NOTIFICATION-TYPE	2-69
fmNmAn3000Commit NOTIFICATION-TYPE	2-69
an3000WarmStart NOTIFICATION-TYPE	2-70
anLinkUp NOTIFICATION-TYPE	2-70
anLinkDown NOTIFICATION-TYPE	2-71
anNmLoginFailure NOTIFICATION-TYPE	2-71
anTaskOverload NOTIFICATION-TYPE	2-72
anBladeOverload NOTIFICATION-TYPE	2-73
anSystemOverload NOTIFICATION-TYPE	2-74
anGtpPeerDown NOTIFICATION-TYPE	2-75
anCantPageSubscriberOutOfBuffers NOTIFICATION-TYPE	2-75
anDiameterPeerLinkDown NOTIFICATION-TYPE	2-76
anDiameterPeerLinkUp NOTIFICATION-TYPE	2-77
anRadiusPeerDown NOTIFICATION-TYPE	2-78
anRadiusPeerUp NOTIFICATION-TYPE	2-78
anGtppPeerDown NOTIFICATION-TYPE	2-79
anGtppPeerUp NOTIFICATION-TYPE	2-79
anPdnSessionAntiSpoofing NOTIFICATION-TYPE	2-80
anSgwServiceUp NOTIFICATION-TYPE	2-80
anSgwServiceDown NOTIFICATION-TYPE	2-81
anPgwServiceUp NOTIFICATION-TYPE	2-81
anPgwServiceDown NOTIFICATION-TYPE	2-82
anGgsnServiceUp NOTIFICATION-TYPE	2-82
anGgsnServiceDown NOTIFICATION-TYPE	2-83
anApnAvailable NOTIFICATION-TYPE	2-83
anApnNotAvailable NOTIFICATION-TYPE	2-84
anCaleaPeerLinkDown NOTIFICATION-TYPE	2-84
anCaleaPeerLinkUp NOTIFICATION-TYPE	2-85
anGtpPeerUp NOTIFICATION-TYPE	2-85
anCaleaTargetsCleared NOTIFICATION-TYPE	2-86
anCaleaInterfacesCleared NOTIFICATION-TYPE	2-86
anCaleaUtilizationLow NOTIFICATION-TYPE	2-87
anCaleaUtilizationMedium NOTIFICATION-TYPE	2-87
anCaleaUtilizationHigh NOTIFICATION-TYPE	2-88
anCaleaUtilizationCritical NOTIFICATION-TYPE	2-88
anCaleaCCBufferConfiguredSizeBelowThreshold NOTIFICATION-TYPE	2-89
anCaleaCCBufferUtilizationThresholdReached NOTIFICATION-TYPE	2-89
anCaleaIRIBufferUtilizationThresholdReached NOTIFICATION-TYPE	2-90
anCaleaTargetDBMaxSubsLimitReached NOTIFICATION-TYPE	2-90
anCaleaIRIBufferConfiguredSizeBelowThreshold NOTIFICATION-TYPE	2-91
anCaleaIfOrIfGroupConfigChange NOTIFICATION-TYPE	2-91
anCaleaLITargetCreatedOrDeleted NOTIFICATION-TYPE	2-92
anCaleaInterfaceGroupStatusDown NOTIFICATION-TYPE	2-92
anCaleaCCBufferDataLost NOTIFICATION-TYPE	2-93
anCaleaIRIBufferBufferDataLost NOTIFICATION-TYPE	2-93

anEmergencyCallAttemptFailed NOTIFICATION-TYPE	2-94
anEmergencyCallDropped NOTIFICATION-TYPE	2-94
anWagServiceDown NOTIFICATION-TYPE	2-95
anWagServiceUp NOTIFICATION-TYPE	2-95
anEpdgServiceUp NOTIFICATION-TYPE	2-96
anEpdgServiceDown NOTIFICATION-TYPE	2-96
anGwSubsGrpFileNotFound NOTIFICATION-TYPE	2-97
anCaleaUserBanFeatureConfigChange NOTIFICATION-TYPE	2-97
anCaleaCCDataLost NOTIFICATION-TYPE	2-98
anCaleaIRIDDataLost NOTIFICATION-TYPE	2-98
anPfcPpPeerDown NOTIFICATION-TYPE	2-99
anPfcPpPeerUp NOTIFICATION-TYPE	2-100
anCaleaIfGrpSourceProfileConfigChange NOTIFICATION-TYPE	2-101
anCaleaIfGrpSourceProfileNotFound NOTIFICATION-TYPE	2-101
anCaleaPdhirNotSupportedForSx3lifTunnelToCPF NOTIFICATION-TYPE	2-102
anCaleaDecryptFail NOTIFICATION-TYPE	2-102
fmSWCompMCMSwitchoverEventData NOTIFICATION-TYPE	2-103
anRedundancyOperState NOTIFICATION-TYPE	2-104
anCpuTosTaskState NOTIFICATION-TYPE	2-105
anNewCoreFileDetected NOTIFICATION-TYPE	2-106
anfiletpfailure NOTIFICATION-TYPE	2-106
anForcedSyncStart NOTIFICATION-TYPE	2-107
anForcedSyncFailed NOTIFICATION-TYPE	2-107
anPortStatusUp NOTIFICATION-TYPE	2-108
anfilepurgedduetodiskfull NOTIFICATION-TYPE	2-108
anKernelOptionsModified NOTIFICATION-TYPE	2-109
anFormatDisk NOTIFICATION-TYPE	2-110
anDiskFull NOTIFICATION-TYPE	2-110
anUEPoolThresholdAlarm NOTIFICATION-TYPE	2-111
anDataRecordFailure NOTIFICATION-TYPE	2-112
anRemoteMountFailed NOTIFICATION-TYPE	2-112
anEdrServerConnectionFailed NOTIFICATION-TYPE	2-113
anPkix509expiring NOTIFICATION-TYPE	2-113
anPkix509expired NOTIFICATION-TYPE	2-114
anPkix509revoked NOTIFICATION-TYPE	2-114
anPkioobjunreachable NOTIFICATION-TYPE	2-115
anPkioobjadded NOTIFICATION-TYPE	2-115
anPkioobjupdated NOTIFICATION-TYPE	2-116
anPkioobjremoved NOTIFICATION-TYPE	2-116
anPkix509crlnextupdateavailable NOTIFICATION-TYPE	2-117
anReleaseMismatch NOTIFICATION-TYPE	2-117
anPkioobjupdatenotavailable NOTIFICATION-TYPE	2-118
anPkisshauthorizedkeyaddedtouser NOTIFICATION-TYPE	2-118
anPkisshauthorizedkeyremovedfromuser NOTIFICATION-TYPE	2-119
anPkisshauthorizedkeyaddedtogroup NOTIFICATION-TYPE	2-119
anPkisshauthorizedkeyremovedfromgroup NOTIFICATION-TYPE	2-120
anPkisshtrustedcakeyaddedtocluster NOTIFICATION-TYPE	2-120
anPkisshtrustedcakeyremovedfromcluster NOTIFICATION-TYPE	2-121
anPkisshtrustedcakeyaddedtogroup NOTIFICATION-TYPE	2-121
anPkisshtrustedcakeyremovedfromgroup NOTIFICATION-TYPE	2-122
anPkisshuseraddedtoauthorizedprincipals NOTIFICATION-TYPE	2-122

anPkisshuserremovedfromauthorizedprincipals NOTIFICATION-TYPE	2-123
anPkisshgroupaddedtoauthorizedprincipals NOTIFICATION-TYPE	2-123
anPkisshgroupremovedfromauthorizedprincipals NOTIFICATION-TYPE	2-124
anfileexportfailure NOTIFICATION-TYPE	2-124
anPkisshnamesaddedtogroupauthorizedprincipals NOTIFICATION-TYPE	2-125
anPkissherrorapplyingconfigurationtosshcontrolfiles NOTIFICATION-TYPE ...	2-125
anPkisshnamesremovedfromauthorizedprincipals NOTIFICATION-TYPE	2-126
anPkisshnamesaddedtoauthorizedprincipals NOTIFICATION-TYPE	2-126
anPkisshnamesremovedfromgroupauthorizedprincipals NOTIFICATION-TYPE ..	2-127
anPkisshmaximumsecuritylevelset NOTIFICATION-TYPE	2-127
anPkisshcompatiblesecuritylevelset NOTIFICATION-TYPE	2-128
anPkisshstricthostkeycheckingsettono NOTIFICATION-TYPE	2-128
anPkisshstricthostkeycheckingsettoask NOTIFICATION-TYPE	2-129
anPkisshstricthostkeycheckingsettoyes NOTIFICATION-TYPE	2-129
anPkisshverifyhostkeydnssettono NOTIFICATION-TYPE	2-130
anPkisshverifyhostkeydnssettoyes NOTIFICATION-TYPE	2-130
anPkisshverifyhostkeydnssettoask NOTIFICATION-TYPE	2-131
anPkisshknownhostcakeyremoved NOTIFICATION-TYPE	2-131
anPkisshknownhostcakeyadded NOTIFICATION-TYPE	2-132
anPkisshknownhostkeyremoved NOTIFICATION-TYPE	2-132
anPkisshknownhostkeyadded NOTIFICATION-TYPE	2-133
anPkisshlocalhostcertificatereplaced NOTIFICATION-TYPE	2-133
anPkisshlocalhostcertificateremoved NOTIFICATION-TYPE	2-134
anPkisshlocalhostcertificateadded NOTIFICATION-TYPE	2-134
anPkisshrevoked NOTIFICATION-TYPE	2-135
anPkimanuallyrevoked NOTIFICATION-TYPE	2-135
anPkisshuserkrlreplaced NOTIFICATION-TYPE	2-136
anPkisshuserkrladded NOTIFICATION-TYPE	2-136
anPkisshuserkrlremoved NOTIFICATION-TYPE	2-137
anPkisshcertexpiring NOTIFICATION-TYPE	2-137
anPkisshcertexpired NOTIFICATION-TYPE	2-138
anNewMemImageFileDetected NOTIFICATION-TYPE	2-138
anNewFaultFileDetected NOTIFICATION-TYPE	2-139
anNodeRebootRequired NOTIFICATION-TYPE	2-139
anRadiusAccountingOnMsgNotSent NOTIFICATION-TYPE	2-140
anClusterRebootRequired NOTIFICATION-TYPE	2-140
anThresholdCrossingAlarm NOTIFICATION-TYPE	2-141
anLicenseCapacityEnforcement NOTIFICATION-TYPE	2-141
anLicenseCapacityLimit NOTIFICATION-TYPE	2-142
anLicenseLifetimeEnforcement NOTIFICATION-TYPE	2-142
anLicenseLifetime NOTIFICATION-TYPE	2-143
anLicensePlsSeparation NOTIFICATION-TYPE	2-143
anLicensePlsGraceExpired NOTIFICATION-TYPE	2-144

List of Tables

Table 2-1 MIB Keywords **2-2**

Preface

This guide describes how to display trap alarm information, the organization of the Affirmed Management Information Base (MIB), and information on accessing and reading the MIB.

Note: *The Affirmed Networks Mobile Content Cloud™ (MCC) is the mobile services software solution that operates on virtual platforms such as blade systems.*

Audience

This guide is intended for network operators (sometimes referred to as Users or Operators in this guide), installation staff, and other qualified service personnel responsible for installing, provisioning, and monitoring the system. The audience should be familiar with Long Term Evolution (LTE), 3G or 4G networks.

Release Information

See the Release Notes for important information, requirements, limitations, and restrictions that apply to this release.

Note: *For details on Acuitas-triggered alarms, see the Acuitas User's Guide.*

How to Use This Guide

This guide contains the following chapters:

Chapter	Describes
Chapter 1, Displaying Alarm Information	Displaying trap alarms and the following information for each alarm: ■ Description of the alarm ■ Trap ID ■ Auto Clearing: Yes or No ■ Severity: Critical, Major, Minor, Warning, Info, Not Applicable ■ Potential impact on the network or service ■ Corrective action to follow to resolve the alarm, when applicable
Chapter 2, Accessing MIB Information	The organization of the Affirmed Management Information Base (MIB) and information on accessing and reading the MIB.

Features in This Release

This release does not include any new alarm-related features.

Note the following:

- For a complete list of the features supported in this release, see the *Software Release Notes*.
- For a list of additional Affirmed Networks documentation, see the *Affirmed Networks Documentation Library*.
- For a comprehensive list of terms and acronyms used in Affirmed Networks documentation, see *Affirmed Networks Terms and Acronyms*.

Changes in This Release

This release includes the following changes to alarm information.

Alarm	Alarm Information Change
anClusterRebootRequired, Trap ID: 338	Description: The cluster needs to be rebooted because one or more of the following have changed on one or more nodes in the cluster. 1. isolcpus 2. core-layout 3. max-packet-size

New Alarms in This Release

This release includes the following new alarms.

Alarm	Description
anCaleaDecryptFail, Trap ID: 343	The alarm is generated when encrypted CALEA Lawful Intercept data can not be decrypted (could be security key mismatch between CPF and UPF).

Conventions

This guide uses the following conventions, when applicable:

Description	Convention	Examples
Command names, keywords, dialog boxes, buttons, icons, menus	Times New Roman bold font	Use configure_ha to configure... Enter y . To continue, press Enter .
Selecting a menu item	Menu => Option	Select Security => Group Management .
Variable parameters for which you supply values	<i><courier bold italic blue font></i>	configure_dr convert slave --masterhost <host IP>
User input	Courier bold blue font	cd /opt/Affirmed/NMS/bin
Screen messages, system output, sample source code	Courier regular blue font	Checking for License...
Required keywords and arguments in square brackets	[]	cluster [id] node [id] reboot
Optional keywords and arguments in curly brackets	{ }	{cdr-file-name}
Keywords separated by the pipe symbol. Requires you to specify only one item from the set.	 	Is this correct? [y n]
Keywords representing a single element in angle brackets	< >	<host name>
Asterisk after a CLI object indicates a required object.	*	name*
Variables, book and chapter titles, file path names, new terms, and emphasized text	<i>Times New Roman italic font</i>	See the <i>Acuitas User's Guide</i> .

Note: Additional information that may apply to the subject text.

Tip: Helpful suggestions.



CAUTION: Proceed carefully to avoid possible equipment damage or data loss.

How to Obtain Product Documentation

Documentation is available for currently supported product releases. Documentation is available online in Adobe PDF format. You can view PDFs online using the latest version of Adobe Reader®. To download the latest version of the Adobe Reader software from the Adobe web site, go to <http://get.adobe.com/reader/>

Product documentation is available from the Affirmed Networks SFTP server. Contact your sales representative or the TAC for instructions on accessing the SFTP server.

See the *Affirmed Networks Documentation Library* for a complete list of Affirmed Networks product documentation.

Technical Assistance Center

Affirmed Networks Technical Assistance Center (TAC) provides technical support 24 hours a day, 7 days a week (24 x 7) for any customer with an active maintenance contract.

To contact the TAC:



E-mail: prodsupport@affirmednetworks.com



24 x 7 Telephone support:

Local: 1-978-268-0871

Toll free: 1-888-283-2838

Displaying Alarm Information

Enter the **show alarms**, **show alarms active**, and **show alarms history** CLI commands from the Exec level to generate a list of alarms.

The MCC supports the following alarm severities:

- **Critical** – A critical condition affecting the service of the GRID or chassis has occurred.
- **Major** – An error has occurred.
- **Minor** – A significant event that may require attention has occurred.
- **Warning** – An event that may require attention has occurred.
- **Info** – A normal operation has occurred.
- **Not Applicable** – No severity.

Alarm Detail

The alarm detail in this chapter lists the following information:

- Description of the alarm
- Trap ID
- Status:
 - *Current* – Indicates a current/valid definition
 - *Deprecated* – Indicates an obsolete definition but permits new or continued implementation to support backward compatibility
 - *Obsolete* – Indicates that the definition is not implemented and should be removed if previously implemented
- Severity: *Critical, Major, Minor, Warning, Info, Not Applicable*
- Auto Clearing: *Yes or No*
- Potential impact on the network or service
- Corrective action to follow to resolve the alarm, when applicable

fmCntnFilterCategoryFileTooBig

Description: Adding CF category failed as file is too large.
Trap ID: 39
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and are never matched.
Corrective Action: Reduce file size to less than 500000 entries.

fmCntnFilterCategoryFileNotFound

Description: Adding CF category failed as file does not exist on NE.
Trap ID: 40
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Any filter using this category will NOT take effect.
Corrective Action: Load required file to designated location on MCC.

fmCntnFilterCategoryFileOverflow

Description: Adding CF category failed as exceeded max supported filter entries per filter database size.
Trap ID: 41
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries will not be built in filter DB and are never matched.
Corrective Action: Increase filter database size of StaticFilter by changing the configuration or reduce the total amount of entries from imported files.

fmCntnFilterBlacklistFileOverflow

Description: Adding CF blacklist failed as exceeded max supported filter entries per filter database size.
Trap ID: 42
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and are never matched.
Corrective Action: Increase filter database size of StaticFilter by changing the configuration or reduce the total amount of entries from imported files.

fmCntnFilterBlacklistFileTooBig

Description: Adding CF blacklist failed as file is too large.
Trap ID: 44
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and are never be matched.
Corrective Action: Reduce the file size to less than 500000 entries.

fmCntnFilterBlacklistFileNotFound

Description: Adding CF blacklist failed as file does not exist on NE.
Trap ID: 45
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Global blacklist using this file will NOT take effect.
Corrective Action: Load required file to designated location on MCC.

fmCntnFilterCategoryFileInvalidEntry

Description: Adding CF category got error as file has invalid entry.
Trap ID: 47
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Invalid entries are dropped and never matched.
Corrective Action: Correct to remove invalid entries in the file.

fmCntnFilterBlacklistFileInvalidEntry

Description: Adding CF blacklist got error as file has invalid entry.
Trap ID: 48
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Invalid entries are dropped and will never be matched.
Corrective Action: Correct or remove invalid entries in the file.

fmCntnHttpProxyServerConnectFail

Description: http-proxy failed to connect server.
Trap ID: 49
Status: Obsolete
Severity: Critical
Auto Clearing: Yes
Potential Impact: Obsolete.
Corrective Action: Obsolete.

anCntnFilterWhitelistFileInvalidEntry

Description: Adding CF whitelist got error as file has invalid entry.
Trap ID: 56
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Invalid entries are dropped and therefore never matched.
Corrective Action: Correct or remove invalid entries in the file.

anCntnFilterWhitelistFileOverflow

Description: Adding CF whitelist failed as exceeded max supported filter entries per filter database size.
Trap ID: 57
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and are never matched.
Corrective Action: Increase filter database size of StaticFilter by changing the configuration or reduce the total amount of entries from imported files.

anCntnFilterWhitelistFileTooBig

Description: Adding CF whitelist failed as file is too large.
Trap ID: 58
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and are never matched.
Corrective Action: Reduce file size to less than 500000 entries.

anCntnFilterWhitelistFileNotFound

Description: Adding CF whitelist failed as file does not exist on NE.
Trap ID: 59
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Global whitelist using this file does NOT take effect.
Corrective Action: Load required file to designated location on MCC.

anCacheDiskOperationalStateAlarm

Description: Monitor the cache SSD operational state.
Trap ID: 61
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Content-cache service do not work.
Corrective Action: Verify that SSDs or disk for caching is mounted.

anCntnUrlListFileInvalidEntry

Description: Adding urlList got error as file has invalid entry.
Trap ID: 62
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Invalid entries are dropped and never matched.
Corrective Action: Correct or remove invalid entries from the file.

anCntnUrlListFileOverflow

Description: Adding UrlList failed as exceeded max supported filter entries per filter database size.
Trap ID: 63
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and are never matched.
Corrective Action: Increase filter database size of UrlList by changing the configuration or reduce the total amount of entries from imported files.

anCntnUrlListFileNotFound

Description: Adding urlList failed as file does not exist on NE.
Trap ID: 64
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Any filter or http-rule-group using this urlList is NOT matched.
Corrective Action: Repeat file download if import-from-server, or load file to designated location on MCC if import-from-local-file.

anCntnUrlListFileTooBig

Description: Adding urlList failed as file is too big.
Trap ID: 65
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Extra entries are not built in filter DB and never matched.
Corrective Action: Reduce file size to less than 500000 entries.

anPlaFileDownloadFail

Description: Policy lists agent failed to download a policy file from external server.
Trap ID: 67
Status: Current
Severity: Warning
Auto Clearing: Yes
Potential Impact: MCC may be using outdated policies (for example, url-list or content categorization databases) or have no policies if none of previous downloads were successful.
Corrective Action: Check if server is reachable from MMC. Verify that the policy file exists on the server. Check configured download login credentials.

anCacheDiskErrorStateAlarm

Description: Monitor the Cache SSD read/write error state.
Trap ID: 79
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Content-cache service do not work.
Corrective Action: Check disk status and clear space.

anLDAPServerConnectFail

Description: Failed to connect LDAP server.

Trap ID: 81

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: This LDAP remote server is not used for LDAP query. If more than one remote server is configured in the LDAP profile, the system will try another server.

Corrective Action: Check LDAP remote-server configuration to verify if it is reachable from MCC.

anLDAPServerConnectLost

Description: LDAP server connection lost.

Trap ID: 82

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: This LDAP remote server is marked as failure and not used for LDAP query. If more than one remote server is configured in the LDAP profile, the system will try another

Corrective Action: Check LDAP server connectivity and make sure it is running properly.

anLDAPProfNoServerConnected

Description: LDAP profile does not have a connection to remote server.

Trap ID: 83

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: This LDAP remote server is not used for LDAP query. If more than one remote server is configured in the LDAP profile, the system will try another server.

Corrective Action: Check LDAP remote server configuration to verify if it is reachable from MCC.

anCntnUaProfDefaultAttsMissing

Description: Missing required attributes in the default UA profile.
Trap ID: 86
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Some of the UA profile attributes are missing. These attributes are taken from the default UA profile instead.
Corrective Action: Verify that the UA profile contains all necessary attribute.

anSMSCServerConnectFail

Description: Failed to connect to SMSC server.
Trap ID: 95
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: The SMS message is not sent because the server is not reachable. The system uses other SMSC servers, if configured, to check connectivity to the SMSC server.
Corrective Action:

anSMSCProfNotFound

Description: SMSC profile not found.
Trap ID: 96
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: The SMS message is not sent because no SMSC profile has been configured.
Corrective Action: Verify that an SMSC profile is configured and associated with an http-proxy instance.

anSMSCServerConnectLost

Description: SMSC server connection lost.
Trap ID: 97
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: MCC was able to bind to the SMSC server indicating that the server is operational, however the connection was abruptly lost. The system uses other SMSC servers, if configured, to check connectivity to the SMSC server.
Corrective Action:

anCntnUaProfFileInvalid

Description: Adding UA profile file failed due to invalid profile file.

Trap ID: 109

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: The UA profile is not added to the database. The default UA profile is used instead.

Corrective Action: Verify that the file for the UA profile exists and is in the correct format.

anSpsServerConnectFail

Description: Failed to connect to SPS server.

Trap ID: 131

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: The SPS server is not reachable and the SPS query is not sent.

Corrective Action: Check connectivity to the SPS server.

anSpsServerConnectLost

Description: SPS server connection lost.

Trap ID: 132

Status: Obsolete

Severity: Critical

Auto Clearing: Yes

Potential Impact: Obsolete.

Corrective Action: Obsolete.

anCntnOnlineCatDBInstallationFailure

Description: Online Categorization Database Installation Failed

Trap ID: 218

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Online Categorization Database maybe left stale even not usable therefor content-categorization on the slot may not be valid.

Corrective Action: Check connectivity between current slot and MCM, check the import-summary for the import_num.

anCntnFilterHashListFileInvalidEntry

Description: Adding filterHashList got error as file has invalid entry.

Trap ID: 291

Status: Current

Severity:

Auto Clearing: Yes

Potential Impact:

Corrective Action:

anCntnFilterHashListFileNotFound

Description: Adding filterHashList failed as file does not exist on NE.

Trap ID: 292

Status: Current

Severity:

Auto Clearing: Yes

Potential Impact:

Corrective Action:

anCntnFilterHashListFileOverflow

Description: Adding FilterHashList failed as exceeded max supported filter entries per filter database size.

Trap ID: 293

Status: Current

Severity:

Auto Clearing: Yes

Potential Impact: Extra entries are not built in filter DB and are never matched.

Corrective Action: Increase filter database size of FilterHashList by changing the configuration or reduce the total amount of entries from imported files.

anCntnFilterHashListFileTooBig

Description: Adding filterHashList failed as file is too big.

Trap ID: 294

Status: Current

Severity:

Auto Clearing: Yes

Potential Impact:

Corrective Action:

anCntnHealthCheckStateDown

Description: The service monitored by content health check is not reachable.
Trap ID: 320
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: The monitored service in specified network context becomes unreachable by proxy.
Corrective Action: Check service status. Check network.

anCntnCACertExpired

Description: One or multiple CA (Certificate Authority) certificates have expired.
Trap ID: 335
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: TFD (Toll Free Data) certificate verification will fail.
Corrective Action: Generate new CA certificate and install it in the CA Cert Store.

fmHmCacheOperStateDown

Description: CSM cache operationally down.
Trap ID: 28
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: content-cache service does not work.
Corrective Action: Check if disk mount point exists.

anTemperatureAlarm

Description: HW sensor raising temperature alarm.
Trap ID: 29
Status: Current
Severity: Minor, Major, Critical
Auto Clearing: Yes
Potential Impact: May indicate a Minor/Major/Critical alarm due to minor temperature increases.
Corrective Action: Minor, Major alarm should clear itself when condition resolves. Critical alarm should be flagged and removed by CLI.

anVoltageAlarm

Description: HW sensor raising voltage alarm.
Trap ID: 30
Status: Current
Severity: Minor, Major, Critical
Auto Clearing: Yes
Potential Impact: Voltage out of tolerance on the external power input may cause the system to shut down. Voltage out of tolerance on an internal power supply may cause system issues.
Corrective Action: If an external system voltage is out of tolerance, -48V DC or AC power, corrected the issue. Contact the TAC for any other voltage alarm internal to the system that does not clear.

anHotSwapAlarm

Description: HW sensor raising hot swap alarm.
Trap ID: 31
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: FRU components hot swap latch is not engaged.
Corrective Action: Perform a hot swap on the FRU and re-engage the latch.

anTelcoAlarm

Description: HW Sensor Raising Telco Alarm
Trap ID: 32
Status: Deprecated
Severity: Minor, Major, Critical
Auto Clearing: No
Potential Impact: Telco alarm reflects the HW telco alarm indications (LEDS, Telco alarm interface).
Corrective Action: Alarm condition must be removed and the CLI must be used to clear the Telco Alarm LEDS and alarm relays on the chassis.

anWatchdogAlarm

Description: HW Sensor Raising Watchdog Alarm
Trap ID: 33
Status: Deprecated
Severity: Major
Auto Clearing: No
Potential Impact: A blade or FRU raised the IPMC watchdog alarm event. A forced reset has occurred on the blade.
Corrective Action: A blade may have had a software fault or hardware issue. If alarm repeats, contact the TAC.

anFanAlarm

Description: HW Sensor Raising Fan Alarm
Trap ID: 34
Status: Deprecated
Severity: Critical
Auto Clearing: No
Potential Impact: Indicates that a fan tray is not present or is not responsive.
Corrective Action: Insert a fan tray FRU. If all fan trays are present, contact the TAC.

anAirFilterAlarm

Description: HW sensor raising air filter alarm.
Trap ID: 35
Status: Current
Severity: Not supported
Auto Clearing: Yes
Potential Impact: Ignore this alarm.
Corrective Action: Ignore this alarm.

anTachAlarm

Description: HW sensor raising tach alarm..
Trap ID: 36
Status: Current
Severity: Minor, Major, Critical
Auto Clearing: Yes
Potential Impact: The system fan speed adjusts according to a preset algorithm. Fan speed adjustment is not an indication of system problems unless the temperature alarms are in a critical state and the fans are at full speed (Critical).
Corrective Action: The alarm shuts off when the fan speed returns to steady state.

anHWAAlarm

Description: HW sensor raising hardware alarm.
Trap ID: 37
Status: Current
Severity: Minor, Major, Critical
Auto Clearing: Yes
Potential Impact: This is a generic HW alarm. To determine the cause, enter the -show chassis sensor-summary- command.
Corrective Action: Alarm behavior depends on the type of alarm being triggered.

anCardNotBootingUp

Description: Card is plugged in but not operational
Trap ID: 46
Status: Deprecated
Severity: Major
Auto Clearing: Yes
Potential Impact: Since a card is not booting up, the services provided by that card are not available.
Corrective Action: This may be due to bad hardware such as bent pins on the RTM. Examine the RTM for any bent pins. If there are no bent pins, replace the card.

anLedStateChange

Description: LED state change.
Trap ID: 74
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: This is an informational level alarm used to flag EMS of a LED state change.
Corrective Action: Not applicable.

anRebootEvent

Description: Module rebooted.
Trap ID: 78
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The module may be rebooted due to an expected event or an unexpected event. Cases when a module reboot is expected are: 1. Image Upgrade2. Module reboot triggered via CLI or Linux ShellModule reboot causes a switchover and the backup takes over the services provided by the rebooted module/card.A module may reboot unexpectedly due to:1. Kernel Crash2. Resource exhaustion (such as memory, buffers)3. Disruption in communication with the controller card4. If an application faults on the controller card, it causes the controller card to reboot
Corrective Action: Collect the tech-support information and contact the TAC.

anPayloadFailure

Description: The specified payload has experienced a hardware or firmware failure.
Trap ID: 80
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Blade is unable to boot or is in an unusable state.
Corrective Action: Contact the TAC for support.

anFmSlotFrequentReboot

Description: Slot (CSM or SSM) has exceeded reboot frequency threshold.
Trap ID: 114
Status: Current
Severity: Minor
Auto Clearing: Yes
Potential Impact: The slot (CSM or SSM) will be set to admin down and taken out of service.
Corrective Action: Collect the tech-support information and contact the TAC.

anPortStatusDown

Description: Port Status is Down
Trap ID: 128
Status: Deprecated
Severity: Not Applicable
Auto Clearing: No
Potential Impact: Not Applicable
Corrective Action: Not Applicable

anPortStatusUP

Description: Port Status is UP
Trap ID: 129
Status: Deprecated
Severity:
Auto Clearing: No
Potential Impact:
Corrective Action:

anHwNodeDepartureEventData

Description: Node has departed from cluster.
Trap ID: 142
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: All services provided by node will go down or failover to the backup.
Corrective Action: The node will automatically restart.

anHwExtStorageCreateFailure

Description: Failure during the creation of an extended-storage disk partition
Trap ID: 199
Status: Current
Severity: Major
Auto Clearing: No
Potential Impact: Loss of extended-storage disk
Corrective Action: Retry CLI command: cluster X extended-storage create

anHwExtStorageSizeMismatch

Description: Alarm is generated when the extended-storage disk size is not matched between the Active and Standby MCMS
Trap ID: 200
Status: Current
Severity: Major
Auto Clearing: No
Potential Impact: Loss of data if both MCMS do not have the same size extended-storage disk
Corrective Action: Modify extended-storage disk sizes in vSphere to match

anHwNoExtStorageDiskAvailable

Description: This alarm is generated when an ext-storage disk is required but none has been created
Trap ID: 201
Status: Current
Severity: Major
Auto Clearing: No
Potential Impact: Loss of data if an extended-storage disk is needed but there is not one available
Corrective Action: Create an extended-storage disk in vSphere with sufficient size to match the peer node ext-storage disk

anHwNotEnoughFreeStorageSpace

Description: Lack of sufficient free storage space available
Trap ID: 202
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Unable to move data back to original storage disk on extended-storage delete
Corrective Action: Purge data from extended-storage disk and retry

anHwExtStorageMoveFilesTimeout

Description: Event generated when moving files from one storage site to another exceeds timeout.
Trap ID: 203
Status: Current
Severity: Major
Auto Clearing: No
Potential Impact: Data could be lost or become hidden in a no longer used disk partition
Corrective Action: Missing data would have to be moved by tech support

anHwExtStorageCloseFilesTimeout

Description: Event generated when waiting for files to close on a disk partition exceeds a timeout
Trap ID: 204
Status: Current
Severity: Major
Auto Clearing: No
Potential Impact: Data could become lost or missing in a hidden disk partition
Corrective Action: Data must be moved manually by tech support

anExtractionPending

Description: Fru entered Extraction pending state
Trap ID: 208
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: Fru entered extraction pending state and wont be available. Possibly done manually to extract the fru.
Corrective Action: Insert the fru back in.

anInsertionPending

Description: Fru entered insertion pending state
Trap ID: 209
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: The fru will be available in inventory and come online.
Corrective Action: Configure the fru in cli if available and not done already.

anIsolCpusMismatch

Description: Incorrect number of Isol Cpus for this platform
Trap ID: 242
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Effectuated nodes are potentially unstable in the cluster
Corrective Action: graceful-restart command

anIpInterfaceOperStatusDown

Description: The operational status of an IP interface is down.
Trap ID: 88
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: This IP interface is no longer available for use when forwarding traffic. Depending on configuration and network topology, this may impact user traffic.
Corrective Action: The operational state of an IP interface is affected by the lower layer interface state. Determine if there is an issue with the physical port. For example, verify that the cable is securely inserted into the port.

anDataFabricOperStateDown

Description: Communication over the data fabric is down.
Trap ID: 110
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Node/card is not able to provide service. When data-plane-protection configuration specifies reset-detached-nodes, this node is automatically removed (and potentially restored) from (to) service based on monitoring of data-plane connectivity status.
Corrective Action: Diagnose the underlying network connectivity issue.

anGeoRedundancyStandbyOperStatusDown

Description: Indicates a Geo-redundant standby cluster is not ready and the active peer is not currently protected.
Trap ID: 117
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Geo-redundant standby cluster is not ready and active cluster is not backed up, therefore a failure of the active cluster causes a service outage.
Corrective Action: Issue show geographic-redundancy redundancy-group-status to determine the cause. Possible causes include: geo link is down, mismatched software versions, inconsistent geo-redundancy configuration, or standby cluster is not booted. Conduct diagnosis at the standby mcm console.

anGeoRedundancyActiveOperStatusDown

Description: Geo-redundant active cluster is not fully functional due to link health status with neighboring network elements.
Trap ID: 118
Status: Current
Severity: Critical
Auto Clearing: Yes
Potential Impact: Geo-redundant active cluster not fully functional due to unhealthy link with external server (for example, radius, ocs, etc). This may potentially result in a service outage.
Corrective Action: Issue show geographic-redundancy redundancy-group-status command to determine the unhealthy link and further isolate the link.

anGeoRedundancyPrimaryNodeStandby

Description: Geo-redundant node designated as HA-Role primary has entered HA-State standby.

Trap ID: 133

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: Informational only, no impact to service.

Corrective Action: If failback desired such that primary geo redundant node is active, issue geographic-redundancy group <geo-group-name> revert command at primary cluster. Issuing this command may disrupt service.

anGeoRedundancySecondaryNodeActive

Description: Geo-redundant node designated as HA-Role secondary has entered HA-State active.

Trap ID: 134

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: Informational only, no impact to service.

Corrective Action: If failback desired such that primary geo redundant node is active, issue geographic-redundancy group <geo-group-name> revert command at primary cluster. Issuing this command may disrupt service.

anGeoRedundancyLinkDown

Description: Geo-redundancy link is down.

Trap ID: 136

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: Communication link between geo redundant clusters is down. A failure of the active cluster will cause service outage.

Corrective Action: Diagnose physical connectivity between the geo redundant node and verify geo redundant configuration at each node.

anGeoRedundancyLinkVersionMismatch

Description: Geo-redundant peers running incompatible software versions.

Trap ID: 137

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: Geo-redundant standby cluster is not ready and active cluster is not backed up, therefore a failure of the active cluster causes a service outage.

Corrective Action: Change the software version of primary or secondary cluster such that they are compatible in terms of geo-redundancy capabilities. Contact the TAC for a compatibility matrix.

anDataFabricOperStateDownPathA

Description: Inter-node connectivity health check over data fabric path A is down.

Trap ID: 144

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Connectivity for data plan path A of a redundant pair is non-functional.

Corrective Action: Diagnose underlying network connectivity issue.

anDataFabricOperStateDownPathB

Description: Inter-node connectivity health check over data fabric path B is down.

Trap ID: 145

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Connectivity for data plan path B of a redundant pair is non-functional.

Corrective Action: Diagnose underlying network connectivity issue.

anBaseSwitchOperStateDownPathA

Description: Inter-node connectivity health check over base switch path A is down.

Trap ID: 147

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: When control plane redundancy is enabled (during low-level node provisioning at the configure command) there are two base devices created and assigned to manage control plane connectivity for the node. Both links are monitored using keep-alive messages to detect and perform failovers from a failed link to a working link.

Corrective Action: Verify base redundancy configuration including vlan tags is consistent across all AN3000 nodes including any external L2 bridge devices. If alarm persists, contact higher level support.

anBaseSwitchOperStateDownPathB

Description: Inter-node connectivity health check over base switch path B is down.

Trap ID: 148

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: When control plane redundancy is enabled (during low-level node provisioning at the configure command) there are two base devices created and assigned to manage control plane connectivity for the node. Both links are monitored using keep-alive messages to detect and perform failovers from a failed link to a working link.

Corrective Action: Verify base redundancy configuration including vlan tags is consistent across all AN3000 nodes including any external L2 bridge devices. If alarm persists, contact higher level support.

anBaseSwitchOperStateDown

Description: Inter-node connectivity health check over base switch paths A and B are down.

Trap ID: 149

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: Inter-node control plane health check over base switch A and B are down.

Corrective Action: Verify base redundancy configuration including vlan tags is consistent across all AN3000 nodes including any external L2 bridge devices. If alarm persists, contact higher level support.

anNtpSyncError

Description: Cannot sync with configured NTP servers.

Trap ID: 151

Status: Current

Severity: Minor

Auto Clearing: No

Potential Impact: System event and log times may be out of sync with actual time.

Corrective Action: Ensure connectivity to the NTP servers.

anBaseSwitchReachabilityDiffersPathAPathB

Description: Base switch node reachability differs between path A and path B.

Trap ID: 168

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: One path of the redundant base switch paths has failed to reach all nodes.

Corrective Action: Issue show cluster <name> control-plane-protection status command and examine the bitmap of reachable nodes. The reachable nodes over path A and path B differs for the node reporting the alarm. Use this information to isolate the connectivity issue.

anDataFabricReachabilityDiffersPathAPathB

Description: Map of reachable nodes over data fabric path A differs from path B.

Trap ID: 169

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: One path of the redundant data fabric paths has failed to reach all nodes.

Corrective Action: Issue show cluster <name> data-plane-protection status command and examine the bitmap of reachable nodes. The reachable nodes over path A and path B differs for the node reporting the alarm. Use this information to isolate the connectivity issue.

anIpBgpPeerOperStatusDown

Description: A BGP peering is not in Established state. The alarm is raised when peering starts, restarts, cleared, or when a peering leaves Established state due to a protocol or networking event. The alarm is cleared when a peering enters Established state.

Trap ID: 186

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Traffic forwarding that relies on routes learned over the BGP peering will fail if there are no alternate routes.

Corrective Action: Verify the configurations of the neighbors at each end of the peering. With MH-EBGP, check the ebgp-multihop configuration parameter. Check for an error code using the show ip-protocols CLI command and n/w reachability using ping command.

anPacketEngineError

Description: The network packet engine has encountered an error preventing any data plane communication on the current node (control plane is not affected)

Trap ID: 206

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: No data plane connectivity on the affected node

Corrective Action: When available, corrective action is described in the alarm information

anPacketEngineCongestion

Description: The packet network engine is experiencing congestion sufficiently severe that packet memory reached critical low level. Packets reception is stopped until packet memory returns to acceptable level

Trap ID: 207

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: No data plane connectivity on the affected node

Corrective Action: If the alarm does not clear on its own quickly, contact customer support/open a ticket

anDataFabricPartialReachabilityPathA

Description: Inter-node connectivity health check detects partial connectivity with peer nodes over data plane path A.

Trap ID: 210

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Packet loss over data plane.

Corrective Action: Use command show data-plane-protection status to determine node(s) that are not reachable. Check path A connectivity of data plane.

anPacketEngineWatchdogAlarm

Description: The packet network engine has experienced a critical error that is preventing packet processing. Packet processing is stopped.

Trap ID: 239

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: No data connectivity on the affected node

Corrective Action:

anPacketEngineKNICongfigurationMismatch

Description: A mismatch exists between the provisioned packet processing resources and what node booted with.

Trap ID: 241

Status: Current

Severity: Minor

Auto Clearing: Yes

Potential Impact: Inefficient allocation of resources

Corrective Action: graceful-restart command

anIpsecTunnelOperStatusDown

Description: IPsec TUNNEL-DOWN

Trap ID: 246

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Loss of connectivity

Corrective Action:

anIpsecTunnelOperStatusUp

Description: IPsec TUNNEL-UP
Trap ID: 247
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact:
Corrective Action:

anIpOspfv2NbrDown

Description: An OSPFv2 neighbor is not in Full/2-Way state. The alarm will be generated when a neighbor leaves Full/2-Way state. The alarm is cleared when neighbor enters Full/2-Way state.
Trap ID: 302
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: Traffic forwarding that relies on routes learned over the OSPFv2 peering will fail if there are no alternate routes.
Corrective Action: verify the configuration at each end of the peering. Also, check for any network failures.

anIpOspfv3NbrDown

Description: An OSPFv3 neighbor is not in Full/2-Way state. The alarm will be generated when a neighbor leaves Full/2-Way state. The alarm is cleared when neighbor enters Full/2-Way state.
Trap ID: 303
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: Traffic forwarding that relies on routes learned over the OSPFv3 peering will fail if there are no alternate routes.
Corrective Action: verify the configuration at each end of the peering. Also, check for any network failures.

anNatPoolSessionAlarmThreshold

Description: The nat-pool session utilization has exceeded threshold. This may potentially lead to session or connection setup failures.

Trap ID: 304

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: If the system continues to remain in this state, the nat pool may run out of IPS or Port-chunks resulting in session or connection setup failures.

Corrective Action: Increase the capacity of the available IPS by increasing the range of the existing ip-sub-pools or adding new ip-sub-pools in the nat-pool.

anNatPoolIpAddressAlarmThreshold

Description: The nat-pool IP address utilization has exceeded threshold. This may potentially lead to session or connection setup failures.

Trap ID: 305

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: If the system continues to remain in this state, the nat pool may run out of IPS resulting in session or connection setup failures.

Corrective Action: Increase the capacity of the available IPS by increasing the range of the existing ip-sub-pools or adding new ip-sub-pools in the nat-pool.

anNatPoolPortChunkAlarmThreshold

Description: The nat-pool Port chunk utilization has exceeded threshold. This may potentially lead to session or connection setup failures.

Trap ID: 306

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: If the system continues to remain in this state, the nat pool may run out of port chunks resulting in session or connection setup failures.

Corrective Action: Increase the capacity of the available IPS by increasing the range of the existing ip-sub-pools or adding new ip-sub-pools in the nat-pool.

anBfdSessionDown

Description: This event is generated when a BFD session goes down. It is cleared when the BFD session goes up. A gratuitous clear will happen the first time the BFD session goes up. Toggled by ip-protocols/bfd/enable-bfd-session-down-alarms

Trap ID: 329

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: If a BFD session is down it indicates a connectivity issue. Additionally, any router instances protected by that BFD session will also be brought down.

Corrective Action: Investigate the connectivity issue.

anPortmapFailure

Description: The network ports are not in the correct order, which causes connectivity to the desired network to appear broken.

Trap ID: 333

Status: Current

Severity: Critical

Auto Clearing: No

Potential Impact: Blade is in an unusable state.

Corrective Action: Contact the TAC for support.

fmNmAn3000ColdStart

Description: A ColdStart trap signifies that the an3000/MCC is reinitializing itself and that its configuration may have been altered.

Trap ID: 23

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The AN3000 rebooted and service is disrupted, configuration may have changed.

Corrective Action: Alarm is informational, but if this condition was not expected then collect the tech-support information and contact the TAC.

fmNmAn3000Commit

Description: An NMD configuration has been committed.
Trap ID: 25
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: System configuration has changed.
Corrective Action: No further action is required. Verify configuration changes if desired.

an3000WarmStart

Description: A WarmStart trap signifies that the an3000/MCC is reinitializing itself such that its configuration is unaltered.
Trap ID: 152
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: Performing a warm start impacts service, but the configuration is not altered.
Corrective Action: None, alarm is informational only.

anLinkUp

Description: A logical link has transitioned from state down to state up.
Trap ID: 153
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: No impact on network or service.
Corrective Action: None, alarm is informational only.

anLinkDown

Description: A logical link has transitioned from state up to state down.
Trap ID: 154
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: No Impact on network or service.
Corrective Action: None, alarm is informational only.

anNmLoginFailure

Description: Failed login attempt
Trap ID: 155
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: No impact to the system. A remote TACACS+ user was not able to login to the system.
Corrective Action: User was probably entering incorrect username/password. If user has forgotten their username/password combination then have the administrator reset the password for the user.

anTaskOverload

Description: A task has generated an overload event.
Trap ID: 69
Status: Current
Severity: Minor, Major, Critical
Auto Clearing: Yes
Potential Impact: Not applicable.
Corrective Action: Not applicable.

anBladeOverload

Description: This blade has generated an overload event.
Trap ID: 70
Status: Current
Severity: Minor, Major, Critical
Auto Clearing: Yes
Potential Impact: A blade has crossed its configured resource thresholds (thresholds are configured for session setup rate, memory utilization, number of HTTP transactions). Potential impact is a future disruption in service unless action is takes to bring the blade out of overload.
Corrective Action: The alarm indicates what resource is in overload.
1. Memory Utilization - The blade may be running low in memory either due to a memory leak or due to the blade reaching its session capacity. If it is due to capacity, then add additional capacity to the cluster. If you suspect a memory leak, then collect the tech-support information and contact the TAC.
2. Session Setup Rate - Add additional capacity to the cluster.
3. Http Transactions - Add additional capacity to the cluster.

anSystemOverload

Description: This system has generated an overload event
Trap ID: 71
Status: Obsolete
Severity: Not Applicable
Auto Clearing: Yes
Potential Impact: Not Applicable
Corrective Action: Not Applicable

anGtpPeerDown

Description: GTP peer down. This indicates that the remote GTP peer is not responding to any GTP messages sent to it. If the peer is statically provisioned, the severity is Major. If the peer is dynamic, the severity is Info.
Trap ID: 60
Status: Current
Severity: Info, Major
Auto Clearing: No
Potential Impact: Sessions that go to the remote peer may be cleared, resulting in loss of data connectivity for the affect UEs.
Corrective Action: Verify that the remote peer is up and running. Verify that the remote peer is reachable. Verify that the local GTP endpoint is correctly provisioned and running normally.

anCantPageSubscriberOutOfBuffers

Description: FP ran out of paging buffers
Trap ID: 73
Status: Deprecated
Severity:
Auto Clearing: Yes
Potential Impact:
Corrective Action:

anDiameterPeerLinkDown

Description: Transport connection to the diameter peer is down.

Trap ID: 89

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: The Diameter Links are Down towards the neighbour peer. This might result in various Diameter based interfaces unavailability. Specifics of the interface are dependant on the configuration.

Corrective Action: The alarm clears when the interface becomes active. Check the routing/connectivity towards the Diameter peer. The alarm clears after the connectivity is restored. Once you have restored the IP connectivity make sure the Diameter Peer is up and routes are correctly configured and Diameter configuration is correct.

anDiameterPeerLinkUp

Description: Diameter Peer Transport Connection Up Event

Trap ID: 90

Status: Deprecated

Severity:

Auto Clearing: No

Potential Impact:

Corrective Action:

anRadiusPeerDown

Description: The RADIUS peer health check failed and this RADIUS peer is declared down.

Trap ID: 91

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: If this RADIUS peer is configured for authentication and there is no alternate operationally Up RADIUS peer, then the new session setups fail. If this RADIUS peer is used for accounting and if there is no alternate operationally Up RADIUS peer and if is-ofc-enabled is enabled on Accounting Service, then the accounting records are stored in the AN3000 and auto played after one of the RADIUS peers recovers.

Corrective Action: Check the routing/connectivity towards the RADIUS peer. The alarm clears after connectivity is restored.

anRadiusPeerUp

Description: Radius Peer Up Event
Trap ID: 92
Status: Deprecated
Severity:
Auto Clearing: No
Potential Impact:
Corrective Action:

anGtppPeerDown

Description: The Transport connection to Gtpp peer is down.
Trap ID: 93
Status: Current
Severity: Major
Auto Clearing: No
Potential Impact: This might result in Ga Interface not able to send the Call Data Records to Billing system via the CGF| mediation function.
Corrective Action: Check the routing/connectivity towards the GTP peer. The alarm clears after the connection is restored. Once you have restored the IP connectivity make sure the Gtpp Peer is up and routes are correctly configured and GTPP configuration is correct.

anGtppPeerUp

Description: Gtpp Peer Up Event
Trap ID: 94
Status: Deprecated
Severity:
Auto Clearing: No
Potential Impact:
Corrective Action:

anPdnSessionAntiSpoofing

Description: The UE sent an IP packet with an unassigned source address.
Trap ID: 98
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: AN3000 performance may be impacted.
Corrective Action: If this is unexpected behavior, clear the subscriber through CLI.

anSgwServiceUp

Description: A SGW service is operationally up.
Trap ID: 99
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: None.
Corrective Action: None.

anSgwServiceDown

Description: A SGW service is operationally down.
Trap ID: 100
Status: Current
Severity: Critical
Auto Clearing: No
Potential Impact: Subscribers are no longer served by this SGW service.
Corrective Action: Verify that the admin state of this SGW service is enabled.

anPgwServiceUp

Description: A PGW service is operationally up.
Trap ID: 101
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: None.
Corrective Action: None.

anPgwServiceDown

Description: A PGW service is operationally down.
Trap ID: 102
Status: Current
Severity: Critical
Auto Clearing: No
Potential Impact: Subscribers are no longer served by this PGW service.
Corrective Action: Verify that the admin state of this PGW service is enabled.

anGgsnServiceUp

Description: A GGSN service is operationally up.
Trap ID: 103
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: None.
Corrective Action: None.

anGgsnServiceDown

Description: A GGSN service is operationally down.
Trap ID: 104
Status: Current
Severity: Minor
Auto Clearing: No
Potential Impact: Subscribers are no more served by this GGSN service.
Corrective Action: Verify the admin-state of this GGSN service is enabled.

anApnAvailable

Description: An APN is available for use by a specific GW service.
Trap ID: 105
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: No impact to the network.
Corrective Action: None

anApnNotAvailable

Description: An APN is not available for use by a specific GW service.
Trap ID: 106
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: Subscribers using this APN cannot be connected to the network.
Corrective Action: Verify that the admin state of this APN is enabled.

anCaleaPeerLinkDown

Description: The alarm is generated when the transport connection to the CALEA peer is down. It is cleared when connectivity to the CALEA peer is restored.

Trap ID: 140

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: If the link to the CALEA peer is down, it can lead to packets being sent over the link to be rerouted over other links, buffered or lost.

Corrective Action: Ensure that connectivity to the peer is restored. Loss of connectivity could be due to network issues, problems on the peer side etc.

anCaleaPeerLinkUp

Description: Indicates when the transport connection to the CALEA peer comes up. It is deprecated and will be removed in future releases, as the anCaleaPeerLinkDown alarm delivers all link status change notifications. It is not used by the existing code.

Trap ID: 141

Status: Deprecated

Severity: Major

Auto Clearing: No

Potential Impact: This alarm is no longer used.

Corrective Action: This alarm is no longer used.

anGtpPeerUp

Description: GTP Peer Up Event

Trap ID: 143

Status: Deprecated

Severity:

Auto Clearing: No

Potential Impact:

Corrective Action:

anCaleaTargetsCleared

Description: The trap is generated when all CALEA targets have been removed and the size of the CALEA target data base becomes zero. It is an informational trap and therefore never cleared.

Trap ID: 162

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: None; this just indicates that there are no CALEA targets configured.

Corrective Action: None needed.

anCaleaInterfacesCleared

Description: This alarm is generated when all Legal Intercept Mediation device Interfaces have been deleted. It is an informational alarm and is never cleared.

Trap ID: 163

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: None; this just indicates that all configured CALEA interfaces have been removed.

Corrective Action: None needed.

anCaleaUtilizationLow

Description: The alarm is generated when the Configured Legal Intercept Targets Utilization is greater than 60% and less than 70% of the maximum capacity. It is cleared when the utilization becomes less than or equal to 60%.

Trap ID: 164

Status: Current

Severity: Minor

Auto Clearing: Yes

Potential Impact: This indicates that the CALEA target database is at least 60% full and if targets continue to be added, corrective action may be needed.

Corrective Action: None needed.

anCaleaUtilizationMedium

Description: This Alarm is generated when Configured Legal Intercept Targets are above 70% but below 80% of maximum allowed configurable targets. It is cleared when the utilization is less than or equal to 70%.

Trap ID: 165

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: If additional targets continue to be added, it is possible that the maximum allowed number of targets might be reached or exceeded, preventing configuration of additional targets.

Corrective Action: Delete some LI targets to bring down the utilization to acceptable levels.

anCaleaUtilizationHigh

Description: This Alarm is generated when Configured Legal Intercept Targets are above 80% but below 90% of maximum allowed targets. It is cleared when the utilization is less than or equal to 80%.

Trap ID: 166

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: If additional targets continue to be added, it is possible that the maximum allowed number of targets might be reached or exceeded, preventing configuration of additional targets.

Corrective Action: Delete some LI targets to bring down the utilization to acceptable levels.

anCaleaUtilizationCritical

Description: This Alarm is generated when Configured Legal Intercept Targets are above 90% but below 100% of maximum allowed targets. It is cleared when the utilization is less than or equal to 90%.

Trap ID: 167

Status: Current

Severity: Critical

Auto Clearing: Yes

Potential Impact: If additional targets continue to be added, it is possible that the maximum allowed number of targets might be reached or exceeded, preventing configuration of additional targets.

Corrective Action: Delete some LI targets to bring down the utilization to acceptable levels.

anCaleaCCBufferConfiguredSizeBelowThreshold

Description: The alarm is generated when the configured size for the CC buffer on the interface group is less than the minimum threshold value (10MB).

Trap ID: 189

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: If the size of the CC buffer on the interface group is too small, this can lead to packets getting lost when connectivity is lost and packets are being buffered.

Corrective Action: A larger value for the CC buffer size should be configured.

anCaleaCCBufferUtilizationThresholdReached

Description: This alarm is generated when the buffer utilization threshold is reached for the CC buffer on the interface group.

Trap ID: 190

Status: Current

Severity: Critical

Auto Clearing: No

Potential Impact: If the CALEA CC buffer utilization continues to grow, it could cause the buffer to fill up completely and potentially overflow, leading to loss of data from the buffer.

Corrective Action: Ensure that connectivity is restored, which would cause the packets stored in the buffer to be sent out on the available CALEA interfaces that are part of this interface group.

anCaleaIRIBufferUtilizationThresholdReached

Description: This alarm is generated when the buffer utilization threshold is reached for the IRI buffer on the interface group.

Trap ID: 191

Status: Current

Severity: Critical

Auto Clearing: No

Potential Impact: If the CALEA IRI buffer utilization continues to grow, it could cause the buffer to fill up completely and potentially overflow, leading to loss of data from the buffer.

Corrective Action: Ensure that connectivity is restored, which would cause the packets stored in the buffer to be sent out on the available CALEA interfaces that are part of this interface group.

anCaleaTargetDBMaxSubsLimitReached

Description: The alarm is generated when the number of entries in the target DB reaches the maximum allowed value of 32,768.

Trap ID: 192

Status: Current

Severity: Critical

Auto Clearing: No

Potential Impact: Any attempts to add LI targets after this target will fail as the limit for the maximum number of allowed subscribers has been reached.

Corrective Action: Delete some targets to ensure that additional targets can be configured. The alarm will be cleared when the count goes down to 99% of the maximum allowed targets.

anCaleaIRIBufferConfiguredSizeBelowThreshold

Description: The alarm is generated when the configured size for the IRI buffer on the interface group is less than the minimum threshold value (1 MB).

Trap ID: 193

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: If the size of the IRI buffer on the interface group is too small, this can lead to packets getting lost when connectivity is lost and packets are being buffered.

Corrective Action: A larger value for the IRI buffer size should be configured.

anCaleaIfOrIfGroupConfigChange

Description: The alarm is raised when the configuration for a CALEA interface/interface group is modified in any way (added, changed or deleted).

Trap ID: 194

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: None; configuration changes will be applied.

Corrective Action: None needed.

anCaleaLITargetCreatedOrDeleted

Description: The alarm is generated whenever a CALEA Lawful Intercept target is created or deleted.

Trap ID: 195

Status: Current

Severity: Minor

Auto Clearing: No

Potential Impact: No adverse impact.

Corrective Action: None needed.

anCaleaInterfaceGroupStatusDown

Description: The alarm is generated whenever the interface group status changes from up to down. It is cleared when the status changes back to up.

Trap ID: 196

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: If this is a primary group and no secondary group is configured, this may lead to packets being buffered, and eventually being lost if the buffer size is exceeded.

Corrective Action: Restore connectivity to the CALEA server so that data can be sent via some interfaces in the group and group status changes to up again.

anCaleaCCBufferDataLost

Description: The alarm is generated whenever CC buffer data is lost because the buffer size was exceeded and inserting additional data in the buffer caused earlier packets to be lost.

Trap ID: 197

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Buffered data is lost, so not all data will be sent to the remote server.

Corrective Action: Increase the CC buffer size or flush the buffers by restoring connectivity to CALEA server.

anCalealRIBufferDataLost

Description: The alarm is generated whenever IRI buffer data is lost because the buffer size was exceeded and inserting additional data in the buffer caused earlier packets to be lost.

Trap ID: 198

Status: Current

Severity: Minor

Auto Clearing: No

Potential Impact: Buffered data is lost, so not all data will be sent to the remote server.

Corrective Action: Increase the IRI buffer size or flush the buffers by restoring connectivity to CALEA server.

anEmergencyCallAttemptFailed

Description: This alarm is generated when the system fails to setup emergency bearers for a session due to reasons such as lack of resources or memory or other call processing errors.

Trap ID: 214

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Emergency Call failed to be setup successfully.

Corrective Action: Determine cause of failure using logs and procedure stats and take corrective action on the system accordingly.

anEmergencyCallDropped

Description: This alarm is generated when active emergency bearers are deactivated due to operator intervention such as deactivation initiated through CLI.

Trap ID: 215

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Active emergency call was deactivated due to operator intervention.

Corrective Action: Operator initiated deactivation of emergency sessions must be performed only if necessary.

anWagServiceDown

Description: A WAG service is operationally down.
Trap ID: 220
Status: Current
Severity: Minor
Auto Clearing: No
Potential Impact: Subscribers are no longer served by this WAG service.
Corrective Action: Verify that the admin state of this WAG service is enabled.

anWagServiceUp

Description: A WAG service is operationally up.
Trap ID: 221
Status: Current
Severity: Info
Auto Clearing: Yes
Potential Impact: None.
Corrective Action: None.

anEpdgServiceUp

Description: An ePDG service is operationally up.
Trap ID: 230
Status: Current
Severity:
Auto Clearing: Yes
Potential Impact: None.
Corrective Action: None.

anEpdgServiceDown

Description: An ePDG service is operationally down.
Trap ID: 231
Status: Current
Severity:
Auto Clearing: No
Potential Impact: Subscribers are no longer served by this ePDG service.
Corrective Action: Verify that the admin state of this ePDG service is enabled.

anGwSubsGrpFileNotFound

Description: File containing Subscriber IDs configured for the subscriber-group does not exist on the MCC.

Trap ID: 296

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Subscriber Group is not updated with the subscriber IDs listed in the file. Services configured for the subscriber-group like the rate-limiting-subscriber-group will not be configured for the subscribers in the file.

Corrective Action: Load the required file from the EMS to the MCC

anCaleaUserBanFeatureConfigChange

Description: This alarm is generated when admin state of Calea User Ban Feature is changed

Trap ID: 299

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact:

Corrective Action:

anCaleaCCDataLost

Description: The alarm is generated when CC data is first lost on an interface which is down (and no interface-group is provisioned for target)

Trap ID: 300

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: CC data is lost, so not all data will be sent to the remote server.

Corrective Action: Use persistent targets associated with calea interface-groups. Interface-groups provide buffering when interfaces are down/congested

anCaleaIRIDataLost

Description: The alarm is generated when IRI data is first lost on an interface which is down (and no interface-group is provisioned for target)

Trap ID: 301

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: IRI data is lost, so not all data will be sent to the remote server.

Corrective Action: Use persistent targets associated with calea interface-groups. Interface-groups provide buffering when interfaces are down/congested.

anPfcPPeerDown

Description: PFCP Peer down indicates that the remote PFCP Peer is not responding to any of the PFCP messages sent to it.

Trap ID: 321

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: Sessions that goto the remote pfcP peer may be cleared, resulting in loss of data connectivity for the affected UEs.

Corrective Action: Verify that the remote peer is up, running and reachable. Make sure that the local PFCP Endpoint is provisioned correctly and running normally.

anPfcPPeerUp

Description: PFCP Peer is up, running and reachable.

Trap ID: 322

Status: Deprecated

Severity:

Auto Clearing: No

Potential Impact: `

Corrective Action: `

anCalealfGrpSourceProfileConfigChange

Description: The alarm is raised when the configuration for a CALEA interface-group-source-profile is modified in any way (added, changed or deleted).

Trap ID: 323

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: None; configuration changes will be applied.

Corrective Action: None needed

anCalealfGrpSourceProfileNotFound

Description: The alarm is raised when the CALEA subsystem is unable to find an interface-group-source-profile for a dynamic target interface/group.

Trap ID: 324

Status: Current

Severity: Critical

Auto Clearing: No

Potential Impact: TCP connection to LEMF will not be established;
Intercepted data for dynamic target will not be reported to LEMF

Corrective Action: CALEA ADMF must configure the appropriate calea interface-group-source-profile

anCaleaPdhirNotSupportedForSx3lifTunnelToCPF

Description: This alarm is generated to indicate control plane will not deliver PDHIR events when CALEA target config is having PDHIR enabled in SX3LIF mode

Trap ID: 342

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Control plane does not deliver the PDHIR events.

Corrective Action: remove Sx3lif config

anCaleaDecryptFail

Description: The alarm is generated when encrypted CALEA Lawful Intercept data can not be decrypted (could be security key mismatch between CPF and UPF)

Trap ID: 343

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: Session/bearer data not intercepted for subscriber which has been targeted by Lawful Intercept

Corrective Action: Configure exact same encryption keys and pfcplawful-intercept-ie encryption settings on both CPF and UPF

fmSWCompMCMSwitchoverEventData

Description: An MCM switchover has taken place.

Trap ID: 19

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: No impact to service.

Corrective Action: MCM switchover may occur due to an application or kernel fault on the active MCM. Capture tech-support information and contact the TAC.

anRedundancyOperState

Description: Indicates whether MCM redundancy is operational. When the standby boots it has 10 minutes to establish redundancy before raising this alarm. If a standby task fails, the system gives 3 minutes to re-established redundancy before raising this alarm.

Trap ID: 107

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: Redundancy is not operational and therefore if active MCM faults, it causes the entire cluster service to go down.

Corrective Action: If a redundant MCM is not added to the system, add one immediately. If redundant MCM exists, replace the card.

anCpuTosTaskState

Description: Indicates whether all tos tasks are operationally UP on this CPU. After a card is booted all tasks have 10 minutes to come up before an alarm is issued. If a task goes down, the system gives 3 minutes for the task to come up before issuing this alarm.

Trap ID: 108

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: One or more service(s) may be operational down.

Corrective Action: Collect the tech-support information and contact the TAC.

anNewCoreFileDetected

Description: A new core file is detected on the chassis.

Trap ID: 111

Status: Deprecated

Severity: Minor

Auto Clearing: Yes

Potential Impact: One or more service may have been affected.

Corrective Action: Collect the tech-support information and contact the TAC.

anfileftpfailure

Description: Last try to ftp files to remote server failed.

Trap ID: 112

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: Files could not be ftped to remote server and are accumulating on local disk. If this continues, the local disk may come close to being full and the system will start purging files locally.

Corrective Action: For the different ftp file transfers configured on the system, make sure proper server information (username, password, ip address and port) is configured. Also verify that the AN3000 can reach the configured ip/port and the remote server has an sftp server running and it is able to accept incoming connections.

anForcedSyncStart

Description: Forced sync of images from active to standby.
Trap ID: 125
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Standby is syncing its image with active, therefore there is no MCM redundancy.
Corrective Action: The sync should complete in 30 minutes and the alarm should clear automatically. If the alarm persists for longer than 30 minutes, collect the tech-support information and contact the TAC.

anForcedSyncFailed

Description: Forced sync failed or timed-out.
Trap ID: 126
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: Standby is out of sync with the active MCM, therefore there is no MCM redundancy.
Corrective Action: Install the released image on the standby MCM using the mcm install feature.

anPortStatusUp

Description: Port Status is UP
Trap ID: 127
Status: Deprecated
Severity: Not Applicable
Auto Clearing: No
Potential Impact: Not Applicable
Corrective Action: Not Applicable

anfilepurgedduetodiskfull

Description: Files have been purged from disk since disk purge threshold was crossed (disk was getting close to full).

Trap ID: 130

Status: Current

Severity: Critical, Major

Auto Clearing: No

Potential Impact: When disk is close to full, we start deleting files from the disk. It will delete oldest files first. Impact is that files like faultfiles, tech support files, log files, etc. may get deleted and hence debugging information may be lost. CDR files and Performance Stat files can also be deleted causing loss of valuable operating information.

Corrective Action: Operator should monitor their disk usage and archive files off the box. Especially files consuming lot of disk space (like fault files, tech support files) should be moved off the MCM to free up disk on the MCM.

anKernelOptionsModified

Description: Kernel options have been automatically modified on the current module. They will take effect on the reboot.

Trap ID: 135

Status: Current

Severity: Info

Auto Clearing: Yes

Potential Impact: System may be performing at sub-optimal levels.

Corrective Action: Reboot the node/card for new kernel options to take effect.

anFormatDisk

Description: Disk format operation took place.

Trap ID: 138

Status: Deprecated

Severity: Not Applicable

Auto Clearing: Yes

Potential Impact: Not Applicable

Corrective Action: Not Applicable

anDiskFull

Description: Disk full
Trap ID: 139
Status: Obsolete
Severity: Not Applicable
Auto Clearing: Yes
Potential Impact: Not Applicable
Corrective Action: Not Applicable

anUEPoolThresholdAlarm

Description: This alarm is generated when the configured threshold for UE pool utilization is crossed.
Trap ID: 146
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: If the system continues to remain in this state, the UE pools may run out of IPS resulting in session setup failures.
Corrective Action: Increase the capacity of the available IPS by increasing the range of the existing pools or adding new pools in the same network-context.

anDataRecordFailure

Description: The system failed to log a data record (i.e. local CDR, HTDR or other such data records). This failure can occur either at the source generating the data record or at the agent which is responsible for flush the data record to the disk.
Trap ID: 205
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: Data Record generation failed, hence important information captured by the data records would be missed.
Corrective Action: Data Record generation would generally fail is no space is left on disk to write the records. So first check the disk space on the controller card (MCM). If disk is full then clean up some unwanted files from the disk and see if you start getting records again. If disk is not full, then capture save-tech-support and contact higher level support.

anRemoteMountFailed

Description: This alarm is raised when a node cannot reach over the nfs mount to the disk on peer MCM. For active MCM, the peer MCM is the standby MCM. For all nodes, the peer MCM is the active MCM.

Trap ID: 211

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: Nodes do not have access to the nfs disk that resides on peer MCM. As a result certain functionalities (like fault files, packet capture) may not work.

Corrective Action: Please contact higher level support to investigate this issue. Rebooting the node for which this alarm is raised may help resolve the situation.

anEdrServerConnectionFailed

Description: The connection to the EDR server has failed.

Trap ID: 222

Status: Current

Severity: Major,Critical

Auto Clearing: Yes

Potential Impact: EDR records cannot be sent to this EDR server.

Corrective Action: Check if the EDR server is running, and verify network connectivity to it.

anPkix509expiring

Description: An X509 certificate is approaching expiration

Trap ID: 232

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: An X509 certificate is approaching its expiration

Corrective Action: Update the X509 certificate with a newer version before it expires or remove it if it is unused

anPkix509expired

Description: An X509 certificate has expired
Trap ID: 233
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: An X509 certificate has expired and should no longer be used
Corrective Action: Replace with an unexpired certificate or remove if unused

anPkix509revoked

Description: An X509 certificate has been revoked
Trap ID: 234
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: An X509 certificate has been reported as revoked and should no longer be used
Corrective Action: Replace with a valid certificate or remove if unused

anPkiobjunreachable

Description: Attempts to update a pki object from a remote source have failed for more than 24 hours
Trap ID: 235
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The update of this pki certificate or key is failing to occur in a timely manner
Corrective Action: Determine why the remote source is unreachable or install from a new source

anPkiobjadded

Description: A new pki object has been added to the system
Trap ID: 236
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: New pki certificate or key available for use
Corrective Action: None required - informational trap only

anPkiobjupdated

Description: An existing pki object has been updated
Trap ID: 237
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: A pki certificate or key has been replaced so clients may wish to reload it
Corrective Action: A pki certificate or key has been replaced so clients may wish to reload it

anPkiobjremoved

Description: A pki object has been removed from the system
Trap ID: 238
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: A pki certificate or key is no longer available for use
Corrective Action: Re-add the object if its removal was not intended

anPkix509crlnextupdateavailable

Description: The next update of this x509 certificate revocation list is available
Trap ID: 240
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: Recently reported revocation of x509 certificates depends on getting the latest x509 certificate revocation list when it becomes available.
Corrective Action: If the cluster is not able to automatically load the latest version of the named x509 certificate revocation list then please install it manually with pki install

anReleaseMismatch

Description: one or more nodes are running a different tos release than they are intended to be running and neither an upgrade nor a rollback is in progress.

Trap ID: 244

Status: Current

Severity: Major

Auto Clearing: Yes

Potential Impact: The nodes on the other release may not support the full functionality of the intended release

Corrective Action: cli command - cluster <nnn> graceful-restart
reason release-mismatch - will restart the reporting nodes to the correct release

anPkioobjupdatenotavailable

Description: Attempts to get an updated version of a pki object from a remote source have failed for more than 24 hours

Trap ID: 248

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The update of this pki certificate or key is failing to occur in a timely manner

Corrective Action: Determine why an updated version of this object is not available from the remote source or install from a new source that has an updated version of this object

anPkisshauthorizedkeyaddedtouser

Description: An ssh public key has been configured to authenticate ssh for a user

Trap ID: 249

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The private key that matches this public key can now provide ssh authentication for a user

Corrective Action: None required - Informational

anPkisshauthorizedkeyremovedfromuser

Description: An ssh public key has been removed from those that may authenticate ssh for a user
Trap ID: 250
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The private key that matches this public key can no longer be used to provide ssh authentication for a user
Corrective Action: None required - Informational

anPkisshauthorizedkeyaddedtogroup

Description: An ssh public key has been configured to authenticate ssh for all users in a group
Trap ID: 251
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The private key that matches this public key can now provide ssh authentication for all users in a group
Corrective Action: None required - Informational

anPkisshauthorizedkeyremovedfromgroup

Description: An ssh public key has been removed from those that may authenticate ssh for all users in a group
Trap ID: 252
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The private key that matches this public key can no longer be used to provide ssh authentication for all users in a group
Corrective Action: None required - Informational

anPkisshtrustedcakeyaddedtocluster

Description: An ssh public key has been trusted as a certificate authority key to validate certificates used to authenticate ssh for any user in the cluster

Trap ID: 253

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The ssh certificates signed by the private key that matches this public key can now provide ssh authentication for all users in the cluster

Corrective Action: None required - Informational

anPkisshtrustedcakeyremovedfromcluster

Description: An ssh public key that had been trusted as a certificate authority key to validate certificates used to authenticate ssh for any user in the cluster has been removed

Trap ID: 254

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The ssh certificates signed by the private key that matches this public key can no longer provide ssh authentication for all users in the cluster

Corrective Action: None required - Informational

anPkisshtrustedcakeyaddedtogroup

Description: An ssh public key has been trusted as a certificate authority key to validate certificates used to authenticate ssh for all users in a group

Trap ID: 255

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The ssh certificates signed by the private key that matches this public key can now provide ssh authentication for all users in a group

Corrective Action: None required - Informational

anPkisshtrustedcakeyremovedfromgroup

Description: An ssh public key that had been trusted as a certificate authority key to validate certificates used to authenticate ssh for all users in a group has been removed

Trap ID: 256

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: The ssh certificates signed by the private key that matches this public key can no longer provide ssh authentication for all users in a group

Corrective Action: None required - Informational

anPkisshuseraddedtoauthorizedprincipals

Description: A user has been added to the group list of authorized principals

Trap ID: 257

Status: Deprecated

Severity: Info

Auto Clearing: No

Potential Impact: A user will now be able to use certificates for ssh authentication even if their name was not included in the certificate when it was created as long as another user that is an authorized principal was included in the certificate

Corrective Action: None required - Informational

anPkisshuserremovedfromauthorizedprincipals

Description: A user has been removed from the group list of authorized principals

Trap ID: 258

Status: Deprecated

Severity: Info

Auto Clearing: No

Potential Impact: A user will only be able to use certificates for ssh authentication if their name was included in the certificate when it was created

Corrective Action: None required - Informational

anPkisshgroupaddedtoauthorizedprincipals

Description: All users in a group have been added to the group list of authorized principals

Trap ID: 259

Status: Deprecated

Severity: Info

Auto Clearing: No

Potential Impact: All users in the group will now be able to use certificates for ssh authentication that included the name of any user in the group in the certificate when it was created

Corrective Action: None required - Informational

anPkisshgroupremovedfromauthorizedprincipals

Description: All users in a group have been removed from the group list of authorized principals

Trap ID: 260

Status: Deprecated

Severity: Info

Auto Clearing: No

Potential Impact: All users in a group will only be able to use certificates for ssh authentication if their name was included in the certificate when it was created

Corrective Action: None required - Informational

anfileexportfailure

Description: Last try to export files to the export directory (as per configuration) failed.

Trap ID: 261

Status: Current

Severity: Major

Auto Clearing: No

Potential Impact: Files could not be exported and hence are not available for export user. If this continues, the local disk may come close to being full and the system will start purging files locally.

Corrective Action: Check the export rules for different file-management configurations. Make sure the export-user configured for each one is valid. If all configuration looks good, then contact next level support.

anPkisshnamesaddedtogroupauthorizedprincipals

Description: One or more names have been added to a group authorized principals list

Trap ID: 262

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Certificates containing a name on a group authorized principals list and also signed by a group or cluster trusted user ca key will be able to authenticate ssh access for any user in that group on the list

Corrective Action: None required - Informational

anPkissherrorapplyingconfigurationtosshcontrolfiles

Description: An error has occurred converting pki ssh configuration to ssh authorizedkeys/authorizedprincipals/trustedusercakeys files

Trap ID: 263

Status: Current

Severity: Minor

Auto Clearing: Yes

Potential Impact: AN attempt to generate ssh control files from pki ssh configuration has failed.. It will retry..

Corrective Action: It will retry.. Examine messages from more detail and contact support if the problem persists for more than a few minutes.

anPkisshnamesremovedfromauthorizedprincipals

Description: One or more names have been removed from a user authorized principals list

Trap ID: 264

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Certificates containing a name on a user authorized principals list and also signed by a group or cluster trusted user ca key will be able to authenticate ssh access to that user

Corrective Action:

anPkisshnamesaddedtoauthorizedprincipals

Description: One or more names have been added to a user authorized principals list

Trap ID: 265

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Certificates containing a name on a user authorized principals list and also signed by a group or cluster trusted user ca key will be able to authenticate ssh access to that user

Corrective Action: None required - Informational

anPkisshnamesremovedfromgroupauthorizedprincipals

Description: One or more names have been removed from a group authorized principals list

Trap ID: 266

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: Certificates containing a name on a group authorized principals list and also signed by a group or cluster trusted user ca key will be able to authenticate ssh access for any user in that group on the list

Corrective Action: None required - Informational

anPkisshmaximumsecuritylevelset

Description: The ssh security level for the cluster has been changed to maximum

Trap ID: 267

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With the ssh security level set to maximum, keys/ciphers/MACs that are considered weak by current standards will not be supported by ssh/scp/sftp. This may cause legacy systems in the network that require them to no longer connect to the cluster.

Corrective Action: If setting ssh security level to maximum prevents communication with some legacy systems in the network, it may be desirable to revert to ssh security level compatible until those legacy systems can have their security upgraded.

anPkisshcompatiblesecuritylevelset

Description: The ssh security level for the cluster has been changed to compatible

Trap ID: 268

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With the ssh security level set to compatible, all legacy and newer keys/ciphers/MACs are supported by ssh/scp/sftp, even some considered weak by current standards. To enhance network security consider switching to security level maximum if the legacy systems in the network have the necessary support.

Corrective Action: None required. Consider increasing ssh security level to maximum if the rest of the network can support it.

anPkisshstricthostkeycheckingsettono

Description: The ssh strict host key checking for the cluster has been changed to no

Trap ID: 269

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With strict host key checking set to no, ssh/scp/sftp from the cluster will add the host key to learned hosts, if the destination server is not already either configured as a known host or is already a learned host.

Corrective Action: Consider changing strict host key checking to yes if you wish to block connection to unexpected servers.

anPkisshstricthostkeycheckingsettoask

Description: The ssh strict host key checking for the cluster has been changed to ask

Trap ID: 270

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With strict host key checking set to ask, ssh/scp/sftp from the cluster will prompt to add the host key to learned hosts, if the destination server is not already either configured as a known host or is already a learned host.

Corrective Action: Consider either changing strict host key checking to no or yes depending on your intent.

anPkisshstricthostkeycheckingsettoyes

Description: The ssh strict host key checking for the cluster has been changed to yes

Trap ID: 271

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With strict host key checking set to yes, ssh/scp/sftp from the cluster will fail if the destination server is not already either configured as a known host or is already a learned host.

Corrective Action: If unable to reach an external server from the cluster then add their host keys using the pki ssh knownhostkey cli command.

anPkisshverifyhostkeydnssettono

Description: The ssh verify host key with dns for the cluster has been changed to no

Trap ID: 272

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With verify host key dns set to no, ssh/scp/sftp from the cluster will check host keys internally based on the setting of strict host key checking.

Corrective Action: Set verify host key dns if and only if your network has a properly configured DNSSEC server containing signed network server host keys.

anPkisshverifyhostkeydnssettoyes

Description: The ssh verify host key with dns for the cluster has been changed to yes

Trap ID: 273

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With verify host key dns set to yes, ssh/scp/sftp from the cluster will check with the management contexts configured DNSSEC server to compare the host keys registered with the host keys returned by the server ssh is connecting to. If the keys dont match the connection will fail.Note setting verify host key dns to yes force strict host key checking be yes as well.

Corrective Action: If ssh connections from the cluster to servers are failing then add the servers host keys to those registered with the configured network DNSSEC.

anPkisshverifyhostkeydnssettoask

Description: The ssh verify host key with dns for the cluster has been changed to ask

Trap ID: 274

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: With verify host key dns set to ask, ssh/scp/sftp from the cluster will check with the management contexts configured DNSSEC server to compare the host keys registered with the host keys returned by the server ssh is connecting to. If the keys dont match the user will be prompted about allowing the connection. Note setting verify host key dns to ask force strict host key checking be ask as well.

Corrective Action: Consider setting verify host key dns to be yes or no.

anPkisshknownhostcakeyremoved

Description: The ssh public key of a certificate authority has been removed from ssh_known_hosts.

Trap ID: 275

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: External servers whose host certificate was signed by this certificate authority key will no longer be recognized and treated as know hosts. (unless they also match another still existing entry)

Corrective Action: None required - Informational

anPkisshknownhostcakeyadded

Description: The ssh public key of a certificate authority has been added to ssh_known_hosts to validate the host certificates presented on connection by ssh/scp/sftp to external servers

Trap ID: 276

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: External servers whose host certificate were signed by this certificate authority key and whose server name/ip match the server argument specified will be recognized and treated as know hosts

Corrective Action: None required - Informational

anPkisshknownhostkeyremoved

Description: An ssh public key has been removed from ssh_known_hosts.
Trap ID: 277
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The external servers whose host key matched this know host key will no longer be recognized and treated as know hosts. (unless they also match another still existing entry)
Corrective Action: None required - Informational

anPkisshknownhostkeyadded

Description: An ssh public key has been added to ssh_known_hosts to validate connections by ssh/scp/sftp to external servers
Trap ID: 278
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The external servers whose host key matches this know host key and whose server name/ip match the server argument specified will be recognized and treated as know hosts
Corrective Action: None required - Informational

anPkisshlocalhostcertificatereplaced

Description: The previous local ssh host certificate has been replaced by a new ssh certificate.
Trap ID: 279
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: A new ssh certificate has replaced the previous local host certificate. External ssh/scp/sftp clients can authenticate this server if the certificate is a signed copy of this servers host key and they have the public ca key used to sign the certificate configured as a know host ca key in their known host files.
Corrective Action: None required - Informational

anPkisshlocalhostcertificateremoved

Description: The local ssh host certificate has been removed.
Trap ID: 280
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: The local host certificate has been removed. External ssh/scp/sftp clients can no longer authenticate this server with a host ca key.
Corrective Action: None required - Informational

anPkisshlocalhostcertificateadded

Description: The local ssh host certificate has been added.
Trap ID: 281
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: An ssh certificate has been added to be the local host certificate. External ssh/scp/sftp clients can authenticate this server if the certificate is a signed copy of this servers host key and they have the public ca key used to sign the certificate configured as a know host ca key in their known host files.
Corrective Action: None required - Informational

anPkisshrevoked

Description: An ssh key or certificate has been revoked by an ssh krl file
Trap ID: 282
Status: Current
Severity: Info
Auto Clearing: No
Potential Impact: An ssh key or certificate has been reported as revoked by an ssh krl file and should no longer be used
Corrective Action: Replace with a valid key or certificate or remove if unused

anPkimanuallyrevoked

Description: An ssh key or certificate has been manually reported as revoked by a revoke cli command

Trap ID: 283

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: An ssh key or certificate has been reported as revoked by a manually issued revoke cli command. This may have been done to prevent its use to authorize ssh user or host authentication

Corrective Action: If not in use to prevent user or host ssh authentication with this key then replace with a valid key or certificate or remove it

anPkisshuserkrlreplaced

Description: A new or updated pki ssh krl file has replaced the previous ssh krl as the RevokedKeys file to the sshd servers.

Trap ID: 285

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: This new or updated krl file will reject revoked ssh keys and certificates that may be offered as user authentication to the sshd servers.

Corrective Action: None required unless the replacement was unexpected.

anPkisshuserkrladded

Description: A pki ssh krl file has been added as the RevokedKeys file to the sshd servers.

Trap ID: 286

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: This krl file will reject revoked ssh keys and certificates that may be offered as user authentication to the sshd servers.

Corrective Action: None required - Informational

anPkisshuserkrlremoved

Description: The ssh krl file that was providing a list of revoked ssh keys has been removed from RevokedKeys on the sshd servers.

Trap ID: 287

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: There is no longer a list of revoked ssh keys and certificates being supplied to the sshd servers.

Corrective Action: None required unless the removal was unexpected.

anPkisshcertexpiring

Description: An ssh certificate is approaching expiration

Trap ID: 288

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: An ssh certificate is approaching its expiration

Corrective Action: Update the ssh certificate with a newer version before it expires or remove it if it is unused

anPkisshcertexpired

Description: An ssh certificate has expired

Trap ID: 289

Status: Current

Severity: Info

Auto Clearing: No

Potential Impact: An ssh certificate has expired and should no longer be used

Corrective Action: Replace with an unexpired certificate or remove if unused

anNewMemImageFileDetected

Description: A new memory image file is detected on the chassis

Trap ID: 298

Status: Deprecated

Severity: Minor

Auto Clearing: Yes

Potential Impact: One or more service may have been affected.

Corrective Action: Collect the tech-support information and contact the TAC.

anNewFaultFileDetected

Description: A new fault file has been detected on the chassis
Trap ID: 309
Status: Current
Severity:
Auto Clearing: Yes
Potential Impact: One or more services may have been impacted
Corrective Action: Collect the tech-support information and contact the TAC.

anNodeRebootRequired

Description: Node needs to be rebooted because one or more of the following have changed on the node. 1. isolcpus 2. core-layout
Trap ID: 332
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: System performance may be impacted
Corrective Action: Reboot the node

anRadiusAccountingOnMsgNotSent

Description: PGW is not accepting sessions using RADIUS towards peer Radius server due to operator configuration
Trap ID: 334
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: PGW service will not accept the calls until it sends accounting on message to radius server. this happens due to Radius-off-on-delay timer configuration.
Corrective Action: Wait till radius-acct-off-on-delay to expire

anClusterRebootRequired

Description: The cluster needs to be rebooted because one or more of the following have changed on one or more nodes in the cluster. 1. isolcpus 2. core-layout 3. max-packet-size
Trap ID: 338
Status: Current
Severity: Major
Auto Clearing: Yes
Potential Impact: System performance may be impacted.
Corrective Action: Reboot the cluster gracefully.

anThresholdCrossingAlarm

Description: A threshold has been crossed.

Trap ID: 68

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: A blade has crossed its configured resource thresholds (thresholds are configured for session setup rate, memory utilization, number of HTTP transactions). To avoid a service disruption, bring the blade out of overload.

Corrective Action: The alarm indicates what resource is in overload.1. Memory Utilization - The blade may be running low in memory either due to a memory leak or due to the blade reaching its session capacity. If it is due to capacity, add more capacity to the cluster. If you suspect a memory leak, collect the tech-support information and contact the TAC.2. Session Setup Rate - Add more capacity to the cluster.3. Http Transactions - Add more capacity to the cluster.

anLicenseCapacityEnforcement

Description: Approaching or crossed licensed service capacity enforcement level. Upon reaching X percent of the capacity enforcement level, a major event will be generated. The event will become critical as the enforcement level is crossed.

Trap ID: 223

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: This indicates the licensed service is either approaching the licensed enforcement level (major level) or has passed (critical). Service may be throttled if enforcement level has been crossed.

Corrective Action: Additional service licenses should be acquired to avoid service impact.

anLicenseCapacityLimit

Description: Approaching or crossed licensed service capacity limit. Upon reaching X percent of the capacity limit, a major event will be generated. The event will become critical as the limit is crossed.

Trap ID: 224

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: This indicates the licensed service is either approaching the licensed limit (major level) or has passed (critical). This event is informational only and not service impacting.

Corrective Action: Additional service licenses should be acquired.

anLicenseLifetimeEnforcement

Description: Approaching or passed licensed service enforcement expiration date. Upon reaching X percent of the license expiration date, a major event will be generated. The event will become critical as the expiration is passed.

Trap ID: 225

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: This indicates the licensed service is either approaching the lifetime expiration enforcement (major level) or has passed (critical). Service may be throttled if enforcement level has been crossed.

Corrective Action: Additional service licenses should be acquired to avoid service impact.

anLicenseLifetime

Description: Approaching or passed licensed service lifetime. Upon reaching X percent of the license lifetime, a major event will be generated. The event will become critical as the lifetime is passed.

Trap ID: 226

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: This indicates the licensed service is either approaching the lifetime expiration (major level) or has passed (critical). This event is informational only and not service impacting.

Corrective Action: Additional service licenses should be acquired to avoid service impact.

anLicensePlsSeparation

Description: The MCC has separated from the PLS server and enter local license management state. During this period, the MCC will manage licenses based on the last PLS view. Services will be impacted if the server is not restored within the grace period.

Trap ID: 227

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: Service will continue to run during grace period but will terminate if connection to PLS is not reestablished

Corrective Action: Reestablish connection to PLS server

anLicensePlsGraceExpired

Description: Connection to the PLS server has not reestablished within the grace period so license-able services are terminated.

Trap ID: 228

Status: Current

Severity: Minor, Major, Critical

Auto Clearing: Yes

Potential Impact: License-able services are terminating as PLS the separation grace period has expired.

Corrective Action: Reestablish connection with PLS server to restore service.

Accessing MIB Information

This chapter describes the organization of the Affirmed Management Information Base (MIB) and information on accessing and reading the MIB.

This chapter lists the following Affirmed Networks SNMP MIB traps and notifications:

- AFFIRMED-TEMS-NOTIFICATION-MIB.mib
- AFFIRMED-TEMS-OBJECT-MIB.mib
- AFFIRMED-TEMS-SNMP-MIB.mib
- AFFIRMED-TEMS-TC-MIB.mib

The MIBs are located in *opt/affirmed/NMS/server/ems/mibs*.

MIB File Format

You should have a basic understanding of the Simple Network Management Protocol (SNMP) and MIB files in order to read the MIB. The Affirmed MIB is identified by the object identifier (OID) 1.3.6.1.4.1.37963. Each object in the Affirmed MIB has a unique name.

Note: For more information on trap alarms, see [Chapter 1, Displaying Alarm Information](#).

The Affirmed MIB contains the following keywords:

Table 2-1 MIB Keywords

Keywords	Description
Object	The Affirmed MIB supports the following objects: ■ affirmedAlarmSeqId ■ affirmedAlarmDateTime ■ affirmedAlarmChassisName ■ affirmedAlarmSourceId ■ affirmedAlarmSeverity ■ affirmedAlarmRefSeqId ■ affirmedAlarmDetails ■ affirmedPotentialImpact ■ affirmedCorrectiveAction ■ affirmedVmSourceIpAddress ■ affirmedVmSourceName ■ name ■ chassis ■ slot ■ cpu ■ dirname ■ adminstate ■ resource ■ sensor ■ data ■ taskname ■ cid ■ sid ■ type ■ subtype ■ level

Table 2-1 MIB Keywords (Continued)

Keywords	Description
Object	■ time
(continued)	■ services ■ actions ■ ledname ■ ledcolor ■ usid ■ hardorsoft ■ readerrors ■ writeerrors ■ slotnumber ■ faileddescription ■ suggestedrecovery ■ netcontext ■ info ■ nodename ■ realmname ■ localhostidentity ■ peerrealmname ■ peerhostidentity ■ peername ■ clientid ■ servicename ■ apnname ■ imsi ■ statestring ■ filepath ■ ip ■ port ■ chassisid ■ slotid ■ cpuid ■ prefix ■ numpurged ■ node ■ diskid ■ interfacename ■ threshold ■ uepoolutilization ■ ipversiontype

Table 2-1 MIB Keywords (Continued)

Keywords	Description
Object	■ ifindex
(continued)	■ ifadminstatus ■ ifoperstatus ■ netctxname ■ peeringname ■ localpeeripaddr ■ remotepeeripaddr ■ lasterrorcode ■ lasterroscode ■ currentstate ■ role ■ groupname ■ operation ■ state ■ status ■ activesize ■ standbysize ■ mcmslotnumber ■ requiredsize ■ availablesize ■ reason ■ importnum ■ resultstr ■ datetime ■ fault ■ action ■ unused ■ clusterid ■ nodeid ■ subgroupname ■ subsidfilename ■ alarmid ■ xpath ■ ifname ■ sessionthreshold ■ sessionutilization ■ ipaddressthreshold ■ ipaddressutilization ■ portchunkthreshold

Table 2-1 MIB Keywords (Continued)

Keywords	Description
Object (continued)	■ portchunkutilization ■ parent ■ destination ■ peeripaddress ■ gatewayname ■ gatewayipaddress ■ bfdsessiondescription ■ cafilename ■ expirydate ■ index
Status	Current, deprecated, or obsolete
Description	A text definition that describes the object.
::	The objects trap identifier.

AFFIRMED-SNMP-AN3000-TRAPS-MIB DEFINITIONS ::= BEGIN

```
IMPORTS
    MODULE-IDENTITY,
    OBJECT-TYPE,
    Integer32,
    NOTIFICATION-TYPE
        FROM SNMPv2-SMI
    DisplayString
        FROM SNMPv2-TC
    affirmedSnmplib
        FROM AFFIRMED-SNMP-MIB
    affirmedSnmplib
        FROM AFFIRMED-SNMP-MIB
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName,
    name,
    chassis,
    slot,
    cpu,
    dirname,
    adminstate,
    resource,
    sensor,
    data,
    taskname,
    cid,
    sid,
    type,
    subtype,
    level,
    time,
    services,
    actions,
    ledname,
    ledcolor,
    usid,
    hardorsoft,
```


readerrors,
writeerrors,
slotnumber,
failuredescription,
suggestedrecovery,
netcontext,
info,
nodename,
realmname,
localhostidentity,
peerrealmname,
peerhostidentity,
peername,
clientid,
servicename,
apnname,
imsi,
statestring,
filepath,
ip,
port,
chassisid,
slotid,
cpuid,
prefix,
numpurged,
node,
diskid,
interfacename,
threshold,
uepoolutilization,
ipversiontype,
ifindex,
ifadminstatus,
ifoperstatus,
netctxtname,
peeringname,
localpeeripaddr,
remotepeeripaddr,
lasterrorcode,
lasterrorsubcode,
currentstate,
role,

```
groupname,  
operation,  
state,  
status,  
activesize,  
standbysize,  
mcmslotnumber,  
requiredsize,  
availablesize,  
reason,  
importnum,  
resultstr,  
datetime,  
fault,  
action,  
unused,  
clusterid,  
nodeid,  
subsgroupname,  
subsidfilename,  
alarmid,  
xpath,  
ifname,  
sessionthreshold,  
sessionutilization,  
ipaddressthreshold,  
ipaddressutilization,  
portchunkthreshold,  
portchunkutilization,  
parent,  
destination,  
peeripaddress,  
gatewayname,  
gatewayipaddress,  
bfdsessiondescription,  
cafilename,  
expirydate,  
index
```

FROM AFFIRMED-ALARM-MIB;

affirmedSnmAn3000Traps MODULE-IDENTITY

```

LAST-UPDATED "201105160000Z"
ORGANIZATION
    "Affirmed Networks, Inc."
CONTACT-INFO
    "Affirmed Networks, Inc.
      35 Nagog Park
      Acton, MA
      USA "
DESCRIPTION
    "Traps MIB objects"
    ::= { affirmedSnmNotifications 4}
-- top level structure
--
affirmedSnmAn3000TrapsScalars      OBJECT IDENTIFIER ::= {
affirmedSnmAn3000Traps 1 }
affirmedSnmAn3000TrapsTables      OBJECT IDENTIFIER ::= {
affirmedSnmAn3000Traps 2 }
affirmedSnmAn3000TrapsNotifications OBJECT IDENTIFIER ::= {
affirmedSnmAn3000Traps 3 }
affirmedSnmAn3000TrapsNotificationPrefix OBJECT IDENTIFIER
                                ::= {
affirmedSnmAn3000TrapsNotifications 0 }
affirmedSnmAn3000TrapsNotificationObjects OBJECT IDENTIFIER
                                ::= {
affirmedSnmAn3000TrapsNotifications 1 }

```

fmCntnFilterCategoryFileTooBig NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF category failed as file is too large."
::= { affirmedSnmAn3000TrapsNotificationPrefix 39}
```

fmCntnFilterCategoryFileNotFound NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF category failed as file does not exist on NE."
::= { affirmedSnmAn3000TrapsNotificationPrefix 40}
```

fmCntnFilterCategoryFileOverflow NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF category failed as exceeded max supported filter entries per
filter database size."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 41}

```

fmCntnFilterBlacklistFileOverflow NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF blacklist failed as exceeded max supported filter entries
per filter database size."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 42}

```

fmCntnFilterBlacklistFileTooBig NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF blacklist failed as file is too large."
::= { affirmedSnmAn3000TrapsNotificationPrefix 44}
```

fmCntnFilterBlacklistFileNotFound NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF blacklist failed as file does not exist on NE."
::= { affirmedSnmAn3000TrapsNotificationPrefix 45}
```

fmCntnFilterCategoryFileInvalidEntry NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF category got error as file has invalid entry."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 47}

```

fmCntnFilterBlacklistFileInvalidEntry NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF blacklist got error as file has invalid entry."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 48}

```

fmCntnHttpProxyServerConnectFail NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS obsolete
DESCRIPTION
"http-proxy failed to connect server."
::= { affirmedSnmAn3000TrapsNotificationPrefix 49}
```

anCntnFilterWhitelistFileInvalidEntry NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF whitelist got error as file has invalid entry."
::= { affirmedSnmAn3000TrapsNotificationPrefix 56}
```


anCntnFilterWhitelistFileOverflow NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF whitelist failed as exceeded max supported filter entries
per filter database size."
::= { affirmedSnmAn3000TrapsNotificationPrefix 57}

```

anCntnFilterWhitelistFileTooBig NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF whitelist failed as file is too large."
::= { affirmedSnmAn3000TrapsNotificationPrefix 58}

```

anCntnFilterWhitelistFileNotFound NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding CF whitelist failed as file does not exist on NE."
::= { affirmedSnmAn3000TrapsNotificationPrefix 59}
```

anCacheDiskOperationalStateAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Monitor the cache SSD operational state."
::= { affirmedSnmAn3000TrapsNotificationPrefix 61}
```

anCntnUrlListFileInvalidEntry NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding urlList got error as file has invalid entry."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 62}

```

anCntnUrlListFileOverflow NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding UrlList failed as exceeded max supported filter entries per
filter database size."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 63}

```

anCntnUrlListFileNotFound NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding urlList failed as file does not exist on NE."
::= { affirmedSnmAn3000TrapsNotificationPrefix 64}
```

anCntnUrlListFileTooBig NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding urlList failed as file is too big."
::= { affirmedSnmAn3000TrapsNotificationPrefix 65}
```

anPlaFileDownloadFail NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Policy lists agent failed to download a policy file from external
server."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 67}

```

anCacheDiskErrorStateAlarm NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    readerrors,
    writeerrors,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Monitor the Cache SSD read/write error state."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 79}

```

anLDAPServerConnectFail NOTIFICATION-TYPE

```
OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    name,
    netcontext,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Failed to connect LDAP server."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 81}
```

anLDAPServerConnectLost NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    name,
    netcontext,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"LDAP server connection lost."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 82}

```

anLDAPProfNoServerConnected NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"LDAP profile does not have a connection to remote server."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 83}

```

anCntnUaProfDefaultAttsMissing NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Missing required attributes in the default UA profile."
::= { affirmedSnmpan3000TrapsNotificationPrefix 86}
```

anSMSCServerConnectFail NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Failed to connect to SMSC server."
::= { affirmedSnmpan3000TrapsNotificationPrefix 95}
```


anSMSCProfNotFound NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"SMSC profile not found."
::= { affirmedSnmAn3000TrapsNotificationPrefix 96}

```

anSMSCServerConnectLost NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"SMSC server connection lost."
::= { affirmedSnmAn3000TrapsNotificationPrefix 97}

```

anCntnUaProfFileInvalid NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding UA profile file failed due to invalid profile file."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 109}
```

anSpsServerConnectFail NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Failed to connect to SPS server."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 131}
```

anSpsServerConnectLost NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    info,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS obsolete
DESCRIPTION
"SPS server connection lost."
 ::= { affirmedSnmAn3000TrapsNotificationPrefix 132}

```

anCntnOnlineCatDBInstallationFailure NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    importnum,
    resultstr,
    slotid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Online Categorization Database Installation Failed"
 ::= { affirmedSnmAn3000TrapsNotificationPrefix 218}

```

anCntnFilterHashListFileInvalidEntry NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding filterHashList got error as file has invalid entry."
::= { affirmedSnmAn3000TrapsNotificationPrefix 291}
```

anCntnFilterHashListFileNotFound NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding filterHashList failed as file does not exist on NE."
::= { affirmedSnmAn3000TrapsNotificationPrefix 292}
```

anCntnFilterHashListFileOverflow NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding FilterHashList failed as exceeded max supported filter entries
per filter database size."
::= { affirmedSnmAn3000TrapsNotificationPrefix 293}

```

anCntnFilterHashListFileTooBig NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Adding filterHashList failed as file is too big."
::= { affirmedSnmAn3000TrapsNotificationPrefix 294}

```

anCntnHealthCheckStateDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    destination,
    parent,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The service monitored by content health check is not reachable."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 320}
```

anCntnCACertExpired NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cafilename,
    expirydate,
    index,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"One or multiple CA (Certificate Authority) certificates have
expired."
::= { affirmedSnmAn3000TrapsNotificationPrefix 335}

```

fmHmCacheOperStateDown NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"CSM cache operationally down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 28}

```

anTemperatureAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"HW sensor raising temperature alarm."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 29}
```


anVoltageAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"HW sensor raising voltage alarm."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 30}
```

anHotSwapAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"HW sensor raising hot swap alarm."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 31}
```

anTelcoAlarm NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"HW Sensor Raising Telco Alarm"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 32}

```

anWatchdogAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"HW Sensor Raising Watchdog Alarm"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 33}
```

anFanAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"HW Sensor Raising Fan Alarm"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 34}
```

anAirFilterAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"HW sensor raising air filter alarm."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 35}
```

anTachAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"HW sensor raising tach alarm.."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 36}
```

anHWAlarm NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    data,
    resource,
    sensor,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"HW sensor raising hardware alarm."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 37}
```

anCardNotBootingUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Card is plugged in but not operational"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 46}
```


anLedStateChange NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ledcolor,
    ledname,
    resource,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"LED state change."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 74}
```

anRebootEvent NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    hardorsoft,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Module rebooted."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 78}
```

anPayloadFailure NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    faileddescription,
    slotnumber,
    suggestedrecovery,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The specified payload has experienced a hardware or firmware
failure."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 80}
```

anFmSlotFrequentReboot NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    chassisid,
    cpuid,
    slotid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Slot (CSM or SSM) has exceeded reboot frequency threshold."
::= { affirmedSnmpan3000TrapsNotificationPrefix 114}
```

anPortStatusDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    port,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Port Status is Down"
::= { affirmedSnmpan3000TrapsNotificationPrefix 128}
```

anPortStatusUP NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    port,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Port Status is UP"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 129}

```

anHwNodeDepartureEventData NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Node has departed from cluster."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 142}

```

anHwExtStorageCreateFailure NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    operation,
    state,
    status,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Failure during the creation of an extended-storage disk partition"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 199}
```

anHwExtStorageSizeMismatch NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    activesize,
    standbysize,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Alarm is generated when the extended-storage disk size is not matched
between the Active and Standby MCMS"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 200}

```

anHwNoExtStorageDiskAvailable NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    mcmslotnumber,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when an ext-storage disk is required but none
has been created"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 201}

```

anHwNotEnoughFreeStorageSpace NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    availablesize,
    requiredsize,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Lack of sufficient free storage space available"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 202}
```

anHwExtStorageMoveFilesTimeout NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    operation,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Event generated when moving files from one storage site to another
exceeds timeout."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 203}
```


anHwExtStorageCloseFilesTimeout NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    operation,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Event generated when waiting for files to close on a disk partition
exceeds a timeout"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 204}

```

anExtractionPending NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    resource,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Fru entered Extraction pending state"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 208}

```

anInsertionPending NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    resource,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Fru entered insertion pending state"
::= { affirmedSnmpan3000TrapsNotificationPrefix 209}
```

anIsolCpusMismatch NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Incorrect number of Isol Cpus for this platform"
::= { affirmedSnmpan3000TrapsNotificationPrefix 242}
```

anIpInterfaceOperStatusDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The operational status of an IP interface is down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 88}

```

anDataFabricOperStateDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Communication over the data fabric is down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 110}

```

anGeoRedundancyStandbyOperStatusDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Indicates a Geo-redundant standby cluster is not ready and the active
peer is not currently protected."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 117}
```

anGeoRedundancyActiveOperStatusDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Geo-redundant active cluster is not fully functional due to link
health status with neighboring network elements."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 118}
```

anGeoRedundancyPrimaryNodeStandby NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Geo-redundant node designated as HA-Role primary has entered HA-State
standby."
 ::= { affirmedSnmAn3000TrapsNotificationPrefix 133}

```

anGeoRedundancySecondaryNodeActive NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Geo-redundant node designated as HA-Role secondary has entered HA-
State active."
 ::= { affirmedSnmAn3000TrapsNotificationPrefix 134}

```

anGeoRedundancyLinkDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Geo-redundancy link is down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 136}
```

anGeoRedundancyLinkVersionMismatch NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Geo-redundant peers running incompatible software versions."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 137}
```

anDataFabricOperStateDownPathA NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Inter-node connectivity health check over data fabric path A is down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 144}

```

anDataFabricOperStateDownPathB NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Inter-node connectivity health check over data fabric path B is down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 145}

```

anBaseSwitchOperStateDownPathA NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Inter-node connectivity health check over base switch path A is down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 147}
```

anBaseSwitchOperStateDownPathB NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Inter-node connectivity health check over base switch path B is down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 148}
```


anBaseSwitchOperStateDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Inter-node connectivity health check over base switch paths A and B
are down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 149}

```

anNtpSyncError NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Cannot sync with configured NTP servers."
::= { affirmedSnmAn3000TrapsNotificationPrefix 151}

```

anBaseSwitchReachabilityDiffersPathAPathB NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Base switch node reachability differs between path A and path B."
::= { affirmedSnmpan3000TrapsNotificationPrefix 168}
```

anDataFabricReachabilityDiffersPathAPathB NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Map of reachable nodes over data fabric path A differs from path B."
::= { affirmedSnmpan3000TrapsNotificationPrefix 169}
```

anIpBgpPeerOperStatusDown NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    currentstate,
    lasterrorcode,
    lasterrosubcode,
    localpeeripaddr,
    netctxtname,
    peeringname,
    remotepeeripaddr,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A BGP peering is not in Established state. The alarm is raised when
peering starts, restarts, cleared, or when a peering leaves
Established state due to a protocol or networking event. The alarm is
cleared when a peering enters Established state."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 186}

```

anPacketEngineError NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    info,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The network packet engine has encountered an error preventing any data
plane communication on the current node (control plane is not
affected)"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 206}
```

anPacketEngineCongestion NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    info,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The packet network engine is experiencing congestion sufficiently
severe that packet memory reached critical low level. Packets
reception is stopped until packet memory returns to acceptable level"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 207}

```

anDataFabricPartialReachabilityPathA NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Inter-node connectivity health check detects partial connectivity
with peer nodes over data plane path A."
::= { affirmedSnmpan3000TrapsNotificationPrefix 210}
```

anPacketEngineWatchdogAlarm NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    info,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The packet network engine has experienced a critical error that is
preventing packet processing.  Packet processing is stopped."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 239}

```

anPacketEngineKNICongfigurationMismatch NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A mismatch exists between the provisioned packet processing resources
and what node booted with."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 241}
```

anIpsecTunnelOperStatusDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    unused,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"IPsec TUNNEL-DOWN"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 246}
```


anIpsecTunnelOperStatusUp NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    unused,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"IPsec TUNNEL-UP"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 247}

```

anIpOspfv2NbrDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    unused,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An OSPFv2 neighbor is not in Full/2-Way state. The alarm will be
generated when a neighbor leaves Full/2-Way state. The alarm is cleared
when neighbor enters Full/2-Way state. "
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 302}

```

anIpOspfv3NbrDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    unused,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An OSPFv3 neighbor is not in Full/2-Way state. The alarm will be
    generated when a neighbor leaves Full/2-Way state. The alarm is cleared
    when neighbor enters Full/2-Way state. "
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 303}
```

anNatPoolSessionAlarmThreshold NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    sessionthreshold,
    sessionutilization,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "The nat-pool session utilization has exceeded threshold. This may
    potentially lead to session or connection setup failures."
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 304}
```

anNatPoolIpAddressAlarmThreshold NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ipaddressthreshold,
    ipaddressutilization,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The nat-pool IP address utilization has exceeded threshold. This may
potentially lead to session or connection setup failures."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 305}

```

anNatPoolPortChunkAlarmThreshold NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    portchunkthreshold,
    portchunkutilization,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The nat-pool Port chunk utilization has exceeded threshold. This may
potentially lead to session or connection setup failures."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 306}
```

anBfdSessionDown NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    bfdsessiondescription,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "This event is generated when a BFD session goes down. It is cleared
    when the BFD session goes up. A gratuitous clear will happen the first
    time the BFD session goes up. Toggled by ip-protocols/bfd/enable-bfd-
    session-down-alarms"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 329}

```

anPortmapFailure NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    failedescription,
    slotnumber,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The network ports are not in the correct order, which causes
connectivity to the desired network to appear broken."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 333}
```

fmNmAn3000ColdStart NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A ColdStart trap signifies that the an3000/MCC is reinitializing
itself and that its configuration may have been altered."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 23}
```

fmNmAn3000Test NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A test event"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 24}

```

fmNmAn3000Commit NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An NMD configuration has been committed."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 25}

```

an3000WarmStart NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A WarmStart trap signifies that the an3000/MCC is reinitializing
itself such that its configuration is unaltered."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 152}
```

anLinkUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ifadminstatus,
    ifindex,
    ifoperstatus,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A logical link has transitioned from state down to state up."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 153}
```


anLinkDown NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ifadminstatus,
    ifindex,
    ifoperstatus,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A logical link has transitioned from state up to state down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 154}

```

anNmLoginFailure NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Failed login attempt"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 155}

```

anTaskOverload NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    cpu,
    level,
    sid,
    subtype,
    taskname,
    time,
    type,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A task has generated an overload event."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 69}
```

anBladeOverload NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    actions,
    cid,
    cpu,
    level,
    services,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This blade has generated an overload event."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 70}
```

anSystemOverload NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    level,
    subtype,
    type,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS obsolete
DESCRIPTION
"This system has generated an overload event"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 71}
```

anGtpPeerDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"GTP peer down. This indicates that the remote GTP peer is not
responding to any GTP messages sent to it. If the peer is statically
provisioned, the severity is Major. If the peer is dynamic, the
severity is Info."
::= { affirmedSnmAn3000TrapsNotificationPrefix 60}

```

anCantPageSubscriberOutOfBuffers NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    chassis,
    cpu,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"FP ran out of paging buffers"
::= { affirmedSnmAn3000TrapsNotificationPrefix 73}

```

anDiameterPeerLinkDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    localhostidentity,
    nodename,
    peerhostidentity,
    peerrealmname,
    realmname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Transport connection to the diameter peer is down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 89}
```

anDiameterPeerLinkUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    localhostidentity,
    nodename,
    peerhostidentity,
    peerrealmname,
    realmname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Diameter Peer Transport Connection Up Event"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 90}
```

anRadiusPeerDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    clientid,
    peername,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The RADIUS peer health check failed and this RADIUS peer is declared
down."
::= { affirmedSnmpan3000TrapsNotificationPrefix 91}
```

anRadiusPeerUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    clientid,
    peername,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Radius Peer Up Event"
::= { affirmedSnmpan3000TrapsNotificationPrefix 92}
```


anGtppPeerDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    peername,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The Transport connection to Gtpp peer is down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 93}

```

anGtppPeerUp NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    peername,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Gtpp Peer Up Event"
::= { affirmedSnmAn3000TrapsNotificationPrefix 94}

```

anPdnSessionAntiSpoofing NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    imsi,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The UE sent an IP packet with an unassigned source address."
::= { affirmedSnmppAn3000TrapsNotificationPrefix 98}
```

anSgwServiceUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A SGW service is operationally up."
::= { affirmedSnmppAn3000TrapsNotificationPrefix 99}
```

anSgwServiceDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A SGW service is operationally down."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 100}

```

anPgwServiceUp NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A PGW service is operationally up."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 101}

```

anPgwServiceDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A PGW service is operationally down."
::= { affirmedSnmpan3000TrapsNotificationPrefix 102}
```

anGgsnServiceUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A GGSN service is operationally up."
::= { affirmedSnmpan3000TrapsNotificationPrefix 103}
```

anGgsnServiceDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A GGSN service is operationally down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 104}

```

anApnAvailable NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    apnname,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An APN is available for use by a specific GW service."
::= { affirmedSnmAn3000TrapsNotificationPrefix 105}

```

anApnNotAvailable NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    apnname,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An APN is not available for use by a specific GW service."
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 106}
```

anCaleaPeerLinkDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    interfacename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "The alarm is generated when the transport connection to the CALEA peer
    is down. It is cleared when connectivity to the CALEA peer is
    restored."
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 140}
```

anCaleaPeerLinkUp NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    interfacename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Indicates when the transport connection to the CALEA peer comes up. It
is deprecated and will be removed in future releases, as the
anCaleaPeerLinkDown alarm delivers all link status change
notifications. It is not used by the existing code."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 141}

```

anGtpPeerUp NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"GTP Peer Up Event"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 143}

```

anCaleaTargetsCleared NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The trap is generated when all CALEA targets have been removed and the
size of the CALEA target data base becomes zero. It is an informational
trap and therefore never cleared."
::= { affirmedSnmpan3000TrapsNotificationPrefix 162}
```

anCaleaInterfacesCleared NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when all Legal Intercept Mediation device
Interfaces have been deleted. It is an informational alarm and is never
cleared."
::= { affirmedSnmpan3000TrapsNotificationPrefix 163}
```


anCaleaUtilizationLow NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when the Configured Legal Intercept Targets
Utilization is greater than 60% and less than 70% of the maximum
capacity. It is cleared when the utilization becomes less than or equal
to 60%."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 164}

```

anCaleaUtilizationMedium NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This Alarm is generated when Configured Legal Intercept Targets are
above 70% but below 80% of maximum allowed configurable targets. It is
cleared when the utilization is less than or equal to 70%."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 165}

```

anCaleaUtilizationHigh NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This Alarm is generated when Configured Legal Intercept Targets are
above 80% but below 90% of maximum allowed targets. It is cleared when
the utilization is less than or equal to 80%."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 166}
```

anCaleaUtilizationCritical NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This Alarm is generated when Configured Legal Intercept Targets are
above 90% but below 100% of maximum allowed targets. It is cleared when
the utilization is less than or equal to 90%."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 167}
```

anCaleaCCBufferConfiguredSizeBelowThreshold NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when the configured size for the CC buffer on
the interface group is less than the minimum threshold value (10MB)."
::= { affirmedSnmpan3000TrapsNotificationPrefix 189}

```

anCaleaCCBufferUtilizationThresholdReached NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when the buffer utilization threshold is
reached for the CC buffer on the interface group."
::= { affirmedSnmpan3000TrapsNotificationPrefix 190}

```

anCaleaIRIBufferUtilizationThresholdReached NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when the buffer utilization threshold is
reached for the IRI buffer on the interface group."
::= { affirmedSnmpan3000TrapsNotificationPrefix 191}
```

anCaleaTargetDBMaxSubsLimitReached NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when the number of entries in the target DB
reaches the maximum allowed value of 32,768."
::= { affirmedSnmpan3000TrapsNotificationPrefix 192}
```

anCalealRIBufferConfiguredSizeBelowThreshold NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when the configured size for the IRI buffer on
the interface group is less than the minimum threshold value (1 MB)."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 193}

```

anCalealfOrlfGroupConfigChange NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is raised when the configuration for a CALEA interface/
interface group is modified in any way (added, changed or deleted)."
```

```

 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 194}

```

anCaleaLITargetCreatedOrDeleted NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated whenever a CALEA Lawful Intercept target is
created or deleted."
::= { affirmedSnmAn3000TrapsNotificationPrefix 195}
```

anCaleaInterfaceGroupStatusDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    role,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated whenever the interface group status changes
from up to down. It is cleared when the status changes back to up."
::= { affirmedSnmAn3000TrapsNotificationPrefix 196}
```

anCaleaCCBufferDataLost NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated whenever CC buffer data is lost because the
buffer size was exceeded and inserting additional data in the buffer
caused earlier packets to be lost."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 197}

```

anCaleaIRIBufferDataLost NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    groupname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated whenever IRI buffer data is lost because the
buffer size was exceeded and inserting additional data in the buffer
caused earlier packets to be lost."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 198}

```

anEmergencyCallAttemptFailed NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    reason,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when the system fails to setup emergency
bearers for a session due to reasons such as lack of resources or
memory or other call processing errors."
::= { affirmedSnmAn3000TrapsNotificationPrefix 214}
```

anEmergencyCallDropped NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    reason,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when active emergency bearers are deactivated
due to operator intervention such as deactivation initiated through
CLI."
::= { affirmedSnmAn3000TrapsNotificationPrefix 215}
```


anWagServiceDown NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A WAG service is operationally down."
::= { affirmedSnmAn3000TrapsNotificationPrefix 220}

```

anWagServiceUp NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A WAG service is operationally up."
::= { affirmedSnmAn3000TrapsNotificationPrefix 221}

```

anEpdgServiceUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ePDG service is operationally up."
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 230}
```

anEpdgServiceDown NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    servicename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ePDG service is operationally down."
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 231}
```

anGwSubsGrpFileNotFound NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    subgroupname,
    subsidfilename,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"File containing Subscriber IDs configured for the subscriber-group
does not exist on the MCC."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 296}

```

anCaleaUserBanFeatureConfigChange NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    state,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when admin state of Calea User Ban Feature is
changed"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 299}

```

anCaleaCCDataLost NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ifname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when CC data is first lost on an interface
which is down (and no interface-group is provisioned for target)"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 300}
```

anCaleaIRIDataLost NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ifname,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when IRI data is first lost on an interface
which is down (and no interface-group is provisioned for target)"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 301}
```

anPfcPpPeerDown NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    gatewayipaddress,
    gatewayname,
    peeripaddress,
    peername,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"PFCEP Peer down indicates that the remote PFCEP Peer is not responding
to any of the PFCEP messages sent to it."
::= { affirmedSnmPAn3000TrapsNotificationPrefix 321}

```

anPfcPPeerUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    gatewayIpAddress,
    gatewayName,
    peerIpAddress,
    peerName,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"PCFP Peer is up, running and reachable."
::= { affirmedSnmPAn3000TrapsNotificationPrefix 322}
```

anCalealfGrpSourceProfileConfigChange NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is raised when the configuration for a CALEA interface-
group-source-profile is modified in any way (added, changed or
deleted)."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 323}

```

anCalealfGrpSourceProfileNotFound NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    name,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is raised when the CALEA subsystem is unable to find an
interface-group-source-profile for a dynamic target interface/group."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 324}

```

anCaleaPdhirNotSupportedForSx3lifTunnelToCPF NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated to indicate control plane will not deliver
PDHIR events when CALEA target config is having PDHIR enabled in SX3LIF
mode"
::= { affirmedSnmAn3000TrapsNotificationPrefix 342}
```

anCaleaDecryptFail NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The alarm is generated when encrypted CALEA Lawful Intercept data can
not be decrypted (could be security key mismatch between CPF and UPF)"
::= { affirmedSnmAn3000TrapsNotificationPrefix 343}
```


fmSWCompMCMSwitchoverEventData NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    chassis,
    cpu,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An MCM switchover has taken place."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 19}
```

anRedundancyOperState NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    statestring,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Indicates whether MCM redundancy is operational. When the standby
boots it has 10 minutes to establish redundancy before raising this
alarm. If a standby task fails, the system gives 3 minutes to re-
established redundancy before raising this alarm."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 107}
```

anCpuTosTaskState NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    cpu,
    sid,
    statestring,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}

```

STATUS current

DESCRIPTION

"Indicates whether all tos tasks are operationally UP on this CPU. After a card is booted all tasks have 10 minutes to come up before an alarm is issued. If a task goes down, the system gives 3 minutes for the task to come up before issuing this alarm."

::= { affirmedSnmpAn3000TrapsNotificationPrefix 108}

anNewCoreFileDetected NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    chassis,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"A new core file is detected on the chassis."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 111}
```

anfileftpfailure NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    filepath,
    ip,
    port,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Last try to ftp files to remote server failed."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 112}
```

anForcedSyncStart NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Forced sync of images from active to standby."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 125}

```

anForcedSyncFailed NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Forced sync failed or timed-out."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 126}

```

anPortStatusUp NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    port,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Port Status is UP"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 127}
```

anfilepurgedduetodiskfull NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    numpurged,
    prefix,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Files have been purged from disk since disk purge threshold was
crossed (disk was getting close to full)."
```

```
::= { affirmedSnmpAn3000TrapsNotificationPrefix 130}
```

anKernelOptionsModified NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    cpu,
    info,
    sid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Kernel options have been automatically modified on the current
module. They will take effect on the reboot. "
::= { affirmedSnmpAn3000TrapsNotificationPrefix 135}

```

anFormatDisk NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    diskid,
    node,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"Disk format operation took place."
::= { affirmedSnmpan3000TrapsNotificationPrefix 138}
```

anDiskFull NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    diskid,
    slot,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS obsolete
DESCRIPTION
"Disk full"
::= { affirmedSnmpan3000TrapsNotificationPrefix 139}
```


anUEPoolThresholdAlarm NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ipversiontype,
    threshold,
    uepoolutilization,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is generated when the configured threshold for UE pool
utilization is crossed."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 146}

```

anDataRecordFailure NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The system failed to log a data record (i.e. local CDR, HTDR or other
such data records). This failure can occur either at the source
generating the data record or at the agent which is responsible for
flush the data record to the disk."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 205}
```

anRemoteMountFailed NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"This alarm is raised when a node cannot reach over the nfs mount to
the disk on peer MCM. For active MCM, the peer MCM is the standby
MCM. For all nodes, the peer MCM is the active MCM."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 211}
```

anEdrServerConnectionFailed NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    ip,
    name,
    port,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The connection to the EDR server has failed."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 222}

```

anPkix509expiring NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An X509 certificate is approaching expiration"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 232}

```

anPkix509expired NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An X509 certificate has expired"
::= { affirmedSnmAn3000TrapsNotificationPrefix 233}
```

anPkix509revoked NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An X509 certificate has been revoked"
::= { affirmedSnmAn3000TrapsNotificationPrefix 234}
```

anPkiobjunreachable NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "Attempts to update a pki object from a remote source have failed for
    more than 24 hours"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 235}

```

anPkiobjadded NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "A new pki object has been added to the system"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 236}

```

anPkiobjupdated NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An existing pki object has been updated"
::= { affirmedSnmppAn3000TrapsNotificationPrefix 237}
```

anPkiobjremoved NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "A pki object has been removed from the system"
::= { affirmedSnmppAn3000TrapsNotificationPrefix 238}
```

anPkix509crlnextupdateavailable NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The next update of this x509 certificate revocation list is available"
::= { affirmedSnmpan3000TrapsNotificationPrefix 240}

```

anReleaseMismatch NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"one or more nodes are running a different tos release than they are
intended to be running and neither an upgrade nor a rollback is in
progress."
::= { affirmedSnmpan3000TrapsNotificationPrefix 244}

```

anPkiobjupdatenotavailable NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Attempts to get an updated version of a pki object from a remote
source have failed for more than 24 hours"
::= { affirmedSnmpan3000TrapsNotificationPrefix 248}
```

anPkisshauthorizedkeyaddedtouser NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An ssh public key has been configured to authenticate ssh for a user"
::= { affirmedSnmpan3000TrapsNotificationPrefix 249}
```


anPkisshauthorizedkeyremovedfromuser NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh public key has been removed from those that may authenticate
    ssh for a user"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 250}

```

anPkisshauthorizedkeyaddedtogroup NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh public key has been configured to authenticate ssh for all
    users in a group"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 251}

```

anPkisshauthorizedkeyremovedfromgroup NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An ssh public key has been removed from those that may authenticate
ssh for all users in a group"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 252}
```

anPkisshtrustedcakeyaddedtocluster NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An ssh public key has been trusted as a certificate authority key to
validate certificates used to authenticate ssh for any user in the
cluster"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 253}
```

anPkisshtrustedcakeyremovedfromcluster NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh public key that had been trusted as a certificate authority key
    to validate certificates used to authenticate ssh for any user in the
    cluster has been removed"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 254}

```

anPkisshtrustedcakeyaddedtogroup NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh public key has been trusted as a certificate authority key to
    validate certificates used to authenticate ssh for all users in a
    group"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 255}

```

anPkisshtrustedcakeyremovedfromgroup NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh public key that had been trusted as a certificate authority key
    to validate certificates used to authenticate ssh for all users in a
    group has been removed"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 256}
```

anPkisshuseraddedtoauthorizedprincipals NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
    "A user has been added to the group list of authorized principals"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 257}
```

anPkisshuserremovedfromauthorizedprincipals NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"A user has been removed from the group list of authorized principals"
::= { affirmedSnmpan3000TrapsNotificationPrefix 258}

```

anPkisshgroupaddedtoauthorizedprincipals NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"All users in a group have been added to the group list of authorized principals"
::= { affirmedSnmpan3000TrapsNotificationPrefix 259}

```

anPkisshgroupremovedfromauthorizedprincipals NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
"All users in a group have been removed from the group list of
authorized principals"
::= { affirmedSnmpan3000TrapsNotificationPrefix 260}
```

anfileexportfailure NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    filepath,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Last try to export files to the export directory (as per
configuration) failed."
::= { affirmedSnmpan3000TrapsNotificationPrefix 261}
```

anPkisshnamesaddedtogroupauthorizedprincipals NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"One or mores names have been added to a group authorized principals
list"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 262}

```

anPkissherrorapplyingconfigurationtosshcontrolfiles NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An error has occurred converting pki ssh configuration to ssh
authorizedkeys/authorizedprincipals/trustedusercakeys files"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 263}

```

anPkisshnamesremovedfromauthorizedprincipals NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"One or mores names have been removed from a user authorized principals
list"
::= { affirmedSnmpan3000TrapsNotificationPrefix 264}
```

anPkisshnamesaddedtoauthorizedprincipals NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"One or mores names have been added to a user authorized principals
list"
::= { affirmedSnmpan3000TrapsNotificationPrefix 265}
```


anPkisshnamesremovedfromgroupauthorizedprincipals NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"One or mores names have been removed from a group authorized
principals list"
::= { affirmedSnmAn3000TrapsNotificationPrefix 266}

```

anPkisshmaximumsecuritylevelset NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh security level for the cluster has been changed to maximum"
::= { affirmedSnmAn3000TrapsNotificationPrefix 267}

```

anPkisshcompatiblesecuritylevelset NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh security level for the cluster has been changed to compatible"
::= { affirmedSnmpan3000TrapsNotificationPrefix 268}
```

anPkisshstricthostkeycheckingsettono NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh strict host key checking for the cluster has been changed to
no"
::= { affirmedSnmpan3000TrapsNotificationPrefix 269}
```

anPkisshstricthostkeycheckingsettoask NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh strict host key checking for the cluster has been changed to
ask"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 270}

```

anPkisshstricthostkeycheckingsettoyes NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh strict host key checking for the cluster has been changed to
yes"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 271}

```

anPkisshverifyhostkeydnssettono NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh verify host key with dns for the cluster has been changed to
no"
::= { affirmedSnmpan3000TrapsNotificationPrefix 272}
```

anPkisshverifyhostkeydnssettoyes NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh verify host key with dns for the cluster has been changed to
yes"
::= { affirmedSnmpan3000TrapsNotificationPrefix 273}
```

anPkisshverifyhostkeydnssettoask NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh verify host key with dns for the cluster has been changed to
ask"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 274}

```

anPkisshknownhostcakeyremoved NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh public key of a certificate authority has been removed from
ssh_known_hosts."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 275}

```

anPkisshknownhostcakeadded NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh public key of a certificate authority has been added to
ssh_known_hosts to validate the host certificates presented on
connection by ssh/scp/sftp to external servers"
::= { affirmedSnmpAn3000TrapsNotificationPrefix 276}
```

anPkisshknownhostkeyremoved NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An ssh public key has been removed from ssh_known_hosts."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 277}
```

anPkisshknownhostkeyadded NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh public key has been added to ssh_known_hosts to validate
    connections by ssh/scp/sftp to external servers"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 278}

```

anPkisshlocalhostcertificatereplaced NOTIFICATION-TYPE

```

OBJECTS   {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "The previous local ssh host certificate has been replaced by a new ssh
    certificate."
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 279}

```

anPkisshlocalhostcertificateremoved NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The local ssh host certificate has been removed."
::= { affirmedSnmAn3000TrapsNotificationPrefix 280}
```

anPkisshlocalhostcertificateadded NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The local ssh host certificate has been added."
::= { affirmedSnmAn3000TrapsNotificationPrefix 281}
```


anPkisshrevoked NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh key or certificate has been revoked by an ssh krl file"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 282}

```

anPkimanuallyrevoked NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh key or certificate has been manually reported as revoked by a
    revoke cli command"
 ::= { affirmedSnmpAn3000TrapsNotificationPrefix 283}

```

anPkisshuserkrlreplaced NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A new or updated pki ssh krl file has replaced the previous ssh krl as
the RevokedKeys file to the sshd servers."
::= { affirmedSnmpan3000TrapsNotificationPrefix 285}
```

anPkisshuserkrladded NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A pki ssh krl file has been added as the RevokedKeys file to the sshd
servers."
::= { affirmedSnmpan3000TrapsNotificationPrefix 286}
```

anPkisshuserkrlremoved NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The ssh krl file that was providing a list of revoked ssh keys has
been removed from RevokedKeys on the sshd servers."
::= { affirmedSnmpan3000TrapsNotificationPrefix 287}

```

anPkisshcertexpiring NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"An ssh certificate is approaching expiration"
::= { affirmedSnmpan3000TrapsNotificationPrefix 288}

```

anPkisshcertexpired NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
    "An ssh certificate has expired"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 289}
```

anNewMemImageFileDetected NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    chassis,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS deprecated
DESCRIPTION
    "A new memory image file is detected on the chassis"
 ::= { affirmedSnmpan3000TrapsNotificationPrefix 298}
```

anNewFaultFileDetected NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    chassis,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A new fault file has been detected on the chassis"
::= { affirmedSnmAn3000TrapsNotificationPrefix 309}

```

anNodeRebootRequired NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Node needs to be rebooted because one or more of the following have
changed on the node. 1. isolcpus 2. core-layout"
::= { affirmedSnmAn3000TrapsNotificationPrefix 332}

```

anRadiusAccountingOnMsgNotSent NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"PGW is not accepting sessions using RADIUS towards peer Radius server
due to operator configuration"
::= { affirmedSnmpan3000TrapsNotificationPrefix 334}
```

anClusterRebootRequired NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    cid,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The cluster needs to be rebooted because one or more of the following
have changed on one or more nodes in the cluster. 1. isolcpus 2. core-
layout 3. max-packet-size"
::= { affirmedSnmpan3000TrapsNotificationPrefix 338}
```

anThresholdCrossingAlarm NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"A threshold has been crossed."
::= { affirmedSnmAn3000TrapsNotificationPrefix 68}

```

anLicenseCapacityEnforcement NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Approaching or crossed licensed service capacity enforcement level.
Upon reaching X percent of the capacity enforcement level, a major
event will be generated. The event will become critical as the
enforcement level is crossed."
::= { affirmedSnmAn3000TrapsNotificationPrefix 223}

```

anLicenseCapacityLimit NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Approaching or crossed licensed service capacity limit. Upon reaching
X percent of the capacity limit, a major event will be generated. The
event will become critical as the limit is crossed."
::= { affirmedSnmAn3000TrapsNotificationPrefix 224}
```

anLicenseLifetimeEnforcement NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Approaching or passed licensed service enforcement expiration date.
Upon reaching X percent of the license expiration date, a major event
will be generated. The event will become critical as the expiration is
passed."
::= { affirmedSnmAn3000TrapsNotificationPrefix 225}
```


anLicenseLifetime NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Approaching or passed licensed service lifetime. Upon reaching X
percent of the license lifetime, a major event will be generated. The
event will become critical as the lifetime is passed."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 226}

```

anLicensePlsSeparation NOTIFICATION-TYPE

```

OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"The MCC has separated from the PLS server and enter local license
management state. During this period, the MCC will manage licenses
based on the last PLS view. Services will be impacted if the server is
not restored within the grace period."
::= { affirmedSnmpAn3000TrapsNotificationPrefix 227}

```

anLicensePlsGraceExpired NOTIFICATION-TYPE

```
OBJECTS    {
    affirmedAlarmSeqId,
    affirmedAlarmDateTime,
    affirmedAlarmChassisName,
    affirmedAlarmSourceId,
    affirmedAlarmSeverity,
    affirmedAlarmRefSeqId,
    affirmedAlarmDetails,
    affirmedPotentialImpact,
    affirmedCorrectiveAction,
    affirmedVmSourceIpAddress,
    affirmedVmSourceName
}
STATUS current
DESCRIPTION
"Connection to the PLS server has not reestablished within the grace
period so license-able services are terminated."
::= { affirmedSnmAn3000TrapsNotificationPrefix 228}
```