1. Converting raw audio to spectrogram or MFCC features reduces dimensionality and highlights frequency patterns over time. This makes the data function like an image, which convolutional neural networks can process much more efficiently and accurately than raw one dimensional waveforms.
2. The representative dataset provides sample input data during quantization so the converter can observe the minimum and maximum activation values across the model layers. This calibration allows the converter to calculate the correct scale and zero point to accurately map floating point numbers to eight bit integers without losing precision.
3. The audio processor get data function fetches a batch of audio samples and applies random background noise or time shifts for data augmentation. It then extracts the designated features like spectrograms and returns them alongside their labels as tensors ready for model inference or training.
4. The g model variable is a C byte array containing the raw hexadecimal representation of your quantized model, and g model len specifies its exact size in bytes. They must be copied correctly into your Arduino source file because the microcontroller runtime reads this specific block of flash memory to build and execute the neural network graph.
5. 

Both yes and no displayed